

ETSI TS 138 214 V15.10.0 (2020-07)



**5G;
NR;
Physical layer procedures for data
(3GPP TS 38.214 version 15.10.0 Release 15)**



Reference

RTS/TSGR-0138214vfa0

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M™ logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	5
1 Scope	6
2 References	6
3 Definitions, symbols and abbreviations	7
3.1 Definitions	7
3.2 Symbols.....	7
3.3 Abbreviations	7
4 Power control	8
4.1 Power allocation for downlink	8
5 Physical downlink shared channel related procedures	9
5.1 UE procedure for receiving the physical downlink shared channel	9
5.1.1 Transmission schemes	10
5.1.1.1 Transmission scheme 1	10
5.1.2 Resource allocation.....	10
5.1.2.1 Resource allocation in time domain	10
5.1.2.1.1 Determination of the resource allocation table to be used for PDSCH.....	11
5.1.2.2 Resource allocation in frequency domain	14
5.1.2.2.1 Downlink resource allocation type 0	15
5.1.2.2.2 Downlink resource allocation type 1	15
5.1.2.3 Physical resource block (PRB) bundling.....	16
5.1.3 Modulation order, target code rate, redundancy version and transport block size determination.....	17
5.1.3.1 Modulation order and target code rate determination	19
5.1.3.2 Transport block size determination	22
5.1.4 PDSCH resource mapping	25
5.1.4.1 PDSCH resource mapping with RB symbol level granularity	25
5.1.4.2 PDSCH resource mapping with RE level granularity	26
5.1.5 Antenna ports quasi co-location.....	27
5.1.6 UE procedure for receiving downlink reference signals.....	29
5.1.6.1 CSI-RS reception procedure.....	29
5.1.6.1.1 CSI-RS for tracking	30
5.1.6.1.2 CSI-RS for L1-RSRP computation.....	31
5.1.6.1.3 CSI-RS for mobility	31
5.1.6.2 DM-RS reception procedure	32
5.1.6.3 PT-RS reception procedure	34
5.1.7 Code block group based PDSCH transmission.....	35
5.1.7.1 UE procedure for grouping of code blocks to code block groups	35
5.1.7.2 UE procedure for receiving code block group based transmissions.....	35
5.2 UE procedure for reporting channel state information (CSI)	36
5.2.1 Channel state information framework.....	36
5.2.1.1 Reporting settings	36
5.2.1.2 Resource settings.....	36
5.2.1.3 (void).....	37
5.2.1.4 Reporting configurations.....	37
5.2.1.4.1 Resource Setting configuration	39
5.2.1.4.2 Report Quantity Configurations	40
5.2.1.4.3 L1-RSRP Reporting.....	42
5.2.1.5 Triggering/activation of CSI Reports and CSI-RS	42
5.2.1.5.1 Aperiodic CSI Reporting/Aperiodic CSI-RS.....	42
5.2.1.5.2 Semi-persistent CSI/Semi-persistent CSI-RS	43
5.2.1.6 CSI processing criteria	45

5.2.2	Channel state information.....	46
5.2.2.1	Channel quality indicator (CQI).....	46
5.2.2.1.1	(void).....	48
5.2.2.2	Precoding matrix indicator (PMI).....	48
5.2.2.2.1	Type I Single-Panel Codebook.....	48
5.2.2.2.2	Type I Multi-Panel Codebook.....	54
5.2.2.2.3	Type II Codebook.....	58
5.2.2.2.4	Type II Port Selection Codebook.....	64
5.2.2.3	Reference signal (CSI-RS).....	67
5.2.2.3.1	NZP CSI-RS.....	67
5.2.2.4	Channel State Information – Interference Measurement (CSI-IM).....	68
5.2.2.5	CSI reference resource definition.....	69
5.2.3	CSI reporting using PUSCH.....	70
5.2.4	CSI reporting using PUCCH.....	72
5.2.5	Priority rules for CSI reports.....	73
5.3	UE PDSCH processing procedure time.....	73
5.4	UE CSI computation time.....	75
6	Physical uplink shared channel related procedure.....	76
6.1	UE procedure for transmitting the physical uplink shared channel.....	76
6.1.1	Transmission schemes.....	77
6.1.1.1	Codebook based UL transmission.....	77
6.1.1.2	Non-Codebook based UL transmission.....	78
6.1.2	Resource allocation.....	79
6.1.2.1	Resource allocation in time domain.....	79
6.1.2.1.1	Determination of the resource allocation table to be used for PUSCH.....	80
6.1.2.2	Resource allocation in frequency domain.....	82
6.1.2.2.1	Uplink resource allocation type 0.....	83
6.1.2.2.2	Uplink resource allocation type 1.....	83
6.1.2.3	Resource allocation for uplink transmission with configured grant.....	84
6.1.3	UE procedure for applying transform precoding on PUSCH.....	85
6.1.4	Modulation order, redundancy version and transport block size determination.....	85
6.1.4.1	Modulation order and target code rate determination.....	87
6.1.4.2	Transport block size determination.....	90
6.1.5	Code block group based PUSCH transmission.....	91
6.1.5.1	UE procedure for grouping of code blocks to code block groups.....	91
6.1.5.2	UE procedure for transmitting code block group based transmissions.....	92
6.2	UE reference signal (RS) procedure.....	92
6.2.1	UE sounding procedure.....	92
6.2.1.1	UE SRS frequency hopping procedure.....	95
6.2.1.2	UE sounding procedure for DL CSI acquisition.....	96
6.2.1.3	UE sounding procedure between component carriers.....	96
6.2.2	UE DM-RS transmission procedure.....	98
6.2.3	UE PT-RS transmission procedure.....	99
6.2.3.1	UE PT-RS transmission procedure when transform precoding is not enabled.....	99
6.2.3.2	UE PT-RS transmission procedure when transform precoding is enabled.....	101
6.3	UE PUSCH frequency hopping procedure.....	102
6.4	UE PUSCH preparation procedure time.....	103
Annex A (informative): Change history		105
History		108

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present document specifies and establishes the characteristics of the physical layer procedures of data channels for 5G-NR.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications"
- [2] 3GPP TS 38.201: " NR; Physical Layer – General Description"
- [3] 3GPP TS 38.202: "NR; Services provided by the physical layer"
- [4] 3GPP TS 38.211: "NR; Physical channels and modulation"
- [5] 3GPP TS 38.212: "NR; Multiplexing and channel coding"
- [6] 3GPP TS 38.213: "NR; Physical layer procedures for control"
- [7] 3GPP TS 38.215: "NR; Physical layer measurements"
- [8] 3GPP TS 38.101: "NR; User Equipment (UE) radio transmission and reception"
- [9] 3GPP TS 38.104: "NR; Base Station (BS) radio transmission and reception"
- [10] 3GPP TS 38.321: "NR; Medium Access Control (MAC) protocol specification"
- [11] 3GPP TS 38.133: "NR; Requirements for support of radio resource management"
- [12] 3GPP TS 38.331: "NR; Radio Resource Control (RRC); Protocol specification"
- [13] 3GPP TS 38.306: "NR; User Equipment (UE) radio access capabilities"
- [14] 3GPP TS 38.423: "NG-RAN; Xn Application Protocol (XnAP)"
- [15] 3GPP TS 36.211: "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation"

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

3.2 Symbols

For the purposes of the present document, the following symbols apply:

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

BWP	Bandwidth part
CBG	Code block group
CP	Cyclic prefix
CQI	Channel quality indicator
CPU	CSI processing unit
CRB	Common resource block
CRC	Cyclic redundancy check
CRI	CSI-RS Resource Indicator
CSI	Channel state information
CSI-RS	Channel state information reference signal
CSI-RSRP	CSI reference signal received power
CSI-RSRQ	CSI reference signal received quality
CSI-SINR	CSI signal-to-noise and interference ratio
CW	Codeword
DCI	Downlink control information
DL	Downlink
DM-RS	Dedicated demodulation reference signals
EPRE	Energy per resource element
L1-RSRP	Layer 1 reference signal received power
LI	Layer Indicator
MCS	Modulation and coding scheme
PDCCH	Physical downlink control channel
PDSCH	Physical downlink shared channel
PSS	Primary Synchronisation signal
PUCCH	Physical uplink control channel
QCL	Quasi co-location
PMI	Precoding Matrix Indicator
PRB	Physical resource block
PRG	Precoding resource block group
PT-RS	Phase-tracking reference signal
RB	Resource block
RBG	Resource block group
RI	Rank Indicator
RIV	Resource indicator value
RS	Reference signal
SLIV	Start and length indicator value
SR	Scheduling Request
SRS	Sounding reference signal
SS	Synchronisation signal
SSS	Secondary Synchronisation signal
SS-RSRP	SS reference signal received power

SS-RSRQ	SS reference signal received quality
SS-SINR	SS signal-to-noise and interference ratio
TB	Transport Block
TCI	Transmission Configuration Indicator
TDM	Time division multiplexing
UE	User equipment
UL	Uplink

4 Power control

4.1 Power allocation for downlink

The gNB determines the downlink transmit EPRE.

For the purpose of SS-RSRP, SS-RSRQ and SS-SINR measurements, the UE may assume downlink EPRE is constant across the bandwidth. For the purpose of SS-RSRP, SS-RSRQ and SS-SINR measurements, the UE may assume downlink EPRE is constant over SSS carried in different SS/PBCH blocks. For the purpose of SS-RSRP, SS-RSRQ and SS-SINR measurements, the UE may assume that the ratio of SSS EPRE to PBCH DM-RS EPRE is 0 dB.

For the purpose of CSI-RSRP, CSI-RSRQ and CSI-SINR measurements, the UE may assume downlink EPRE of a port of CSI-RS resource configuration is constant across the configured downlink bandwidth and constant across all configured OFDM symbols.

The downlink SS/PBCH SSS EPRE can be derived from the SS/PBCH downlink transmit power given by the parameter *ss-PBCH-BlockPower* provided by higher layers. The downlink SSS transmit power is defined as the linear average over the power contributions (in [W]) of all resource elements that carry the SSS within the operating system bandwidth.

The downlink CSI-RS EPRE can be derived from the SS/PBCH block downlink transmit power given by the parameter *ss-PBCH-BlockPower* and CSI-RS power offset given by the parameter *powerControlOffsetSS* provided by higher layers. The downlink reference-signal transmit power is defined as the linear average over the power contributions (in [W]) of the resource elements that carry the configured CSI-RS within the operating system bandwidth.

For downlink DM-RS associated with PDSCH, the UE may assume the ratio of PDSCH EPRE to DM-RS EPRE (β_{DMRS} [dB]) is given by Table 4.1-1 according to the number of DM-RS CDM groups without data as described in Clause 5.1.6.2. The DM-RS scaling factor β_{PDSCH}^{DMRS} specified in Clause 7.4.1.1.2 of [4, TS 38.211] is given by

$$\beta_{PDSCH}^{DMRS} = 10^{\frac{\beta_{DMRS}}{20}}.$$

Table 4.1-1: The ratio of PDSCH EPRE to DM-RS EPRE

Number of DM-RS CDM groups without data	DM-RS configuration type 1	DM-RS configuration type 2
1	0 dB	0 dB
2	-3 dB	-3 dB
3	-	-4.77 dB

When the UE is scheduled with a PT-RS port associated with the PDSCH,

- if the UE is configured with the higher layer parameter *epre-Ratio*, the ratio of PT-RS EPRE to PDSCH EPRE per layer per RE for PT-RS port (ρ_{PTRS}) is given by Table 4.1-2 according to the *epre-Ratio*, the PT-RS scaling factor β_{PTRS} specified in clause 7.4.1.2.2 of [4, TS 38.211] is given by $\beta_{PTRS} = 10^{\frac{\rho_{PTRS}}{20}}$.
- otherwise, the UE shall assume *epre-Ratio* is set to state '0' in Table 4.1-2 if not configured.

Table 4.1-2: PT-RS EPRE to PDSCH EPRE per layer per RE (ρ_{PTRS})

epre-Ratio	The number of PDSCH layers					
	1	2	3	4	5	6
0	0	3	4.77	6	7	7.78
1	0	0	0	0	0	0
2	reserved					
3	reserved					

For link recovery, as described in clause 6 of [6, TS 38.213] the ratio of the PDCCH EPRE to NZP CSI-RS EPRE is assumed as 0 dB.

5 Physical downlink shared channel related procedures

5.1 UE procedure for receiving the physical downlink shared channel

For downlink, a maximum of 16 HARQ processes per cell is supported by the UE. The number of processes the UE may assume will at most be used for the downlink is configured to the UE for each cell separately by higher layer parameter *nrofHARQ-ProcessesForPDSCH*, and when no configuration is provided the UE may assume a default number of 8 processes.

A UE shall upon detection of a PDCCH with a configured DCI format 1_0 or 1_1 decode the corresponding PDSCHs as indicated by that DCI. For any HARQ process ID(s) in a given scheduled cell, the UE is not expected to receive a PDSCH that overlaps in time with another PDSCH. The UE is not expected to receive another PDSCH for a given HARQ process until after the end of the expected transmission of HARQ-ACK for that HARQ process, where the timing is given by Clause 9.2.3 of [6]. In a given scheduled cell, the UE is not expected to receive a first PDSCH in slot i , with the corresponding HARQ-ACK assigned to be transmitted in slot j , and a second PDSCH starting later than the first PDSCH with its corresponding HARQ-ACK assigned to be transmitted in a slot before slot j . For any two HARQ process IDs in a given scheduled cell, if the UE is scheduled to start receiving a first PDSCH starting in symbol j by a PDCCH ending in symbol i , the UE is not expected to be scheduled to receive a PDSCH starting earlier than the end of the first PDSCH with a PDCCH that ends later than symbol i . In a given scheduled cell, for any PDSCH corresponding to SI-RNTI, the UE is not expected to decode a re-transmission of an earlier PDSCH with a starting symbol less than N symbols after the last symbol of that PDSCH, where the value of N depends on the PDSCH subcarrier spacing configuration μ , with $N=13$ for $\mu=0$, $N=13$ for $\mu=1$, $N=20$ for $\mu=2$, and $N=24$ for $\mu=3$.

When receiving PDSCH scheduled with SI-RNTI or P-RNTI, the UE may assume that the DM-RS port of PDSCH is quasi co-located with the associated SS/PBCH block with respect to Doppler shift, Doppler spread, average delay, delay spread, spatial RX parameters when applicable.

When receiving PDSCH scheduled with RA-RNTI the UE may assume that the DM-RS port of PDSCH is quasi co-located with the SS/PBCH block or the CSI-RS resource the UE used for RACH association and transmission with respect to Doppler shift, Doppler spread, average delay, delay spread, spatial RX parameters when applicable. When receiving a PDSCH scheduled with RA-RNTI in response to a random access procedure triggered by a PDCCH order which triggers contention-free random access procedure for the SpCell [10, TS 38.321], the UE may assume that the DM-RS port of the received PDCCH order and the DM-RS ports of the corresponding PDSCH scheduled with RA-RNTI are quasi co-located with the same SS/PBCH block or CSI-RS with respect to Doppler shift, Doppler spread, average delay, delay spread, spatial RX parameters when applicable.

When receiving PDSCH in response to a PUSCH transmission scheduled by a RAR UL grant or corresponding PUSCH retransmission the UE may assume that the DM-RS port of PDSCH is quasi co-located with the SS/PBCH block the UE selected for RACH association and transmission with respect to Doppler shift, Doppler spread, average delay, delay spread, spatial RX parameters when applicable.

If the UE is not configured for PUSCH/PUCCH transmission for at least one serving cell configured with slot formats comprised of DL and UL symbols, and if the UE is not capable of simultaneous reception and transmission on serving cell c_1 and serving cell c_2 , the UE is not expected to receive PDSCH on serving cell c_1 if the PDSCH overlaps in time

with SRS transmission (including any interruption due to uplink or downlink RF retuning time [10]) on serving cell c_2 not configured for PUSCH/PUCCH transmission.

The UE is not expected to decode a PDSCH scheduled in a serving cell with C-RNTI or MCS-C-RNTI and another PDSCH scheduled in the same serving cell with CS-RNTI if the PDSCHs partially or fully overlap in time except if the PDCCH scheduling the PDSCH with C-RNTI or MCS-C-RNTI ends at least 14 symbols before the start of the PDSCH with CS-RNTI without the corresponding DCI, in which case the UE shall decode the PDSCH scheduled with C-RNTI or MCS-C-RNTI.

The UE is not expected to decode a PDSCH scheduled with C-RNTI, MCS-C-RNTI, or CS-RNTI if another PDSCH in the same cell scheduled with RA-RNTI partially or fully overlap in time.

The UE in RRC_IDLE and RRC_INACTIVE modes shall be able to decode two PDSCHs each scheduled with SI-RNTI, P-RNTI, RA-RNTI or TC-RNTI, with the two PDSCHs partially or fully overlapping in time in non-overlapping PRBs.

On a frequency range 1 cell, the UE shall be able to decode a PDSCH scheduled with C-RNTI, MCS-C-RNTI, or CS-RNTI and, during a process of P-RNTI triggered SI acquisition, another PDSCH scheduled with SI-RNTI that partially or fully overlap in time in non-overlapping PRBs, unless the PDSCH scheduled with C-RNTI, MCS-C-RNTI, or CS-RNTI requires Capability 2 processing time according to clause 5.3 in which case the UE may skip decoding of the scheduled PDSCH with C-RNTI, MCS-C-RNTI, or CS-RNTI.

On a frequency range 2 cell, the UE is not expected to decode a PDSCH scheduled with C-RNTI, MCS-C-RNTI, or CS-RNTI if in the same cell, during a process of P-RNTI triggered SI acquisition, another PDSCH scheduled with SI-RNTI partially or fully overlap in time.

The UE is expected to decode a PDSCH scheduled with C-RNTI, MCS-C-RNTI, or CS-RNTI during a process of autonomous SI acquisition.

If the UE is configured by higher layers to decode a PDCCH with its CRC scrambled by a CS-RNTI, the UE shall receive PDSCH transmissions without corresponding PDCCH transmissions using the higher-layer-provided PDSCH configuration for those PDSCHs.

5.1.1 Transmission schemes

Only one transmission scheme is defined for the PDSCH, and is used for all PDSCH transmissions.

5.1.1.1 Transmission scheme 1

For transmission scheme 1 of the PDSCH, the UE may assume that a gNB transmission on the PDSCH would be performed with up to 8 transmission layers on antenna ports 1000-1011 as defined in Clause 7.3.1.4 of [4, TS 38.211], subject to the DM-RS reception procedures in Clause 5.1.6.2.

5.1.2 Resource allocation

5.1.2.1 Resource allocation in time domain

When the UE is scheduled to receive PDSCH by a DCI, the *Time domain resource assignment* field value m of the DCI provides a row index $m + 1$ to an allocation table. The determination of the used resource allocation table is defined in Clause 5.1.2.1.1. The indexed row defines the slot offset K_0 , the start and length indicator $SLIV$, or directly the start symbol S and the allocation length L , and the PDSCH mapping type to be assumed in the PDSCH reception.

Given the parameter values of the indexed row:

- The slot allocated for the PDSCH is $\left\lfloor n \cdot \frac{2^{\mu_{\text{PDSCH}}}}{2^{\mu_{\text{PDCCH}}}} \right\rfloor + K_0$, where n is the slot with the scheduling DCI, and K_0 is

based on the numerology of PDSCH, and μ_{PDSCH} and μ_{PDCCH} are the subcarrier spacing configurations for PDSCH and PDCCH, respectively, and

- The starting symbol S relative to the start of the slot, and the number of consecutive symbols L counting from the symbol S allocated for the PDSCH are determined from the start and length indicator $SLIV$:

if $(L-1) \leq 7$ then

$$SLIV = 14 \cdot (L-1) + S$$

else

$$SLIV = 14 \cdot (14-L+1) + (14-1-S)$$

where $0 < L \leq 14 - S$, and

- The PDSCH mapping type is set to Type A or Type B as defined in Clause 7.4.1.1.2 of [4, TS 38.211].

The UE shall consider the S and L combinations defined in table 5.1.2.1-1 as valid PDSCH allocations:

Table 5.1.2.1-1: Valid S and L combinations

PDSCH mapping type	Normal cyclic prefix			Extended cyclic prefix		
	S	L	$S+L$	S	L	$S+L$
Type A	{0,1,2,3} (Note 1)	{3,...,14}	{3,...,14}	{0,1,2,3} (Note 1)	{3,...,12}	{3,...,12}
Type B	{0,...,12}	{2,4,7}	{2,...,14}	{0,...,10}	{2,4,6}	{2,...,12}

Note 1: $S = 3$ is applicable only if $dmrs\text{-}TypeA\text{-}Position = 3$

When receiving PDSCH scheduled by DCI format 1_1 in PDCCH with CRC scrambled by C-RNTI, MCS-C-RNTI, CS-RNTI, or PDSCH scheduled without corresponding PDCCH transmission using *sps-Config* and activated by DCI format 1_1, if the UE is configured with *pdsch-AggregationFactor*, the same symbol allocation is applied across the *pdsch-AggregationFactor* consecutive slots. The UE may expect that the TB is repeated within each symbol allocation among each of the *pdsch-AggregationFactor* consecutive slots and the PDSCH is limited to a single transmission layer. The redundancy version to be applied on the n^{th} transmission occasion of the TB, where $n = 0, 1, \dots, pdsch\text{-}AggregationFactor - 1$, is determined according to table 5.1.2.1-2 and " rv_{id} indicated by the DCI scheduling the PDSCH" in table 5.1.2.1-2 is assumed to be 0 for PDSCH scheduled without corresponding PDCCH transmission using *sps-Config* and activated by DCI format 1_1.

Table 5.1.2.1-2: Applied redundancy version when *pdsch-AggregationFactor* is present

rv_{id} indicated by the DCI scheduling the PDSCH	rv_{id} to be applied to n^{th} transmission occasion			
	$n \bmod 4 = 0$	$n \bmod 4 = 1$	$n \bmod 4 = 2$	$n \bmod 4 = 3$
0	0	2	3	1
2	2	3	1	0
3	3	1	0	2
1	1	0	2	3

A PDSCH reception in a slot of a multi-slot PDSCH reception is omitted according to the conditions in Clause 11.1 of [6, TS38.213].

The UE is not expected to receive a PDSCH with mapping type A in a slot, if the PDCCH scheduling the PDSCH was received in the same slot and was not contained within the first three symbols of the slot.

The UE is not expected to receive a PDSCH with mapping type B in a slot, if the first symbol of the PDCCH scheduling the PDSCH was received in a later symbol than the first symbol indicated in the PDSCH time domain resource allocation.

5.1.2.1.1 Determination of the resource allocation table to be used for PDSCH

Table 5.1.2.1.1-1 defines which PDSCH time domain resource allocation configuration to apply. Either a default PDSCH time domain allocation A, B or C according to tables 5.1.2.1.1-2, 5.1.2.1.1-3, 5.1.2.1.1-4 and 5.1.2.1.1-5 is applied, or the higher layer configured *pdsch-TimeDomainAllocationList* in either *pdsch-ConfigCommon* or *pdsch-Config* is applied.

Table 5.1.2.1.1-1: Applicable PDSCH time domain resource allocation

RNTI	PDCCH search space	SS/PBCH block and CORESET multiplexing pattern	<i>pdsch-ConfigCommon</i> includes <i>pdsch-TimeDomainAllocationList</i>	<i>pdsch-Config</i> includes <i>pdsch-TimeDomainAllocationList</i>	PDSCH time domain resource allocation to apply
SI-RNTI	Type0 common	1	-	-	Default A for normal CP
		2	-	-	Default B
		3	-	-	Default C
SI-RNTI	Type0A common	1	No	-	Default A
		2	No	-	Default B
		3	No	-	Default C
		1,2,3	Yes	-	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-ConfigCommon</i>
RA-RNTI, TC-RNTI	Type1 common	1, 2, 3	No	-	Default A
		1, 2, 3	Yes	-	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-ConfigCommon</i>
P-RNTI	Type2 common	1	No	-	Default A
		2	No	-	Default B
		3	No	-	Default C
		1,2,3	Yes	-	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-ConfigCommon</i>
C-RNTI, MCS-C-RNTI, CS-RNTI	Any common search space associated with CORESET 0	1, 2, 3	No	-	Default A
		1, 2, 3	Yes	-	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-ConfigCommon</i>
C-RNTI, MCS-C-RNTI, CS-RNTI	Any common search space not associated with CORESET 0	1,2,3	No	No	Default A
		1,2,3	Yes	No	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-ConfigCommon</i>
	UE specific search space	1,2,3	No/Yes	Yes	<i>pdsch-TimeDomainAllocationList</i> provided in <i>pdsch-Config</i>

Table 5.1.2.1.1-2: Default PDSCH time domain resource allocation A for normal CP

Row index	<i>dmrs-TypeA-Position</i>	PDSCH mapping type	K_0	S	L
1	2	Type A	0	2	12
	3	Type A	0	3	11
2	2	Type A	0	2	10
	3	Type A	0	3	9
3	2	Type A	0	2	9
	3	Type A	0	3	8
4	2	Type A	0	2	7
	3	Type A	0	3	6
5	2	Type A	0	2	5
	3	Type A	0	3	4
6	2	Type B	0	9	4
	3	Type B	0	10	4
7	2	Type B	0	4	4
	3	Type B	0	6	4
8	2,3	Type B	0	5	7
9	2,3	Type B	0	5	2
10	2,3	Type B	0	9	2
11	2,3	Type B	0	12	2
12	2,3	Type A	0	1	13
13	2,3	Type A	0	1	6
14	2,3	Type A	0	2	4
15	2,3	Type B	0	4	7
16	2,3	Type B	0	8	4

Table 5.1.2.1.1-3: Default PDSCH time domain resource allocation A for extended CP

Row index	<i>dmrs-TypeA-Position</i>	PDSCH mapping type	K_0	S	L
1	2	Type A	0	2	6
	3	Type A	0	3	5
2	2	Type A	0	2	10
	3	Type A	0	3	9
3	2	Type A	0	2	9
	3	Type A	0	3	8
4	2	Type A	0	2	7
	3	Type A	0	3	6
5	2	Type A	0	2	5
	3	Type A	0	3	4
6	2	Type B	0	6	4
	3	Type B	0	8	2
7	2	Type B	0	4	4
	3	Type B	0	6	4
8	2,3	Type B	0	5	6
9	2,3	Type B	0	5	2
10	2,3	Type B	0	9	2
11	2,3	Type B	0	10	2
12	2,3	Type A	0	1	11
13	2,3	Type A	0	1	6
14	2,3	Type A	0	2	4
15	2,3	Type B	0	4	6
16	2,3	Type B	0	8	4

Table 5.1.2.1.1-4: Default PDSCH time domain resource allocation B

Row index	<i>dmrs-TypeA-Position</i>	PDSCH mapping type	K_0	S	L
1	2,3	Type B	0	2	2
2	2,3	Type B	0	4	2
3	2,3	Type B	0	6	2
4	2,3	Type B	0	8	2
5	2,3	Type B	0	10	2
6	2,3	Type B	1	2	2
7	2,3	Type B	1	4	2
8	2,3	Type B	0	2	4
9	2,3	Type B	0	4	4
10	2,3	Type B	0	6	4
11	2,3	Type B	0	8	4
12 (Note 1)	2,3	Type B	0	10	4
13 (Note 1)	2,3	Type B	0	2	7
14 (Note 1)	2	Type A	0	2	12
	3	Type A	0	3	11
15	2,3	Type B	1	2	4
16	Reserved				

Note 1: If the PDSCH was scheduled with SI-RNTI in PDCCH Type0 common search space, the UE may assume that this PDSCH resource allocation is not applied

Table 5.1.2.1.1-5: Default PDSCH time domain resource allocation C

Row index	<i>dmrs-TypeA-Position</i>	PDSCH mapping type	K_0	S	L
1 (Note 1)	2,3	Type B	0	2	2
2	2,3	Type B	0	4	2
3	2,3	Type B	0	6	2
4	2,3	Type B	0	8	2
5	2,3	Type B	0	10	2
6	Reserved				
7	Reserved				
8	2,3	Type B	0	2	4
9	2,3	Type B	0	4	4
10	2,3	Type B	0	6	4
11	2,3	Type B	0	8	4
12	2,3	Type B	0	10	4
13 (Note 1)	2,3	Type B	0	2	7
14 (Note 1)	2	Type A	0	2	12
	3	Type A	0	3	11
15 (Note 1)	2,3	Type A	0	0	6
16 (Note 1)	2,3	Type A	0	2	6

Note 1: The UE may assume that this PDSCH resource allocation is not used, if the PDSCH was scheduled with SI-RNTI in PDCCH Type0 common search space

5.1.2.2 Resource allocation in frequency domain

Two downlink resource allocation schemes, type 0 and type 1, are supported. The UE shall assume that when the scheduling grant is received with DCI format 1_0, then downlink resource allocation type 1 is used.

If the scheduling DCI is configured to indicate the downlink resource allocation type as part of the *Frequency domain resource assignment* field by setting a higher layer parameter *resourceAllocation* in *pdsch-Config* to 'dynamicswitch', the UE shall use downlink resource allocation type 0 or type 1 as defined by this DCI field. Otherwise the UE shall use the downlink frequency resource allocation type as defined by the higher layer parameter *resourceAllocation*.

If a bandwidth part indicator field is not configured in the scheduling DCI or the UE does not support active BWP change via DCI, the RB indexing for downlink type 0 and type 1 resource allocation is determined within the UE's active bandwidth part. If a bandwidth part indicator field is configured in the scheduling DCI and the UE supports active BWP change via DCI, the RB indexing for downlink type 0 and type 1 resource allocation is determined within

the UE's bandwidth part indicated by bandwidth part indicator field value in the DCI. The UE shall upon detection of PDCCH intended for the UE determine first the downlink bandwidth part and then the resource allocation within the bandwidth part.

For a PDSCH scheduled with a DCI format 1_0 in any type of PDCCH common search space, regardless of which bandwidth part is the active bandwidth part, RB numbering starts from the lowest RB of the CORESET in which the DCI was received; otherwise RB numbering starts from the lowest RB in the determined downlink bandwidth part.

5.1.2.2.1 Downlink resource allocation type 0

In downlink resource allocation of type 0, the resource block assignment information includes a bitmap indicating the Resource Block Groups (RBGs) that are allocated to the scheduled UE where a RBG is a set of consecutive virtual resource blocks defined by higher layer parameter *rbg-Size* configured by *PDSCH-Config* and the size of the bandwidth part as defined in Table 5.1.2.2.1-1.

Table 5.1.2.2.1-1: Nominal RBG size P

Bandwidth Part Size	Configuration 1	Configuration 2
1 – 36	2	4
37 – 72	4	8
73 – 144	8	16
145 – 275	16	16

The total number of RBGs (N_{RBG}) for a downlink bandwidth part i of size $N_{\text{BWP},i}^{\text{size}}$ PRBs is given by

$$N_{\text{RBG}} = \left\lceil \left(N_{\text{BWP},i}^{\text{size}} + \left(N_{\text{BWP},i}^{\text{start}} \bmod P \right) \right) / P \right\rceil, \text{ where}$$

- the size of the first RBG is $\text{RBG}_0^{\text{size}} = P - N_{\text{BWP},i}^{\text{start}} \bmod P$,
- the size of last RBG is $\text{RBG}_{\text{last}}^{\text{size}} = \left(N_{\text{BWP},i}^{\text{start}} + N_{\text{BWP},i}^{\text{size}} \right) \bmod P$ if $\left(N_{\text{BWP},i}^{\text{start}} + N_{\text{BWP},i}^{\text{size}} \right) \bmod P > 0$ and P otherwise,
- the size of all other RBGs is P .

The bitmap is of size N_{RBG} bits with one bitmap bit per RBG such that each RBG is addressable. The RBGs shall be indexed in the order of increasing frequency and starting at the lowest frequency of the bandwidth part. The order of RBG bitmap is such that RBG 0 to RBG $N_{\text{RBG}} - 1$ are mapped from MSB to LSB. The RBG is allocated to the UE if the corresponding bit value in the bitmap is 1, the RBG is not allocated to the UE otherwise.

5.1.2.2.2 Downlink resource allocation type 1

In downlink resource allocation of type 1, the resource block assignment information indicates to a scheduled UE a set of contiguously allocated non-interleaved or interleaved virtual resource blocks within the active bandwidth part of size $N_{\text{BWP}}^{\text{size}}$ PRBs except for the case when DCI format 1_0 is decoded in any common search space in which case the size of CORESET 0 shall be used if CORESET 0 is configured for the cell and the size of initial DL bandwidth part shall be used if CORESET 0 is not configured for the cell.

A downlink type 1 resource allocation field consists of a resource indication value (*RIV*) corresponding to a starting virtual resource block (RB_{start}) and a length in terms of contiguously allocated resource blocks L_{RBs} . The resource indication value is defined by

if $(L_{\text{RBs}} - 1) \leq \lfloor N_{\text{BWP}}^{\text{size}} / 2 \rfloor$ then

$$RIV = N_{\text{BWP}}^{\text{size}}(L_{\text{RBs}} - 1) + \text{RB}_{\text{start}}$$

else

$$RIV = N_{\text{BWP}}^{\text{size}}(N_{\text{BWP}}^{\text{size}} - L_{\text{RBs}} + 1) + (N_{\text{BWP}}^{\text{size}} - 1 - \text{RB}_{\text{start}})$$

where $L_{RBs} \geq 1$ and shall not exceed $N_{BWP}^{size} - RB_{start}$.

When the DCI size for DCI format 1_0 in USS is derived from the size of DCI format 1_0 in CSS but applied to an active BWP with size of N_{BWP}^{active} , a downlink type 1 resource block assignment field consists of a resource indication value (RIV) corresponding to a starting resource block $RB_{start} = 0, K, 2 \cdot K, \dots, (N_{BWP}^{initial} - 1) \cdot K$ and a length in terms of virtually contiguously allocated resource blocks $L_{RBs} = K, 2 \cdot K, \dots, N_{BWP}^{initial} \cdot K$, where $N_{BWP}^{initial}$ is given by

- the size of CORESET 0 if CORESET 0 is configured for the cell;
- the size of initial DL bandwidth part if CORESET 0 is not configured for the cell.

The resource indication value is defined by:

if $(L'_{RBs} - 1) \leq \lfloor N_{BWP}^{initial} / 2 \rfloor$ then

$$RIV = N_{BWP}^{initial} (L'_{RBs} - 1) + RB'_{start}$$

else

$$RIV = N_{BWP}^{initial} (N_{BWP}^{initial} - L'_{RBs} + 1) + (N_{BWP}^{initial} - 1 - RB'_{start})$$

where $L'_{RBs} = L_{RBs} / K$, $RB'_{start} = RB_{start} / K$ and where L'_{RBs} shall not exceed $N_{BWP}^{initial} - RB'_{start}$.

If $N_{BWP}^{active} > N_{BWP}^{initial}$, K is the maximum value from set $\{1, 2, 4, 8\}$ which satisfies $K \leq \lfloor N_{BWP}^{active} / N_{BWP}^{initial} \rfloor$; otherwise $K = 1$.

5.1.2.3 Physical resource block (PRB) bundling

A UE may assume that precoding granularity is $P'_{BWP,i}$ consecutive resource blocks in the frequency domain. $P'_{BWP,i}$ can be equal to one of the values among $\{2, 4, \text{wideband}\}$.

If $P'_{BWP,i}$ is determined as "wideband", the UE is not expected to be scheduled with non-contiguous PRBs and the UE may assume that the same precoding is applied to the allocated resource.

If $P'_{BWP,i}$ is determined as one of the values among $\{2, 4\}$, Precoding Resource Block Group (PRGs) partitions the bandwidth part i with $P'_{BWP,i}$ consecutive PRBs. Actual number of consecutive PRBs in each PRG could be one or more.

The first PRG size is given by $P'_{BWP,i} - N_{BWP,i}^{start} \bmod P'_{BWP}$ and the last PRG size given by $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod P'_{BWP,i}$ if $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod P'_{BWP,i} \neq 0$, and the last PRG size is $P'_{BWP,i}$ if $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod P'_{BWP,i} = 0$.

The UE may assume the same precoding is applied for any downlink contiguous allocation of PRBs in a PRG.

For PDSCH carrying SIB1 scheduled by PDCCH with CRC scrambled by SI-RNTI, a PRG is partitioned from the lowest numbered resource block of CORESET 0 if the corresponding PDCCH is associated with CORESET 0 and Type0-PDCCH common search space and is addressed to SI-RNTI; otherwise, a PRG is partitioned from common resource block 0.

If a UE is scheduled a PDSCH with DCI format 1_0, the UE shall assume that $P'_{BWP,i}$ is equal to 2 PRBs.

When receiving PDSCH scheduled by PDCCH with DCI format 1_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, or CS-RNTI, $P'_{BWP,i}$ for bandwidth part is equal to 2 PRBs unless configured by the higher layer parameter *prb-BundlingType* given by *PDSCH-Config*.

When receiving PDSCH scheduled by PDCCH with DCI format 1_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, or CS-RNTI, if the higher layer parameter *prb-BundlingType* is set to 'dynamicBundling', the higher layer parameters *bundleSizeSet1* and *bundleSizeSet2* configure two sets of $P'_{BWP,i}$ values, the first set can take one or two $P'_{BWP,i}$ values among $\{2, 4, \text{wideband}\}$, and the second set can take one $P'_{BWP,i}$ value among $\{2, 4, \text{wideband}\}$.

If the *PRB bundling size indicator* signalled in DCI format 1_1 as defined in Clause 7.3.1.2.2 of [5, TS 38.212]

- is set to '0', the UE shall use the $P'_{BWP,i}$ value from the second set of $P'_{BWP,i}$ values when receiving PDSCH scheduled by the same DCI.
- is set to '1' and one value is configured for the first set of $P'_{BWP,i}$ values, the UE shall use this $P'_{BWP,i}$ value when receiving PDSCH scheduled by the same DCI
- is set to '1' and two values are configured for the first set of $P'_{BWP,i}$ values as 'n2-wideband' (corresponding to two $P'_{BWP,i}$ values 2 and wideband) or 'n4-wideband' (corresponding to two $P'_{BWP,i}$ values 4 and wideband), the UE shall use the value when receiving PDSCH scheduled by the same DCI as follows:
 - If the scheduled PRBs are contiguous and the size of the scheduled PRBs is larger than $N_{BWP,i}^{size} / 2$, $P'_{BWP,i}$ is the same as the scheduled bandwidth, otherwise $P'_{BWP,i}$ is set to the remaining configured value of 2 or 4, respectively.

When receiving PDSCH scheduled by PDCCH with DCI format 1_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, or CS-RNTI, if the higher layer parameter *prb-BundlingType* is set to 'staticBundling', the $P'_{BWP,i}$ value is configured with the single value indicated by the higher layer parameter *bundleSize*.

When a UE is configured with nominal RBG size $P = 2$ for bandwidth part i according to Clause 5.1.2.2.1, or when a UE is configured with interleaving unit of 2 for VRB to PRB mapping provided by the higher layer parameter *vrB-ToPRB-Interleaver* given by *PDSCH-Config* for bandwidth part i , the UE is not expected to be configured with $P'_{BWP,i} = 4$.

5.1.3 Modulation order, target code rate, redundancy version and transport block size determination

To determine the modulation order, target code rate, and transport block size(s) in the physical downlink shared channel, the UE shall first

- read the 5-bit modulation and coding scheme field (I_{MCS}) in the DCI to determine the modulation order (Q_m) and target code rate (R) based on the procedure defined in Clause 5.1.3.1, and
- read *redundancy version* field (rv) in the DCI to determine the redundancy version..

and second

- the UE shall use the number of layers (v), the total number of allocated PRBs before rate matching (n_{PRB}) to determine to the transport block size based on the procedure defined in Clause 5.1.3.2.

The UE may skip decoding a transport block in an initial transmission if the effective channel code rate is higher than 0.95, where the effective channel code rate is defined as the number of downlink information bits (including CRC bits) divided by the number of physical channel bits on PDSCH.

The UE is not expected to handle any transport blocks (TBs) in a 14 consecutive-symbol duration for normal CP (or 12 for extended CP) ending at the last symbol of the latest PDSCH transmission within an active BWP on a serving cell whenever

$$2^{\max(0, \mu - \mu')} \cdot \sum_{i \in S} \left\lfloor \frac{C'_i}{L_i} \right\rfloor x_{i, F_i} > \left\lfloor \frac{X}{4} \right\rfloor \cdot \frac{1}{R_{LBRM}} \cdot TBS_{LBRM}$$

where, for the serving cell,

- S is the set of TBs belonging to PDSCH(s) that are partially or fully contained in the consecutive-symbol duration
- for the i th TB
 - C'_i is the number of scheduled code blocks for as defined in [5, 38.212].
 - L_i is the number of OFDM symbols assigned to the PDSCH

- x_i is the number of OFDM symbols of the PDSCH contained in the consecutive-symbol duration
- $F_i = \max_{j=0, \dots, J-1} (\min(k_{0,i}^j + E_i^j, N_{cb,i}))$ based on the values defined in Clause 5.4.2.1 [5, TS 38.212]
- $k_{0,i}^j$ is the starting location of RV for the j th transmission
- $E_i^j = \min(E_r)$ of the scheduled code blocks for the j th transmission
- $N_{cb,i}$ is the circular buffer length
- $J - 1$ is the current (re)transmission for the i th TB
- μ' corresponds to the subcarrier spacing of the BWP (across all configured BWPs of a carrier) that has the largest configured number of PRBs
 - in case there is more than one BWP corresponding to the largest configured number of PRBs, μ' follows the BWP with the largest subcarrier spacing.
- μ corresponds to the subcarrier spacing of the active BWP
- $R_{LBRM} = 2/3$ as defined in Clause 5.4.2.1 [5, TS 38.212]
- TBS_{LBRM} as defined in Clause 5.4.2.1 [5, TS 38.212]
- X as defined for downlink in Clause 5.4.2.1 [5, TS 38.212].

If the UE skips decoding, the physical layer indicates to higher layer that the transport block is not successfully decoded.

Within a cell group, a UE is not required to handle PDSCH(s) transmissions in slot s_j in serving cell- j , and for $j = 0, 1, 2, \dots, J-1$, slot s_j overlapping with any given point in time, if the following condition is not satisfied at that point in time:

$$\sum_{j=0}^{J-1} \frac{\sum_{m=0}^{M-1} V_{j,m}}{T_{slot}^{\mu(j)}} \leq DataRate$$

where,

- J is the number of configured serving cells belonging to a frequency range
- for the j -th serving cell,
 - M is the number of TB(s) transmitted in slot s_j .
 - $T_{slot}^{\mu(j)} = 10^{-3}/2^{\mu(j)}$, where $\mu(j)$ is the numerology for PDSCH(s) in slot s_j of the j -th serving cell.
 - for the m -th TB, $V_{j,m} = C' \cdot \left\lfloor \frac{A}{C} \right\rfloor$
 - A is the number of bits in the transport block as defined in Clause 7.2.1 [5, TS 38.212]
 - C is the total number of code blocks for the transport block defined in Clause 5.2.2 [5, TS 38.212].
 - C' is the number of scheduled code blocks for the transport block as defined in Clause 5.4.2.1 [5, TS 38.212]
- $DataRate$ [Mbps] is computed as the maximum data rate summed over all the carriers in the frequency range for any signaled band combination and feature set consistent with the configured serving cells, where the data rate value is given by the formula in Clause 4.1.2 in [13, TS 38.306], including the scaling factor $f(i)$.

For a j -th serving cell, if higher layer parameter *processingType2Enabled* of *PDSCH-ServingCellConfig* is configured for the serving cell and set to *enable*, or if at least one $I_{MCS} > W$ for a PDSCH, where $W = 28$ for MCS tables 5.1.3.1-1 and 5.1.3.1-3, and $W = 27$ for MCS table 5.1.3.1-2, the UE is not required to handle PDSCH transmissions, if the following condition is not satisfied:

$$\frac{\sum_{m=0}^{M-1} V_{j,m}}{L \times T_s^\mu} \leq DataRateCC$$

where

- L is the number of symbols assigned to the PDSCH
- M is the number of TB(s) in the PDSCH
- $T_s^\mu = \frac{10^{-3}}{2^{\mu \cdot N_{symbol}}}$ where μ is the numerology of the PDSCH
- for the m -th TB, $V_{j,m} = C' \cdot \left\lfloor \frac{A}{C} \right\rfloor$
 - A is the number of bits in the transport block as defined in Clause 7.2.1 [5, TS 38.212]
 - C is the total number of code blocks for the transport block defined in Clause 5.2.2 [5, TS 38.212]
 - C' is the number of scheduled code blocks for the transport block as defined in Clause 5.4.2.1 [5, TS 38.212]
- $DataRateCC$ [Mbps] is computed as the maximum data rate for a carrier in the frequency band of the serving cell for any signaled band combination and feature set consistent with the serving cell, where the data rate value is given by the formula in Clause 4.1.2 in [13, TS 38.306], including the scaling factor $f(i)$.

5.1.3.1 Modulation order and target code rate determination

For the PDSCH scheduled by a PDCCH with DCI format 1_0 or format 1_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI, SI-RNTI, RA-RNTI, or P-RNTI, or for the PDSCH scheduled without corresponding PDCCH transmissions using the higher-layer-provided PDSCH configuration *SPS-Config*,

if the higher layer parameter *mcs-Table* given by *PDSCH-Config* is set to 'qam256', and the PDSCH is scheduled by a PDCCH with DCI format 1_1 with CRC scrambled by C-RNTI

- the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

elseif the UE is not configured with MCS-C-RNTI, the higher layer parameter *mcs-Table* given by *PDSCH-Config* is set to 'qam64LowSE', and the PDSCH is scheduled by a PDCCH in a UE-specific search space with CRC scrambled by C-RNTI

- the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

elseif the UE is configured with MCS-C-RNTI, and the PDSCH is scheduled by a PDCCH with CRC scrambled by MCS-C-RNTI

- the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

elseif the UE is not configured with the higher layer parameter *mcs-Table* given by *SPS-Config*, the higher layer parameter *mcs-Table* given by *PDSCH-Config* is set to 'qam256',

- if the PDSCH is scheduled by a PDCCH with DCI format 1_1 with CRC scrambled by CS-RNTI or
- if the PDSCH is scheduled without corresponding PDCCH transmission using *SPS-Config*,
 - the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

elseif the UE is configured with the higher layer parameter *mcs-Table* given by *SPS-Config* set to 'qam64LowSE'

- if the PDSCH is scheduled by a PDCCH with CRC scrambled by CS-RNTI or
- if the PDSCH is scheduled without corresponding PDCCH transmission using *SPS-Config*,

- the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

else

- the UE shall use I_{MCS} and Table 5.1.3.1-1 to determine the modulation order (Q_m) and Target code rate (R) used in the physical downlink shared channel.

end

The UE is not expected to decode a PDSCH scheduled with P-RNTI, RA-RNTI, SI-RNTI and $Q_m > 2$

Table 5.1.3.1-1: MCS index table 1 for PDSCH

MCS Index I_{MCS}	Modulation Order Q_m	Target code Rate $R \times [1024]$	Spectral efficiency
0	2	120	0.2344
1	2	157	0.3066
2	2	193	0.3770
3	2	251	0.4902
4	2	308	0.6016
5	2	379	0.7402
6	2	449	0.8770
7	2	526	1.0273
8	2	602	1.1758
9	2	679	1.3262
10	4	340	1.3281
11	4	378	1.4766
12	4	434	1.6953
13	4	490	1.9141
14	4	553	2.1602
15	4	616	2.4063
16	4	658	2.5703
17	6	438	2.5664
18	6	466	2.7305
19	6	517	3.0293
20	6	567	3.3223
21	6	616	3.6094
22	6	666	3.9023
23	6	719	4.2129
24	6	772	4.5234
25	6	822	4.8164
26	6	873	5.1152
27	6	910	5.3320
28	6	948	5.5547
29	2	reserved	
30	4	reserved	
31	6	reserved	

Table 5.1.3.1-2: MCS index table 2 for PDSCH

MCS Index I_{MCS}	Modulation Order Q_m	Target code Rate R_x [1024]	Spectral efficiency
0	2	120	0.2344
1	2	193	0.3770
2	2	308	0.6016
3	2	449	0.8770
4	2	602	1.1758
5	4	378	1.4766
6	4	434	1.6953
7	4	490	1.9141
8	4	553	2.1602
9	4	616	2.4063
10	4	658	2.5703
11	6	466	2.7305
12	6	517	3.0293
13	6	567	3.3223
14	6	616	3.6094
15	6	666	3.9023
16	6	719	4.2129
17	6	772	4.5234
18	6	822	4.8164
19	6	873	5.1152
20	8	682.5	5.3320
21	8	711	5.5547
22	8	754	5.8906
23	8	797	6.2266
24	8	841	6.5703
25	8	885	6.9141
26	8	916.5	7.1602
27	8	948	7.4063
28	2	reserved	
29	4	reserved	
30	6	reserved	
31	8	reserved	

Table 5.1.3.1-3: MCS index table 3 for PDSCH

MCS Index I_{MCS}	Modulation Order Q_m	Target code Rate $R \times [1024]$	Spectral efficiency
0	2	30	0.0586
1	2	40	0.0781
2	2	50	0.0977
3	2	64	0.1250
4	2	78	0.1523
5	2	99	0.1934
6	2	120	0.2344
7	2	157	0.3066
8	2	193	0.3770
9	2	251	0.4902
10	2	308	0.6016
11	2	379	0.7402
12	2	449	0.8770
13	2	526	1.0273
14	2	602	1.1758
15	4	340	1.3281
16	4	378	1.4766
17	4	434	1.6953
18	4	490	1.9141
19	4	553	2.1602
20	4	616	2.4063
21	6	438	2.5664
22	6	466	2.7305
23	6	517	3.0293
24	6	567	3.3223
25	6	616	3.6094
26	6	666	3.9023
27	6	719	4.2129
28	6	772	4.5234
29	2	reserved	
30	4	reserved	
31	6	reserved	

5.1.3.2 Transport block size determination

In case the higher layer parameter *maxNrofCodeWordsScheduledByDCI* indicates that two codeword transmission is enabled, then one of the two transport blocks is disabled by DCI format 1_1 if $I_{MCS} = 26$ and if $rv_{id} = 1$ for the corresponding transport block. If both transport blocks are enabled, transport block 1 and 2 are mapped to codeword 0 and 1 respectively. If only one transport block is enabled, then the enabled transport block is always mapped to the first codeword.

For the PDSCH assigned by a PDCCH with DCI format 1_0 or format 1_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI, or SI-RNTI, if Table 5.1.3.1-2 is used and $0 \leq I_{MCS} \leq 27$, or a table other than Table 5.1.3.1-2 is used and $0 \leq I_{MCS} \leq 28$, the UE shall, except if the transport block is disabled in DCI format 1_1, first determine the TBS as specified below:

1) The UE shall first determine the number of REs (N_{RE}) within the slot.

- A UE first determines the number of REs allocated for PDSCH within a PRB (N'_{RE}) by

$$N'_{RE} = N_{sc}^{RB} \cdot N_{symb}^{sh} - N_{DMRS}^{PRB} - N_{oh}^{PRB}, \text{ where } N_{sc}^{RB} = 12 \text{ is the number of subcarriers in a physical resource}$$

block, N_{symb}^{sh} is the number of symbols of the PDSCH allocation within the slot, N_{DMRS}^{PRB} is the number of REs for DM-RS per PRB in the scheduled duration including the overhead of the DM-RS CDM groups without data, as indicated by DCI format 1_1 or as described for format 1_0 in Clause 5.1.6.2, and N_{oh}^{PRB} is the overhead configured by higher layer parameter *xOverhead* in *PDSCH-ServingCellConfig*. If the *xOverhead* in *PDSCH-ServingCellConfig* is not configured (a value from 0, 6, 12, or 18), the N_{oh}^{PRB} is set to

0. If the PDSCH is scheduled by PDCCH with a CRC scrambled by SI-RNTI, RA-RNTI or P-RNTI, N_{oh}^{PRB} is assumed to be 0.

- A UE determines the total number of REs allocated for PDSCH (N_{RE}) by $N_{RE} = \min(156, N_{RE}^i) \cdot n_{PRB}$, where n_{PRB} is the total number of allocated PRBs for the UE.

2) Intermediate number of information bits (N_{info}) is obtained by $N_{info} = N_{RE} \cdot R \cdot Q_m \cdot \nu$.

If $N_{info} \leq 3824$

Use step 3 as the next step of the TBS determination

else

Use step 4 as the next step of the TBS determination

end if

3) When $N_{info} \leq 3824$, TBS is determined as follows

- quantized intermediate number of information bits $N_{info}^i = \max\left(24, 2^n \cdot \left\lfloor \frac{N_{info}}{2^n} \right\rfloor\right)$, where $n = \max(3, \lfloor \log_2(N_{info}) \rfloor - 6)$.
- use Table 5.1.3.2-1 find the closest TBS that is not less than N_{info}^i .

Table 5.1.3.2-1: TBS for $N_{info} \leq 3824$

Index	TBS	Index	TBS	Index	TBS	Index	TBS
1	24	31	336	61	1288	91	3624
2	32	32	352	62	1320	92	3752
3	40	33	368	63	1352	93	3824
4	48	34	384	64	1416		
5	56	35	408	65	1480		
6	64	36	432	66	1544		
7	72	37	456	67	1608		
8	80	38	480	68	1672		
9	88	39	504	69	1736		
10	96	40	528	70	1800		
11	104	41	552	71	1864		
12	112	42	576	72	1928		
13	120	43	608	73	2024		
14	128	44	640	74	2088		
15	136	45	672	75	2152		
16	144	46	704	76	2216		
17	152	47	736	77	2280		
18	160	48	768	78	2408		
19	168	49	808	79	2472		
20	176	50	848	80	2536		
21	184	51	888	81	2600		
22	192	52	928	82	2664		
23	208	53	984	83	2728		
24	224	54	1032	84	2792		
25	240	55	1064	85	2856		
26	256	56	1128	86	2976		
27	272	57	1160	87	3104		
28	288	58	1192	88	3240		
29	304	59	1224	89	3368		
30	320	60	1256	90	3496		

4) When $N_{info} > 3824$, TBS is determined as follows.

- quantized intermediate number of information bits $N'_{info} = \max\left(3840, 2^n \times \text{round}\left(\frac{N_{info} - 24}{2^n}\right)\right)$, where $n = \lfloor \log_2(N_{info} - 24) \rfloor - 5$ and ties in the round function are broken towards the next largest integer.

- if $R \leq 1/4$

$$TBS = 8 \cdot C \cdot \left\lceil \frac{N'_{info} + 24}{8 \cdot C} \right\rceil - 24, \text{ where } C = \left\lceil \frac{N'_{info} + 24}{3816} \right\rceil$$

else

if $N'_{info} > 8424$

$$TBS = 8 \cdot C \cdot \left\lceil \frac{N'_{info} + 24}{8 \cdot C} \right\rceil - 24, \text{ where } C = \left\lceil \frac{N'_{info} + 24}{8424} \right\rceil$$

else

$$TBS = 8 \cdot \left\lceil \frac{N'_{info} + 24}{8} \right\rceil - 24$$

end if

end if

else if Table 5.1.3.1-2 is used and $28 \leq I_{MCS} \leq 31$,

- the TBS is assumed to be as determined from the DCI transported in the latest PDCCH for the same transport block using $0 \leq I_{MCS} \leq 27$. If there is no PDCCH for the same transport block using $0 \leq I_{MCS} \leq 27$, and if the initial PDSCH for the same transport block is semi-persistently scheduled, the TBS shall be determined from the most recent semi-persistent scheduling assignment PDCCH.

else

- the TBS is assumed to be as determined from the DCI transported in the latest PDCCH for the same transport block using $0 \leq I_{MCS} \leq 28$. If there is no PDCCH for the same transport block using $0 \leq I_{MCS} \leq 28$, and if the initial PDSCH for the same transport block is semi-persistently scheduled, the TBS shall be determined from the most recent semi-persistent scheduling assignment PDCCH.

The UE is not expected to receive a PDSCH assigned by a PDCCH with CRC scrambled by SI-RNTI with a TBS exceeding 2976 bits.

For the PDSCH assigned by a PDCCH with DCI format 1_0 with CRC scrambled by P-RNTI, or RA-RNTI, TBS determination follows the steps 1-4 with the following modification in step 2: a scaling $N_{info} = S \cdot N_{RE} \cdot R \cdot Q_m \cdot v$ is applied in the calculation of N_{info} , where the scaling factor is determined based on the *TB scaling* field in the DCI as in Table 5.1.3.2-2.

Table 5.1.3.2-2: Scaling factor of N_{info} for P-RNTI and RA-RNTI

TB scaling field	Scaling factor S
00	1
01	0.5
10	0.25
11	

The NDI and HARQ process ID, as signalled on PDCCH, and the TBS, as determined above, shall be reported to higher layers.

5.1.4 PDSCH resource mapping

When receiving the PDSCH scheduled with SI-RNTI and the system information indicator in DCI is set to 0, the UE shall assume that no SS/PBCH block is transmitted in REs used by the UE for a reception of the PDSCH.

When receiving the PDSCH scheduled with SI-RNTI and the system information indicator in DCI is set to 1, RA-RNTI, P-RNTI or TC-RNTI, the UE assumes SS/PBCH block transmission according to *ssb-PositionsInBurst*, and if the PDSCH resource allocation overlaps with PRBs containing SS/PBCH block transmission resources the UE shall assume that the PRBs containing SS/PBCH block transmission resources are not available for PDSCH in the OFDM symbols where SS/PBCH block is transmitted.

A UE expects a configuration provided by *ssb-PositionsInBurst* in *ServingCellConfigCommon* to be same as a configuration provided by *ssb-PositionsInBurst* in *SIB1*.

When receiving PDSCH scheduled by PDCCH with CRC scrambled by C-RNTI, MCS-C-RNTI, CS-RNTI, or PDSCHs with SPS, the REs corresponding to the configured or dynamically indicated resources in Clauses 5.1.4.1, 5.1.4.2 are not available for PDSCH. Furthermore, the UE assumes SS/PBCH block transmission according to *ssb-PositionsInBurst* if the PDSCH resource allocation overlaps with PRBs containing SS/PBCH block transmission resources, the UE shall assume that the PRBs containing SS/PBCH block transmission resources are not available for PDSCH in the OFDM symbols where SS/PBCH block is transmitted.

A UE is not expected to handle the case where PDSCH DM-RS REs are overlapping, even partially, with any RE(s) not available for PDSCH.

5.1.4.1 PDSCH resource mapping with RB symbol level granularity

A UE may be configured with any of the following higher layer parameters indicating REs declared as not available for PDSCH:

- *rateMatchPatternToAddModList* given by *PDSCH-Config*, by *ServingCellConfig* or by *ServingCellConfigCommon* and configuring up to 4 *RateMatchPattern(s)* per BWP and up to 4 *RateMatchPattern(s)* per serving-cell. A *RateMatchPattern* may contain:
 - within a BWP, when provided by *PDSCH-Config* or within a serving cell when provided by *ServingCellConfig* or *ServingCellConfigCommon*, a pair of reserved resources with numerology provided by higher layer parameter *subcarrierSpacing* given by *RateMatchPattern* when configured per serving cell or by numerology of associated BWP when configured per BWP. The pair of reserved resources are respectively indicated by an RB level bitmap (higher layer parameter *resourceBlocks* given by *RateMatchPattern*) with 1RB granularity and a symbol level bitmap spanning one or two slots (higher layer parameters *symbolsInResourceBlock* given by *RateMatchPattern*) for which the reserved RBs apply. A bit value equal to 1 in the RB and symbol level bitmaps indicates that the corresponding resource is not available for PDSCH. For each pair of RB and symbol level bitmaps, a UE may be configured with a time-domain pattern (higher layer parameter *periodicityAndPattern* given by *RateMatchPattern*), where each bit of *periodicityAndPattern* corresponds to a unit equal to a duration of the symbol level bitmap, and a bit value equal to 1 indicates that the pair is present in the unit. The *periodicityAndPattern* can be {1, 2, 4, 5, 8, 10, 20 or 40} units long, but maximum of 40ms. The first symbol of *periodicityAndPattern* every 40ms/P periods is a first symbol in frame $n_f \bmod 4 = 0$, where P is the duration of *periodicityAndPattern* in units of ms. When *periodicityAndPattern* is not configured for a pair, for a symbol level bitmap spanning two slots, the bits of the first and second slots correspond respectively to even and odd slots of a radio frame, and for a symbol level bitmap spanning one slot, the bits of the slot correspond to every slot of a radio frame. The pair can be included in one or two groups of resource sets (higher layer parameters *rateMatchPatternGroup1* and *rateMatchPatternGroup2*). The *rateMatchPatternToAddModList* given by *ServingCellConfig* or *ServingCellConfigCommon* configuration in numerology μ applies only to PDSCH of the same numerology μ .
 - within a BWP, a frequency domain resource of a CORESET configured by *ControlResourceSet* with *controlResourceSetId* or *ControlResourceSetZero* and time domain resource determined by the higher layer parameters *monitoringSlotPeriodicityAndOffset*, *duration* and *monitoringSymbolsWithinSlot* of all search-space-sets configured by *SearchSpace* and time domain resource of search-space-set zero configured by

searchSpaceZero associated with the CORESET as well as CORESET duration configured by *ControlResourceSet* with *controlResourceSetId* or *ControlResourceSetZero*. This resource not available for PDSCH can be included in one or two groups of resource sets (higher layer parameters *rateMatchPatternGroup1* and *rateMatchPatternGroup2*).

A configured group *rateMatchPatternGroup1* or *rateMatchPatternGroup2* contains a list of indices of *RateMatchPattern(s)* forming a union of resource-sets not available for a PDSCH dynamically if a corresponding bit of the Rate matching indicator field of the DCI format 1_1 scheduling the PDSCH is equal to 1. The REs corresponding to the union of resource-sets configured by *RateMatchPattern(s)* that are not included in either of the two groups are not available for a PDSCH scheduled by a DCI format 1_0, a PDSCH scheduled by a DCI format 1_1, and PDSCHs with SPS. When receiving a PDSCH scheduled by a DCI format 1_0 or PDSCHs with SPS activated by a DCI format 1_0, the REs corresponding to configured resources in *rateMatchPatternGroup1* or *rateMatchPatternGroup2* are not available for the scheduled PDSCH or the activated PDSCHs with SPS. When receiving PDSCHs with SPS activated by a DCI format 1_1, the REs corresponding to configured resources in *rateMatchPatternGroup1* or *rateMatchPatternGroup2* are not available for the PDSCHs with SPS if a corresponding bit of the Rate matching indicator field of the DCI format 1_1 activating the PDSCHs with SPS is equal to 1.

For a bitmap pair included in one or two groups of resource sets, the dynamic indication of availability for PDSCH applies to a set of slot(s) where the *rateMatchPatternToAddModList* is present among the slots of scheduled PDSCH.

If a UE monitors PDCCH candidates of aggregation levels 8 and 16 with the same starting CCE index in non-interleaved CORESET spanning one OFDM symbol and if a detected PDCCH scheduling the PDSCH has aggregation level 8, the resources corresponding to the aggregation level 16 PDCCH candidate are not available for the PDSCH.

If a PDSCH scheduled by a PDCCH would overlap with resources in the CORESET containing the PDCCH, the resources corresponding to a union of the detected PDCCH that scheduled the PDSCH and associated PDCCH DM-RS are not available for the PDSCH. When *precoderGranularity* configured in a CORESET where the PDCCH was detected is equal to *allContiguousRBs*, the associated PDCCH DM-RS are DM-RS in all REGs of the CORESET. Otherwise, the associated DM-RS are the DM-RS in REGs of the PDCCH.

5.1.4.2 PDSCH resource mapping with RE level granularity

A UE may be configured with any of the following higher layer parameters:

- REs indicated by the *RateMatchingPatternLTE-CRS* in *lte-CRS-ToMatchAround* in *ServingCellConfig* or *ServingCellConfigCommon* configuring common RS, in 15 kHz subcarrier spacing applicable only to 15 kHz subcarrier spacing PDSCH, of one LTE carrier in a serving cell are declared as not available for PDSCH. The *RateMatchingPatternLTE-CRS* configuration contains *v-Shift* consisting of LTE-CRS-*vshift(s)*, *nrofCRS-Ports* consisting of LTE-CRS antenna ports 1, 2 or 4 ports, *carrierFreqDL* representing the offset in units of 15 kHz subcarriers from (reference) point A to the LTE carrier centre subcarrier location, *carrierBandwidthDL* representing the LTE carrier bandwidth, and may also configure *mbsfn-SubframeConfigList* representing MBSFN subframe configuration. A UE determines the CRS position within the slot according to Clause 6.10.1.2 in [15, TS 36.211], where slot corresponds to LTE subframe.
- within a BWP, the UE can be configured with one or more ZP CSI-RS resource set configuration(s) for aperiodic, semi-persistent and periodic time-domain behaviours (higher layer parameters *aperiodic-ZP-CSI-RS-ResourceSetsToAddModList*, *sp-ZP-CSI-RS-ResourceSetsToAddModList* and *p-ZP-CSI-RS-ResourceSet* respectively comprised in *PDSCH-Config*), with each ZP-CSI-RS resource set consisting of at most 16 ZP CSI-RS resources (higher layer parameter *ZP-CSI-RS-Resource*) in numerology of the BWP. The REs indicated by *p-ZP-CSI-RS-ResourceSet* are declared as not available for PDSCH. The REs indicated by *sp-ZP-CSI-RS-ResourceSetsToAddModList* and *aperiodic-ZP-CSI-RS-ResourceSetsToAddModList* are declared as not available for PDSCH when their triggering and activation are applied, respectively. The following parameters are configured via higher layer signaling for each ZP CSI-RS resource configuration:
 - *zp-CSI-RS-ResourceId* in *ZP-CSI-RS-Resource* determines ZP CSI-RS resource configuration identity.
 - *nrofPorts* defines the number of CSI-RS ports, where the allowable values are given in Clause 7.4.1.5 of [4, TS 38.211].
 - *cdm-Type* defines CDM values and pattern, where the allowable values are given in Clause 7.4.1.5 of [4, TS 38.211].
 - *resourceMapping* given by *ZP-CSI-RS-Resource* defines the OFDM symbol and subcarrier occupancy of the ZP-CSI-RS resource within a slot that are given in Clause 7.4.1.5 of [4, TS 38.211].

- *periodicityAndOffset* in *ZP-CSI-RS-Resource* defines the ZP-CSI-RS periodicity and slot offset for periodic/semi-persistent ZP-CSI-RS.

The UE may be configured with a DCI field for triggering the aperiodic ZP-CSI-RS. A list of *ZP-CSI-RS-ResourceSet(s)*, provided by higher layer parameter *aperiodic-ZP-CSI-RS-ResourceSetsToAddModList* in *PDSCH-Config*, is configured for aperiodic triggering. The maximum number of aperiodic *ZP-CSI-RS-ResourceSet(s)* configured per BWP is 3. The bit-length of DCI field *ZP-CSI-RS-trigger* depends on the number of aperiodic *ZP-CSI-RS-ResourceSet(s)* configured (up to 2 bits). Each non-zero codepoint of *ZP-CSI-RS-trigger* in DCI format 1_1 triggers one aperiodic *ZP-CSI-RS-ResourceSet* in the list *aperiodic-ZP-CSI-RS-ResourceSetsToAddModList* by indicating the aperiodic ZP CSI-RS resource set ID. The DCI codepoint '01' triggers the resource set with *ZP-CSI-RS-ResourceSetIds* = 1, the DCI codepoint '10' triggers the resource set with *ZP-CSI-RS-ResourceSetIds* = 2, and the DCI codepoint '11' triggers the resource set with *ZP-CSI-RS-ResourceSetIds* = 3. Codepoint '00' is reserved for not triggering aperiodic ZP CSI-RS. When receiving PDSCH scheduled by DCI format 1_0 or PDSCHs with SPS activated by DCI format 1_0, the REs corresponding to configured resources in *aperiodic-ZP-CSI-RS-ResourceSetsToAddModList* are available for PDSCH.

When the UE is configured with multi-slot and single-slot PDSCH scheduling, the triggered aperiodic ZP CSI-RS is applied to all the slot(s) of the PDSCH scheduled or the PDSCHs with SPS activated by the PDCCH containing the trigger.

For a UE configured with a list of *ZP-CSI-RS-ResourceSet(s)* provided by higher layer parameter *sp-ZP-CSI-RS-ResourceSetsToAddModList*:

- when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the activation command, as described in clause 6.1.3.19 of [10, TS 38.321], for ZP CSI-RS resource(s), the corresponding action in [10, TS 38.321] and the UE assumption on the PDSCH RE mapping corresponding to the activated ZP CSI-RS resource(s) shall be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH.
- when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the deactivation command, as described in clause 6.1.3.19 of [10, TS 38.321], for activated ZP CSI-RS resource(s), the corresponding action in [10, TS 38.321] and the UE assumption on cessation of the PDSCH RE mapping corresponding to the de-activated ZP CSI-RS resource(s) shall be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH.

5.1.5 Antenna ports quasi co-location

The UE can be configured with a list of up to M *TCI-State* configurations within the higher layer parameter *PDSCH-Config* to decode PDSCH according to a detected PDCCH with DCI intended for the UE and the given serving cell, where M depends on the UE capability *maxNumberConfiguredTCIstatesPerCC*. Each *TCI-State* contains parameters for configuring a quasi co-location relationship between one or two downlink reference signals and the DM-RS ports of the PDSCH, the DM-RS port of PDCCH or the CSI-RS port(s) of a CSI-RS resource. The quasi co-location relationship is configured by the higher layer parameter *qcl-Type1* for the first DL RS, and *qcl-Type2* for the second DL RS (if configured). For the case of two DL RSs, the QCL types shall not be the same, regardless of whether the references are to the same DL RS or different DL RSs. The quasi co-location types corresponding to each DL RS are given by the higher layer parameter *qcl-Type* in *QCL-Info* and may take one of the following values:

- 'QCL-TypeA': {Doppler shift, Doppler spread, average delay, delay spread}
- 'QCL-TypeB': {Doppler shift, Doppler spread}
- 'QCL-TypeC': {Doppler shift, average delay}
- 'QCL-TypeD': {Spatial Rx parameter}

The UE receives an activation command, as described in clause 6.1.3.14 of [10, TS 38.321], used to map up to 8 TCI states to the codepoints of the DCI field '*Transmission Configuration Indication*'. When the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the activation command, the indicated mapping between TCI states and codepoints of the DCI field '*Transmission Configuration Indication*' should be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH. If *tci-PresentInDCI* is set to "enabled" for the CORESET scheduling the PDSCH, and the time offset between the reception of the DL DCI and the corresponding PDSCH is equal to or greater than *timeDurationForQCL* if applicable, after a UE receives an initial higher layer configuration of TCI states and before reception of the activation

command, the UE may assume that the DM-RS ports of PDSCH of a serving cell are quasi co-located with the SS/PBCH block determined in the initial access procedure with respect to 'QCL-TypeA', and when applicable, also with respect to 'QCL-TypeD'.

If a UE is configured with the higher layer parameter *tcj-PresentInDCI* that is set as 'enabled' for the CORESET scheduling the PDSCH, the UE assumes that the TCI field is present in the DCI format 1_1 of the PDCCH transmitted on the CORESET. If *tcj-PresentInDCI* is not configured for the CORESET scheduling the PDSCH or the PDSCH is scheduled by a DCI format 1_0, and the time offset between the reception of the DL DCI and the corresponding PDSCH is equal to or greater than a threshold *timeDurationForQCL* if applicable, where the threshold is based on reported UE capability [13, TS 38.306], for determining PDSCH antenna port quasi co-location, the UE assumes that the TCI state or the QCL assumption for the PDSCH is identical to the TCI state or QCL assumption whichever is applied for the CORESET used for the PDCCH transmission.

If the *tcj-PresentInDCI* is set as 'enabled', the TCI field in DCI in the scheduling component carrier points to the activated TCI states in the scheduled component carrier or DL BWP and when the PDSCH is scheduled by DCI format 1_1, the UE shall use the *TCI-State* according to the value of the 'Transmission Configuration Indication' field in the detected PDCCH with DCI for determining PDSCH antenna port quasi co-location. The UE may assume that the DM-RS ports of PDSCH of a serving cell are quasi co-located with the RS(s) in the TCI state with respect to the QCL type parameter(s) given by the indicated TCI state if the time offset between the reception of the DL DCI and the corresponding PDSCH is equal to or greater than a threshold *timeDurationForQCL*, where the threshold is based on reported UE capability [13, TS 38.306]. When the UE is configured with a single slot PDSCH, the indicated TCI state should be based on the activated TCI states in the slot with the scheduled PDSCH. When the UE is configured with a multi-slot PDSCH, the indicated TCI state should be based on the activated TCI states in the first slot with the scheduled PDSCH, and UE shall expect the activated TCI states are the same across the slots with the scheduled PDSCH. When the UE is configured with CORESET associated with a search space set for cross-carrier scheduling, the UE expects *tcj-PresentInDCI* is set as 'enabled' for the CORESET, and if one or more of the TCI states configured for the serving cell scheduled by the search space set contains 'QCL-TypeD', the UE expects the time offset between the reception of the detected PDCCH in the search space set and the corresponding PDSCH is larger than or equal to the threshold *timeDurationForQCL*.

For both the cases when *tcj-PresentInDCI* is set to 'enabled' and *tcj-PresentInDCI* is not configured in RRC connected mode, if the offset between the reception of the DL DCI and the corresponding PDSCH is less than the threshold *timeDurationForQCL*, the UE may assume that the DM-RS ports of PDSCH of a serving cell are quasi co-located with the RS(s) with respect to the QCL parameter(s) used for PDCCH quasi co-location indication of the CORESET associated with a monitored search space with the lowest *controlResourceSetId* in the latest slot in which one or more CORESETs within the active BWP of the serving cell are monitored by the UE. In this case, if the 'QCL-TypeD' of the PDSCH DM-RS is different from that of the PDCCH DM-RS with which they overlap in at least one symbol, the UE is expected to prioritize the reception of PDCCH associated with that CORESET. This also applies to the intra-band CA case (when PDSCH and the CORESET are in different component carriers). If none of configured TCI states for the serving cell of scheduled PDSCH contains 'QCL-TypeD', the UE shall obtain the other QCL assumptions from the indicated TCI states for its scheduled PDSCH irrespective of the time offset between the reception of the DL DCI and the corresponding PDSCH.

For a periodic CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info*, the UE shall expect that a TCI-State indicates one of the following quasi co-location type(s):

- 'QCL-TypeC' with an SS/PBCH block and, when applicable, 'QCL-TypeD' with the same SS/PBCH block, or
- 'QCL-TypeC' with an SS/PBCH block and, when applicable, 'QCL-TypeD' with a CSI-RS resource in an *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, or

For an aperiodic CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info*, the UE shall expect that a *TCI-State* indicates 'QCL-TypeA' with a periodic CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with the same periodic CSI-RS resource.

For a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured without higher layer parameter *trs-Info* and without the higher layer parameter *repetition*, the UE shall expect that a *TCI-State* indicates one of the following quasi co-location type(s):

- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource, or

- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with an SS/PBCH block , or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, or
- 'QCL-TypeB' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* when 'QCL-TypeD' is not applicable.

For a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, the UE shall expect that a *TCI-State* indicates one of the following quasi co-location type(s):

- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource, or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, or
- 'QCL-TypeC' with an SS/PBCH block and, when applicable, 'QCL-TypeD' with the same SS/PBCH block.

For the DM-RS of PDCCH, the UE shall expect that a *TCI-State* indicates one of the following quasi co-location type(s):

- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource, or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with a CSI-RS resource in an *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured without higher layer parameter *trs-Info* and without higher layer parameter *repetition* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource.

For the DM-RS of PDSCH, the UE shall expect that a *TCI-State* indicates one of the following quasi co-location type(s):

- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource, or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info* and, when applicable, 'QCL-TypeD' with a CSI-RS resource in an *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *repetition*, or
- 'QCL-TypeA' with a CSI-RS resource in a *NZP-CSI-RS-ResourceSet* configured without higher layer parameter *trs-Info* and without higher layer parameter *repetition* and, when applicable, 'QCL-TypeD' with the same CSI-RS resource.

5.1.6 UE procedure for receiving downlink reference signals

5.1.6.1 CSI-RS reception procedure

The CSI-RS defined in Clause 7.4.1.5 of [4, TS 38.211], may be used for time/frequency tracking, CSI computation, L1-RSRP computation and mobility.

For a CSI-RS resource associated with a *NZP-CSI-RS-ResourceSet* with the higher layer parameter *repetition* set to 'on', the UE shall not expect to be configured with CSI-RS over the symbols during which the UE is also configured to monitor the CORESET, while for other *NZP-CSI-RS-ResourceSet* configurations, if the UE is configured with a CSI-RS resource and a search space set associated with a CORESET in the same OFDM symbol(s), the UE may assume that the CSI-RS and a PDCCH DM-RS transmitted in all the search space sets associated with CORESET are quasi co-located with 'QCL-TypeD', if 'QCL-TypeD' is applicable. This also applies to the case when CSI-RS and the CORESET are in different intra-band component carriers, if 'QCL-TypeD' is applicable. Furthermore, the UE shall not expect to be

configured with the CSI-RS in PRBs that overlap those of the CORESET in the OFDM symbols occupied by the search space set(s).

The UE is not expected to receive CSI-RS and *SIB1* message in the overlapping PRBs in the OFDM symbols where *SIB1* is transmitted.

If the UE is configured with DRX, the most recent CSI measurement occasion occurs in DRX active time for CSI to be reported.

5.1.6.1.1 CSI-RS for tracking

A UE in RRC connected mode is expected to receive the higher layer UE specific configuration of a *NZP-CSI-RS-ResourceSet* configured with higher layer parameter *trs-Info*.

For a *NZP-CSI-RS-ResourceSet* configured with the higher layer parameter *trs-Info*, the UE shall assume the antenna port with the same port index of the configured NZP CSI-RS resources in the *NZP-CSI-RS-ResourceSet* is the same. For frequency range 1, the UE may be configured with one or more NZP CSI-RS set(s), where a *NZP-CSI-RS-ResourceSet* consists of four periodic NZP CSI-RS resources in two consecutive slots with two periodic NZP CSI-RS resources in each slot. For frequency range 2 the UE may be configured with one or more NZP CSI-RS set(s), where a *NZP-CSI-RS-ResourceSet* consists of two periodic CSI-RS resources in one slot or with a *NZP-CSI-RS-ResourceSet* of four periodic NZP CSI-RS resources in two consecutive slots with two periodic NZP CSI-RS resources in each slot.

A UE configured with *NZP-CSI-RS-ResourceSet(s)* configured with higher layer parameter *trs-Info* may have the CSI-RS resources configured as:

- Periodic, with the CSI-RS resources in the *NZP-CSI-RS-ResourceSet* configured with same periodicity, bandwidth and subcarrier location
- Periodic CSI-RS resource in one set and aperiodic CSI-RS resources in a second set, with the aperiodic CSI-RS and periodic CSI-RS resource having the same bandwidth (with same RB location) and the aperiodic CSI-RS being 'QCL-Type-A' and 'QCL-TypeD', where applicable, with the periodic CSI-RS resources. For frequency range 2, the UE does not expect that the scheduling offset between the last symbol of the PDCCH carrying the triggering DCI and the first symbol of the aperiodic CSI-RS resources is smaller than the UE reported *beamSwitchTiming*. The UE shall expect that the periodic CSI-RS resource set and aperiodic CSI-RS resource set are configured with the same number of CSI-RS resources and with the same number of CSI-RS resources in a slot. For the aperiodic CSI-RS resource set if triggered, and if the associated periodic CSI-RS resource set is configured with four periodic CSI-RS resources with two consecutive slots with two periodic CSI-RS resources in each slot, the higher layer parameter *aperiodicTriggeringOffset* indicates the triggering offset for the first slot for the first two CSI-RS resources in the set.

A UE does not expect to be configured with a *CSI-ReportConfig* that is linked to a *CSI-ResourceConfig* containing an *NZP-CSI-RS-ResourceSet* configured with *trs-Info* and with the *CSI-ReportConfig* configured with the higher layer parameter *timeRestrictionForChannelMeasurements* set to 'configured'.

A UE does not expect to be configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to other than 'none' for aperiodic NZP CSI-RS resource set configured with *trs-Info*.

A UE does not expect to be configured with a *CSI-ReportConfig* for periodic NZP CSI-RS resource set configured with *trs-Info*.

A UE does not expect to be configured with a *NZP-CSI-RS-ResourceSet* configured both with *trs-Info* and *repetition*.

Each CSI-RS resource, defined in Clause 7.4.1.5.3 of [4, TS 38.211], is configured by the higher layer parameter *NZP-CSI-RS-Resource* with the following restrictions:

- the time-domain locations of the two CSI-RS resources in a slot, or of the four CSI-RS resources in two consecutive slots (which are the same across two consecutive slots), as defined by higher layer parameter *CSI-RS-resourceMapping*, is given by one of
 - $l \in \{4,8\}$, $l \in \{5,9\}$, or $l \in \{6,10\}$ for frequency range 1 and frequency range 2,
 - $l \in \{0,4\}$, $l \in \{1,5\}$, $l \in \{2,6\}$, $l \in \{3,7\}$, $l \in \{7,11\}$, $l \in \{8,12\}$ or $l \in \{9,13\}$ for frequency range 2.

- a single port CSI-RS resource with density $\rho = 3$ given by Table 7.4.1.5.3-1 from [4, TS 38.211] and higher layer parameter *density* configured by *CSI-RS-ResourceMapping*.
- the bandwidth of the CSI-RS resource, as given by the higher layer parameter *freqBand* configured by *CSI-RS-ResourceMapping*, is the minimum of 52 and $N_{\text{BWP},i}^{\text{size}}$ resource blocks, or is equal to $N_{\text{BWP},i}^{\text{size}}$ resource blocks
- the UE is not expected to be configured with the periodicity of $2^\mu \times 10$ slots if the bandwidth of CSI-RS resource is larger than 52 resource blocks.
- the periodicity and slot offset for periodic NZP CSI-RS resources, as given by the higher layer parameter *periodicityAndOffset* configured by *NZP-CSI-RS-Resource*, is one of $2^\mu X_p$ slots where $X_p = 10, 20, 40, \text{ or } 80$ and where μ is defined in Clause 4.3 of [4, TS 38.211].
- same *powerControlOffset* and *powerControlOffsetSS* given by *NZP-CSI-RS-Resource* value across all resources.

5.1.6.1.2 CSI-RS for L1-RSRP computation

If a UE is configured with a *NZP-CSI-RS-ResourceSet* configured with the higher layer parameter *repetition* set to 'on', the UE may assume that the CSI-RS resources, described in Clause 5.2.2.3.1, within the *NZP-CSI-RS-ResourceSet* are transmitted with the same downlink spatial domain transmission filter, where the CSI-RS resources in the *NZP-CSI-RS-ResourceSet* are transmitted in different OFDM symbols. If *repetition* is set to 'off', the UE shall not assume that the CSI-RS resources within the *NZP-CSI-RS-ResourceSet* are transmitted with the same downlink spatial domain transmission filter.

If the UE is configured with a *CSI-ReportConfig* with *reportQuantity* set to "cri-RSRP", or "none" and if the *CSI-ResourceConfig* for channel measurement (higher layer parameter *resourcesForChannelMeasurement*) contains a *NZP-CSI-RS-ResourceSet* that is configured with the higher layer parameter *repetition* and without the higher layer parameter *trs-Info*, the UE can only be configured with the same number (1 or 2) of ports with the higher layer parameter *nrofPorts* for all CSI-RS resources within the set. If the UE is configured with the CSI-RS resource in the same OFDM symbol(s) as an SS/PBCH block, the UE may assume that the CSI-RS and the SS/PBCH block are quasi co-located with 'QCL-TypeD' if 'QCL-TypeD' is applicable. Furthermore, the UE shall not expect to be configured with the CSI-RS in PRBs that overlap with those of the SS/PBCH block, and the UE shall expect that the same subcarrier spacing is used for both the CSI-RS and the SS/PBCH block.

5.1.6.1.3 CSI-RS for mobility

If a UE is configured with the higher layer parameter *CSI-RS-Resource-Mobility* and the higher layer parameter *associatedSSB* is not configured, the UE shall perform measurements based on *CSI-RS-Resource-Mobility* and the UE may base the timing of the CSI-RS resource on the timing of the serving cell.

If a UE is configured with the higher layer parameters *CSI-RS-Resource-Mobility* and *associatedSSB*, the UE may base the timing of the CSI-RS resource on the timing of the cell given by the *cellId* of the CSI-RS resource configuration. Additionally, for a given CSI-RS resource, if the associated SS/PBCH block is configured but not detected by the UE, the UE is not required to monitor the corresponding CSI-RS resource. The higher layer parameter *isQuasiColocated* indicates whether the associated SS/PBCH block given by the *associatedSSB* and the CSI-RS resource(s) are quasi co-located with respect to ['QCL-TypeD'].

If a UE is configured with the higher layer parameter *CSI-RS-Resource-Mobility* and with periodicity greater than 10 ms in paired spectrum, the UE may assume the absolute value of the time difference between radio frame i between any two cells, listed in the configuration with the higher layer parameter *CSI-RS-CellMobility* and with same *refFreqCSI-RS*, is less than $153600 T_s$.

If the UE is configured with DRX, the UE is not required to perform measurement of CSI-RS resources other than during the active time for measurements based on *CSI-RS-Resource-Mobility*.

If the UE is configured with DRX and DRX cycle in use is larger than 80 ms, the UE may not expect CSI-RS resources are available other than during the active time for measurements based on *CSI-RS-Resource-Mobility*. Otherwise, the UE may assume CSI-RS are available for measurements based on *CSI-RS-Resource-Mobility*.

A UE configured with the higher layer parameters *CSI-RS-Resource-Mobility* may expect to be configured

- with no more than 96 CSI-RS resources per higher layer parameter *MeasObjectNR* when all CSI-RS resources configured by the same higher layer parameter *MeasObjectNR* have been configured with *associatedSSB*, or,
- with no more than 64 CSI-RS resources per higher layer parameter *MeasObjectNR* when all CSI-RS resources have been configured without *associatedSSB* or when only some of the CSI-RS resources have been configured with *associatedSSB* by the same higher layer parameter *MeasObjectNR*
 - For frequency range 1 the *associatedSSB* is optionally present for each CSI-RS resource
 - For frequency range 2 the *associatedSSB* is either present for all configured CSI-RS resources or not present for any configured CSI-RS resource per higher layer parameter *MeasObjectNR*.

For any CSI-RS resource configuration, the UE shall assume that the value for parameter *cdm-Type* is 'noCDM', and there is only one antenna port.

5.1.6.2 DM-RS reception procedure

When receiving PDSCH scheduled by DCI format 1_0 or receiving PDSCH before dedicated higher layer configuration of any of the parameters *dmrs-AdditionalPosition*, *maxLength* and *dmrs-Type*, the UE shall assume that the PDSCH is not present in any symbol carrying DM-RS except for PDSCH with allocation duration of 2 symbols with PDSCH mapping type B (described in clause 7.4.1.1.2 of [4, TS 38.211]), and a single symbol front-loaded DM-RS of configuration type 1 on DM-RS port 1000 is transmitted, and that all the remaining orthogonal antenna ports are not associated with transmission of PDSCH to another UE and in addition

- For PDSCH with mapping type A, the UE shall assume *dmrs-AdditionalPosition*='pos2' and up to two additional single-symbol DM-RS present in a slot according to the PDSCH duration indicated in the DCI as defined in Clause 7.4.1.1 of [4, TS 38.211], and
- For PDSCH with allocation duration of 7 symbols for normal CP or 6 symbols for extended CP with mapping type B, the UE shall assume one additional single-symbol DM-RS present in the 5th or 6th symbol when the front-loaded DM-RS symbol is in the 1st or 2nd symbol respectively of the PDSCH allocation duration, otherwise the UE shall assume that the additional DM-RS symbol is not present, and
- For PDSCH with allocation duration of 4 symbols with mapping type B, the UE shall assume that no additional DM-RS are present, and
- For PDSCH with allocation duration of 2 symbols with mapping type B, the UE shall assume that no additional DM-RS are present, and the UE shall assume that the PDSCH is present in the symbol carrying DM-RS.

When receiving PDSCH scheduled by DCI format 1_1 by PDCCH with CRC scrambled by C-RNTI, MCS-C-RNTI, or CS-RNTI,

- the UE may be configured with the higher layer parameter *dmrs-Type*, and the configured DM-RS configuration type is used for receiving PDSCH in as defined in Clause 7.4.1.1 of [4, TS 38.211].
- the UE may be configured with the maximum number of front-loaded DM-RS symbols for PDSCH by higher layer parameter *maxLength* given by *DMRS-DownlinkConfig*.
 - if *maxLength* is set to 'len1', single-symbol DM-RS can be scheduled for the UE by DCI, and the UE can be configured with a number of additional DM-RS for PDSCH by higher layer parameter *dmrs-AdditionalPosition*, which can be set to 'pos0', 'pos1', 'pos2' or 'pos3'.
 - if *maxLength* is set to 'len2', both single-symbol DM-RS and double symbol DM-RS can be scheduled for the UE by DCI, and the UE can be configured with a number of additional DM-RS for PDSCH by higher layer parameter *dmrs-AdditionalPosition*, which can be set to 'pos0' or 'pos1'.
 - and the UE shall assume to receive additional DM-RS as specified in Table 7.4.1.1.2-3 and Table 7.4.1.1.2-4 as described in Clause 7.4.1.1.2 of [4, TS 38.211].

For the UE-specific reference signals generation as defined in Clause 7.4.1.1 of [4, TS 38.211], a UE can be configured by higher layers with one or two scrambling identity(s), $n_{ID}^{DMRS,i}$ $i = 0,1$ which are the same for both PDSCH mapping Type A and Type B.

A UE may be scheduled with a number of DM-RS ports by the antenna port index in DCI format 1_1 as described in Clause 7.3.1.2 of [5, TS 38.212].

For DM-RS configuration type 1,

- if a UE is scheduled with one codeword and assigned with the antenna port mapping with indices of {2, 9, 10, 11 or 30} in Table 7.3.1.2.2-1 and Table 7.3.1.2.2-2 of Clause 7.3.1.2 of [5, TS 38.212], or
- if a UE is scheduled with two codewords,

the UE may assume that all the remaining orthogonal antenna ports are not associated with transmission of PDSCH to another UE.

For DM-RS configuration type 2,

- if a UE is scheduled with one codeword and assigned with the antenna port mapping with indices of {2, 10 or 23} in Table 7.3.1.2.2-3 and Table 7.3.1.2.2-4 of Clause 7.3.1.2 of [5, TS38.212], or
- if a UE is scheduled with two codewords,

the UE may assume that all the remaining orthogonal antenna ports are not associated with transmission of PDSCH to another UE.

If a UE receiving PDSCH is configured with the higher layer parameter *phaseTrackingRS* in *DMRS-DownlinkConfig*, the UE may assume that the following configurations are not occurring simultaneously for the received PDSCH:

- any DM-RS ports among 1004-1007 or 1006-1011 for DM-RS configurations type 1 and type 2, respectively are scheduled for the UE and the other UE(s) sharing the DM-RS REs on the same CDM group(s), and
- PT-RS is transmitted to the UE.

The UE is not expected to simultaneously be configured with the maximum number of front-loaded DM-RS symbols for PDSCH by higher layer parameter *maxLength* being set equal to 'len2' and more than one additional DM-RS symbol as given by the higher layer parameter *dmrs-AdditionalPosition*.

The UE is not expected to assume co-scheduled UE(s) with different DM-RS configuration with respect to the actual number of front-loaded DM-RS symbol(s), the actual number of additional DM-RS, the DM-RS symbol location, and DM-RS configuration type as described in Clause 7.4.1.1 of [4, TS 38.211].

The UE does not expect the precoding of the potential co-scheduled UE(s) in other DM-RS ports of the same CDM group to be different in the PRG-level grid configured to this UE with PRG =2 or 4.

The UE does not expect the resource allocation of the potential co-scheduled UE(s) in other DM-RS ports of the same CDM group to be misaligned in the PRG-level grid to this UE with PRG=2 or 4.

When receiving PDSCH scheduled by DCI format 1_1, the UE shall assume that the CDM groups indicated in the configured index from Tables 7.3.1.2.2-1, 7.3.1.2.2-2, 7.3.1.2.2-3, 7.3.1.2.2-4 of [5, TS. 38.212] contain potential co-scheduled downlink DM-RS and are not used for data transmission, where "1", "2" and "3" for the number of DM-RS CDM group(s) in Tables 7.3.1.2.2-1, 7.3.1.2.2-2, 7.3.1.2.2-3, 7.3.1.2.2-4 of [5, TS. 38.212] correspond to CDM group 0, {0,1}, {0,1,2}, respectively.

When receiving PDSCH scheduled by DCI format 1_0, the UE shall assume the number of DM-RS CDM groups without data is 1 which corresponds to CDM group 0 for the case of PDSCH with allocation duration of 2 symbols, and the UE shall assume that the number of DM-RS CDM groups without data is 2 which corresponds to CDM group {0,1} for all other cases.

The UE is not expected to receive PDSCH scheduling DCI which indicates CDM group(s) with potential DM-RS ports which overlap with any configured CSI-RS resource(s) for that UE.

If the UE receives the DM-RS for PDSCH and an SS/PBCH block in the same OFDM symbol(s), then the UE may assume that the DM-RS and SS/PBCH block are quasi co-located with 'QCL-TypeD', if 'QCL-TypeD' is applicable. Furthermore, the UE shall not expect to receive DM-RS in resource elements that overlap with those of the SS/PBCH block, and the UE can expect that the same or different subcarrier spacing is configured for the DM-RS and SS/PBCH block in a CC except for the case of 240 kHz where only different subcarrier spacing is supported.

5.1.6.3 PT-RS reception procedure

A UE shall report the preferred MCS and bandwidth thresholds based on the UE capability at a given carrier frequency, for each subcarrier spacing applicable to data channel at this carrier frequency, assuming the MCS table with the maximum Modulation Order as it reported to support.

If a UE is configured with the higher layer parameter *phaseTrackingRS* in *DMRS-DownlinkConfig*,

- the higher layer parameters *timeDensity* and *frequencyDensity* in *PTRS-DownlinkConfig* indicate the threshold values $ptrs-MCS_i$, $i=1,2,3$ and $N_{RB,i}$, $i=0,1$, as shown in Table 5.1.6.3-1 and Table 5.1.6.3-2, respectively.
- if either or both of the additional higher layer parameters *timeDensity* and *frequencyDensity* are configured, and the RNTI equals MCS-C-RNTI, C-RNTI or CS-RNTI, the UE shall assume the PT-RS antenna port' presence and pattern is a function of the corresponding scheduled MCS of the corresponding codeword and scheduled bandwidth in corresponding bandwidth part as shown in Table 5.1.6.3-1 and Table 5.1.6.3-2,
 - if the higher layer parameter *timeDensity* given by *PTRS-DownlinkConfig* is not configured, the UE shall assume $L_{PT-RS} = 1$.
 - if the higher layer parameter *frequencyDensity* given by *PTRS-DownlinkConfig* is not configured, the UE shall assume $K_{PT-RS} = 2$.
- otherwise, if neither of the additional higher layer parameters *timeDensity* and *frequencyDensity* are configured and the RNTI equals MCS-C-RNTI, C-RNTI or CS-RNTI, the UE shall assume the PT-RS is present with $L_{PT-RS} = 1$, $K_{PT-RS} = 2$, and the UE shall assume PT-RS is not present when
 - the scheduled MCS from Table 5.1.3.1-1 is smaller than 10, or
 - the scheduled MCS from Table 5.1.3.1-2 is smaller than 5, or
 - the scheduled MCS from Table 5.1.3.1-3 is smaller than 15, or
 - the number of scheduled RBs is smaller than 3, or
- otherwise, if the RNTI equals RA-RNTI, SI-RNTI, or P-RNTI, the UE shall assume PT-RS is not present

Table 5.1.6.3-1: Time density of PT-RS as a function of scheduled MCS

Scheduled MCS	Time density (L_{PT-RS})
$l_{MCS} < ptrs-MCS_1$	PT-RS is not present
$ptrs-MCS_1 \leq l_{MCS} < ptrs-MCS_2$	4
$ptrs-MCS_2 \leq l_{MCS} < ptrs-MCS_3$	2
$ptrs-MCS_3 \leq l_{MCS} < ptrs-MCS_4$	1

Table 5.1.6.3-2: Frequency density of PT-RS as a function of scheduled bandwidth

Scheduled bandwidth	Frequency density (K_{PT-RS})
$N_{RB} < N_{RB0}$	PT-RS is not present
$N_{RB0} \leq N_{RB} < N_{RB1}$	2
$N_{RB1} \leq N_{RB}$	4

If a UE is not configured with the higher layer parameter *phaseTrackingRS* in *DMRS-DownlinkConfig*, the UE assumes PT-RS is not present.

The higher layer parameter *PTRS-DownlinkConfig* provides the parameters $ptrs-MCS_i$, $i=1,2,3$ and with values in range 0-29 when MCS Table 5.1.3.1-1 or MCS Table 5.1.3.1-3 is used and 0-28 when MCS Table 5.1.3.1-2 is used, respectively. $ptrs-MCS_4$ is not explicitly configured by higher layers but assumed 29 when MCS Table 5.1.3.1-1 or MCS Table 5.1.3.1-3 is used and 28 when MCS Table 5.1.3.1-2 is used, respectively. The higher layer parameter *frequencyDensity* in *PTRS-DownlinkConfig* provides the parameters $N_{RB,i}$ $i=0,1$ with values in range 1-276.

If the higher layer parameter *PTRS-DownlinkConfig* indicates that the time density thresholds $ptrs-MCS_i = ptrs-MCS_{i+1}$, then the time density L_{PT-RS} of the associated row where both these thresholds appear in Table 5.1.6.3-1 is disabled. If the higher layer parameter *PTRS-DownlinkConfig* indicates that the frequency density thresholds $N_{RBi} = N_{RBi+1}$, then the frequency density K_{PT-RS} of the associated row where both these thresholds appear in Table 5.1.6.3-2 is disabled.

If either or both of the parameters PT-RS time density (L_{PT-RS}) and PT-RS frequency density (K_{PT-RS}), shown in Table 5.1.6.3-1 and Table 5.1.6.3-2, indicates that 'PT-RS not present', the UE shall assume that PT-RS is not present.

When the UE is receiving a PDSCH with allocation duration of 2 symbols as defined in Clause 7.4.1.1.2 of [4, TS 38.211] and if L_{PT-RS} is set to 2 or 4, the UE shall assume PT-RS is not transmitted.

When the UE is receiving a PDSCH with allocation duration of 4 symbols and if L_{PT-RS} is set to 4, the UE shall assume PT-RS is not transmitted.

When a UE is receiving PDSCH for retransmission, if the UE is scheduled with an MCS index greater than V, where V=28 for MCS Table 5.1.3.1-1 and Table 5.1.3.1-3, and V=27 for MCS Table 5.1.3.1-2 respectively, the MCS for the PT-RS time-density determination is obtained from the DCI received for the same transport block in the initial transmission, which is smaller than or equal to V.

The DL DM-RS port(s) associated with a PT-RS port are assumed to be quasi co-located with respect to {'QCL-TypeA' and 'QCL-TypeD'}. If a UE is scheduled with one codeword, the PT-RS antenna port is associated with the lowest indexed DM-RS antenna port among the DM-RS antenna ports assigned for the PDSCH.

If a UE is scheduled with two codewords, the PT-RS antenna port is associated with the lowest indexed DM-RS antenna port among the DM-RS antenna ports assigned for the codeword with the higher MCS. If the MCS indices of the two codewords are the same, the PT-RS antenna port is associated with the lowest indexed DM-RS antenna port assigned for codeword 0.

5.1.7 Code block group based PDSCH transmission

5.1.7.1 UE procedure for grouping of code blocks to code block groups

If a UE is configured to receive code block group (CBG) based transmissions by receiving the higher layer parameter *codeBlockGroupTransmission* for PDSCH, the UE shall determine the number of CBGs for a transport block reception as

$$M = \min(N, C),$$

where N is the maximum number of CBGs per transport block as configured by *maxCodeBlockGroupsPerTransportBlock* for PDSCH, and C is the number of code blocks in the transport block according to the procedure defined in Clause 7.2.3 of [5, TS 38.212].

Define $M_1 = \text{mod}(C, M)$, $K_1 = \left\lceil \frac{C}{M} \right\rceil$, and $K_2 = \left\lfloor \frac{C}{M} \right\rfloor$.

If $M_1 > 0$, CBG m , $m = 0, 1, \dots, M_1 - 1$, consists of code blocks with indices $m \cdot K_1 + k$, $k = 0, 1, \dots, K_1 - 1$. CBG m , $m = M_1, M_1 + 1, \dots, M - 1$, consists of code blocks with indices $M_1 \cdot K_1 + (m - M_1) \cdot K_2 + k$, $k = 0, 1, \dots, K_2 - 1$.

5.1.7.2 UE procedure for receiving code block group based transmissions

If a UE is configured to receive code block group based transmissions by receiving the higher layer parameter *codeBlockGroupTransmission* for PDSCH,

- The CBG transmission information (CBGTI) field of DCI format 1_1 is of length $N_{TB} \cdot N$ bits, where N_{TB} is the value of the higher layer parameter *maxNrofCodeWordsScheduledByDCI*. If $N_{TB} = 2$ the CBGTI field bits are mapped such that the first set of N bits starting from the MSB corresponds to the first TB while the second set of N bits corresponds to a second TB, if scheduled. The first M bits of each set of N bits in the CBGTI field have an in-order one-to-one mapping with the M CBGs of the TB, with the MSB mapped to CBG#0.
- For initial transmission of a TB as indicated by the *New Data Indicator* field of the scheduling DCI, the UE may assume that all the code block groups of the TB are present.

- For a retransmission of a TB as indicated by the *New Data Indicator* field of the scheduling DCI, the UE may assume that
 - The *CBGTI* field of the scheduling DCI indicates which CBGs of the TB are present in the transmission. A bit value of 0' in the *CBGTI* field indicates that the corresponding CBG is not transmitted and 1' indicates that it is transmitted.
 - If the CBG flushing out information (*CBGFI*) field of the scheduling DCI is present, *CBGFI* set to 0' indicates that the earlier received instances of the same CBGs being transmitted may be corrupted, and *CBGFI* set to 1' indicates that the CBGs being retransmitted are combinable with the earlier received instances of the same CBGs.
 - A CBG contains the same CBs as in the initial transmission of the TB.

5.2 UE procedure for reporting channel state information (CSI)

5.2.1 Channel state information framework

The time and frequency resources that can be used by the UE to report CSI are controlled by the gNB. CSI may consist of Channel Quality Indicator (CQI), precoding matrix indicator (PMI), CSI-RS resource indicator (CRI), SS/PBCH Block Resource indicator (SSBRI), layer indicator (LI), rank indicator (RI) and/or L1-RSRP.

For CQI, PMI, CRI, SSBRI, LI, RI, L1-RSRP, a UE is configured by higher layers with $N \geq 1$ *CSI-ReportConfig* Reporting Settings, $M \geq 1$ *CSI-ResourceConfig* Resource Settings, and one or two list(s) of trigger states (given by the higher layer parameters *CSI-AperiodicTriggerStateList* and *CSI-SemiPersistentOnPUSCH-TriggerStateList*). Each trigger state in *CSI-AperiodicTriggerStateList* contains a list of associated *CSI-ReportConfigs* indicating the Resource Set IDs for channel and optionally for interference. Each trigger state in *CSI-SemiPersistentOnPUSCH-TriggerStateList* contains one associated *CSI-ReportConfig*.

5.2.1.1 Reporting settings

Each Reporting Setting *CSI-ReportConfig* is associated with a single downlink BWP (indicated by higher layer parameter *BWP-Id*) given in the associated *CSI-ResourceConfig* for channel measurement and contains the parameter(s) for one CSI reporting band:codebook configuration including codebook subset restriction, time-domain behavior, frequency granularity for CQI and PMI, measurement restriction configurations, and the CSI-related quantities to be reported by the UE such as the layer indicator (LI), L1-RSRP, CRI, and SSBRI (SSB Resource Indicator).

The time domain behavior of the *CSI-ReportConfig* is indicated by the higher layer parameter *reportConfigType* and can be set to 'aperiodic', 'semiPersistentOnPUCCH', 'semiPersistentOnPUSCH', or 'periodic'. For periodic and semiPersistentOnPUCCH/semiPersistentOnPUSCH CSI reporting, the configured periodicity and slot offset applies in the numerology of the UL BWP in which the CSI report is configured to be transmitted on. The higher layer parameter *reportQuantity* indicates the CSI-related or L1-RSRP-related quantities to report. The *reportFreqConfiguration* indicates the reporting granularity in the frequency domain, including the CSI reporting band and if PMI/CQI reporting is wideband or sub-band. The *timeRestrictionForChannelMeasurements* parameter in *CSI-ReportConfig* can be configured to enable time domain restriction for channel measurements and *timeRestrictionForInterferenceMeasurements* can be configured to enable time domain restriction for interference measurements. The *CSI-ReportConfig* can also contain *CodebookConfig*, which contains configuration parameters for Type-I or Type II CSI including codebook subset restriction, and configurations of group based reporting.

5.2.1.2 Resource settings

Each CSI Resource Setting *CSI-ResourceConfig* contains a configuration of a list of $S \geq 1$ CSI Resource Sets (given by higher layer parameter *csi-RS-ResourceSetList*), where the list is comprised of references to either or both of NZP CSI-RS resource set(s) and SS/PBCH block set(s) or the list is comprised of references to CSI-IM resource set(s). Each CSI Resource Setting is located in the DL BWP identified by the higher layer parameter *BWP-id*, and all CSI Resource Settings linked to a CSI Report Setting have the same DL BWP.

The time domain behavior of the CSI-RS resources within a CSI Resource Setting are indicated by the higher layer parameter *resourceType* and can be set to aperiodic, periodic, or semi-persistent. For periodic and semi-persistent CSI Resource Settings, the number of CSI-RS Resource Sets configured is limited to $S=1$. For periodic and semi-persistent CSI Resource Settings, the configured periodicity and slot offset is given in the numerology of its associated DL BWP,

as given by *BWP-id*. When a UE is configured with multiple *CSI-ResourceConfigs* consisting the same NZP CSI-RS resource ID, the same time domain behavior shall be configured for the *CSI-ResourceConfigs*. When a UE is configured with multiple *CSI-ResourceConfigs* consisting the same CSI-IM resource ID, the same time-domain behavior shall be configured for the *CSI-ResourceConfigs*. All CSI Resource Settings linked to a CSI Report Setting shall have the same time domain behavior.

The following are configured via higher layer signaling for one or more CSI Resource Settings for channel and interference measurement:

- CSI-IM resource for interference measurement as described in Clause 5.2.2.4.
- NZP CSI-RS resource for interference measurement as described in Clause 5.2.2.3.1.
- NZP CSI-RS resource for channel measurement as described in Clause 5.2.2.3.1.

The UE may assume that the NZP CSI-RS resource(s) for channel measurement and the CSI-IM resource(s) for interference measurement configured for one CSI reporting are resource-wise QCLed with respect to 'QCL-TypeD'. When NZP CSI-RS resource(s) is used for interference measurement, the UE may assume that the NZP CSI-RS resource for channel measurement and the CSI- IM resource and/or NZP CSI-RS resource(s) for interference measurement configured for one CSI reporting are QCLed with respect to 'QCL-TypeD'.

5.2.1.3 (void)

5.2.1.4 Reporting configurations

The UE shall calculate CSI parameters (if reported) assuming the following dependencies between CSI parameters (if reported)

- LI shall be calculated conditioned on the reported CQI, PMI, RI and CRI
- CQI shall be calculated conditioned on the reported PMI, RI and CRI
- PMI shall be calculated conditioned on the reported RI and CRI
- RI shall be calculated conditioned on the reported CRI.

The Reporting configuration for CSI can be aperiodic (using PUSCH), periodic (using PUCCH) or semi-persistent (using PUCCH, and DCI activated PUSCH). The CSI-RS Resources can be periodic, semi-persistent, or aperiodic. Table 5.2.1.4-1 shows the supported combinations of CSI Reporting configurations and CSI-RS Resource configurations and how the CSI Reporting is triggered for each CSI-RS Resource configuration. Periodic CSI-RS is configured by higher layers. Semi-persistent CSI-RS is activated and deactivated as described in Clause 5.2.1.5.2. Aperiodic CSI-RS is configured and triggered/activated as described in Clause 5.2.1.5.1.

Table 5.2.1.4-1: Triggering/Activation of CSI Reporting for the possible CSI-RS Configurations.

CSI-RS Configuration	Periodic CSI Reporting	Semi-Persistent CSI Reporting	Aperiodic CSI Reporting
Periodic CSI-RS	No dynamic triggering/activation	For reporting on PUCCH, the UE receives an activation command, as described in clause 6.1.3.16 of [10, TS 38.321]; for reporting on PUSCH, the UE receives triggering on DCI	Triggered by DCI; additionally, subselection indication as described in clause 6.1.3.13 of [10, TS 38.321] possible as defined in Clause 5.2.1.5.1.
Semi-Persistent CSI-RS	Not Supported	For reporting on PUCCH, the UE receives an activation command, as described in clause 6.1.3.16 of [10, TS 38.321]; for reporting on PUSCH, the UE receives triggering on DCI	Triggered by DCI; additionally, subselection indication as described in clause 6.1.3.13 of [10, TS 38.321] possible as defined in Clause 5.2.1.5.1.
Aperiodic CSI-RS	Not Supported	Not Supported	Triggered by DCI; additionally, subselection indication as described in clause 6.1.3.13 of [10, TS 38.321] possible as defined in Clause 5.2.1.5.1.

When the UE is configured with higher layer parameter *NZP-CSI-RS-ResourceSet* and when the higher layer parameter *repetition* is set to 'off', the UE shall determine a CRI from the supported set of CRI values as defined in Clause 6.3.1.1.2 of [5, TS 38.212] and report the number in each CRI report. When the higher layer parameter *repetition* is set to 'on', CRI is not reported. CRI reporting is not supported when the higher layer parameter *codebookType* is set to 'typeII' or to 'typeII-PortSelection'.

For a periodic or semi-persistent CSI report on PUCCH, the periodicity T_{CSI} (measured in slots) and the slot offset T_{offset} are configured by the higher layer parameter *reportSlotConfig*. Unless specified otherwise, the UE shall transmit the CSI report in frames with SFN n_f and slot number within the frame $n_{s,f}^\mu$ satisfying

$$(N_{slot}^{\text{frame},\mu} n_f + n_{s,f}^\mu - T_{offset}) \bmod T_{CSI} = 0$$

where μ is the SCS configuration of the UL BWP the CSI report is transmitted on.

For a semi-persistent CSI report on PUSCH, the periodicity T_{CSI} (measured in slots) is configured by the higher layer parameter *reportSlotConfig*. Unless specified otherwise, the UE shall transmit the CSI report in frames with SFN n_f and slot number within the frame $n_{s,f}^\mu$ satisfying

$$(N_{slot}^{\text{frame},\mu} (n_f - n_f^{\text{start}}) + n_{s,f}^\mu - n_{s,f}^{\text{start}}) \bmod T_{CSI} = 0$$

where n_f^{start} and $n_{s,f}^{\text{start}}$ are the SFN and slot number within the frame respectively of the initial semi-persistent PUSCH transmission according to the activating DCI.

For a semi-persistent or aperiodic CSI report on PUSCH, the allowed slot offsets are configured by the higher layer parameter *reportSlotOffsetList*. The offset is selected in the activating/triggering DCI.

For CSI reporting, a UE can be configured via higher layer signaling with one out of two possible subband sizes, where a subband is defined as $N_{\text{PRB}}^{\text{SB}}$ contiguous PRBs and depends on the total number of PRBs in the bandwidth part according to Table 5.2.1.4-2.

Table 5.2.1.4-2: Configurable subband sizes

Bandwidth part (PRBs)	Subband size (PRBs)
-----------------------	---------------------

24 – 72	4, 8
73 – 144	8, 16
145 – 275	16, 32

The *reportFreqConfiguration* contained in a *CSI-ReportConfig* indicates the frequency granularity of the CSI Report. A CSI Reporting Setting configuration defines a CSI reporting band as a subset of subbands of the bandwidth part, where the *reportFreqConfiguration* indicates:

- the *csi-ReportingBand* as a contiguous or non-contiguous subset of subbands in the bandwidth part for which CSI shall be reported.
- A UE is not expected to be configured with *csi-ReportingBand* which contains a subband where a CSI-RS resource linked to the CSI Report setting has the frequency density of each CSI-RS port per PRB in the subband less than the configured density of the CSI-RS resource.
- If a CSI-IM resource is linked to the CSI Report Setting, a UE is not expected to be configured with *csi-ReportingBand* which contains a subband where not all PRBs in the subband have the CSI-IM REs present.
- wideband CQI or subband CQI reporting, as configured by the higher layer parameter *cqi-FormatIndicator*. When wideband CQI reporting is configured, a wideband CQI is reported for each codeword for the entire CSI reporting band. When subband CQI reporting is configured, one CQI for each codeword is reported for each subband in the CSI reporting band.
- wideband PMI or subband PMI reporting as configured by the higher layer parameter *pmi-FormatIndicator*. When wideband PMI reporting is configured, a wideband PMI is reported for the entire CSI reporting band. When subband PMI reporting is configured, except with 2 antenna ports, a single wideband indication (i_1 in Clause 5.2.2.2) is reported for the entire CSI reporting band and one subband indication (i_2 in clause 5.2.2.2) is reported for each subband in the CSI reporting band. When subband PMIs are configured with 2 antenna ports, a PMI is reported for each subband in the CSI reporting band.

A CSI Reporting Setting is said to have a wideband frequency-granularity if

- *reportQuantity* is set to 'cri-RI-PMI-CQI', or 'cri-RI-LI-PMI-CQI', *cqi-FormatIndicator* is set to 'widebandCQI' and *pmi-FormatIndicator* is set to 'widebandPMI', or
- *reportQuantity* is set to 'cri-RI-i1' or
- *reportQuantity* is set to 'cri-RI-CQI' or 'cri-RI-i1-CQI' and *cqi-FormatIndicator* is set to 'widebandCQI', or
- *reportQuantity* is set to 'cri-RSRP' or 'ssb-Index-RSRP'

otherwise, the CSI Reporting Setting is said to have a subband frequency-granularity.

If the UE is configured with a CSI Reporting Setting for a bandwidth part with fewer than 24 PRBs, the CSI reporting setting is expected to have a wideband frequency-granularity, and, if applicable, the higher layer parameter *codebookType* is set to 'typeI-SinglePanel'.

The first subband size is given by $N_{PRB}^{SB} - (N_{BWP,i}^{start} \bmod N_{PRB}^{SB})$ and the last subband size given by $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod N_{PRB}^{SB}$ if $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod N_{PRB}^{SB} \neq 0$ and N_{PRB}^{SB} if $(N_{BWP,i}^{start} + N_{BWP,i}^{size}) \bmod N_{PRB}^{SB} = 0$

If a UE is configured with semi-persistent CSI reporting, the UE shall report CSI when both CSI-IM and NZP CSI-RS resources are configured as periodic or semi-persistent. If a UE is configured with aperiodic CSI reporting, the UE shall report CSI when both CSI-IM and NZP CSI-RS resources are configured as periodic, semi-persistent or aperiodic.

A UE configured with DCI 0_1 does not expect to be triggered with multiple CSI reports with the same *CSI-ReportConfigId*.

5.2.1.4.1 Resource Setting configuration

For aperiodic CSI, each trigger state configured using the higher layer parameter *CSI-AperiodicTriggerState* is associated with one or multiple *CSI-ReportConfig* where each *CSI-ReportConfig* is linked to periodic, or semi-persistent, or aperiodic resource setting(s):

- When one Resource Setting is configured, the Resource Setting (given by higher layer parameter *resourcesForChannelMeasurement*) is for channel measurement for L1-RSRP computation.
- When two Resource Settings are configured, the first one Resource Setting (given by higher layer parameter *resourcesForChannelMeasurement*) is for channel measurement and the second one (given by either higher layer parameter *csi-IM-ResourcesForInterference* or higher layer parameter *nzp-CSI-RS-ResourcesForInterference*) is for interference measurement performed on CSI-IM or on NZP CSI-RS.
- When three Resource Settings are configured, the first Resource Setting (higher layer parameter *resourcesForChannelMeasurement*) is for channel measurement, the second one (given by higher layer parameter *csi-IM-ResourcesForInterference*) is for CSI-IM based interference measurement and the third one (given by higher layer parameter *nzp-CSI-RS-ResourcesForInterference*) is for NZP CSI-RS based interference measurement.

For semi-persistent or periodic CSI, each *CSI-ReportConfig* is linked to periodic or semi-persistent Resource Setting(s):

- When one Resource Setting (given by higher layer parameter *resourcesForChannelMeasurement*) is configured, the Resource Setting is for channel measurement for L1-RSRP computation.
- When two Resource Settings are configured, the first Resource Setting (given by higher layer parameter *resourcesForChannelMeasurement*) is for channel measurement and the second Resource Setting (given by higher layer parameter *csi-IM-ResourcesForInterference*) is used for interference measurement performed on CSI-IM.

A UE is not expected to be configured with more than one CSI-RS resource in resource set for channel measurement for a *CSI-ReportConfig* with the higher layer parameter *codebookType* set to 'typeII' or to 'typeII-PortSelection'. A UE is not expected to be configured with more than 64 NZP CSI-RS resources in resource setting for channel measurement for a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'none', 'cri-RI-CQI', 'cri-RSRP' or 'ssb-Index-RSRP'. If interference measurement is performed on CSI-IM, each CSI-RS resource for channel measurement is resource-wise associated with a CSI-IM resource by the ordering of the CSI-RS resource and CSI-IM resource in the corresponding resource sets. The number of CSI-RS resources for channel measurement equals to the number of CSI-IM resources.

If interference measurement is performed on NZP CSI-RS, a UE does not expect to be configured with more than one NZP CSI-RS resource in the associated resource set within the resource setting for channel measurement. The UE configured with the higher layer parameter *nzp-CSI-RS-ResourcesForInterference* may expect no more than 18 NZP CSI-RS ports configured in a NZP CSI-RS resource set.

For CSI measurement(s), a UE assumes:

- each NZP CSI-RS port configured for interference measurement corresponds to an interference transmission layer.
- all interference transmission layers on NZP CSI-RS ports for interference measurement take into account the associated EPRE ratios configured in 5.2.2.3.1;
- other interference signal on REs of NZP CSI-RS resource for channel measurement, NZP CSI-RS resource for interference measurement, or CSI-IM resource for interference measurement.

5.2.1.4.2 Report Quantity Configurations

A UE may be configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to either 'none', 'cri-RI-PMI-CQI', 'cri-RI-i1', 'cri-RI-i1-CQI', 'cri-RI-CQI', 'cri-RSRP', 'ssb-Index-RSRP' or 'cri-RI-LI-PMI-CQI'.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'none', then the UE shall not report any quantity for the *CSI-ReportConfig*.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RI-PMI-CQI', or 'cri-RI-LI-PMI-CQI', the UE shall report a preferred precoder matrix for the entire reporting band, or a preferred precoder matrix per subband, according to Clause 5.2.2.2.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RI-i1',

- the UE expects, for that *CSI-ReportConfig*, to be configured with higher layer parameter *codebookType* set to 'typeI-SinglePanel' and *pmi-FormatIndicator* set to 'widebandPMI' and,

- the UE shall report a PMI consisting of a single wideband indication (i_1 in Clause 5.2.2.2.1) for the entire CSI reporting band.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RI-i1-CQI',

- the UE expects, for that *CSI-ReportConfig*, to be configured with higher layer parameter *codebookType* set to 'typeI-SinglePanel' and *pmi-FormatIndicator* set to 'widebandPMI' and,
- the UE shall report a PMI consisting of a single wideband indication (i_1 in Clause 5.2.2.2.1) for the entire CSI reporting band. The CQI is calculated conditioned on the reported i_1 assuming PDSCH transmission with $N_p \geq 1$ precoders (corresponding to the same i_1 but different i_2 in Clause 5.2.2.2.1), where the UE assumes that one precoder is randomly selected from the set of N_p precoders for each PRG on PDSCH, where the PRG size for CQI calculation is configured by the higher layer parameter *pdsch-BundleSizeForCSI*.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RI-CQI',

- if the UE is configured with higher layer parameter *non-PMI-PortIndication* contained in a *CSI-ReportConfig*, r ports are indicated in the order of layer ordering for rank r and each CSI-RS resource in the CSI resource setting is linked to the *CSI-ReportConfig* based on the order of the associated *NZP-CSI-RS-ResourceId* in the linked CSI resource setting for channel measurement given by higher layer parameter *resourcesForChannelMeasurement*. The configured higher layer parameter *non-PMI-PortIndication* contains a sequence $p_0^{(1)}, p_0^{(2)}, p_1^{(2)}, p_0^{(3)}, p_1^{(3)}, p_2^{(3)}, \dots, p_0^{(R)}, p_1^{(R)}, \dots, p_{R-1}^{(R)}$ of port indices, where $p_0^{(v)}, \dots, p_{v-1}^{(v)}$ are the CSI-RS port indices associated with rank v and $R \in \{1, 2, \dots, P\}$ where $P \in \{1, 2, 4, 8\}$ is the number of ports in the CSI-RS resource. The UE shall only report RI corresponding to the configured fields of *PortIndexFor8Ranks*.
- if the UE is not configured with higher layer parameter *non-PMI-PortIndication*, the UE assumes, for each CSI-RS resource in the CSI resource setting linked to the *CSI-ReportConfig*, that the CSI-RS port indices $p_0^{(v)}, \dots, p_{v-1}^{(v)} = \{0, \dots, v-1\}$ are associated with ranks $v = 1, 2, \dots, P$ where $P \in \{1, 2, 4, 8\}$ is the number of ports in the CSI-RS resource.
- When calculating the CQI for a rank, the UE shall use the ports indicated for that rank for the selected CSI-RS resource. The precoder for the indicated ports shall be assumed to be the identity matrix scaled by $\frac{1}{\sqrt{v}}$.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RSRP' or 'ssb-Index-RSRP',

- if the UE is configured with the higher layer parameter *groupBasedBeamReporting* set to 'disabled', the UE is not required to update measurements for more than 64 CSI-RS and/or SSB resources, and the UE shall report in a single report *nrofReportedRS* (higher layer configured) different CRI or SSBRI for each report setting.
- if the UE is configured with the higher layer parameter *groupBasedBeamReporting* set to 'enabled', the UE is not required to update measurements for more than 64 CSI-RS and/or SSB resources, and the UE shall report in a single reporting instance two different CRI or SSBRI for each report setting, where CSI-RS and/or SSB resources can be received simultaneously by the UE either with a single spatial domain receive filter, or with multiple simultaneous spatial domain receive filters.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RSRP', 'cri-RI-PMI-CQI', 'cri-RI-i1', 'cri-RI-i1-CQI', 'cri-RI-CQI' or 'cri-RI-LI-PMI-CQI', and $K_s > 1$ resources are configured in the corresponding resource set for channel measurement, then the UE shall derive the CSI parameters other than CRI conditioned on the reported CRI, where CRI k ($k \geq 0$) corresponds to the configured $(k+1)$ -th entry of associated *nzp-CSI-RSResource* in the corresponding *nzp-CSI-RS-ResourceSet* for channel measurement, and $(k+1)$ -th entry of associated *csi-IM-Resource* in the corresponding *csi-IM-ResourceSet* (if configured) If $K_s = 2$ CSI-RS resources are configured, each resource shall contain at most 16 CSI-RS ports. If $2 < K_s \leq 8$ CSI-RS resources are configured, each resource shall contain at most 8 CSI-RS ports.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'ssb-Index-RSRP', the UE shall report SSBRI, where SSBRI k ($k \geq 0$) corresponds to the configured $(k+1)$ -th entry of the associated *csi-SSB-ResourceList* in the corresponding *CSI-SSB-ResourceSet*.

If the UE is configured with a *CSI-ReportConfig* with the higher layer parameter *reportQuantity* set to 'cri-RI-PMI-CQI', 'cri-RI-i1', 'cri-RI-i1-CQI', 'cri-RI-CQI' or 'cri-RI-LI-PMI-CQI', then the UE is not expected to be configured with more than 8 CSI-RS resources in a CSI-RS resource set contained within a resource setting that is linked to the *CSI-ReportConfig*.

If the UE is configured with a *CSI-ReportConfig* with higher layer parameter *reportQuantity* set to 'cri-RSRP' or 'none' and the *CSI-ReportConfig* is linked to a resource setting configured with the higher layer parameter *resourceType* set to 'aperiodic', then the UE is not expected to be configured with more than 16 CSI-RS resources in a CSI-RS resource set contained within the resource setting.

The LI indicates which column of the precoder matrix of the reported PMI corresponds to the strongest layer of the codeword corresponding to the largest reported wideband CQI. If two wideband CQIs are reported and have equal value, the LI corresponds to strongest layer of the first codeword.

5.2.1.4.3 L1-RSRP Reporting

For L1-RSRP computation

- the UE may be configured with CSI-RS resources, SS/PBCH Block resources or both CSI-RS and SS/PBCH block resources, when resource-wise quasi co-located with 'QCL-Type C' and 'QCL-TypeD' when applicable.
- the UE may be configured with CSI-RS resource setting up to 16 CSI-RS resource sets having up to 64 resources within each set. The total number of different CSI-RS resources over all resource sets is no more than 128.

For L1-RSRP reporting, if the higher layer parameter *nrofReportedRS* in *CSI-ReportConfig* is configured to be one, the reported L1-RSRP value is defined by a 7-bit value in the range [-140, -44] dBm with 1dB step size, if the higher layer parameter *nrofReportedRS* is configured to be larger than one, or if the higher layer parameter *groupBasedBeamReporting* is configured as 'enabled', the UE shall use differential L1-RSRP based reporting, where the largest measured value of L1-RSRP is quantized to a 7-bit value in the range [-140, -44] dBm with 1dB step size, and the differential L1-RSRP is quantized to a 4-bit value. The differential L1-RSRP value is computed with 2 dB step size with a reference to the largest measured L1-RSRP value which is part of the same L1-RSRP reporting instance. The mapping between the reported L1-RSRP value and the measured quantity is described in [11, TS 38.133].

5.2.1.5 Triggering/activation of CSI Reports and CSI-RS

5.2.1.5.1 Aperiodic CSI Reporting/Aperiodic CSI-RS

For CSI-RS resource sets associated with Resource Settings configured with the higher layer parameter *resourceType* set to 'aperiodic', 'periodic', or 'semi-persistent', trigger states for Reporting Setting(s) (configured with the higher layer parameter *reportConfigType* set to 'aperiodic') and/or Resource Setting for channel and/or interference measurement on one or more component carriers are configured using the higher layer parameter *CSI-AperiodicTriggerStateList*. For aperiodic CSI report triggering, a single set of CSI triggering states are higher layer configured, wherein the CSI triggering states can be associated with any candidate DL BWP. A UE is not expected to receive more than one DCI with non-zero CSI request per slot. A UE is not expected to be configured with different *TCI-StateId*'s for the same aperiodic CSI-RS resource ID configured in multiple aperiodic CSI-RS resource sets with the same triggering offset in the same aperiodic trigger state. A UE is not expected to receive more than one aperiodic CSI report request for transmission in a given slot. A UE is not expected to be triggered with a CSI report for a non-active DL BWP. A trigger state is initiated using the *CSI request* field in DCI.

- When all the bits of *CSI request* field in DCI are set to zero, no CSI is requested.
- When the number of configured CSI triggering states in *CSI-AperiodicTriggerStateList* is greater than $2^{N_{TS}} - 1$, where N_{TS} is the number of bits in the DCI *CSI request* field, the UE receives a subselection indication, as described in clause 6.1.3.13 of [10, TS 38.321], used to map up to $2^{N_{TS}} - 1$ trigger states to the codepoints of the *CSI request* field in DCI. N_{TS} is configured by the higher layer parameter *reportTriggerSize* where $N_{TS} \in \{0, 1, 2, 3, 4, 5, 6\}$. When the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the subselection indication, the corresponding action in [10, TS 38.321] and UE assumption on the mapping of the selected CSI trigger state(s) to the codepoint(s) of DCI CSI request field shall be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe, \mu}$ where μ is the SCS configuration for the PUCCH.

- When the number of CSI triggering states in *CSI-AperiodicTriggerStateList* is less than or equal to $2^{N_{TS}} - 1$, the *CSI request* field in DCI directly indicates the triggering state.
- For each aperiodic CSI-RS resource in a CSI-RS resource set associated with each CSI triggering state, the UE is indicated the quasi co-location configuration of quasi co-location RS source(s) and quasi co-location type(s), as described in Clause 5.1.5, through higher layer signaling of *qcl-info* which contains a list of references to *TCI-State's* for the aperiodic CSI-RS resources associated with the CSI triggering state. If a *State* referred to in the list is configured with a reference to an RS associated with '*QCL-TypeD*', that RS may be an SS/PBCH block located in the same or different CC/DL BWP or a CSI-RS resource configured as periodic or semi-persistent located in the same or different CC/DL BWP.
- If the scheduling offset between the last symbol of the PDCCH carrying the triggering DCI and the first symbol of the aperiodic CSI-RS resources in a *NZP-CSI-RS-ResourceSet* configured without higher layer parameter *trs-Info* and without the higher layer parameter *repetition* is smaller than the UE reported threshold *beamSwitchTiming*, as defined in [13, TS 38.306], when the reported value is one of the values of {14, 28, 48}.
 - if there is any other DL signal with an indicated TCI state in the same symbols as the CSI-RS, the UE applies the QCL assumption of the other DL signal also when receiving the aperiodic CSI-RS. The other DL signal refers to PDSCH scheduled with offset larger than or equal to the threshold *timeDurationForQCL*, as defined in [13, TS 38.306], aperiodic CSI-RS scheduled with offset larger than or equal to the UE reported threshold *beamSwitchTiming* when the reported value is one of the values {14,28,48}, periodic CSI-RS, semi-persistent CSI-RS;
 - else, when receiving the aperiodic CSI-RS, the UE applies the QCL assumption used for the CORESET associated with a monitored search space with the lowest *controlResourceSetId* in the latest slot in which one or more CORESETs within the active BWP of the serving cell are monitored.
- If the scheduling offset between the last symbol of the PDCCH carrying the triggering DCI and the first symbol of the aperiodic CSI-RS resources is equal to or greater than the UE reported threshold *beamSwitchTiming* when the reported value is one of the values of {14,28,48}, the UE is expected to apply the QCL assumptions in the indicated TCI states for the aperiodic CSI-RS resources in the CSI triggering state indicated by the CSI trigger field in DCI.
- A non-zero codepoint of the CSI request field in the DCI is mapped to a CSI triggering state according to the order of the associated positions of the up to $2^{N_{TS}} - 1$ trigger states in *CSI-AperiodicTriggerStateList* with codepoint '1' mapped to the triggering state in the first position.

For a UE configured with the higher layer parameter *CSI-AperiodicTriggerStateList*, if a Resource Setting linked to a *CSI-ReportConfig* has multiple aperiodic resource sets, only one of the aperiodic CSI-RS resource sets from the Resource Setting is associated with the trigger state, and the UE is higher layer configured per trigger state per Resource Setting to select the one CSI-IM/NZP CSI-RS resource set from the Resource Setting.

When aperiodic CSI-RS is used with aperiodic reporting, the CSI-RS offset is configured per resource set by the higher layer parameter *aperiodicTriggeringOffset*. The CSI-RS triggering offset has the values of {0, 1, 2, 3, 4, 16, 24} slots. If all the associated trigger states do not have the higher layer parameter *qcl-Type* set to '*QCL-TypeD*' in the corresponding TCI states, the CSI-RS triggering offset is fixed to zero. The aperiodic triggering offset of the CSI-IM follows offset of the associated NZP CSI-RS for channel measurement.

The UE does not expect that aperiodic CSI-RS is transmitted before the OFDM symbol(s) carrying its triggering DCI.

If interference measurement is performed on aperiodic NZP CSI-RS, a UE is not expected to be configured with a different aperiodic triggering offset of the NZP CSI-RS for interference measurement from the associated NZP CSI-RS for channel measurement.

If the UE is configured with a single carrier for uplink, the UE is not expected to transmit more than one aperiodic CSI report triggered by different DCIs on overlapping OFDM symbols.

5.2.1.5.2 Semi-persistent CSI/Semi-persistent CSI-RS

For semi-persistent reporting on PUSCH, a set of trigger states are higher layer configured by *CSI-SemiPersistentOnPUSCH-TriggerStateList*, where the CSI request field in DCI scrambled with SP-CSI-RNTI activates one of the trigger states. A UE is not expected to receive a DCI scrambled with SP-CSI-RNTI activating one semi-

persistent CSI report with the same CSI-ReportConfigId as in a semi-persistent CSI report which is activated by a previously received DCI scrambled with SP-CSI-RNTI.

For semi-persistent reporting on PUCCH, the PUCCH resource used for transmitting the CSI report are configured by *reportConfigType*. Semi-persistent reporting on PUCCH is activated by an activation command as described in clause 6.1.3.16 of [10, TS 38.321], which selects one of the semi-persistent Reporting Settings for use by the UE on the PUCCH. When the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the activation command, the indicated semi-persistent Reporting Setting should be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH.

For a UE configured with CSI resource setting(s) where the higher layer parameter *resourceType* set to 'semiPersistent'.

- when a UE receives an activation command, as described in clause 6.1.3.12 of [10, TS 38.321], for CSI-RS resource set(s) for channel measurement and CSI-IM/NZP CSI-RS resource set(s) for interference measurement associated with configured CSI resource setting(s), and when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the selection command, the corresponding actions in [10, TS 38.321] and the UE assumptions (including QCL assumptions provided by a list of reference to *TCI-State*'s, one per activated resource) on CSI-RS/CSI-IM transmission corresponding to the configured CSI-RS/CSI-IM resource configuration(s) shall be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH. If a *TCI-State* referred to in the list is configured with a reference to an RS associated with 'QCL-TypeD', that RS can be an SS/PBCH block, periodic or semi-persistent CSI-RS located in same or different CC/DL BWP.
- when a UE receives a deactivation command, as described in clause 6.1.3.12 of [10, TS 38.321], for activated CSI-RS/CSI-IM resource set(s) associated with configured CSI resource setting(s), and when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the deactivation command, the corresponding actions in [10, TS 38.321] and UE assumption on cessation of CSI-RS/CSI-IM transmission corresponding to the deactivated CSI-RS/CSI-IM resource set(s) shall apply starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH.

A codepoint of the CSI request field in the DCI is mapped to a SP-CSI triggering state according to the order of the positions of the configured trigger states in *CSI-SemiPersistentOnPUSCH-TriggerStateList*, with codepoint '0' mapped to the triggering state in the first position. A UE validates, for semi-persistent CSI activation or release, a DL semi-persistent assignment PDCCH on a DCI only if the following conditions are met:

- the CRC parity bits of the DCI format are scrambled with a SP-CSI-RNTI provided by higher layer parameter *sp-CSI-RNTI*
- Special fields for the DCI format are set according to Table 5.2.1.5.2-1 or Table 5.2.1.5.2-2.

If validation is achieved, the UE considers the information in the DCI format as a valid activation or valid release of semi-persistent CSI transmission on PUSCH, and the UE activates or deactivates a CSI Reporting Setting indicated by CSI request field in the DCI. If validation is not achieved, the UE considers the DCI format as having been detected with a non-matching CRC.

Table 5.2.1.5.2-1: Special fields for semi-persistent CSI activation PDCCH validation

	DCI format 0_1
HARQ process number	set to all '0's
Redundancy version	set to '00'

Table 5.2.1.5.2-2: Special fields for semi-persistent CSI deactivation PDCCH validation

	DCI format 0_1
HARQ process number	set to all '0's
Modulation and coding scheme	set to all '1's
Resource block assignment	If higher layer configures RA type 0 only, set to all '0's; If higher layer configures RA type 1 only, set to all '1's; If higher layer configures dynamic switch between RA type 0 and 1, then if MSB is '0', set to all '0's; else, set to all '1's
Redundancy version	set to '00'

If the UE has an active semi-persistent CSI-RS/CSI-IM resource configuration, or an active semi-persistent ZP CSI-RS resource set configuration, and has not received a deactivation command, the activated semi-persistent CSI-RS/CSI-IM resource set or the activated semi-persistent ZP CSI-RS resource set configurations are considered to be active when the corresponding DL BWP is active, otherwise they are considered suspended.

If the UE is configured with carrier deactivation, the following configurations in the carrier in activated state would also be deactivated and need re-activation configuration(s): semi-persistent CSI-RS/CSI-IM resource, semi-persistent CSI reporting on PUCCH, semi-persistent SRS, semi-persistent ZP CSI-RS resource set.

5.2.1.6 CSI processing criteria

The UE indicates the number of supported simultaneous CSI calculations N_{CPU} . If a UE supports N_{CPU} simultaneous CSI calculations it is said to have N_{CPU} CSI processing units for processing CSI reports across all configured cells. If L CPUs are occupied for calculation of CSI reports in a given OFDM symbol, the UE has $N_{CPU} - L$ unoccupied CPUs. If N CSI reports start occupying their respective CPUs on the same OFDM symbol on which $N_{CPU} - L$ CPUs are unoccupied, where each CSI report $n = 0, \dots, N - 1$ corresponds to $O_{CPU}^{(n)}$, the UE is not required to update the $N - M$ requested CSI reports with lowest priority (according to Clause 5.2.5), where $0 \leq M \leq N$ is the largest value such that $\sum_{n=0}^{M-1} O_{CPU}^{(n)} \leq N_{CPU} - L$ holds.

A UE is not expected to be configured with an aperiodic CSI trigger state containing more than N_{CPU} Reporting Settings. Processing of a CSI report occupies a number of CPUs for a number of symbols as follows:

- $O_{CPU} = 0$ for a CSI report with *CSI-ReportConfig* with higher layer parameter *reportQuantity* set to 'none' and *CSI-RS-ResourceSet* with higher layer parameter *trs-Info* configured
- $O_{CPU} = 1$ for a CSI report with *CSI-ReportConfig* with higher layer parameter *reportQuantity* set to 'cri-RSRP', 'ssb-Index-RSRP' or 'none' (and *CSI-RS-ResourceSet* with higher layer parameter *trs-Info* not configured)
- for a CSI report with *CSI-ReportConfig* with higher layer parameter *reportQuantity* set to 'cri-RI-PMI-CQI', 'cri-RI-i1', 'cri-RI-i1-CQI', 'cri-RI-CQI', or 'cri-RI-LI-PMI-CQI',
 - if a CSI report is aperiodically triggered without transmitting a PUSCH with either transport block or HARQ-ACK or both when $L = 0$ CPUs are occupied, where the CSI corresponds to a single CSI with wideband frequency-granularity and to at most 4 CSI-RS ports in a single resource without CRI report and where *codebookType* is set to 'typeI-SinglePanel' or where *reportQuantity* is set to 'cri-RI-CQI', $O_{CPU} = N_{CPU}$,
 - otherwise, $O_{CPU} = K_s$, where K_s is the number of CSI-RS resources in the CSI-RS resource set for channel measurement.

For a CSI report with *CSI-ReportConfig* with higher layer parameter *reportQuantity* not set to 'none', the CPU(s) are occupied for a number of OFDM symbols as follows:

- A periodic or semi-persistent CSI report (excluding an initial semi-persistent CSI report on PUSCH after the PDCCH triggering the report) occupies CPU(s) from the first symbol of the earliest one of each CSI-RS/CSI-IM/SSB resource for channel or interference measurement, respective latest CSI-RS/CSI-IM/SSB occasion no later than the corresponding CSI reference resource, until the last symbol of the PUSCH/PUCCH carrying the report.
- An aperiodic CSI report occupies CPU(s) from the first symbol after the PDCCH triggering the CSI report until the last symbol of the PUSCH carrying the report.
- An initial semi-persistent CSI report on PUSCH after the PDCCH trigger occupies CPU(s) from the first symbol after the PDCCH until the last symbol of the PUSCH carrying the report.

For a CSI report with *CSI-ReportConfig* with higher layer parameter *reportQuantity* set to 'none' and *CSI-RS-ResourceSet* with higher layer parameter *trs-Info* is not configured, the CPU(s) are occupied for a number of OFDM symbols as follows:

- A semi-persistent CSI report (excluding an initial semi-persistent CSI report on PUSCH after the PDCCH triggering the report) occupies CPU(s) from the first symbol of the earliest one of each transmission occasion of periodic or semi-persistent CSI-RS/SSB resource for channel measurement for L1-RSRP computation, until Z'_3 symbols after the last symbol of the latest one of the CSI-RS/SSB resource for channel measurement for L1-RSRP computation in each transmission occasion.

- An aperiodic CSI report occupies CPU(s) from the first symbol after the PDCCH triggering the CSI report until the last symbol between Z_3 symbols after the first symbol after the PDCCH triggering the CSI report and Z'_3 symbols after the last symbol of the latest one of each CSI-RS/SSB resource for channel measurement for L1-RSRP computation.

where (Z_3, Z'_3) are defined in the table 5.4-2.

In any slot, the UE is not expected to have more active CSI-RS ports or active CSI-RS resources in active BWPs than reported as capability. NZP CSI-RS resource is active in a duration of time defined as follows. For aperiodic CSI-RS, starting from the end of the PDCCH containing the request and ending at the end of the PUSCH containing the report associated with this aperiodic CSI-RS. For semi-persistent CSI-RS, starting from the end of when the activation command is applied, and ending at the end of when the deactivation command is applied. For periodic CSI-RS, starting when the periodic CSI-RS is configured by higher layer signalling, and ending when the periodic CSI-RS configuration is released. If a CSI-RS resource is referred N times by one or more CSI Reporting Settings, the CSI-RS resource and the CSI-RS ports within the CSI-RS resource are counted N times.

5.2.2 Channel state information

5.2.2.1 Channel quality indicator (CQI)

The CQI indices and their interpretations are given in Table 5.2.2.1-2 or Table 5.2.2.1-4 for reporting CQI based on QPSK, 16QAM and 64QAM. The CQI indices and their interpretations are given in Table 5.2.2.1-3 for reporting CQI based on QPSK, 16QAM, 64QAM and 256QAM.

Based on an unrestricted observation interval in time unless specified otherwise in this Clause, and an unrestricted observation interval in frequency, the UE shall derive for each CQI value reported in uplink slot n the highest CQI index which satisfies the following condition:

- A single PDSCH transport block with a combination of modulation scheme, target code rate and transport block size corresponding to the CQI index, and occupying a group of downlink physical resource blocks termed the CSI reference resource, could be received with a transport block error probability not exceeding:
 - 0.1, if the higher layer parameter *cqi-Table* in *CSI-ReportConfig* configures 'table1' (corresponding to Table 5.2.2.1-2), or 'table2' (corresponding to Table 5.2.2.1-3), or
 - 0.00001, if the higher layer parameter *cqi-Table* in *CSI-ReportConfig* configures 'table3' (corresponding to Table 5.2.2.1-4).

If a UE is not configured with higher layer parameter *timeRestrictionForChannelMeasurements*, the UE shall derive the channel measurements for computing CSI value reported in uplink slot n based on only the NZP CSI-RS, no later than the CSI reference resource, (defined in TS 38.211[4]) associated with the CSI resource setting.

If a UE is configured with higher layer parameter *timeRestrictionForChannelMeasurements* in *CSI-ReportConfig*, the UE shall derive the channel measurements for computing CSI reported in uplink slot n based on only the most recent, no later than the CSI reference resource, occasion of NZP CSI-RS (defined in [4, TS 38.211]) associated with the CSI resource setting.

If a UE is not configured with higher layer parameter *timeRestrictionForInterferenceMeasurements*, the UE shall derive the interference measurements for computing CSI value reported in uplink slot n based on only the CSI-IM and/or NZP CSI-RS for interference measurement no later than the CSI reference resource associated with the CSI resource setting.

If a UE is configured with higher layer parameter *timeRestrictionForInterferenceMeasurements* in *CSI-ReportConfig*, the UE shall derive the interference measurements for computing the CSI value reported in uplink slot n based on the most recent, no later than the CSI reference resource, occasion of CSI-IM and/or NZP CSI-RS for interference measurement (defined in [4, TS 38.211]) associated with the CSI resource setting.

For each sub-band index s , a 2-bit sub-band differential CQI is defined as:

- Sub-band Offset level (s) = sub-band CQI index (s) - wideband CQI index.

The mapping from the 2-bit sub-band differential CQI values to the offset level is shown in Table 5.2.2.1-1

Table 5.2.2.1-1: Mapping sub-band differential CQI value to offset level

Sub-band differential CQI value	Offset level
0	0
1	1
2	≥ 2
3	≤ -1

A combination of modulation scheme and transport block size corresponds to a CQI index if:

- the combination could be signaled for transmission on the PDSCH in the CSI reference resource according to the Transport Block Size determination described in Clause 5.1.3.2, and
- the modulation scheme is indicated by the CQI index, and
- the combination of transport block size and modulation scheme when applied to the reference resource results in the effective channel code rate which is the closest possible to the code rate indicated by the CQI index. If more than one combination of transport block size and modulation scheme results in an effective channel code rate equally close to the code rate indicated by the CQI index, only the combination with the smallest of such transport block sizes is relevant.

Table 5.2.2.1-2: 4-bit CQI Table

CQI index	modulation	code rate x 1024	efficiency
0	out of range		
1	QPSK	78	0.1523
2	QPSK	120	0.2344
3	QPSK	193	0.3770
4	QPSK	308	0.6016
5	QPSK	449	0.8770
6	QPSK	602	1.1758
7	16QAM	378	1.4766
8	16QAM	490	1.9141
9	16QAM	616	2.4063
10	64QAM	466	2.7305
11	64QAM	567	3.3223
12	64QAM	666	3.9023
13	64QAM	772	4.5234
14	64QAM	873	5.1152
15	64QAM	948	5.5547

Table 5.2.2.1-3: 4-bit CQI Table 2

CQI index	modulation	code rate x 1024	efficiency
0	out of range		
1	QPSK	78	0.1523
2	QPSK	193	0.3770
3	QPSK	449	0.8770
4	16QAM	378	1.4766
5	16QAM	490	1.9141
6	16QAM	616	2.4063
7	64QAM	466	2.7305
8	64QAM	567	3.3223
9	64QAM	666	3.9023
10	64QAM	772	4.5234
11	64QAM	873	5.1152
12	256QAM	711	5.5547
13	256QAM	797	6.2266
14	256QAM	885	6.9141
15	256QAM	948	7.4063

Table 5.2.2.1-4: 4-bit CQI Table 3

CQI index	modulation	code rate x 1024	efficiency
0	out of range		
1	QPSK	30	0.0586
2	QPSK	50	0.0977
3	QPSK	78	0.1523
4	QPSK	120	0.2344
5	QPSK	193	0.3770
6	QPSK	308	0.6016
7	QPSK	449	0.8770
8	QPSK	602	1.1758
9	16QAM	378	1.4766
10	16QAM	490	1.9141
11	16QAM	616	2.4063
12	64QAM	466	2.7305
13	64QAM	567	3.3223
14	64QAM	666	3.9023
15	64QAM	772	4.5234

5.2.2.1.1 (void)

5.2.2.2 Precoding matrix indicator (PMI)

5.2.2.2.1 Type I Single-Panel Codebook

For 2 antenna ports {3000, 3001} and the UE configured with higher layer parameter *codebookType* set to 'typeI-SinglePanel' each PMI value corresponds to a codebook index given in Table 5.2.2.2.1-1. The UE is configured with the higher layer parameter *twoTX-CodebookSubsetRestriction*. The bitmap parameter *twoTX-CodebookSubsetRestriction* forms the bit sequence a_5, \dots, a_1, a_0 where a_0 is the LSB and a_5 is the MSB and where a bit value of zero indicates that PMI reporting is not allowed to correspond to the precoder associated with the bit. Bits 0 to 3 are associated respectively with the codebook indices 0 to 3 for $v = 1$ layer, and bits 4 and 5 are associated respectively with the codebook indices 0 and 1 for $v = 2$ layers.

Table 5.2.2.2.1-1: Codebooks for 1-layer and 2-layer CSI reporting using antenna ports 3000 to 3001

Codebook index	Number of layers v	
	1	2
0	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$
1	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 1 \\ j & -j \end{bmatrix}$
2	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$	-
3	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -j \end{bmatrix}$	-

For 4 antenna ports {3000, 3001, 3002, 3003}, 8 antenna ports {3000, 3001, ..., 3007}, 12 antenna ports {3000, 3001, ..., 3011}, 16 antenna ports {3000, 3001, ..., 3015}, 24 antenna ports {3000, 3001, ..., 3023}, and 32 antenna ports {3000, 3001, ..., 3031}, and the UE configured with higher layer parameter *codebookType* set to 'typeI-SinglePanel', except when the number of layers $v \in \{2, 3, 4\}$ (where v is the associated RI value), each PMI value corresponds to

three codebook indices $i_{1,1}, i_{1,2}, i_{1,3}$. When the number of layers $v \in \{2, 3, 4\}$, each PMI value corresponds to four codebook indices $i_{1,1}, i_{1,2}, i_{1,3}, i_{1,4}$. The composite codebook index i_1 is defined by

$$i_1 = \begin{cases} [i_{1,1} & i_{1,2}] & v \notin \{2, 3, 4\} \\ [i_{1,1} & i_{1,2} & i_{1,3}] & v \in \{2, 3, 4\} \end{cases}$$

The codebooks for 1-8 layers are given respectively in Tables 5.2.2.2.1-5, 5.2.2.2.1-6, 5.2.2.2.1-7, 5.2.2.2.1-8, 5.2.2.2.1-9, 5.2.2.2.1-10, 5.2.2.2.1-11, and 5.2.2.2.1-12. The mapping from $i_{1,3}$ to k_1 and k_2 for 2-layer reporting is given in Table 5.2.2.2.1-3. The mapping from $i_{1,3}$ to k_1 and k_2 for 3-layer and 4-layer reporting when $P_{\text{CSI-RS}} < 16$ is given in Table 5.2.2.2.1-4. The quantities φ_n , θ_p , u_m , $v_{l,m}$, and $\tilde{v}_{l,m}$ are given by

$$\begin{aligned} \varphi_n &= e^{j\pi n/2} \\ \theta_p &= e^{j\pi p/4} \\ u_m &= \begin{cases} \left[\begin{array}{ccc} 1 & e^{j\frac{2\pi m}{O_2 N_2}} & \dots & e^{j\frac{2\pi m(N_2-1)}{O_2 N_2}} \end{array} \right] & N_2 > 1 \\ \left[\begin{array}{ccc} & & & 1 \end{array} \right] & N_2 = 1 \end{cases} \\ v_{l,m} &= \left[\begin{array}{ccc} u_m & e^{j\frac{2\pi l}{O_1 N_1} u_m} & \dots & e^{j\frac{2\pi l(N_1-1)}{O_1 N_1} u_m} & u_m \end{array} \right]^T \\ \tilde{v}_{l,m} &= \left[\begin{array}{ccc} u_m & e^{j\frac{4\pi l}{O_1 N_1} u_m} & \dots & e^{j\frac{4\pi l(N_1/2-1)}{O_1 N_1} u_m} & u_m \end{array} \right]^T \end{aligned}$$

- The values of N_1 and N_2 are configured with the higher layer parameter $nI-n2$, respectively. The supported configurations of (N_1, N_2) for a given number of CSI-RS ports and the corresponding values of (O_1, O_2) are given in Table 5.2.2.2.1-2. The number of CSI-RS ports, $P_{\text{CSI-RS}}$, is $2N_1N_2$.
- UE shall only use $i_{1,2} = 0$ and shall not report $i_{1,2}$ if the value of N_2 is 1.

The bitmap parameter $nI-n2$ forms the bit sequence $a_{A_c-1}, \dots, a_1, a_0$ where a_0 is the LSB and a_{A_c-1} is the MSB and where a bit value of zero indicates that PMI reporting is not allowed to correspond to any precoder associated with the bit. The number of bits is given by $A_c = N_1O_1N_2O_2$. Except when the number of layers $v \in \{3, 4\}$ and the number of antenna ports is 16, 24, or 32, bit $a_{N_2O_2l+m}$ is associated with all precoders based on the quantity $v_{l,m}$,

$l = 0, \dots, N_1O_1 - 1$, $m = 0, \dots, N_2O_2 - 1$. When the number of layers $v \in \{3, 4\}$ and the number of antenna ports is 16, 24, or 32,

- bits $a_{(N_2O_2(2l-1)+m) \bmod N_1O_1N_2O_2}$, $a_{N_2O_2(2l)+m}$, and $a_{N_2O_2(2l+1)+m}$ are each associated with all precoders based on the quantity $\tilde{v}_{l,m}$, $l = 0, \dots, N_1O_1/2 - 1$, $m = 0, \dots, N_2O_2 - 1$;
- if one or more of the associated bits is zero, then PMI reporting is not allowed to correspond to any precoder based on $\tilde{v}_{l,m}$.

For UE configured with higher layer parameter *codebookType* set to 'typeI-SinglePanel', the bitmap parameter *typeI-SinglePanel-ri-Restriction* forms the bit sequence r_7, \dots, r_1, r_0 where r_0 is the LSB and r_7 is the MSB. When r_i is zero, $i \in \{0, 1, \dots, 7\}$, PMI and RI reporting are not allowed to correspond to any precoder associated with $v = i + 1$ layers.

For UE configured with higher layer parameter *reportQuantity* set to 'cri-RI-i1-CQI', the bitmap parameter *typeI-SinglePanel-codebookSubsetRestriction-i2* forms the bit sequence b_{15}, \dots, b_1, b_0 where b_0 is the LSB and b_{15} is the

MSB. The bit b_i is associated with precoders corresponding to codebook index $i_2 = i$. When b_i is zero, the randomly selected precoder for CQI calculation is not allowed to correspond to any precoder associated with the bit b_i .

Table 5.2.2.1-2: Supported configurations of (N_1, N_2) and (O_1, O_2)

Number of CSI-RS antenna ports, $P_{\text{CSI-RS}}$	(N_1, N_2)	(O_1, O_2)
4	(2,1)	(4,1)
8	(2,2)	(4,4)
	(4,1)	(4,1)
12	(3,2)	(4,4)
	(6,1)	(4,1)
16	(4,2)	(4,4)
	(8,1)	(4,1)
24	(4,3)	(4,4)
	(6,2)	(4,4)
	(12,1)	(4,1)
32	(4,4)	(4,4)
	(8,2)	(4,4)
	(16,1)	(4,1)

Table 5.2.2.1-3: Mapping of $i_{1,3}$ to k_1 and k_2 for 2-layer CSI reporting

$i_{1,3}$	$N_1 > N_2 > 1$		$N_1 = N_2$		$N_1 = 2, N_2 = 1$		$N_1 > 2, N_2 = 1$	
	k_1	k_2	k_1	k_2	k_1	k_2	k_1	k_2
0	0	0	0	0	0	0	0	0
1	O_1	0	O_1	0	O_1	0	O_1	0
2	0	O_2	0	O_2			$2O_1$	0
3	$2O_1$	0	O_1	O_2			$3O_1$	0

Table 5.2.2.1-4: Mapping of $i_{1,3}$ to k_1 and k_2 for 3-layer and 4-layer CSI reporting when $P_{\text{CSI-RS}} < 16$

$i_{1,3}$	$N_1 = 2, N_2 = 1$		$N_1 = 4, N_2 = 1$		$N_1 = 6, N_2 = 1$		$N_1 = 2, N_2 = 2$		$N_1 = 3, N_2 = 2$	
	k_1	k_2	k_1	k_2	k_1	k_2	k_1	k_2	k_1	k_2
0	O_1	0	O_1	0	O_1	0	O_1	0	O_1	0
1			$2O_1$	0	$2O_1$	0	0	O_2	0	O_2
2			$3O_1$	0	$3O_1$	0	O_1	O_2	O_1	O_2
3					$4O_1$	0			$2O_1$	0

Table 5.2.2.1-5: Codebook for 1-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1			
$i_{1,1}$	$i_{1,2}$	i_2	
$0, 1, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	$0, 1, 2, 3$	$W_{i_{1,1}, i_{1,2}, i_2}^{(1)}$
where $W_{l,m,n}^{(1)} = \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_n v_{l,m} \end{bmatrix}$.			

codebookMode = 2, $N_2 > 1$					
$i_{1,1}$	$i_{1,2}$	i_2			
		0	1	2	3
$0,1,\dots,\frac{N_1O_1}{2}-1$	$0,1,\dots,\frac{N_2O_2}{2}-1$	$W_{2i_{1,1},2i_{1,2},0}^{(1)}$	$W_{2i_{1,1},2i_{1,2},1}^{(1)}$	$W_{2i_{1,1},2i_{1,2},2}^{(1)}$	$W_{2i_{1,1},2i_{1,2},3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		4	5	6	7
$0,1,\dots,\frac{N_1O_1}{2}-1$	$0,1,\dots,\frac{N_2O_2}{2}-1$	$W_{2i_{1,1}+1,2i_{1,2},0}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2},1}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2},2}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2},3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		8	9	10	11
$0,1,\dots,\frac{N_1O_1}{2}-1$	$0,1,\dots,\frac{N_2O_2}{2}-1$	$W_{2i_{1,1},2i_{1,2}+1,0}^{(1)}$	$W_{2i_{1,1},2i_{1,2}+1,1}^{(1)}$	$W_{2i_{1,1},2i_{1,2}+1,2}^{(1)}$	$W_{2i_{1,1},2i_{1,2}+1,3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		12	13	14	15
$0,1,\dots,\frac{N_1O_1}{2}-1$	$0,1,\dots,\frac{N_2O_2}{2}-1$	$W_{2i_{1,1}+1,2i_{1,2}+1,0}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2}+1,1}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2}+1,2}^{(1)}$	$W_{2i_{1,1}+1,2i_{1,2}+1,3}^{(1)}$
where $W_{l,m,n}^{(1)} = \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_n v_{l,m} \end{bmatrix}$.					

codebookMode = 2, $N_2 = 1$					
$i_{1,1}$	$i_{1,2}$	i_2			
		0	1	2	3
$0,1,\dots,\frac{N_1O_1}{2}-1$	0	$W_{2i_{1,1},0,0}^{(1)}$	$W_{2i_{1,1},0,1}^{(1)}$	$W_{2i_{1,1},0,2}^{(1)}$	$W_{2i_{1,1},0,3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		4	5	6	7
$0,1,\dots,\frac{N_1O_1}{2}-1$	0	$W_{2i_{1,1}+1,0,0}^{(1)}$	$W_{2i_{1,1}+1,0,1}^{(1)}$	$W_{2i_{1,1}+1,0,2}^{(1)}$	$W_{2i_{1,1}+1,0,3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		8	9	10	11
$0,1,\dots,\frac{N_1O_1}{2}-1$	0	$W_{2i_{1,1}+2,0,0}^{(1)}$	$W_{2i_{1,1}+2,0,1}^{(1)}$	$W_{2i_{1,1}+2,0,2}^{(1)}$	$W_{2i_{1,1}+2,0,3}^{(1)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		12	13	14	15
$0,1,\dots,\frac{N_1O_1}{2}-1$	0	$W_{2i_{1,1}+3,0,0}^{(1)}$	$W_{2i_{1,1}+3,0,1}^{(1)}$	$W_{2i_{1,1}+3,0,2}^{(1)}$	$W_{2i_{1,1}+3,0,3}^{(1)}$
where $W_{l,m,n}^{(1)} = \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_n v_{l,m} \end{bmatrix}$.					

Table 5.2.2.1-6: Codebook for 2-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1			
$i_{1,1}$	$i_{1,2}$	i_2	
$0,1,\dots,N_1O_1-1$	$0,\dots,N_2O_2-1$	0,1	$W_{i_{1,1},i_{1,1}+k_1,i_{1,2},i_{1,2}+k_2,i_2}^{(2)}$
where $W_{l,l',m,m',n}^{(2)} = \frac{1}{\sqrt{2P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l',m'} \\ \varphi_n v_{l,m} & -\varphi_n v_{l',m'} \end{bmatrix}$.			
and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.1-3.			

codebookMode = 2, $N_2 > 1$			
$i_{1,1}$	$i_{1,2}$	i_2	
		0	1
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	$W_{2i_{1,1}, 2i_{1,1}+k_1, 2i_{1,2}, 2i_{1,2}+k_2, 0}^{(2)}$	$W_{2i_{1,1}, 2i_{1,1}+k_1, 2i_{1,2}, 2i_{1,2}+k_2, 1}^{(2)}$
$i_{1,1}$	$i_{1,2}$	i_2	
		2	3
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 2i_{1,2}, 2i_{1,2}+k_2, 0}^{(2)}$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 2i_{1,2}, 2i_{1,2}+k_2, 1}^{(2)}$
$i_{1,1}$	$i_{1,2}$	i_2	
		4	5
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	$W_{2i_{1,1}, 2i_{1,1}+k_1, 2i_{1,2}+1, 2i_{1,2}+1+k_2, 0}^{(2)}$	$W_{2i_{1,1}, 2i_{1,1}+k_1, 2i_{1,2}+1, 2i_{1,2}+1+k_2, 1}^{(2)}$
$i_{1,1}$	$i_{1,2}$	i_2	
		6	7
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 2i_{1,2}+1, 2i_{1,2}+1+k_2, 0}^{(2)}$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 2i_{1,2}+1, 2i_{1,2}+1+k_2, 1}^{(2)}$

where $W_{l,l',m,m',n}^{(2)} = \frac{1}{\sqrt{2P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l',m'} \\ \varphi_n v_{l,m} & -\varphi_n v_{l',m'} \end{bmatrix}$.

and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2.1-3.

codebookMode = 2, $N_2 = 1$					
$i_{1,1}$	$i_{1,2}$	i_2			
		0	1	2	3
$0, \dots, \frac{N_1 O_1}{2} - 1$	0	$W_{2i_{1,1}, 2i_{1,1}+k_1, 0, 0, 0}^{(2)}$	$W_{2i_{1,1}, 2i_{1,1}+k_1, 0, 0, 1}^{(2)}$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 0, 0, 0}^{(2)}$	$W_{2i_{1,1}+1, 2i_{1,1}+1+k_1, 0, 0, 1}^{(2)}$
$i_{1,1}$	$i_{1,2}$	i_2			
		4	5	6	7
$0, \dots, \frac{N_1 O_1}{2} - 1$	0	$W_{2i_{1,1}+2, 2i_{1,1}+2+k_1, 0, 0, 0}^{(2)}$	$W_{2i_{1,1}+2, 2i_{1,1}+2+k_1, 0, 0, 1}^{(2)}$	$W_{2i_{1,1}+3, 2i_{1,1}+3+k_1, 0, 0, 0}^{(2)}$	$W_{2i_{1,1}+3, 2i_{1,1}+3+k_1, 0, 0, 1}^{(2)}$

where $W_{l,l',m,m',n}^{(2)} = \frac{1}{\sqrt{2P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l',m'} \\ \varphi_n v_{l,m} & -\varphi_n v_{l',m'} \end{bmatrix}$.

and the mapping from $i_{1,3}$ to k_1 is given in Table 5.2.2.2.1-3.

Table 5.2.2.2.1-7: Codebook for 3-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2, $P_{\text{CSI-RS}} < 16$			
$i_{1,1}$	$i_{1,2}$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, 1, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1}+k_1, i_{1,2}, i_{1,2}+k_2, i_2}^{(3)}$

where $W_{l,l',m,m',n}^{(3)} = \frac{1}{\sqrt{3P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l',m'} & v_{l,m} \\ \varphi_n v_{l,m} & \varphi_n v_{l',m'} & -\varphi_n v_{l,m} \end{bmatrix}$.

and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2.1-4.

codebookMode = 1-2, $P_{\text{CSI-RS}} \geq 16$				
$i_{1,1}$	$i_{1,2}$	$i_{1,3}$	i_2	
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, N_2 O_2 - 1$	$0, 1, 2, 3$	$0, 1$	$W_{i_{1,1}, i_{1,2}, i_{1,3}, i_2}^{(3)}$
where $W_{l,m,p,n}^{(3)} = \frac{1}{\sqrt{3P_{\text{CSI-RS}}}}$ $\begin{bmatrix} \tilde{v}_{l,m} & \tilde{v}_{l,m} & \tilde{v}_{l,m} \\ \theta_p \tilde{v}_{l,m} & -\theta_p \tilde{v}_{l,m} & \theta_p \tilde{v}_{l,m} \\ \varphi_n \tilde{v}_{l,m} & \varphi_n \tilde{v}_{l,m} & -\varphi_n \tilde{v}_{l,m} \\ \varphi_n \theta_p \tilde{v}_{l,m} & -\varphi_n \theta_p \tilde{v}_{l,m} & -\varphi_n \theta_p \tilde{v}_{l,m} \end{bmatrix}$				

Table 5.2.2.1-8: Codebook for 4-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2, $P_{\text{CSI-RS}} < 16$			
$i_{1,1}$	$i_{1,2}$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, 1, \dots, N_2 O_2 - 1$	$0, 1$	$W_{i_{1,1}, i_{1,1}+k_1, i_{1,2}, i_{1,2}+k_2, i_2}^{(4)}$
where $W_{l,l',m,m',n}^{(4)} = \frac{1}{\sqrt{4P_{\text{CSI-RS}}}}$ $\begin{bmatrix} v_{l,m} & v_{l',m'} & v_{l,m} & v_{l',m'} \\ \varphi_n v_{l,m} & \varphi_n v_{l',m'} & -\varphi_n v_{l,m} & -\varphi_n v_{l',m'} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.1-4.			

codebookMode = 1-2, $P_{\text{CSI-RS}} \geq 16$				
$i_{1,1}$	$i_{1,2}$	$i_{1,3}$	i_2	
$0, \dots, \frac{N_1 O_1}{2} - 1$	$0, \dots, N_2 O_2 - 1$	$0, 1, 2, 3$	$0, 1$	$W_{i_{1,1}, i_{1,2}, i_{1,3}, i_2}^{(4)}$
where $W_{l,m,p,n}^{(4)} = \frac{1}{\sqrt{4P_{\text{CSI-RS}}}}$ $\begin{bmatrix} \tilde{v}_{l,m} & \tilde{v}_{l,m} & \tilde{v}_{l,m} & \tilde{v}_{l,m} \\ \theta_p \tilde{v}_{l,m} & -\theta_p \tilde{v}_{l,m} & \theta_p \tilde{v}_{l,m} & -\theta_p \tilde{v}_{l,m} \\ \varphi_n \tilde{v}_{l,m} & \varphi_n \tilde{v}_{l,m} & -\varphi_n \tilde{v}_{l,m} & -\varphi_n \tilde{v}_{l,m} \\ \varphi_n \theta_p \tilde{v}_{l,m} & -\varphi_n \theta_p \tilde{v}_{l,m} & -\varphi_n \theta_p \tilde{v}_{l,m} & \varphi_n \theta_p \tilde{v}_{l,m} \end{bmatrix}$				

Table 5.2.2.1-9: Codebook for 5-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2				
	$i_{1,1}$	$i_{1,2}$	i_2	
$N_2 > 1$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	$0, 1$	$W_{i_{1,1}, i_{1,1}+O_1, i_{1,1}+O_1, i_{1,2}, i_{1,2}+O_2, i_2}^{(5)}$
$N_1 > 2, N_2 = 1$	$0, \dots, N_1 O_1 - 1$	0	$0, 1$	$W_{i_{1,1}, i_{1,1}+O_1, i_{1,1}+2O_1, 0, 0, i_2}^{(5)}$
where $W_{l,l',l'',m,m',m'',n}^{(5)} = \frac{1}{\sqrt{5P_{\text{CSI-RS}}}}$ $\begin{bmatrix} v_{l,m} & v_{l,m} & v_{l',m'} & v_{l',m'} & v_{l'',m''} \\ \varphi_n v_{l,m} & -\varphi_n v_{l,m} & v_{l',m'} & -v_{l',m'} & v_{l'',m''} \end{bmatrix}$				

Table 5.2.2.1-10: Codebook for 6-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2				
	$i_{1,1}$	$i_{1,2}$	i_2	
$N_2 > 1$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_2}^{(6)}$
$N_1 > 2, N_2 = 1$	$0, \dots, N_1 O_1 - 1$	0	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + 2O_1, 0, 0, 0, i_2}^{(6)}$
where $W_{l, l', l'', m, m', m'', n}^{(6)} = \frac{1}{\sqrt{6P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l,m} & v_{l',m'} & v_{l',m'} & v_{l'',m''} & v_{l'',m''} \\ \varphi_n v_{l,m} & -\varphi_n v_{l,m} & \varphi_n v_{l',m'} & -\varphi_n v_{l',m'} & v_{l'',m''} & -v_{l'',m''} \end{bmatrix}$.				

Table 5.2.2.1-11: Codebook for 7-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2				
	$i_{1,1}$	$i_{1,2}$	i_2	
$N_1 = 4, N_2 = 1$	$0, \dots, \frac{N_1 O_1}{2} - 1$	0	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + 2O_1, i_{1,1} + 3O_1, 0, 0, 0, 0, i_2}^{(7)}$
$N_1 > 4, N_2 = 1$	$0, \dots, N_1 O_1 - 1$	0	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + 2O_1, i_{1,1} + 3O_1, 0, 0, 0, 0, i_2}^{(7)}$
$N_1 = 2, N_2 = 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(7)}$
$N_1 > 2, N_2 = 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(7)}$
$N_1 > 2, N_2 > 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(7)}$
where $W_{l, l', l'', l''', m, m', m'', m''', n}^{(7)} = \frac{1}{\sqrt{7P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l,m} & v_{l',m'} & v_{l',m'} & v_{l'',m''} & v_{l'',m''} & v_{l''',m'''} & v_{l''',m'''} \\ \varphi_n v_{l,m} & -\varphi_n v_{l,m} & \varphi_n v_{l',m'} & v_{l',m'} & -v_{l'',m''} & v_{l'',m''} & -v_{l''',m'''} & v_{l''',m'''} \end{bmatrix}$.				

Table 5.2.2.1-12: Codebook for 8-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1-2				
	$i_{1,1}$	$i_{1,2}$	i_2	
$N_1 = 4, N_2 = 1$	$0, \dots, \frac{N_1 O_1}{2} - 1$	0	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + 2O_1, i_{1,1} + 3O_1, 0, 0, 0, 0, 0, i_2}^{(8)}$
$N_1 > 4, N_2 = 1$	$0, \dots, N_1 O_1 - 1$	0	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1} + 2O_1, i_{1,1} + 3O_1, 0, 0, 0, 0, 0, i_2}^{(8)}$
$N_1 = 2, N_2 = 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(8)}$
$N_1 > 2, N_2 = 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, \frac{N_2 O_2}{2} - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(8)}$
$N_1 > 2, N_2 > 2$	$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1	$W_{i_{1,1}, i_{1,1} + O_1, i_{1,1}, i_{1,1} + O_1, i_{1,2}, i_{1,2} + O_2, i_{1,2} + O_2, i_2}^{(8)}$
where $W_{l, l', l'', l''', l''', m, m', m'', m''', m''', n}^{(8)} = \frac{1}{\sqrt{8P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} & v_{l,m} & v_{l',m'} & v_{l',m'} & v_{l'',m''} & v_{l'',m''} & v_{l''',m'''} & v_{l''',m'''} \\ \varphi_n v_{l,m} & -\varphi_n v_{l,m} & \varphi_n v_{l',m'} & -\varphi_n v_{l',m'} & v_{l'',m''} & -v_{l'',m''} & v_{l''',m'''} & -v_{l''',m'''} \end{bmatrix}$.				

5.2.2.2.2 Type I Multi-Panel Codebook

For 8 antenna ports {3000, 3001, ..., 3007}, 16 antenna ports {3000, 3001, ..., 3015}, and 32 antenna ports {3000, 3001, ..., 3031}, and the UE configured with higher layer parameter *codebookType* set to 'typeI-MultiPanel',

- The values of N_g , N_1 and N_2 are configured with the higher layer parameters $ng-n1-n2$. The supported configurations of (N_g, N_1, N_2) for a given number of CSI-RS ports and the corresponding values of (O_1, O_2) are given in Table 5.2.2.2.2-1. The number of CSI-RS ports, $P_{\text{CSI-RS}}$, is $2N_gN_1N_2$.
- When $N_g = 2$, *codebookMode* shall be set to either '1' or '2'. When $N_g = 4$, *codebookMode* shall be set to '1'.

The bitmap parameter $ng-n1-n2$ forms the bit sequence $a_{A_c-1}, \dots, a_1, a_0$ where a_0 is the LSB and a_{A_c-1} is the MSB and where a bit value of zero indicates that PMI reporting is not allowed to correspond to any precoder associated with the bit. The number of bits is given by $A_c = N_1O_1N_2O_2$. Bit $a_{N_2O_2l+m}$ is associated with all precoders based on the quantity $v_{l,m}$, $l = 0, \dots, N_1O_1 - 1$, $m = 0, \dots, N_2O_2 - 1$, as defined below. The bitmap parameter *ri-Restriction* forms the bit sequence r_3, \dots, r_1, r_0 where r_0 is the LSB and r_3 is the MSB. When r_i is zero, $i \in \{0, 1, \dots, 3\}$, PMI and RI reporting are not allowed to correspond to any precoder associated with $v = i + 1$ layers.

Table 5.2.2.2.2-1: Supported configurations of (N_g, N_1, N_2) and (O_1, O_2)

Number of CSI-RS antenna ports, $P_{\text{CSI-RS}}$	(N_g, N_1, N_2)	(O_1, O_2)
8	(2,2,1)	(4,1)
16	(2,4,1)	(4,1)
	(4,2,1)	(4,1)
	(2,2,2)	(4,4)
	(2,8,1)	(4,1)
32	(4,4,1)	(4,1)
	(2,4,2)	(4,4)
	(4,2,2)	(4,4)

Each PMI value corresponds to the codebook indices i_1 and i_2 , where i_1 is the vector

$$i_1 = \begin{cases} \begin{bmatrix} i_{1,1} & i_{1,2} & i_{1,4} \end{bmatrix} & v = 1 \\ \begin{bmatrix} i_{1,1} & i_{1,2} & i_{1,3} & i_{1,4} \end{bmatrix} & v \in \{2, 3, 4\} \end{cases}$$

and v is the associated RI value. When *codebookMode* is set to '1', $i_{1,4}$ is

$$i_{1,4} = \begin{cases} i_{1,4,1} & N_g = 2 \\ \begin{bmatrix} i_{1,4,1} & i_{1,4,2} & i_{1,4,3} \end{bmatrix} & N_g = 4 \end{cases}$$

When *codebookMode* is set to '2', $i_{1,4}$ and i_2 are

$$i_{1,4} = \begin{bmatrix} i_{1,4,1} & i_{1,4,2} \end{bmatrix}$$

$$i_2 = \begin{bmatrix} i_{2,0} & i_{2,1} & i_{2,2} \end{bmatrix}$$

The mapping from $i_{1,3}$ to k_1 and k_2 for 2-layer reporting is given in Table 5.2.2.2.1-3. The mapping from $i_{1,3}$ to k_1 and k_2 for 3-layer and 4-layer reporting is given in Table 5.2.2.2.2-2.

- UE shall only use $i_{1,2} = 0$ and shall not report $i_{1,2}$ if the value of N_2 is 1.

Table 5.2.2.2-2: Mapping of $i_{1,3}$ to k_1 and k_2 for 3-layer and 4-layer CSI reporting

$i_{1,3}$	$N_1 = 2, N_2 = 1$		$N_1 = 4, N_2 = 1$		$N_1 = 8, N_2 = 1$		$N_1 = 2, N_2 = 2$		$N_1 = 4, N_2 = 2$	
	k_1	k_2	k_1	k_2	k_1	k_2	k_1	k_2	k_1	k_2
0	O_1	0	O_1	0	O_1	0	O_1	0	O_1	0
1			$2O_1$	0	$2O_1$	0	0	O_2	0	O_2
2			$3O_1$	0	$3O_1$	0	O_1	O_2	O_1	O_2
3					$4O_1$	0			$2O_1$	0

Several quantities are used to define the codebook elements. The quantities φ_n , a_p , b_n , u_m , and $v_{l,m}$ are given by

$$\begin{aligned}\varphi_n &= e^{j\pi n/2} \\ a_p &= e^{j\pi/4} e^{j\pi p/2} \\ b_n &= e^{-j\pi/4} e^{j\pi n/2} \\ u_m &= \begin{cases} \left[1 \quad e^{j\frac{2\pi m}{O_2 N_2}} \quad \dots \quad e^{j\frac{2\pi m(N_2-1)}{O_2 N_2}} \right] & N_2 > 1 \\ 1 & N_2 = 1 \end{cases} \\ v_{l,m} &= \left[u_m \quad e^{j\frac{2\pi l}{O_1 N_1}} u_m \quad \dots \quad e^{j\frac{2\pi l(N_1-1)}{O_1 N_1}} u_m \right]^T\end{aligned}$$

Furthermore, the quantities $W_{l,m,p,n}^{1,N_g,1}$ and $W_{l,m,p,n}^{2,N_g,1}$ ($N_g \in \{2,4\}$) are given by

$$\begin{aligned}W_{l,m,p,n}^{1,2,1} &= \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_n v_{l,m} \\ \varphi_{p_1} v_{l,m} \\ \varphi_n \varphi_{p_1} v_{l,m} \end{bmatrix} & W_{l,m,p,n}^{2,2,1} &= \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ -\varphi_n v_{l,m} \\ \varphi_{p_1} v_{l,m} \\ -\varphi_n \varphi_{p_1} v_{l,m} \end{bmatrix} \\ W_{l,m,p,n}^{1,4,1} &= \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_n v_{l,m} \\ \varphi_{p_1} v_{l,m} \\ \varphi_n \varphi_{p_1} v_{l,m} \\ \varphi_{p_2} v_{l,m} \\ \varphi_n \varphi_{p_2} v_{l,m} \\ \varphi_{p_3} v_{l,m} \\ \varphi_n \varphi_{p_3} v_{l,m} \end{bmatrix} & W_{l,m,p,n}^{2,4,1} &= \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ -\varphi_n v_{l,m} \\ \varphi_{p_1} v_{l,m} \\ -\varphi_n \varphi_{p_1} v_{l,m} \\ \varphi_{p_2} v_{l,m} \\ -\varphi_n \varphi_{p_2} v_{l,m} \\ \varphi_{p_3} v_{l,m} \\ -\varphi_n \varphi_{p_3} v_{l,m} \end{bmatrix}\end{aligned}$$

where

$$p = \begin{cases} p_1 & N_g = 2 \\ [p_1 \quad p_2 \quad p_3] & N_g = 4 \end{cases},$$

and the quantities $W_{l,m,p,n}^{1,N_g,2}$ and $W_{l,m,p,n}^{2,N_g,2}$ ($N_g = 2$) are given by

$$W_{l,m,p,n}^{1,2,2} = \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ \varphi_{n_0} v_{l,m} \\ a_{p_1} b_{n_1} v_{l,m} \\ a_{p_2} b_{n_2} v_{l,m} \end{bmatrix} \quad W_{l,m,p,n}^{2,2,2} = \frac{1}{\sqrt{P_{\text{CSI-RS}}}} \begin{bmatrix} v_{l,m} \\ -\varphi_{n_0} v_{l,m} \\ a_{p_1} b_{n_1} v_{l,m} \\ -a_{p_2} b_{n_2} v_{l,m} \end{bmatrix}$$

where

$$p = [p_1 \quad p_2]$$

$$n = [n_0 \quad n_1 \quad n_2]$$

The codebooks for 1-4 layers are given respectively in Tables 5.2.2.2.2-3, 5.2.2.2.2-4, 5.2.2.2.2-5, and 5.2.2.2.2-6.

Table 5.2.2.2.2-3: Codebook for 1-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1, $N_g \in \{2, 4\}$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, \dots, N_g - 1$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1, 2, 3	$W_{i_{1,1}, i_{1,2}, i_{1,4}, i_2}^{(1)}$
where $W_{l,m,p,n}^{(1)} = W_{l,m,p,n}^{1,N_g,1}$.				

codebookMode = 2, $N_g = 2$					
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, 2$	$i_{2,0}$	$i_{2,q}, q = 1, 2$	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,2}, i_{1,4}, i_2}^{(1)}$
where $W_{l,m,p,n}^{(1)} = W_{l,m,p,n}^{1,N_g,2}$.					

Table 5.2.2.2.2-4: Codebook for 2-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1, $N_g \in \{2, 4\}$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, \dots, N_g - 1$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1}+k_1, i_{1,2}, i_{1,2}+k_2, i_{1,4}, i_2}^{(2)}$
where $W_{l,l',m,m',p,n}^{(2)} = \frac{1}{\sqrt{2}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,1} & W_{l',m',p,n}^{2,N_g,1} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2.1-3.				

codebookMode = 2, $N_g = 2$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, 2$	$i_{2,q}, q = 0, 1, 2$	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1}+k_1, i_{1,2}, i_{1,2}+k_2, i_{1,4}, i_2}^{(2)}$
where $W_{l,l',m,m',p,n}^{(2)} = \frac{1}{\sqrt{2}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,2} & W_{l',m',p,n}^{2,N_g,2} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2.1-3.				

Table 5.2.2.2-5: Codebook for 3-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1, $N_g \in \{2, 4\}$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, \dots, N_g - 1$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1} + k_1, i_{1,2}, i_{1,2} + k_2, i_{1,4}, i_2}^{(3)}$
where $W_{l,l',m,m',p,n}^{(3)} = \frac{1}{\sqrt{3}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,1} & W_{l',m',p,n}^{1,N_g,1} & W_{l,m,p,n}^{2,N_g,1} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2-2.				

codebookMode = 2, $N_g = 2$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, 2$	$i_{2,q}, q = 0, 1, 2$	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1} + k_1, i_{1,2}, i_{1,2} + k_2, i_{1,4}, i_2}^{(3)}$
where $W_{l,l',m,m',p,n}^{(3)} = \frac{1}{\sqrt{3}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,2} & W_{l',m',p,n}^{1,N_g,2} & W_{l,m,p,n}^{2,N_g,2} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2-2.				

Table 5.2.2.2-6: Codebook for 4-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

codebookMode = 1, $N_g \in \{2, 4\}$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, \dots, N_g - 1$	i_2	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1} + k_1, i_{1,2}, i_{1,2} + k_2, i_{1,4}, i_2}^{(4)}$
where $W_{l,l',m,m',p,n}^{(4)} = \frac{1}{\sqrt{4}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,1} & W_{l',m',p,n}^{1,N_g,1} & W_{l,m,p,n}^{2,N_g,1} & W_{l',m',p,n}^{2,N_g,1} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2-2.				

codebookMode = 2, $N_g = 2$				
$i_{1,1}$	$i_{1,2}$	$i_{1,4,q}, q = 1, 2$	$i_{2,q}, q = 0, 1, 2$	
$0, \dots, N_1 O_1 - 1$	$0, \dots, N_2 O_2 - 1$	0, 1, 2, 3	0, 1	$W_{i_{1,1}, i_{1,1} + k_1, i_{1,2}, i_{1,2} + k_2, i_{1,4}, i_2}^{(4)}$
where $W_{l,l',m,m',p,n}^{(4)} = \frac{1}{\sqrt{4}} \begin{bmatrix} W_{l,m,p,n}^{1,N_g,2} & W_{l',m',p,n}^{1,N_g,2} & W_{l,m,p,n}^{2,N_g,2} & W_{l',m',p,n}^{2,N_g,2} \end{bmatrix}$ and the mapping from $i_{1,3}$ to k_1 and k_2 is given in Table 5.2.2.2-2.				

5.2.2.2.3 Type II Codebook

For 4 antenna ports {3000, 3001, ..., 3003}, 8 antenna ports {3000, 3001, ..., 3007}, 12 antenna ports {3000, 3001, ..., 3011}, 16 antenna ports {3000, 3001, ..., 3015}, 24 antenna ports {3000, 3001, ..., 3023}, and 32 antenna ports {3000, 3001, ..., 3031}, and the UE configured with higher layer parameter *codebookType* set to 'typeII'

- The values of N_1 and N_2 are configured with the higher layer parameter *n1-n2-codebookSubsetRestriction*. The supported configurations of (N_1, N_2) for a given number of CSI-RS ports and the corresponding values of (O_1, O_2) are given in Table 5.2.2.2.1-2. The number of CSI-RS ports, $P_{\text{CSI-RS}}$, is $2N_1N_2$.
- The value of L is configured with the higher layer parameter *numberOfBeams*, where $L = 2$ when $P_{\text{CSI-RS}} = 4$ and $L \in \{2, 3, 4\}$ when $P_{\text{CSI-RS}} > 4$.

- The value of N_{PSK} is configured with the higher layer parameter *phaseAlphabetSize*, where $N_{\text{PSK}} \in \{4, 8\}$.
- The UE is configured with the higher layer parameter *subbandAmplitude* set to 'true' or 'false'.
- The UE shall not report $\text{RI} > 2$.

When $\nu \leq 2$, where ν is the associated RI value, each PMI value corresponds to the codebook indices i_1 and i_2 where

$$i_1 = \begin{cases} [i_{1,1} & i_{1,2} & i_{1,3,1} & i_{1,4,1}] & \nu = 1 \\ [i_{1,1} & i_{1,2} & i_{1,3,1} & i_{1,4,1} & i_{1,3,2} & i_{1,4,2}] & \nu = 2 \end{cases}$$

$$i_2 = \begin{cases} [i_{2,1,1}] & \text{subbandAmplitude} = \text{'false'}, \nu = 1 \\ [i_{2,1,1} & i_{2,1,2}] & \text{subbandAmplitude} = \text{'false'}, \nu = 2 \\ [i_{2,1,1} & i_{2,2,1}] & \text{subbandAmplitude} = \text{'true'}, \nu = 1 \\ [i_{2,1,1} & i_{2,2,1} & i_{2,1,2} & i_{2,2,2}] & \text{subbandAmplitude} = \text{'true'}, \nu = 2 \end{cases}$$

The L vectors combined by the codebook are identified by the indices $i_{1,1}$ and $i_{1,2}$, where

$$i_{1,1} = [q_1 \quad q_2]$$

$$q_1 \in \{0, 1, \dots, O_1 - 1\}$$

$$q_2 \in \{0, 1, \dots, O_2 - 1\}$$

$$i_{1,2} \in \left\{ 0, 1, \dots, \binom{N_1 N_2}{L} - 1 \right\}.$$

Let

$$n_1 = [n_1^{(0)}, \dots, n_1^{(L-1)}]$$

$$n_2 = [n_2^{(0)}, \dots, n_2^{(L-1)}]$$

$$n_1^{(i)} \in \{0, 1, \dots, N_1 - 1\}$$

$$n_2^{(i)} \in \{0, 1, \dots, N_2 - 1\}$$

and

$$C(x, y) = \begin{cases} \begin{pmatrix} x \\ y \end{pmatrix} & x \geq y \\ 0 & x < y \end{cases}.$$

where the values of $C(x, y)$ are given in Table 5.2.2.2.3-1.

Then the elements of n_1 and n_2 are found from $i_{1,2}$ using the algorithm:

$$s_{-1} = 0$$

for $i = 0, \dots, L-1$

Find the largest $x^* \in \{L-1-i, \dots, N_1 N_2 - 1 - i\}$ in Table 5.2.2.2.3-1 such that $i_{1,2} - s_{i-1} \geq C(x^*, L-i)$

$$e_i = C(x^*, L-i)$$

$$s_i = s_{i-1} + e_i$$

$$n^{(i)} = N_1 N_2 - 1 - x^*$$

$$n_1^{(i)} = n^{(i)} \bmod N_1$$

$$n_2^{(i)} = \frac{\left(n^{(i)} - n_1^{(i)} \right)}{N_1}$$

When n_1 and n_2 are known, $i_{1,2}$ is found using:

$$n^{(i)} = N_1 n_2^{(i)} + n_1^{(i)} \text{ where the indices } i = 0, 1, \dots, L-1 \text{ are assigned such that } n^{(i)} \text{ increases as } i \text{ increases}$$

$$i_{1,2} = \sum_{i=0}^{L-1} C\left(N_1 N_2 - 1 - n^{(i)}, L - i\right), \text{ where } C(x, y) \text{ is given in Table 5.2.2.2.3-1.}$$

- If $N_2 = 1$, $q_2 = 0$ and $n_2^{(i)} = 0$ for $i = 0, 1, \dots, L-1$, and q_2 is not reported.
- When $(N_1, N_2) = (2, 1)$, $n_1 = [0, 1]$ and $n_2 = [0, 0]$, and $i_{1,2}$ is not reported.
- When $(N_1, N_2) = (4, 1)$ and $L = 4$, $n_1 = [0, 1, 2, 3]$ and $n_2 = [0, 0, 0, 0]$, and $i_{1,2}$ is not reported.
- When $(N_1, N_2) = (2, 2)$ and $L = 4$, $n_1 = [0, 1, 0, 1]$ and $n_2 = [0, 0, 1, 1]$, and $i_{1,2}$ is not reported.

Table 5.2.2.2.3-1: Combinatorial coefficients $C(x, y)$

$x \backslash y$	1	2	3	4
0	0	0	0	0
1	1	0	0	0
2	2	1	0	0
3	3	3	1	0
4	4	6	4	1
5	5	10	10	5
6	6	15	20	15
7	7	21	35	35
8	8	28	56	70
9	9	36	84	126
10	10	45	120	210
11	11	55	165	330
12	12	66	220	495
13	13	78	286	715
14	14	91	364	1001
15	15	105	455	1365

The strongest coefficient on layer l , $l = 1, \dots, \nu$ is identified by $i_{1,3,l} \in \{0, 1, \dots, 2L-1\}$.

The amplitude coefficient indicators $i_{1,4,l}$ and $i_{2,2,l}$ are

$$i_{1,4,l} = \left[k_{l,0}^{(1)}, k_{l,1}^{(1)}, \dots, k_{l,2L-1}^{(1)} \right]$$

$$i_{2,2,l} = \left[k_{l,0}^{(2)}, k_{l,1}^{(2)}, \dots, k_{l,2L-1}^{(2)} \right]$$

$$k_{l,i}^{(1)} \in \{0, 1, \dots, 7\}$$

$$k_{l,i}^{(2)} \in \{0, 1\}$$

for $l = 1, \dots, \nu$. The mapping from $k_{l,i}^{(1)}$ to the amplitude coefficient $p_{l,i}^{(1)}$ is given in Table 5.2.2.2.3-2 and the mapping from $k_{l,i}^{(2)}$ to the amplitude coefficient $p_{l,i}^{(2)}$ is given in Table 5.2.2.2.3-3. The amplitude coefficients are represented by

$$p_l^{(1)} = [p_{l,0}^{(1)}, p_{l,1}^{(1)}, \dots, p_{l,2L-1}^{(1)}]$$

$$p_l^{(2)} = [p_{l,0}^{(2)}, p_{l,1}^{(2)}, \dots, p_{l,2L-1}^{(2)}]$$

for $l = 1, \dots, \nu$.

Table 5.2.2.2.3-2: Mapping of elements of $i_{1,4,l}$: $k_{l,i}^{(1)}$ to $p_{l,i}^{(1)}$

$k_{l,i}^{(1)}$	$p_{l,i}^{(1)}$
0	0
1	$\sqrt{1/64}$
2	$\sqrt{1/32}$
3	$\sqrt{1/16}$
4	$\sqrt{1/8}$
5	$\sqrt{1/4}$
6	$\sqrt{1/2}$
7	1

Table 5.2.2.2.3-3: Mapping of elements of $i_{2,2,l}$: $k_{l,i}^{(2)}$ to $p_{l,i}^{(2)}$

$k_{l,i}^{(2)}$	$p_{l,i}^{(2)}$
0	$\sqrt{1/2}$
1	1

The phase coefficient indicators are

$$i_{2,1,l} = [c_{l,0}, c_{l,1}, \dots, c_{l,2L-1}]$$

for $l = 1, \dots, \nu$.

The amplitude and phase coefficient indicators are reported as follows:

- The indicators $k_{l,i_{1,3,l}}^{(1)} = 7$, $k_{l,i_{1,3,l}}^{(2)} = 1$, and $c_{l,i_{1,3,l}} = 0$ ($l = 1, \dots, \nu$). $k_{l,i_{1,3,l}}^{(1)}$, $k_{l,i_{1,3,l}}^{(2)}$, and $c_{l,i_{1,3,l}}$ are not reported for $l = 1, \dots, \nu$.
- The remaining $2L - 1$ elements of $i_{1,4,l}$ ($l = 1, \dots, \nu$) are reported, where $k_{l,i}^{(1)} \in \{0, 1, \dots, 7\}$. Let M_l ($l = 1, \dots, \nu$) be the number of elements of $i_{1,4,l}$ that satisfy $k_{l,i}^{(1)} > 0$.
- The remaining $2L - 1$ elements of $i_{2,1,l}$ and $i_{2,2,l}$ ($l = 1, \dots, \nu$) are reported as follows:
 - When *subbandAmplitude* is set to 'false',
 - $k_{l,i}^{(2)} = 1$ for $l = 1, \dots, \nu$, and $i = 0, 1, \dots, 2L - 1$. $i_{2,2,l}$ is not reported for $l = 1, \dots, \nu$.

- For $l = 1, \dots, v$, the elements of $i_{2,1,l}$ corresponding to the coefficients that satisfy $k_{l,i}^{(1)} > 0$, $i \neq i_{1,3,l}$, as determined by the reported elements of $i_{1,4,l}$, are reported, where $c_{l,i} \in \{0, 1, \dots, N_{\text{PSK}} - 1\}$ and the remaining $2L - M_l$ elements of $i_{2,1,l}$ are not reported and are set to $c_{l,i} = 0$.
- When *subbandAmplitude* is set to 'true',
 - For $l = 1, \dots, v$, the elements of $i_{2,2,l}$ and $i_{2,1,l}$ corresponding to the $\min(M_l, K^{(2)}) - 1$ strongest coefficients (excluding the strongest coefficient indicated by $i_{1,3,l}$), as determined by the corresponding reported elements of $i_{1,4,l}$, are reported, where $k_{l,i}^{(2)} \in \{0, 1\}$ and $c_{l,i} \in \{0, 1, \dots, N_{\text{PSK}} - 1\}$. The values of $K^{(2)}$ are given in Table 5.2.2.2.3-4. The remaining $2L - \min(M_l, K^{(2)})$ elements of $i_{2,2,l}$ are not reported and are set to $k_{l,i}^{(2)} = 1$. The elements of $i_{2,1,l}$ corresponding to the $M_l - \min(M_l, K^{(2)})$ weakest non-zero coefficients are reported, where $c_{l,i} \in \{0, 1, 2, 3\}$. The remaining $2L - M_l$ elements of $i_{2,1,l}$ are not reported and are set to $c_{l,i} = 0$.
 - When two elements, $k_{l,x}^{(1)}$ and $k_{l,y}^{(1)}$, of the reported elements of $i_{1,4,l}$ are identical ($k_{l,x}^{(1)} = k_{l,y}^{(1)}$), then element $\min(x, y)$ is prioritized to be included in the set of the $\min(M_l, K^{(2)}) - 1$ strongest coefficients for $i_{2,1,l}$ and $i_{2,2,l}$ ($l = 1, \dots, v$) reporting.

Table 5.2.2.2.3-4: Full resolution subband coefficients when *subbandAmplitude* is set to 'true'

L	$K^{(2)}$
2	4
3	4
4	6

The codebooks for 1-2 layers are given in Table 5.2.2.2.3-5, where the indices $m_1^{(i)}$ and $m_2^{(i)}$ are given by

$$m_1^{(i)} = O_1 n_1^{(i)} + q_1$$

$$m_2^{(i)} = O_2 n_2^{(i)} + q_2$$

for $i = 0, 1, \dots, L-1$, and the quantities $\varphi_{l,i}$, u_m , and $v_{l,m}$ are given by

$$\varphi_{l,i} = \begin{cases} e^{j2\pi c_{l,i}/N_{\text{PSK}}} & \text{subbandAmplitude = 'false'} \\ e^{j2\pi c_{l,i}/N_{\text{PSK}}} & \text{subbandAmplitude = 'true', } \min(M_l, K^{(2)}) \text{ strongest coefficients (including } i_{1,3,l} \text{) with } k_{l,i}^{(1)} > 0 \\ e^{j2\pi c_{l,i}/4} & \text{subbandAmplitude = 'true', } M_l - \min(M_l, K^{(2)}) \text{ weakest coefficients with } k_{l,i}^{(1)} > 0 \\ 1 & \text{subbandAmplitude = 'true', } 2L - M_l \text{ coefficients with } k_{l,i}^{(1)} = 0 \end{cases}$$

$$u_m = \begin{cases} \begin{bmatrix} 1 & e^{j\frac{2\pi m}{O_2 N_2}} & \dots & e^{j\frac{2\pi m(N_2-1)}{O_2 N_2}} \end{bmatrix} & N_2 > 1 \\ 1 & N_2 = 1 \end{cases}$$

$$v_{l,m} = \begin{bmatrix} u_m & e^{j\frac{2\pi l}{O_1 N_1} u_m} & \dots & e^{j\frac{2\pi l(N_1-1)}{O_1 N_1} u_m} \end{bmatrix}^T$$

Table 5.2.2.3-5: Codebook for 1-layer and 2-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

Layers	
$v = 1$	$W_{q_1, q_2, n_1, n_2, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^{(1)} = W_{q_1, q_2, n_1, n_2, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^1$
$v = 2$	$W_{q_1, q_2, n_1, n_2, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}, p_2^{(1)}, p_2^{(2)}, i_{2,1,2}}^{(2)} = \frac{1}{\sqrt{2}} \begin{bmatrix} W_{q_1, q_2, n_1, n_2, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^1 & W_{q_1, q_2, n_1, n_2, p_2^{(1)}, p_2^{(2)}, i_{2,1,2}}^2 \end{bmatrix}$
	<p>where $W_{q_1, q_2, n_1, n_2, p_1^{(1)}, p_1^{(2)}, c_l}^l = \frac{1}{\sqrt{N_1 N_2 \sum_{i=0}^{2L-1} (p_{l,i}^{(1)} p_{l,i}^{(2)})^2}} \begin{bmatrix} \sum_{i=0}^{L-1} v_{m_1^{(i)}, m_2^{(i)}} p_{l,i}^{(1)} p_{l,i}^{(2)} \varphi_{l,i} \\ \sum_{i=0}^{L-1} v_{m_1^{(i)}, m_2^{(i)}} p_{l,i+L}^{(1)} p_{l,i+L}^{(2)} \varphi_{l,i+L} \end{bmatrix}, l = 1, 2,$</p> <p>and the mappings from i_1 to $q_1, q_2, n_1, n_2, p_1^{(1)}$, and $p_2^{(1)}$, and from i_2 to $i_{2,1,1}, i_{2,1,2}, p_1^{(2)}$ and $p_2^{(2)}$ are as described above, including the ranges of the constituent indices of i_1 and i_2.</p>

When the UE is configured with higher layer parameter *codebookType* set to 'typeII', the bitmap parameter *typeII-RI-Restriction* forms the bit sequence r_1, r_0 where r_0 is the LSB and r_1 is the MSB. When r_i is zero, $i \in \{0, 1\}$, PMI and RI reporting are not allowed to correspond to any precoder associated with $v = i + 1$ layers. The bitmap parameter *n1-n2-codebookSubsetRestriction* forms the bit sequence $B = B_1 B_2$ where bit sequences B_1 , and B_2 are concatenated to form B . To define B_1 and B_2 , first define the $O_1 O_2$ vector groups $G(r_1, r_2)$ as

$$G(r_1, r_2) = \{v_{N_1 r_1 + x_1, N_2 r_2 + x_2} : x_1 = 0, 1, \dots, N_1 - 1; x_2 = 0, 1, \dots, N_2 - 1\}$$

for

$$\begin{aligned} r_1 &\in \{0, 1, \dots, O_1 - 1\} \\ r_2 &\in \{0, 1, \dots, O_2 - 1\} \end{aligned}$$

The UE shall be configured with restrictions for 4 vector groups indicated by $(r_1^{(k)}, r_2^{(k)})$ for $k = 0, 1, 2, 3$ and identified by the group indices

$$g^{(k)} = O_1 r_2^{(k)} + r_1^{(k)}$$

for $k = 0, 1, \dots, 3$, where the indices are assigned such that $g^{(k)}$ increases as k increases. The remaining vector groups are not restricted.

- If $N_2 = 1$, $g^{(k)} = k$ for $k = 0, 1, \dots, 3$, and B_1 is empty.
- If $N_2 > 1$, $B_1 = b_1^{(10)} \dots b_1^{(0)}$ is the binary representation of the integer β_1 where $b_1^{(10)}$ is the MSB and $b_1^{(0)}$ is the LSB. β_1 is found using:

$$\beta_1 = \sum_{k=0}^3 C(O_1 O_2 - 1 - g^{(k)}, 4 - k),$$

where $C(x, y)$ is defined in Table 5.2.2.2.3-1. The group indices $g^{(k)}$ and indicators $(r_1^{(k)}, r_2^{(k)})$ for $k = 0, 1, 2, 3$ may be found from β_1 using the algorithm:

$$\begin{aligned} s_{-1} &= 0 \\ \text{for } k &= 0, \dots, 3 \end{aligned}$$

Find the largest $x^* \in \{3-k, \dots, O_1 O_2 - 1 - k\}$ such that $\beta_1 - s_{k-1} \geq C(x^*, 4-k)$

$$e_k = C(x^*, 4-k)$$

$$s_k = s_{k-1} + e_k$$

$$g^{(k)} = O_1 O_2 - 1 - x^*$$

$$r_1^{(k)} = g^{(k)} \bmod O_1$$

$$r_2^{(k)} = \frac{(g^{(k)} - r_1^{(k)})}{O_1}$$

The bit sequence $B_2 = B_2^{(0)} B_2^{(1)} B_2^{(2)} B_2^{(3)}$ is the concatenation of the bit sequences $B_2^{(k)}$ for $k = 0, 1, \dots, 3$, corresponding to the group indices $g^{(k)}$. The bit sequence $B_2^{(k)}$ is defined as

$$B_2^{(k)} = b_2^{(k, 2N_1 N_2 - 1)} \dots b_2^{(k, 0)}$$

Bits $b_2^{(k, 2(N_1 x_2 + x_1) + 1)}$, $b_2^{(k, 2(N_1 x_2 + x_1))}$ indicate the maximum allowed amplitude coefficient $p_{l,i}^{(1)}$ for the vector in group $g^{(k)}$ indexed by x_1, x_2 , where the maximum amplitude coefficients are given in Table 5.2.2.2.3-6. A UE that does not report parameter *amplitudeSubsetRestriction* = 'supported' in its capability signaling is not expected to be configured with $b_2^{(k, 2(N_1 x_2 + x_1) + 1)}$, $b_2^{(k, 2(N_1 x_2 + x_1))} = 01$ or 10 .

Table 5.2.2.2.3-6: Maximum allowed amplitude coefficients for restricted vectors

Bits $b_2^{(k, 2(N_1 x_2 + x_1) + 1)}$, $b_2^{(k, 2(N_1 x_2 + x_1))}$	Maximum Amplitude Coefficient $p_{l,i}^{(1)}$
00	0
01	$\sqrt{1/4}$
10	$\sqrt{1/2}$
11	1

5.2.2.2.4 Type II Port Selection Codebook

For 4 antenna ports {3000, 3001, ..., 3003}, 8 antenna ports {3000, 3001, ..., 3007}, 12 antenna ports {3000, 3001, ..., 3011}, 16 antenna ports {3000, 3001, ..., 3015}, 24 antenna ports {3000, 3001, ..., 3023}, and 32 antenna ports {3000, 3001, ..., 3031}, and the UE configured with higher layer parameter *codebookType* set to 'typeII-PortSelection'

- The number of CSI-RS ports is given by $P_{\text{CSI-RS}} \in \{4, 8, 12, 16, 24, 32\}$ as configured by higher layer parameter *nrofPorts*.
- The value of L is configured with the higher layer parameter *numberOfBeams*, where $L = 2$ when $P_{\text{CSI-RS}} = 4$ and $L \in \{2, 3, 4\}$ when $P_{\text{CSI-RS}} > 4$.
- The value of d is configured with the higher layer parameter *portSelectionSamplingSize*, where $d \in \{1, 2, 3, 4\}$ and $d \leq \min\left(\frac{P_{\text{CSI-RS}}}{2}, L\right)$.
- The value of N_{PSK} is configured with the higher layer parameter *phaseAlphabetSize*, where $N_{\text{PSK}} \in \{4, 8\}$.
- The UE is configured with the higher layer parameter *subbandAmplitude* set to 'true' or 'false'.

- The UE shall not report $RI > 2$.

The UE is also configured with the higher layer parameter *typeII-PortSelectionRI-Restriction*. The bitmap parameter *typeII-PortSelectionRI-Restriction* forms the bit sequence r_1, r_0 where r_0 is the LSB and r_1 is the MSB. When r_i is zero, $i \in \{0,1\}$, PMI and RI reporting are not allowed to correspond to any precoder associated with $v = i + 1$ layers.

When $v \leq 2$, where v is the associated RI value, each PMI value corresponds to the codebook indices i_1 and i_2 where

$$i_1 = \begin{cases} [i_{1,1} & i_{1,3,1} & i_{1,4,1}] & v = 1 \\ [i_{1,1} & i_{1,3,1} & i_{1,4,1} & i_{1,3,2} & i_{1,4,2}] & v = 2 \end{cases}$$

$$i_2 = \begin{cases} [i_{2,1,1}] & \text{subbandAmplitude} = \text{'false'}, v = 1 \\ [i_{2,1,1} & i_{2,1,2}] & \text{subbandAmplitude} = \text{'false'}, v = 2 \\ [i_{2,1,1} & i_{2,2,1}] & \text{subbandAmplitude} = \text{'true'}, v = 1 \\ [i_{2,1,1} & i_{2,2,1} & i_{2,1,2} & i_{2,2,2}] & \text{subbandAmplitude} = \text{'true'}, v = 2 \end{cases}$$

The L antenna ports per polarization are selected by the index $i_{1,1}$, where

$$i_{1,1} \in \left\{ 0, 1, \dots, \left\lfloor \frac{P_{\text{CSI-RS}}}{2d} \right\rfloor - 1 \right\}.$$

The strongest coefficient on layer l , $l = 1, \dots, v$ is identified by $i_{1,3,l} \in \{0, 1, \dots, 2L-1\}$.

The amplitude coefficient indicators $i_{1,4,l}$ and $i_{2,2,l}$ are

$$i_{1,4,l} = [k_{l,0}^{(1)}, k_{l,1}^{(1)}, \dots, k_{l,2L-1}^{(1)}]$$

$$i_{2,2,l} = [k_{l,0}^{(2)}, k_{l,1}^{(2)}, \dots, k_{l,2L-1}^{(2)}]$$

$$k_{l,i}^{(1)} \in \{0, 1, \dots, 7\}$$

$$k_{l,i}^{(2)} \in \{0, 1\}$$

for $l = 1, \dots, v$. The mapping from $k_{l,i}^{(1)}$ to the amplitude coefficient $p_{l,i}^{(1)}$ is given in Table 5.2.2.2.3-2 and the mapping from $k_{l,i}^{(2)}$ to the amplitude coefficient $p_{l,i}^{(2)}$ is given in Table 5.2.2.2.3-3. The amplitude coefficients are represented by

$$p_l^{(1)} = [p_{l,0}^{(1)}, p_{l,1}^{(1)}, \dots, p_{l,2L-1}^{(1)}]$$

$$p_l^{(2)} = [p_{l,0}^{(2)}, p_{l,1}^{(2)}, \dots, p_{l,2L-1}^{(2)}]$$

for $l = 1, \dots, v$.

The phase coefficient indicators are

$$i_{2,1,l} = [c_{l,0}, c_{l,1}, \dots, c_{l,2L-1}]$$

for $l = 1, \dots, v$.

The amplitude and phase coefficient indicators are reported as follows:

- The indicators $k_{l,i_{1,3,l}}^{(1)} = 7$, $k_{l,i_{1,3,l}}^{(2)} = 1$, and $c_{l,i_{1,3,l}} = 0$ ($l = 1, \dots, v$). $k_{l,i_{1,3,l}}^{(1)}$, $k_{l,i_{1,3,l}}^{(2)}$, and $c_{l,i_{1,3,l}}$ are not reported for $l = 1, \dots, v$.

- The remaining $2L-1$ elements of $i_{1,4,l}$ ($l=1, \dots, \nu$) are reported, where $k_{l,i}^{(1)} \in \{0,1, \dots, 7\}$. Let M_l ($l=1, \dots, \nu$) be the number of elements of $i_{1,4,l}$ that satisfy $k_{l,i}^{(1)} > 0$.
- The remaining $2L-1$ elements of $i_{2,1,l}$ and $i_{2,2,l}$ ($l=1, \dots, \nu$) are reported as follows:
 - When *subbandAmplitude* is set to 'false',
 - $k_{l,i}^{(2)} = 1$ for $l=1, \dots, \nu$, and $i=0, 1, \dots, 2L-1$. $i_{2,2,l}$ is not reported for $l=1, \dots, \nu$.
 - For $l=1, \dots, \nu$, the M_l-1 elements of $i_{2,1,l}$ corresponding to the coefficients that satisfy $k_{l,i}^{(1)} > 0$, $i \neq i_{1,3,l}$, as determined by the reported elements of $i_{1,4,l}$, are reported, where $c_{l,i} \in \{0, 1, \dots, N_{\text{PSK}}-1\}$ and the remaining $2L-M_l$ elements of $i_{2,1,l}$ are not reported and are set to $c_{l,i} = 0$.
 - When *subbandAmplitude* is set to 'true',
 - For $l=1, \dots, \nu$, the elements of $i_{2,2,l}$ and $i_{2,1,l}$ corresponding to the $\min(M_l, K^{(2)})-1$ strongest coefficients (excluding the strongest coefficient indicated by $i_{1,3,l}$), as determined by the corresponding reported elements of $i_{1,4,l}$, are reported, where $k_{l,i}^{(2)} \in \{0, 1\}$ and $c_{l,i} \in \{0, 1, \dots, N_{\text{PSK}}-1\}$. The values of $K^{(2)}$ are given in Table 5.2.2.2.3-4. The remaining $2L-\min(M_l, K^{(2)})$ elements of $i_{2,2,l}$ are not reported and are set to $k_{l,i}^{(2)} = 1$. The elements of $i_{2,1,l}$ corresponding to the $M_l-\min(M_l, K^{(2)})$ weakest non-zero coefficients are reported, where $c_{l,i} \in \{0, 1, 2, 3\}$. The remaining $2L-M_l$ elements of $i_{2,1,l}$ are not reported and are set to $c_{l,i} = 0$.
 - When two elements, $k_{l,x}^{(1)}$ and $k_{l,y}^{(1)}$, of the reported elements of $i_{1,4,l}$ are identical ($k_{l,x}^{(1)} = k_{l,y}^{(1)}$), then element $\min(x, y)$ is prioritized to be included in the set of the $\min(M_l, K^{(2)})-1$ strongest coefficients for $i_{2,1,l}$ and $i_{2,2,l}$ ($l=1, \dots, \nu$) reporting.

The codebooks for 1-2 layers are given in Table 5.2.2.2.4-1, where the quantity $\varphi_{l,i}$ is given by

$$\varphi_{l,i} = \begin{cases} e^{j2\pi c_{l,i}/N_{\text{PSK}}} & \text{subbandAmplitude} = \text{'false'}$$

$$\left. \begin{cases} e^{j2\pi c_{l,i}/N_{\text{PSK}}} & \text{subbandAmplitude} = \text{'true'}, \min(M_l, K^{(2)}) \text{ strongest coefficients (including } i_{1,3,l}) \text{ with } k_{l,i}^{(1)} > 0 \\ e^{j2\pi c_{l,i}/4} & \text{subbandAmplitude} = \text{'true'}, M_l - \min(M_l, K^{(2)}) \text{ weakest coefficients with } k_{l,i}^{(1)} > 0 \\ 1 & \text{subbandAmplitude} = \text{'true'}, 2L - M_l \text{ coefficients with } k_{l,i}^{(1)} = 0 \end{cases} \right\}$$

and v_m is a $P_{\text{CSI-RS}}/2$ -element column vector containing a value of 1 in element $(m \bmod P_{\text{CSI-RS}}/2)$ and zeros elsewhere (where the first element is element 0).

Table 5.2.2.4-1: Codebook for 1-layer and 2-layer CSI reporting using antenna ports 3000 to 2999+ $P_{\text{CSI-RS}}$

Layers	
$v = 1$	$W_{i_1, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^{(1)} = W_{i_1, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^1$
$v = 2$	$W_{i_1, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}, p_2^{(1)}, p_2^{(2)}, i_{2,1,2}}^{(2)} = \frac{1}{\sqrt{2}} \begin{bmatrix} W_{i_1, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^1 & W_{i_1, p_2^{(1)}, p_2^{(2)}, i_{2,1,2}}^2 \end{bmatrix}$
	<p>where $W_{i_1, p_1^{(1)}, p_1^{(2)}, i_{2,1,1}}^l = \frac{1}{\sqrt{\sum_{i=0}^{2L-1} (p_{l,i}^{(1)} p_{l,i}^{(2)})^2}} \begin{bmatrix} \sum_{i=0}^{L-1} v_{i_1, d+i} p_{l,i}^{(1)} p_{l,i}^{(2)} \phi_{l,i} \\ \sum_{i=0}^{L-1} v_{i_1, d+i} p_{l,i+L}^{(1)} p_{l,i+L}^{(2)} \phi_{l,i+L} \end{bmatrix}, l = 1, 2,$</p> <p>and the mappings from i_1 to $i_{1,1}$, $p_1^{(1)}$, and $p_2^{(1)}$ and from i_2 to $i_{2,1,1}$, $i_{2,1,2}$, $p_1^{(2)}$, and $p_2^{(2)}$ are as described above, including the ranges of the constituent indices of i_1 and i_2.</p>

5.2.2.3 Reference signal (CSI-RS)

5.2.2.3.1 NZP CSI-RS

The UE can be configured with one or more NZP CSI-RS resource set configuration(s) as indicated by the higher layer parameters *CSI-ResourceConfig*, and *NZP-CSI-RS-ResourceSet*. Each NZP CSI-RS resource set consists of $K \geq 1$ NZP CSI-RS resource(s).

The following parameters for which the UE shall assume non-zero transmission power for CSI-RS resource are configured via the higher layer parameter *NZP-CSI-RS-Resource*, *CSI-ResourceConfig* and *NZP-CSI-RS-ResourceSet* for each CSI-RS resource configuration:

- *nzp-CSI-RS-ResourceId* determines CSI-RS resource configuration identity.
- *periodicityAndOffset* defines the CSI-RS periodicity and slot offset for periodic/semi-persistent CSI-RS. All the CSI-RS resources within one set are configured with the same periodicity, while the slot offset can be same or different for different CSI-RS resources.
- *resourceMapping* defines the number of ports, CDM-type, and OFDM symbol and subcarrier occupancy of the CSI-RS resource within a slot that are given in Clause 7.4.1.5 of [4, TS 38.211].
- *nrofPorts* in *resourceMapping* defines the number of CSI-RS ports, where the allowable values are given in Clause 7.4.1.5 of [4, TS 38.211].
- *density* in *resourceMapping* defines CSI-RS frequency density of each CSI-RS port per PRB, and CSI-RS PRB offset in case of the density value of 1/2, where the allowable values are given in Clause 7.4.1.5 of [4, TS 38.211]. For density 1/2, the odd/even PRB allocation indicated in *density* is with respect to the common resource block grid.
- *cdm-Type* in *resourceMapping* defines CDM values and pattern, where the allowable values are given in Clause 7.4.1.5 of [4, TS 38.211].
- *powerControlOffset*: which is the assumed ratio of PDSCH EPRE to NZP CSI-RS EPRE when UE derives CSI feedback and takes values in the range of [-8, 15] dB with 1 dB step size.
- *powerControlOffsetSS*: which is the assumed ratio of NZP CSI-RS EPRE to SS/PBCH block EPRE.
- *scramblingID* defines scrambling ID of CSI-RS with length of 10 bits.
- *BWP-Id* in *CSI-ResourceConfig* defines which bandwidth part the configured CSI-RS is located in.
- *repetition* in *NZP-CSI-RS-ResourceSet* is associated with a CSI-RS resource set and defines whether UE can assume the CSI-RS resources within the NZP CSI-RS Resource Set are transmitted with the same downlink

spatial domain transmission filter or not as described in Clause 5.1.6.1.2. and can be configured only when the higher layer parameter *reportQuantity* associated with all the reporting settings linked with the CSI-RS resource set is set to 'cri-RSRP' or 'none'.

- *qcl-InfoPeriodicCSI-RS* contains a reference to a *TCI-State* indicating QCL source RS(s) and QCL type(s). If the *TCI-State* is configured with a reference to an RS with 'QCL-TypeD' association, that RS may be an SS/PBCH block located in the same or different CC/DL BWP or a CSI-RS resource configured as periodic located in the same or different CC/DL BWP.
- *trs-Info* in *NZP-CSI-RS-ResourceSet* is associated with a CSI-RS resource set and for which the UE can assume that the antenna port with the same port index of the configured NZP CSI-RS resources in the *NZP-CSI-RS-ResourceSet* is the same as described in Clause 5.1.6.1.1 and can be configured when reporting setting is not configured or when the higher layer parameter *reportQuantity* associated with all the reporting settings linked with the CSI-RS resource set is set to 'none'.

All CSI-RS resources within one set are configured with same *density* and same *nrofPorts*, except for the NZP CSI-RS resources used for interference measurement.

The UE expects that all the CSI-RS resources of a resource set are configured with the same starting RB and number of RBs and the same *cdm-type*.

The bandwidth and initial common resource block (CRB) index of a CSI-RS resource within a BWP, as defined in Clause 7.4.1.5 of [4, TS 38.211], are determined based on the higher layer parameters *nrofRBs* and *startingRB*, respectively, within the CSI-FrequencyOccupation IE configured by the higher layer parameter *freqBand* within the *CSI-RS-ResourceMapping* IE. Both *nrofRBs* and *startingRB* are configured as integer multiples of 4 RBs, and the reference point for *startingRB* is CRB 0 on the common resource block grid. If $startingRB < N_{BWP}^{start}$, the UE shall assume that the initial CRB index of the CSI-RS resource is $N_{initial\ RB} = N_{BWP}^{start}$, otherwise $N_{initial\ RB} = startingRB$. If $nrofRBs > N_{BWP}^{size} + N_{BWP}^{start} - N_{initial\ RB}$, the UE shall assume that the bandwidth of the CSI-RS resource is $N_{CSI-RS}^{BW} = N_{BWP}^{size} + N_{BWP}^{start} - N_{initial\ RB}$, otherwise $N_{CSI-RS}^{BW} = nrofRBs$. In all cases, the UE shall expect that $N_{CSI-RS}^{BW} \geq \min(24, N_{BWP}^{size})$.

5.2.2.4 Channel State Information – Interference Measurement (CSI-IM)

The UE can be configured with one or more CSI-IM resource set configuration(s) as indicated by the higher layer parameter *CSI-IM-ResourceSet*. Each CSI-IM resource set consists of $K \geq 1$ CSI-IM resource(s).

The following parameters are configured via higher layer parameter *CSI-IM-Resource* for each CSI-IM resource configuration:

- *csi-IM-ResourceId* determines CSI-IM resource configuration identity
- *subcarrierLocation-p0* or *subcarrierLocation-p1* defines subcarrier occupancy of the CSI-IM resource within a slot for *csi-IM-ResourceElementPattern* set to 'pattern0' or 'pattern1', respectively.
- *symbolLocation-p0* or *symbolLocation-p1* defines OFDM symbol location of the CSI-IM resource within a slot for *csi-IM-ResourceElementPattern* set to 'pattern0' or 'pattern1', respectively.
- *periodicityAndOffset* defines the CSI-IM periodicity and slot offset for periodic/semi-persistent CSI-IM.
- *freqBand* includes parameters to enable configuration of frequency-occupancy of CSI-IM

In each of the PRBs configured by *freqBand*, the UE shall assume each CSI-IM resource is located in,

- resource elements $(k_{CSI-IM}, l_{CSI-IM}), (k_{CSI-IM}, l_{CSI-IM} + 1), (k_{CSI-IM} + 1, l_{CSI-IM})$ and $(k_{CSI-IM} + 1, l_{CSI-IM} + 1)$, if *csi-IM-ResourceElementPattern* is set to 'pattern0',
- resource elements $(k_{CSI-IM}, l_{CSI-IM}), (k_{CSI-IM} + 1, l_{CSI-IM}), (k_{CSI-IM} + 2, l_{CSI-IM})$ and $(k_{CSI-IM} + 3, l_{CSI-IM})$ if *csi-IM-ResourceElementPattern* is set to 'pattern1',

where k_{CSI-IM} and l_{CSI-IM} are the configured frequency-domain location and time-domain location, respectively, given by the higher layer parameters in the above list.

5.2.2.5 CSI reference resource definition

The CSI reference resource for a serving cell is defined as follows:

- In the frequency domain, the CSI reference resource is defined by the group of downlink physical resource blocks corresponding to the band to which the derived CSI relates.
- In the time domain, the CSI reference resource for a CSI reporting in uplink slot n' is defined by a single downlink slot $n - n_{CSI_ref}$,
 - where $n = \left\lceil n' \cdot \frac{2^{\mu_{DL}}}{2^{\mu_{UL}}} \right\rceil$ and μ_{DL} and μ_{UL} are the subcarrier spacing configurations for DL and UL, respectively
 - where for periodic and semi-persistent CSI reporting
 - if a single CSI-RS/SSB resource is configured for channel measurement n_{CSI_ref} is the smallest value greater than or equal to $4 \cdot 2^{\mu_{DL}}$, such that it corresponds to a valid downlink slot, or
 - if multiple CSI-RS/SSB resources are configured for channel measurement n_{CSI_ref} is the smallest value greater than or equal to $5 \cdot 2^{\mu_{DL}}$, such that it corresponds to a valid downlink slot.
 - where for aperiodic CSI reporting, if the UE is indicated by the DCI to report CSI in the same slot as the CSI request, n_{CSI_ref} is such that the reference resource is in the same valid downlink slot as the corresponding CSI request, otherwise n_{CSI_ref} is the smallest value greater than or equal to $\left\lfloor Z' / N_{symbol}^{slot} \right\rfloor$, such that slot $n - n_{CSI_ref}$ corresponds to a valid downlink slot, where Z' corresponds to the delay requirement as defined in Clause 5.4.
 - when periodic or semi-persistent CSI-RS/CSI-IM or SSB is used for channel/interference measurements, the UE is not expected to measure channel/interference on the CSI-RS/CSI-IM/SSB whose last OFDM symbol is received up to Z' symbols before transmission time of the first OFDM symbol of the aperiodic CSI reporting.

A slot in a serving cell shall be considered to be a valid downlink slot if:

- it comprises at least one higher layer configured downlink or flexible symbol, and
- it does not fall within a configured measurement gap for that UE

If there is no valid downlink slot for the CSI reference resource corresponding to a CSI Report Setting in a serving cell, CSI reporting is omitted for the serving cell in uplink slot n' .

After the CSI report (re)configuration, serving cell activation, BWP change, or activation of SP-CSI, the UE reports a CSI report only after receiving at least one CSI-RS transmission occasion for channel measurement and CSI-RS and/or CSI-IM occasion for interference measurement no later than CSI reference resource and drops the report otherwise.

When DRX is configured, the UE reports a CSI report only if receiving at least one CSI-RS transmission occasion for channel measurement and CSI-RS and/or CSI-IM occasion for interference measurement in DRX Active Time no later than CSI reference resource and drops the report otherwise.

When deriving CSI feedback, the UE is not expected that a NZP CSI -RS resource for channel measurement overlaps with CSI-IM resource for interference measurement or NZP CSI -RS resource for interference measurement.

If configured to report CQI index, in the CSI reference resource, the UE shall assume the following for the purpose of deriving the CQI index, and if also configured, for deriving PMI and RI:

- The first 2 OFDM symbols are occupied by control signaling.
- The number of PDSCH and DM-RS symbols is equal to 12.
- The same bandwidth part subcarrier spacing configured as for the PDSCH reception
- The bandwidth as configured for the corresponding CQI report.
- The reference resource uses the CP length and subcarrier spacing configured for PDSCH reception
- No resource elements used by primary or secondary synchronization signals or PBCH.

- Redundancy Version 0.
- The ratio of PDSCH EPRE to CSI-RS EPRE is as given in Clause 4.1.
- Assume no REs allocated for NZP CSI-RS and ZP CSI-RS.
- Assume the same number of front loaded DM-RS symbols as the maximum front-loaded symbols configured by the higher layer parameter *maxLength* in *DMRS-DownlinkConfig*.
- Assume the same number of additional DM-RS symbols as the additional symbols configured by the higher layer parameter *dmrs-AdditionalPosition*.
- Assume the PDSCH symbols are not containing DM-RS.
- Assume PRB bundling size of 2 PRBs.
- The PDSCH transmission scheme where the UE may assume that PDSCH transmission would be performed with up to 8 transmission layers as defined in Clause 7.3.1.4 of [4, TS 38.211]. For CQI calculation, the UE should assume that PDSCH signals on antenna ports in the set [1000, ..., 1000+v-1] for v layers would result in signals equivalent to corresponding symbols transmitted on antenna ports [3000, ..., 3000+P-1], as given by

$$\begin{bmatrix} y^{(3000)}(i) \\ \dots \\ y^{(3000+P-1)}(i) \end{bmatrix} = W(i) \begin{bmatrix} x^{(0)}(i) \\ \dots \\ x^{(v-1)}(i) \end{bmatrix}$$

where $x(i) = [x^{(0)}(i) \dots x^{(v-1)}(i)]^T$ is a vector of PDSCH symbols from the layer mapping defined in Clause 7.3.1.4 of [4, TS 38.211], $P \in [1, 2, 4, 8, 12, 16, 24, 32]$ is the number of CSI-RS ports. If only one CSI-RS port is configured, $W(i)$ is 1. If the higher layer parameter *reportQuantity* in *CSI-ReportConfig* for which the CQI is reported is set to either 'cri-RI-PMI-CQI' or 'cri-RI-LI-PMI-CQI', $W(i)$ is the precoding matrix corresponding to the reported PMI applicable to $x(i)$. If the higher layer parameter *reportQuantity* in *CSI-ReportConfig* for which the CQI is reported is set to 'cri-RI-CQI', $W(i)$ is the precoding matrix corresponding to the procedure described in Clause 5.2.1.4.2. If the higher layer parameter *reportQuantity* in *CSI-ReportConfig* for which the CQI is reported is set to 'cri-RI-i1-CQI', $W(i)$ is the precoding matrix corresponding to the reported i1 according to the procedure described in Clause 5.2.1.4.2. The corresponding PDSCH signals transmitted on antenna ports [3000, ..., 3000 + P - 1] would have a ratio of EPRE to CSI-RS EPRE equal to the ratio given in Clause 5.2.2.3.1.

5.2.3 CSI reporting using PUSCH

A UE shall perform aperiodic CSI reporting using PUSCH on serving cell c upon successful decoding of a DCI format 0_1 which triggers an aperiodic CSI trigger state.

An aperiodic CSI report carried on the PUSCH supports wideband, and sub-band frequency granularities. An aperiodic CSI report carried on the PUSCH supports Type I and Type II CSI.

A UE shall perform semi-persistent CSI reporting on the PUSCH upon successful decoding of a DCI format 0_1 which activates a semi-persistent CSI trigger state. DCI format 0_1 contains a CSI request field which indicates the semi-persistent CSI trigger state to activate or deactivate. Semi-persistent CSI reporting on the PUSCH supports Type I and Type II CSI with wideband, and sub-band frequency granularities. The PUSCH resources and MCS shall be allocated semi-persistently by an uplink DCI.

CSI reporting on PUSCH can be multiplexed with uplink data on PUSCH except that semi-persistent CSI reporting on PUSCH activated by a DCI format is not expected to be multiplexed with uplink data on the PUSCH. CSI reporting on PUSCH can also be performed without any multiplexing with uplink data from the UE.

Type I CSI feedback is supported for CSI Reporting on PUSCH. Type I wideband and sub-band CSI is supported for CSI Reporting on the PUSCH. Type II CSI is supported for CSI Reporting on the PUSCH.

For Type I and Type II CSI feedback on PUSCH, a CSI report comprises of two parts. Part 1 has a fixed payload size and is used to identify the number of information bits in Part 2. Part 1 shall be transmitted in its entirety before Part 2.

- For Type I CSI feedback, Part 1 contains RI (if reported), CRI (if reported), CQI for the first codeword (if reported). Part 2 contains PMI (if reported) and contains the CQI for the second codeword (if reported) when RI (if reported) is larger than 4.

- For Type II CSI feedback, Part 1 contains RI (if reported), CQI, and an indication of the number of non-zero wideband amplitude coefficients per layer for the Type II CSI (see Clause 5.2.2). The fields of Part 1 – RI (if reported), CQI, and the indication of the number of non-zero wideband amplitude coefficients for each layer – are separately encoded. Part 2 contains the PMI of the Type II CSI. Part 1 and 2 are separately encoded.

A Type II CSI report that is carried on the PUSCH shall be computed independently from any Type II CSI report that is carried on the PUCCH formats 3 or 4 (see Clause 5.2.4 and 5.2.2).

When the higher layer parameter *reportQuantity* is configured with one of the values 'cri-RSRP' or 'ssb-Index-RSRP', the CSI feedback consists of a single part.

For both Type I and Type II reports configured for PUCCH but transmitted on PUSCH, the determination of the payload for CSI part 1 and CSI part 2 follows that of PUCCH as described in Clause 5.2.4.

When CSI reporting on PUSCH comprises two parts, the UE may omit a portion of the Part 2 CSI. Omission of Part 2 CSI is according to the priority order shown in Table 5.2.3-1, where N_{Rep} is the number of CSI reports configured to be carried on the PUSCH. Priority 0 is the highest priority and priority $2N_{\text{Rep}}$ is the lowest priority and the CSI report n corresponds to the CSI report with the n th smallest $\text{Pri}_{i,\text{CSI}}(y,k,c,s)$ value among the N_{Rep} CSI reports as defined in Clause 5.2.5. The subbands for a given CSI report n indicated by the higher layer parameter *csi-ReportingBand* are numbered continuously in increasing order with the lowest subband of *csi-ReportingBand* as subband 0. When omitting Part 2 CSI information for a particular priority level, the UE shall omit all of the information at that priority level.

Table 5.2.3-1: Priority reporting levels for Part 2 CSI

Priority 0: Part 2 wideband CSI for CSI reports 1 to N_{Rep}
Priority 1: Part 2 subband CSI of even subbands for CSI report 1
Priority 2: Part 2 subband CSI of odd subbands for CSI report 1
Priority 3: Part 2 subband CSI of even subbands for CSI report 2
Priority 4: Part 2 subband CSI of odd subbands for CSI report 2
⋮
Priority $2N_{\text{Rep}} - 1$: Part 2 subband CSI of even subbands for CSI report N_{Rep}
Priority $2N_{\text{Rep}}$: Part 2 subband CSI of odd subbands for CSI report N_{Rep}

When the UE is scheduled to transmit a transport block on PUSCH multiplexed with a CSI report(s), Part 2 CSI is

omitted only when $\left[(O_{\text{CSI-2}} + L_{\text{CSI-2}}) \cdot \beta_{\text{offset}}^{\text{PUSCH}} \cdot \sum_{l=0}^{N_{\text{sym_all}}^{\text{PUSCH}}-1} M_{\text{sc}}^{\text{UCI}}(l) / \sum_{r=0}^{C_{\text{UL-SCH}}-1} K_r \right]$ is larger than

$$\left[\alpha \cdot \sum_{l=0}^{N_{\text{sym_all}}^{\text{PUSCH}}-1} M_{\text{sc}}^{\text{UCI}}(l) \right] - Q'_{\text{ACK}} - Q'_{\text{CSI-1}}, \text{ where parameters } O_{\text{CSI-2}}, L_{\text{CSI-2}}, \beta_{\text{offset}}^{\text{PUSCH}}, N_{\text{sym_all}}^{\text{PUSCH}}, M_{\text{sc}}^{\text{UCI}}(l), C_{\text{UL-SCH}}, K_r,$$

$Q'_{\text{CSI-1}}$, Q'_{ACK} and α are defined in Clause 6.3.2.4 of [5, TS 38.212].

Part 2 CSI is omitted level by level, beginning with the lowest priority level until the lowest priority level is reached

which causes the $\left[(O_{\text{CSI-2}} + L_{\text{CSI-2}}) \cdot \beta_{\text{offset}}^{\text{PUSCH}} \cdot \sum_{l=0}^{N_{\text{sym_all}}^{\text{PUSCH}}-1} M_{\text{sc}}^{\text{UCI}}(l) / \sum_{r=0}^{C_{\text{UL-SCH}}-1} K_r \right]$ to be less than or equal to

$$\left[\alpha \cdot \sum_{l=0}^{N_{\text{sym_all}}^{\text{PUSCH}}-1} M_{\text{sc}}^{\text{UCI}}(l) \right] - Q'_{\text{ACK}} - Q'_{\text{CSI-1}}.$$

When part 2 CSI is transmitted on PUSCH with no transport block, lower priority bits are omitted until Part 2 CSI code rate, which is given by $(O_{\text{CSI-2}} + L_{\text{CSI-2}})/(N_L \cdot Q'_{\text{CSI,2}} \cdot Q_m)$ where $O_{\text{CSI-2}}$, $L_{\text{CSI-2}}$, N_L , $Q'_{\text{CSI,2}}$, Q_m are given in clause 6.3.2.4 of [5, 38.212] before HARQ-ACK puncturing part 2 CSI if any, is below a threshold code rate c_T lower than one, where

$$c_T = \frac{R}{\beta_{\text{offset}}^{\text{CSI-part2}}}$$

- $\beta_{\text{offset}}^{\text{CSI-part2}}$ is the CSI offset value from Table 9.3-2 of [6, TS 38.213]
- R is signaled code rate in DCI

If the UE is in an active semi-persistent CSI reporting configuration on PUSCH, the CSI reporting is deactivated when either the downlink BWP or the uplink BWP is changed. Another activation command is required to enable the semi-persistent CSI reporting.

5.2.4 CSI reporting using PUCCH

A UE is semi-statically configured by higher layers to perform periodic CSI Reporting on the PUCCH. A UE can be configured by higher layers for multiple periodic CSI Reports corresponding to multiple higher layer configured CSI Reporting Settings, where the associated CSI Resource Settings are higher layer configured. Periodic CSI reporting on PUCCH formats 2, 3, 4 supports Type I CSI with wideband granularity.

A UE shall perform semi-persistent CSI reporting on the PUCCH applied starting from the first slot that is after slot $n + 3N_{\text{slot}}^{\text{subframe},\mu}$ when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the activation command described in clause 6.1.3.16 of [10, TS 38.321] where μ is the SCS configuration for the PUCCH. The activation command will contain one or more Reporting Settings where the associated CSI Resource Settings are configured. Semi-persistent CSI reporting on the PUCCH supports Type I CSI. Semi-persistent CSI reporting on the PUCCH format 2 supports Type I CSI with wideband frequency granularity. Semi-persistent CSI reporting on PUCCH formats 3 or 4 supports Type I CSI with wideband and sub-band frequency granularities and Type II CSI Part 1.

When the PUCCH carry Type I CSI with wideband frequency granularity, the CSI payload carried by the PUCCH format 2 and PUCCH formats 3, or 4 are identical and the same irrespective of RI (if reported), CRI (if reported). For type I CSI sub-band reporting on PUCCH formats 3, or 4, the payload is split into two parts. The first part contains RI (if reported), CRI (if reported), CQI for the first codeword. The second part contains PMI and contains the CQI for the second codeword when RI > 4.

A semi-persistent report carried on the PUCCH formats 3 or 4 supports Type II CSI feedback, but only Part 1 of Type II CSI feedback (See Clause 5.2.2 and 5.2.3). Supporting Type II CSI reporting on the PUCCH formats 3 or 4 is a UE capability *type2-SP-CSI-Feedback-LongPUCCH*. A Type II CSI report (Part 1 only) carried on PUCCH formats 3 or 4 shall be calculated independently of any Type II CSI reports carried on the PUSCH (see Clause 5.2.3).

When the UE is configured with CSI Reporting on PUCCH formats 2, 3 or 4, each PUCCH resource is configured for each candidate UL BWP.

If the UE is in an active semi-persistent CSI reporting configuration on PUCCH and has not received a deactivation command, the CSI reporting takes place when the BWP in which the reporting is configured to take place is the active BWP, otherwise the CSI reporting is suspended.

A UE is not expected to report CSI with a total number of UCI bits and CRC bits larger than 115 bits when configured with PUCCH format 4. For CSI reports transmitted on a PUCCH, if all CSI reports consist of one part, the UE may omit a portion of CSI reports. Omission of CSI is according to the priority order determined from the $\text{Pri}_{i,\text{CSI}}(y,k,c,s)$ value as defined in Clause 5.2.5. CSI report is omitted beginning with the lowest priority level until the CSI report code rate is less or equal to the one configured by the higher layer parameter *maxCodeRate*.

If any of the CSI reports consist of two parts, the UE may omit a portion of Part 2 CSI. Omission of Part 2 CSI is according to the priority order shown in Table 5.2.3-1. Part 2 CSI is omitted beginning with the lowest priority level until the Part 2 CSI code rate is less or equal to the one configured by higher layer parameter *maxCodeRate*.

5.2.5 Priority rules for CSI reports

CSI reports are associated with a priority value $\text{Pri}_{i\text{CSI}}(y, k, c, s) = 2 \cdot N_{\text{cells}} \cdot M_s \cdot y + N_{\text{cells}} \cdot M_s \cdot k + M_s \cdot c + s$ where

- $y = 0$ for aperiodic CSI reports to be carried on PUSCH $y = 1$ for semi-persistent CSI reports to be carried on PUSCH, $y = 2$ for semi-persistent CSI reports to be carried on PUCCH and $y = 3$ for periodic CSI reports to be carried on PUCCH;
- $k = 0$ for CSI reports carrying L1-RSRP and $k = 1$ for CSI reports not carrying L1-RSRP;
- c is the serving cell index and N_{cells} is the value of the higher layer parameter *maxNrofServingCells*;
- s is the *reportConfigID* and M_s is the value of the higher layer parameter *maxNrofCSI-ReportConfigurations*.

A first CSI report is said to have priority over second CSI report if the associated $\text{Pri}_{i\text{CSI}}(y, k, c, s)$ value is lower for the first report than for the second report.

Two CSI reports are said to collide if the time occupancy of the physical channels scheduled to carry the CSI reports overlap in at least one OFDM symbol and are transmitted on the same carrier. When a UE is configured to transmit two colliding CSI reports,

- if y values are different between the two CSI reports, the following rules apply except for the case when one of the y value is 2 and the other y value is 3 (for CSI reports transmitted on PUSCH, as described in Clause 5.2.3; for CSI reports transmitted on PUCCH, as described in Clause 5.2.4):
 - The CSI report with higher $\text{Pri}_{i\text{CSI}}(y, k, c, s)$ value shall not be sent by the UE.
- otherwise, the two CSI reports are multiplexed or either is dropped based on the priority values, as described in Clause 9.2.5.2 in [6, TS 38.213].

If a semi-persistent CSI report to be carried on PUSCH overlaps in time with PUSCH data transmission in one or more symbols on the same carrier, and if the earliest symbol of these PUSCH channels starts no earlier than $N_2 + d_{2,1}$ symbols after the last symbol of the DCI scheduling the PUSCH where $d_{2,1}$ is the maximum of the $d_{2,1}$ associated with the PUSCH carrying semi-persistent CSI report and the PUSCH with data transmission, the CSI report shall not be transmitted by the UE. Otherwise, if the timeline requirement is not satisfied this is an error case.

If a UE would transmit a first PUSCH that includes semi-persistent CSI reports and a second PUSCH that includes an UL-SCH and the first PUSCH transmission would overlap in time with the second PUSCH transmission, the UE does not transmit the first PUSCH and transmits the second PUSCH. The UE expects that the first and second PUSCH transmissions satisfy the above timing conditions for PUSCH transmissions that overlap in time when at least one of the first or second PUSCH transmissions is in response to a DCI format detection by the UE.

5.3 UE PDSCH processing procedure time

If the first uplink symbol of the PUCCH which carries the HARQ-ACK information, as defined by the assigned HARQ-ACK timing K_I and the PUCCH resource to be used and including the effect of the timing advance, starts no earlier than at symbol L_I , where L_I is defined as the next uplink symbol with its CP starting after

$T_{\text{proc},1} = (N_1 + d_{1,1})(2048 + 144) \cdot \kappa 2^{-\mu} \cdot T_C$ after the end of the last symbol of the PDSCH carrying the TB being acknowledged, then the UE shall provide a valid HARQ-ACK message.

- N_1 is based on μ of table 5.3-1 and table 5.3-2 for UE processing capability 1 and 2 respectively, where μ corresponds to the one of $(\mu_{\text{PDCCH}}, \mu_{\text{PDSCH}}, \mu_{\text{UL}})$ resulting with the largest $T_{\text{proc},1}$, where the μ_{PDCCH} corresponds to the subcarrier spacing of the PDCCH scheduling the PDSCH, the μ_{PDSCH} corresponds to the subcarrier spacing of the scheduled PDSCH, and μ_{UL} corresponds to the subcarrier spacing of the uplink channel with which the HARQ-ACK is to be transmitted, and κ is defined in clause 4.1 of [4, TS 38.211].
- If the PDSCH DM-RS position l_1 for the additional DM-RS in Table 7.4.1.1.2-3 in clause 7.4.1.1.2 of [4, TS 38.211] is $l_1 = 12$ then $N_{1,0} = 14$ in Table 5.3-1, otherwise $N_{1,0} = 13$.

- If the UE is configured with multiple active component carriers, the first uplink symbol which carries the HARQ-ACK information further includes the effect of timing difference between the component carriers as given in [11, TS 38.133].
- For the PDSCH mapping type A as given in clause 7.4.1.1 of [4, TS 38.211]: if the last symbol of PDSCH is on the i -th symbol of the slot where $i < 7$, then $d_{l,l} = 7 - i$, otherwise $d_{l,l} = 0$
- For UE processing capability 1: If the PDSCH is mapping type B as given in clause 7.4.1.1 of [4, TS 38.211], and
 - if the number of PDSCH symbols allocated is 7, then $d_{l,l} = 0$,
 - if the number of PDSCH symbols allocated is 4, then $d_{l,l} = 3$
 - if the number of PDSCH symbols allocated is 2, then $d_{l,l} = 3 + d$, where d is the number of overlapping symbols of the scheduling PDCCH and the scheduled PDSCH.
- For UE processing capability 2: If the PDSCH is mapping type B as given in clause 7.4.1.1 of [4, TS 38.211],
 - if the number of PDSCH symbols allocated is 7, then $d_{l,l} = 0$,
 - if the number of PDSCH symbols allocated is 4, then $d_{l,l}$ is the number of overlapping symbols of the scheduling PDCCH and the scheduled PDSCH,
 - if the number of PDSCH symbols allocated is 2,
 - if the scheduling PDCCH was in a 3-symbol CORESET and the CORESET and the PDSCH had the same starting symbol, then $d_{l,l} = 3$,
 - otherwise $d_{l,l}$ is the number of overlapping symbols of the scheduling PDCCH and the scheduled PDSCH.
- For UE processing capability 2 with scheduling limitation when $\mu_{PDSCH} = 1$, if the scheduled RB allocation exceeds 136 RBs, the UE defaults to capability 1 processing time. The UE may skip decoding a number of PDSCHs with last symbol within 10 symbols before the start of a PDSCH that is scheduled to follow Capability 2, if any of those PDSCHs are scheduled with more than 136 RBs with 30kHz SCS and following Capability 1 processing time.
- For a UE that supports capability 2 on a given cell, the processing time according to UE processing capability 2 is applied if the high layer parameter *processingType2Enabled* in *PDSCH-ServingCellConfig* is configured for the cell and set to *enable*.
- If this PUCCH resource is overlapping with another PUCCH or PUSCH resource, then HARQ-ACK is multiplexed following the procedure in clause 9.2.5 of [6, TS 38.213], otherwise the HARQ-ACK message is transmitted on PUCCH.

Otherwise the UE may not provide a valid HARQ-ACK corresponding to the scheduled PDSCH. The value of $T_{proc,1}$ is used both in the case of normal and extended cyclic prefix.

Table 5.3-1: PDSCH processing time for PDSCH processing capability 1

μ	PDSCH decoding time N_1 [symbols]	
	<i>dmrs-AdditionalPosition</i> = pos0 in <i>DMRS-DownlinkConfig</i> in both of <i>dmrs-DownlinkForPDSCH-MappingTypeA</i> , <i>dmrs-DownlinkForPDSCH-MappingTypeB</i>	<i>dmrs-AdditionalPosition</i> ≠ pos0 in <i>DMRS-DownlinkConfig</i> in either of <i>dmrs-DownlinkForPDSCH-MappingTypeA</i> , <i>dmrs-DownlinkForPDSCH-MappingTypeB</i> or if the higher layer parameter is not configured
0	8	$N_{1,0}$
1	10	13
2	17	20
3	20	24

Table 5.3-2: PDSCH processing time for PDSCH processing capability 2

μ	PDSCH decoding time N_T [symbols]
	<i>dmrs-AdditionalPosition</i> = pos0 in <i>DMRS-DownlinkConfig</i> in both of <i>dmrs-DownlinkForPDSCH-MappingTypeA</i> , <i>dmrs-DownlinkForPDSCH-MappingTypeB</i>
0	3
1	4.5
2	9 for frequency range 1

5.4 UE CSI computation time

When the *CSI request* field on a DCI triggers a CSI report(s) on PUSCH, the UE shall provide a valid CSI report for the n -th triggered report,

- if the first uplink symbol to carry the corresponding CSI report(s) including the effect of the timing advance, starts no earlier than at symbol Z_{ref} , and
- if the first uplink symbol to carry the n -th CSI report including the effect of the timing advance, starts no earlier than at symbol $Z'_{ref}(n)$,

where Z_{ref} is defined as the next uplink symbol with its CP starting $T_{proc,CSI} = (Z)(2048+144) \cdot \kappa 2^{-\mu} \cdot T_C$ after the end of the last symbol of the PDCCH triggering the CSI report(s), and where $Z'_{ref}(n)$, is defined as the next uplink symbol with its CP starting $T'_{proc,CSI} = (Z')(2048+144) \cdot \kappa 2^{-\mu} \cdot T_C$ after the end of the last symbol in time of the latest of: aperiodic CSI-RS resource for channel measurements, aperiodic CSI-IM used for interference measurements, and aperiodic NZP CSI-RS for interference measurement, when aperiodic CSI-RS is used for channel measurement for the n -th triggered CSI report.

If the PUSCH indicated by the DCI is overlapping with another PUCCH or PUSCH, then the CSI report(s) are multiplexed following the procedure in clause 9.2.5 of [6, TS 38.213] and clause 5.2.5 when applicable, otherwise the CSI report(s) are transmitted on the PUSCH indicated by the DCI.

When the *CSI request* field on a DCI triggers a CSI report(s) on PUSCH, if the first uplink symbol to carry the corresponding CSI report(s) including the effect of the timing advance, starts earlier than at symbol Z_{ref} ,

- the UE may ignore the scheduling DCI if no HARQ-ACK or transport block is multiplexed on the PUSCH.

When the *CSI request* field on a DCI triggers a CSI report(s) on PUSCH, if the first uplink symbol to carry the n -th CSI report including the effect of the timing advance, starts earlier than at symbol $Z'_{ref}(n)$,

- the UE may ignore the scheduling DCI if the number of triggered reports is one and no HARQ-ACK or transport block is multiplexed on the PUSCH
- Otherwise, the UE is not required to update the CSI for the n -th triggered CSI report.

Z , Z' and μ are defined as:

$Z = \max_{m=0, \dots, M-1} (Z(m))$ and $Z' = \max_{m=0, \dots, M-1} (Z'(m))$, where M is the number of updated CSI report(s) according to Clause 5.2.1.6, $(Z(m), Z'(m))$ corresponds to the m -th updated CSI report and is defined as

- (Z_1, Z'_1) of the table 5.4-1 if the CSI is triggered without a PUSCH with either transport block or HARQ-ACK or both when $L = 0$ CPUs are occupied (according to Clause 5.2.1.6) and the CSI to be transmitted is a single CSI and corresponds to wideband frequency-granularity where the CSI corresponds to at most 4 CSI-RS ports in a single resource without CRI report and where *CodebookType* is set to 'typeI-SinglePanel' or where *reportQuantity* is set to 'cri-RI-CQI', or
- (Z_1, Z'_1) of the table 5.4-2 if the CSI to be transmitted corresponds to wideband frequency-granularity where the CSI corresponds to at most 4 CSI-RS ports in a single resource without CRI report and where *CodebookType* is set to 'typeI-SinglePanel' or where *reportQuantity* is set to 'cri-RI-CQI', or

- (Z_3, Z'_3) of the table 5.4-2 if *reportQuantity* is set to 'cri-RSRP' or 'ssb-Index-RSRP', where X_μ is according to UE reported capability *beamReportTiming* and KB_1 is according to UE reported capability *beamSwitchTiming* as defined in [13, TS 38.306], or
- (Z_2, Z'_2) of table 5.4-2 otherwise.
- μ of table 5.4-1 and table 5.4-2 corresponds to the min $(\mu_{PDCCH}, \mu_{CSI-RS}, \mu_{UL})$ where the μ_{PDCCH} corresponds to the subcarrier spacing of the PDCCH with which the DCI was transmitted and μ_{UL} corresponds to the subcarrier spacing of the PUSCH with which the CSI report is to be transmitted and μ_{CSI-RS} corresponds to the minimum subcarrier spacing of the aperiodic CSI-RS triggered by the DCI

Table 5.4-1: CSI computation delay requirement 1

μ	Z_1 [symbols]	
	Z_1	Z'_1
0	10	8
1	13	11
2	25	21
3	43	36

Table 5.4-2: CSI computation delay requirement 2

μ	Z_1 [symbols]		Z_2 [symbols]		Z_3 [symbols]	
	Z_1	Z'_1	Z_2	Z'_2	Z_3	Z'_3
0	22	16	40	37	22	X_0
1	33	30	72	69	33	X_1
2	44	42	141	140	$\min(44, X_2 + KB_1)$	X_2
3	97	85	152	140	$\min(97, X_3 + KB_2)$	X_3

6 Physical uplink shared channel related procedure

6.1 UE procedure for transmitting the physical uplink shared channel

PUSCH transmission(s) can be dynamically scheduled by an UL grant in a DCI, or the transmission can correspond to a configured grant Type 1 or Type 2. The configured grant Type 1 PUSCH transmission is semi-statically configured to operate upon the reception of higher layer parameter of *configuredGrantConfig* including *rrc-ConfiguredUplinkGrant* without the detection of an UL grant in a DCI. The configured grant Type 2 PUSCH transmission is semi-persistently scheduled by an UL grant in a valid activation DCI according to Clause 10.2 of [6, TS 38.213] after the reception of higher layer parameter *configuredGrantConfig* not including *rrc-ConfiguredUplinkGrant*.

For the PUSCH transmission corresponding to a configured grant, the parameters applied for the transmission are provided by *configuredGrantConfig* except for *dataScramblingIdentityPUSCH*, *txConfig*, *codebookSubset*, *maxRank*, *scaling* of *UCI-OnPUSCH*, which are provided by *pusch-Config*. If the UE is provided with *transformPrecoder* in *configuredGrantConfig*, the UE applies the higher layer parameter *tp-pi2BPSK*, if provided in *pusch-Config*, according to the procedure described in Clause 6.1.4 for the PUSCH transmission corresponding to a configured grant.

For the PUSCH retransmission scheduled by a PDCCH with CRC scrambled by CS-RNTI with NDI=1, the parameters in *pusch-Config* are applied for the PUSCH transmission except for *p0-NominalWithoutGrant*, *p0-PUSCH-Alpha*, *powerControlLoopToUse*, *pathlossReferenceIndex* described in Clause 7.1 of [6, TS 38.213], *mcs-Table*, *mcs-TableTransformPrecoder* described in Clause 6.1.4.1 and *transformPrecoder* described in Clause 6.1.3.

For a UE configured with two uplinks in a serving cell, PUSCH retransmission for a TB on the serving cell is not expected to be on a different uplink than the uplink used for the PUSCH initial transmission of that TB.

A UE shall upon detection of a DCI format scheduling a PUSCH transmit the corresponding PUSCH unless the UE does not generate a transport block as described in [10, TS38.321] and there is no PUCCH with CSI/HARQ-ACK that overlaps in time with the PUSCH. In this release of the specification, the UE behavior is undefined if there would be a PUCCH

with CSI/HARQ-ACK overlapping in time with a PUSCH scheduled by a DCI format and if the UE does not generate a transport block as described in [10, TS38.321] when *skipUplinkTxDynamic* provided by higher layers is set to *true*. Upon detection of a DCI format 0_1 with "UL-SCH indicator" set to "0" and with a non-zero "CSI request" where the associated "reportQuantity" in *CSI-ReportConfig* set to "none" for all CSI report(s) triggered by "CSI request" in this DCI format 0_1, the UE ignores all fields in this DCI except the "CSI request" and the UE shall not transmit the corresponding PUSCH as indicated by this DCI format 0_1. For any HARQ process ID(s) in a given scheduled cell, the UE is not expected to transmit a PUSCH that overlaps in time with another PUSCH. For any two HARQ process IDs in a given scheduled cell, if the UE is scheduled to start a first PUSCH transmission starting in symbol j by a PDCCH ending in symbol i , the UE is not expected to be scheduled to transmit a PUSCH starting earlier than the end of the first PUSCH by a PDCCH that ends later than symbol i . The UE is not expected to be scheduled to transmit another PUSCH by DCI format 0_0 or 0_1 scrambled by C-RNTI or MCS-C-RNTI for a given HARQ process until after the end of the expected transmission of the last PUSCH for that HARQ process.

A UE is not expected to be scheduled by a PDCCH ending in symbol i to transmit a PUSCH on a given serving cell overlapping in time with a transmission occasion, where the UE is allowed to transmit a PUSCH with configured grant according to [10, TS38.321], starting in a symbol j on the same serving cell if the end of symbol i is not at least N_2 symbols before the beginning of symbol j . The value N_2 in symbols is determined according to the UE processing capability defined in Clause 6.4, and N_2 and the symbol duration are based on the minimum of the subcarrier spacing corresponding to the PUSCH with configured grant and the subcarrier spacing of the PDCCH scheduling the PUSCH.

A UE is not expected to be scheduled by a PDCCH ending in symbol i to transmit a PUSCH on a given serving cell for a given HARQ process, if there is a transmission occasion where the UE is allowed to transmit a PUSCH with configured grant according to [10, TS38.321] with the same HARQ process on the same serving cell starting in a symbol j after symbol i , and if the gap between the end of PDCCH and the beginning of symbol j is less than N_2 symbols. The value N_2 in symbols is determined according to the UE processing capability defined in Clause 6.4, and N_2 and the symbol duration are based on the minimum of the subcarrier spacing corresponding to the PUSCH with configured grant and the subcarrier spacing of the PDCCH scheduling the PUSCH.

For PUSCH scheduled by DCI format 0_0 on a cell, the UE shall transmit PUSCH according to the spatial relation, if applicable, corresponding to the dedicated PUCCH resource with the lowest ID within the active UL BWP of the cell, as described in Clause 9.2.1 of [6, TS 38.213].

For uplink, 16 HARQ processes per cell is supported by the UE.

6.1.1 Transmission schemes

Two transmission schemes are supported for PUSCH: codebook based transmission and non-codebook based transmission. The UE is configured with codebook based transmission when the higher layer parameter *txConfig* in *pusch-Config* is set to 'codebook', the UE is configured non-codebook based transmission when the higher layer parameter *txConfig* is set to 'nonCodebook'. If the higher layer parameter *txConfig* is not configured, the UE is not expected to be scheduled by DCI format 0_1. If PUSCH is scheduled by DCI format 0_0, the PUSCH transmission is based on a single antenna port. The UE shall not expect PUSCH scheduled by DCI format 0_0 in a BWP without configured PUCCH resource with *PUCCH-SpatialRelationInfo* in frequency range 2 in RRC connected mode.

6.1.1.1 Codebook based UL transmission

For codebook based transmission, PUSCH can be scheduled by DCI format 0_0, DCI format 0_1 or semi-statically configured to operate according to Clause 6.1.2.3. If this PUSCH is scheduled by DCI format 0_1, or semi-statically configured to operate according to Clause 6.1.2.3, the UE determines its PUSCH transmission precoder based on SRI, TPMI and the transmission rank, where the SRI, TPMI and the transmission rank are given by DCI fields of SRS resource indicator and Precoding information and number of layers in clause 7.3.1.1.2 of [5, TS 38.212] or given by *srs-ResourceIndicator* and *precodingAndNumberOfLayers* according to clause 6.1.2.3. The TPMI is used to indicate the precoder to be applied over the layers $\{0 \dots v-1\}$ and that corresponds to the SRS resource selected by the SRI when multiple SRS resources are configured, or if a single SRS resource is configured TPMI is used to indicate the precoder to be applied over the layers $\{0 \dots v-1\}$ and that corresponds to the SRS resource. The transmission precoder is selected from the uplink codebook that has a number of antenna ports equal to higher layer parameter *nrofSRS-Ports* in SRS-Config, as defined in Clause 6.3.1.5 of [4, TS 38.211]. When the UE is configured with the higher layer parameter *txConfig* set to 'codebook', the UE is configured with at least one SRS resource. The indicated SRI in slot n is associated with the most recent transmission of SRS resource identified by the SRI, where the SRS resource is prior to the PDCCH carrying the SRI.

For codebook based transmission, the UE determines its codebook subsets based on TPMI and upon the reception of higher layer parameter *codebookSubset* in *pusch-Config* which may be configured with 'fullyAndPartialAndNonCoherent', or 'partialAndNonCoherent', or 'nonCoherent' depending on the UE capability. The maximum transmission rank may be configured by the higher layer parameter *maxRank* in *pusch-Config*.

A UE reporting its UE capability of 'partialAndNonCoherent' transmission shall not expect to be configured by *codebookSubset* with 'fullyAndPartialAndNonCoherent'.

A UE reporting its UE capability of 'nonCoherent' transmission shall not expect to be configured by *codebookSubset* with 'fullyAndPartialAndNonCoherent' or with 'partialAndNonCoherent'.

A UE shall not expect to be configured with the higher layer parameter *codebookSubset* set to 'partialAndNonCoherent' when higher layer parameter *nrofSRS-Ports* in an *SRS-ResourceSet* with *usage* set to 'codebook' indicates that two SRS antenna ports are configured.

For codebook based transmission, the UE may be configured with a single *SRS-ResourceSet* with *usage* set to 'codebook' and only one SRS resource can be indicated based on the SRI from within the SRS resource set. The maximum number of configured SRS resources for codebook based transmission is 2. If aperiodic SRS is configured for a UE, the SRS request field in DCI triggers the transmission of aperiodic SRS resources.

The UE shall transmit PUSCH using the same antenna port(s) as the SRS port(s) in the SRS resource indicated by the DCI format 0_1 or by *configuredGrantConfig* according to clause 6.1.2.3.

The DM-RS antenna ports $\{\tilde{p}_0, \dots, \tilde{p}_{v-1}\}$ in Clause 6.4.1.1.3 of [4, TS38.211] are determined according to the ordering of DM-RS port(s) given by Tables 7.3.1.1.2-6 to 7.3.1.1.2-23 in Clause 7.3.1.1.2 of [5, TS 38.212].

When multiple SRS resources are configured by *SRS-ResourceSet* with *usage* set to 'codebook', the UE shall expect that higher layer parameters *nrofSRS-Ports* in *SRS-Resource* in *SRS-ResourceSet* shall be configured with the same value for all these SRS resources.

6.1.1.2 Non-Codebook based UL transmission

For non-codebook based transmission, PUSCH can be scheduled by DCI format 0_0, DCI format 0_1 or semi-statically configured to operate according to Clause 6.1.2.3. The UE can determine its PUSCH precoder and transmission rank based on the SRI when multiple SRS resources are configured, where the SRI is given by the SRS resource indicator in DCI according to clause 7.3.1.1.2 of [5, 38.212], or the SRI is given by *srs-ResourceIndicator* according to clause 6.1.2.3. The UE shall use one or multiple SRS resources for SRS transmission, where, in a SRS resource set, the maximum number of SRS resources which can be configured to the UE for simultaneous transmission in the same symbol and the maximum number of SRS resources are UE capabilities. The SRS resources transmitted simultaneously occupy the same RBs. Only one SRS port for each SRS resource is configured. Only one SRS resource set can be configured with higher layer parameter *usage* in *SRS-ResourceSet* set to 'nonCodebook'. The maximum number of SRS resources that can be configured for non-codebook based uplink transmission is 4. The indicated SRI in slot *n* is associated with the most recent transmission of SRS resource(s) identified by the SRI, where the SRS transmission is prior to the PDCCH carrying the SRI.

For non-codebook based transmission, the UE can calculate the precoder used for the transmission of SRS based on measurement of an associated NZP CSI-RS resource. A UE can be configured with only one NZP CSI-RS resource for the SRS resource set with higher layer parameter *usage* in *SRS-ResourceSet* set to 'nonCodebook' if configured.

- If aperiodic SRS resource set is configured, the associated NZP-CSI-RS is indicated via SRS request field in DCI format 0_1 and 1_1, where *AperiodicSRS-ResourceTrigger* and *AperiodicSRS-ResourceTriggerList* (indicating the association between aperiodic SRS triggering state(s) and SRS resource sets), triggered SRS resource(s) *srs-ResourceSetId*, *csi-RS* (indicating the associated *NZP-CSI-RS-ResourceId*) are higher layer configured in *SRS-ResourceSet*. A UE is not expected to update the SRS precoding information if the gap from the last symbol of the reception of the aperiodic NZP-CSI-RS resource and the first symbol of the aperiodic SRS transmission is less than 42 OFDM symbols.
- If the UE configured with aperiodic SRS associated with aperiodic NZP CSI-RS resource, the presence of the associated CSI-RS is indicated by the SRS request field if the value of the SRS request field is not '00' as in Table 7.3.1.1.2-24 of [5, TS 38.212] and if the scheduling DCI is not used for cross carrier or cross bandwidth part scheduling. The CSI-RS is located in the same slot as the SRS request field. If the UE configured with aperiodic SRS associated with aperiodic NZP CSI-RS resource, any of the TCI states configured in the scheduled CC shall not be configured with 'QCL-TypeD'.

- If periodic or semi-persistent SRS resource set is configured, the *NZP-CSI-RS-ResourceId* for measurement is indicated via higher layer parameter *associatedCSI-RS* in *SRS-ResourceSet*.

The UE shall perform one-to-one mapping from the indicated SRI(s) to the indicated DM-RS ports(s) and their corresponding PUSCH layers $\{0 \dots v-1\}$ given by DCI format 0_1 or by *configuredGrantConfig* according to clause 6.1.2.3 in increasing order.

The UE shall transmit PUSCH using the same antenna ports as the SRS port(s) in the SRS resource(s) indicated by SRI(s) given by DCI format 0_1 or by *configuredGrantConfig* according to clause 6.1.2.3, where the SRS port in $(i+1)$ -th SRS resource in the SRS resource set is indexed as $p_i = 1000 + i$.

The DM-RS antenna ports $\{\tilde{p}_0, \dots, \tilde{p}_{v-1}\}$ in Clause 6.4.1.1.3 of [4, TS 38.211] are determined according to the ordering of DM-RS port(s) given by Tables 7.3.1.1.2-6 to 7.3.1.1.2-23 in Clause 7.3.1.1.2 of [5, TS 38.212].

For non-codebook based transmission, the UE does not expect to be configured with both *spatialRelationInfo* for SRS resource and *associatedCSI-RS* in *SRS-ResourceSet* for SRS resource set.

For non-codebook based transmission, the UE can be scheduled with DCI format 0_1 when at least one SRS resource is configured in *SRS-ResourceSet* with *usage* set to 'nonCodebook'.

6.1.2 Resource allocation

6.1.2.1 Resource allocation in time domain

When the UE is scheduled to transmit a transport block and no CSI report, or the UE is scheduled to transmit a transport block and a CSI report(s) on PUSCH by a DCI, the *Time domain resource assignment* field value m of the DCI provides a row index $m + 1$ to an allocated table. The determination of the used resource allocation table is defined in Clause 6.1.2.1.1. The indexed row defines the slot offset K_2 , the start and length indicator *SLIV*, or directly the start symbol S and the allocation length L , and the PUSCH mapping type to be applied in the PUSCH transmission.

When the UE is scheduled to transmit a PUSCH with no transport block and with a CSI report(s) by a *CSI request* field on a DCI, the *Time domain resource assignment* field value m of the DCI provides a row index $m + 1$ to an allocated table which is defined by the higher layer configured *pusch-TimeDomainAllocationList* in *pusch-Config*. The indexed row defines the start and length indicator *SLIV*, and the PUSCH mapping type to be applied in the PUSCH transmission and the K_2 value is determined as $K_2 = \max_j Y_j(m+1)$, where $Y_j, j = 0, \dots, N_{\text{Rep}} - 1$ are the corresponding list entries of the higher layer parameter *reportSlotOffsetList* in *CSI-ReportConfig* for the N_{Rep} triggered CSI Reporting Settings and $Y_j(m+1)$ is the $(m+1)$ th entry of Y_j .

- The slot where the UE shall transmit the PUSCH is determined by K_2 as $\left\lfloor n \cdot \frac{2^{\mu_{\text{PUSCH}}}}{2^{\mu_{\text{PDCCH}}}} \right\rfloor + K_2$ where n is the slot with the scheduling DCI, K_2 is based on the numerology of PUSCH, and μ_{PUSCH} and μ_{PDCCH} are the subcarrier spacing configurations for PUSCH and PDCCH, respectively, and
- The starting symbol S relative to the start of the slot, and the number of consecutive symbols L counting from the symbol S allocated for the PUSCH are determined from the start and length indicator *SLIV* of the indexed row:

if $(L-1) \leq 7$ then

$$SLIV = 14 \cdot (L-1) + S$$

else

$$SLIV = 14 \cdot (14-L+1) + (14-1-S)$$

where $0 < L \leq 14 - S$, and

- The PUSCH mapping type is set to Type A or Type B as defined in Clause 6.4.1.1.3 of [4, TS 38.211] as given by the indexed row.

The UE shall consider the S and L combinations defined in table 6.1.2.1-1 as valid PUSCH allocations

Table 6.1.2.1-1: Valid S and L combinations

PUSCH mapping type	Normal cyclic prefix			Extended cyclic prefix		
	S	L	$S+L$	S	L	$S+L$
Type A	0	{4,...,14}	{4,...,14}	0	{4,...,12}	{4,...,12}
Type B	{0,...,13}	{1,...,14}	{1,...,14}	{0,..., 11}	{1,...,12}	{1,...,12}

When transmitting PUSCH scheduled by DCI format 0_1 in PDCCH with CRC scrambled with C-RNTI, MCS-C-RNTI, or CS-RNTI with NDI=1, if the UE is configured with *pusch-AggregationFactor*, the same symbol allocation is applied across the *pusch-AggregationFactor* consecutive slots and the PUSCH is limited to a single transmission layer. The UE shall repeat the TB across the *pusch-AggregationFactor* consecutive slots applying the same symbol allocation in each slot. The redundancy version to be applied on the n th transmission occasion of the TB, where $n = 0, 1, \dots, \text{pusch-AggregationFactor} - 1$, is determined according to table 6.1.2.1-2.

Table 6.1.2.1-2: Redundancy version when *pusch-AggregationFactor* is present

r_{vid} indicated by the DCI scheduling the PUSCH	r_{vid} to be applied to n^{th} transmission occasion			
	$n \bmod 4 = 0$	$n \bmod 4 = 1$	$n \bmod 4 = 2$	$n \bmod 4 = 3$
0	0	2	3	1
2	2	3	1	0
3	3	1	0	2
1	1	0	2	3

A PUSCH transmission in a slot of a multi-slot PUSCH transmission is omitted according to the conditions in Clause 11.1 of [6, TS38.213].

6.1.2.1.1 Determination of the resource allocation table to be used for PUSCH

Table 6.1.2.1.1-1 defines which PUSCH time domain resource allocation configuration to apply. Either a default PUSCH time domain allocation A according to table 6.1.2.1.1-2, is applied, or the higher layer configured *pusch-TimeDomainAllocationList* in either *pusch-ConfigCommon* or *pusch-Config* is applied.

Table 6.1.2.1.1-4 defines the subcarrier spacing specific values j . j is used in determination of K_2 in conjunction to table 6.1.2.1.1-2, for normal CP or table 6.1.2.1.1.-3 for extended CP, where μ_{PUSCH} is the subcarrier spacing configurations for PUSCH.

Table 6.1.2.1.1-5 defines the additional subcarrier spacing specific slot delay value for the first transmission of PUSCH scheduled by the RAR. When the UE transmits a PUSCH scheduled by RAR, the Δ value specific to the PUSCH subcarrier spacing μ_{PUSCH} is applied in addition to the K_2 value.

Table 6.1.2.1.1-1: Applicable PUSCH time domain resource allocation

RNTI	PDCCH search space	<i>pusch-ConfigCommon</i> includes <i>pusch-TimeDomainAllocationList</i>	<i>pusch-Config</i> includes <i>pusch-TimeDomainAllocationList</i>	PUSCH time domain resource allocation to apply
PUSCH scheduled by MAC RAR as described in clause 8.2 of [6, TS 38.213]		No	-	Default A
		Yes		<i>pusch-TimeDomainAllocationList</i> provided in <i>pusch-ConfigCommon</i>
C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI	Any common search space associated with CORESET 0	No	-	Default A
		Yes		<i>pusch-AllTimeDomainAllocationList</i> provided in <i>pusch-ConfigCommon</i>
C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI, SP-CSI-RNTI	Any common search space not associated with CORESET 0, UE specific search space	No	No	Default A
		Yes	No	<i>pusch-TimeDomainAllocationList</i> provided in <i>pusch-ConfigCommon</i>
		No/Yes	Yes	<i>pusch-TimeDomainAllocationList</i> provided in <i>pusch-Config</i>

Table 6.1.2.1.1-2: Default PUSCH time domain resource allocation A for normal CP

Row index	PUSCH mapping type	K_2	S	L
1	Type A	j	0	14
2	Type A	j	0	12
3	Type A	j	0	10
4	Type B	j	2	10
5	Type B	j	4	10
6	Type B	j	4	8
7	Type B	j	4	6
8	Type A	$j+1$	0	14
9	Type A	$j+1$	0	12
10	Type A	$j+1$	0	10
11	Type A	$j+2$	0	14
12	Type A	$j+2$	0	12
13	Type A	$j+2$	0	10
14	Type B	j	8	6
15	Type A	$j+3$	0	14
16	Type A	$j+3$	0	10

Table 6.1.2.1.1-3: Default PUSCH time domain resource allocation A for extended CP

Row index	PUSCH mapping type	K_2	S	L
1	Type A	j	0	8
2	Type A	j	0	12
3	Type A	j	0	10
4	Type B	j	2	10
5	Type B	j	4	4
6	Type B	j	4	8
7	Type B	j	4	6
8	Type A	$j+1$	0	8
9	Type A	$j+1$	0	12
10	Type A	$j+1$	0	10
11	Type A	$j+2$	0	6
12	Type A	$j+2$	0	12
13	Type A	$j+2$	0	10
14	Type B	j	8	4
15	Type A	$j+3$	0	8
16	Type A	$j+3$	0	10

Table 6.1.2.1.1-4: Definition of value j

μ_{PUSCH}	j
0	1
1	1
2	2
3	3

Table 6.1.2.1.1-5: Definition of value Δ

μ_{PUSCH}	Δ
0	2
1	3
2	4
3	6

6.1.2.2 Resource allocation in frequency domain

The UE shall determine the resource block assignment in frequency domain using the resource allocation field in the detected PDCCH DCI except for a PUSCH transmission scheduled by a RAR UL grant, in which case the frequency domain resource allocation is determined according to Clause 8.3 of [6, 38.213]. Two uplink resource allocation schemes type 0 and type 1 are supported. Uplink resource allocation scheme type 0 is supported for PUSCH only when transform precoding is disabled. Uplink resource allocation scheme type 1 is supported for PUSCH for both cases when transform precoding is enabled or disabled.

If the scheduling DCI is configured to indicate the uplink resource allocation type as part of the *Frequency domain resource* assignment field by setting a higher layer parameter *resourceAllocation* in *pusch-Config* to 'dynamicSwitch', the UE shall use uplink resource allocation type 0 or type 1 as defined by this DCI field. Otherwise the UE shall use the uplink frequency resource allocation type as defined by the higher layer parameter *resourceAllocation*.

The UE shall assume that when the scheduling PDCCH is received with DCI format 0_0, then uplink resource allocation type 1 is used.

If a bandwidth part indicator field is not configured in the scheduling DCI or the UE does not support active bandwidth part change via DCI, the RB indexing for uplink type 0 and type 1 resource allocation is determined within the UE's active bandwidth part. If a bandwidth part indicator field is configured in the scheduling DCI and the UE supports active bandwidth part change via DCI, the RB indexing for uplink type 0 and type 1 resource allocation is determined within the UE's bandwidth part indicated by bandwidth part indicator field value in the DCI. The UE shall upon detection of PDCCH intended for the UE determine first the uplink bandwidth part and then the resource allocation within the bandwidth part. RB numbering starts from the lowest RB in the determined uplink bandwidth part.

6.1.2.2.1 Uplink resource allocation type 0

In uplink resource allocation of type 0, the resource block assignment information includes a bitmap indicating the Resource Block Groups (RBGs) that are allocated to the scheduled UE where a RBG is a set of consecutive virtual resource blocks defined by higher layer parameter *rbg-Size* configured in *pusch-Config* and the size of the bandwidth part as defined in Table 6.1.2.2.1-1.

Table 6.1.2.2.1-1: Nominal RBG size P

Bandwidth Part Size	Configuration 1	Configuration 2
1 – 36	2	4
37 – 72	4	8
73 – 144	8	16
145 – 275	16	16

The total number of RBGs (N_{RBG}) for a uplink bandwidth part i of size $N_{\text{BWP},i}^{\text{size}}$ PRBs is given by

$$N_{\text{RBG}} = \left\lceil \left(N_{\text{BWP},i}^{\text{size}} + \left(N_{\text{BWP},i}^{\text{start}} \bmod P \right) \right) / P \right\rceil \text{ where}$$

- the size of the first RBG is $\text{RBG}_0^{\text{size}} = P - N_{\text{BWP},i}^{\text{start}} \bmod P$,
- the size of the last RBG is $\text{RBG}_{\text{last}}^{\text{size}} = \left(N_{\text{BWP},i}^{\text{start}} + N_{\text{BWP},i}^{\text{size}} \right) \bmod P$ if $\left(N_{\text{BWP},i}^{\text{start}} + N_{\text{BWP},i}^{\text{size}} \right) \bmod P > 0$ and P otherwise.
- the size of all other RBG is P .

The bitmap is of size N_{RBG} bits with one bitmap bit per RBG such that each RBG is addressable. The RBGs shall be indexed in the order of increasing frequency of the bandwidth part and starting at the lowest frequency. The order of RBG bitmap is such that RBG 0 to RBG $N_{\text{RBG}} - 1$ are mapped from MSB to LSB of the bitmap. The RBG is allocated to the UE if the corresponding bit value in the bitmap is 1, the RBG is not allocated to the UE otherwise.

In frequency range 1, only 'almost contiguous allocation' defined in [8, TS 38.101-1] is allowed as non-contiguous allocation per component carrier for UL RB allocation for CP-OFDM.

In frequency range 2, non-contiguous allocation per component carrier for UL RB allocation for CP-OFDM is not supported.

6.1.2.2.2 Uplink resource allocation type 1

In uplink resource allocation of type 1, the resource block assignment information indicates to a scheduled UE a set of contiguously allocated non-interleaved virtual resource blocks within the active bandwidth part of size $N_{\text{BWP}}^{\text{size}}$ PRBs except for the case when DCI format 0_0 is decoded in any common search space in which case the size of the initial UL bandwidth part $N_{\text{BWP},0}^{\text{size}}$ shall be used.

An uplink type 1 resource allocation field consists of a resource indication value (RIV) corresponding to a starting virtual resource block (RB_{start}) and a length in terms of contiguously allocated resource blocks L_{RBs} . The resource indication value is defined by

if $(L_{\text{RBs}} - 1) \leq \lfloor N_{\text{BWP}}^{\text{size}} / 2 \rfloor$ then

$$RIV = N_{\text{BWP}}^{\text{size}}(L_{\text{RBs}} - 1) + RB_{\text{start}}$$

else

$$RIV = N_{\text{BWP}}^{\text{size}}(N_{\text{BWP}}^{\text{size}} - L_{\text{RBs}} + 1) + (N_{\text{BWP}}^{\text{size}} - 1 - RB_{\text{start}})$$

where $L_{\text{RBs}} \geq 1$ and shall not exceed $N_{\text{BWP}}^{\text{size}} - RB_{\text{start}}$.

When the DCI size for DCI format 0_0 in USS is derived from the initial UL BWP with size $N_{BWP}^{initial}$ but applied to another active BWP with size of N_{BWP}^{active} , an uplink type 1 resource block assignment field consists of a resource indication value (RIV) corresponding to a starting resource block $RB_{start} = 0, K, 2 \cdot K, \dots, (N_{BWP}^{initial} - 1) \cdot K$ and a length in terms of virtually contiguously allocated resource blocks $L_{RBs} = K, 2 \cdot K, \dots, N_{BWP}^{initial} \cdot K$.

The resource indication value is defined by

if $(L'_{RBs} - 1) \leq \lfloor N_{BWP}^{initial} / 2 \rfloor$ then

$$RIV = N_{BWP}^{initial} (L'_{RBs} - 1) + RB'_{start}$$

else

$$RIV = N_{BWP}^{initial} (N_{BWP}^{initial} - L'_{RBs} + 1) + (N_{BWP}^{initial} - 1 - RB'_{start})$$

where $L'_{RBs} = L_{RBs} / K$, $RB'_{start} = RB_{start} / K$ and where L'_{RBs} shall not exceed $N_{BWP}^{initial} - RB'_{start}$.

If $N_{BWP}^{active} > N_{BWP}^{initial}$, K is the maximum value from set $\{1, 2, 4, 8\}$ which satisfies $K \leq \lfloor N_{BWP}^{active} / N_{BWP}^{initial} \rfloor$; otherwise $K = 1$.

6.1.2.3 Resource allocation for uplink transmission with configured grant

When PUSCH resource allocation is semi-statically configured by higher layer parameter *configuredGrantConfig* in *BWP-UplinkDedicated* information element, and the PUSCH transmission corresponding to a configured grant, the following higher layer parameters are applied in the transmission:

- For Type 1 PUSCH transmissions with a configured grant, the following parameters are given in *configuredGrantConfig*:
 - The higher layer parameter *timeDomainAllocation* value m provides a row index $m+1$ pointing to an allocated table, indicating a combination of start symbol and length and PUSCH mapping type, where the table selection follows the rules for the UE specific search space, as defined in Clause 6.1.2.1.1;
 - Frequency domain resource allocation is determined by the N LSB bits in the higher layer parameter *frequencyDomainAllocation*, forming a bit sequence f_{17}, \dots, f_1, f_0 , where f_0 is the LSB, according to the procedure in Clause 6.1.2.2 and N is determined as the size of frequency domain resource assignment field in DCI format 0_1 for a given resource allocation type indicated by *resourceAllocation*;
 - The I_{MCS} is provided by higher layer parameter *mcsAndTBS*;
 - Number of DM-RS CDM groups, DM-RS ports, SRS resource indication and DM-RS sequence initialization are determined as in Clause 7.3.1.1 of [5, TS 38.212], and the antenna port value, the bit value for DM-RS sequence initialization, precoding information and number of layers, SRS resource indicator are provided by *antennaPort*, *dmrs-SeqInitialization*, *precodingAndNumberOfLayers*, and *srs-ResourceIndicator* respectively;
 - When frequency hopping is enabled, the frequency offset between two frequency hops can be configured by higher layer parameter *frequencyHoppingOffset*.
- For Type 2 PUSCH transmissions with a configured grant: the resource allocation follows the higher layer configuration according to [10, TS 38.321], and UL grant received on the DCI.

The UE shall not transmit anything on the resources configured by *configuredGrantConfig* if the higher layers did not deliver a transport block to transmit on the resources allocated for uplink transmission without grant.

A set of allowed periodicities P are defined in [12, TS 38.331].

6.1.2.3.1 Transport Block repetition for uplink transmissions with a configured grant

The higher layer configured parameters *repK* and *repK-RV* define the K repetitions to be applied to the transmitted transport block, and the redundancy version pattern to be applied to the repetitions. If the parameter *repK-RV* is not

provided in the *configuredGrantConfig*, the redundancy version for uplink transmissions with a configured grant shall be set to 0. Otherwise, for the n th transmission occasion among K repetitions, $n=1, 2, \dots, K$, it is associated with $(\text{mod}(n-1,4)+1)^{\text{th}}$ value in the configured RV sequence. The initial transmission of a transport block may start at

- the first transmission occasion of the K repetitions if the configured RV sequence is {0,2,3,1},
- any of the transmission occasions of the K repetitions that are associated with RV=0 if the configured RV sequence is {0,3,0,3},
- any of the transmission occasions of the K repetitions if the configured RV sequence is {0,0,0,0}, except the last transmission occasion when $K=8$.

For any RV sequence, the repetitions shall be terminated after transmitting K repetitions, or at the last transmission occasion among the K repetitions within the period P , or from the starting symbol of the repetition that overlaps with a PUSCH with the same HARQ process scheduled by DCI format 0_0 or 0_1, whichever is reached first. The UE is not expected to be configured with the time duration for the transmission of K repetitions larger than the time duration derived by the periodicity P . If the UE determines that, for a transmission occasion, the number of symbols available for the PUSCH transmission in a slot is smaller than transmission duration L , the UE does not transmit the PUSCH in the transmission occasion.

For both Type 1 and Type 2 PUSCH transmissions with a configured grant, when the UE is configured with $\text{rep}K > 1$, the UE shall repeat the TB across the $\text{rep}K$ consecutive slots applying the same symbol allocation in each slot. A Type 1 or Type 2 PUSCH transmission with a configured grant in a slot is omitted according to the conditions in Clause 11.1 of [6, TS38.213].

6.1.3 UE procedure for applying transform precoding on PUSCH

For a PUSCH scheduled by RAR UL grant or for a PUSCH scheduled by DCI format 0_0 with CRC scrambled by TC-RNTI, the UE shall consider the transform precoding either 'enabled' or 'disabled' according to the higher layer configured parameter *msg3-transformPrecoder*.

For PUSCH transmission scheduled by a PDCCH with CRC scrambled by CS-RNTI with NDI=1, C-RNTI, or MCS-C-RNTI or SP-CSI-RNTI:

- If the DCI with the scheduling grant was received with DCI format 0_0, the UE shall, for this PUSCH transmission, consider the transform precoding either enabled or disabled according to the higher layer configured parameter *msg3-transformPrecoder*.
- If the DCI with the scheduling grant was not received with DCI format 0_0
 - If the UE is configured with the higher layer parameter *transformPrecoder* in *pusch-Config*, the UE shall, for this PUSCH transmission, consider the transform precoding either enabled or disabled according to this parameter.
 - If the UE is not configured with the higher layer parameter *transformPrecoder* in *pusch-Config*, the UE shall, for this PUSCH transmission, consider the transform precoding either enabled or disabled according to the higher layer configured parameter *msg3-transformPrecoder*.

For PUSCH transmission with a configured grant

- If the UE is configured with the higher layer parameter *transformPrecoder* in *configuredGrantConfig*, the UE shall, for this PUSCH transmission, consider the transform precoding either enabled or disabled according to this parameter.
- If the UE is not configured with the higher layer parameter *transformPrecoder* in *configuredGrantConfig*, the UE shall, for this PUSCH transmission, consider the transform precoding either enabled or disabled according to the higher layer configured parameter *msg3-transformPrecoder*.

6.1.4 Modulation order, redundancy version and transport block size determination

To determine the modulation order, target code rate, redundancy version and transport block size for the physical uplink shared channel, the UE shall first

- read the 5-bit modulation and coding scheme field (I_{MCS}) in the DCI scheduling PUSCH or provided in a DCI activating a configured grant Type 2 PUSCH, or as provided by $mcsAndTBS$ as described in Clause 6.1.2.3 for a configured grant Type 1 PUSCH to determine the modulation order (O_m) and target code rate (R) based on the procedure defined in Clause 6.1.4.1
- read redundancy version field (rv) in the DCI to determine the redundancy version for PUSCH scheduled by DCI, or determine the redundancy version according to Clause 6.1.2.3.1 for configured grant Type 1 and Type 2 PUSCH,

and second

- use the number of layers (ν), the total number of allocated PRBs (n_{PRB}) to determine the transport block size based on the procedure defined in Clause 6.1.4.2.

Within a cell group, a UE is not required to handle PUSCH(s) transmissions in slot s_j in serving cell- j , and for $j = 0, 1, 2, \dots, J-1$, slot s_j overlapping with any given point in time, if the following condition is not satisfied at that point in time:

$$\sum_{j=0}^{J-1} \frac{\sum_{m=0}^{M-1} V_{j,m}}{T_{slot}^{\mu(j)}} \leq DataRate,$$

where

- J is the number of configured serving cells belong to a frequency range
 - for the j -th serving cell,
 - M is the number of TB(s) transmitted in slot- s_j .
 - $T_{slot}^{\mu(j)} = 10^{-3}/2^{\mu(j)}$, where $\mu(j)$ is the numerology for PUSCH(s) in slot s_j of the j -th serving cell.
 - for the m -th TB, $V_{j,m} = C' \cdot \left\lfloor \frac{A}{C} \right\rfloor$
 - A is the number of bits in the transport block as defined in Clause 6.2.1 [5, TS 38.212]
 - C is the total number of code blocks for the transport block defined in Clause 5.2.2 [5, TS 38.212].
 - C' is the number of scheduled code blocks for the transport block as defined in Clause 5.4.2.1 [5,38.212]
- $DataRate$ [Mbps] is computed as the maximum data rate summed over all the carriers in the frequency range for any signaled band combination and feature set consistent with the configured serving cells, where the data rate value is given by the formula in Clause 4.1.2 in [13, TS 38.306], including the scaling factor $f(i)$.

For a j -th serving cell, if higher layer parameter $processingType2Enabled$ of $PUSCH-ServingCellConfig$ is configured for the serving cell and set to *enable*, or if at least one $I_{MCS} > W$ for a PUSCH, where $W = 28$ for MCS tables 5.1.3.1-1 and 5.1.3.1-3, and $W = 27$ for MCS tables 5.1.3.1-2, 6.1.4.1-1, and 6.1.4.1-2, the UE is not required to handle PUSCH transmissions, if the following condition is not satisfied:

$$\frac{\sum_{m=0}^{M-1} V_{j,m}}{L \times T_s^{\mu}} \leq DataRateCC$$

where

- L is the number of symbols assigned to the PUSCH
- M is the number of TB in the PUSCH
- $T_s^{\mu} = \frac{10^{-3}}{2^{\mu \cdot N_{symb}^{slot}}}$ where μ is the numerology of the PUSCH
- for the m -th TB, $V_{j,m} = C' \cdot \left\lfloor \frac{A}{C} \right\rfloor$
 - A is the number of bits in the transport block as defined in Clause 6.2.1 [5, TS 38.212]

- C is the total number of code blocks for the transport block defined in Clause 5.2.2 [5, TS 38.212]
- C' is the number of scheduled code blocks for the transport block as defined in Clause 5.4.2.1 [5, TS 38.212]
- $DataRateCC$ [Mbps] is computed as the maximum data rate for a carrier in the frequency band of the serving cell for any signaled band combination and feature set consistent with the serving cell, where the data rate value is given by the formula in Clause 4.1.2 in [13, TS 38.306], including the scaling factor $f(i)$.

6.1.4.1 Modulation order and target code rate determination

For a PUSCH scheduled by RAR UL grant or

for a PUSCH scheduled by a DCI format 0_0 with CRC scrambled by C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI, or

for a PUSCH scheduled by a DCI format 0_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, CS-RNTI, SP-CSI-RNTI, or

for a PUSCH with configured grant using CS-RNTI, and

if transform precoding is disabled for this PUSCH transmission according to Clause 6.1.3

- if $mcs\text{-}Table$ in $pusch\text{-}Config$ is set to 'qam256', and PUSCH is scheduled by a PDCCH with DCI format 0_1 with CRC scrambled by C-RNTI or SP-CSI-RNTI,
 - the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif the UE is not configured with MCS-C-RNTI, $mcs\text{-}Table$ in $pusch\text{-}Config$ is set to 'qam64LowSE', and the PUSCH is scheduled by a PDCCH in a UE-specific search space with CRC scrambled by C-RNTI or SP-CSI-RNTI,
 - the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif the UE is configured with MCS-C-RNTI, and the PUSCH is scheduled by a PDCCH with CRC scrambled by MCS-C-RNTI,
 - the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif $mcs\text{-}Table$ in $configuredGrantConfig$ is set to 'qam256',
 - if PUSCH is scheduled by a PDCCH with CRC scrambled by CS-RNTI or
 - if PUSCH is transmitted with configured grant
 - the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif $mcs\text{-}Table$ in $configuredGrantConfig$ is set to 'qam64LowSE',
 - if PUSCH is scheduled by a PDCCH with CRC scrambled by CS-RNTI or
 - if PUSCH is transmitted with configured grant,
 - the UE shall use I_{MCS} and Table 5.1.3.1-3 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- else
 - the UE shall use I_{MCS} and Table 5.1.3.1-1 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.

else

- if $mcs\text{-}Table\text{TransformPrecoder}$ in $pusch\text{-}Config$ is set to 'qam256', and PUSCH is scheduled by a PDCCH with DCI format 0_1 with CRC scrambled by C-RNTI or SP-CSI-RNTI,

- the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif the UE is not configured with MCS-C-RNTI, *mcs-TableTransformPrecoder* in *pusch-Config* is set to 'qam64LowSE', and the PUSCH is scheduled by a PDCCH in a UE-specific search space with CRC scrambled by C-RNTI or SP-CSI-RNTI,
 - the UE shall use I_{MCS} and Table 6.1.4.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif the UE is configured with MCS-C-RNTI, and the PUSCH is scheduled by a PDCCH with CRC scrambled by MCS-C-RNTI,
 - the UE shall use I_{MCS} and Table 6.1.4.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif *mcs-TableTransformPrecoder* in *configuredGrantConfig* is set to 'qam256',
 - if PUSCH is scheduled by a PDCCH with CRC scrambled by CS-RNTI or
 - if PUSCH is transmitted with configured grant,
 - the UE shall use I_{MCS} and Table 5.1.3.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- elseif *mcs-TableTransformPrecoder* in *configuredGrantConfig* is set to 'qam64LowSE',
 - if PUSCH is scheduled by a PDCCH with CRC scrambled by CS-RNTI or
 - if PUSCH is transmitted with configured grant,
 - the UE shall use I_{MCS} and Table 6.1.4.1-2 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.
- else
 - the UE shall use I_{MCS} and Table 6.1.4.1-1 to determine the modulation order (Q_m) and Target code rate (R) used in the physical uplink shared channel.

end

For Table 6.1.4.1-1 and Table 6.1.4.1-2, if higher layer parameter *tp-pi2BPSK* is configured, $q = 1$ otherwise $q=2$.

Table 6.1.4.1-1: MCS index table for PUSCH with transform precoding and 64QAM

MCS Index I_{MCS}	Modulation Order Q_m	Target code Rate R x 1024	Spectral efficiency
0	q	240/ q	0.2344
1	q	314/ q	0.3066
2	2	193	0.3770
3	2	251	0.4902
4	2	308	0.6016
5	2	379	0.7402
6	2	449	0.8770
7	2	526	1.0273
8	2	602	1.1758
9	2	679	1.3262
10	4	340	1.3281
11	4	378	1.4766
12	4	434	1.6953
13	4	490	1.9141
14	4	553	2.1602
15	4	616	2.4063
16	4	658	2.5703
17	6	466	2.7305
18	6	517	3.0293
19	6	567	3.3223
20	6	616	3.6094
21	6	666	3.9023
22	6	719	4.2129
23	6	772	4.5234
24	6	822	4.8164
25	6	873	5.1152
26	6	910	5.3320
27	6	948	5.5547
28	q	reserved	
29	2	reserved	
30	4	reserved	
31	6	reserved	

Table 6.1.4.1-2: MCS index table 2 for PUSCH with transform precoding and 64QAM

MCS Index I_{MCS}	Modulation Order Q_m	Target code Rate R x 1024	Spectral efficiency
0	q	$60/q$	0.0586
1	q	$80/q$	0.0781
2	q	$100/q$	0.0977
3	q	$128/q$	0.1250
4	q	$156/q$	0.1523
5	q	$198/q$	0.1934
6	2	120	0.2344
7	2	157	0.3066
8	2	193	0.3770
9	2	251	0.4902
10	2	308	0.6016
11	2	379	0.7402
12	2	449	0.8770
13	2	526	1.0273
14	2	602	1.1758
15	2	679	1.3262
16	4	378	1.4766
17	4	434	1.6953
18	4	490	1.9141
19	4	553	2.1602
20	4	616	2.4063
21	4	658	2.5703
22	4	699	2.7305
23	4	772	3.0156
24	6	567	3.3223
25	6	616	3.6094
26	6	666	3.9023
27	6	772	4.5234
28	q	reserved	
29	2	reserved	
30	4	reserved	
31	6	reserved	

6.1.4.2 Transport block size determination

For a PUSCH scheduled by RAR UL grant or

for a PUSCH scheduled by a DCI format 0_0 with CRC scrambled by C-RNTI, MCS-C-RNTI, TC-RNTI, CS-RNTI, or

for a PUSCH scheduled by a DCI format 0_1 with CRC scrambled by C-RNTI, MCS-C-RNTI, CS-RNTI, or

for a PUSCH transmission with configured grant,

if

- $0 \leq I_{MCS} \leq 27$ and transform precoding is disabled and Table 5.1.3.1-2 is used, or
- $0 \leq I_{MCS} \leq 28$ and transform precoding is disabled and a table other than Table 5.1.3.1-2 is used, or
- $0 \leq I_{MCS} \leq 27$ and transform precoding is enabled, the UE shall first determine the TBS as specified below:

The UE shall first determine the number of REs (N_{RE}) within the slot:

- A UE first determines the number of REs allocated for PUSCH within a PRB (N'_{RE}) by

- $N_{RE}' = N_{sc}^{RB} \cdot N_{symp}^{sh} - N_{DMRS}^{PRB} - N_{oh}^{PRB}$, where $N_{sc}^{RB} = 12$ is the number of subcarriers in the frequency domain in a physical resource block, N_{symp}^{sh} is the number of symbols of the PUSCH allocation within the slot, N_{DMRS}^{PRB} is the number of REs for DM-RS per PRB in the allocated duration including the overhead of the DM-RS CDM groups without data, as described for PUSCH with a configured grant in Clause 6.1.2.3 or as indicated by DCI format 0_1 or as described for DCI format 0_0 in Clause 6.2.2, and N_{oh}^{PRB} is the overhead configured by higher layer parameter $xOverhead$ in *PUSCH-ServingCellConfig*. If the N_{oh}^{PRB} is not configured (a value from 6, 12, or 18), the N_{oh}^{PRB} is assumed to be 0. For Msg3 transmission the N_{oh}^{PRB} is always set to 0.
- A UE determines the total number of REs allocated for PUSCH (N_{RE}) by $N_{RE} = \min(156, N_{RE}') \cdot n_{PRB}$ where n_{PRB} is the total number of allocated PRBs for the UE.
- Next, proceed with steps 2-4 as defined in Clause 5.1.3.2

else if

- $28 \leq I_{MCS} \leq 31$ and transform precoding is disabled and Table 5.1.3.1-2 is used, or
- $28 \leq I_{MCS} \leq 31$ and transform precoding is enabled,
- the TBS is assumed to be as determined from the DCI transported in the latest PDCCH for the same transport block using $0 \leq I_{MCS} \leq 27$. If there is no PDCCH for the same transport block using $0 \leq I_{MCS} \leq 27$, and if the initial PUSCH for the same transport block is transmitted with configured grant,
 - the TBS shall be determined from *configuredGrantConfig* for a configured grant Type 1 PUSCH.
 - the TBS shall be determined from the most recent PDCCH scheduling a configured grant Type 2 PUSCH.

else

- the TBS is assumed to be as determined from the DCI transported in the latest PDCCH for the same transport block using $0 \leq I_{MCS} \leq 28$. If there is no PDCCH for the same transport block using $0 \leq I_{MCS} \leq 28$, and if the initial PUSCH for the same transport block is transmitted with configured grant,
 - the TBS shall be determined from *configuredGrantConfig* for a configured grant Type 1 PUSCH.
 - the TBS shall be determined from the most recent PDCCH scheduling a configured grant Type 2 PUSCH.

6.1.5 Code block group based PUSCH transmission

6.1.5.1 UE procedure for grouping of code blocks to code block groups

If a UE is configured to transmit code block group (CBG) based transmissions by receiving the higher layer parameter *codeBlockGroupTransmission* in *PUSCH-ServingCellConfig*, the UE shall determine the number of CBGs for a PUSCH transmission as

$$M = \min(N, C),$$

where N is the maximum number of CBGs per transport block as configured by *maxCodeBlockGroupsPerTransportBlock* in *PUSCH-ServingCellConfig*, and C is the number of code blocks in the PUSCH according to the procedure defined in Clause 6.2.3 of [5, TS 38.212].

Define $M_1 = \text{mod}(C, M)$, $K_1 = \left\lceil \frac{C}{M} \right\rceil$, and $K_2 = \left\lfloor \frac{C}{M} \right\rfloor$.

If $M_1 > 0$, CBG m , $m = 0, 1, \dots, M_1 - 1$, consists of code blocks with indices $m \cdot K_1 + k$, $k = 0, 1, \dots, K_1 - 1$. CBG m , $m = M_1, M_1 + 1, \dots, M - 1$, consists of code blocks with indices $M_1 \cdot K_1 + (m - M_1) \cdot K_2 + k$, $k = 0, 1, \dots, K_2 - 1$.

6.1.5.2 UE procedure for transmitting code block group based transmissions

If a UE is configured to transmit code block group based transmissions by receiving the higher layer parameter *codeBlockGroupTransmission* in *PUSCH-ServingCellConfig*,

- For an initial transmission of a TB as indicated by the *New Data Indicator* field of the scheduling DCI, the UE may expect that the *CBGTI* field indicates all the CBGs of the TB are to be transmitted, and the UE shall include all the code block groups of the TB.
- For a retransmission of a TB as indicated by the *New Data Indicator* field of the scheduling DCI, the UE shall include only the CBGs indicated by the *CBGTI* field of the scheduling DCI.

A bit value of '0' in the *CBGTI* field indicates that the corresponding CBG is not to be transmitted and '1' indicates that it is to be transmitted. The order of *CBGTI* field bits is such that the CBGs are mapped in order from CBG#0 onwards starting from the MSB.

6.2 UE reference signal (RS) procedure

6.2.1 UE sounding procedure

The UE may be configured with one or more Sounding Reference Signal (SRS) resource sets as configured by the higher layer parameter *SRS-ResourceSet*. For each SRS resource set, a UE may be configured with $K \geq 1$ SRS resources (higher layer parameter *SRS-Resource*), where the maximum value of K is indicated by UE capability [13, 38.306]. The SRS resource set applicability is configured by the higher layer parameter *usage* in *SRS-ResourceSet*. When the higher layer parameter *usage* is set to 'beamManagement', only one SRS resource in each of multiple SRS sets may be transmitted at a given time instant, but the SRS resources in different SRS resource sets with the same time domain behaviour in the same BWP may be transmitted simultaneously.

For aperiodic SRS at least one state of the DCI field is used to select at least one out of the configured SRS resource set(s).

The following SRS parameters are semi-statically configurable by higher layer parameter *SRS-Resource*.

- *srs-ResourceId* determines SRS resource configuration identity.
- Number of SRS ports as defined by the higher layer parameter *nrofSRS-Ports* and described in Clause 6.4.1.4 of [4, TS 38.211].
- Time domain behaviour of SRS resource configuration as indicated by the higher layer parameter *resourceType*, which may be periodic, semi-persistent, aperiodic SRS transmission as defined in Clause 6.4.1.4 of [4, TS 38.211].
- Slot level periodicity and slot level offset as defined by the higher layer parameters *periodicityAndOffset-p* or *periodicityAndOffset-sp* for an SRS resource of type periodic or semi-persistent. The UE is not expected to be configured with SRS resources in the same SRS resource set *SRS-ResourceSet* with different slot level periodicities. For an *SRS-ResourceSet* configured with higher layer parameter *resourceType* set to 'aperiodic', a slot level offset is defined by the higher layer parameter *slotOffset*.
- Number of OFDM symbols in the SRS resource, starting OFDM symbol of the SRS resource within a slot including repetition factor R as defined by the higher layer parameter *resourceMapping* and described in Clause 6.4.1.4 of [4, TS 38.211].
- SRS bandwidth B_{SRS} and C_{SRS} , as defined by the higher layer parameter *freqHopping* and described in Clause 6.4.1.4 of [4, TS 38.211].
- Frequency hopping bandwidth, b_{hop} , as defined by the higher layer parameter *freqHopping* and described in Clause 6.4.1.4 of [4, TS 38.211].

- Defining frequency domain position and configurable shift, as defined by the higher layer parameters *freqDomainPosition* and *freqDomainShift*, respectively, and described in Clause 6.4.1.4 of [4, TS 38.211].
- Cyclic shift, as defined by the higher layer parameter *cyclicShift-n2* or *cyclicShift-n4* for transmission comb value 2 and 4, respectively, and described in Clause 6.4.1.4 of [4, TS 38.211].
- Transmission comb value as defined by the higher layer parameter *transmissionComb* described in Clause 6.4.1.4 of [4, TS 38.211].
- Transmission comb offset as defined by the higher layer parameter *combOffset-n2* or *combOffset-n4* for transmission comb value 2 or 4, respectively, and described in Clause 6.4.1.4 of [4, TS 38.211].
- SRS sequence ID as defined by the higher layer parameter *sequenceId* in Clause 6.4.1.4 of [4].
- The configuration of the spatial relation between a reference RS and the target SRS, where the higher layer parameter *spatialRelationInfo*, if configured, contains the ID of the reference RS. The reference RS may be an SS/PBCH block, CSI-RS configured on serving cell indicated by higher layer parameter *servingCellId* if present, same serving cell as the target SRS otherwise, or an SRS configured on uplink BWP indicated by the higher layer parameter *uplinkBWP*, and serving cell indicated by the higher layer parameter *servingCellId* if present, same serving cell as the target SRS otherwise.

The UE may be configured by the higher layer parameter *resourceMapping* in *SRS-Resource* with an SRS resource occupying $N_s \in \{1, 2, 4\}$ adjacent symbols within the last 6 symbols of the slot, where all antenna ports of the SRS resources are mapped to each symbol of the resource.

When PUSCH and SRS are transmitted in the same slot, the UE may only be configured to transmit SRS after the transmission of the PUSCH and the corresponding DM-RS.

For a UE configured with one or more SRS resource configuration(s), and when the higher layer parameter *resourceType* in *SRS-Resource* is set to 'periodic':

- if the UE is configured with the higher layer parameter *spatialRelationInfo* containing the ID of a reference 'ssb-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference SS/PBCH block, if the higher layer parameter *spatialRelationInfo* contains the ID of a reference 'csi-RS-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference periodic CSI-RS or of the reference semi-persistent CSI-RS, if the higher layer parameter *spatialRelationInfo* containing the ID of a reference 'srs', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the transmission of the reference periodic SRS.

For a UE configured with one or more SRS resource configuration(s), and when the higher layer parameter *resourceType* in *SRS-Resource* is set to 'semi-persistent':

- when a UE receives an activation command, as described in clause 6.1.3.17 of [10, TS 38.321], for an SRS resource, and when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the activation command is transmitted in slot n , the corresponding actions in [10, TS 38.321] and the UE assumptions on SRS transmission corresponding to the configured SRS resource set shall be applied starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH. The activation command also contains spatial relation assumptions provided by a list of references to reference signal IDs, one per element of the activated SRS resource set. Each ID in the list refers to a reference SS/PBCH block, NZP CSI-RS resource configured on serving cell indicated by *Resource Serving Cell ID* field in the activation command if present, same serving cell as the SRS resource set otherwise, or SRS resource configured on serving cell and uplink bandwidth part indicated by *Resource Serving Cell ID* field and *Resource BWP ID* field in the activation command if present, same serving cell and bandwidth part as the SRS resource set otherwise.
- if an SRS resource in the activated resource set is configured with the higher layer parameter *spatialRelationInfo*, the UE shall assume that the ID of the reference signal in the activation command overrides the one configured in *spatialRelationInfo*.
- when a UE receives a deactivation command [10, TS 38.321] for an activated SRS resource set, and when the UE would transmit a PUCCH with HARQ-ACK information in slot n corresponding to the PDSCH carrying the deactivation command, the corresponding actions in [10, TS 38.321] and UE assumption on cessation of SRS

transmission corresponding to the deactivated SRS resource set shall apply starting from the first slot that is after slot $n + 3N_{slot}^{subframe,\mu}$ where μ is the SCS configuration for the PUCCH.

- if the UE is configured with the higher layer parameter *spatialRelationInfo* containing the ID of a reference 'ssb-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference SS/PBCH block, if the higher layer parameter *spatialRelationInfo* contains the ID of a reference 'csi-RS-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference periodic CSI-RS or of the reference semi-persistent CSI-RS, if the higher layer parameter *spatialRelationInfo* contains the ID of a reference 'srs', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the transmission of the reference periodic SRS or of the reference semi-persistent SRS.

If the UE has an active semi-persistent SRS resource configuration and has not received a deactivation command, the semi-persistent SRS configuration is considered to be active in the UL BWP which is active, otherwise it is considered suspended.

For a UE configured with one or more SRS resource configuration(s), and when the higher layer parameter *resourceType* in *SRS-Resource* is set to 'aperiodic':

- the UE receives a configuration of SRS resource sets,
- the UE receives a downlink DCI, a group common DCI, or an uplink DCI based command where a codepoint of the DCI may trigger one or more SRS resource set(s). For SRS in a resource set with usage set to 'codebook' or 'antennaSwitching', the minimal time interval between the last symbol of the PDCCH triggering the aperiodic SRS transmission and the first symbol of SRS resource is N_2 . Otherwise, the minimal time interval between the last symbol of the PDCCH triggering the aperiodic SRS transmission and the first symbol of SRS resource is $N_2 + 14$. The minimal time interval in units of OFDM symbols is counted based on the minimum subcarrier spacing between the PDCCH and the aperiodic SRS.
- If the UE receives the DCI triggering aperiodic SRS in slot n , the UE transmits aperiodic SRS in each of the triggered SRS resource set(s) in slot $\left\lfloor n \cdot \frac{2^{\mu_{SRS}}}{2^{\mu_{PDCCH}}} \right\rfloor + k$ where k is configured via higher layer parameter *slotOffset* for each triggered SRS resources set and is based on the subcarrier spacing of the triggered SRS transmission, μ_{SRS} and μ_{PDCCH} are the subcarrier spacing configurations for triggered SRS and PDCCH carrying the triggering command respectively.
- if the UE is configured with the higher layer parameter *spatialRelationInfo* containing the ID of a reference 'ssb-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference SS/PBCH block, if the higher layer parameter *spatialRelationInfo* contains the ID of a reference 'csi-RS-Index', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the reception of the reference periodic CSI-RS or of the reference semi-persistent CSI-RS, or of the latest reference aperiodic CSI-RS. If the higher layer parameter *spatialRelationInfo* contains the ID of a reference 'srs', the UE shall transmit the target SRS resource with the same spatial domain transmission filter used for the transmission of the reference periodic SRS or of the reference semi-persistent SRS or of the reference aperiodic SRS.

The UE is not expected to be configured with different time domain behavior for SRS resources in the same SRS resource set. The UE is also not expected to be configured with different time domain behavior between SRS resource and associated SRS resources set.

The SRS request field [5, TS38.212] in DCI format 0_1, 1_1 indicates the triggered SRS resource set given in Table 7.3.1.1.2-24 of [5, TS 38.212]. The 2-bit SRS request field [5, TS38.212] in DCI format 2_3 indicates the triggered SRS resource set given in Clause 7.3 of [5, TS 38.212] if the UE is configured with higher layer parameter *srs-TPC-PDCCH-Group* set to 'typeB', or indicates the SRS transmission on a set of serving cells configured by higher layers if the UE is configured with higher layer parameter *srs-TPC-PDCCH-Group* set to 'typeA'.

For PUCCH and SRS on the same carrier, a UE shall not transmit SRS when semi-persistent and periodic SRS are configured in the same symbol(s) with PUCCH carrying only CSI report(s), or only L1-RSRP report(s). A UE shall not transmit SRS when semi-persistent or periodic SRS is configured or aperiodic SRS is triggered to be transmitted in the same symbol(s) with PUCCH carrying HARQ-ACK and/or SR. In the case that SRS is not transmitted due to overlap with PUCCH, only the SRS symbol(s) that overlap with PUCCH symbol(s) are dropped. PUCCH shall not be

transmitted when aperiodic SRS is triggered to be transmitted to overlap in the same symbol with PUCCH carrying semi-persistent/periodic CSI report(s) or semi-persistent/periodic L1-RSRP report(s) only.

In case of intra-band carrier aggregation or in inter-band CA band combination if simultaneous SRS and PUCCH/PUSCH transmissions are not supported by UE, the UE is not expected to be configured with SRS from a carrier and PUSCH/UL DM-RS/UL PT-RS/PUCCH formats from a different carrier in the same symbol.

In case of intra-band carrier aggregation or in inter-band CA band combination if simultaneous SRS and PRACH transmissions are not supported by UE, the UE shall not transmit simultaneously SRS resource(s) from a carrier and PRACH from a different carrier.

In case a SRS resource with *resourceType* set as 'aperiodic' is triggered on the OFDM symbol(s) configured with periodic/semi-persistent SRS transmission, the UE shall transmit the aperiodic SRS resource and only the periodic/semi-persistent SRS symbol(s) overlapping within the symbol(s) are dropped, while the periodic/semi-persistent SRS symbol(s) that are not overlapped with the aperiodic SRS resource are transmitted. In case a SRS resource with *resourceType* set as 'semi-persistent' is triggered on the OFDM symbol(s) configured with periodic SRS transmission, the UE shall transmit the semi-persistent SRS resource and only the periodic SRS symbol(s) overlapping within the symbol(s) are dropped, while the periodic SRS symbol(s) that are not overlapped with the semi-persistent SRS resource are transmitted.

When the UE is configured with the higher layer parameter *usage* in *SRS-ResourceSet* set to 'antennaSwitching', and a guard period of Y symbols is configured according to Clause 6.2.1.2, the UE shall use the same priority rules as defined above during the guard period as if SRS was configured.

6.2.1.1 UE SRS frequency hopping procedure

For a given SRS resource, the UE is configured with repetition factor $R \in \{1, 2, 4\}$ by higher layer parameter *resourceMapping* in *SRS-Resource* where $R \leq N_s$. When frequency hopping within an SRS resource in each slot is not configured ($R=N_s$), each of the antenna ports of the SRS resource in each slot is mapped in all the N_s symbols to the same set of subcarriers in the same set of PRBs. When frequency hopping within an SRS resource in each slot is configured without repetition ($R=1$), according to the SRS hopping parameters B_{SRS} , C_{SRS} and b_{hop} defined in Clause 6.4.1.4 of [4, TS 38.211], each of the antenna ports of the SRS resource in each slot is mapped to different sets of subcarriers in each OFDM symbol, where the same transmission comb value is assumed for different sets of subcarriers. When both frequency hopping and repetition within an SRS resource in each slot are configured ($N_s=4$, $R=2$), each of the antenna ports of the SRS resource in each slot is mapped to the same set of subcarriers within each pair of R adjacent OFDM symbols, and frequency hopping across the two pairs is according to the SRS hopping parameters B_{SRS} , C_{SRS} and b_{hop} .

A UE may be configured $N_s = 2$ or 4 adjacent symbol aperiodic SRS resource with intra-slot frequency hopping within a bandwidth part, where the full hopping bandwidth is sounded with an equal-size subband across N_s symbols when frequency hopping is configured with $R=1$. A UE may be configured $N_s = 4$ adjacent symbols aperiodic SRS resource with intra-slot frequency hopping within a bandwidth part, where the full hopping bandwidth is sounded with an equal-size subband across two pairs of R adjacent OFDM symbols, when frequency hopping is configured with $R=2$. Each of the antenna ports of the SRS resource is mapped to the same set of subcarriers within each pair of R adjacent OFDM symbols of the resource.

A UE may be configured $N_s = 1$ symbol periodic or semi-persistent SRS resource with inter-slot hopping within a bandwidth part, where the SRS resource occupies the same symbol location in each slot. A UE may be configured $N_s = 2$ or 4 symbol periodic or semi-persistent SRS resource with intra-slot and inter-slot hopping within a bandwidth part, where the N -symbol SRS resource occupies the same symbol location(s) in each slot. For $N_s=4$, when frequency hopping is configured with $R=2$, intra-slot and inter-slot hopping is supported with each of the antenna ports of the SRS resource mapped to different sets of subcarriers across two pairs of R adjacent OFDM symbol(s) of the resource in each slot. Each of the antenna ports of the SRS resource is mapped to the same set of subcarriers within each pair of R adjacent OFDM symbols of the resource in each slot. For $N_s=R$, when frequency hopping is configured, inter-slot frequency hopping is supported with each of the antenna ports of the SRS resource mapped to the same set of subcarriers in R adjacent OFDM symbol(s) of the resource in each slot.

6.2.1.2 UE sounding procedure for DL CSI acquisition

When the UE is configured with the higher layer parameter *usage* in *SRS-ResourceSet* set as 'antennaSwitching', the UE may be configured with one of the following configurations depending on the indicated UE capability *supportedSRS-TxPortSwitch* ('t1r2' for 1T2R, 't2r4' for 2T4R, 't1r4' for 1T4R, 't1r4-t2r4' for 1T4R/2T4R, 't1r1' for 1T=1R, 't2r2' for 2T=2R, or 't4r4' for 4T=4R):

- For 1T2R, up to two SRS resource sets configured with a different value for the higher layer parameter *resourceType* in *SRS-ResourceSet* set, where each set has two SRS resources transmitted in different symbols, each SRS resource in a given set consisting of a single SRS port, and the SRS port of the second resource in the set is associated with a different UE antenna port than the SRS port of the first resource in the same set, or
- For 2T4R, up to two SRS resource sets configured with a different value for the higher layer parameter *resourceType* in *SRS-ResourceSet* set, where each SRS resource set has two SRS resources transmitted in different symbols, each SRS resource in a given set consisting of two SRS ports, and the SRS port pair of the second resource is associated with a different UE antenna port pair than the SRS port pair of the first resource, or
- For 1T4R, zero or one SRS resource set configured with higher layer parameter *resourceType* in *SRS-ResourceSet* set to 'periodic' or 'semi-persistent' with four SRS resources transmitted in different symbols, each SRS resource in a given set consisting of a single SRS port, and the SRS port of each resource is associated with a different UE antenna port, and
- For 1T4R, zero or two SRS resource sets each configured with higher layer parameter *resourceType* in *SRS-ResourceSet* set to 'aperiodic' and with a total of four SRS resources transmitted in different symbols of two different slots, and where the SRS port of each SRS resource in the given two sets is associated with a different UE antenna port. The two sets are each configured with two SRS resources, or one set is configured with one SRS resource and the other set is configured with three SRS resources. The UE shall expect that the two sets are both configured with the same values of the higher layer parameters *alpha*, *p0*, *pathlossReferenceRS*, and *srs-PowerControlAdjustmentStates* in *SRS-ResourceSet*. The UE shall expect that the value of the higher layer parameter *aperiodicSRS-ResourceTrigger* or the value of an entry in *AperiodicSRS-ResourceTriggerList* in each *SRS-ResourceSet* is the same, and the value of the higher layer parameter *slotOffset* in each *SRS-ResourceSet* is different. Or,
- For 1T=1R, or 2T=2R, or 4T=4R, up to two SRS resource sets each with one SRS resource, where the number of SRS ports for each resource is equal to 1, 2, or 4.

The UE is configured with a guard period of *Y* symbols, in which the UE does not transmit any other signal, in the case the SRS resources of a set are transmitted in the same slot. The guard period is in-between the SRS resources of the set.

If the indicated UE capability is 't1r4-t2r4', the UE shall expect to be configured with the same number of SRS ports, either one or two, for all SRS resources in the SRS resource set(s).

If the indicated UE capability is 't1r2', 't2r4', 't1r4', 't1r4-t2r4', the UE shall not expect to be configured or triggered with more than one SRS resource set with higher layer parameter *usage* set as 'antennaSwitching' in the same slot. If the indicated UE capability is 't1r1', or 't2r2', or 't4r4' the UE shall not expect to be configured or triggered with more than one SRS resource set with higher layer parameter *usage* set as 'antennaSwitching' in the same symbol.

The value of *Y* is defined by Table 6.2.1.2-1.

Table 6.2.1.2-1: The minimum guard period between two SRS resources of an SRS resource set for antenna switching

μ	$\Delta f = 2^\mu \cdot 15$ [kHz]	<i>Y</i> [symbol]
0	15	1
1	30	1
2	60	1
3	120	2

6.2.1.3 UE sounding procedure between component carriers

For a carrier of a serving cell with slot formats comprised of DL and UL symbols, not configured for PUSCH/PUCCH transmission, the UE shall not transmit SRS whenever SRS transmission (including any interruption due to uplink or

downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*) on the carrier of the serving cell and PUSCH/PUCCH transmission carrying HARQ-ACK/positive SR/RI/CRI and/or PRACH happen to overlap in the same symbol and that can result in uplink transmissions beyond the UE's indicated uplink carrier aggregation capability included in [13, TS 38.306].

For a carrier of a serving cell with slot formats comprised of DL and UL symbols, not configured for PUSCH/PUCCH transmission, the UE shall not transmit a periodic/semi-persistent SRS whenever periodic/semi-persistent SRS transmission (including any interruption due to uplink or downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*) on the carrier of the serving cell and PUSCH transmission carrying aperiodic CSI happen to overlap in the same symbol and that can result in uplink transmissions beyond the UE's indicated uplink carrier aggregation capability included in [13, TS 38.306].

For a carrier of a serving cell with slot formats comprised of DL and UL symbols, not configured for PUSCH/PUCCH transmission, the UE shall drop PUCCH/PUSCH transmission carrying periodic CSI comprising only CQI/PMI, and/or SRS transmission on another serving cell configured for PUSCH/PUCCH transmission whenever the transmission and SRS transmission (including any interruption due to uplink or downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*) on the serving cell happen to overlap in the same symbol and that can result in uplink transmissions beyond the UE's indicated uplink carrier aggregation capability included in [13, TS 38.306].

For a carrier of a serving cell with slot formats comprised of DL and UL symbols, not configured for PUSCH/PUCCH transmission, the UE shall drop PUSCH transmission carrying aperiodic CSI comprising only CQI/PMI whenever the transmission and aperiodic SRS transmission (including any interruption due to uplink or downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*) on the carrier of the serving cell happen to overlap in the same symbol and that can result in uplink transmissions beyond the UE's indicated uplink carrier aggregation capability included in [13, TS 38.306].

For an aperiodic SRS triggered in DCI format 2_3 and if the UE is configured with higher layer parameter *srs-TPC-PDCCH-Group* set to 'typeA', and given by *SRS-CarrierSwitching*, without PUSCH/PUCCH transmission, the order of the triggered SRS transmission on the serving cells follow the order of the serving cells in the indicated set of serving cells configured by higher layers, where the UE in each serving cell transmits the configured one or two SRS resource set(s) with higher layer parameter *usage* set to 'antennaSwitching' and higher layer parameter *resourceType* in *SRS-ResourceSet* set to 'aperiodic'.

For an aperiodic SRS triggered in DCI format 2_3 and if the UE is configured with higher layer parameter *srs-TPC-PDCCH-Group* set to 'typeB' without PUSCH/PUCCH transmission, the order of the triggered SRS transmission on the serving cells follow the order of the serving cells with aperiodic SRS triggered in the DCI, and the UE in each serving cell transmits the configured one or two SRS resource set(s) with higher layer parameter *usage* set to 'antennaSwitching' and higher layer parameter *resourceType* in *SRS-ResourceSet* set to 'aperiodic'.

A UE can be configured with SRS resource(s) on a carrier c_1 with slot formats comprised of DL and UL symbols and not configured for PUSCH/PUCCH transmission. For carrier c_1 , the UE is configured with higher layer parameter *srs-SwitchFromServCellIndex* and *srs-SwitchFromCarrier* the switching from carrier c_2 which is configured for PUSCH/PUCCH transmission. During SRS transmission on carrier c_1 (including any interruption due to uplink or downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*), the UE temporarily suspends the uplink transmission on carrier c_2 .

If the UE is not configured for PUSCH/PUCCH transmission on carrier c_1 with slot formats comprised of DL and UL symbols, and if the UE is not capable of simultaneous reception and transmission on carrier c_1 and serving cell c_2 , the UE is not expected to be configured or indicated with SRS resource(s) such that SRS transmission on carrier c_1 (including any interruption due to uplink or downlink RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*) would collide with the REs corresponding to the SS/PBCH blocks configured for the UE or the slots belonging to a control resource set indicated by *MIB* or *SIB1* on serving cell c_2 .

For n -th ($n \geq 1$) aperiodic SRS transmission on a cell c , upon detection of a positive SRS request on a grant, the UE shall commence this SRS transmission on the configured symbol and slot provided

- it is no earlier than the summation of
 - the maximum time duration between the two durations spanned by N OFDM symbols of the numerology of cell c and the cell carrying the grant respectively, and
 - the UL or DL RF retuning time [11, TS 38.133] as defined by higher layer parameters *switchingTimeUL* and *switchingTimeDL* of *srs-SwitchingTimeNR*,

- it does not collide with any previous SRS transmissions, or interruption due to UL or DL RF retuning time.

otherwise, n -th SRS transmission is dropped, where N is the reported capability as the minimum time interval in unit of symbols, between the DCI triggering and aperiodic SRS transmission.

In case of inter-band carrier aggregation, a UE can simultaneously transmit SRS and PUCCH/PUSCH across component carriers in different bands subject to the UE's capability.

In case of inter-band carrier aggregation, a UE can simultaneously transmit PRACH and SRS across component carriers in different bands subject to UE's capability.

6.2.2 UE DM-RS transmission procedure

When transmitted PUSCH is neither scheduled by DCI format 0_1 with CRC scrambled by C-RNTI, CS-RNTI, SP-CSI-RNTI or MCS-C-RNTI, nor corresponding to a configured grant, the UE shall use single symbol front-loaded DM-RS of configuration type 1 on DM-RS port 0 and the remaining REs not used for DM-RS in the symbols are not used for any PUSCH transmission except for PUSCH with allocation duration of 2 or less OFDM symbols with transform precoding disabled, additional DM-RS can be transmitted according to the scheduling type and the PUSCH duration as specified in Table 6.4.1.1.3-3 of [4, TS38.211] for frequency hopping disabled and as specified in Table 6.4.1.1.3-6 of [4, TS38.211] for frequency hopping enabled, and

If frequency hopping is disabled:

- The UE shall assume *dmrs-AdditionalPosition* equals to 'pos2' and up to two additional DM-RS can be transmitted according to PUSCH duration, or

If frequency hopping is enabled:

- The UE shall assume *dmrs-AdditionalPosition* equals to 'pos1' and up to one additional DM-RS can be transmitted according to PUSCH duration.

When transmitted PUSCH is scheduled by activation DCI format 0_0 with CRC scrambled by CS-RNTI, the UE shall use single symbol front-loaded DM-RS of configuration type provided by higher layer parameter *dmrs-Type* in *configuredGrantConfig* on DM-RS port 0 and the remaining REs not used for DM-RS in the symbols are not used for any PUSCH transmission except for PUSCH with allocation duration of 2 or less OFDM symbols with transform precoding disabled, and additional DM-RS with *dmrs-AdditionalPosition* from *configuredGrantConfig* can be transmitted according to the scheduling type and the PUSCH duration as specified in Table 6.4.1.1.3-3 of [4, TS38.211] for frequency hopping disabled and as specified in Table 6.4.1.1.3-6 of [4, TS38.211] for frequency hopping enabled.

For the UE-specific reference signals generation as defined in Clause 6.4.1.1 of [4, TS 38.211], a UE can be configured by higher layers with one or two scrambling identity(s), $n_{ID}^{DMRS,i}$ $i = 0,1$ which are the same for both PUSCH mapping Type A and Type B.

When transmitted PUSCH is scheduled by DCI format 0_1 with CRC scrambled by C-RNTI, CS-RNTI, SP-CSI-RNTI or MCS-C-RNTI, or corresponding to a configured grant,

- the UE may be configured with higher layer parameter *dmrs-Type* in *DMRS-UplinkConfig*, and the configured DM-RS configuration type is used for transmitting PUSCH in as defined in Clause 6.4.1.1 of [4, TS 38.211].
- the UE may be configured with the maximum number of front-loaded DM-RS symbols for PUSCH by higher layer parameter *maxLength* in *DMRS-UplinkConfig*.
 - if *maxLength* is not configured, single-symbol DM-RS can be scheduled for the UE by DCI or configured by the configured grant configuration, and the UE can be configured with a number of additional DM-RS for PUSCH by higher layer parameter *dmrs-AdditionalPosition*, which can be 'pos0', 'pos1', 'pos2', 'pos3'.
 - if *maxLength* is configured, either single-symbol DM-RS or double symbol DM-RS can be scheduled for the UE by DCI or configured by the configured grant configuration, and the UE can be configured with a number of additional DM-RS for PUSCH by higher layer parameter *dmrs-AdditionalPosition*, which can be 'pos0' or 'pos1'.
- and, the UE shall transmit a number of additional DM-RS as specified in Table 6.4.1.1.3-3 and Table 6.4.1.1.3-4 in -Clause 6.4.1.1.3 of [4, TS 38.211].

If a UE transmitting PUSCH is configured with the higher layer parameter *phaseTrackingRS* in *DMRS-UplinkConfig*, the UE may assume that the following configurations are not occurring simultaneously for the transmitted PUSCH

- any DM-RS ports among 4-7 or 6-11 for DM-RS configurations type 1 and type 2, respectively are scheduled for the UE and PT-RS is transmitted from the UE.

For PUSCH scheduled by DCI format 0_1, by activation DCI format 0_1 with CRC scrambled by CS-RNTI, or configured by configured grant Type 1 configuration, the UE shall assume the DM-RS CDM groups indicated in Tables 7.3.1.1.2-6 to 7.3.1.1.2-23 of Clause 7.3.1.1 of [5, TS38.212] are not used for data transmission, where "1", "2" and "3" for the number of DM-RS CDM group(s) correspond to CDM group 0, {0,1}, {0,1,2}, respectively.

For PUSCH scheduled by DCI format 0_0 or by activation DCI format 0_0 with CRC scrambled by CS-RNTI, the UE shall assume the number of DM-RS CDM groups without data is 1 which corresponds to CDM group 0 for the case of PUSCH with allocation duration of 2 or less OFDM symbols with transform precoding disabled, the UE shall assume that the number of DM-RS CDM groups without data is 3 which corresponds to CDM group {0,1,2} for the case of PUSCH scheduled by activation DCI format 0_0 and the *dmrs-Type* in *cg-DMRS-Configuration* equal to 'type2' and the PUSCH allocation duration being more than 2 OFDM symbols, and the UE shall assume that the number of DM-RS CDM groups without data is 2 which corresponds to CDM group {0,1} for all other cases.

For uplink DM-RS with PUSCH, the UE may assume the ratio of PUSCH EPRE to DM-RS EPRE (β_{DMRS} [dB]) is given by Table 6.2.2-1 according to the number of DM-RS CDM groups without data. The DM-RS scaling factor

$\beta_{\text{PUSCH}}^{\text{DMRS}}$ specified in clause 6.4.1.1.3 of [4, TS 38.211] is given by $\beta_{\text{PUSCH}}^{\text{DMRS}} = 10^{\frac{\beta_{\text{DMRS}}}{20}}$.

Table 6.2.2-1: The ratio of PUSCH EPRE to DM-RS EPRE

Number of DM-RS CDM groups without data	DM-RS configuration type 1	DM-RS configuration type 2
1	0 dB	0 dB
2	-3 dB	-3 dB
3	-	-4.77 dB

6.2.3 UE PT-RS transmission procedure

If a UE is not configured with the higher layer parameter *phaseTrackingRS* in *DMRS-UplinkConfig*, the UE shall not transmit PT-RS. The PTRS is only present on PUSCH scheduled by PDCCH with CRC scrambled by MCS-C-RNTI, C-RNTI, CS-RNTI, SP-CSI-RNTI and on PUSCH corresponding to a configured grant.

6.2.3.1 UE PT-RS transmission procedure when transform precoding is not enabled

When transform precoding is not enabled and if a UE is configured with the higher layer parameter *phaseTrackingRS* in *DMRS-UplinkConfig*,

- the higher layer parameters *timeDensity* and *frequencyDensity* in *PTRS-UplinkConfig* indicate the threshold values ptrs-MCS_i , $i=1,2,3$ and $N_{\text{RB},i}$, $i=0,1$, as shown in Table 6.2.3.1-1 and Table 6.2.3.1-2, respectively.
- if either or both higher layer parameters *timeDensity* and/or *frequencyDensity* in *PTRS-UplinkConfig* are configured, the UE shall assume the PT-RS antenna ports' presence and pattern are a function of the corresponding scheduled MCS and scheduled bandwidth in a corresponding bandwidth part as shown in Table 6.2.3.1-1 and Table 6.2.3.1-2, respectively,
 - if the higher layer parameter *timeDensity* is not configured, the UE shall assume $L_{\text{PT-RS}} = 1$.
 - if the higher layer parameter *frequencyDensity* is not configured, the UE shall assume $K_{\text{PT-RS}} = 2$.
- if none of the higher layer parameters *timeDensity* and *frequencyDensity* in *PTRS-UplinkConfig* are configured, the UE shall assume $L_{\text{PT-RS}} = 1$ and $K_{\text{PT-RS}} = 2$.

Table 6.2.3.1-1: Time density of PT-RS as a function of scheduled MCS

Scheduled MCS	Time density (L_{PT-RS})
$I_{MCS} < \text{ptrs-MCS}_1$	PT-RS is not present
$\text{ptrs-MCS}_1 \leq I_{MCS} < \text{ptrs-MCS}_2$	4
$\text{ptrs-MCS}_2 \leq I_{MCS} < \text{ptrs-MCS}_3$	2
$\text{ptrs-MCS}_3 \leq I_{MCS} < \text{ptrs-MCS}_4$	1

Table 6.2.3.1-2: Frequency density of PT-RS as a function of scheduled bandwidth

Scheduled bandwidth	Frequency density (K_{PT-RS})
$N_{RB} < N_{RB0}$	PT-RS is not present
$N_{RB0} \leq N_{RB} < N_{RB1}$	2
$N_{RB1} \leq N_{RB}$	4

The higher layer parameter *PTRS-UplinkConfig* provides the parameters *ptrs-MCS_i*, *i*=1,2,3 and with values in 0-29 when MCS Table 5.1.3.1-1 is used and 0-28 when MCS Table 5.1.3.1-2 is used, respectively. *ptrs-MCS₄* is not explicitly configured by higher layers but assumed 29 when MCS Table 5.1.3.1-1 is used and 28 when MCS Table 5.1.3.1-2 is used. The higher layer parameter *PTRS-UplinkConfig* provides the parameters *N_{RB*i*}* *i*=0,1 with values in range 1-276.

If the higher layer parameter *PTRS-UplinkConfig* indicates that the time density thresholds *ptrs-MCS_i* = *ptrs-MCS_{i+1}*, then the time density L_{PT-RS} of the associated row where both these thresholds appear in Table 6.2.3.1-1 is disabled. If the higher layer parameter *frequencyDensity* in *PTRS-UplinkConfig* indicates that the frequency density thresholds *N_{RB,i}* = *N_{RB,i+1}*, then the frequency density K_{PT-RS} of the associated row where both these thresholds appear in Table 6.2.3.1-2 is disabled.

If either or both of the parameters PT-RS time density (L_{PT-RS}) and PT-RS frequency density (K_{PT-RS}), shown in Table 6.2.3.1-1 and Table 6.2.3.1-2, indicates that are configured as 'PT-RS not present', the UE shall assume that PT-RS is not present.

When a UE is scheduled to transmit PUSCH with allocation duration of 2 symbols or less, and if L_{PT-RS} is set to 2 or 4, the UE shall not transmit PT-RS. When a UE is scheduled to transmit PUSCH with allocation duration of 4 symbols or less, and if L_{PT-RS} is set to 4, the UE shall not transmit PT-RS.

When a UE is scheduled to transmit PUSCH for retransmission, if the UE is scheduled with $I_{MCS} > V$, where $V = 28$ for MCS Table 5.1.3.1-1 and MCS Table 5.1.3.1-3 and $V = 27$ for MCS Table 5.1.3.1-2, respectively, the MCS for PT-RS time-density determination is obtained from the DCI for the same transport block in the initial transmission, which is smaller than or equal to V .

The maximum number of configured PT-RS ports is given by the higher layer parameter *maxNrofPorts* in *PTRS-UplinkConfig*. The UE is not expected to be configured with a larger number of UL PT-RS ports than it has reported need for.

If a UE has reported the capability of supporting full-coherent UL transmission, the UE shall expect the number of UL PT-RS ports to be configured as one if UL-PTRS is configured.

For codebook or non-codebook based UL transmission, the association between UL PT-RS port(s) and DM-RS port(s) is signalled by *PTRS-DMRS association* field in DCI format 0_1. For a PUSCH corresponding to a configured grant Type 1 transmission, the UE may assume the association between UL PT-RS port(s) and DM-RS port(s) defined by value 0 in Table 7.3.1.1.2-25 or value "00" in Table 7.3.1.1.2-26 described in Clause 7.3.1 of [5, TS38.212].

For PUSCH scheduled by DCI format 0_0 or by activation DCI format 0_0, the UL PT-RS port is associated to DM-RS port 0.

For non-codebook based UL transmission, the actual number of UL PT-RS port(s) to transmit is determined based on SRI(s) in DCI format 0_1 or higher layer parameter *sri-ResourceIndicator* in *rrc-ConfiguredUplinkGrant*. A UE is configured with the PT-RS port index for each configured SRS resource by the higher layer parameter *ptrs-PortIndex* configured by *SRS-Config* if the UE is configured with the higher layer parameter *phaseTrackingRS* in *DMRS-*

UplinkConfig. If the PT-RS port index associated with different SRIs are the same, the corresponding UL DM-RS ports are associated to the one UL PT-RS port.

For partial-coherent and non-coherent codebook based UL transmission, the actual number of UL PT-RS port(s) is determined based on TPMI and/or number of layers which are indicated by *Precoding information and number of layers* field in DCI format 0_1 or configured by higher layer parameter *precodingAndNnumberOfLayers*:

- if the UE is configured with the higher layer parameter *maxNrofPorts* in *PTRS-UplinkConfig* set to 'n2', the actual UL PT-RS port(s) and the associated transmission layer(s) are derived from indicated TPMI as:
- PUSCH antenna port 1000 and 1002 in indicated TPMI share PT-RS port 0, and PUSCH antenna port 1001 and 1003 in indicated TPMI share PT-RS port 1.
 - UL PT-RS port 0 is associated with the UL layer [x] of layers which are transmitted with PUSCH antenna port 1000 and PUSCH antenna port 1002 in indicated TPMI, and UL PT-RS port 1 is associated with the UL layer [y] of layers which are transmitted with PUSCH antenna port 1001 and PUSCH antenna port 1003 in indicated TPMI, where [x] and/or [y] are given by DCI parameter *PTRS-DMRS association* as shown in DCI format 0_1 described in Clause 7.3.1 of [5, TS38.212].

When the UE is scheduled with $Q_p = \{1, 2\}$ PT-RS port(s) in uplink and the number of scheduled layers is n_{layer}^{PUSCH} ,

- If the UE is configured with higher layer parameter *ptrs-Power*, the PUSCH to PT-RS power ratio per layer per RE ρ_{PTRS}^{PUSCH} is given by $\rho_{PTRS}^{PUSCH} = -\alpha_{PTRS}^{PUSCH} [dB]$, where α_{PTRS}^{PUSCH} is shown in the Table 6.2.3.1-3 according to the higher layer parameter *ptrs-Power*, the PT-RS scaling factor β_{PTRS} specified in clause 6.4.1.2.2.1 of [4, TS 38.211] is given by $\beta_{PTRS} = 10^{\frac{\rho_{PTRS}^{PUSCH}}{20}}$ and also on the *Precoding Information and Number of Layers* field in DCI.
- The UE shall assume *ptrs-Power* in *PTRS-UplinkConfig* is set to state "00" in Table 6.2.3.1-3 if not configured or in case of non-codebook based PUSCH.

Table 6.2.3.1-3: Factor related to PUSCH to PT-RS power ratio per layer per RE α_{PTRS}^{PUSCH}

UL-PTRS-power / α_{PTRS}^{PUSCH}	The number of PUSCH layers (n_{layer}^{PUSCH})							
	1	2		3		4		
	All cases	Full coherent	Partial and non-coherent and non-codebook based	Full coherent	Partial and non-coherent and non-codebook based	Full coherent	Partial coherent	Non-coherent and non-codebook based
00	0	3	$3Q_p-3$	4.77	$3Q_p-3$	6	$3Q_p$	$3Q_p-3$
01	0	3	3	4.77	4.77	6	6	6
10	Reserved							
11	Reserved							

6.2.3.2 UE PT-RS transmission procedure when transform precoding is enabled

When transform precoding is enabled and if a UE is configured with the higher layer parameter *transformPrecoderEnabled* in *PTRS-UplinkConfig*,

- the UE shall be configured with the higher layer parameters *sampleDensity* and the UE shall assume the PT-RS antenna ports' presence and PT-RS group pattern are a function of the corresponding scheduled bandwidth in a corresponding bandwidth part, as shown in Table 6.2.3.2-1. The UE shall assume no PT-RS is present when the number of scheduled RBs is less than N_{RBO} if $N_{RBO} > 1$ or if the RNTI equals TC-RNTI.
- and the UE may be configured PT-RS time density $L_{PT-RS} = 2$ with the higher layer parameter *timeDensityTransformPrecoding*. Otherwise, the UE shall assume $L_{PT-RS} = 1$.

- if the higher layer parameter *sampleDensity* indicates that the sample density thresholds $N_{RB,i} = N_{RB,i+1}$, then the associated row where both these thresholds appear in Table 6.2.3.2-1 is disabled.

Table 6.2.3.2-1: PT-RS group pattern as a function of scheduled bandwidth

Scheduled bandwidth	Number of PT-RS groups	Number of samples per PT-RS group
$N_{RB0} \leq N_{RB} < N_{RB1}$	2	2
$N_{RB1} \leq N_{RB} < N_{RB2}$	2	4
$N_{RB2} \leq N_{RB} < N_{RB3}$	4	2
$N_{RB3} \leq N_{RB} < N_{RB4}$	4	4
$N_{RB4} \leq N_{RB}$	8	4

When transform precoding is enabled and if a UE is configured with the higher layer parameter *transformPrecoderEnabled* in *PT-RS-UplinkConfig*, the PT-RS scaling factor β' specified in Clause 6.4.1.2.2.2 of [4, TS 38.211] is determined by the scheduled modulation order as shown in table 6.2.3.2-2.

Table 6.2.3.2-2: PT-RS scaling factor (β') when transform precoding enabled.

Scheduled modulation	PT-RS scaling factor (β')
$\pi/2$ -BPSK	1
QPSK	1
16QAM	$3/\sqrt{5}$
64QAM	$7/\sqrt{21}$
256QAM	$15/\sqrt{85}$

6.3 UE PUSCH frequency hopping procedure

A UE is configured for frequency hopping of scheduled or configured PUSCH transmission by the higher layer parameter *frequencyHopping* provided respectively in *pusch-Config* or in *configuredGrantConfig*. One of two frequency hopping modes can be configured:

- Intra-slot frequency hopping, applicable to single slot and multi-slot PUSCH transmission.
- Inter-slot frequency hopping, applicable to multi-slot PUSCH transmission.

In case of resource allocation type 1, whether or not transform precoding is enabled for PUSCH transmission, the UE may perform PUSCH frequency hopping, if the frequency hopping field in a corresponding detected DCI format or in a random access response UL grant is set to 1, or if for a Type 1 PUSCH transmission with a configured grant the higher layer parameter *frequencyHoppingOffset* is provided, otherwise no PUSCH frequency hopping is performed. When frequency hopping is enabled for PUSCH, the RE mapping is defined in clause 6.3.1.6 of [4, TS 38.211].

For a PUSCH scheduled by RAR UL grant or by DCI format 0_0 with CRC scrambled by TC-RNTI, frequency offsets are obtained as described in clause 8.3 of [6, TS 38.213]. Otherwise, for a PUSCH scheduled by DCI format 0_0/0_1 or a PUSCH based on a Type2 configured UL grant and for resource allocation type 1, frequency offsets are configured by higher layer parameter *frequencyHoppingOffsetLists* in *pusch-Config*:

- when the size of the active BWP is less than 50 PRBs, one of two higher layer configured offsets is indicated in the UL grant
- when the size of the active BWP is equal to or greater than 50 PRBs, one of four higher layer configured offsets is indicated in the UL grant.

For PUSCH based on a Type1 configured UL grant the frequency offset is provided by the higher layer parameter *frequencyHoppingOffset* in *rrc-ConfiguredUplinkGrant*.

In case of intra-slot frequency hopping, the starting RB in each hop is given by:

$$\text{RB}_{\text{start}} = \begin{cases} \text{RB}_{\text{start}} & i = 0 \\ (\text{RB}_{\text{start}} + \text{RB}_{\text{offset}}) \bmod N_{\text{BWP}}^{\text{size}} & i = 1 \end{cases},$$

where $i=0$ and $i=1$ are the first hop and the second hop respectively, and RB_{start} is the starting RB within the UL BWP, as calculated from the resource block assignment information of resource allocation type 1 (described in Clause 6.1.2.2.2) and $\text{RB}_{\text{offset}}$ is the frequency offset in RBs between the two frequency hops. The number of symbols in the first hop is given by $\lfloor N_{\text{ymb}}^{\text{PUSCH},s} / 2 \rfloor$, the number of symbols in the second hop is given by $N_{\text{ymb}}^{\text{PUSCH},s} - \lfloor N_{\text{ymb}}^{\text{PUSCH},s} / 2 \rfloor$, where $N_{\text{ymb}}^{\text{PUSCH},s}$ is the length of the PUSCH transmission in OFDM symbols in one slot.

In case of inter-slot frequency hopping, the starting RB during slot n_s^μ is given by:

$$\text{RB}_{\text{start}}(n_s^\mu) = \begin{cases} \text{RB}_{\text{start}} & n_s^\mu \bmod 2 = 0 \\ (\text{RB}_{\text{start}} + \text{RB}_{\text{offset}}) \bmod N_{\text{BWP}}^{\text{size}} & n_s^\mu \bmod 2 = 1 \end{cases},$$

where n_s^μ is the current slot number within a radio frame, where a multi-slot PUSCH transmission can take place, RB_{start} is the starting RB within the UL BWP, as calculated from the resource block assignment information of resource allocation type 1 (described in Clause 6.1.2.2.2) and $\text{RB}_{\text{offset}}$ is the frequency offset in RBs between the two frequency hops.

6.4 UE PUSCH preparation procedure time

If the first uplink symbol in the PUSCH allocation for a transport block, including the DM-RS, as defined by the slot offset K_2 and the start and length indicator $SLIV$ of the scheduling DCI and including the effect of the timing advance, is no earlier than at symbol L_2 , where L_2 is defined as the next uplink symbol with its CP starting

$T_{\text{proc},2} = \max\left((N_2 + d_{2,1})(2048 + 144) \cdot \kappa 2^{-\mu} \cdot T_c, d_{2,2}\right)$ after the end of the reception of the last symbol of the PDCCH carrying the DCI scheduling the PUSCH, then the UE shall transmit the transport block.

- N_2 is based on μ of Table 6.4-1 and Table 6.4-2 for UE processing capability 1 and 2 respectively, where μ corresponds to the one of $(\mu_{\text{DL}}, \mu_{\text{UL}})$ resulting with the largest $T_{\text{proc},2}$, where the μ_{DL} corresponds to the subcarrier spacing of the downlink with which the PDCCH carrying the DCI scheduling the PUSCH was transmitted and μ_{UL} corresponds to the subcarrier spacing of the uplink channel with which the PUSCH is to be transmitted, and κ is defined in clause 4.1 of [4, TS 38.211].
- If the first symbol of the PUSCH allocation consists of DM-RS only, then $d_{2,1} = 0$, otherwise $d_{2,1} = 1$.
- If the UE is configured with multiple active component carriers, the first uplink symbol in the PUSCH allocation further includes the effect of timing difference between component carriers as given in [11, TS 38.133].
- If the scheduling DCI triggered a switch of BWP, $d_{2,2}$ equals to the switching time as defined in [11, TS 38.133], otherwise $d_{2,2} = 0$.
- For a UE that supports capability 2 on a given cell, the processing time according to UE processing capability 2 is applied if the high layer parameter *processingType2Enabled* in *PUSCH-ServingCellConfig* is configured for the cell and set to *enable*,
- If the PUSCH indicated by the DCI is overlapping with one or more PUCCH channels, then the transport block is multiplexed following the procedure in clause 9.2.5 of [6, TS 38.213], otherwise the transport block is transmitted on the PUSCH indicated by the DCI.

Otherwise the UE may ignore the scheduling DCI.

The value of $T_{\text{proc},2}$ is used both in the case of normal and extended cyclic prefix.

Table 6.4-1: PUSCH preparation time for PUSCH timing capability 1

μ	PUSCH preparation time N_2 [symbols]
0	10
1	12
2	23
3	36

Table 6.4-2: PUSCH preparation time for PUSCH timing capability 2

μ	PUSCH preparation time N_2 [symbols]
0	5
1	5.5
2	11 for frequency range 1

Annex A (informative): Change history

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-05	RAN1#89	R1-1708892	-	-	-	Draft skeleton	0.0.0
2017-07	AH_1706	R1-1712016				Inclusion of agreements up to and including RAN1#AH2	0.0.1
2017-08	AH_1706	R1-1714234				Inclusion of agreements up to and including RAN1#AH2	0.0.2
2017-08	RAN1#90	R1-1714596				Updated editor's version	0.0.3
2017-08	RAN1#90	R1-1714626				Updated editor's version	0.0.4
2017-08	RAN1#90	R1-1715077				Endorsed version by RAN1#90	0.1.0
2017-08	RAN1#90	R1-1715324				Inclusion of agreements up to and including RAN1#90	0.1.1
2017-08	RAN1#90	R1-1715331				Updated editor's version	0.1.2
2017-09	RAN#77	RP-172001				For information to plenary	1.0.0
2017-09	AH_1709	R1-1716930				Inclusion of agreements up to and including RAN1#AH3	1.0.1
2017-10	RAN1#90 bis	R1-1718808				Updated editor's version	1.0.2
2017-10	RAN1#90 bis	R1-1718819				Endorsed version by RAN1#90bis	1.1.0
2017-10	RAN1#90 bis	R1-1719227				Inclusion of agreements up to and including RAN1#90bis	1.1.1
2017-11	RAN1#90 bis	R1-1720113				Inclusion of agreements up to and including RAN1#90bis	1.1.2
2017-11	RAN1#90 bis	R1-1720114				Inclusion of agreements up to and including RAN1#90bis	1.1.3
2017-11	RAN1#90 bis	R1-1721051				Endorsed version	1.2.0
2017-12	RAN1#91	R1-1721344				Inclusion of agreements up to and including RAN1#91	1.3.0
2017-12	RAN#78	RP-172416				Endorsed version for approval by plenary	2.0.0
2017-12	RAN#78					Approved by plenary – Rel-15 spec under change control	15.0.0
2018-03	RAN#79	RP-180200	0001		F	CR capturing the Jan18 ad-hoc and RAN1#92 meeting agreements	15.1.0
2018-06	RAN#80	RP-181172	0002	1	F	CR to 38.214 capturing the RAN1#92bis and RAN1#93 meeting agreements	15.2.0
2018-06	RAN#80	RP-181257	0003	-	B	CR to 38.214 capturing the RAN1#92bis and RAN1#93 meeting agreements related to URLLC	15.2.0
2018-06	RAN#80	RP-181172	0004	-	F	CR to 38.214: maintenance according to agreed Rel 15 features	15.2.0
2018-09	RAN#81	RP-181789	0005	-	F	CR to 38.214 capturing the RAN1#94 meeting agreements	15.3.0
2018-12	RAN#82	RP-182523	0006	2	F	Combined CR of all essential corrections to 38.214 from RAN1#94bis and RAN1#95	15.4.0
2019-03	RAN#83	RP-190632	0007	3	F	Correction to aperiodic CSI-RS triggering with different numerology between PDCCH and CSI-RS	15.5.0
2019-03	RAN#83	RP-190450	0009	-	F	Correction on CSI-RS configuration in 38.214	15.5.0
2019-03	RAN#83	RP-190450	0010	-	F	Correction on uplink resource allocation type 1	15.5.0
2019-03	RAN#83	RP-190450	0011	-	F	Correction on determination of the resource allocation table for PUSCH with SP CSI	15.5.0
2019-03	RAN#83	RP-190450	0012	-	F	Correction on PUSCH resource allocation	15.5.0
2019-03	RAN#83	RP-190450	0013	-	F	Change Request for alignment of frequency domain resource allocation with 38.213 for a PUSCH transmission scheduled by a RAR UL grant	15.5.0
2019-03	RAN#83	RP-190450	0014	-	F	CR on sequential PDSCH and PUSCH scheduling	15.5.0
2019-03	RAN#83	RP-190450	0015	-	F	CR on out of HARQ order with multiple PDSCHs within one slot	15.5.0
2019-03	RAN#83	RP-190450	0016	-	F	Correction to LBRM restriction	15.5.0
2019-03	RAN#83	RP-190450	0017	-	F	CR on PDSCH beam indication	15.5.0
2019-03	RAN#83	RP-190450	0018	-	F	Correction on TCI indication for multi-slot PDSCH	15.5.0
2019-03	RAN#83	RP-190450	0019	-	F	Clarifications on CSI reporting on PUSCH	15.5.0
2019-03	RAN#83	RP-190450	0020	-	F	QCL properties of Msg4 in CONNECTED Mode	15.5.0
2019-03	RAN#83	RP-190450	0022	1	F	CR on dynamic grant overriding configured grant	15.5.0
2019-03	RAN#83	RP-190450	0023	-	F	Correction on PUSCH with configured grant	15.5.0
2019-03	RAN#83	RP-190450	0024	-	F	Corrections to 38.214	15.5.0
2019-03	RAN#83	RP-190425	0025	1	F	CR on QCL assumption for receiving PDSCH for RAR	15.5.0
2019-06	RAN#84	RP-191552	0035	-	F	Removal of "Correction to aperiodic CSI-RS triggering with different numerology between PDCCH and CSI-RS"	15.6.0
2019-06	RAN#84	RP-191284	0026	-	F	Corrections on non-codebook based UL transmission to TS 38.214	15.6.0
2019-06	RAN#84	RP-191284	0027	-	F	CR on UE procedure for PDSCH and PUSCH	15.6.0
2019-06	RAN#84	RP-191284	0028	-	F	Correction on configured scheduling PUSCH repetition with dynamic SFI	15.6.0
2019-06	RAN#84	RP-191284	0029	-	F	CR on rate matching for PDSCH scheduled by DCI format 1_0	15.6.0
2019-06	RAN#84	RP-191284	0030	-	F	Clarification on CG transmission opportunities	15.6.0
2019-06	RAN#84	RP-191284	0031	5	F	Corrections to 38.214 including alignment of terminology across specifications	15.6.0
2019-06	RAN#84	RP-191284	0032	-	F	CR to 38.214 clarifying calculation of DataRate and DataRateCC	15.6.0
2019-06	RAN#84	RP-191284	0033	-	F	Correction on PUSCH retransmission for a serving cell configured with two uplinks	15.6.0
2019-06	RAN#84	RP-191284	0034	-	F	Corrections to 38.214 regarding the MAC CE activation/deactivation timing in mixed numerology scenario	15.6.0

2019-09	RAN#85	RP-191943	0037	-	F	Correction on UE receiving PDSCH procedure in FR2	15.7.0
2019-09	RAN#85	RP-191943	0038	-	F	Correction on slot aggregation	15.7.0
2019-09	RAN#85	RP-191943	0039	-	F	CR on grant-based PDSCH overlapping with SPS PDSCH	15.7.0
2019-09	RAN#85	RP-191943	0040	-	F	Correction on the resource mapping of PDSCH in TS 38.214	15.7.0
2019-09	RAN#85	RP-191943	0041	1	F	Corrections to 38.214 including alignment of terminology across specifications in RAN1#98	15.7.0
2019-09	RAN#85	RP-191943	0042	-	F	Clarification of PUSCH with SP-CSI overlapping with PUSCH with data	15.7.0
2019-12	RAN#86	RP-192627	0045	-	F	Correction on resource allocation for uplink transmission with configured grant Type 1	15.8.0
2019-12	RAN#86	RP-192627	0046	-	F	Clarification to the dynamically scheduled PDSCH collision with SPS-PDSCH	15.8.0
2019-12	RAN#86	RP-192627	0047	-	F	Correction on rate-matching for LTE-CRS-toMatchAround	15.8.0
2019-12	RAN#86	RP-192627	0048	-	F	Correction on timing for MAC CE applicability in 38.214	15.8.0
2019-12	RAN#86	RP-192627	0049	-	F	Corrections to 38.214 including alignment of terminology across specifications in RAN1#98bis and RAN1#99	15.8.0
2020-03	RAN#87-e	RP-200181	0077	-	F	CR on UL PTRS density selection	15.9.0
2020-06	RAN#88-e	RP-200683	0079	-	F	CR on CSI reporting for BWP size < 24 PRBs	15.10.0
2020-06	RAN#88-e	RP-200683	0081	-	F	CR on 38.214 PDSCH resource mapping	15.10.0
2020-06	RAN#88-e	RP-200683	0083	-	F	CR to 38.214 clarification on resource and port occupation of duplicate CSI-RS resources	15.10.0
2020-06	RAN#88-e	RP-200683	0096	-	F	CR on SRS for 38.214	15.10.0
2020-06	RAN#88-e	RP-200683	0098	-	F	CR on 38.214 rate-matching for PDSCH with SPS	15.10.0
2020-06	RAN#88-e	RP-200683	0100	-	F	Correction for SP-CSI reporting on PUSCH	15.10.0
2020-06	RAN#88-e	RP-200683	0102	-	F	CR on port and CSI-RS resource counting	15.10.0
2020-06	RAN#88-e	RP-200683	0104	-	F	Correction of RRC parameter name for AP-TRS	15.10.0
2020-06	RAN#88-e	RP-200683	0105	-	F	Correction on 38.214 for PUSCH with UL skipping	15.10.0

History

Document history		
V15.2.0	July 2018	Publication
V15.3.0	October 2018	Publication
V15.4.0	April 2019	Publication
V15.5.0	May 2019	Publication
V15.6.0	July 2019	Publication
V15.7.0	October 2019	Publication
V15.8.0	January 2020	Publication
V15.9.0	April 2020	Publication
V15.10.0	July 2020	Publication