

# ETSI TS 138 521-3 V15.4.1 (2020-05)



**5G;  
NR;  
User Equipment (UE) conformance specification;  
Radio transmission and reception;  
Part 3: Range 1 and Range 2 Interworking  
operation with other radios  
(3GPP TS 38.521-3 version 15.4.1 Release 15)**



---

Reference

RTS/TSGR-0538521-3v41

---

Keywords

5G

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at [www.etsi.org/deliver](http://www.etsi.org/deliver).

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020.

All rights reserved.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

**3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

**oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

**GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

## Intellectual Property Rights

### Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

### Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

---

## Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

---

## Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

# Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	13
1 Scope .....	14
2 References .....	14
3 Definitions, symbols and abbreviations .....	15
3.1 Definitions .....	15
3.2 Symbols.....	15
3.3 Abbreviations .....	16
4 General .....	16
4.1 Relationship between minimum requirements and test requirements .....	16
4.2 Applicability of minimum requirements .....	17
4.3 Specification suffix information.....	17
4.4 Test points analysis .....	18
4.5 Applicability and test coverage rules.....	18
4.5.1 Test coverage across 5G NR architecture options .....	18
4.6 E-UTRA configuration for EN-DC FR1 tests applying the E-UTRA anchor-agnostic approach .....	19
4.7 E-UTRA configuration for EN-DC FR2 tests applying the E-UTRA anchor-agnostic approach .....	20
5 Operating bands and Channel arrangement.....	22
5.1 General .....	22
5.2 Operating bands.....	23
5.2A Operating bands for CA .....	23
5.2A.1 Inter-band CA between FR1 and FR2.....	23
5.2B Operating bands for DC .....	23
5.2B.1 General.....	23
5.2B.2 to 5.2B.7 Void .....	23
5.3 UE Channel bandwidth .....	23
5.3A UE Channel bandwidth for CA .....	23
5.3A.1 Inter-band CA between FR1 and FR2.....	23
5.3B UE Channel bandwidth for EN-DC.....	23
5.3B.1 Intra-band EN-DC in FR1.....	24
5.3B.1.1 General .....	24
5.3B.1.2 BCS for Intra-band contiguous EN-DC .....	24
5.3B.1.3 BCS for Intra-band non-contiguous EN-DC.....	25
5.4 Channel arrangement.....	26
5.4A Channel arrangement for CA.....	26
5.4B Channel arrangement for DC.....	26
5.4B.1 Channel spacing for intra-band EN-DC carriers.....	26
5.5 Configuration .....	27
5.5A Configuration for CA .....	27
5.5A.1 Inter-band CA configurations between FR1 and FR2.....	27
5.5B Configuration for DC .....	31
5.5B.1 General.....	31
5.5B.2 Intra-band contiguous EN-DC .....	31
5.5B.3 Intra-band non-contiguous EN-DC.....	31
5.5B.4 Inter-band EN-DC within FR1.....	32
5.5B.4.1 Inter-band EN-DC configurations within FR1 (two bands) .....	33
5.5B.4.2 Inter-band EN-DC configurations within FR1 (three bands).....	37
5.5B.4.3 Inter-band EN-DC configurations within FR1 (four bands).....	44
5.5B.4.4 Inter-band EN-DC configurations within FR1 (five bands).....	50
5.5B.4.5 Inter-band EN-DC configurations within FR1 (six bands) .....	53
5.5B.5 Inter-band EN-DC including FR2.....	53

5.5B.5.1	Inter-band EN-DC configurations including FR2 (two bands) .....	54
5.5B.5.2	Inter-band EN-DC configurations including FR2 (three bands) .....	60
5.5B.5.3	Inter-band EN-DC configurations including FR2 (four bands).....	65
5.5B.5.4	Inter-band EN-DC configurations including FR2 (five bands).....	68
5.5B.5.5	Inter-band EN-DC configurations including FR2 (six bands).....	69
5.5B.6	Inter-band EN-DC including FR1 and FR2 .....	69
5.5B.6.1	Void.....	70
5.5B.6.2	Inter-band EN-DC configurations including FR1 and FR2 (three bands).....	70
5.5B.6.3	Inter-band EN-DC configurations including FR1 and FR2 (four bands) .....	73
5.5B.6.4	Inter-band EN-DC configurations including FR1 and FR2 (five bands) .....	74
5.5B.6.5	Inter-band EN-DC configurations including FR1 and FR2 (six bands) .....	75
5.5B.7	Inter-band NR-DC between FR1 and FR2.....	75
5.5B.7.1	Inter-band NR-DC configurations between FR1 and FR2 (two bands) .....	76
6	Transmitter characteristics .....	76
6.1	General .....	76
6.2	Transmitter power .....	77
6.2A	Transmitter power for CA without EN-DC.....	77
6.2A.1	UE maximum output power for CA.....	77
6.2A.1.1	UE maximum output power for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	77
6.2A.2	UE maximum output power reduction for CA.....	77
6.2A.2.1	UE maximum output power reduction for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	77
6.2A.3	UE additional maximum output power reduction for CA.....	78
6.2A.3.1	UE additional maximum output power reduction for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	78
6.2A.4	Configured output power level for CA .....	78
6.2A.4.1	Configured output power level for inter-band NR CA between FR 1 and FR 2 without EN-DC.....	78
6.2A.4.2	$\Delta TIB,c$ for CA.....	78
6.2A.4.2.1	$\Delta TIB,c$ for inter-band CA between FR 1 and FR 2 .....	78
6.2B	Transmitter power for EN-DC.....	78
6.2B.1	UE Maximum Output Power for EN-DC .....	78
6.2B.1.1	UE Maximum Output Power for Intra-Band Contiguous EN-DC .....	79
6.2B.1.2	UE Maximum Output Power for Intra-Band Non-Contiguous EN-DC .....	83
6.2B.1.3	UE Maximum Output Power for Inter-Band EN-DC within FR1.....	87
6.2B.1.4	UE Maximum Output Power for Inter-Band EN-DC including FR2.....	100
6.2B.1.4.1	UE maximum output power - EIRP and TRP.....	100
6.2B.1.4.2	UE maximum output power - Spherical coverage.....	101
6.2B.1.4.2	UE maximum output power for Inter-band EN-DC including FR2 (3 CCs).....	102
6.2B.1.4.2.1	UE maximum output power - EIRP and TRP.....	102
6.2B.1.4.3	UE maximum output power for Inter-band EN-DC including FR2 (4 CCs).....	103
6.2B.1.4.3.1	UE maximum output power - EIRP and TRP.....	103
6.2B.1.4.4	UE maximum output power for Inter-band EN-DC including FR2 (5 CCs).....	104
6.2B.1.4.4.1	UE maximum output power - EIRP and TRP.....	104
6.2B.2	UE Maximum Output Power reduction for EN-DC .....	105
6.2B.2.0	General .....	105
6.2B.2.1	UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC .....	105
6.2B.2.2	UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC .....	110
6.2B.2.2.1	Test purpose .....	110
6.2B.2.2.2	Test applicability .....	111
6.2B.2.2.3	Minimum conformance requirements.....	111
6.2B.2.2.4	Test description .....	111
6.2B.2.2.5	Test requirement.....	112
6.2B.2.3	UE Maximum Output Power reduction for Inter-Band EN-DC within FR1.....	112
6.2B.2.3.5	Test requirement.....	113
6.2B.2.4	UE Maximum Output Power reduction for Inter-Band EN-DC including FR2.....	113
6.2B.2.4.1	Test purpose .....	113
6.2B.2.4.2	Test applicability .....	113
6.2B.2.4.3	Minimum conformance requirements.....	113
6.2B.2.4.4	Test description .....	113
6.2B.2.4.5	Test requirement.....	114
6.2B.2.4.2	Transmit OFF Power for Inter-band EN-DC including FR2 (3 CCs).....	114

6.2B.2.4.3	Transmit OFF Power for Inter-band EN-DC including FR2 (4 CCs).....	115
6.2B.2.4.4	Transmit OFF Power for Inter-band EN-DC including FR2 (5 CCs).....	116
6.2B.2.5	UE Maximum Output power reduction for inter-band EN-DC including both FR1 and FR2 .....	117
6.2B.3	UE additional maximum output power reduction for EN-DC .....	117
6.2B.3.1	UE Additional Maximum Output Power reduction for Intra-band contiguous EN-DC .....	117
6.2B.3.1.3.2.1	A-MPR <sub>IM3</sub> for NS_04 to meet -13 dBm / 1MHz for 26dBm UE power.....	120
6.2B.3.1.3.2.2	A-MPR for NS_04 to meet -25 dBm / 1MHz for 26 dBm UE power .....	121
6.2B.3.2	UE Additional Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC .....	140
6.2B.3.2.3.1	A-MPR for NS_04.....	141
6.2B.3.3	UE Additional Maximum Output Power reduction for Inter-Band EN-DC within FR1 .....	150
6.2B.3.3.1	Test purpose .....	151
6.2B.3.3.2	Test applicability .....	151
6.2B.3.3.3	Minimum conformance requirements.....	151
6.2B.3.3.4	Test description .....	151
6.2B.3.4	UE Additional Maximum Output Power reduction for Inter-Band EN-DC including FR2.....	151
6.2B.3.5	UE Additional Maximum Output power reduction for inter-band EN-DC including both FR1 and FR2.....	152
6.2B.4	Configured Output Power for EN-DC .....	153
6.2B.4.1	Configured Output Power Level for EN-DC .....	153
6.2B.4.1.0	Minimum Conformance Requirements .....	153
6.2B.4.1.0.1	Configured output power level .....	153
6.2B.4.1.0.1.1	Intra-band contiguous EN-DC.....	153
6.2B.4.1.0.1.2	Intra-band non-contiguous EN-DC .....	156
6.2B.4.1.0.1.3	Inter-band EN-DC within FR1 .....	157
6.2B.4.1.0.1.4	Inter-band EN-DC including FR2 .....	159
6.2B.4.1.0.1.5	Inter-band EN-DC including both FR1 and FR2.....	160
6.2B.4.1.0.2	$\Delta T_{IB,c}$ for EN-DC .....	160
6.2B.4.1.0.2.1	Intra-band contiguous EN-DC.....	160
6.2B.4.1.0.2.2	Intra-band non-contiguous EN-DC .....	160
6.2B.4.1.0.2.3	Inter-band EN-DC within FR1 .....	161
6.2B.4.1.0.2.4	Inter-band EN-DC including FR2 .....	178
6.2B.4.1.0.2.5	Inter-band EN-DC including both FR1 and FR2.....	179
6.2B.4.1.1	Configured Output Power Level for Intra-Band Contiguous EN-DC .....	179
6.2B.4.2	$\Delta T_{IB,c}$ for EN-DC .....	185
6.2B.4.2.1	Intra-Band Contiguous EN-DC .....	185
6.2B.4.2.2	Intra-Band non-Contiguous EN-DC .....	185
6.2B.4.2.3	Inter-Band EN-DC within FR1.....	186
6.2B.4.2.3.3	$\Delta T_{IB,c}$ for EN-DC four bands .....	195
6.2B.4.2.3.4	$\Delta T_{IB,c}$ for EN-DC five bands .....	200
6.2B.4.2.3.5	$\Delta T_{IB,c}$ for EN-DC six bands .....	203
6.2B.4.2.4	Inter-band EN-DC including FR2 .....	203
6.2B.4.2.4.1	$\Delta T_{IB,c}$ for EN-DC two bands .....	203
6.2B.4.2.4.2	$\Delta T_{IB,c}$ for EN-DC three bands .....	203
6.2B.4.2.4.3	$\Delta T_{IB,c}$ for EN-DC four bands .....	203
6.2B.4.2.4.4	$\Delta T_{IB,c}$ for EN-DC five bands.....	203
6.2B.4.2.4.5	$\Delta T_{IB,c}$ for EN-DC six bands .....	204
6.2B.4.2.5	Inter-band EN-DC including both FR1 and FR2.....	204
6.2B.4.2.5.1	$\Delta T_{IB,c}$ for EN-DC three bands .....	204
6.2B.4.2.5.2	$\Delta T_{IB,c}$ for EN-DC four bands .....	204
6.2B.4.2.5.3	$\Delta T_{IB,c}$ for EN-DC five bands.....	204
6.2B.4.2.5.4	$\Delta T_{IB,c}$ for EN-DC six bands .....	204
6.3	Output power dynamics.....	204
6.3B	.....	204
6.3B.1	Minimum Output Power for EN-DC .....	204
6.3B.1.1	Minimum Output Power for intra-band contiguous EN-DC .....	204
6.3B.1.2	Minimum output power for intra-band non-contiguous EN-DC.....	205
6.3B.1.3	Minimum output power for inter-band EN-DC within FR1.....	207
6.3B.1.4	Minimum Output Power for EN-DC Interband including FR2.....	208
6.3B.2	Transmit OFF Power for EN-DC.....	209
6.3B.2.1	Transmit OFF Power for intra-band contiguous EN-DC .....	209
6.3B.2.1.1	Test purpose .....	209
6.3B.2.1.2	Test applicability .....	209

6.3B.2.1.3	Minimum conformance requirements.....	209
6.3B.2.1.4	Test description .....	209
6.3B.2.1.5	Test requirements .....	209
6.3B.2.2	Transmit OFF Power for intra-band non-contiguous EN-DC.....	210
6.3B.2.2.1	Test purpose .....	210
6.3B.2.2.2	Test applicability .....	210
6.3B.2.2.3	Minimum conformance requirements.....	210
6.3B.2.2.4	Test description .....	210
6.3B.2.2.5	Test requirements .....	210
6.3B.2.3	Transmit OFF Power for inter-band EN-DC within FR1.....	210
6.3B.2.3.1	Test purpose .....	210
6.3B.2.3.2	Test applicability .....	210
6.3B.2.3.3	Minimum conformance requirements.....	210
6.3B.2.3.4	Test description .....	210
6.3B.2.3.5	Test requirements .....	211
6.3B.3	Tx ON/OFF time mask/PUCCH time mask for EN-DC.....	211
6.3B.3.1	Tx ON/OFF time mask for intra-band contiguous EN-DC .....	211
6.3B.3.1.1	Test purpose .....	211
6.3B.3.1.2	Test applicability .....	211
6.3B.3.1.3	Minimum conformance requirements.....	211
6.3B.3.1.4	Test description .....	211
6.3B.3.2	Tx ON/OFF time mask for intra-band non-contiguous EN-DC.....	211
6.3B.3.2.1	Test purpose .....	211
6.3B.3.2.2	Test applicability .....	212
6.3B.3.2.3	Minimum conformance requirements.....	212
6.3B.3.2.4	Test description .....	212
6.3B.3.2.5	Test requirements .....	212
6.3B.3.3	Tx ON/OFF time mask for inter-band EN-DC within FR1.....	212
6.3B.3.3.1	Test purpose .....	212
6.3B.3.3.2	Test applicability .....	212
6.3B.3.3.3	Minimum conformance requirements.....	212
6.3B.3.3.4	Test description .....	212
6.3B.3.3.5	Test requirements .....	213
6.3B.4	PRACH time mask for EN-DC.....	213
6.3B.4.1	PRACH time mask for intra-band contiguous EN-DC .....	213
6.3B.4.2	PRACH Time Mask for intra-band non-contiguous EN-DC .....	214
6.3B.4.3	PRACH Time Mask for inter-band EN-DC within FR1 .....	214
6.3B.4.3.1	Test purpose .....	215
6.3B.5	Output power dynamics for EN-DC with UL sharing from UE perspective .....	216
6.3B.5.1	E-UTRA and NR switching time mask for TDM based UL sharing from UE perspective .....	216
6.3B.6	Output power dynamics for intra-band EN-DC without dual PA capability .....	216
6.3B.7	Output power dynamics for intra-band EN-DC with dual PA capability .....	216
6.4	Transmit signal quality.....	216
6.4A	Transmit Signal Quality for inter-band NR CA between FR and FR2 without EN-DC.....	216
6.4A.1	Frequency error for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	216
6.4A.2	Transmit Modulation Quality for inter-band NR CA without EN-DC.....	217
6.4A.2.1	Error Vector Magnitude for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	217
6.4A.2.2	Carrier Leakage for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	217
6.4A.2.3	In-band Emissions for inter-band NR CA between FR 1 and FR 2 without EN-DC .....	217
6.4B	.....	218
6.4B.1	Frequency error.....	218
6.4B.1.1	Frequency error for Intra-band contiguous EN-DC .....	218
6.4B.1.2	Frequency error for Intra-band non-contiguous EN-DC .....	218
6.4B.1.3	Frequency error for Inter-band EN-DC within FR1 .....	218
6.4B.1.3.1	Test purpose .....	218
6.4B.1.3.2	Test applicability .....	218
6.4B.1.3.3	Minimum conformance requirements.....	218
6.4B.1.3.4	Test description .....	218
6.4B.1.3.5	Test Requirement.....	219
6.4B.1.4	.....	219
6.4B.1.5	Frequency Error for inter-band EN-DC including FR2.....	219
6.4B.1.5.2	Frequency Error for Inter-band EN-DC including FR2 (3 CCs) .....	220

6.4B.1.5.3	Frequency Error for Inter-band EN-DC including FR2 (4 CCs) .....	221
6.4B.1.5.4	Frequency Error for Inter-band EN-DC including FR2 (5 CCs) .....	222
6.4B.2	.....	223
6.4B.2.1	Transmit Modulation Quality for intra-band contiguous EN-DC .....	223
6.4B.2.1.1	Error Vector Magnitude for intra-band contiguous EN-DC .....	223
6.4B.2.1.2	Carrier Leakage for intra-band contiguous EN-DC .....	224
6.4B.2.1.3	In-band Emissions for intra-band contiguous EN-DC .....	225
6.4B.2.2	Transmit Modulation Quality for intra-band non-contiguous EN-DC .....	229
6.4B.2.2.1	Error Vector Magnitude for intra-band non-contiguous EN-DC .....	230
6.4B.2.2.2	Carrier Leakage for intra-band non-contiguous EN-DC .....	230
6.4B.2.2.3	In-band Emissions for intra-band non-contiguous EN-DC .....	231
6.4B.2.2.4	EVM Equalizer Flatness for intra-band non-contiguous EN-DC .....	236
6.4B.2.3	Transmit Modulation Quality for inter-band EN-DC within FR1 .....	238
6.4B.2.3.1	Error Vector Magnitude for inter-band EN-DC within FR1 .....	238
6.4B.2.3.2	Carrier Leakage for inter-band EN-DC within FR1 .....	238
6.4B.2.3.3	In-band Emissions for inter-band EN-DC within FR1 .....	239
6.4B.2.3.4	EVM Equalizer Flatness for inter-band EN-DC within FR1 .....	240
6.4B.2.4	Transmit Modulation Quality for inter-band EN-DC including FR2 .....	241
6.4B.2.4.1	Error Vector Magnitude for inter-band EN-DC including FR2 .....	241
6.4B.2.4.2	Carrier Leakage for inter-band EN-DC including FR2 .....	242
6.4B.2.4.3	In-band Emissions for inter-band EN-DC including FR2 .....	242
6.4B.2.4.4	EVM Equalizer Flatness for inter-band EN-DC including FR2 .....	243
6.5	Output RF spectrum emissions .....	244
6.5A	Output RF spectrum emissions for CA .....	244
6.5A.1	Occupied bandwidth for CA without EN-DC .....	244
6.5A.2	Out-of-band emissions for CA without EN-DC .....	245
6.5A.2.2	Additional Spectrum emissions mask for CA without EN-DC .....	245
6.5A.2.3	Adjacent channel leakage ratio for CA without EN-DC .....	245
6.5A.3	Spurious emissions for CA without EN-DC .....	245
6.5B	Output RF spectrum emissions for DC .....	245
6.5B.1	Occupied bandwidth for EN-DC .....	245
6.5B.1.1	Occupied bandwidth for Intra-Band Contiguous EN-DC .....	245
6.5B.1.2	Occupied bandwidth for Intra-Band Non-Contiguous EN-DC .....	247
6.5B.1.3	Occupied bandwidth for Inter-Band EN-DC within FR1 .....	248
6.5B.1.4	Occupied bandwidth for Inter-Band EN-DC including FR2 .....	249
6.5B.1.4.2	Occupied bandwidth for Inter-band EN-DC including FR2 (3 CCs) .....	250
6.5B.1.4.3	Occupied bandwidth for Inter-band EN-DC including FR2 (4 CCs) .....	251
6.5B.1.4.4	Occupied bandwidth for Inter-band EN-DC including FR2 (5 CCs) .....	252
6.5B.2	Out-of-band emissions for EN-DC .....	253
6.5B.2.1	Out-of-band emissions for Intra-band contiguous EN-DC .....	253
6.5B.2.2	Out-of-band emissions for Intra-band non-contiguous EN-DC .....	268
6.5B.2.2.1	Spectrum emissions mask for intra-band non-contiguous EN-DC .....	268
6.5B.2.2.3	Adjacent channel leakage ratio for intra-band non-contiguous EN-DC .....	269
6.5B.2.3	Out-of-band emissions for Inter-band EN-DC within FR1 .....	271
6.5B.2.3.1	Spectrum emissions mask for Inter-band EN-DC within FR1 .....	271
6.5B.2.3.2	Additional Spectrum emissions mask for Inter-band EN-DC within FR1 .....	271
6.5B.2.3.3	Adjacent channel leakage ratio for inter-band EN-DC within FR1 .....	271
6.5B.2.4	Out-of-band emissions for Inter-band EN-DC including FR2 .....	272
6.5B.2.4.1	Spectrum emissions mask for Inter-band EN-DC including FR2 .....	272
6.5B.2.4.1.1	Test purpose .....	272
6.5B.2.4.1.2	Test applicability .....	272
6.5B.2.4.1.3	Minimum conformance requirements .....	272
6.5B.2.4.1.4	Test description .....	273
6.5B.2.4.1.4.1	Initial conditions .....	273
6.5B.2.4.1.5	Test requirement .....	273
6.5B.2.4.1.2	Spectrum emissions mask for Inter-band EN-DC including FR2 (3 CCs) .....	273
6.5B.2.4.1.3	Spectrum emissions mask for Inter-band EN-DC including FR2 (4 CCs) .....	274
6.5B.2.4.1.4	Spectrum emissions mask for Inter-band EN-DC including FR2 (5 CCs) .....	275
6.5B.2.4.3	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 .....	276
6.5B.2.4.3.1	Test purpose .....	276
6.5B.2.4.3.2	Test applicability .....	276
6.5B.2.4.3.3	Minimum conformance requirements .....	276



6.5B.2.4.3.4	Test description.....	276
6.5B.2.4.3.4.1	Initial conditions .....	276
6.5B.2.4.3.5	Test requirement .....	277
6.5B.2.4.3.2	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (3 CCs) .....	277
6.5B.2.4.3.3	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (4 CCs) .....	278
6.5B.2.4.3.4	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (5 CCs) .....	279
6.5B.3	Spurious emissions for EN-DC.....	280
6.5B.3.1	Spurious Emissions for intra-band contiguous EN-DC.....	280
6.5B.3.1.1	General spurious emissions for intra-band contiguous EN-DC.....	280
6.5B.3.1.2	Spurious emission band UE co-existence for intra-band contiguous EN-DC .....	282
6.5B.3.2	Spurious Emissions for intra-band non-contiguous EN-DC .....	285
6.5B.3.2.1	General spurious emissions for Intra-band non-contiguous EN-DC .....	285
6.5B.3.2.2	Spurious emission band UE co-existence for intra-band non-contiguous EN-DC .....	287
6.5B.3.2.2.1	Test purpose.....	287
6.5B.3.2.2.2	Test applicability.....	287
6.5B.3.2.2.3	Minimum conformance requirements.....	287
6.5B.3.2.2.4	Test description.....	288
6.5B.3.2.2.5	Test Requirement.....	289
6.5B.3.3	Spurious Emissions for Inter-band EN-DC within FR1 .....	289
6.5B.3.3.1	General spurious emissions for Inter-band EN-DC within FR1 .....	289
6.5B.3.3.2	Spurious emission band UE co-existence for Inter-band within FR1 .....	290
6.5B.3.4	Spurious Emissions for Inter-band including FR2 .....	302
6.5B.3.4.1	General Spurious Emissions for Inter-band including FR2 .....	303
6.5B.3.4.1.2	Transmitter Spurious emissions for Inter-band EN-DC including FR2 (3 CCs) .....	303
6.5B.3.4.1.3	Transmitter Spurious emissions for Inter-band EN-DC including FR2 (4 CCs) .....	304
6.5B.3.4.1.4	Transmitter Spurious emissions for Inter-band EN-DC including FR2 (5 CCs) .....	305
6.5B.4	Additional Spurious Emissions for EN-DC.....	307
6.5B.4.1	Additional Spurious Emissions for Intra-band contiguous EN-DC .....	307
6.5B.4.1.4	Test description .....	308
6.5B.4.1.5	Test Requirement.....	310
6.5B.4.2	Additional Spurious Emissions for Intra-band non-contiguous EN-DC .....	310
6.5B.4.3	Additional Spurious Emissions for Inter-band EN-DC .....	311
6.5B.5	Transmit intermodulation .....	312
6.5B.5.1	Intra-band contiguous EN-DC .....	312
6.5B.5.2	Intra-band non-contiguous EN-DC .....	312
6.5B.5.3	Inter-band EN-DC within FR1 .....	312
6.5B.5.3.3	Minimum conformance requirements.....	312
6.5B.5.3.4	Test description .....	312
6.5B.5.3.5	Test Requirement.....	313
6.5B.5.4	Inter-band EN-DC including FR2 .....	313
6.5B.5.5	Inter-band EN-DC including both FR1 and FR2 .....	313
7	Receiver characteristics.....	313
7.1	General .....	313
7.2	Diversity characteristics .....	314
7.3	Reference sensitivity .....	314
7.3A	Reference sensitivity for CA without EN-DC .....	314
7.3A.1	General.....	314
7.3A.2	Reference sensitivity power level for CA without EN-DC.....	314
7.3A.3	$\Delta R_{IB,c}$ for CA without EN-DC .....	314
7.3A.3.1	Reference Sensitivity for Inter-band CA between FR1 and FR2 without EN-DC .....	315
7.3A.4	Reference sensitivity exceptions due to UL harmonic interference for CA.....	315
7.3B	Reference sensitivity level for DC .....	315
7.3B.1	General.....	315
7.3B.2	Reference sensitivity for EN-DC .....	315
7.3B.2.0	Minimum Conformance Requirements of Reference sensitivity for EN-DC .....	316
7.3B.2.0.1	Intra-band contiguous EN-DC.....	316
7.3B.2.0.2	Intra-band non-contiguous EN-DC.....	316
7.3B.2.0.3	Inter-band EN-DC within FR1 .....	316
7.3B.2.0.3.1	Reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1 .....	316
7.3B.2.0.3.2	Reference sensitivity exceptions due to receiver harmonic mixing for EN-DC in NR FR1.....	320
7.3B.2.0.3.3	Void.....	322

7.3B.2.0.3.4	Reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1 .....	322
7.3B.2.0.3.5	MSD for intermodulation interference due to dual uplink operation for EN-DC in NR FR1 .....	323
7.3B.2.1	Reference sensitivity for Intra-band Contiguous EN-DC (2 CCs) .....	333
7.3B.2.1.1	Test purpose .....	333
7.3B.2.1.2	Test applicability .....	333
7.3B.2.1.3	Minimum conformance requirements .....	333
7.3B.2.2	Reference sensitivity for Intra-band non-contiguous EN-DC (2 CCs) .....	337
7.3B.2.2.1	Test purpose .....	337
7.3B.2.2.2	Test applicability .....	337
7.3B.2.2.3	Minimum conformance requirements .....	337
7.3B.2.2.4	Test Description .....	337
7.3B.2.2.5	Test Requirement .....	339
7.3B.2.3	Reference sensitivity for Inter-band EN-DC within FR1 (2 CCs) .....	339
7.3B.2.3.1	Test purpose .....	340
7.3B.2.3.2	Test applicability .....	340
7.3B.2.3.3	Minimum conformance requirements .....	340
7.3B.2.3.4	Test description .....	340
7.3B.2.4	Reference sensitivity for Inter-band EN-DC including FR2 .....	370
7.3B.2.5	Reference sensitivity for Inter-band EN-DC including FR1 and FR2 (3 CCs) .....	371
7.3B.2.6	Reference sensitivity for EN-DC within FR1 (3 CCs) .....	371
7.3B.3	$\Delta R_{IB,c}$ $\Delta R_{IBNC}$ for EN-DC .....	382
7.3B.3.1	Reference sensitivity $\Delta R_{IB,c}$ for Intra-band Contiguous EN-DC .....	383
7.3B.3.2	Reference sensitivity $\Delta R_{IB,c}$ for Intra-band non-contiguous EN-DC .....	384
7.3B.3.3	$\Delta R_{IB,c}$ for Inter-band EN-DC within FR1 .....	385
7.3B.3.3.1	$\Delta R_{IB,c}$ for Inter-band EN-DC in two bands within FR1 .....	385
7.3B.3.3.2	$\Delta R_{IB,c}$ for Inter-band EN-DC in three bands within FR1 .....	388
7.3B.3.3.3	$\Delta R_{IB,c}$ for Inter-band EN-DC in four bands within FR1 .....	393
7.3B.3.4	Reference sensitivity for $\Delta R_{IB,c}$ Inter-band EN-DC including FR2 .....	399
7.3B.3.4.1	Reference sensitivity for $\Delta R_{IB,c}$ Inter-band EN-DC in two bands including FR2 .....	399
7.3B.3.4.2	Reference sensitivity for $\Delta R_{IB,c}$ Inter-band EN-DC in three bands including FR2 .....	400
7.3B.3.4.3	Reference sensitivity for $\Delta R_{IB,c}$ Inter-band EN-DC in four bands including FR2 .....	401
7.3B.3.4.4	Reference sensitivity for $\Delta R_{IB,c}$ Inter-band EN-DC in five bands including FR2 .....	402
7.3B.3.4.5	$\Delta R_{IB,c}$ for EN-DC six bands .....	403
7.4	Maximum Input Level .....	403
7.4B	Maximum Input Level for EN-DC .....	403
7.4B.0	Minimum conformance requirement .....	403
7.4B.0.1	Intra-band contiguous EN-DC in FR1 .....	403
7.4B.0.2	Intra-band non-contiguous EN-DC in FR1 .....	403
7.4B.0.3	Inter-band EN-DC within FR1 .....	403
7.4B.0.4	Inter-band EN-DC including FR2 .....	404
7.4B.0.5	Inter-band EN-DC including both FR1 and FR2 .....	404
7.4B.1	Maximum Input Level for Intra-Band Contiguous EN-DC (2 CCs) .....	404
7.4B.1.1	Test purpose .....	404
7.4B.1.2	Test applicability .....	404
7.4B.1.3	Minimum conformance requirements .....	404
7.4B.1.4	Test Description .....	404
7.4B.1.5	Test Requirement .....	406
7.4B.2	Maximum Input Level for Intra-Band Non-Contiguous EN-DC (2 CCs) .....	407
7.4B.2.1	Test purpose .....	407
7.4B.2.2	Test applicability .....	408
7.4B.2.3	Minimum conformance requirements .....	408
7.4B.2.4	Test Description .....	408
7.4B.2.5	Test Requirement .....	409
7.4B.3	Maximum Input Level for Inter-band EN-DC within FR1 .....	409
7.4B.3.1	Test purpose .....	409
7.4B.3.2	Test applicability .....	409
7.4B.3.3	Minimum conformance requirements .....	409
7.4B.3.4	Test Description .....	410
7.4B.3.5	Test Requirement .....	410
7.5	Adjacent channel selectivity .....	411
7.5B	Adjacent channel selectivity for EN-DC .....	411
7.5B.0	Minimum Conformance Requirements .....	411

7.5B.0.1	Intra-band contiguous EN-DC in FR1.....	411
7.5B.0.2	Intra-band non-contiguous EN-DC in FR1 .....	411
7.5B.0.3	Inter-band EN-DC within FR1 .....	412
7.5B.0.4	Inter-band EN-DC including FR2 .....	412
7.5B.0.5	Inter-band EN-DC including both FR1 and FR2 .....	412
7.5B.1	Adjacent Channel Selectivity for intra-band contiguous EN-DC (2 CCs).....	412
7.5B.2	Adjacent Channel Selectivity for intra-band non-contiguous EN-DC (2 CCs) .....	414
7.5B.3	Adjacent Channel Selectivity for inter-band EN-DC within FR1 (2 CCs) .....	416
7.5B.4	Adjacent Channel Selectivity for inter-band EN-DC including FR2.....	416
7.5B.4.1	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (2CCs).....	416
7.5B.4.1.1	Test purpose .....	417
7.5B.4.1.2	Test applicability .....	417
7.5B.4.1.3	Minimum conformance requirements.....	417
7.5B.4.1.4	Test description .....	417
7.5B.4.2	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (3CCs).....	418
7.5B.4.3	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (4CCs).....	419
7.5B.4.4	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (5CCs).....	420
7.5B.4.5	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (6CCs).....	422
7.5B.5	Adjacent Channel Selectivity for inter-band EN-DC including both FR1 and FR2 (3 CCs).....	424
7.6	Blocking characteristics .....	424
7.6B	Blocking characteristics for EN-DC.....	424
7.6B.1	General.....	424
7.6B.2	Inband blocking for EN-DC.....	424
7.6B.2.0	Minimum Conformance Requirements .....	424
7.6B.2.0.1	Intra-band contiguous EN-DC .....	424
7.6B.2.0.2	Intra-band non-contiguous EN-DC.....	425
7.6B.2.0.3	Inter-band EN-DC within FR1 .....	425
7.6B.2.0.4	Inter-band EN-DC including FR2 .....	425
7.6B.2.0.5	Inter-band EN-DC including both FR1 and FR2.....	425
7.6B.2.1	Inband blocking for intra-band contiguous EN-DC (2 CCs).....	425
7.6B.2.2	Inband blocking for intra-band non-contiguous EN-DC (2 CCs) .....	428
7.6B.2.3	Inband blocking for inter-band EN-DC within FR1 (2 CCs) .....	429
7.6B.2.4	Inband blocking for inter-band EN-DC including FR2.....	430
7.6B.2.4.1	Inband blocking for inter-band EN-DC including FR2 (2 CCs).....	430
7.6B.2.5	Inband blocking for inter-band EN-DC including both FR1 and FR2 .....	431
7.6B.3	Out-of-band blocking for EN-DC.....	431
7.6B.3.0	Minimum Conformance Requirements .....	431
7.6B.3.0.1	Intra-band contiguous EN-DC.....	431
7.6B.3.0.2	Intra-band non-contiguous EN-DC.....	431
7.6B.3.0.3	Inter-band EN-DC within FR1 .....	432
7.6B.3.0.4	Inter-band EN-DC including FR2 .....	432
7.6B.3.0.5	Inter-band EN-DC including both FR1 and FR2.....	432
7.6B.3.1	Out-of-band blocking for intra-band contiguous EN-DC (2 CCs).....	432
7.6B.3.2	Out-of-band blocking for intra-band non-contiguous EN-DC (2 CCs).....	435
7.6B.3.3	Out-of-band blocking for inter-band EN-DC within FR1 (2 CCs).....	436
7.6B.4	Narrow band blocking for EN-DC in FR1 .....	437
7.6B.4.0	Minimum Conformance Requirements .....	437
7.6B.4.0.1	Intra-band contiguous EN-DC .....	437
7.6B.4.0.2	Intra-band non-contiguous EN-DC.....	437
7.6B.4.0.3	Inter-band EN-DC within FR1 .....	438
7.6B.4.0.4	Inter-band EN-DC including FR2 .....	438
7.6B.4.0.5	Inter-band EN-DC including both FR1 and FR2.....	438
7.6B.4.1	Narrow band blocking for intra-band contiguous EN-DC (2 CCs).....	438
7.6B.4.2	Narrow band blocking for intra-band non-contiguous EN-DC (2 CCs).....	441
7.6B.4.3	Narrow band blocking for inter-band EN-DC within FR1 (2 CCs) .....	442
7.7	.....	443
7.7B	Spurious response for EN-DC in FR1 .....	443
7.7B.0	Minimum Conformance Requirements.....	443
7.7B.0.1	Intra-band contiguous EN-DC .....	443
7.7B.0.2	Intra-band non-contiguous EN-DC .....	443
7.7B.0.3	Inter-band EN-DC within FR1 .....	443
7.7B.0.4	Inter-band EN-DC including FR2 .....	443

7.7B.0.5	Inter-band EN-DC including both FR1 and FR2 .....	443
7.7B.1	Spurious Response for intra-band contiguous EN-DC (2 CCs).....	444
7.7B.2	Spurious Response for intra-band non-contiguous EN-DC (2 CCs).....	445
7.7B.3	Spurious Response for inter-band EN-DC within FR1 (2 CCs) .....	446
7.8	Intermodulation characteristics .....	447
7.8B	Intermodulation characteristics for EN-DC in FR1 .....	447
7.8B.1	General.....	447
7.8B.2	Wide band Intermodulation .....	447
7.8B.2.0	Minimum Conformance Requirements .....	447
7.8B.2.0.1	Intra-band contiguous EN-DC in FR1 .....	447
7.8B.2.0.2	Intra-band non-contiguous EN-DC in FR1 .....	447
7.8B.2.0.3	Inter-band EN-DC within FR1 .....	447
7.8B.2.0.4	Inter-band EN-DC including FR2 .....	448
7.8B.2.0.5	Inter-band EN-DC including both FR1 and FR2.....	448
7.8B.2.1	Wideband Intermodulation for intra-band contiguous EN-DC in FR1 .....	448
7.8B.2.2	Wideband Intermodulation for intra-band non-contiguous EN-DC in FR1 .....	450
7.8B.2.3	Wideband Intermodulation for inter-band EN-DC in FR1 (2 CCs) .....	451
7.8B.2.4	Wideband Intermodulation for EN-DC including FR2 (2 CCs).....	452
7.8B.2.5	Wideband Intermodulation for inter-band EN-DC including both FR1 and FR2 (3 CCs).....	452
7.8B.2.6	Wideband Intermodulation for EN-DC including FR1 (3 CCs).....	452
7.8B.2.7	Wideband Intermodulation for EN-DC including FR1 (4 CCs).....	456
7.8B.2.8	Wideband Intermodulation for EN-DC including FR1 (5 CCs).....	456
7.8B.2.9	Wideband Intermodulation for EN-DC including FR1 (6 CCs).....	456
7.9	Spurious emissions .....	456
7.9B	Spurious emissions for EN-DC in FR1 .....	456
7.9B.0	Minimum Conformance Requirements.....	456
7.9B.0.1	Intra-band contiguous EN-DC in FR1.....	456
7.9B.0.2	Intra-band non-contiguous EN-DC in FR1 .....	457
7.9B.0.3	Inter-band EN-DC within FR1 .....	457
7.9B.0.4	Inter-band EN-DC including FR2 .....	457
7.9B.0.5	Inter-band EN-DC including both FR1 and FR2 .....	457
7.9B.1	Spurious Emissions for intra-band contiguous EN-DC in FR1(2 CCs).....	457
7.9B.2	Spurious Emissions for intra-band non-contiguous EN-DC in FR1(2 CCs).....	458
7.9B.3	Spurious Emissions for inter-band EN-DC within FR1(2 CCs) .....	459
7.9B.4	Spurious Emissions for inter-band EN-DC including FR2 (2 CCs) .....	460
7.9B.5	Spurious Emissions for inter-band EN-DC including both FR1 and FR2 (3 CCs).....	460
7.9B.6	Spurious Emissions for EN-DC (3 CCs).....	460
7.9B.7	Spurious Emissions for EN-DC (4 CCs).....	460
7.9B.8	Spurious Emissions for EN-DC (5 CCs).....	460
7.9B.9	Spurious Emissions for EN-DC (6 CCs).....	460
<b>Annex A (normative):</b>	<b>Measurement Channels.....</b>	<b>461</b>
A.1	General .....	461
A.2	UL reference measurement channels for E-UTRA TDD Config 2.....	461
A.2.1	General .....	461
A.2.2	Reference measurement channels for E-UTRA .....	462
A.2.2.1	Full RB allocation.....	462
A.2.2.1.1	QPSK .....	462
A.2.2.1.2	16-QAM .....	462
A.2.2.1.3	64-QAM.....	463
A.2.2.1.4	256 QAM .....	464
A.2.2.2	Partial RB allocation.....	465
A.2.2.2.1	QPSK .....	465
A.2.2.2.2	16-QAM .....	466
A.2.2.2.3	64-QAM.....	467
A.2.2.2.4	256 QAM .....	470
A.3	DL reference measurement channels for E-UTRA .....	470
A.3.1	General .....	470
<b>Annex B (normative):</b>	<b>Propagation Conditions.....</b>	<b>472</b>

<b>Annex C (normative):</b>	<b>Downlink Physical Channels.....</b>	<b>473</b>
<b>Annex D (normative):</b>	<b>Characteristics of the Interfering Signal .....</b>	<b>474</b>
<b>Annex E (normative):</b>	<b>Global In-Channel Tx Test .....</b>	<b>475</b>
<b>Annex F (informative):</b>	<b>Measurement uncertainties and Test Tolerances .....</b>	<b>476</b>
F.1	Acceptable uncertainty of Test System (normative) .....	476
F.1.1	Measurement of test environments .....	476
F.1.2	Measurement of transmitter .....	477
F.1.3	Measurement of receiver .....	482
F.2	Interpretation of measurement results (normative).....	484
F.3	Test Tolerance and Derivation of Test Requirements (informative) .....	484
F.3.1	Measurement of test environments .....	484
F.3.2	Measurement of transmitter .....	485
F.3.3	Measurement of receiver .....	490
<b>Annex G (normative):</b>	<b>Uplink Physical Channels .....</b>	<b>493</b>
<b>Annex H (normative):</b>	<b>Statistical Testing.....</b>	<b>494</b>
H.1	General .....	494
H.2	Statistical testing of receiver characteristics.....	494
H.2.1	General.....	494
H.2.2	Mapping throughput to error ratio .....	494
H.2.3	Design of the test .....	495
H.2.4	Numerical definition of the pass fail limits.....	496
H.2.5	Pass fail decision rules .....	497
<b>Annex I (normative):</b>	<b>Void .....</b>	<b>498</b>
<b>Annex J (normative):</b>	<b>Test applicability per permitted test method .....</b>	<b>499</b>
<b>Annex K (normative):</b>	<b>EIRP, TRP, and EIS measurement procedures .....</b>	<b>500</b>
<b>Annex L (normative):</b>	<b>Void .....</b>	<b>501</b>
<b>Annex M (normative):</b>	<b>Dual uplink interferer .....</b>	<b>502</b>
<b>Annex N (informative):</b>	<b>Change history .....</b>	<b>503</b>
History .....		511

---

# Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

The present document is part 3 of a multi-part Technical Specification (TS) covering the New Radio (NR) User Equipment (UE) conformance specification, which is divided in the following parts:

FFS

---

# 1 Scope

The present document specifies the measurement procedures for the conformance test of the user equipment (UE) that contain RF characteristics for carrier aggregation between Range 1 and Range 2 and additional requirements due to NR non-standalone (NSA) operation mode with E-UTRA.

The requirements are listed in different clauses only if the corresponding parameters deviate. More generally, tests are only applicable to those mobiles that are intended to support the appropriate functionality. To indicate the circumstances in which tests apply, this is noted in the "*definition and applicability*" part of the test.

For example only Release 15 and later UE declared to support 5G-NR shall be tested for this functionality. In the event that for some tests different conditions apply for different releases, this is indicated within the text of the test itself.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

**Editor's note: intended to capture more references**

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications"
- [2] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone".
- [3] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone".
- [4] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios".
- [5] 3GPP TS 36.101: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio transmission and reception".
- [6] 3GPP TS 38.508-1: "5GS; User Equipment (UE) conformance specification; Part 1: Common test environment".
- [7] 3GPP TR 38.905: "NR; Derivation of test points for radio transmission and reception conformance test cases".
- [8] 3GPP TS 38.521-1: "User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone.
- [9] 3GPP TS 38.521-2: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Range 2 Standalone".
- [10] 3GPP TS 36.521-1: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Conformance testing"
- [11] 3GPP TS 36.508: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Packet Core (EPC); Common test environments for User Equipment (UE) conformance testing".
- [12] 3GPP TS 36.133: "Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management".

- [13] 3GPP TS 36.211: "E-UTRA; Physical channels and modulation".
- [14] 3GPP TS 38.522: "NR; User Equipment (UE) conformance specification; Applicability of radio transmission, radio reception and radio resource management test cases".
- [15] 3GPP TS 38.331: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) protocol specification".
- [16] 3GPP TS 38.306: "NR: User Equipment (UE) radio access capabilities"
- [17] 3GPP TS 36.331: " Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification"
- [18] 3GPP TS 38.331: "NR; Radio Resource Control (RRC) protocol specification"
- [19] 3GPP TS 38.213: "NR; Physical layer procedures for control"

## 3 Definitions, symbols and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

**Editor's note: intended to capture definitions**

### 3.2 Symbols

For the purposes of the present document, the following symbols apply:

$\Delta R_{IB,c}$	Allowed reference sensitivity relaxation due to support for CA or DC operation, for serving cell $c$ .
$\Delta T_{IB,c}$	Allowed maximum configured output power relaxation due to support for CA or DC operation, for serving cell $c$
$BW_{E-UTRA\_Channel}$	Channel bandwidth of E-UTRA carrier
$BW_{E-UTRA\_Channel\_CA}$	Channel bandwidth of E-UTRA sub-block which is composed of intra-band contiguous CA E-UTRA carriers
$BW_{NR\_Channel}$	Channel bandwidth of NR carrier
$BW_{NR\_Channel\_CA}$	Channel bandwidth of NR sub-block which is composed of intra-band contiguous CA NR carriers
$Ceil(x)$	Rounding upwards; $ceil(x)$ is the smallest integer such that $ceil(x) \geq x$
$EN-DC_{ACLR}$	The ratio of the filtered mean power centred on the aggregated sub-block bandwidth ENBW to the filtered mean power centred on an adjacent bandwidth of the same size ENBW
$E-UTRA_{ACLR}$	E-UTRA ACLR
$F_C$	<i>RF reference frequency</i> for the carrier centre on the channel raster
$F_{DL\_low}$	The lowest frequency of the downlink <i>operating band</i>
$F_{DL\_high}$	The highest frequency of the downlink <i>operating band</i>
$F_{UL\_low}$	The lowest frequency of the uplink <i>operating band</i>
$F_{UL\_high}$	The highest frequency of the uplink <i>operating band</i>
$F_{OOB}$	The boundary between the NR out of band emission and spurious emission domains
$L_{CRB}$	Transmission bandwidth which represents the length of a contiguous resource block allocation expressed in units of resources blocks
$Max()$	The largest of given numbers
$Min()$	The smallest of given numbers
$NR_{ACLR}$	NR ACLR
$N_{RB}$	Transmission bandwidth configuration, expressed in units of resource blocks
$P_{CMAX}$	The configured maximum UE output power
$RB_{start}$	Indicates the lowest RB index of transmitted resource blocks
$W_{gap}$	The sub-block gap between the two sub-blocks



### 3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ACLR	Adjacent Channel Leakage Ratio
ACS	Adjacent Channel Selectivity
A-MPR	Additional Maximum Power Reduction
BCS	Bandwidth Combination Set
CA	Carrier Aggregation
CC	Component Carrier
DC	Dual Connectivity
EN-DC	E-UTRA/NR DC
EVM	Error Vector Magnitude
FR	Frequency Range
ENBW	The aggregated bandwidth of an E-UTRA sub-block and an adjacent NR sub-block
ITU-R	Radiocommunication Sector of the International Telecommunication Union
MBW	Measurement bandwidth defined for the protected band
MPR	Allowed maximum power reduction
MSD	Maximum Sensitivity Degradation
MCG	Master Cell Group
NR	New Radio
NS	Network Signalling
NSA	Non-Standalone, a mode of operation where operation of another radio is assisted with another radio
OOB	Out-of-band
OOBE	Out-of-band emission
OTA	Over The Air
PRB	Physical Resource Block
RE	Resource Element
REFSENS	Reference Sensitivity
RF	Radio Frequency
Rx	Receiver
SCG	Secondary Cell Group
SCS	Subcarrier spacing
SEM	Spectrum Emission Mask
SUL	Supplementary uplink
TDM	Time Division Multiplex
Tx	Transmitter
UE	User Equipment
UL-MIMO	Up Link Multiple Antenna transmission
ULSUP	Uplink sharing from UE perspective

---

## 4 General

### 4.1 Relationship between minimum requirements and test requirements

The present document is interwork specification for NR UE, covering RF characteristics and minimum performance requirements. Conformance to the present specification is demonstrated by fulfilling the test requirements specified in the conformance specification 3GPP TS 38.521-3 [5].

The Minimum Requirements given in this specification make no allowance for measurement uncertainty (MU). The test specification TS 38.521-3 [5] defines test tolerances (TT). These test tolerances are individually calculated for each test. The test tolerances are used to relax the minimum requirements in this specification to create test requirements. For some requirements, including regulatory requirements, the test tolerance is set to zero.

The measurement results returned by the test system are compared - without any modification - against the test requirements as defined by either the “Never fail a good DUT” principle for test tolerance equal to measurement uncertainty (TT = MU) or “Shared Risk” principle for Test Tolerance equal to 0 (TT = 0) Test tolerances lower than measurement uncertainty and greater than 0 ( $0 < TT < MU$ ) are also considered in this specification..

The “Never fail a good DUT” and the “Shared Risk” principles are defined in Recommendation ITU-R M.1545 [6].

## 4.2 Applicability of minimum requirements

- a) In this specification the Minimum Requirements are specified as general requirements and additional requirements. Where the Requirement is specified as a general requirement, the requirement is mandated to be met in all scenarios
- b) For specific scenarios for which an additional requirement is specified, in addition to meeting the general requirement, the UE is mandated to meet the additional requirements.
- c) The spurious emissions power requirements are for the long-term average of the power. For the purpose of reducing measurement uncertainty it is acceptable to average the measured power over a period of time sufficient to reduce the uncertainty due to the statistical nature of the signal.
- d) Terminal that supports EN-DC configuration shall meet E-UTRA requirements as specified in TS 36.101 [4] and NR requirements as in TS 38.101-1 [2] and TS 38.101-2 [3] unless otherwise specified in this specification.e) All the requirements for intra-band contiguous and non-contiguous CA apply under the assumption of the same uplink-downlink and special subframe configurations in the PCell and SCells for SA.
- e) All the requirements for intra-band contiguous and non-contiguous EN-DC apply under the assumption of the same uplink-downlink and special subframe configurations in the E-UTRA and slot format indicated by UL-DL-configuration-common in the NR for the EN-DC.
- f) For EN-DC combinations with CA configurations for E-UTRA and/or NR, all the requirements for E-UTRA and/or NR all the requirements for E-UTRA and/or NR intra-band contiguous and non-contiguous CA apply under the assumption of the same slot format indicated by UL-DL-configuration-common in the PCell and SCells for NR and the same uplink-downlink and special subframe configurations in Pcell and SCells for E-UTRA.

A terminal which supports an inter-band EN-DC configuration shall support all specified E-UTRA bandwidth combination set that belong to the E-UTRA CA configuration part of E-UTRA – NR DC and shall support all specified NR bandwidth combination set that belong to the NR CA configuration part of E-UTRA – NR DC.

A terminal which supports an inter-band EN-DC configuration with a certain UL configuration shall support the all lower order DL configurations of the lower order EN-DC combinations, which have this certain UL configuration and the fallbacks of this UL configuration.

Terminal that supports inter-band NR-DC between FR1 and FR2 configuration shall meet the requirements for corresponding CA configuration (suffix A), unless otherwise specified.

## 4.3 Specification suffix information

Unless stated otherwise the following suffixes are used for indicating at 2<sup>nd</sup> level sub-clause, shown in Table 4.3-1.

**Table 4.3-1: Definition of suffixes**

Clause suffix	Variant
None	Single Carrier
A	Carrier Aggregation (CA)
B	Dual-Connectivity (DC)
C	Supplement Uplink (SUL)
D	UL MIMO

## 4.4 Test points analysis

The information on test point analysis and test point selection including number of test points for each test case is shown in TR 38.905 [7] clause 4.3.

## 4.5 Applicability and test coverage rules

- (1) The applicability and test coverage rules for EN-DC only capable devices shall include the following:
  - (a) Test all the EN-DC exception test requirements as per test procedures in TS38.521-3.
  - (b) Test all the EN-DC FR2 non-exception test requirements in TS38.521-3 with test procedures which refer appropriately back to TS38.521-2. Test only one EN-DC combination per FR2 band for each EN-DC configuration as defined in section 5.5B of 38.101-3 using LTE anchor agnostic approach.
  - (c) Test all the EN-DC FR1 non-exception test requirements in TS38.521-3 with test procedures which refer appropriately back to TS38.521-1. Test only one EN-DC combination per FR1 band for each EN-DC configuration as defined in section 5.5B of 38.101-3 using LTE anchor agnostic approach.
- (2) The applicability and test coverage rules for Standalone and EN-DC capable devices shall include the following:
  - (a) Test all the EN-DC exception test requirements as per test procedures in TS38.521-3.
  - (b) Test all the Standalone FR2 test requirements as per test procedures in TS38.521-2. This also fulfils coverage for all non-exception EN-DC FR2 test requirements and need not be retested. If Standalone FR2 cannot be tested (due to test case not being complete), then test in EN-DC mode following (1)(b) above.
  - (c) Test all the Standalone FR1 test requirements as per test procedures in TS38.521-1. This also fulfils coverage for all non-exception EN-DC FR1 test requirements and need not be retested. If Standalone FR1 cannot be tested (due to test case not being complete), then test in EN-DC mode following (1)(c) above.

### 4.5.1 Test coverage across 5G NR architecture options

The test cases in this specification cover both Standalone (FR1+FR2 CA without DC) as well as Non-Standalone FR1 and FR2 (E-UTRA and 5G NR interworking) testing. Below shall be the understanding with respect to coverage across 5G NR architecture options:

- 1) Unless otherwise stated within the test case, it shall be understood that test requirements are agnostic of the NSA architecture option configured within the test. The test coverage across NSA options shall be considered fulfilled by execution of the NSA test case in one NSA option. Subsequently the test execution and test results can be leveraged to other NSA options.
- 2) Only one SA or NSA architecture option type is identified and utilized in the definition of each test case within this test specification. NSA test cases are configured using *Connectivity EN-DC* i.e. NSA Option 3 and Standalone (SA) test cases are configured using *Connectivity NR* i.e. SA Option 2 which shall be the default architecture options used for NSA and SA test execution respectively.
- 3) If a UE does not support NSA Option 3, any other supported NSA option can be configured to execute the test. This is accomplished by appropriately picking the generic procedure parameter from Table 4.5.1-2. The leverage rule detailed in (1) would apply.

**Table 4.5.1-1: Generic procedure parameter summary for SA**

Generic Procedure Parameter to use in Initial Conditions		Description	5G NR SA Architecture Option supported by UE
<i>Connectivity</i>	<i>NR</i>	NG-RAN NR Radio Access	SA Option 2
	<i>E-UTRA</i>	NG-RAN E-UTRA Radio Access	SA Option 5

**Editor's Note: Any additional test config details needed for SA Option 5 is FFS.**

Table 4.5.1-2: Generic procedure parameter summary for NSA

Generic Procedure Parameter to use in Initial Conditions		Description	5G NR NSA Architecture Option supported by UE
Connectivity	<b>NSA</b>		
	<i>EN-DC</i>	E-UTRA-NR Dual Connectivity	NSA Option 3
	<i>NGEN-DC</i>	NG-RAN E-UTRA-NR Dual Connectivity	NSA Option 4
	<i>NE-DC</i>	NR-E-UTRA Dual Connectivity	NSA Option 7

Editor's Note: Any additional test config details needed for NSA Options 4 and 7 are FFS.

## 4.6 E-UTRA configuration for EN-DC FR1 tests applying the E-UTRA anchor-agnostic approach

This section applies to EN-DC test cases where E-UTRA anchor needs to be configured as per the anchor-agnostic approach outlined in section 6.1 and 7.1 of TS 38.101-3 [4]. The LTE anchor-agnostic approach is defined as measurements on the NR carrier under conditions where the LTE anchor resources do not interfere with NR operation. The configuration defined in this section ensures establishment of such conditions.

For baseline configuration, the E-UTRA carrier will be configured for each test case in section 6 and 7 as defined in the equivalent standalone E-UTRA test in TS 36.521-1. However, the below exceptions defined in Table 4.6-1, 4.6-2, 4.6-3, 4.6-4 and 4.6-5 are applied to ensure that the E-UTRA anchor resources do not interfere with NR operation.

For EN-DC within FR1 band combinations with multiple E-UTRA component carriers, it is sufficient to configure any one E-UTRA carrier from the carrier group whenever it is determined that anchor agnostic approach can be applied.

Table 4.6-1: E-UTRA configuration for EN-DC FR1 tests applying anchor agnostic approach

Parameter	Value	Comments
Test Frequency during and after connection setup	Mid (See Table 4.6-2)	As defined in TS 36.508 for the LTE band under test
Bandwidth during and after connection setup	5 MHz (See Table 4.6-2)	Supported by all LTE bands.
DL signal levels during connection setup	RS EPRE -85.0 dBm/15kHz	DL physical channels as defined in Annex C0, C.1, C.2 and Annex C.3 of TS 36.521-1 36.521-1 annex C.0 defines the default DL power level of RS EPRE to be -85dBm/15kHz.
UL Signal levels during connection setup	PUSCH Power	Attained by enabling open loop power control and setting up UL signal levels according to Annex H.0, H.2 and H.3 of TS 36.521-1
DL/UL RMC after connection setup	0 RB allocation on both DL and UL (see Table 4.6-2)	Once the LTE link is established, then LTE Tx can be restricted by configuring 0 RB allocation on DL and UL. <i>TimeAlignmentTimerDedicated</i> IE to be set to infinity to ensure UE doesn't look for TA adjustments (See Table 4.6-5)
CQI Reports and SRS after connection setup	Disabled (See Table 4.6-3 and 4.6-4)	Disable periodic and aperiodic CQI reports to ensure none of these transmissions occur on the LTE uplink. Since LTE transmissions could easily exceed spurious emissions limits, tests that are intended to measure RF parametrics on the NR should simply avoid LTE transmit altogether.

Table 4.6-2: E-UTRA Test Configuration Table

E-UTRA Test Parameters					
E-UTRA Channel Bandwidth	E-UTRA Test Frequency	Downlink		Uplink	
		Modulation	RB allocation	Modulation	RB allocation
5 MHz <sup>2</sup>	MidRange <sup>1</sup>	N/A	0	N/A	0
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [11] subclause 4.3.1.					
NOTE 2: For EN-DC Intra-band tests that need to apply E-UTRA anchor agnostic approach, refer to and pick applicable E-UTRA channel bandwidth from subclause 5.3B.1 and indicate within test case if it is different than 5 MHz.					

Table 4.6-3: *CQI-ReportConfig-DEFAULT*: Additional E-UTRA Anchor Configuration

Derivation Path: TS 36.508 [7] clause 4.6.3, Table 4.6.3-2 CQI-ReportConfig-DEFAULT			
Information Element	Value/remark	Comment	Condition
CQI-ReportConfig-DEFAULT ::= SEQUENCE {			
cqi-ReportModeAperiodic	NOT PRESENT		
cqi-ReportPeriodic	NOT PRESENT		
}			

Table 4.6-4: *PhysicalConfigDedicated-DEFAULT*: Additional E-UTRA Anchor Configuration

Derivation Path: TS 36.508 [7] clause 4.8.2, Table 4.8.2.1.6-1 PhysicalConfigDedicated-DEFAULT			
Information Element	Value/remark	Comment	Condition
PhysicalConfigDedicated-DEFAULT ::= SEQUENCE {			
soundingRS-UL-ConfigDedicated	Not present		RBC
}			

Table 4.6-5: *MAC-MainConfig-RBC*: Additional E-UTRA Anchor Configuration

Derivation Path: TS 36.508 [7] clause 4.8.2.1.5, Table 4.8.2.1.5-1 MAC-MainConfig-RBC			
Information Element	Value/remark	Comment	Condition
timeAlignmentTimerDedicated	Infinity		

## 4.7 E-UTRA configuration for EN-DC FR2 tests applying the E-UTRA anchor-agnostic approach

This section applies to EN-DC test cases where E-UTRA anchor needs to be configured as per the anchor-agnostic approach outlined in section 6.1 and 7.1 of TS 38.101-3 [4]. The LTE anchor-agnostic approach is defined as measurements on the NR carrier under conditions where the LTE anchor resources do not interfere with NR operation. The configuration defined in this section ensures establishment of such conditions.

For baseline configuration, the E-UTRA carrier will be configured for each test case in section 6 and 7 as defined in the equivalent standalone E-UTRA test in TS 36.521-1. However, the below exceptions defined in Table 4.7-1 to 4.7-7 are applied to ensure that the E-UTRA anchor resources do not interfere with NR operation.

Since the E-UTRA link is always a functional link when testing EN-DC including FR2 band combinations, it is sufficient to configure any one E-UTRA carrier from the carrier group, irrespective of the number of E-UTRA carriers in the EN-DC combination under test.

**Table 4.7-1: E-UTRA configuration for EN-DC FR2 tests applying anchor agnostic approach**

Parameter	Value	Comments
Test Frequency during and after connection setup	Mid (See Table 4.7-2)	As defined in TS 36.508 for the LTE band under test
Bandwidth during and after connection setup	5 MHz (See Table 4.7-2)	Supported by all LTE bands.
DL signal levels	See table 4.7-3	DL physical channels as defined in Annex C0, C.1, C.2 and Annex C.3 of TS 36.521-1
UL Signal levels for connection setup and UBF transmission	PUSCH Power	Attained by enabling open loop power control and setting up UL signal levels according to Annex H.0, H.2 and H.3 of TS 36.521-1 with the exception for power control message exception defined in Table 4.7-5
DL/UL RMC after connection setup except for UBF transmission	0 RB allocation on both DL and UL (see Table 4.7-2)	Once the LTE link is established, then LTE Tx can be restricted by configuring 0 RB allocation on DL and UL. <i>TimeAlignmentTimerDedicated</i> IE to be set to infinity to ensure UE doesn't look for TA adjustments (See Table 4.7-7)
CQI Reports and SRS after connection setup	Disabled (See Table 4.7-4 and 4.7-6)	Disable periodic and aperiodic CQI reports to ensure none of these transmissions occur on the LTE uplink. Since LTE transmissions could easily exceed spurious emissions limits, tests that are intended to measure RF parameters on the NR should simply avoid LTE transmit altogether.

**Table 4.7-2: E-UTRA Test Configuration Table**

E-UTRA Test Parameters					
E-UTRA Channel Bandwidth	E-UTRA Test Frequency	Downlink		Uplink	
		Modulation	RB allocation	Modulation	RB allocation
5 MHz <sup>2</sup>	MidRange <sup>1</sup>	N/A	0	N/A	0
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [11] subclause 4.3.1					
NOTE 2: For EN-DC Intra-band tests that need to apply E-UTRA anchor agnostic approach, refer to and pick applicable E-UTRA channel bandwidth from subclause 5.3B.1 and indicate within test case if it is different than 5 MHz.					

**Table 4.7-3: Default Downlink power levels for E-UTRA anchor**

	Unit	Band Group	Channel Bandwidth					
			1.4 MHz	3 MHz	5MHz	10MHz	15 MHz	20 MHz
RS EPRE	dBm/15kHz	FDD_A, TDD_A	N/A	N/A	≥ -120.0	N/A	N/A	N/A
		FDD_B1, TDD_B1	N/A	N/A	≥ -119.5	N/A	N/A	N/A
		FDD_C, TDD_C	N/A	N/A	≥ -119.0	N/A	N/A	N/A
		FDD_D, TDD_D	N/A	N/A	≥ -118.5	N/A	N/A	N/A
		FDD_E, TDD_E	N/A	N/A	≥ -118.0	N/A	N/A	N/A
		FDD_G, TDD_G	N/A	N/A	≥ -117.0	N/A	N/A	N/A
		FDD_H, TDD_H	N/A	N/A	≥ -116.5	N/A	N/A	N/A
		FDD_N, TDD_N	N/A	N/A	≥ -113.5	N/A	N/A	N/A
Note 1: The power level is specified at RSRP reference point as defined in TS 36.214 [21]								
Note 2: E-UTRA Band groups are defined in TS 36.133 [12] clause 3.5.1.								

**Table 4.7-4: CQI-ReportConfig-DEFAULT: Additional E-UTRA Anchor Configuration**

Derivation Path: TS 36.508 [7] clause 4.6.3, Table 4.6.3-2 CQI-ReportConfig-DEFAULT			
Information Element	Value/remark	Comment	Condition
CQI-ReportConfig-DEFAULT ::= SEQUENCE {			
cqi-ReportModeAperiodic	NOT PRESENT		
cqi-ReportPeriodic	NOT PRESENT		
}			

**Table 4.7-5: UplinkPowerControlCommon-DEFAULT : Additional E-UTRA Anchor Configuration**

Derivation Path: TS 36.508 [7] clause 4.6.3, UplinkPowerControlCommon-DEFAULT			
Information Element	Value/remark	Comment	Condition
UplinkPowerControlCommon-DEFAULT ::= SEQUENCE {			
p0-NominalPUSCH	-60 (-60 dBm)	To attain maximum power from the DUT	
}			

**Table 4.7-6: PhysicalConfigDedicated-DEFAULT: Additional E-UTRA Anchor Configuration**

Derivation Path: TS 36.508 [7] clause 4.8.2, Table 4.8.2.1.6-1 PhysicalConfigDedicated-DEFAULT			
Information Element	Value/remark	Comment	Condition
PhysicalConfigDedicated-DEFAULT ::= SEQUENCE {			
soundingRS-UL-ConfigDedicated	Not present		RBC
}			

**Table 4.7-7: MAC-MainConfig-RBC: Additional E-UTRA Anchor Configuration**

Derivation Path: TS 36.508 [7] clause 4.8.2.1.5, Table 4.8.2.1.5-1 MAC-MainConfig-RBC			
Information Element	Value/remark	Comment	Condition
timeAlignmentTimerDedicated	Infinity		

## 5 Operating bands and Channel arrangement

### 5.1 General

The channel arrangements presented in this clause are based on the operating bands and channel bandwidths defined in the present release of specifications.

NOTE: Other operating bands and channel bandwidths may be considered in future releases.

Requirements throughout the RF specifications are in many cases defined separately for different frequency ranges (FR). The frequency ranges in which NR can operate according to this version of the specifications are identified as described in Table 5.1-1.

**Table 5.1-1: Definition of frequency ranges**

Frequency range designation	Corresponding frequency range
FR1	410 MHz – 7125 MHz
FR2	24250 MHz – 52600 MHz

The present specification covers band combinations including

- at least one FR1 operating band and one FR2 operating band for carrier aggregation and dual connectivity operations;
- at least one E-UTRA operating band for dual connectivity operations.

## 5.2 Operating bands

NR is designed to operate in FR1 operating bands defined in TS 38.101-1 [2] and FR2 operating bands defined in TS 38.101-2 [3]. E-UTRA is designed to operate in operating bands defined in TS 36.101 [4].

### 5.2A Operating bands for CA

#### 5.2A.1 Inter-band CA between FR1 and FR2

NR carrier aggregation is designed to operate in the operating bands defined in Table 5.2A.1-1. The band combinations include at least one FR1 operating band and one FR2 operating band.

**Table 5.2A.1-1: Band combinations for inter-band NR CA between FR1 and FR2**

NR CA Band	NR Band
CA_n8-n258	n8, n258
CA_n71-n257 <sup>1</sup>	n71, n257
CA_n77-n257 <sup>1</sup>	n77, n257
CA_n78-n257 <sup>1</sup>	n78, n257
CA_n79-n257 <sup>1</sup>	n79, n257
NOTE 1: Applicable for UE supporting inter-band carrier aggregation with mandatory simultaneous Rx/Tx capability.	

### 5.2B Operating bands for DC

#### 5.2B.1 General

The operating bands are specified in subclause 5.5B for operation with EN-DC, NGEN-DC or NR-DC configured.

#### 5.2B.2 to 5.2B.7 Void

## 5.3 UE Channel bandwidth

### 5.3A UE Channel bandwidth for CA

#### 5.3A.1 Inter-band CA between FR1 and FR2

For inter-band NR CA between FR1 and FR2, a carrier aggregation configuration is a combination of operating bands, each supporting a carrier aggregation bandwidth class as specified in clause 5.3A.5 of TS 38.101-1 [2] and clause 5.3A.4 of TS 38.101-2 [3] independently.

### 5.3B UE Channel bandwidth for EN-DC

For intra-band contiguous EN-DC, the aggregated channel bandwidth is sum of the individual NR and E-UTRA channel bandwidths assuming nominal EN-DC channel with 0 kHz offset spacing as specified in sub-clause 5.4.



$$ENBW = BW_{NR\_Channel} + BW_{E-UTRA\_Channel}$$

In the case where the NR sub-block and/or the E-UTRA sub-block itself is composed of intra-band contiguous CA carriers, the EN-DC aggregated channel bandwidth is the sum of the aggregated channel bandwidths of the NR and E-UTRA sub-blocks assuming nominal EN-DC channel spacing between the NR sub-block and E-UTRA sub-block.

$$ENBW = BW_{NR\_Channel\_CA} + BW_{E-UTRA\_Channel\_CA}$$

For NR inter-band dual connectivity specified in sub-clause 5.2B.7, the corresponding NR CA configurations in sub-clause 5.5A.1, i.e., dual uplink inter-band carrier aggregation between FR1 and FR2 with uplink assigned to two NR bands, are applicable to Dual Connectivity.

NOTE 1: Requirements for the dual connectivity configurations are defined in the section corresponding NR uplink CA between FR1 and FR2 configurations, unless otherwise specified.

Intra-band contiguous EN-DC configurations are defined using intra-band contiguous EN-DC bandwidth class notation where the first EN-DC bandwidth class letter indicates the number of contiguous E-UTRA carriers and the second EN-DC bandwidth class letter indicates the number of contiguous NR carriers. Applicable contiguous intraband EN-DC bandwidth classes are listed in Table 5.3B-1

**Table 5.3B-1: Intra-band contiguous EN-DC bandwidth classes**

Intra-band contiguous EN-DC bandwidth class	Number of contiguous CC	
	E-UTRA	NR
AA	1	1
CA	2	1
DA	3	1

## 5.3B.1 Intra-band EN-DC in FR1

### 5.3B.1.1 General

The requirements for intra-band EN-DC in this specification are defined for EN-DC configurations with associated bandwidth combination sets.

For each EN-DC configuration, requirements are specified for all bandwidth combinations contained in a *bandwidth combination set*, which is indicated per supported band combination in the UE radio access capability. A UE can indicate support of several bandwidth combination sets per band combination.

### 5.3B.1.2 BCS for Intra-band contiguous EN-DC

For intra-band contiguous EN-DC, an EN-DC configuration is a single operating band supporting an intra-band contiguous EN-DC bandwidth class.

Bandwidth combination sets for intra-band contiguous EN-DC are specified in Table 5.3B.1.2-1.

**Table 5.3B.1.2-1: EN-DC configurations and bandwidth combination sets defined for intra-band contiguous EN-DC**

E-UTRA – NR configuration / Bandwidth combination set						
Downlink EN-DC configuration	Uplink EN-DC configurations	Component carriers in order of increasing carrier frequency			Maximum aggregated bandwidth (MHz)	Bandwidth combination set
		Channel bandwidths for LTE carrier (MHz)	Channel bandwidths for NR carrier (MHz)	Channel bandwidths for LTE carrier (MHz)		

DC_(n)41AA	DC_(n)41AA	20	40, 60, 80,100		120	0
			40, 60, 80,100	20		
		20	40, 50, 60, 80,100		120	1
			40, 50, 60, 80,100	20		
DC_(n)41CA	DC_(n)41AA <sup>1</sup> , DC_41A_n41A <sup>2</sup>	20+20	40, 60, 80,100		140	0
			40, 60, 80,100	20+20		
		20+20	40, 50, 60, 80,100		140	1
			40, 50, 60, 80,100	20+20		
DC_(n)41DA	DC_(n)41AA <sup>1</sup> , DC_41A_n41A <sup>2</sup>	20+20+20	40, 60, 80,100		160	0
			40, 60, 80,100	20+20+20		
		20+20+20	40, 50, 60, 80,100		160	1
			40, 50, 60, 80,100	20+20+20		
DC_(n)71AA	DC_(n)71AA <sup>3</sup>	15	5		20	0
		10	5, 10			
		5	5, 10, 15			
			5	15		
			5, 10	10		
			5, 10, 15	5		

NOTE 1: Contiguous intra-band EN-DC uplink requirements shall apply.

NOTE 2: LTE and NR ACLR requirements and non-contiguous intra-band EN-DC uplink requirements shall apply.

### 5.3B.1.3 BCS for Intra-band non-contiguous EN-DC

For intra-band non-contiguous EN-DC, an EN-DC configuration is a single operating band supporting E-UTRA and NR carriers, where E-UTRA configuration is indicated by using E-UTRA CA bandwidth class as defined in TS 36.101 [4] and NR configuration is indicated by using NR CA bandwidth class as defined in TS 38.101-1 [2].

Requirements for intra-band non-contiguous EN-DC are defined for the EN-DC configurations and bandwidth combination sets specified in Table 5.3B.1.3-1.

**Table 5.3B.1.3-1: EN-DC configurations and bandwidth combination sets defined for intra-band non-contiguous EN-DC**

E-UTRA – NR configuration / Bandwidth combination set						
Downlink EN-DC configuration	Uplink EN-DC configurations	Component carriers in order of increasing carrier frequency			Maximum aggregated bandwidth (MHz)	Bandwidth combination set
		Channel bandwidths for LTE carrier (MHz)	Channel bandwidths for NR carrier (MHz)	Channel bandwidths for LTE carrier (MHz)		

DC_3A_n3A	DC_3A_n3A <sup>(1)</sup>		5, 10, 15, 20, 25, 30	5, 10, 15, 20	50	0
DC_41A_n41A	DC_41A_n41A	20	40, 60, 80,100		120	0
			40, 60, 80,100	20		
		20	40, 50, 60, 80,100		120	1
			40, 50, 60, 80,100	20		
DC_41C_n41A	DC_41A_n41A	20+20	40, 60, 80,100		140	0
			40, 60, 80,100	20+20		
		20+20	40, 50, 60, 80,100		140	1
			40, 50, 60, 80,100	20+20		
DC_41D_n41A	DC_41A_n41A	20+20+20	40, 60, 80,100		160	0
			40, 60, 80,100	20+20+20		
		20+20+20	40, 50, 60, 80,100		160	1
			40, 50, 60, 80,100	20+20+20		

NOTE 1: Only single switched UL is supported in Rel.15.

## 5.4 Channel arrangement

### 5.4A Channel arrangement for CA

The channel arrangement for CA operations in FR1 and FR2 as specified in 38.101-1 and 38.101-2, respectively.

### 5.4B Channel arrangement for DC

The channel arrangement for intra-band EN-DC operations in FR1 is specified in TS 36.101 [4] and TS 38.101-1, respectively.

#### 5.4B.1 Channel spacing for intra-band EN-DC carriers

The spacing between carriers will depend on the deployment scenario, the size of the frequency block available and the channel bandwidths. The nominal channel spacing between and E-UTRA carrier and an adjacent NR carrier for intra-band contiguous EN-DC is defined as following:

- For NR operating bands with 15 kHz channel raster,

$$\text{Nominal Channel spacing} = (\text{BW}_{\text{E-UTRA\_Channel}} + \text{BW}_{\text{NR\_Channel}})/2 + \{-5\text{kHz}, 0\text{kHz}, 5\text{kHz}\}$$

- For NR operating bands with 30 kHz channel raster,

$$\text{Nominal Channel spacing} = (\text{BW}_{\text{E-UTRA\_Channel}} + \text{BW}_{\text{NR\_Channel}})/2 + \{-10\text{kHz}, 0\text{kHz}, 10\text{kHz}\}$$

where  $\text{BW}_{\text{E-UTRA\_Channel}}$  and  $\text{BW}_{\text{NR\_Channel}}$  are the channel bandwidths of the E-UTRA and NR carriers. The channel spacing can be adjusted depending on the channel raster to optimize performance in a particular deployment scenario.

For intra-band non-contiguous EN-DC the channel spacing between E-UTRA and NR carriers shall be larger than the nominal channel spacing defined in this subclause.

## 5.5 Configuration

### 5.5A Configuration for CA

#### 5.5A.1 Inter-band CA configurations between FR1 and FR2

**Table 5.5A.1-1: Inter-band CA configurations and bandwidth combinations sets between FR1 and FR2 (two bands)**

NR CA configuration	Uplink CA configuration	NR Band	SCS (kHz)	5 MHz	10 MHz	15 MHz	20 MHz	40 MHz	50 MHz	60 MHz	80 MHz	100 MHz	200 MHz	400 MHz	Band width combination set
CA_n8A-n258A	CA_n8A-n258A	n8	15	Yes	Yes	Yes	Yes								0
			30		Yes	Yes	Yes								
			60												
		n258	60						Yes			Yes	Yes		
			120						Yes			Yes	Yes	Yes	
CA_n71A-n257A	-	n71	15	Yes	Yes	Yes	Yes								0
			30		Yes	Yes	Yes								
			60												
		n257	60						Yes			Yes	Yes		
			120						Yes			Yes	Yes	Yes	
CA_n77A-n257A	CA_n77A-n257A	n77	15		Yes	Yes	Yes	Yes	Yes						0
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
		n257	60						Yes			Yes	Yes		
			120						Yes			Yes	Yes	Yes	
CA_n77A-n257D	CA_n77A-n257A	n77	15		Yes	Yes	Yes	Yes	Yes						0
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
		n257	See CA_n257D in Table 5.5A.1-1 in TS 38.521-2 [9]												
CA_n77A-n257E	CA_n77A-n257A	n77	15		Yes	Yes	Yes	Yes	Yes						0
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		
		n257	See CA_n257E in Table 5.5A.1-1 in TS 38.521-2 [9]												
CA_n77A-n257F	CA_n77A-n257A	n77	15		Yes	Yes	Yes	Yes	Yes						0
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
		n257	See CA_n257F in Table 5.5A.1-1 in TS 38.521-2 [9]												
CA_n77C-n257A	CA_n77A-n257A	n77	See CA_n77C in Table 5.5A.1-1 in TS 38.521-1 [8]											0	
		n257	60						Yes			Yes	Yes		
			120						Yes			Yes	Yes		Yes
CA_n77C-n257D	CA_n77A-n257A	n257	See CA_n77C in Table 5.5A.1-1 in TS 38.521-1 [8]											0	
CA_n77C-n257E	CA_n77A-n257A	n77	See CA_n77C in Table 5.5A.1-1 in TS 38.521-1 [8]											0	
		n257	See CA_n257E in Table 5.5A.1-2 in TS 38.521-2 [9]												
CA_n77C-n257F	CA_n77A-n257A	n77	See CA_n77C in Table 5.5A.1-1 in TS 38.521-1 [8]											0	
		n257	See CA_n257F in Table 5.5A.1-2 in TS 38.521-2 [9]												
CA_n78A-n257A	CA_n78A-n257A	n78	15		Yes	Yes	Yes	Yes	Yes						0
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		

		n257	60					Yes			Yes	Yes		
			120					Yes			Yes	Yes	Yes	
CA_n78A -n257D	CA_n78A -n257A	n78	15		Yes	Yes	Yes	Yes	Yes					
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		
		n257	See CA_n257D in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n78A -n257E	CA_n78A -n257A	n78	15		Yes	Yes	Yes	Yes	Yes					
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		
		n257	See CA_n257E in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n78A -n257F	CA_n78A -n257A	n78	15		Yes	Yes	Yes	Yes	Yes					
			30		Yes	Yes	Yes	Yes	Yes	Yes	Yes			
			60		Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		
		n257	See CA_n257F in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n78C -n257A	CA_n78A -n257A	n78	See CA_n78C in Table 5.5A.1-1 in TS 38.521-1 [8]											
		n257	60					Yes			Yes	Yes		
			120					Yes			Yes	Yes	Yes	
CA_n78C -n257D	CA_n78A -n257A	n78	See CA_n78C in Table 5.5A.1-1 in TS 38.521-1 [8]											
		n257	See CA_n257D in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n78C -n257E	CA_n78A -n257A	n78	See CA_n78C in Table 5.5A.1-1 in TS 38.521-1 [8]											
		n257	See CA_n257E in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n78C -n257F	CA_n78A -n257A	n78	See CA_n78C in Table 5.5A.1-1 in TS 38.521-1 [8]											
		n257	See CA_n257F in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n79A -n257A	CA_n79A -n257A	n79	15				Yes	Yes						
			30				Yes	Yes	Yes	Yes	Yes			
			60				Yes	Yes	Yes	Yes	Yes			
		n257	60					Yes			Yes	Yes		
			120					Yes			Yes	Yes	Yes	
CA_n79A -n257D	CA_n79A -n257A	n79	15				Yes	Yes						
			30				Yes	Yes	Yes	Yes	Yes			
			60				Yes	Yes	Yes	Yes	Yes			
		n257	See CA_n257D in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n79A -n257E	CA_n79A -n257A	n79	15				Yes	Yes						
			30				Yes	Yes	Yes	Yes	Yes			
			60				Yes	Yes	Yes	Yes	Yes			
		n257	See CA_n257E in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n79A -n257F	CA_n79A -n257A	n79	15				Yes	Yes						
			30				Yes	Yes	Yes	Yes	Yes			
			60				Yes	Yes	Yes	Yes	Yes			
		n257	See CA_n257F in Table 5.5A.1-1 in TS 38.521-2 [9]											
CA_n79C -n257A	CA_n79A -n257A	n79	See CA_n79C in Table 5.5A.1-1 in TS 38.521-1 [8]											
		n257	60					Yes			Yes	Yes		
			120					Yes			Yes	Yes	Yes	
		n79	See CA_n79C in Table 5.5A.1-1 in TS 38.521-1 [8]											

CA_n79C -n257D	CA_n79A -n257A	n257	See CA_n257D in Table 5.5A.1-2 in TS 38.521-2 [9]	
CA_n79C -n257E	CA_n79A -n257A	n79	See CA_n79C in Table 5.5A.1-1 in TS 38.521-1 [8]	0
		n257	See CA_n257E in Table 5.5A.1-1 in TS 38.521-2 [9]	
CA_n79C -n257F	CA_n79A -n257A	n79	See CA_n79C in Table 5.5A.1-1 in TS 38.521-1 [8]	0
		n257	See CA_n257F in Table 5.5A.1-1 in TS 38.521-2 [9]	

## 5.5B Configuration for DC

### 5.5B.1 General

The operating bands and bandwidth classes are specified for operation with EN-DC, NGEN-DC or NR-DC configured. The EN-DC or NGEN-DC band combinations include at least one E-UTRA operating band.

For EN-DC configurations indicated by column “Single Uplink allowed” (e.g., problematic band combinations as defined in TS38.306 [xx]) in tables in this section the UE may indicate capability of not supporting simultaneous dual and triple uplink operation due to possible intermodulation interference to its own primary downlink channel bandwidth if the intermodulation order is 2 or if the intermodulation order is 3 for the combinations when both operating bands are between 450 MHz – 960 MHz or between 1427 MHz – 2690 MHz. In case for the EN-DC configurations listed in tables in this section for which the intermodulation products caused by the dual and triple uplink operation fall into the receive band but do not interfere with the own primary downlink channel bandwidth as defined in Annex-I the UE is mandated to operate in dual and triple uplink mode. Single Uplink is also allowed for certain band combinations where intermodulation or reverse intermodulation products could create difficulty for meeting emission requirements.

For EN-DC combinations of order 3 or higher, “Single Uplink allowed” UL configurations captured in Table 5.5B.2-1, Table 5.5B.3-1, and Table 5.5B.4-1 apply.

If multiple UL DC configurations are listed for multiple DL DC configurations, valid uplink configurations are such that uplink does not have more carriers than downlink.

### 5.5B.2 Intra-band contiguous EN-DC

Supported channel bandwidths for E-UTRA operating bands are defined in TS 36.521-1 [10] and for NR operating bands in TS 38.521-1 [8].

**Table 5.5B.2-1: Intra-band contiguous EN-DC configurations**

EN-DC Configuration	Uplink EN-DC configuration (NOTE 1)	Single UL allowed
DC_(n)41AA <sup>5</sup> DC_(n)41CA <sup>5</sup> DC_(n)41DA <sup>5</sup>	DC_(n)41AA	Yes <sup>3</sup>
DC_(n)41CA <sup>5</sup> DC_(n)41DA <sup>5</sup>	DC_41A_n41A	Yes <sup>3</sup>
DC_(n)71AA	DC_(n)71AA	No <sup>4</sup>
NOTE 1: Uplink EN-DC configurations are the configurations supported by the present release of specifications.		
NOTE 2: Requirements in this specification apply for NR SCS of 15 kHz only.		
NOTE 3: Single UL allowed due to potential emission issues, not self-interference.		
NOTE 4: For UE(s) supporting dynamic power sharing it is mandatory to do dual simultaneous UL. For UE(s) not supporting dynamic power sharing single UL is allowed.		
NOTE 5: The minimum requirements only apply for non-simultaneous Tx/Rx between all carriers.		

### 5.5B.3 Intra-band non-contiguous EN-DC

Supported channel bandwidths for E-UTRA operating bands are defined in TS 36.521-1 [10] and for NR operating bands in TS 38.521-1 [8].



**Table 5.5B.3-1: Intra-band non-contiguous EN-DC configurations**

EN-DC Configuration	Uplink EN-DC configuration (NOTE 1)	Single UL allowed
DC_3A_n3A	DC_3A_n3A <sup>2</sup>	Yes <sup>2</sup>
DC_41A_n41A <sup>3</sup> DC_41C_n41A <sup>3</sup> DC_41D_n41A <sup>3</sup>	DC_41A_n41A	Yes
NOTE 1: Uplink EN-DC configurations are the configurations supported by the present release of specifications.		
NOTE 2: Only single switched UL is supported in Rel.15		
NOTE 3: The minimum requirements only apply for non-simultaneous Tx/Rx between all carriers.		

#### 5.5B.4 Inter-band EN-DC within FR1

Supported channel bandwidths for E-UTRA operating bands and CA configurations are defined in TS 36.521-1 [10] and for NR operating bands and CA configurations in TS 38.521-1 [8] and present document.

5.5B.4.1 Inter-band EN-DC configurations within FR1 (two bands)

**Table 5.5B.4.1-1: Inter-band EN-DC configurations within FR1 (two bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)	Single UL allowed
DC_1A_n28A	DC_1A_n28A	No
DC_1A_n40A	DC_1A_n40A	No
DC_1A_n51A	DC_1A_n51A	No
DC_1A_n77A <sup>7</sup> DC_1A_n77C <sup>7</sup>	DC_1A_n77A	DC_1_n77
DC_1A_n78A <sup>7</sup> DC_1A_n78C <sup>7</sup>	DC_1A_n78A	No
DC_1A_n79A <sup>7</sup> DC_1A_n79C <sup>7</sup>	DC_1A_n79A	No
DC_2A_n5A	DC_2A_n5A	No
DC_2A_n66A	DC_2A_n66A	DC_2_n66
DC_2A_n71A	DC_2A_n71A	No
DC_2A_n78A	DC_2A_n78A	DC_2_n78
DC_3A_n7A	DC_3A_n7A	No
DC_3A_n28A	DC_3A_n28A	No
DC_3A_n40A	DC_3A_n40A	No
DC_3A_n51A	DC_3A_n51A	No
DC_3A_n77A <sup>7</sup> DC_3A_n77C <sup>7</sup>	DC_3A_n77A	DC_3_n77
DC_3A_n78A <sup>7</sup> DC_3A_n78C <sup>7</sup> DC_3C_n78A <sup>7</sup>	DC_3A_n78A	DC_3_n78
DC_3A_n79A <sup>7</sup> DC_3A_n79C <sup>7</sup>	DC_3A_n79A	No
DC_5A_n40A	DC_5A_n40A	No
DC_5A_n66A	DC_5A_n66A	DC_5_n66
DC_5A_n78A <sup>7</sup>	DC_5A_n78A	No
DC_7A_n28A	DC_7A_n28A	No
DC_7A_n51A	DC_7A_n51A	No
DC_7A_n78A <sup>7</sup> DC_7C_n78A <sup>7</sup>	DC_7A_n78A DC_7C_n78A	No
DC_7A-7A_n78A <sup>7</sup>	DC_7A_n78A	No
DC_8A_n40A	DC_8A_n40A	No
DC_8A_n77A <sup>7</sup>	DC_8A_n77A	No
DC_8A_n78A <sup>7</sup>	DC_8A_n78A	No
DC_8A_n79A <sup>7</sup>	DC_8A_n79A	No
DC_11A_n77A <sup>7</sup>	DC_11A_n77A	No
DC_11A_n78A <sup>7</sup>	DC_11A_n78A	No
DC_11A_n79A <sup>7</sup>	DC_11A_n79A	No
DC_12A_n5A	DC_12A_n5A	No
DC_12A_n66A	DC_12A_n66A	No
DC_18A_n77A <sup>7</sup>	DC_18A_n77A	No
DC_18A_n78A <sup>7</sup>	DC_18A_n78A	No
DC_18A_n79A <sup>7</sup>	DC_18A_n79A	No
DC_19A_n77A <sup>7</sup> DC_19A_n77C <sup>7</sup>	DC_19A_n77A	No

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)	Single UL allowed
DC_19A_n78A <sup>7</sup> DC_19A_n78C <sup>7</sup>	DC_19A_n78A	No
DC_19A_n79A <sup>7</sup> DC_19A_n79C <sup>7</sup>	DC_19A_n79A	No
DC_20A_n8A	DC_20A_n8A	DC_20_n8
DC_20A_n28A <sup>8,10</sup>	DC_20A_n28A	No
DC_20A_n51A	DC_20A_n51A	No
DC_20A_n77A	DC_20A_n77A	No
DC_20A_n78A <sup>7</sup>	DC_20A_n78A	No
DC_21A_n77A <sup>7</sup> DC_21A_n77C <sup>7</sup>	DC_21A_n77A	No
DC_21A_n78A <sup>7</sup> DC_21A_n78C <sup>7</sup>	DC_21A_n78A	No
DC_21A_n79A <sup>7</sup> DC_21A_n79C <sup>7</sup>	DC_21A_n79A	No
DC_25A_n41A	DC_25A_n41A	No
DC_26A_n41A <sup>7</sup>	DC_26A_n41A	No
DC_26A_n77A <sup>7</sup>	DC_26A_n77A	No
DC_26A_n78A <sup>7</sup>	DC_26A_n78A	No
DC_26A_n79A <sup>7</sup>	DC_26A_n79A	No
DC_28A_n51A	DC_28A_n51A	No
DC_28A_n77A <sup>7</sup> DC_28A_n77C <sup>7</sup>	DC_28A_n77A	No
DC_28A_n78A <sup>7</sup> DC_28A_n78C <sup>7</sup>	DC_28A_n78A	No
DC_28A_n79A <sup>7</sup> DC_28A_n79C <sup>7</sup>	DC_28A_n79A	No
DC_30A_n5A	DC_30A_n5A	No
DC_30A_n66A	DC_30A_n66A	No
DC_38A_n78A	N/A	No
DC_39A_n78A <sup>5,7</sup>	DC_39A_n78A	No
DC_39A_n79A <sup>7</sup>	DC_39A_n79A	No
DC_40A_n77A	N/A	No
DC_41A_n77A DC_41C_n77A	DC_41A_n77A DC_41C_n77A	No
DC_41A_n78A DC_41C_n78A	DC_41A_n78A DC_41C_n78A	No
DC_41A_n79A <sup>6,7</sup> DC_41C_n79A <sup>6,7</sup>	DC_41A_n79A DC_41C_n79A	No
DC_42A_n51A	DC_42A_n51A	No
DC_42A_n77A <sup>3,4,9</sup> DC_42A_n77C <sup>3,4,9</sup> DC_42C_n77A <sup>3,4,9</sup> DC_42C_n77C <sup>3,4,9</sup> DC_42D_n77A <sup>3,4,9</sup> DC_42E_n77A <sup>3,4,9</sup>	N/A	N/A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)	Single UL allowed
DC_42A_n78A <sup>3,4,9</sup> DC_42A_n78C <sup>3,4,9</sup> DC_42C_n78A <sup>3,4,9</sup> DC_42C_n78C <sup>3,4,9</sup> DC_42D_n78A <sup>3,4,9</sup> DC_42E_n78A <sup>3,4,9</sup>	N/A	N/A
DC_42A_n79A <sup>9</sup> DC_42A_n79C <sup>9</sup> DC_42C_n79A <sup>9</sup> DC_42C_n79C <sup>9</sup> DC_42D_n79A <sup>9</sup> DC_42E_n79A <sup>9</sup>	N/A	N/A
DC_46A_n78A <sup>2</sup> DC_46C_n78A <sup>2</sup> DC_46D_n78A <sup>2</sup> DC_46E_n78A <sup>2</sup>	N/A	N/A
DC_66A_n5A	DC_66A_n5A	DC_66_n5
DC_66A_n71A	DC_66A_n71A	No
DC_66A_n78A	DC_66A_n78A	No
<p>NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.</p> <p>NOTE 2: Restricted to E-UTRA operation when inter-band carrier aggregation is configured. The downlink operating band for Band 46 is paired with the uplink operating band (external E-UTRA band) of the carrier aggregation configuration that is supporting the configured Pcell.</p> <p>NOTE 3: The minimum requirements apply only when there is non-simultaneous Tx/Rx operation between E-UTRA and NR carriers. This restriction applies also for these carriers when applicable EN-DC configuration is part of a higher order EN-DC configuration.</p> <p>NOTE 4: The minimum requirements for intra-band EN-DC apply. The intra-band requirements also apply for these carriers when applicable EN-DC configuration is a subset of a higher order EN-DC configuration.</p> <p>NOTE 5: The frequency range above 3600 MHz for Band n78 is not used in this combination.</p> <p>NOTE 6: The frequency range below 2506 MHz for Band 41 is not used in this combination.</p> <p>NOTE 7: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability.</p> <p>NOTE 8: The frequency range in band n28 is restricted for this band combination to 703-733 MHz for the UL and 758-788 MHz for the DL.</p> <p>NOTE 9: The combination is not used alone as fall back mode of other band combinations in which UL in Band 42 is not used.</p> <p>NOTE 10: The maximum power spectral density imbalance between downlink carriers is within [6] dB. The power spectral density imbalance condition also applies for these carriers when applicable EN-DC configuration is a subset of a higher order EN-DC configuration.</p>		

5.5B.4.2 Inter-band EN-DC configurations within FR1 (three bands)

**Table 5.5B.4.2-1: Inter-band EN-DC configurations within FR1 (three bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A_n28A	DC_1A_n28A DC_3A_n28A
DC_1A-3A_n77A <sup>5</sup> DC_1A-3A_n77C <sup>5</sup>	DC_1A_n77A DC_3A_n77A
DC_1A-3A_n78A <sup>5</sup> DC_1A-3A_n78C <sup>5</sup> DC_1A-3C_n78A <sup>5</sup>	DC_1A_n78A DC_3A_n78A
DC_1A-3A_n79A <sup>5</sup> DC_1A-3A_n79C <sup>5</sup>	DC_1A_n79A DC_3A_n79A
DC_1A-5A_n78A <sup>5</sup>	DC_1A_n78A DC_5A_n78A
DC_1A-7A_n28A <sup>5</sup>	DC_1A_n28A DC_7A_n28A
DC_1A-7A_n78A <sup>5</sup>	DC_1A_n78A DC_7A_n78A
DC_1A-7A-7A_n78A <sup>5</sup>	DC_1A_n78A DC_7A_n78A
DC_1A-8A_n78A <sup>5</sup>	DC_1A_n78A DC_8A_n78A
DC_1A-18A_n77A <sup>5</sup>	DC_1A_n77A DC_18A_n77A
DC_1A-18A_n78A <sup>5</sup>	DC_1A_n78A DC_18A_n78A
DC_1A-18A_n79A	DC_1A_n79A DC_18A_n79A
DC_1A-19A_n77A <sup>5</sup> DC_1A-19A_n77C <sup>5</sup>	DC_1A_n77A DC_19A_n77A
DC_1A-19A_n78A <sup>5</sup> DC_1A-19A_n78C <sup>5</sup>	DC_1A_n78A DC_19A_n78A
DC_1A-19A_n79A <sup>5</sup> DC_1A-19A_n79C <sup>5</sup>	DC_1A_n79A DC_19A_n79A
DC_1A-20A_n28A <sup>6</sup>	DC_1A_n28A DC_20A_n28A
DC_1A-20A_n78A <sup>5</sup>	DC_1A_n78A DC_20A_n78A
DC_1A-21A_n77A <sup>5</sup> DC_1A-21A_n77C <sup>5</sup>	DC_1A_n77A DC_21A_n77A
DC_1A-21A_n78A <sup>5</sup> DC_1A-21A_n78C <sup>5</sup>	DC_1A_n78A DC_21A_n78A
DC_1A-21A_n79A <sup>5</sup> DC_1A-21A_n79C <sup>5</sup>	DC_1A_n79A DC_21A_n79A
DC_1A-28A_n77A <sup>5</sup> DC_1A-28A_n77C <sup>5</sup>	DC_1A_n77A DC_28A_n77A
DC_1A-28A_n78A <sup>5</sup> DC_1A-28A_n78C <sup>5</sup>	DC_1A_n78A DC_28A_n78A
DC_1A_n28A-n78A <sup>5</sup>	DC_1A_n28A, DC_1A_n78A
DC_1A-28A_n79A DC_1A-28A_n79C	DC_1A_n79A DC_28A_n79A
DC_1A-41A_n77A DC_1A-41C_n77A	DC_1A_n77A DC_41A_n77A DC_41C_n77A
DC_1A-41A_n78A DC_1A-41C_n78A	DC_1A_n78A DC_41A_n78A DC_41C_n78A
DC_1A-41C_n79A	DC_1A_n79A DC_41C_n79A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-42A_n77A DC_1A-42A_n77C DC_1A-42C_n77A DC_1A-42C_n77C DC_1A-42D_n77A DC_1A-42E_n77A	DC_1A_n77A
DC_1A-42A_n78A DC_1A-42A_n78C DC_1A-42C_n78A DC_1A-42C_n78C DC_1A-42D_n78A DC_1A-42E_n78A	DC_1A_n78A
DC_1A-42A_n79A DC_1A-42A_n79C DC_1A-42C_n79A DC_1A-42C_n79C DC_1A-42D_n79A DC_1A-42E_n79A	DC_1A_n79A
DC_1A_n77A-n79A	DC_1A_n77A DC_1A_n79A
DC_1A_n78A-n79A	DC_1A_n78A DC_1A_n79A
DC_1A_SUL_n78A-n84A <sup>5</sup>	DC_1A_n78A DC_1A_n84A_ULSUP-TDM_n78A DC_1A_n84A_ULSUP-FDM_n78A
DC_2A-5A_n66A	DC_2A_n66A DC_5A_n66A
DC_2A-12A_n66A	DC_2A_n66A DC_12A_n66A
DC_2A-30A_n66A	DC_2A_n66A DC_30A_n66A
DC_2A-66A_n71A	DC_2A_n71A DC_66A_n71A
DC_2A-(n)71AA	DC_2A_n71A DC_(n)71AA
DC_3A_n3A-n77A	DC_3A_n77A DC_3A_n3A <sup>2</sup>
DC_3A_n3A-n78A	DC_3A_n78A DC_3A_n3A <sup>2</sup>
DC_3A-5A_n78A <sup>5</sup>	DC_3A_n78A DC_5A_n78A
DC_3A-7A_n28A	DC_3A_n28A DC_7A_n28A
DC_3A-7A_n78A <sup>5</sup> DC_3C-7A_n78A <sup>5</sup>	DC_3A_n78A DC_7A_n78A
DC_3A-7C_n78A <sup>5</sup> DC_3C-7C_n78A <sup>5</sup>	DC_3A_n78A DC_7C_n78A
DC_3A-7A-7A_n78A <sup>5</sup>	DC_3A_n78A DC_7A_n78A
DC_3A-8A_n78A	DC_3A_n78A DC_8A_n78A
DC_3A-19A_n77A <sup>5</sup> DC_3A-19A_n77C <sup>5</sup>	DC_3A_n77A DC_19A_n77A
DC_3A-19A_n78A <sup>5</sup> DC_3A-19A_n78C <sup>5</sup>	DC_3A_n78A DC_19A_n78A
DC_3A-19A_n79A <sup>5</sup> DC_3A-19A_n79C <sup>5</sup>	DC_3A_n79A DC_19A_n79A
DC_3A-20A_n28A <sup>5,6</sup>	DC_3A_n28A DC_20A_n28A



EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_3A-20A_n78A <sup>5</sup> DC_3C-20A_n78A <sup>5</sup>	DC_3A_n78A DC_20A_n78A
DC_3A-21A_n77A <sup>5</sup> DC_3A-21A_n77C <sup>5</sup>	DC_3A_n77A DC_21A_n77A
DC_3A-21A_n78A <sup>5</sup> DC_3A-21A_n78C <sup>5</sup>	DC_3A_n78A DC_21A_n78A
DC_3A-21A_n79A <sup>5</sup> DC_3A-21A_n79C <sup>5</sup>	DC_3A_n79A DC_21A_n79A
DC_3A-28A_n77A DC_3A-28A_n77C	DC_3A_n77A DC_28A_n77A
DC_3A-28A_n78A <sup>5</sup> DC_3A-28A_n78C <sup>5</sup>	DC_3A_n78A DC_28A_n78A
DC_3A_n28A-n78A <sup>5</sup>	DC_3A_n28A, DC_3A_n78A
DC_3A-28A_n79A DC_3A-28A_n79C	DC_3A_n79A DC_28A_n79A
DC_3A-38A_n78A	DC_3A_n78A
DC_3A-41A_n78A	DC_3A_n78A DC_41A_n78A
DC_3A-42A_n77A DC_3A-42A_n77C DC_3A-42C_n77A DC_3A-42C_n77C DC_3A-42D_n77A DC_3A-42E_n77A	DC_3A_n77A
DC_3A-42A_n78A DC_3A-42A_n78C DC_3A-42C_n78A DC_3A-42C_n78C DC_3A-42D_n78A DC_3A-42E_n78A	DC_3A_n78A
DC_3A-42A_n79A DC_3A-42A_n79C DC_3A-42C_n79A DC_3A-42C_n79C DC_3A-42D_n79A DC_3A-42E_n79A	DC_3A_n79A
DC_3A_n77A-n79A	DC_3A_n77A DC_3A_n79A
DC_3A_n78A-n79A	DC_3A_n78A DC_3A_n79A
DC_3A_SUL_n78A-n80A <sup>5</sup>	DC_3A_n78A DC_3A_n80A_ULSUP-TDM_n78A DC_3A_n80A_ULSUP-FDM_n78A
DC_3A_SUL_n78A-n82A <sup>5</sup>	DC_3A_n78A DC_3A_n82A
DC_3A_SUL_n79A-n80A <sup>5</sup>	DC_3A_n79A DC_3A_n80A_ULSUP-TDM_n79A DC_3A_n80A_ULSUP-FDM_n79A
DC_5A-7A_n78A	DC_5A_n78A DC_7A_n78A
DC_5A-7A-7A_n78A	DC_5A_n78A DC_7A_n78A
DC_5A-30A_n66A	DC_5A_n66A DC_30A_n66A
DC_7A-20A_n28A <sup>6</sup>	DC_7A_n28A DC_20A_n28A
DC_7A-20A_n78A <sup>5</sup>	DC_7A_n78A DC_20A_n78A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_7A-28A_n78A <sup>5</sup>	DC_7A_n78A DC_28A_n78A
DC_7C-28A_n78A <sup>5</sup>	DC_7C_n78A DC_28A_n78A
DC_7A_n28A-n78A <sup>5</sup>	DC_7A_n28A, DC_7A_n78A
DC_7A-46A_n78A <sup>3</sup> DC_7A-46C_n78A <sup>3</sup> DC_7A-46D_n78A <sup>3</sup> DC_7A-46E_n78A <sup>3</sup>	DC_7A_n78A
DC_8A_SUL_n78A-n81A <sup>5</sup>	DC_8A_n78A DC_8A_n81A_ULSUP-TDM_n78A DC_8A_n81A_ULSUP-FDM_n78A
DC_8A_SUL_n79A-n81A <sup>5</sup>	DC_8A_n79A DC_8A_n81A_ULSUP-TDM_n79A DC_8A_n81A_ULSUP-FDM_n79A
DC_12A-30A_n66A	DC_12A_n66A DC_30A_n66A
DC_18A-28A_n77A <sup>5</sup>	DC_18A_n77A DC_28A_n77A
DC_18A-28A_n78A <sup>5</sup>	DC_18A_n78A DC_28A_n78A
DC_18A-28A_n79A <sup>5</sup>	DC_18A_n79A DC_28A_n79A
DC_19A-21A_n77A <sup>5</sup> DC_19A-21A_n77C <sup>5</sup>	DC_19A_n77A DC_21A_n77A
DC_19A-21A_n78A <sup>5</sup> DC_19A-21A_n78C <sup>5</sup>	DC_19A_n78A DC_21A_n78A
DC_19A-21A_n79A <sup>5</sup> DC_19A-21A_n79C <sup>5</sup>	DC_19A_n79A DC_21A_n79A
DC_19A-42A_n77A DC_19A-42A_n77C DC_19A-42C_n77A DC_19A-42C_n77C	DC_19A_n77A
DC_19A-42A_n78A DC_19A-42A_n78C DC_19A-42C_n78A DC_19A-42C_n78C	DC_19A_n78A
DC_19A-42A_n79A DC_19A-42A_n79C DC_19A-42C_n79A DC_19A-42C_n79C	DC_19A_n79A
DC_19A_n77A-n79A	DC_19A_n77A DC_19A_n79A
DC_19A_n78A-n79A	DC_19A_n78A DC_19A_n79A
DC_20A_n8A-n75A <sup>6</sup>	DC_20A_n8A
DC_20A_n28A-n75A <sup>6</sup>	DC_20A_n28A
DC_20A_n28A-n78A <sup>5,6</sup>	DC_20A_n28A DC_20A_n78A
DC_20A_n75A-n78A <sup>5</sup>	DC_20A_n78A
DC_20A_n76A-n78A <sup>5</sup>	DC_20A_n78A
DC_20A_SUL_n78A-n82A <sup>5</sup>	DC_20A_n78A DC_20A_n82A_ULSUP-TDM_n78A DC_20A_n82A_ULSUP-FDM_n78A
DC_20A_SUL_n78A-n83A <sup>5</sup>	DC_20A_n78A DC_20A_n83A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_21A-28A_n77A DC_21A-28A_n77C	DC_21A_n77A DC_28A_n77A
DC_21A-28A_n78A DC_21A-28A_n78C	DC_21A_n78A DC_28A_n78A
DC_21A-28A_n79A DC_21A-28A_n79C	DC_21A_n79A DC_28A_n79A
DC_21A-42A_n77A DC_21A-42A_n77C DC_21A-42C_n77A DC_21A-42C_n77C	DC_21A_n77A
DC_21A-42A_n78A DC_21A-42A_n78C DC_21A-42C_n78A DC_21A-42C_n77C	DC_21A_n78A
DC_21A-42A_n79A DC_21A-42A_n79C DC_21A-42C_n79A DC_21A-42C_n77C	DC_21A_n79A
DC_21A_n77A-n79A	DC_21A_n77A DC_21A_n79A
DC_21A_n78A-n79A	DC_21A_n78A DC_21A_n79A
DC_28A-42A_n77A DC_28A-42A_n77C DC_28A-42C_n77A	DC_28A_n77A
DC_28A-42A_n78A DC_28A-42A_n78C DC_28A-42C_n78A	DC_28A_n78A
DC_28A-42A_n79A DC_28A-42A_n79C DC_28A-42C_n79A	DC_28A_n79A
DC_28A_SUL_n78A-n83A <sup>5</sup>	DC_28A_n78A DC_28A_n83A_ULSUP-TDM_n78A DC_28A_n83A_ULSUP-FDM_n78A
DC_41A-42A_n77A DC_41A-42C_n77A DC_41C-42A_n77A DC_41C-42C_n77A	DC_41A_n77A DC_41C_n77A
DC_41A-42A_n78A DC_41A-42C_n78A DC_41C-42A_n78A DC_41C-42C_n78A	DC_41A_n78A DC_41C_n78A
DC_41A-42A_n79A DC_41A-42C_n79A DC_41C-42A_n79A DC_41C-42C_n79A	DC_41A_n79A DC_41C_n79A
DC_66A_(n)71AA	DC_66A_n71A DC_(n)71AA
DC_66A_SUL_n78A-n86A <sup>5</sup>	DC_66A_n78A DC_66A_n86A_ULSUP-TDM_n78A DC_66A_n86A_ULSUP-FDM_n78A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
<p>NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.</p> <p>NOTE 2: Only single switched UL is supported in Rel.15</p> <p>NOTE 3: Restricted to E-UTRA operation when inter-band carrier aggregation is configured. The downlink operating band for Band 46 is paired with the uplink operating band (external E-UTRA band) of the carrier aggregation configuration that is supporting the configured Pcell.</p> <p>NOTE 4: If a UE is configured with both NR UL and NR SUL carriers in a cell, the switching time between NR UL carrier and NR SUL carrier can be up to 140us and placed in SUL resources.</p> <p>NOTE 5: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability</p> <p>NOTE 6: The frequency range in band n28 is restricted for this band combination to 703-733 MHz for the UL and 758-788 MHz for the DL.</p>	

5.5B.4.3 Inter-band EN-DC configurations within FR1 (four bands)

**Table 5.5B.4.3-1: Inter-band EN-DC configurations within FR1 (four bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_5A_n78A
DC_1A-3A-7A_n28A	DC_1A_n28A DC_3A_n28A DC_7A_n28A
DC_1A-3A-7A_n78A <sup>2</sup> DC_1A-3C-7A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_7A_n78A
DC_1A-3A-7A-7A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_7A_n78A
DC_1A-3A-8A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_8A_n78A
DC_1A-3A-19A_n77A <sup>2</sup> DC_1A-3A-19A_n77C <sup>2</sup>	DC_1A_n77A DC_3A_n77A DC_19A_n77A
DC_1A-3A-19A_n78A <sup>2</sup> DC_1A-3A-19A_n78C <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_19A_n78A
DC_1A-3A-19A_n79A <sup>2</sup> DC_1A-3A-19A_n79C <sup>2</sup>	DC_1A_n79A DC_3A_n79A DC_19A_n79A
DC_1A-3A-20A_n28A <sup>3</sup>	DC_1A_n28A DC_3A_n28A DC_20A_n28A
DC_1A-3A-20A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_20A_n78A
DC_1A-3A-21A_n77A <sup>2</sup> DC_1A-3A-21A_n77C <sup>2</sup>	DC_1A_n77A DC_3A_n77A DC_21A_n77A
DC_1A-3A-21A_n78A <sup>2</sup> DC_1A-3A-21A_n78C <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_21A_n78A
DC_1A-3A-21A_n79A <sup>2</sup> DC_1A-3A-21A_n79C <sup>2</sup>	DC_1A_n79A DC_3A_n79A DC_21A_n79A
DC_1A-3A-28A_n77A <sup>2</sup>	DC_1A_n77A DC_3A_n77A DC_28A_n77A
DC_1A-3A-28A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_28A_n78A
DC_1A-3A_n28A-n78A <sup>2</sup>	DC_1A_n28A DC_1A_n78A DC_3A_n28A DC_3A_n78A
DC_1A-3A-28A_n79A <sup>2</sup>	DC_1A_n79A DC_3A_n79A DC_28A_n79A
DC_1A-3A-42A_n77A DC_1A-3A-42A_n77C DC_1A-3A-42C_n77A DC_1A-3A-42C_n77C	DC_1A_n77A DC_3A_n77A
DC_1A-3A-42A_n78A DC_1A-3A-42A_n78C DC_1A-3A-42C_n78A DC_1A-3A-42C_n78C	DC_1A_n78A DC_3A_n78A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-42A_n79A DC_1A-3A-42A_n79C DC_1A-3A-42C_n79A DC_1A-3A-42C_n79C	DC_1A_n79A DC_3A_n79A
DC_1A-5A-7A_n78A	DC_1A_n78A DC_5A_n78A DC_7A_n78A
DC_1A-5A-7A-7A_n78A	DC_1A_n78A DC_5A_n78A DC_7A_n78A
DC_1A-7A-20A_n28A <sup>3</sup>	DC_1A_n28A DC_7A_n28A DC_20A_n28A
DC_1A-7A-20A_n78A <sup>2</sup>	DC_1A_n78A DC_7A_n78A DC_20A_n78A
DC_1A-7A_n28A-n78A <sup>2</sup>	DC_1A_n28A DC_1A_n78A DC_7A_n28A DC_7A_n78A
DC_1A-18A-28A_n77A	DC_1A_n77A DC_18A_n77A DC_28A_n77A
DC_1A-18A-28A_n78A	DC_1A_n78A DC_18A_n78A DC_28A_n78A
DC_1A-18A-28A_n79A <sup>2</sup>	DC_1A_n79A DC_18A_n79A DC_28A_n79A
DC_1A-19A-21A_n77A DC_1A-19A-21A_n77C	DC_1A_n77A DC_19A_n77A DC_21A_n77A
DC_1A-19A-21A_n78A DC_1A-19A-21A_n78C	DC_1A_n78A DC_19A_n78A DC_21A_n78A
DC_1A-19A-21A_n79A DC_1A-19A-21A_n79C	DC_1A_n79A DC_19A_n79A DC_21A_n79A
DC_1A-19A-42A_n77A DC_1A-19A-42A_n77C DC_1A-19A-42C_n77A DC_1A-19A-42C_n77C	DC_1A_n77A DC_19A_n77A
DC_1A-19A-42A_n78A DC_1A-19A-42A_n78C DC_1A-19A-42C_n78A DC_1A-19A-42C_n78C	DC_1A_n78A DC_19A_n78A
DC_1A-19A-42A_n79A DC_1A-19A-42A_n79C DC_1A-19A-42C_n79A DC_1A-19A-42C_n79C	DC_1A_n79A DC_19A_n79A
DC_1A-20A_n28A-n78A <sup>2,3</sup>	DC_1A_n28A DC_1A_n78A DC_20A_n28A DC_20A_n78A
DC_1A-21A-28A_n77A <sup>2</sup>	DC_1A_n77A DC_21A_n77A DC_28A_n77A
DC_1A-21A-28A_n78A <sup>2</sup>	DC_1A_n78A DC_21A_n78A DC_28A_n78A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-21A-28A_n79A <sup>2</sup>	DC_1A_n79A DC_21A_n79A DC_28A_n79A
DC_1A-21A-42A_n77A DC_1A-21A-42A_n77C DC_1A-21A-42C_n77A DC_1A-21A-42C_n77C	DC_1A_n77A DC_21A_n77A
DC_1A-21A-42A_n78A DC_1A-21A-42A_n78C DC_1A-21A-42C_n78A DC_1A-21A-42C_n78C	DC_1A_n78A DC_21A_n78A
DC_1A-21A-42A_n79A DC_1A-21A-42A_n79C DC_1A-21A-42C_n79A DC_1A-21A-42C_n79C	DC_1A_n79A DC_21A_n79A
DC_1A-28A-42A_n77A DC_1A-28A-42C_n77A	DC_1A_n77A DC_28A_n77A
DC_1A-28A-42A_n78A DC_1A-28A-42C_n78A	DC_1A_n78A DC_28A_n78A
DC_1A-28A-42A_n79A DC_1A-28A-42C_n79A	DC_1A_n79A DC_28A_n79A
DC_1A-41A-42A_n77A DC_1A-41A-42C_n77A DC_1A-41C-42A_n77A DC_1A-41C-42C_n77A	DC_1A_n77A DC_41A_n77A
DC_1A-41A-42A_n78A DC_1A-41A-42C_n78A DC_1A-41C-42A_n78A DC_1A-41C-42C_n78A	DC_1A_n78A DC_41A_n78A
DC_1A-41A-42A_n79A DC_1A-41A-42C_n79A DC_1A-41C-42A_n79A DC_1A-41C-42C_n79A	DC_1A_n79A DC_41A_n79A
DC_2A-66A-(n)71AA	DC_2A_n71A DC_66A_n71A DC_(n)71AA
DC_3A-5A-7A_n78A	DC_3A_n78A DC_5A_n78A DC_7A_n78A
DC_3A-5A-7A-7A_n78A	DC_3A_n78A DC_5A_n78A DC_7A_n78A
DC_3A-7A-20A_n28A <sup>3</sup>	DC_3A_n28A DC_7A_n28A DC_20A_n28A
DC_3A-7A-20A_n78A <sup>2</sup>	DC_3A_n78A DC_7A_n78A DC_20A_n78A
DC_3A-7A-28A_n78A <sup>2</sup> DC_3A-7C-28A_n78A <sup>2</sup>	DC_3A_n78A DC_7A_n78A DC_28A_n78A
DC_3A-7A_n28A-n78A <sup>2</sup>	DC_3A_n28A DC_3A_n78A DC_7A_n28A DC_7A_n78A
DC_3A-19A-21A_n77A <sup>2</sup> DC_3A-19A-21A_n77C <sup>2</sup>	DC_3A_n77A DC_19A_n77A DC_21A_n77A
DC_3A-19A-21A_n78A <sup>2</sup> DC_3A-19A-21A_n78C <sup>2</sup>	DC_3A_n78A DC_19A_n78A DC_21A_n78A



EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_3A-19A-21A_n79A <sup>2</sup> DC_3A-19A-21A_n79C <sup>2</sup>	DC_3A_n79A DC_19A_n79A DC_21A_n79A
DC_3A-19A-42A_n77A DC_3A-19A-42A_n77C DC_3A-19A-42C_n77A DC_3A-19A-42C_n77C	DC_3A_n77A DC_19A_n77A
DC_3A-19A-42A_n78A DC_3A-19A-42A_n78C DC_3A-19A-42C_n78A DC_3A-19A-42C_n78C	DC_3A_n78A DC_19A_n78A
DC_3A-19A-42A_n79A <sup>2</sup> DC_3A-19A-42A_n79C <sup>2</sup> DC_3A-19A-42C_n79A <sup>2</sup> DC_3A-19A-42C_n79C <sup>2</sup>	DC_3A_n79A DC_19A_n79A
DC_3A-20A_n28A-n78A <sup>2,3</sup>	DC_3A_n28A DC_3A_n78A DC_20A_n28A DC_20A_n78A
DC_3A-21A-42A_n77A DC_3A-21A-42A_n77C DC_3A-21A-42C_n77A DC_3A-21A-42C_n77C	DC_3A_n77A DC_21A_n77A
DC_3A-21A-42A_n78A DC_3A-21A-42A_n78C DC_3A-21A-42C_n78A DC_3A-21A-42C_n78C	DC_3A_n78A DC_21A_n78A
DC_3A-21A-42A_n79A DC_3A-21A-42A_n79C DC_3A-21A-42C_n79A DC_3A-21A-42C_n79C	DC_3A_n79A DC_21A_n79A
DC_3A-28A-42A_n77A DC_3A-28A-42C_n77A	DC_3A_n77A DC_28A_n77A
DC_3A-28A-42A_n78A DC_3A-28A-42C_n78A	DC_3A_n78A DC_28A_n78A
DC_3A-28A-42A_n79A DC_3A-28A-42C_n79A	DC_3A_n79A DC_28A_n79A
DC_7A-20A_n28A-n78A <sup>2,3</sup>	DC_7A_n28A DC_7A_n78A DC_20A_n28A DC_20A_n78A
DC_19A-21A-42A_n77A DC_19A-21A-42A_n77C DC_19A-21A-42C_n77A DC_19A-21A-42C_n77C	DC_19A_n77A DC_21A_n77A
DC_19A-21A-42A_n78A DC_19A-21A-42A_n78C DC_19A-21A-42C_n78A DC_19A-21A-42C_n78C	DC_19A_n78A DC_21A_n78A
DC_19A-21A-42A_n79A DC_19A-21A-42A_n79C DC_19A-21A-42C_n79A DC_19A-21A-42C_n79C	DC_19A_n79A DC_21A_n79A
DC_21A-28A-42A_n77A DC_21A-28A-42C_n77A	DC_21A_n77A DC_28A_n77A
DC_21A-28A-42A_n78A DC_21A-28A-42C_n78A	DC_21A_n78A DC_28A_n78A
DC_21A-28A-42A_n79A DC_21A-28A-42C_n79A	DC_21A_n79A DC_28A_n79A

<b>EN-DC configuration</b>	<b>Uplink EN-DC configuration (NOTE 1)</b>
<p>NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.</p> <p>NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability</p> <p>NOTE 3: The frequency range in band n28 is restricted for this band combination to 703-733 MHz for the UL and 758-788 MHz for the DL.</p>	

5.5B.4.4 Inter-band EN-DC configurations within FR1 (five bands)

**Table 5.5B.4.4-1: Inter-band EN-DC configurations within FR1 (five bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A-7A_n78A	DC_1A_n78A DC_3A_n78A DC_5A_n78A DC_7A_n78A
DC_1A-3A-5A-7A-7A_n78A	DC_1A_n78A DC_3A_n78A DC_5A_n78A DC_7A_n78A
DC_1A-3A-7A-20A_n28A <sup>3</sup>	DC_1A_n28A DC_3A_n28A DC_7A_n28A DC_20A_n28A
DC_1A-3A-7A-20A_n78A <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_7A_n78A DC_20A_n78A
DC_1A-3A-7A_n28A-n78A <sup>2</sup>	DC_1A_n28A DC_1A_n78A DC_3A_n28A DC_3A_n78A DC_7A_n28A DC_7A_n78A
DC_1A-3A-19A-21A_n77A <sup>2</sup> DC_1A-3A-19A-21A_n77C <sup>2</sup>	DC_1A_n77A DC_3A_n77A DC_19A_n77A DC_21A_n77A
DC_1A-3A-19A-21A_n78A <sup>2</sup> DC_1A-3A-19A-21A_n78C <sup>2</sup>	DC_1A_n78A DC_3A_n78A DC_19A_n78A DC_21A_n78A
DC_1A-3A-19A-21A_n79A <sup>2</sup> DC_1A-3A-19A-21A_n79C <sup>2</sup>	DC_1A_n79A DC_3A_n79A DC_19A_n79A DC_21A_n79A
DC_1A-3A-19A-42A_n77A DC_1A-3A-19A-42A_n77C DC_1A-3A-19A-42C_n77A DC_1A-3A-19A-42C_n77C	DC_1A_n77A DC_3A_n77A DC_19A_n77A
DC_1A-3A-19A-42A_n78A DC_1A-3A-19A-42A_n78C DC_1A-3A-19A-42C_n78A DC_1A-3A-19A-42C_n78C	DC_1A_n78A DC_3A_n78A DC_19A_n78A
DC_1A-3A-19A-42A_n79A DC_1A-3A-19A-42A_n79C DC_1A-3A-19A-42C_n79A DC_1A-3A-19A-42C_n79C	DC_1A_n79A DC_3A_n79A DC_19A_n79A
DC_1A-3A-20A_n28A-n78A <sup>2,3</sup>	DC_1A_n28A DC_1A_n78A DC_3A_n28A DC_3A_n78A DC_20A_n28A DC_20A_n78A
DC_1A-3A-21A-42A_n77A DC_1A-3A-21A-42A_n77C DC_1A-3A-21A-42C_n77A DC_1A-3A-21A-42C_n77C	DC_1A_n77A DC_3A_n77A DC_21A_n77A
DC_1A-3A-21A-42A_n78A DC_1A-3A-21A-42A_n78C DC_1A-3A-21A-42C_n78A DC_1A-3A-21A-42C_n78C	DC_1A_n78A DC_3A_n78A DC_21A_n78A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-21A-42A_n79A DC_1A-3A-21A-42A_n79C DC_1A-3A-21A-42C_n79A DC_1A-3A-21A-42C_n79C	DC_1A_n79A DC_3A_n79A DC_21A_n79A
DC_1A-3A-28A-42A_n77A DC_1A-3A-28A-42C_n77A	DC_1A_n77A DC_3A_n77A DC_28A_n77A
DC_1A-3A-28A-42A_n78A DC_1A-3A-28A-42C_n78A	DC_1A_n78A DC_3A_n78A DC_28A_n78A
DC_1A-3A-28A-42A_n79A DC_1A-3A-28A-42C_n79A	DC_1A_n79A DC_3A_n79A DC_28A_n79A
DC_1A-7A-20A_n28A-n78A <sup>2,3</sup>	DC_1A_n28A DC_1A_n78A DC_7A_n28A DC_7A_n78A DC_20A_n28A DC_20A_n78A
DC_1A-19A-21A-42A_n77A DC_1A-19A-21A-42A_n77C DC_1A-19A-21A-42C_n77A DC_1A-19A-21A-42C_n77C	DC_1A_n77A DC_19A_n77A DC_21A_n77A
DC_1A-19A-21A-42A_n78A DC_1A-19A-21A-42A_n78C DC_1A-19A-21A-42C_n78A DC_1A-19A-21A-42C_n78C	DC_1A_n78A DC_19A_n78A DC_21A_n78A
DC_1A-19A-21A-42A_n79A DC_1A-19A-21A-42A_n79C DC_1A-19A-21A-42C_n79A DC_1A-19A-21A-42C_n79C	DC_1A_n79A DC_19A_n79A DC_21A_n79A
DC_1A-21A-28A-42A_n77A DC_1A-21A-28A-42C_n77A	DC_1A_n77A DC_21A_n77A DC_28A_n77A
DC_1A-21A-28A-42A_n78A DC_1A-21A-28A-42C_n78A	DC_1A_n78A DC_21A_n78A DC_28A_n78A
DC_1A-21A-28A-42A_n79A DC_1A-21A-28A-42C_n79A	DC_1A_n79A DC_21A_n79A DC_28A_n79A
DC_3A-7A-20A_n28A-n78A <sup>2,3</sup>	DC_3A_n28A DC_3A_n78A DC_7A_n28A DC_7A_n78A DC_20A_n28A DC_20A_n78A
<p>NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.</p> <p>NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability</p> <p>NOTE 3: The frequency range in band n28 is restricted for this band combination to 703-733 MHz for the UL and 758-788 MHz for the DL</p>	

## 5.5B.4.5 Inter-band EN-DC configurations within FR1 (six bands)

Table 5.5B.4.5-1: Inter-band EN-DC configurations within FR1 (six bands)

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-7A-20A_n28A-n78A <sup>2,3</sup>	DC_1A_n28A DC_1A_n78A DC_3A_n28A DC_3A_n78A DC_7A_n28A DC_7A_n78A DC_20A_n28A DC_20A_n78A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications. NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability NOTE 3: The frequency range in band n28 is restricted for this band combination to 703-733 MHz for the UL and 758-788 MHz for the DL	

## 5.5B.5 Inter-band EN-DC including FR2

Supported channel bandwidths for E-UTRA operating bands and CA configurations are defined in TS 36.521-1 [10] and for NR operating bands and CA configurations in TS 38.521-1 [8], TS 38.521-2 [9] and present document.

5.5B.5.1 Inter-band EN-DC configurations including FR2 (two bands)

**Table 5.5B.5.1-1: Inter-band EN-DC configurations including FR2 (two bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A_n257A DC_1A_n257D DC_1A_n257E DC_1A_n257F	DC_1A_n257A
DC_2A_n257A DC_2C_n257A	DC_2A_n257A
DC_2A_n257(2A)	DC_2A_n257A
DC_2A-2A_n257A	DC_2A_n257A
DC_2A_n260A DC_2A_n260G DC_2A_n260H DC_2A_n260I DC_2A_n260J DC_2A_n260K DC_2A_n260L DC_2A_n260M DC_2C_n260A	DC_2A_n260A
DC_2A_n260(2A)	DC_2A_n260A
DC_2A-2A_n260A DC_2A-2A_n260G DC_2A-2A_n260H DC_2A-2A_n260I DC_2A-2A_n260J DC_2A-2A_n260K DC_2A-2A_n260L DC_2A-2A_n260M	DC_2A_n260A
DC_3A_n257A DC_3A_n257D DC_3A_n257E DC_3A_n257F	DC_3A_n257A
DC_3A_n258A	DC_3A_n258A
DC_5A_n257A DC_5B_n257A	DC_5A_n257A DC_5B_n257A
DC_5A-5A_n257A	DC_5A_n257A
DC_5A_n260A DC_5A_n260B DC_5A_n260C DC_5A_n260D DC_5A_n260E DC_5A_n260F DC_5A_n260G DC_5A_n260H DC_5A_n260I DC_5A_n260J DC_5A_n260K DC_5A_n260L DC_5A_n260M DC_5A_n260O DC_5A_n260P DC_5A_n260Q DC_5B_n260A	DC_5A_n260A DC_5B_n260A



EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_5A_n260(2A) DC_5A_n260(3A) DC_5A_n260(4A) DC_5A_n260(A-I) DC_5A_n260(D-G) DC_5A_n260(D-H) DC_5A_n260(D-I) DC_5A_n260(D-O) DC_5A_n260(D-P) DC_5A_n260(D-Q) DC_5A_n260(E-O) DC_5A_n260(E-P) DC_5A_n260(E-Q) DC_5A_n260(G-I)	DC_5A_n260A
DC_5A-5A_n260A	DC_5A_n260A
DC_5A_n261A DC_5A_n261B DC_5A_n261C DC_5A_n261D DC_5A_n261E DC_5A_n261F DC_5A_n261G DC_5A_n261H DC_5A_n261I DC_5A_n261J DC_5A_n261K DC_5A_n261L DC_5A_n261M DC_5A_n261O DC_5A_n261P DC_5A_n261Q	DC_5A_n261A
DC_5A_n261(2A) DC_5A_n261(3A) DC_5A_n261(4A) DC_5A_n261(D-G) DC_5A_n261(D-H) DC_5A_n261(D-I) DC_5A_n261(D-O) DC_5A_n261(D-P) DC_5A_n261(D-Q) DC_5A_n261(E-O) DC_5A_n261(E-P) DC_5A_n261(E-Q)	DC_5A_n261A
DC_7A_n257A	DC_7A_n257A
DC_7A-7A_n257A	DC_7A_n257A
DC_7A_n258A	DC_7A_n258A
DC_8A_n257A	DC_8A_n257A
DC_8A_n258A	DC_8A_n258A
DC_11A_n257A	DC_11A_n257A
DC_12A_n260A DC_12A_n260G DC_12A_n260H DC_12A_n260I DC_12A_n260J DC_12A_n260K DC_12A_n260L DC_12A_n260M	DC_12A_n260A
DC_12A_n260(A-I) DC_12A_n260(G-I)	DC_12A_n260A
DC_13A_n257A	DC_13A_n257A
DC_13A_n260A	DC_13A_n260A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_18A_n257A	DC_18A_n257A
DC_19A_n257A DC_19A_n257D DC_19A_n257E DC_19A_n257F	DC_19A_n257A
DC_20A_n258A	DC_20A_n258A
DC_21A_n257A DC_21A_n257D DC_21A_n257E DC_21A_n257F	DC_21A_n257A
DC_26A_n257A	DC_26A_n257A
DC_28A_n257A DC_28A_n257D DC_28A_n257E DC_28A_n257F	DC_28A_n257A
DC_28A_n258A	DC_28A_n258A
DC_30A_n260A DC_30A_n260G DC_30A_n260H DC_30A_n260I DC_30A_n260J DC_30A_n260K DC_30A_n260L DC_30A_n260M	DC_30A_n260A
DC_30A_n260(A-I) DC_30A_n260(G-I)	DC_30A_n260A
DC_39A_n258A	DC_39A_n258A
DC_41A_n257A DC_41C_n257A	DC_41A_n257A DC_41C_n257A
DC_41A_n258A	DC_41A_n258A
DC_42A_n257A DC_42A_n257D DC_42A_n257E DC_42A_n257F DC_42C_n257A DC_42E_n257A DC_42C_n257A DC_42C_n257D DC_42C_n257E DC_42C_n257F DC_42D_n257A	DC_42A_n257A DC_42C_n257A
DC_48A_n257A DC_48C_n257A	DC_48A_n257A DC_48C_n257A
DC_48A-48A_n257A	DC_48A_n257A
DC_48A_n260A DC_48C_n260A	DC_48A_n260A DC_48C_n260A
DC_48A-48A_n260A	DC_48A_n260A
DC_66A_n257A DC_66A_n257G DC_66A_n257H DC_66A_n257I DC_66A_n257J DC_66A_n257K DC_66A_n257L DC_66A_n257M DC_66C_n257A	DC_66A_n257A DC_66C_n257A
DC_66A_n257(2A)	DC_66A_n257A
DC_66A-66A_n257A	DC_66A_n257A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_66A_n260A DC_66A_n260D DC_66A_n260E DC_66A_n260F DC_66A_n260G DC_66A_n260H DC_66A_n260I DC_66A_n260J DC_66A_n260K DC_66A_n260L DC_66A_n260M DC_66A_n260O DC_66A_n260P DC_66A_n260Q	DC_66A_n260A
DC_66A_n260(2A) DC_66A_n260(3A) DC_66A_n260(4A) DC_66A_n260(A-I) DC_66A_n260(D-G) DC_66A_n260(D-H) DC_66A_n260(D-I) DC_66A_n260(D-O) DC_66A_n260(D-Q) DC_66A_n260(E-O) DC_66A_n260(E-P) DC_66A_n260(E-Q) DC_66A_n260(G-I)	DC_66A_n260A
DC_66A-66A_n260A DC_66A-66A_n260G DC_66A-66A_n260H DC_66A-66A_n260I DC_66A-66A_n260J DC_66A-66A_n260K DC_66A-66A_n260L DC_66A-66A_n260M	DC_66A_n260A
DC_66A_n261A DC_66A_n261D DC_66A_n261E DC_66A_n261F DC_66A_n261G DC_66A_n261H DC_66A_n261I DC_66A_n261J DC_66A_n261K DC_66A_n261L DC_66A_n261M DC_66A_n261O DC_66A_n261P DC_66A_n261Q	DC_66A_n261A
DC_66A_n261(2A) DC_66A_n261(3A) DC_66A_n261(4A) DC_66A_n261(D-G) DC_66A_n261(D-H) DC_66A_n261(D-I) DC_66A_n261(D-O) DC_66A_n261(D-P) DC_66A_n261(D-Q) DC_66A_n261(E-O) DC_66A_n261(E-P) DC_66A_n261(E-Q)	DC_66A_n261A

<b>EN-DC configuration</b>	<b>Uplink EN-DC configuration (NOTE 1)</b>
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications. NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability for all of the above combinations	

5.5B.5.2 Inter-band EN-DC configurations including FR2 (three bands)

**Table 5.5B.5.2-1: Inter-band EN-DC configurations including FR2 (three bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A_n257A <sup>2</sup> DC_1A-3A_n257D <sup>2</sup> DC_1A-3A_n257E <sup>2</sup> DC_1A-3A_n257F <sup>2</sup>	DC_1A_n257A DC_3A_n257A
DC_1A-5A_n257A <sup>2</sup>	DC_1A_n257A DC_5A_n257A
DC_1A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_7A_n257A
DC_1A-7A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_7A_n257A
DC_1A-8A_n257A <sup>2</sup>	DC_1A_n257A DC_8A_n257A
DC_1A-18A_n257A <sup>2</sup>	DC_1A_n257A DC_18A_n257A
DC_1A-19A_n257A <sup>2</sup> DC_1A-19A_n257D <sup>2</sup> DC_1A-19A_n257E <sup>2</sup> DC_1A-19A_n257F <sup>2</sup>	DC_1A_n257A DC_19A_n257A
DC_1A-21A_n257A <sup>2</sup> DC_1A-21A_n257D <sup>2</sup> DC_1A-21A_n257E <sup>2</sup> DC_1A-21A_n257F <sup>2</sup>	DC_1A_n257A DC_21A_n257A
DC_1A-28A_n257A <sup>2</sup> DC_1A-28A_n257D <sup>2</sup> DC_1A-28A_n257E <sup>2</sup> DC_1A-28A_n257F <sup>2</sup>	DC_1A_n257A DC_28A_n257A
DC_1A-41A_n257A DC_1A-41C_n257A	DC_1A_n257A DC_41A_n257A DC_41C_n257A
DC_1A-42A_n257A DC_1A-42A_n257D DC_1A-42A_n257E DC_1A-42A_n257F DC_1A-42C_n257A DC_1A-42D_n257A DC_1A-42E_n257A	DC_1A_n257A DC_42A_n257A
DC_2A-5A_n257A <sup>2</sup>	DC_2A_n257A DC_5A_n257A
DC_2A-5A_n260A DC_2A-5A_n260G DC_2A-5A_n260H DC_2A-5A_n260I DC_2A-5A_n260J DC_2A-5A_n260K DC_2A-5A_n260L DC_2A-5A_n260M	DC_2A_n260A DC_5A_n260A
DC_2A-12A_n260A DC_2A-12A_n260G DC_2A-12A_n260H DC_2A-12A_n260I DC_2A-12A_n260J DC_2A-12A_n260K DC_2A-12A_n260L DC_2A-12A_n260M	DC_2A_n260A DC_12A_n260A
DC_2A-13A_n257A <sup>2</sup>	DC_2A_n257A DC_13A_n257A
DC_2A-13A_n260A <sup>2</sup>	DC_2A_n260A DC_13A_n260A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_2A-30A_n260A DC_2A-30A_n260G DC_2A-30A_n260H DC_2A-30A_n260I DC_2A-30A_n260J DC_2A-30A_n260K DC_2A-30A_n260L DC_2A-30A_n260M	DC_2A_n260A DC_30A_n260A
DC_2A-66A_n257A <sup>2</sup>	DC_2A_n257A DC_66A_n257A
DC_2A-66A_n260A DC_2A-66A_n260G DC_2A-66A_n260H DC_2A-66A_n260I DC_2A-66A_n260J DC_2A-66A_n260K DC_2A-66A_n260L DC_2A-66A_n260M	DC_2A_n260A DC_66A_n260A
DC_3A-5A_n257A <sup>2</sup>	DC_3A_n257A DC_5A_n257A
DC_3A-7A_n257A <sup>2</sup>	DC_3A_n257A DC_7A_n257A
DC_3A-7A-7A_n257A <sup>2</sup>	DC_3A_n257A DC_7A_n257A
DC_3A-19A_n257A <sup>2</sup> DC_3A-19A_n257D <sup>2</sup> DC_3A-19A_n257E <sup>2</sup> DC_3A-19A_n257F <sup>2</sup>	DC_3A_n257A DC_19A_n257A
DC_3A-21A_n257A <sup>2</sup> DC_3A-21A_n257D <sup>2</sup> DC_3A-21A_n257E <sup>2</sup> DC_3A-21A_n257F <sup>2</sup>	DC_3A_n257A DC_21A_n257A
DC_3A-28A_n257A <sup>2</sup> DC_3A-28A_n257D <sup>2</sup> DC_3A-28A_n257E <sup>2</sup> DC_3A-28A_n257F <sup>2</sup>	DC_3A_n257A DC_28A_n257A
DC_3A-41A_n257A	DC_3A_n257A DC_41A_n257A
DC_3A-42A_n257A <sup>2</sup> DC_3A-42A_n257D <sup>2</sup> DC_3A-42A_n257E <sup>2</sup> DC_3A-42A_n257F <sup>2</sup> DC_3A-42C_n257A <sup>2</sup> DC_3A-42D_n257A <sup>2</sup> DC_3A-42E_n257A <sup>2</sup>	DC_3A_n257A DC_42A_n257A
DC_5A-7A_n257A <sup>2</sup>	DC_5A_n257A DC_7A_n257A
DC_5A-7A-7A_n257A	DC_5A_n257A DC_7A_n257A
DC_5A-30A_n260A DC_5A-30A_n260G DC_5A-30A_n260H DC_5A-30A_n260I DC_5A-30A_n260J DC_5A-30A_n260K DC_5A-30A_n260L DC_5A-30A_n260M	DC_5A_n260A DC_30A_n260A
DC_5A-66A_n257A	DC_5A_n257A DC_66A_n257A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_5A-66A_n260A DC_5A-66A_n260G DC_5A-66A_n260H DC_5A-66A_n260I DC_5A-66A_n260J DC_5A-66A_n260K DC_5A-66A_n260L DC_5A-66A_n260M	DC_5A_n260A DC_66A_n260A
DC_12A-30A_n260A DC_12A-30A_n260G DC_12A-30A_n260H DC_12A-30A_n260I DC_12A-30A_n260J DC_12A-30A_n260K DC_12A-30A_n260L DC_12A-30A_n260M	DC_12A_n260A DC_30A_n260A
DC_12A-66A_n260A DC_12A-66A_n260G DC_12A-66A_n260H DC_12A-66A_n260I DC_12A-66A_n260J DC_12A-66A_n260K DC_12A-66A_n260L DC_12A-66A_n260M	DC_12A_n260A DC_66A_n260A
DC_13A-66A_n257A <sup>2</sup>	DC_13A_n257A DC_66A_n257A
DC_13A-66A_n260A <sup>2</sup>	DC_13A_n260A DC_66A_n260A
DC_18A-28A_n257A <sup>2</sup>	DC_18A_n257A DC_28A_n257A
DC_19A-21A_n257A <sup>2</sup> DC_19A-21A_n257D <sup>2</sup> DC_19A-21A_n257E <sup>2</sup> DC_19A-21A_n257F <sup>2</sup>	DC_19A_n257A DC_21A_n257A
DC_19A-42A_n257A <sup>2</sup> DC_19A-42A_n257D <sup>2</sup> DC_19A-42A_n257E <sup>2</sup> DC_19A-42A_n257F <sup>2</sup> DC_19A-42C_n257A <sup>2</sup>	DC_19A_n257A DC_42A_n257A
DC_21A-28A_n257A <sup>2</sup> DC_21A-28A_n257D <sup>2</sup> DC_21A-28A_n257E <sup>2</sup> DC_21A-28A_n257F <sup>2</sup>	DC_21A_n257A DC_28A_n257A
DC_21A-42A_n257A <sup>2</sup> DC_21A-42A_n257D <sup>2</sup> DC_21A-42A_n257E <sup>2</sup> DC_21A-42A_n257F <sup>2</sup> DC_21A-42C_n257A <sup>2</sup>	DC_21A_n257A DC_42A_n257A
DC_28A-42C_n257A <sup>2</sup> DC_28A-42A_n257A <sup>2</sup>	DC_28A_n257A DC_42A_n257A
DC_30A-66A_n260A DC_30A-66A_n260G DC_30A-66A_n260H DC_30A-66A_n260I DC_30A-66A_n260J DC_30A-66A_n260K DC_30A-66A_n260L DC_30A-66A_n260M	DC_30A_n260A DC_66A_n260A
DC_41A-42A_n257A DC_41A-42C_n257A DC_41C-42A_n257A DC_41C-42C_n257A	DC_41A_n257A DC_42A_n257A



<b>EN-DC configuration</b>	<b>Uplink EN-DC configuration (NOTE 1)</b>
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications. NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability	

5.5B.5.3 Inter-band EN-DC configurations including FR2 (four bands)

**Table 5.5B.5.3-1: Inter-band EN-DC configurations including FR2 (four bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_5A_n257A
DC_1A-3A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_7A_n257A
DC_1A-3A-7A-7A_n257A	DC_1A_n257A DC_3A_n257A DC_7A_n257A
DC_1A-3A-19A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_19A_n257A
DC_1A-3A-21A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_21A_n257A
DC_1A-3A-28A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_28A_n257A
DC_1A-3A-42A_n257A DC_1A-3A-42C_n257A DC_1A-3A-42C_n257D DC_1A-3A-42C_n257E DC_1A-3A-42C_n257F	DC_1A_n257A DC_3A_n257A DC_42A_n257A
DC_1A-5A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_5A_n257A DC_7A_n257A
DC_1A-5A-7A-7A_n257A	DC_1A_n257A DC_5A_n257A DC_7A_n257A
DC_1A-18A-28A_n257A <sup>2</sup>	DC_1A_n257A DC_18A_n257A DC_28A_n257A
DC_1A-19A-21A_n257A DC_1A-19A-21A_n257D DC_1A-19A-21A_n257E DC_1A-19A-21A_n257F	DC_1A_n257A DC_19A_n257A DC_21A_n257A
DC_1A-19A-42A_n257A DC_1A-19A-42C_n257A DC_1A-19A-42C_n257D DC_1A-19A-42C_n257E DC_1A-19A-42C_n257F	DC_1A_n257A DC_19A_n257A DC_42A_n257A
DC_1A-21A-28A_n257A <sup>2</sup>	DC_1A_n257A DC_21A_n257A DC_28A_n257A
DC_1A-21A-42A_n257A DC_1A-21A-42C_n257A DC_1A-21A-42C_n257D DC_1A-21A-42C_n257E DC_1A-21A-42C_n257F	DC_1A_n257A DC_21A_n257A DC_42A_n257A
DC_1A-28A-42A_n257A DC_1A-28A-42C_n257A	DC_1A_n257A DC_28A_n257A DC_42A_n257A
DC_1A-41A-42A_n257A DC_1A-41A-42C_n257A DC_1A-41C-42A_n257A DC_1A-41C-42C_n257A	DC_1A_n257A DC_41A_n257A DC_42A_n257A
DC_3A-5A-7A_n257A <sup>2</sup>	DC_3A_n257A DC_5A_n257A DC_7A_n257A

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_3A-5A-7A-7A_n257A <sup>2</sup>	DC_3A_n257A DC_5A_n257A DC_7A_n257A
DC_3A-19A-21A_n257A <sup>2</sup>	DC_3A_n257A DC_19A_n257A DC_21A_n257A
DC_3A-19A-42A_n257A DC_3A-19A-42C_n257A DC_3A-19A-42C_n257D DC_3A-19A-42C_n257E DC_3A-19A-42C_n257F	DC_3A_n257A DC_19A_n257A DC_42A_n257A
DC_3A-21A-42A_n257A DC_3A-21A-42C_n257A DC_3A-21A-42C_n257D DC_3A-21A-42C_n257E DC_3A-21A-42C_n257F	DC_3A_n257A DC_21A_n257A DC_42A_n257A
DC_3A-28A-42A_n257A DC_3A-28A-42C_n257A	DC_3A_n257A DC_28A_n257A DC_42A_n257A
DC_19A-21A-42A_n257A <sup>2</sup> DC_19A-21A-42C_n257A <sup>2</sup> DC_19A-21A-42C_n257D <sup>2</sup> DC_19A-21A-42C_n257E <sup>2</sup> DC_19A-21A-42C_n257F <sup>2</sup>	DC_19A_n257A DC_21A_n257A DC_42A_n257A
DC_21A-28A-42A_n257A <sup>2</sup> DC_21A-28A-42C_n257A <sup>2</sup>	DC_21A_n257A DC_28A_n257A DC_42A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.	
NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability	

## 5.5B.5.4 Inter-band EN-DC configurations including FR2 (five bands)

Table 5.5B.5.4-1: Inter-band EN-DC configurations including FR2 (five bands)

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_5A_n257A DC_7A_n257A
DC_1A-3A-5A-7A-7A_n257A <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_5A_n257A DC_7A_n257A
DC_1A-3A-19A-21A_n257A <sup>2</sup> DC_1A-3A-19A-21A_n257D <sup>2</sup> DC_1A-3A-19A-21A_n257E <sup>2</sup> DC_1A-3A-19A-21A_n257F <sup>2</sup>	DC_1A_n257A DC_3A_n257A DC_19A_n257A DC_21A_n257A
DC_1A-3A-19A-42A_n257A DC_1A-3A-19A-42A_n257D DC_1A-3A-19A-42A_n257E DC_1A-3A-19A-42A_n257F DC_1A-3A-19A-42C_n257A DC_1A-3A-19A-42C_n257D DC_1A-3A-19A-42C_n257E DC_1A-3A-19A-42C_n257F	DC_1A_n257A DC_3A_n257A DC_19A_n257A DC_42A_n257A
DC_1A-3A-21A-42A_n257A DC_1A-3A-21A-42C_n257A DC_1A-3A-21A-42C_n257D DC_1A-3A-21A-42C_n257E DC_1A-3A-21A-42C_n257F	DC_1A_n257A DC_3A_n257A DC_21A_n257A DC_42A_n257A
DC_1A-3A-28A-42A_n257A DC_1A-3A-28A-42C_n257A	DC_1A_n257A DC_3A_n257A DC_28A_n257A DC_42A_n257A
DC_1A-19A-21A-42A_n257A DC_1A-19A-21A-42A_n257D DC_1A-19A-21A-42A_n257E DC_1A-19A-21A-42A_n257F DC_1A-19A-21A-42C_n257A DC_1A-19A-21A-42C_n257D DC_1A-19A-21A-42C_n257E DC_1A-19A-21A-42C_n257F	DC_1A_n257A DC_19A_n257A DC_21A_n257A DC_42A_n257A
DC_1A-19A-28A-42C_n257A	DC_1A_n257A DC_19A_n257A DC_28A_n257A DC_42A_n257A
DC_1A-21A-28A-42A_n257A	DC_1A_n257A DC_21A_n257A DC_28A_n257A DC_42A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications. NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability	

### 5.5B.5.5 Inter-band EN-DC configurations including FR2 (six bands)

**Table 5.5B.5.5-1: Inter-band EN-DC configurations including FR2 (six bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
FFS	
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.	

### 5.5B.6 Inter-band EN-DC including FR1 and FR2

Supported channel bandwidths for E-UTRA operating bands and CA configurations are defined in TS 36.521-1 [10] and for NR operating bands and CA configurations in TS 38.521-1 [8], TS 38.521-2 [9] and present document.

5.5B.6.1 Void

5.5B.6.2 Inter-band EN-DC configurations including FR1 and FR2 (three bands)

**Table 5.5B.6.2-1: Inter-band EN-DC configurations including FR1 and FR2\_(three bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A_n77A-n257A DC_1A_n77A-n257D DC_1A_n77A-n257E DC_1A_n77A-n257F DC_1A_n77C-n257A DC_1A_n77C-n257D DC_1A_n77C-n257E DC_1A_n77C-n257F	DC_1A_n77A DC_1A_n257A DC_1A_n77A-n257A
DC_1A_n78A-n257A DC_1A_n78A-n257D DC_1A_n78A-n257E DC_1A_n78A-n257F DC_1A_n78C-n257A DC_1A_n78C-n257D DC_1A_n78C-n257E DC_1A_n78C-n257F	DC_1A_n78A DC_1A_n257A DC_1A_n78A-n257A
DC_1A_n79A-n257A DC_1A_n79A-n257D DC_1A_n79A-n257E DC_1A_n79A-n257F DC_1A_n79C-n257A DC_1A_n79C-n257D DC_1A_n79C-n257E DC_1A_n79C-n257F	DC_1A_n79A DC_1A_n257A DC_1A_n79A-n257A
DC_3A_n77A-n257A DC_3A_n77A-n257D DC_3A_n77A-n257E DC_3A_n77A-n257F DC_3A_n77C-n257A DC_3A_n77C-n257D DC_3A_n77C-n257E DC_3A_n77C-n257F	DC_3A_n77A DC_3A_n257A DC_3A_n77A-n257A
DC_3A_n78A-n257A DC_3A_n78A-n257D DC_3A_n78A-n257E DC_3A_n78A-n257F DC_3A_n78C-n257A DC_3A_n78C-n257D DC_3A_n78C-n257E DC_3A_n78C-n257F	DC_3A_n78A DC_3A_n257A DC_3A_n78A-n257A
DC_3A_n79A-n257A DC_3A_n79A-n257D DC_3A_n79A-n257E DC_3A_n79A-n257F DC_3A_n79C-n257A DC_3A_n79C-n257D DC_3A_n79C-n257E DC_3A_n79C-n257F	DC_3A_n79A DC_3A_n257A DC_3A_n79A-n257A
DC_5A_n78A-n257A <sup>2</sup>	DC_5A_n78A DC_5A_n257A
DC_7A_n78A-n257A	DC_7A_n78A DC_7A_n257A
DC_7A-7A_n78A-n257A	DC_7A_n78A DC_7A_n257A DC_7A_n78A-n257A
DC_19A_n77A-n257A DC_19A_n77A-n257D DC_19A_n77A-n257E DC_19A_n77A-n257F DC_19A_n77C-n257A DC_19A_n77C-n257D DC_19A_n77C-n257E DC_19A_n77C-n257F	DC_19A_n77A DC_19A_n257A DC_19A_n77A-n257A



EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_19A_n78A-n257A DC_19A_n78A-n257D DC_19A_n78A-n257E DC_19A_n78A-n257F DC_19A_n78C-n257A DC_19A_n78C-n257D DC_19A_n78C-n257E DC_19A_n78C-n257F	DC_19A_n78A DC_19A_n257A DC_19A_n78A-n257A
DC_19A_n79A-n257A DC_19A_n79A-n257D DC_19A_n79A-n257E DC_19A_n79A-n257F DC_19A_n79C-n257A DC_19A_n79C-n257D DC_19A_n79C-n257E DC_19A_n79C-n257F	DC_19A_n79A DC_19A_n257A DC_19A_n79A-n257A
DC_21A_n77A-n257A	DC_21A_n77A DC_21A_n257A
DC_21A_n78A-n257A	DC_21A_n78A DC_21A_n257A
DC_21A_n79A-n257A	DC_21A_n79A DC_21A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications. NOTE 2: Applicable for UE supporting inter-band EN-DC with mandatory simultaneous Rx/Tx capability	

## 5.5B.6.3 Inter-band EN-DC configurations including FR1 and FR2 (four bands)

Table 5.5B.6.3-1: Inter-band EN-DC configurations including FR1 and FR2 (four bands)

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_3A_n78A DC_3A_n257A
DC_1A-5A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_5A_n78A DC_5A_n257A
DC_1A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_7A_n78A DC_7A_n257A
DC_1A-7A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_7A_n78A DC_7A_n257A
DC_3A-5A_n78A-n257A	DC_3A_n78A DC_3A_n257A DC_5A_n78A DC_5A_n257A
DC_3A-7A_n78A-n257A	DC_3A_n78A DC_3A_n257A DC_7A_n78A DC_7A_n257A
DC_3A-7A-7A_n78A-n257A	DC_3A_n78A DC_3A_n257A DC_7A_n78A DC_7A_n257A
DC_5A-7A_n78A-n257A	DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
DC_5A-7A-7A_n78A-n257A	DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.	

5.5B.6.4 Inter-band EN-DC configurations including FR1 and FR2 (five bands)

**Table 5.5B.6.4-1: Inter-band EN-DC configurations including FR1 and FR2 (five bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_3A_n78A DC_3A_n257A DC_5A_n78A DC_5A_n257A
DC_1A-3A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_3A_n78A DC_3A_n257A DC_7A_n78A DC_7A_n257A
DC_1A-3A-7A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_3A_n78A DC_3A_n257A DC_7A_n78A DC_7A_n257A
DC_1A-5A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
DC_1A-5A-7A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
DC_3A-5A-7A_n78A-n257A	DC_3A_n78A DC_3A_n257A DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
DC_3A-5A-7A-7A_n78A-n257A	DC_3A_n78A DC_3A_n257A DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.	

### 5.5B.6.5 Inter-band EN-DC configurations including FR1 and FR2 (six bands)

**Table 5.5B.6.5-1: Inter-band EN-DC configurations including FR1 and FR2 (six bands)**

EN-DC configuration	Uplink EN-DC configuration (NOTE 1)
DC_1A-3A-5A-7A_n78A-n257A	DC_1A_n78A DC_1A_n257A DC_3A_n78A DC_3A_n257A DC_5A_n78A DC_5A_n257A DC_7A_n78A DC_7A_n257A
NOTE 1: Uplink CA configurations are the configurations supported by the present release of specifications.	

### 5.5B.7 Inter-band NR-DC between FR1 and FR2

Supported channel bandwidths for E-UTRA operating bands and CA configurations are defined in TS 36.521-1 [10] and for NR operating bands and CA configurations in TS 38.521-1 [8], TS 38.521-2 [9] and present document.

## 5.5B.7.1 Inter-band NR-DC configurations between FR1 and FR2 (two bands)

Table 5.5B.7-1: Inter-band NR-DC configurations between FR1 and FR2 (two bands)

Downlink NR DC configuration	Uplink NR DC configuration (Note 1)
DC_n77A-n257A DC_n77A-n257D DC_n77A-n257E DC_n77A-n257F DC_n77A-n257G DC_n77A-n257H DC_n77A-n257I DC_n77A-n257J DC_n77A-n257K DC_n77A-n257L DC_n77A-n257M DC_n77C-n257A DC_n77C-n257D DC_n77C-n257E DC_n77C-n257F	DC_n77A-n257A
DC_n78A-n257A DC_n78A-n257D DC_n78A-n257E DC_n78A-n257F DC_n78A-n257G DC_n78A-n257H DC_n78A-n257I DC_n78A-n257J DC_n78A-n257K DC_n78A-n257L DC_n78A-n257M DC_n78C-n257A DC_n78C-n257D DC_n78C-n257E DC_n78C-n257F	DC_n78A-n257A
DC_n79A-n257A DC_n79A-n257D DC_n79A-n257E DC_n79A-n257F DC_n79A-n257G DC_n79A-n257H DC_n79A-n257I DC_n79A-n257J DC_n79A-n257K DC_n79A-n257L DC_n79A-n257M DC_n79C-n257A DC_n79C-n257D DC_n79C-n257E DC_n79C-n257F	DC_n79A-n257A
NOTE 1: NR configuration for FR1 and FR2 are defined in TS 38.101-1 [2] and TS 38.101-2 [3] respectively.	

---

## 6 Transmitter characteristics

### 6.1 General

**Editor's Note:** Test configurations/environments that require new spherical scan shall be included in test procedure section and identifying such scenarios is currently FFS and owned by RAN5.

For Tx test cases the identified beam peak direction can be stored and reused for a device under test in various configurations/environments for the full duration of device testing as long as beam peak direction is the same.

Unless otherwise stated the transmitter, characteristics are specified at the antenna connector(s) of the UE for the bands operating on frequency range 1 and over the air of the UE for the bands operating on frequency range 2. The requirements for frequency range 1 and frequency range 2 can be verified separately. For the carrier in frequency range 1, requirements can be verified with NR FR2 link disabled. For the carrier in frequency range 2, requirements can be verified in OTA mode with LTE connecting to the network by OTA without calibration.

Unless otherwise stated, requirements for NR transmitter written in TS 38.101-1 and TS 38.101-2 apply and are assumed anchor agnostic. Requirements are verified under conditions where anchor resources do not interfere NR operation.

Unless otherwise stated, Channel Bandwidth shall be prioritized in the selecting of test points. Subcarrier spacing shall be selected after Test Channel Bandwidth is selected.

For conformance testing involving FR2 test cases in this specification, the UE under test shall disable UL Tx diversity schemes.

## 6.2 Transmitter power

### 6.2A Transmitter power for CA without EN-DC

#### 6.2A.1 UE maximum output power for CA

##### 6.2A.1.1 UE maximum output power for inter-band NR CA between FR 1 and FR 2 without EN-DC

###### 6.2A.1.1.1 Test purpose

Same test purpose as in clause 6.2.1 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.2.1 in TS 38.521-2 [9] for NR FR2 carrier(s).

###### 6.2A.1.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for maximum output power apply and are tested in TS 38.521-1 [8] clauses 6.2 and 6.2A and TS 38.521-2 [9] clauses 6.2 and 6.2A

#### 6.2A.2 UE maximum output power reduction for CA

##### 6.2A.2.1 UE maximum output power reduction for inter-band NR CA between FR 1 and FR 2 without EN-DC

###### 6.2A.2.1.1 Test purpose

Same test purpose as in 6.2.2 in TS 38.521-1 [8] for NR FR1 carrier(s) and 6.2.2 in TS 38.521-2 [9] for NR FR2 carrier(s).

###### 6.2A.2.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for additional spectrum emissions mask apply and are tested in TS 38.521-1 [8] clause 6.2 and 6.2A and TS 38.521-2 [9] clause 6.2 and 6.2A

### 6.2A.3 UE additional maximum output power reduction for CA

#### 6.2A.3.1 UE additional maximum output power reduction for inter-band NR CA between FR 1 and FR 2 without EN-DC

##### 6.2A.3.1.1 Test purpose

Same test purpose as in 6.2.3.1 in TS 38.521-1 [8] for NR FR1 carrier and 6.2.3.1 in TS 38.521-2 [9] for NR FR2 carrier.

##### 6.2A.3.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 and E-UTRA in conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The single carrier requirements for Additional Maximum Output Power apply and are tested as part of 6.2.3 in TS 38.521-1 [8] for NR FR1 carrier and 6.2.3 in TS 38.521-2 [9] for NR FR2 carrier.

### 6.2A.4 Configured output power level for CA

#### 6.2A.4.1 Configured output power level for inter-band NR CA between FR 1 and FR 2 without EN-DC

##### 6.2A.4.1.1 Test purpose

Same test purpose as in clause 6.2.4 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.2.4 in TS 38.521-2 [9] for NR FR2 carrier(s).

##### 6.2A.4.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for configured output power level apply and are tested in TS 38.521-1 [8] clauses 6.2 and 6.2A and TS 38.521-2 [9] clauses 6.2 and 6.2A.

#### 6.2A.4.2 $\Delta T_{IB,c}$ for CA

##### 6.2A.4.2.1 $\Delta T_{IB,c}$ for inter-band CA between FR 1 and FR 2

$\Delta T_{IB,c}$  for NR CA For the UE which supports inter-band NR CA configuration,  $\Delta T_{IB,c}$  in Tables below applies. Unless otherwise stated,  $\Delta T_{IB,c}$  is set to zero.

## 6.2B Transmitter power for EN-DC

### 6.2B.1 UE Maximum Output Power for EN-DC

FFS

## 6.2B.1.1 UE Maximum Output Power for Intra-Band Contiguous EN-DC

**Editor's note: The test case is incomplete, the following aspects are either missing or not yet determined:- Test applicability for DC\_(n)71AA and DC\_(n)41AA is TBD**

**- Recommendation on specific time difference between MCG and SCG is TBD**

### 6.2B.1.1.1 Test purpose

To verify that the error of the UE maximum output power does not exceed the range prescribed by the specified nominal maximum output power and tolerance.

An excess maximum output power has the possibility to interfere to other channels or other systems. A small maximum output power decreases the coverage area.

### 6.2B.1.1.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC operation on FR1.

### 6.2B.1.1.3 Minimum conformance requirements

The following UE Power Classes define the total maximum output power for any transmission bandwidth(s) of the CG(s) configured.

The maximum output power is measured as the total maximum output power across the UE antenna connector(s). The period of measurement shall be at least one sub frame.

**Table 6.2B.1.1.3-1: Maximum output power for EN-DC (continuous sub-blocks)**

DC configuration	Power class 2 (dBm)	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_(n)71AA			23	+2/-3
DC_(n)41AA	26	+2/-2 <sup>1</sup>	23	+2/-2 <sup>1</sup>
NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL_low and FUL_low + 4 MHz or/and FUL_high – 4 MHz and FUL_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB				
NOTE 2: Power Class 3 is the default power class unless otherwise stated.				

If UE supports a different power class than the default UE power class for EN-DC band combination, and the supported power class enables higher maximum output power than that of the default power class:

- if the LTE UL/DL configuration is 0 or 6; or
- if the LTE UL/DL configuration is 1 and special subframe configuration is 0 or 5; or
- if the IE *p-maxUE-FRI* as defined in TS 38.331 [7] is provided and set to the maximum output power of the default power class or lower;
  - apply all requirements for the default power class, and set the configured transmitted power as specified in sub-clause 6.2B.4;
- else
  - apply all requirements for the supported power class, and set the configured transmitted power class as specified in sub-clause 6.2B.4;

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.

LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.



6.2B.1.1.4 Test description

6.2B.1.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2, and are shown in table 6.2B.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2 for E-UTRA RMC for TDD, TS 36.521-1 [10] Annex A.2 for E-UTRA RMC for FDD, and TS 38.521-1 [8] Annex A.2 for NR RMC. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.1.1.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC, TL/VL, TL/VH, TH/VL, TH/VH			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, Mid range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE		Lowest, Mid, Highest			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest ,Highest			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation	Modulation( NOTE 2)	RB allocation(N OTE 1)
1	N/A for MOP testing.	NOTE 3		DFT-s-OFDM PI/2 BPSK	Inner Full
2				DFT-s-OFDM PI/2 BPSK	Inner 1RB Left
3				DFT-s-OFDM PI/2 BPSK	Inner 1RB Right
4				DFT-s-OFDM QPSK	Inner Full
5				DFT-s-OFDM QPSK	Inner 1RB Left
6				DFT-s-OFDM QPSK	Inner 1RB Right
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1. NOTE 2: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1. NOTE 3: Modulation and RB allocation for E-UTRA Cell is selected from Table 6.2.2.4.1-1 in TS 36.521-1[10] as per the test channel bandwidth of E-UTRA cell. NOTE 4: Unless otherwise stated, for a specific intra-band contiguous EN-DC comb, if a UE indicates support of dynamicPowerSharing in the UE-MRDC-Capability IE and Single UL allowed is "NO" according to Clause 5.2B.2, run test points with E-UTRA UL transmission overlapping NR UL transmission in time; otherwise, run test points with E-UTRA UL transmission not overlapping with NR UL transmission in time.					

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.
7. Ensure E-UTRA UL transmission overlaps with NR UL transmission in time by restricting timing difference between MCG and SCG to be [TBD], or E-UTRA UL transmission doesn't overlap with NR UL transmission in time by restricting timing difference between MCG and SCG to be [TBD].

#### 6.2B.1.1.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 6.2B.1.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command for the UE to reach  $P_{UMAX}$  level for Power Class 3.
3. Measure the mean transmitted power over all EN-DC component carriers in the EN-DC, which shall meet the requirements described in table 6.2B.1.1.5-1 the period of the measurement shall be at least the continuous duration of one active sub-frame.
4. For UEs supporting Power Class 2, repeat steps 1~3 on the applicable bands except  $P_{UMAX}$  level in step 2 is corresponding to Power Class 2.

#### 6.2B.1.1.4.3 Message contents

Message contents are according to TS 36.508-1[11] subclause 4.6.1 and TS 36.508 [11] subclause 4.6.1 and TS 38.508-1 [6] subclause 4.6.1 with the following exceptions.

##### 6.2B.1.1.4.3-1: PhysicalCellGroupConfig

Derivation Path: TS 38.508-1 [6], Table 4.6.3-106			
Information Element	Value/remark	Comment	Condition
p-NR-FR1	23	Apply if Power Class 3 UE	

**6.2B.1.1.4.3-2: RRCConnectionReconfiguration: nr-Config-r15**

Derivation Path: TS 36.508 [11], Table 4.6.1-8			
Information Element	Value/remark	Comment	Condition
p-MaxEUTRA-r15	23	Apply if run test points with E-UTRA UL transmission not overlapping with NR UL transmission in time for PC3 UE	
	20	Apply if run test points with E-UTRA UL transmission overlapping with NR UL transmission in time for PC3 UE	

**6.2B.1.1.4.3-3: RRCConnectionReconfiguration: tdm-PatternConfig if operating on FDD band**

Derivation Path: TS 36.508 [11], Table 4.6.1-8			
Information Element	Value/remark	Comment	Condition
setup ::= SEQUENCE {		Apply if operating on FDD band for a UE indicating support of dynamicPowerSharing in the <i>UE-MRDC-Capability</i> IE according to TS 38.213 [x] clause 7.6.1	
subframeAssignment-r15	sa2		
harq-Offset-r15	0		
}			

**6.2B.1.1.4.3-4: SystemInformationBlockType1: tdd-Config if operating on TDD band**

Derivation Path: TS 36.508 [11], Table 4.6.3-23			
Information Element	Value/remark	Comment	Condition
TDD-Config-DEFAULT ::= SEQUENCE {		Operating on TDD band	
subframeAssignment	sa2		
specialSubframePatterns	ssp6		
}			

6.2B.1.1.5 Test requirements

The maximum output power for the DC configuration, derived in step 3 shall be within the range prescribed by the DC UE Power Class and tolerance in Table 6.2B.1.1.5-1.

**Table 6.2B.1.1.5-1: Maximum output power for EN-DC (continuous sub-blocks) for power class 3**

DC configuration	Power class2	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_(n)71B			23	+2+TT/-3-TT
DC_(n)41AA			23	+2+TT/-2 <sup>1</sup> +TT
NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL_low and FUL_low + 4 MHz or/and FUL_high – 4 MHz and FUL_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB				
NOTE 2: TT for each frequency and channel bandwidth is specified in TBD				

**Table 6.2B.1.1.5-2: Maximum output power for EN-DC (continuous sub-blocks) for Power Class 2**

DC configuration	Power class2	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_(n)41AA	26	+2+TT/-2 <sup>1</sup> -TT		
NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL_low and FUL_low + 4 MHz or/and FUL_high – 4 MHz and FUL_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB				
NOTE 2: TT for each frequency and channel bandwidth is specified in Table 6.2B.1.5-3				

**Table 6.2B.1.5-3: Test Tolerance**

	f ≤ 3.0GHz	3.0GHz < f ≤ 6GHz
BW ≤ 40MHz	0.7 dB	1.0 dB
40MHz < BW ≤ 100MHz	1.0 dB	1.0 dB

### 6.2B.1.2 UE Maximum Output Power for Intra-Band Non-Contiguous EN-DC

Editor's note: The test case is incomplete, the following aspects are either missing or not yet determined:

- Test applicability for DC\_41A\_n41A is TBD
- Recommendation on specific time difference between MCG and SCG is TBD

#### 6.2B.1.2.1 Test purpose

To verify that the error of the UE maximum output power does not exceed the range prescribed by the specified nominal maximum output power and tolerance.

An excess maximum output power has the possibility to interfere to other channels or other systems. A small maximum output power decreases the coverage area.

#### 6.2B.1.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non contiguous EN-DC operation on FR1.

NOTE: For the test for DC\_41A\_(n)41A, it is applicable to UE which supports dynamic power sharing.

#### 6.2B.1.2.3 Minimum conformance requirements

The following UE Power Classes define the total maximum output power for any transmission bandwidth(s) of the CG(s) configured.

The maximum output power is measured as the total maximum output power across the UE antenna connector(s). The period of measurement shall be at least one sub frame.

**Table 6.2B.1.2.3-1: Maximum output power for EN-DC (non-continuous sub-blocks)**

DC configuration	Power class 2 (dBm)	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_3A_n3A <sup>(2)</sup>			23	+2/-3
DC_41A_n41A	26	+2/-2 <sup>1</sup>	23	+2/-2 <sup>1</sup>
NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL_low and FUL_low + 4 MHz or/and FUL_high – 4 MHz and FUL_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB				
NOTE 2: Only single switched UL is supported in Rel.15				
NOTE 3: Power Class 3 is the default power class unless otherwise stated.				

If UE supports a different power class than the default UE power class for EN-DC band combination, and the supported power class enables higher maximum output power than that of the default power class:

- if the LTE UL/DL configuration is 0 or 6; or
- if the LTE UL/DL configuration is 1 and special subframe configuration is 0 or 5; or
- if the IE *p-maxUE-FRI* as defined in TS 38.331 [7] is provided and set to the maximum output power of the default power class or lower;
  - apply all requirements for the default power class, and set the configured transmitted power as specified in sub-clause 6.2B.4;
- else
- apply all requirements for the supported power class, and set the configured transmitted power class as specified in sub-clause 6.2B.4;

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.

LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.2B.1.2.4 Test description

##### 6.2B.1.2.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in Table 5.3B.1.3-1, channel bandwidths and sub-carrier spacings for the NR cell are specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in Table 5.3B.1.3-1, and are shown in table 6.2B.1.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2 for E-UTRA RMC for TDD, TS 36.521-1 [10] Annex A.2 for E-UTRA RMC for FDD, and TS 38.521-1 [8] Annex A.2 for NR RMC Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.1.2.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC, TL/VL, TL/VH, TH/VL, TH/VH			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		minWgap , MaxWgap			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE		Lowest, Mid, Highest			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest, Highest			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation	Modulation( NOTE 2)	RB allocation(N OTE 1)
1	N/A for MOP testing.	NOTE 3		DFT-s-OFDM PI/2 BPSK	Inner Full
2				DFT-s-OFDM PI/2 BPSK	Inner 1RB Left
3				DFT-s-OFDM PI/2 BPSK	Inner 1RB Right
4				DFT-s-OFDM QPSK	Inner Full
5				DFT-s-OFDM QPSK	Inner 1RB Left
6				DFT-s-OFDM QPSK	Inner 1RB Right
<p>NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1.</p> <p>NOTE 2: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1.</p> <p>NOTE 3: Modulation and RB allocation for E-UTRA Cell is selected from Table 6.2.2.4.1-1 in TS 36.521-1[10] as per the test channel bandwidth of E-UTRA cell.</p> <p>NOTE 4: Unless otherwise stated, for a specific intra band non-contiguous EN-DC comb, if a UE indicates support of dynamicPowerSharing in the UE-MRDC-Capability IE and Single UL allowed is "NO" according to Clause 5.2B.3, run test points with E-UTRA UL transmission overlapping NR UL transmission in time; otherwise, run test points with E-UTRA UL transmission not overlapping with NR UL transmission in time.</p>					

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] A.3.1.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.2.4.3.
7. Ensure E-UTRA UL transmission overlaps with NR UL transmission in time by restricting timing difference between MCG and SCG to be [TBD], or E-UTRA UL transmission doesn't overlap with NR UL transmission in time by restricting timing difference between MCG and SCG to be [TBD].

#### 6.2B.1.2.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 6.2B.1.2.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier according to table 6.2B.1.2.4.1-1 until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command for the UE to reach  $P_{UMAX}$  level for Power class 2.
3. Measure the mean transmitted power over all EN-DC component carriers in the EN-DC, which shall meet the requirements described in table 6.2B.1.2.5-1 the period of the measurement shall be at least the continuous duration of one active sub-frame.
4. For UEs supporting Power Class 2, repeat steps 1~3 on the applicable bands except  $P_{UMAX}$  level in step 2 is corresponding to Power Class 2.

#### 6.2B.1.2.4.3 Message contents

Same message contents as specified in 6.2B.1.1.4.3.

#### 6.2B.1.2.5 Test requirements

The maximum output power for the DC configuration, derived in step 3 shall be within the range prescribed by the DC UE Power Class and tolerance in Table 6.2B.1.2.5-1.

**Table 6.2B.1.2.5-1: Maximum output power for EN-DC (non-continuous sub-blocks) for power class 3**

DC configuration	Power class 2 (dBm)	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_3A_n3A <sup>(2)</sup>			23	+2+TT/-3-TT
DC_41A_n41A			23	+2/-2 <sup>1</sup>

NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL\_low and FUL\_low + 4 MHz or/and FUL\_high – 4 MHz and FUL\_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB

NOTE 2: Only single switched UL is supported in Rel.15

NOTE 3: TT for frequency and channel bandwidth is Table 6.2B.1.2.5-3

**Table 6.2B.1.2.5-2: Maximum output power for EN-DC (non-continuous sub-blocks) for power class 2**

DC configuration	Power class 2 (dBm)	Tolerance (dB)	Power class 3 (dBm)	Tolerance (dB)
DC_41A_n41A	26	+2+TT/-2 <sup>1</sup> -TT		

NOTE 1: If all transmitted resource blocks over all component carriers are confined within FUL\_low and FUL\_low + 4 MHz or/and FUL\_high – 4 MHz and FUL\_high, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB

NOTE 2: TT for frequency and channel bandwidth is Table 6.2B.1.2.5-3

Table 6.2B.1.2.5-3: Test Tolerance

	$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 40\text{MHz}$	0.7 dB	1.0 dB
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	1.0 dB	1.0 dB

### 6.2B.1.3 UE Maximum Output Power for Inter-Band EN-DC within FR1

#### 6.2B.1.3.1 Test purpose

To verify that the error of the UE maximum output power does not exceed the range prescribed by the specified nominal maximum output power and tolerance.

An excess maximum output power has the possibility to interfere to other channels or other systems. A small maximum output power decreases the coverage area.

#### 6.2B.1.3.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC operating on FR1.

#### 6.2B.1.3.3 Minimum conformance requirements

For inter-band EN-DC of LTE and NR in FR1, the following UE Power Classes define the maximum output power for any transmission bandwidth within the aggregated channel bandwidth. The maximum output power is measured as the sum of the maximum output power at each UE antenna connector. The period of measurement shall be at least one sub frame (1ms). UE maximum output power shall be measured over all component carriers from different bands. If each band has separate antenna connectors, maximum output power is measured as the sum of maximum output power at each UE antenna connector.



**Table 6.2B.1.3.3-1: Maximum output power for inter-band EN-DC (two bands)**

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_1A_n28A	23	+2/-3
DC_1A_n40A	23	+2/-3
DC_1A_n51A	23	+2/-3
DC_1A_n77A	23	+2/-3
DC_1A_n78A DC_1A_n84A_ULSUP- TDM_n78A DC_1A_n84A_ULSUP- FDM_n78A	23	+2/-3
DC_1A_n79A	23	+2/-3
DC_2A_n5A	23	+2/-3 <sup>1</sup>
DC_2A_n66A	23	+2/-3 <sup>1</sup>
DC_2A_n71A	23	+2/-3
DC_2A_n78A	23	+2/-3
DC_3A_n7A	23	+2/-3 <sup>1</sup>
DC_3A_n28A	23	+2/-3 <sup>1</sup>
DC_3A_n40A	23	+2/-3 <sup>1</sup>
DC_3A_n51A	23	+2/-3 <sup>1</sup>
DC_3A_n77A	23	+2/-3 <sup>1</sup>
DC_3A_n78A DC_3A_n80A_ULSUP- TDM_n78A, DC_3A_n80A_ULSUP- FDM_n78A	23	+2/-3 <sup>1</sup>
DC_3A_n79A DC_3A_n80A_ULSUP- TDM_n79A, DC_3A_n80A_ULSUP- FDM_n79A	23	+2/-3 <sup>1</sup>
DC_3A_n82A	23	+2/-3 <sup>1</sup>
DC_5A_n40A	23	+2/-3 <sup>1</sup>
DC_5A_n66A	23	+2/-3 <sup>1</sup>
DC_5A_n78A	23	+2/-3
DC_7A_n28A	23	+2/-3 <sup>1</sup>
DC_7A_n51A	23	+2/-3 <sup>1</sup>
DC_7A_n78A DC_7C_n78A	23	+2/-3
DC_8A_n40A	23	+2/-3 <sup>1</sup>
DC_8A_n77A	23	+2/-3
DC_8A_n78A DC_8A_n81A_ULSUP- TDM_n78A, DC_8A_n81A_ULSUP- FDM_n78A	23	+2/-3
DC_8A_n79A DC_8A_n81A_ULSUP- TDM_n79A, DC_8A_n81A_ULSUP- FDM_n79A	23	+2/-3
DC_11A_n77A	23	+2/-3
DC_11A_n78A	23	+2/-3
DC_11A_n79A	23	+2/-3
DC_12A_n5A	23	+2/-3
DC_12A_n66A	23	+2/-3

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_18A_n77A	23	+2/-3
DC_18A_n78A	23	+2/-3
DC_18A_n79A	23	+2/-3
DC_19A_n77A	23	+2/-3
DC_19A_n78A	23	+2/-3
DC_19A_n79A	23	+2/-3
DC_20A_n8A	23	+2/-3
DC_20A_n28A DC_20A_n83A	23	+2/-3
DC_20A_n51A	23	+2/-3
DC_20A_n77A	23	+2/-3
DC_20A_n78A DC_20A_n82A_ULSUP -TDM_n78A, DC_20A_n82A_ULSUP -FDM_n78A	23	+2/-3
DC_21A_n77A	23	+2/-3
DC_21A_n78A	23	+2/-3
DC_21A_n79A	23	+2/-3
DC_25A_n41A	23	+2/-3
DC_26A_n41A	23	+2/-3
DC_26A_n77A	23	+2/-3
DC_26A_n78A	23	+2/-3
DC_26A_n79A	23	+2/-3
DC_28A_n51A	23	+2/-3
DC_28A_n77A	23	+2/-3
DC_28A_n78A DC_28A_n83A_ULSUP -TDM_n78A, DC_28A_n83A_ULSUP -FDM_n78A	23	+2/-3
DC_28A_n79A	23	+2/-3
DC_30A_n5A	23	+2/-3
DC_30A_n66A	23	+2/-3
DC_38A_n78A	N/A	N/A
DC_39A_n78A	23	+2/-3 <sup>1</sup>
DC_39A_n79A	23	+2/-3 <sup>1</sup>
DC_40A_n77A	N/A	N/A
DC_41A_n77A DC_41C_n77A	23	+2/-3 <sup>1</sup>
DC_41A_n78A DC_41C_n78A	23	+2/-3 <sup>1</sup>
DC_41A_n79A DC_41C_n79A	23	+2/-3 <sup>1</sup>
DC_42A_n51A	23	+2/-3
DC_42A_n77A	N/A	N/A
DC_42A_n78A	N/A	N/A
DC_42A_n79A	N/A	N/A
DC_66A_n5A	23	+2/-3 <sup>1</sup>
DC_66A_n71A	23	+2/-3

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_66A_n78A, DC_66A_n86A_ULSUP -TDM_n78A,  DC_66A_n86A_ULSUP -FDM_n78A	23	+2/-3
<p>NOTE 1: <sup>2</sup> refers to the transmission bandwidths confined within <math>F_{UL\_low}</math> and <math>F_{UL\_low} + 4</math> MHz or <math>F_{UL\_high} - 4</math> MHz and <math>F_{UL\_high}</math>, the maximum output power requirement is relaxed by reducing the lower tolerance limit by 1.5 dB</p> <p>NOTE 2: <math>P_{PowerClass\_EN-DC}</math> is the maximum UE power specified without taking into account the tolerance</p> <p>NOTE 3: For inter-band EN-DC the maximum power requirement should apply to the total transmitted power over all component carriers (per UE).</p>		

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.

LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.2B.1.3.4 Test description

##### 6.2B.1.3.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies, DC configuration specified in clause 5.5B.4 and test channel bandwidths specified in TS 36.508 [6] subclause 4.3.1 and TS 38.508-1 clause 4.3.1, and sub-carrier spacing based on NR operating bands specified in TS 38.521-1 [8] clause 5.3 .All of these configurations shall be tested with applicable test parameters for each EN-DC configuration, and are shown in table 6.2B.1.3.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexe A.2 for E-UTRA RMC for TDD, TS 36.521-1 [10] Annex A.2 for E-UTRA RMC for FDD , and TS 38.521-1 [8] Annex A.2 for NR RMC. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.1.3.4.1-1: Test configuration table**

Default Conditions								
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					NC, TL/ML, TL/VH, TH/VL, TH/VH			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1 and TS 36.508 [6]					Low for E-UTRA CC1 and NR CC1, Mid for E-UTRA CC1 and NR CC1, High for E-UTRA CC1 and NR CC1			
Test EN_DC channel bandwidth as specified in TS 36.508 [6] subclause 4.3.1 and TS 38.508-1 clause 4.3.1					5MHz for E-UTRA CC1 and Lowest for NR CC1, Highest for E-UTRA CC1 and Highest for NR CC1			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1					Lowest, Highest			
Test Parameters								
Test ID	Test Freq	E-UTRA BW	NR BW	Downlink Configuration	EN-DC Uplink Configuration			
					E-UTRA Cell		NR Cell	
					Modulation	RB allocation (Note 2)	Modulation	RB allocation (Note 3)
1	High	5	Default	N/A N/A	QPSK	Outer_1R B_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Right
2	Low	5	Default		QPSK	Outer_1R B_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Left
3	Default	5	Default		QPSK	8	DFT-s-OFDM PI/2 BPSK	Inner_Full
4	High	5	Default		QPSK	Outer_1R B_Right	DFT-s-OFDM QPSK	Edge_1RB _Right
5	Low	5	Default		QPSK	Outer_1R B_Left	DFT-s-OFDM QPSK	Edge_1RB _Left
6	Default	5	Default		QPSK	8	DFT-s-OFDM QPSK	Inner_Full
7	High	10	Default		QPSK	Outer_1R B_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Right
8	Low	10	Default		QPSK	Outer_1R B_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Left
9	Default	10	Default		QPSK	12	DFT-s-OFDM PI/2 BPSK	Inner_Full
10	High	10	Default		QPSK	Outer_1R B_Right	DFT-s-OFDM QPSK	Edge_1RB _Right
11	Low	10	Default		QPSK	Outer_1R B_Left	DFT-s-OFDM QPSK	Edge_1RB _Left
12	Default	10	Default		QPSK	12	DFT-s-OFDM QPSK	Inner_Full
13	High	15	Default		QPSK	Outer_1R B_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Right
14	Low	15	Default		QPSK	Outer_1R B_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB _Left
15	Default	15	Default		QPSK	16	DFT-s-OFDM PI/2 BPSK	Inner_Full
16	High	15	Default		QPSK	Outer_1R B_Right	DFT-s-OFDM QPSK	Edge_1RB _Right

17	Low	15	Default		QPSK	Outer_1R B_Left	DFT-s- OFDM QPSK	Edge_1RB _Left
18	Default	15	Default		QPSK	16	DFT-s- OFDM QPSK	Inner_Full
19	High	20	Default		QPSK	Outer_1R B_Right	DFT-s- OFDM PI/2 BPSK	Edge_1RB_ Right
20	Low	20	Default		QPSK	Outer_1R B_Left	DFT-s- OFDM PI/2 BPSK	Edge_1RB_ Left
21	Default	20	Default		QPSK	18	DFT-s- OFDM PI/2 BPSK	Inner_Full
22	High	20	Default		QPSK	Outer_1R B_Right	DFT-s- OFDM QPSK	Edge_1RB_ Right
23	Low	20	Default		QPSK	Outer_1R B_Left	DFT-s- OFDM QPSK	Edge_1RB_ Left
24	Default	20	Default		QPSK	18	DFT-s- OFDM QPSK	Inner_Full
<p>NOTE 1: For non-1RB allocation on E-UTRA bands, the RBstart shall be RB #0 for low and mid range, and RB# (max +1 - RB allocation) for high range test frequency.</p> <p>NOTE 2: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].</p> <p>NOTE 3: Outer_1RB_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer_1RB_Right defined as 1 RB allocated at the right edge of the E-UTRA component.</p> <p>NOTE 4: Unless otherwise stated, for a specific inter-band EN-DC comb, if a UE indicates support of dynamicPowerSharing in the <i>UE-MRDC-Capability</i> IE and Single UL allowed is "NO" according to Clause 5.2B.4, run test points with E-UTRA UL transmission overlapping NR UL transmission in time; otherwise, run test points with E-UTRA UL transmission not overlapping with NR UL transmission in time.</p>								

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.1 for SS and A.3.2.1 for UE.
2. The parameter settings for the cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.3.4.3.
7. For the case of testing overlapping E-UTRA and NR UL transmission scenario when both bands are TDD, ensure E-UTRA UL transmission overlaps with NR UL transmission in time by giving SCG a delay of 3 E-UTRA subframes, or by giving MCG a delay of 2 subframes.

#### 6.2B.1.3.3.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 6.2B.1.3.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.

2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms for the UE to reach  $P_{UMAX}$  level.
3. Measure the mean transmitted power over all EN-DC component carriers in the EN-DC, which shall meet the requirements described in table 6.2B.1.3.5-1 the period of the measurement shall be at least the continuous duration of one active sub-frame.

#### 6.2B.1.3.4.3 Message contents

Message contents are according to TS 36.508-1[11] subclause 4.6.1 and TS 38.508-1 [6] subclause 4.6.1 with the following exceptions.

##### 6.2B.1.3.4.3-1: PhysicalCellGroupConfig

Derivation Path: TS 38.508-1 [6], Table 4.6.3-106			
Information Element	Value/remark	Comment	Condition
PhysicalCellGroupConfig ::= SEQUENCE {			
p-NR-FR1	23	Apply if Power Class 3 UE	
}			

##### 6.2B.1.3.4.3-2: RRCConnectionReconfiguration: nr-Config-r15

Derivation Path: TS 36.508 [11], Table 4.6.1-8			
Information Element	Value/remark	Comment	Condition
p-MaxEUTRA-r15	23	Apply if run test points with E-UTRA UL transmission not overlapping with NR UL transmission in time for PC3 UE	
	20	Apply if run test points with E-UTRA UL transmission overlapping with NR UL transmission in time for PC3 UE	

##### 6.2B.1.3.4.3-3: RRCConnectionReconfiguration: tdm-PatternConfig if E-UTRA on FDD band

Derivation Path: TS 36.508 [11], Table 4.6.1-8			
Information Element	Value/remark	Comment	Condition
setup ::= SEQUENCE {		Apply if operating on FDD band for a UE indicating support of dynamicPowerSharing in the <i>UE-MRDC-Capability</i> IE according to TS 38.213 [x] clause 7.6.1	
subframeAssignment-r15	sa2		
harq-Offset-r15	0		
}			

##### 6.2B.1.3.4.3-4: SystemInformationBlockType1: tdd-Config if E-UTRA on TDD band

Derivation Path: TS 36.508 [11], Table 4.6.3-23			
Information Element	Value/remark	Comment	Condition
TDD-Config-DEFAULT ::= SEQUENCE {		Operating on TDD band	
subframeAssignment	Sa2		
specialSubframePatterns	Ssp6		
}			



### 6.2B.1.3.5 Test requirements

The maximum output power for the DC configuration, derived in step 3 shall be within the range prescribed by the UE Power Class and tolerance in Table 6.2B.1.3.5-1.

**Table 6.2B.1.3.5-1: Maximum output power for inter-band EN-DC (two bands)**

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_1A_n28A	23	+2 +TT/-3-TT
DC_1A_n40A	23	+2 +TT/-3-TT
DC_1A_n51A	23	+2 +TT/-3-TT
DC_1A_n77A	23	+2 +TT/-3-TT
DC_1A_n78A DC_1A_n84A_ULSUP- TDM_n78A DC_1A_n84A_ULSUP- FDM_n78A	23	+2 +TT/-3-TT
DC_1A_n79A	23	+2 +TT/-3-TT
DC_2A_n5A	23	+2 +TT/-3-TT
DC_2A_n66A	23	+2 +TT/-3-TT
DC_2A_n71A	23	+2 +TT/-3-TT
DC_2A_n78A	23	+2 +TT/-3-TT
DC_3A_n7A	23	+2 +TT/-3-TT
DC_3A_n28A	23	+2 +TT/-3-TT
DC_3A_n40A	23	+2 +TT/-3-TT
DC_3A_n51A	23	+2 +TT/-3-TT
DC_3A_n77A	23	+2 +TT/-3-TT
DC_3A_n78A DC_3A_n80A_ULSUP- TDM_n78A, DC_3A_n80A_ULSUP- FDM_n78A	23	+2 +TT/-3-TT
DC_3A_n79A DC_3A_n80A_ULSUP- TDM_n79A, DC_3A_n80A_ULSUP- FDM_n79A	23	+2 +TT/-3-TT
DC_3A_n82A	23	+2 +TT/-3-TT
DC_5A_n40A	23	+2 +TT/-3-TT
DC_5A_n66A	23	+2 +TT/-3-TT
DC_5A_n78A	23	+2 +TT/-3-TT
DC_7A_n28A	23	+2 +TT/-3-TT
DC_7A_n51A	23	+2 +TT/-3-TT
DC_7A_n78A	23	+2 +TT/-3-TT
DC_8A_n40A	23	+2 +TT/-3-TT
DC_8A_n77A	23	+2 +TT/-3-TT
DC_8A_n78A DC_8A_n81A_ULSUP- TDM_n78A, DC_8A_n81A_ULSUP- FDM_n78A	23	+2 +TT/-3-TT
DC_8A_n79A DC_8A_n81A_ULSUP- TDM_n79A, DC_8A_n81A_ULSUP- FDM_n79A	23	+2 +TT/-3-TT
DC_11A_n77A	23	+2 +TT/-3-TT
DC_11A_n78A	23	+2 +TT/-3-TT
DC_11A_n79A	23	+2 +TT/-3-TT
DC_12A_n5A	23	+2 +TT/-3-TT
DC_12A_n66A	23	+2 +TT/-3-TT

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_18A_n77A	23	+2 +TT/-3-TT
DC_18A_n78A	23	+2 +TT/-3-TT
DC_18A_n79A	23	+2 +TT/-3-TT
DC_19A_n77A	23	+2 +TT/-3-TT
DC_19A_n78A	23	+2 +TT/-3-TT
DC_19A_n79A	23	+2 +TT/-3-TT
DC_20A_n8A	23	+2 +TT/-3-TT
DC_20A_n28A DC_20A_n83A	23	+2 +TT/-3-TT
DC_20A_n51A	23	+2 +TT/-3-TT
DC_20A_n77A	23	+2 +TT/-3-TT
DC_20A_n78A DC_20A_n82A_ULSUP -TDM_n78A, DC_20A_n82A_ULSUP -FDM_n78A	23	+2 +TT/-3-TT
DC_21A_n77A	23	+2 +TT/-3-TT
DC_21A_n78A	23	+2 +TT/-3-TT
DC_21A_n79A	23	+2 +TT/-3-TT
DC_25A_n41A	23	+2 +TT/-3-TT
DC_26A_n41A	23	+2 +TT/-3-TT
DC_26A_n77A	23	+2 +TT/-3-TT
DC_26A_n78A	23	+2 +TT/-3-TT
DC_26A_n79A	23	+2 +TT/-3-TT
DC_28A_n51A	23	+2 +TT/-3-TT
DC_28A_n77A	23	+2 +TT/-3-TT
DC_28A_n78A DC_28A_n83A_ULSUP -TDM_n78A, DC_28A_n83A_ULSUP -FDM_n78A	23	+2 +TT/-3-TT
DC_28A_n79A	23	+2 +TT/-3-TT
DC_30A_n5A	23	+2 +TT/-3-TT
DC_30A_n66A	23	+2 +TT/-3-TT
DC_38A_n78A	N/A	N/A
DC_39A_n78A	23	+2 +TT/-3-TT
DC_39A_n79A	23	+2 +TT/-3-TT
DC_40A_n77A	N/A	N/A
DC_41A_n77A	23	+2 +TT/-3-TT
DC_41A_n78A	23	+2 +TT/-3-TT
DC_41A_n79A	23	+2 +TT/-3-TT
DC_42A_n51A	23	+2 +TT/-3-TT
DC_42A_n77A	N/A	N/A
DC_42A_n78A	N/A	N/A
DC_42A_n79A	N/A	N/A
DC_66A_n5A	23	+2 +TT/-3-TT
DC_66A_n71A	23	+2 +TT/-3-TT

EN-DC configuration	Power class 3 (dBm)	Tolerance (dB)
DC_66A_n78A, DC_66A_n86A_ULSUP -TDM_n78A, DC_66A_n86A_ULSUP -FDM_n78A	23	+2 +TT/-3-TT
<p>NOTE 1: TT applies to output power in each UL carrier with E-UTRA UL transmission not overlapping with NR UL transmission in time, and its value is the same as TT of standalone E-UTRA or NR transmission. For detailed values refer to Table 6.2B.1.3.5-2.</p> <p>NOTE 2: TT applies to overall output power with E-UTRA UL transmission overlapping with NR UL transmission in time, and its value is the maximum TT among all E-UTRA and NR UL carriers. For detailed values refer to Table 6.2B.1.3.5-3.</p>		

Table 6.2B.1.3.5-2: Test Tolerance for UE maximum output power (Non-overlapping UL transmission)

Uplink TX		f ≤ 3.0GHz	3.0GHz < f ≤ 4.2GHz	4.2GHz < f ≤ 6GHz
E-UTRA	BW ≤ 20MHz	0.7	1.0	1.3
NR	BW ≤ 40MHz	0.7 dB	1.0 dB	1.0
	40MHz < BW ≤ 100MHz	1.0 dB	1.0 dB	1.0

Table 6.2B.1.3.5-3: Test Tolerance for UE maximum output power (Overlapping UL transmission)

TT for overall output power											
			NR								
			BW ≤ 20MHz			20 MHz < BW ≤ 40MHz			40MHz < BW ≤ 100MHz		
			f ≤ 3.0GHz	3.0GHz < f ≤ 4.2GHz	4.2GHz < f ≤ 6.0GHz	f ≤ 3.0GHz	3.0GHz < f ≤ 4.2GHz	4.2GHz < f ≤ 6.0GHz	f ≤ 3.0GHz	3.0GHz < f ≤ 4.2GHz	4.2GHz < f ≤ 6.0GHz
E-UTRA	BW ≤ 20MHz	f ≤ 3.0GHz	0,7	1,0	1,0	0,7	1,0	1,0	1,0	1,0	1,0
		3.0GHz < f ≤ 4.2GHz	1,0	1,0	1,0	1,0	1,0	1,0	1,0	1,0	1,0

6.2B.1.4 UE Maximum Output Power for Inter-Band EN-DC including FR2

6.2B.1.4.1 UE maximum output power - EIRP and TRP

Editor’s note: The following aspects are either missing or not yet determined:

- The referred test case 6.2.1.1 in TS 38.521-2 is incomplete for power class 1, 2 and 4.
- The following aspects of the clause are for future consideration:
  - Test Procedures for EIRP beam peak Extreme Conditions are FFS

6.2B.1.4.1.1 Test purpose

Same test purpose as in clause 6.2.1.1.1 in TS 38.521-2 [9] for the NR carrier.

6.2B.1.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.2B.1.4.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.1.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 subclause 6.2B.1.4.

#### 6.2B.1.4.1.4 Test description

Same test description as in clause 6.2.1.1.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For initial conditions as in clause 6.2.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.2.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.2.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.1.4.1.5 Test requirement

Same test requirement as in clause 6.2.1.1.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.2B.1.4.2 UE maximum output power - Spherical coverage

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- All clauses related to Power class 3 can be tested using working assumptions of MU/TT
- The referred test case 6.2.1.2 in TS 38.521-2 is incomplete.
- Measurement Uncertainties and Test Tolerances are FFS for power class 1, 2 and 4.

#### 6.2B.1.4.2.1 Test purpose

Same test purpose as in clause 6.2.1.2.1 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.2B.1.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.2B.1.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.1.2.3 in TS 38.521-2 [9] for the *NR* carrier.

The normative reference for this requirement is TS 38.101-3 subclause 6.2B.1.4.

#### 6.2B.1.4.2.4 Test description

Same test description as in clause 6.2.1.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For initial conditions as in clause 6.2.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of initial conditions as in clause 6.2.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.2.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.1.4.2.5 Test requirement

Same test requirement as in clause 6.2.1.2.5 in TS 38.521-2 [9] for the *NR* carrier.

[IS: 5446 NTT created a duplication!!]

#### 6.2B.1.4.2 UE maximum output power for Inter-band EN-DC including FR2 (3 CCs)

##### 6.2B.1.4.2.1 UE maximum output power - EIRP and TRP

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.2A.1.1.1 in TS 38.521-2 is incomplete.

##### 6.2B.1.4.2.1.1 Test purpose

Same test purpose as in clause 6.2.1.1.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.2B.1.4.2.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

##### 6.2B.1.4.2.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.1.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.4.

## 6.2B.1.4.2.1.4 Test description

## 6.2B.1.4.2.1.4.1 Initial condition

Same test description as in clause 6.2A.1.1.1.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.2A.1.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.2A.1.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.2A.1.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

## 6.2B.1.4.2.1.5 Test Requirements

Same test requirement as in clause 6.2A.1.1.1.5 in TS 38.521-2 [9] for the *NR* carrier.

[IS: 5446 NTT end of a duplication!!]

## 6.2B.1.4.3 UE maximum output power for Inter-band EN-DC including FR2 (4 CCs)

## 6.2B.1.4.3.1 UE maximum output power - EIRP and TRP

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.2A.1.1.2 in TS 38.521-2 is incomplete.

## 6.2B.1.4.3.1.1 Test purpose

Same test purpose as in clause 6.2.1.1.1 in TS 38.521-2 [9] for the *NR* carrier.

## 6.2B.1.4.3.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4 CCs.

## 6.2B.1.4.3.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.1.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.



The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.4.

#### 6.2B.1.4.3.1.4 Test description

##### 6.2B.1.4.3.1.4.1 Initial condition

Same test description as in clause 6.2A.1.1.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.2A.1.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.2A.1.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.2A.1.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.1.4.3.1.5 Test Requirements

Same test requirement as in clause 6.2A.1.1.2.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.2B.1.4.4 UE maximum output power for Inter-band EN-DC including FR2 (5 CCs)

##### 6.2B.1.4.4.1 UE maximum output power - EIRP and TRP

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.2A.1.1.3 in TS 38.521-2 is incomplete.

##### 6.2B.1.4.4.1.1 Test purpose

Same test purpose as in clause 6.2.1.1.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.2B.1.4.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5 CCs.

##### 6.2B.1.4.4.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.1.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.1.4.

#### 6.2B.1.4.4.1.4 Test description

##### 6.2B.1.4.4.1.4.1 Initial condition

Same test description as in clause 6.2A.1.1.3.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.2A.1.1.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.2A.1.1.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.2A.1.1.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.1.4.4.1.5 Test Requirements

Same test requirement as in clause 6.2A.1.1.3.5 in TS 38.521-2 [9] for the *NR* carrier.

## 6.2B.2 UE Maximum Output Power reduction for EN-DC

### 6.2B.2.0 General

The UE maximum output power reduction (MPR) specified in this subclause is applicable for UEs configured with EN-DC when `NS_01` is indicated in the MCG and the SCG. The MPR applies subject to indication in the field *modifiedMPRbehavior* for the SCG [2].

### 6.2B.2.1 UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC

#### 6.2B.2.1.1 Test purpose

Same test purpose as in clause 6.2.2.1 in TS 38.521-1 [8] for the *NR* carrier.

#### 6.2B.2.1.2 Test applicability

This test case applies to all types of E-UTRA power class 3 and power class 2 UE release 15 and forward, supporting intra-band EN-DC.

#### 6.2B.2.1.3 Minimum conformance requirements

When the UE is configured for intra-band contiguous EN-DC, the UE determines the total allowed maximum output power reduction as specified in this subclause.

For UE supporting dynamic power sharing the following:

- for the MCG,  $MPR_c$  in accordance with [5]
- for the SCG,

$$MPR'_c = MPR_{NR} = \text{MAX}(MPR_{\text{single,NR}}, MPR_{\text{ENDC}})$$

- for the total configured transmission power,

$$MPR_{\text{tot}} = P_{\text{PowerClass,EN-DC}} - \min(P_{\text{PowerClass,EN-DC}}, 10 * \log_{10}(10^{((P_{\text{PowerClass,E-UTRA}} - MPR_{\text{E-UTRA}})/10)} + 10^{((P_{\text{PowerClass,NR}} - MPR_{\text{NR}})/10)}))$$

where

$$MPR_{\text{E-UTRA}} = \text{MAX}(MPR_{\text{single,E-UTRA}}, MPR_{\text{ENDC}})$$

with

- $MPR_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5]
- $MPR_{\text{single,NR}}$  is the MPR defined for the NR transmission in [2]

For UEs not supporting dynamic power sharing the following

- for the MCG,

$$MPR_c = \text{MAX}(MPR_{\text{single,E-UTRA}}, MPR_{\text{ENDC}})$$

- for the SCG,

$$MPR'_c = \text{MAX}(MPR_{\text{single,NR}}, MPR_{\text{ENDC}})$$

where

- $MPR_{\text{single,NR}}$  is the MPR defined for the NR transmission in [2]
- $MPR_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5]

MPR in this sub-clause is applicable for power class 3 and power class 2. The allowed maximum output power reduction applied to transmission on the MCG and the SCG is defined as follows:

$$MPR_{\text{ENDC}} = M_A$$

Where  $M_A$  is defined as follows

$$M_A = \begin{cases} [15] & ; \quad 0 \leq B < 0.5 \\ [10] & ; \quad 0.5 \leq B < 1.0 \\ [8] & ; \quad 1.0 \leq B < 2.0 \\ [6] & ; \quad 2.0 < B \end{cases}$$

Where:

For UEs supporting dynamic power sharing,

$$B = (L_{\text{CRB\_alloc,E-UTRA}} * 12 * \text{SCS}_{\text{E-UTRA}} + L_{\text{CRB\_alloc,NR}} * 12 * \text{SCS}_{\text{NR}}) / 1,000,000$$

For UEs not supporting dynamic power sharing,

For E-UTRA

$$B = (L_{\text{CRB\_alloc,E-UTRA}} * 12 * \text{SCS}_{\text{E-UTRA}} + 12 * \text{SCS}_{\text{NR}}) / 1,000,000$$

For NR

$$B = (12 * \text{SCS}_{\text{E-UTRA}} + L_{\text{CRB\_alloc,NR}} * 12 * \text{SCS}_{\text{NR}}) / 1,000,000$$

and  $M_A$  is reduced by 1 dB for  $B < 2$ . The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.2.1.

Exception requirements for both NR and E-UTRA are defined for this test when transmission on E-UTRA overlap in time with NR. LTE anchor agnostic approach is not applied for this case and referred to as sub-test 1. E-UTRA test point analysis is included and E-UTRA measurements are performed,

No exception requirements for NR or E-UTRA are defined for this test when transmission on E-UTRA doesn't overlap in time with NR. LTE anchor agnostic approach is applied for this case and referred to as sub-test 2.

6.2B.2.1.4 Test description

6.2B.2.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial condition part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's

The initial test configurations consist of environmental conditions, test frequencies and test channel bandwidths based on NR operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.4B.2.1.3.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexes A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521.1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.2.1.4.1-1: Test configuration table**

Initial Conditions						
Test Environment as specified in TS 38.508-1 [6] subclause 4.1			Normal, TL/VL, TL/VH, TH/VL, TH/VH			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1			Low range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.3-1			Lowest N <sub>RB_agg</sub> , Highest N <sub>RB_agg</sub> (Note 2)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1			Lowest, Highest			
Test Parameters						
Test ID	Freq	Downlink Configuration	EN-DC Uplink Configuration			
			E-UTRA Cell		NR Cell	
			Modulation	RB allocation	Modulation	RB allocation (NOTE 1)
1	Default	N/A	16QAM	Outer_Full	DFT-s-OFDM PI/2 BPSK	Outer_Full
2 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	Edge_1RB_Right
3 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	Edge_1RB_Left
4	Default		16QAM	Outer_Full	CP-OFDM 64QAM	Outer_Full
5	Default		16QAM	Outer_Full	CP-OFDM 256QAM	Outer_Full
6	Default		16QAM	0	DFT-s-OFDM 64QAM	Outer_Full
<p>NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].</p> <p>NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same N<sub>RB_agg</sub>, select the combination to test as follows:</p> <ul style="list-style-type: none"> <li>- Lowest ENBW: NR component with lowest NRB is tested.</li> <li>- Highest ENBW: NR component with highest NRB is tested.</li> </ul> <p>NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.</p> <p>NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.</p> <p>NOTE 5: Outer_Full defined as the transmission bandwidth configuration NRB per channel bandwidth for the E-UTRA component as indicated in TS 36.521 [10] Table 5.4.2-1. Outer_1RB_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer_1RB_Right defined as 1 RB allocated at the right edge of the E-UTRA component.</p> <p>NOTE 6: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1.</p>						

- 1.1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1 for TE diagram and section A.3.2.1 for UE diagram.
  - 1.2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
  - 1.3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
  - 1.4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS 38.521-1[8].
  - 1.5. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
  - 1.6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
  - 1.7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.4B.2.1.3.4.3.
  - 1.8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.
2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same initial condition as in clause 6.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For initial conditions as in clause 6.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Same initial conditions as in clause 6.2.2.4.1 in TS 38.521-1 [8] with the following steps exception:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.2B.2.1.4.3 Test procedure

The test procedure part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's
  - 1.1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to Table 6.2B.2.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send, the UE transmits uplink MAC padding bits on the UL RMC.
  - 1.2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.

1.3. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.2B.2.1.5. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms). For TDD slots with transient periods are not under test.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.2B.2.1.4.1-1, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-89 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same test procedure as in clause 6.2.2.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

#### 6.2B.2.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1 with the following exceptions:

**Table 6.2B.2.1.4.3-1: AdditionalSpectrumEmission for MCG**

Derivation Path: 36.508 [11] clause 4.6.3, Table 4.4.3.3-1			
Information Element	Value/remark	Comment	Condition
AdditionalSpectrumEmission	0 (NS_01)		

**Table 6.2B.2.1.4.3-2: AdditionalSpectrumEmission for SCG**

Derivation Path: 38.508-1 [5] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
AdditionalSpectrumEmission	0 (NS_01)		

**Table 6.2B.2.1.4.3-3: RF-Parameters**

Derivation Path: 38.331 [15] clause 6.3.3			
Information Element	Value/remark	Comment	Condition
modifiedMPR-Behaviour	[00000001]		

#### 6.2B.2.1.5 Test requirement

The maximum output power, derived in step 1.3 in sub test 1 shall be within the range prescribed by the nominal maximum output power and tolerance in table 6.2B.2.1.5-1/table 6.2B.2.1.5-2 for UE supporting dynamic power sharing and table 6.2B.2.1.5-3/table 6.2B.2.1.5-4 for UE not supporting dynamic power sharing. Same test requirement as in 6.2.2.5 in TS 38.521-1 [8] for sub test 2.

**Table 6.2B.2.1.5-1: UE Power Class 3 test requirements, UE supporting dynamic power sharing**

Configuration ID	MPR <sub>tot</sub> (dB)	P <sub>EN-DC, tot_L</sub> (dBm)	P <sub>EN-DC, tot_H</sub> (dBm)	T <sub>LOW</sub> (P <sub>C<sub>MAX_L</sub></sub> ) (dB)	T <sub>HIGH</sub> (P <sub>C<sub>MAX_H</sub></sub> ) (dB)	Upper limit (dBm)	Lower limit (dBm)
1	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT
2	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT
3	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT
4	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT
5	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT
6	12,0	11,0	23,0	6,0	3,0	26,0 + TT	5,0 - TT

Table 6.2B.2.1.5-2: UE Power Class 2 test requirements, UE supporting dynamic power sharing

Configuration ID	MPR <sub>tot</sub> (dB)	P <sub>EN-DC, tot_L</sub> (dBm)	P <sub>EN-DC, tot_H</sub> (dBm)	T <sub>LOW</sub> (P <sub>CMAX_L</sub> ) (dB)	T <sub>HIGH</sub> (P <sub>CMAX_H</sub> ) (dB)	Upper limit (dBm)	Lower limit (dBm)
1	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT
2	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT
3	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT
4	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT
5	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT
6	12.0	14.0	26.0	6.0	2.0	28.0 + TT	8.0 - TT

Table 6.2B.2.1.5-3: UE Power Class 3 test requirements, UE not supporting dynamic power sharing

Configuration ID	MPR <sub>tot</sub> (dB)	P <sub>EN-DC, tot_L</sub> (dBm)	P <sub>EN-DC, tot_H</sub> (dBm)	T <sub>LOW</sub> (P <sub>CMAX_L</sub> ) (dB)	T <sub>HIGH</sub> (P <sub>CMAX_H</sub> ) (dB)	Upper limit (dBm)	Lower limit (dBm)
1	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT
2	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT
3	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT
4	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT
5	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT
6	11.0	12.0	23.0	6.0	2.0	25.0 + TT	6.0 - TT

Table 6.2B.2.1.5-4: UE Power Class 2 test requirements, UE not supporting dynamic power sharing

Configuration ID	MPR <sub>tot</sub> (dB)	P <sub>EN-DC, tot_L</sub> (dBm)	P <sub>EN-DC, tot_H</sub> (dBm)	T <sub>LOW</sub> (P <sub>CMAX_L</sub> ) (dB)	T <sub>HIGH</sub> (P <sub>CMAX_H</sub> ) (dB)	Upper limit (dBm)	Lower limit (dBm)
1	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT
2	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT
3	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT
4	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT
5	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT
6	11.0	15.0	26.0	6.0	2.0	28.0 + TT	9.0 - TT

Table 6.2B.2.1.5-5: Test Tolerance

	f ≤ 3.0GHz	3.0GHz < f ≤ 6GHz
BW ≤ 40MHz	0.7	1.0
40MHz < BW ≤ 100MHz	1.0	1.0

## 6.2B.2.2 UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC

Editor's note: The following aspects are either missing or not yet determined:

- Initial condition is not complete.
- Equations for <P<sub>cm</sub>> is missing in TS 38.521-3, 6.2B.4.1.2
- Test requirement is TBD
- Test tolerance is not complete.
- W<sub>gap</sub> not defined

### 6.2B.2.2.1 Test purpose

FFS

### 6.2B.2.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC.

### 6.2B.2.2.3 Minimum conformance requirements

For intra-band non-contiguous EN-DC, single carrier UE maximum output power reduction specified in TS 36.101 [4] for E-UTRA and TS 38.101-1 [2] for NR apply for E-UTRA and NR carriers respectively, unless additional MPR is specified in 6.2B.3.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.2.2.

### 6.2B.2.2.4 Test description

#### 6.2B.2.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and test channel bandwidths based on NR operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.2B.2.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexes A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521.1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.2.2.4.1-1: Test configuration table**

FFS

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6], Figure A.3.1.1.1 for SS diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.2.2.4.3.

#### 6.2B.2.2.4.2 Test procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.2.2.4.1-1 and Table 6.2.2.4.1-2 of TS 38.521-1[8] for UE power class 3 and UE power class 2 respectively. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to Table 6.2.3.3-1 and Table 6.2.3\_1.3-1 of TS 36.521-1[10] for UE power class 3 and UE power class 2 respectively. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.



3. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms for the UE to reach  $P_{UMAX}$  level.
4. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.2B.2.2.5-1. The period of the measurement shall be at least the continuous duration of [one active sub-frame].

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.5B.2.1.2.4.1-1 and 6.5B.2.1.2.4.1-2, send an RRCConnectionReconfiguration message containing NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-118 PUSCH-Config without CP-OFDM condition. When switching to CP-OFDM waveform, send an RRCConnectionReconfiguration message containing NR RRCReconfiguration message with CP-OFDM condition.

#### 6.2B.2.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 6.2B.2.2.5 Test requirement

The maximum output power, derived in step 3 shall be within the range prescribed by the nominal maximum output power and tolerance in table 6.2B.2.2.5-1.

**Table 6.2B.2.2.5-1: UE Power Class test requirements**

TBD

### 6.2B.2.3 UE Maximum Output Power reduction for Inter-Band EN-DC within FR1

**Editor's note:**

- Future optimization is possible by include this test case with corresponding ACLR test case
- The reason why minimum requirement doesn't specify "sum of output power at each UE antenna connector", as in corresponding MOP test case, needs to be understood.

#### 6.2B.2.3.1 Test purpose

Same test purpose as in clause 6.2.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.2B.2.3.2 Test applicability

The requirements of this test apply to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.2B.2.3.3 Minimum conformance requirements

For inter-band EN-DC between E-UTRA and FR1 NR, UE maximum output power reduction specified in TS 36.101 [5] and TS 38.101-1 [2] apply for E-UTRA and NR respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.2.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.2B.2.3.4 Test description

Same test description as in clause 6.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3 with E-UTRA channel bandwidth and test frequencies defined in Table 6.2B.2.3.4-1.
- 3.1. Downlink E-UTRA signals are initially set up according to TS 36.521-1 [10] Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0.
- 4.1. The E-UTRA UL Reference Measurement channels are set according to Table 6.2B.2.3.4-1.

Step 6 of Initial conditions as in clause 6.2.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.2.2.4.2 in TS 38.521-1 [8].

### 6.2B.2.3.5 Test requirement

Same test requirement as in clause 6.2.2.5 in TS 38.521-1 [8].

## 6.2B.2.4 UE Maximum Output Power reduction for Inter-Band EN-DC including FR2

**Editor's Note: This test case is incomplete. Following aspects are missing or under discussion**

- Test configuration table is FFS (referenced FR2 test case is incomplete)
- The referred test case 6.2.2 in TS 38.521-2 is incomplete

### 6.2B.2.4.1 Test purpose

To verify that the error of the UE maximum output power does not exceed the range prescribed by the specified maximum output power with MPR and tolerance.

An excess maximum output power has the possibility to interfere to other channels or other systems. A small maximum output power decreases the coverage area.

### 6.2B.2.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

### 6.2B.2.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.2.3 in TS 38.521-2 [9] for the NR carrier. No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 6.2B.2.4.4 Test description

#### 6.2B.2.4.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and test channel bandwidths based on NR operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.2B.2.4.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexes A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521.1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.7-1.

**Table 6.2B.2.4.4.1-1: Test configuration Table**

FFS

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. The UL Reference Measurement channels for NR are set according to Table 6.5.3.1.4.1-1 of TS38.521-1[8].
8. NR propagation conditions are set according to Annex B.0 of TS38.521-1[8].
9. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.2.4.4.3.
- 10 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.2.4.4.2 Test procedure

Same test procedure as in clause 6.2.2.4.2 in TS 38.521-2 [9].

#### 6.2B.2.4.4.3 Message contents

Same message contents as in clause 6.2.2.4.3 in TS 38.521-2 [9].

#### 6.2B.2.4.5 Test requirement

Same test requirement as in clause 6.2.2.5 in TS 38.521-2 [9].

[IS: 5446 NTT created a 2. duplication!!]

#### 6.2B.2.4.2 Transmit OFF Power for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **Test configuration table and Connection diagram in TS 38.521-2 are TBD**
- **The referred test case 6.3A.2.1 in TS 38.521-2 is incomplete.**

#### 6.2B.2.4.2.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.2B.2.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

#### 6.2B.2.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.2B.2.4.2.4 Test description

##### 6.2B.2.4.2.4.1 Initial condition

Same test description as in clause 6.3A.2.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.3A.2.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3A.2.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3A.2.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.2.4.2.5 Test Requirements

Same test requirement as in clause 6.3A.2.1.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.2B.2.4.3 Transmit OFF Power for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.3A.2.2 in TS 38.521-2 is incomplete.

##### 6.2B.2.4.3.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.2B.2.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4 CCs.

##### 6.2B.2.4.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.2B.2.4.3.4 Test description

##### 6.2B.2.4.3.4.1 Initial condition

Same test description as in clause 6.3A.2.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.3A.2.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3A.2.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3A.2.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.2.4.3.5 Test Requirements

Same test requirement as in clause 6.3A.2.2.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.2B.2.4.4 Transmit OFF Power for Inter-band EN-DC including FR2 (5 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **Test configuration table and Connection diagram in TS 38.521-2 are TBD**
- **The referred test case 6.3A.2.3 in TS 38.521-2 is incomplete.**

##### 6.2B.2.4.4.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.2B.2.4.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5 CCs.

##### 6.2B.2.4.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.2B.2.4.4.4 Test description

##### 6.2B.2.4.4.4.1 Initial condition

Same test description as in clause 6.3A.2.3.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.3A.2.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3A.2.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3A.2.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.2B.2.4.4.5 Test Requirements

Same test requirement as in clause 6.3A.2.3.5 in TS 38.521-2 [9] for the *NR* carrier.

[IS: 5446 NTT end of the 2. duplication!!]

### 6.2B.2.5 UE Maximum Output power reduction for inter-band EN-DC including both FR1 and FR2

#### 6.2B.2.5.1 Test purpose

Same test purpose as in 6.2B.2.3.1 in TS 38.521-1 [8] for NR FR1 carrier(s) and 6.2B.2.4.1 in 38.521-2 [9] for NR FR2 carrier(s).

#### 6.2B.2.5.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 and E-UTRA in conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The NSA requirements for maximum output power apply and are tested as part of the EN-DC within FR1 and EN-DC including FR2 test cases in clause 6.2B.

### 6.2B.3 UE additional maximum output power reduction for EN-DC

#### 6.2B.3.1 UE Additional Maximum Output Power reduction for Intra-band contiguous EN-DC

**Editor's note: This test case is incomplete. The following aspects are either missing or not yet determined:**

- Test requirements and test configuration table for NS\_35 incomplete.
- UE Power Class 2 test requirements

- Test requirements for NS\_04 power class 3 are TBD.

#### 6.2B.3.1.1 Test purpose

Additional emission requirements can be signalled by the network with network signalling value indicated by the field *additionalSpectrumEmission*. To meet these additional requirements, additional maximum power reduction (A-MPR) is allowed for the maximum output power as specified in Table 6.2B.1.1.3-1. Unless stated otherwise, an A-MPR of 0 dB shall be used.

#### 6.2B.3.1.2 Test applicability

The requirements of this test apply in test case 6.5B.2.1.2 Additional spectrum emission mask for network signalled values NS\_04 and NS\_35 to all types of E-UTRA power class 3 and power class 2 UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.2B.3.1.3 Minimum conformance requirements

For EN-DC band combinations with additional requirements the A-MPR allowed are specified in table 6.2B.3.1.3-1 for combinations of network signalling values indicated in E-UTRA or NRcell group(s). Unless otherwise stated the A-MPR specified in sub-clause 6.2B.3.1 for intra-band contiguous EN-DC configurations includes MPR.

**Table 6.2B.3.1.3-1: Additional maximum power reduction for Intra-band contiguous EN-DC**

DC configuration	Requirement (sub-clause)	E-UTRA network signalling value	NR network signalling value	A-MPR (subclause)
DC_(n)71AA	6.5B.2.1.2.3.1	NS_35	NS_35	6.2B.3.1.3.1 <sup>3</sup>
DC_(n)41AA <sup>1</sup>	6.5B.2.1.2.3.2	NS_01 or NS_04	NS_04	6.2B.3.1.3.2 <sup>4</sup>
NOTE 1: Only applies to UEs that support dual UL transmission for this EN-DC combination.				
NOTE 2: The network signalling value for NR is mapped to configured FBI and <i>AdditionalSpectrumEmission</i> values as specified in [6].				
NOTE 3: The A-MPR is applied as MPR if NS_35 is not signalled.				
NOTE 4: The A-MPR is applied as MPR if NS_04 is not signalled.				

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.3.1.

Exception requirements for both NR and E-UTRA are defined for this test when transmission on E-UTRA overlap in time with NR.LTE anchor agnostic approach is not applied for this case and referred to as sub-test 1. E-UTRA test point analysis is included and E-UTRA measurements are performed.

No exception requirements for NR or E-UTRA are defined for this test when transmission on E-UTRA doesn't overlap in time with NR. LTE anchor agnostic approach is applied for this case and referred to as sub-test 2.

#### 6.2B.3.1.3.1 A-MPR for DC\_(n)71AA

For UE supporting dynamic power sharing the following:

- for the MCG,  $A-MPR_c$  in accordance with [5]
- for the SCG,  $A-MPR'_c = [A-MPR_{DC}]$
- for the total configured transmission power,  $A-MPR_{tot} = A-MPR_{DC}$

with  $A-MPR_{DC}$  as defined in this sub-clause.

For UEs not supporting dynamic power sharing the following

- for the MCG,

$$A-MPR_c = A-MPR_{LTE}$$

- for the SCG,

$$A-MPR'_c = A-MPR_{NR}$$

with  $A\text{-MPR}_{\text{LTE}}$  and  $A\text{-MPR}_{\text{NR}}$  as defined in this sub-clause.

For DC\_(n)71AA with configured with network signalling values as per Table 6.2B.3.1.3-1 the allowed A-MPR is defined by

- for UE indicating support of dynamicPowerSharing in the *UE-MRDC-Capability* IE

$$A\text{-MPR}_{\text{DC}} = \text{CEIL}\{ M_{\text{A,DC}}(A), 0.5\}$$

where  $A\text{-MPR}_{\text{DC}}$  is the total power reduction allowed (dB),

- for OFDM:

$$\begin{aligned} M_{\text{A,DC}} &= 11.00 - 11.67 * A; & 0.00 < A \leq 0.30 \\ &8.10 - 2.00 * A; & 0.30 < A \leq 0.80 \\ &6.50; & 0.80 < A \leq 1.00 \end{aligned}$$

- for DFT-S-OFDM:

$$\begin{aligned} M_{\text{A,DC}} &= 11.00 - 13.33 * A; & 0.00 < A \leq 0.30 \\ &8.00 - 3.33 * A; & 0.30 < A \leq 0.60 \\ &6.00; & 0.60 < A \leq 1.00 \end{aligned}$$

where

$$A = \frac{L_{\text{CRB,LTE}} + L_{\text{CRB,NR}}}{N_{\text{RB,LTE}} + N_{\text{RB,NR}}}$$

with  $L_{\text{CRB}}$  and  $N_{\text{RB}}$  the number of allocated PRB and transmission bandwidth for the respective CG,

- for UE not indicating support of dynamicPowerSharing

$$A\text{-MPR}_{\text{LTE}} = \text{CEIL}\{ M_{\text{A,LTE}}, 0.5\}$$

$$A\text{-MPR}_{\text{NR}} = \text{CEIL}\{ M_{\text{A,NR}}, 0.5\}$$

where A-MPR is the total power reduction allowed per CG with

$$M_{\text{A,NR}} = M_{\text{A,DC}}(A_{\text{NR,wc}}) - 1 - \Delta_{\text{NR}}$$

$$A_{\text{LTE,wc}} = \frac{L_{\text{CRB,LTE}} + 1}{N_{\text{RB,LTE}} + N_{\text{RB,NR}}}$$

$$A_{\text{NR,wc}} = \frac{1 + L_{\text{CRB,NR}}}{N_{\text{RB,LTE}} + N_{\text{RB,NR}}}$$

$$\Delta_{\text{LTE}} = 10 \log_{10} \frac{N_{\text{RB,LTE}}}{N_{\text{RB,LTE}} + N_{\text{RB,NR}}}$$

$$\Delta_{\text{NR}} = 10 \log_{10} \frac{N_{\text{RB,NR}}}{N_{\text{RB,LTE}} + N_{\text{RB,NR}}}$$

### 6.2B.3.1.3.2 A-MPR for NS\_04

#### 6.2B.3.1.3.2.0 General

When the UE is configured for B41/n41 intra-band contiguous EN-DC and it receives IE NS\_04, the UE determines the total allowed maximum output power reduction as specified in this subclause. The A-MPR for EN-DC defined in this section is used instead of MPR defined in 6.2B.2.2, not additively, so EN-DC MPR=0 when NS\_04 is signalled.

For UE supporting dynamic power sharing the following:

- for the MCG,  $A\text{-MPR}_c$  in accordance with [5]
- for the SCG,

$$A\text{-MPR}'_c = A\text{-MPR}_{\text{NR}} = \text{MAX}(A\text{-MPR}_{\text{single,NR}}, A\text{-MPR}_{\text{IM3}})$$



- for the total configured transmission power,

$$A\text{-MPR}_{\text{tot}} = P_{\text{PowerClass,EN-DC}} - \min(P_{\text{PowerClass,EN-DC}}, 10 * \log_{10}(10^{(P_{\text{PowerClass,E-UTRA}} - A\text{-MPR}_{\text{E-UTRA}})/10}) + 10^{(P_{\text{PowerClass,NR}} - A\text{-MPR}_{\text{NR}})/10}))$$

where

$$A\text{-MPR}_{\text{E-UTRA}} = \text{MAX}(A\text{-MPR}_{\text{single,E-UTRA}} + \text{MPR}_{\text{single,E-UTRA}}, A\text{-MPR}_{\text{IM3}})$$

with

- $A\text{-MPR}_{\text{single,E-UTRA}}$  is the A-MPR defined for the E-UTRA transmission in [5]
- $A\text{-MPR}_{\text{single,NR}}$  is the A-MPR defined for the NR transmission in [2]
- $\text{MPR}_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5]

For UEs not supporting dynamic power sharing the following

- for the MCG,

$$A\text{-MPR}_c = \text{MAX}(A\text{-MPR}_{\text{single,E-UTRA}} + \text{MPR}_{\text{single,E-UTRA}}, A\text{-MPR}_{\text{IM3}})$$

- for the SCG,

$$A\text{-MPR}'_c = \text{MAX}(A\text{-MPR}_{\text{single,NR}}, A\text{-MPR}_{\text{IM3}})$$

where

- $A\text{-MPR}_{\text{single,E-UTRA}}$  is the A-MPR defined for the E-UTRA transmission in [5]
- $A\text{-MPR}_{\text{single,NR}}$  is the A-MPR defined for the NR transmission in [2]
- $\text{MPR}_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5]

The UE determines the Channel Configuration Case and the value of  $A\text{-MPR}_{\text{IM3}}$  as follows:

If  $F_{\text{IM3,low\_block,low}} < 2490.5$  MHz

Channel Configuration Case B.  $A\text{-MPR}_{\text{IM3}}$  defined in subclause 6.2B.3.1.3.2.2.

Else

Channel Configuration Case A.  $A\text{-MPR}_{\text{IM3}}$  defined in subclause 6.2B.3.1.3.2.1.

where

- $F_{\text{IM3,low\_block,low}} = (2 * F_{\text{low\_channel,low\_edge}}) - F_{\text{high\_channel,high\_edge}}$
- $F_{\text{low\_channel,low\_edge}}$  is the lowermost frequency of lower transmission bandwidth configuration.
- $F_{\text{high\_channel,high\_edge}}$  is the uppermost frequency of upper transmission bandwidth configuration.

#### 6.2B.3.1.3.2.1 $A\text{-MPR}_{\text{IM3}}$ for NS\_04 to meet -13 dBm / 1MHz for 26dBm UE power

$A\text{-MPR}$  in this sub-clause is relative to 26 dBm for power class 2. The same  $A\text{-MPR}$  is used relative to 23 dBm for power class 3. For the UE is configured with channel configurations Case A or Case C (defined in Subclause 6.2B.3.2.3.1), the allowed maximum output power reduction for IM3s applied to transmission on the MCG and the SCG with non-contiguous resource allocation is defined as follows:

$$A\text{-MPR}_{\text{IM3}} = M_A$$

Where  $M_A$  is defined as follows

$$M_A = \begin{cases} 15 ; & 0 \leq B < 0.5 \\ 10 ; & 0.5 \leq B < 1.0 \end{cases}$$

$$8 ; 1.0 \leq B < 2.0$$

$$6 ; 2.0 < B$$

Where:

For UEs supporting dynamic power sharing,

$$B = (L_{CRB\_alloc, E-UTRA} * 12 * SCS_{E-UTRA} + L_{CRB\_alloc, NR} * 12 * SCS_{NR}) / 1,000,000$$

For UEs not supporting dynamic power sharing,

For E-UTRA

$$B = (L_{CRB\_alloc, E-UTRA} * 12 * SCS_{E-UTRA} + 12 * SCS_{NR}) / 1,000,000$$

For NR

$$B = (12 * SCS_{E-UTRA} + L_{CRB\_alloc, NR} * 12 * SCS_{NR}) / 1,000,000$$

and  $M_A$  is reduced by 1 dB for  $B < 2.0$ .

#### 6.2B.3.1.3.2.2 A-MPR for NS\_04 to meet -25 dBm / 1MHz for 26 dBm UE power

A-MPR in this sub-clause is relative to 26 dBm. The same A-MPR is used relative to 23 dBm for power class 3. For the UE is configured with channel configurations Case B or Case D (defined in subclause 6.2B.3.2.1), the allowed maximum output power reduction for IM3s applied to transmission on the MCG and the SCG with non-contiguous resource allocation is defined as follows:

$$A-MPR_{IM3} = M_A$$

Where  $M_A$  is defined as follows

$$M_A = 15 ; 0 \leq B < 1.0$$

$$14 ; 1.0 \leq B < 2.0$$

$$13 ; 2.0 \leq B < 5.0$$

$$12 ; 5.0 < B$$

Where:

For UEs supporting dynamic power sharing,

$$B = (L_{CRB\_alloc, E-UTRA} * 12 * SCS_{E-UTRA} + L_{CRB\_alloc, NR} * 12 * SCS_{NR}) / 1,000,000$$

For UEs not supporting dynamic power sharing,

For E-UTRA

$$B = (L_{CRB\_alloc, E-UTRA} * 12 * SCS_{E-UTRA} + 12 * SCS_{NR}) / 1,000,000$$

For NR

$$B = (L_{CRB\_alloc, E-UTRA} * 12 * SCS_{E-UTRA} + 12 * SCS_{NR}) / 1,000,000$$

and  $M_A$  is reduced by 1 dB.

#### 6.2B.3.1.4 Test description

##### 6.2B.3.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial condition part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.5B.2.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.3.1.4.1-0: E-UTRA test configuration table for NS\_04**

E-UTRA Test Parameters				
E-UTRA Channel Bandwidth	E-UTRA Test Frequency (Note 1)	Downlink	Uplink	
		N/A for A-MPR testing.	Modulation	RB allocation
20 MHz	Low range and High range (Note 2)		QPSK	100
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [6] subclause 4.3.1				
NOTE 2: NR carrier shall be the outermost carrier during test.				

**Table 6.2B.3.1.4.1-1: Test configuration table (network signalled value "NS\_35")**

Initial Conditions						
Test Environment as specified in TS 38.508-1 [6] subclause 4.1			NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1			Low range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1			Lowest N <sub>RB_agg</sub> , Highest N <sub>RB_agg</sub> (Note 2)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1			Lowest, Highest			
Test Parameters						
Test ID	Freq	Downlink Configuration	EN-DC Uplink Configuration			
			E-UTRA Cell		NR Cell	
			Modulation	RB allocation (Note 5)	Modulation	RB allocation (NOTE 1)
1	Default	N/A	16QAM	Outer_Full	DFT-s-OFDM PI/2 BPSK	Outer_Full
2 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
3 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	N/A
4 (Note 3)	High		16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
5 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
6 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
7 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	N/A
8	Default		16QAM	Outer_Full	DFT-s-OFDM QPSK	Outer_Full
9 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	Edge_1RB_Right
10 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	N/A
11 (Note 3)	High		16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Right
12 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	Edge_1RB_Left
13 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Left
14 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	N/A
15	Default		16QAM	Outer_Full	DFT-s-OFDM 16QAM	Outer_Full
16 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	Edge_1RB_Right
17 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	N/A
18 (Note 3)	High		16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Right
19 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	Edge_1RB_Left
20 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Left
21 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	N/A
22	Default		16QAM	Outer_Full	DFT-s-OFDM 64QAM	Outer_Full
23 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 64QAM	Edge_1RB_Right
24 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM 64QAM	Edge_1RB_Left
25	Default		16QAM	Outer_Full	DFT-s-OFDM 256QAM	Outer_Full
26 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 256QAM	Edge_1RB_Right

27 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM 256QAM	Edge_1RB_Left
28	Default		16QAM	Outer_Full	CP-OFDM QPSK	Outer_Full
29 (Note 3)	Default		16QAM	Outer_1RB_Left	CP-OFDM QPSK	Edge_1RB_Right
30 (Note 3)	Low		16QAM	Outer_1RB_Left	CP-OFDM QPSK	N/A
31 (Note 3)	High		16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Right
32 (Note 4)	Default		16QAM	Outer_1RB_Right	CP-OFDM QPSK	Edge_1RB_Left
33 (Note 4)	Low		16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Left
34 (Note 4)	High		16QAM	Outer_1RB_Right	CP-OFDM QPSK	N/A
35	Default		16QAM	Outer_Full	CP-OFDM 16QAM	Outer_Full
36 (Note 3)	Default		16QAM	Outer_1RB_Left	CP-OFDM 16QAM	Edge_1RB_Right
37 (Note 3)	Low		16QAM	Outer_1RB_Left	CP-OFDM 16QAM	N/A
38 (Note 3)	High		16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Right
39 (Note 4)	Default		16QAM	Outer_1RB_Right	CP-OFDM 16QAM	Edge_1RB_Left
40 (Note 4)	Low		16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Left
41 (Note 4)	High		16QAM	Outer_1RB_Right	CP-OFDM 16QAM	N/A
42	Default		16QAM	Outer_Full	CP-OFDM 64QAM	Outer_Full
43 (Note 3)	Low		16QAM	Outer_1RB_Left	CP-OFDM 64QAM	Edge_1RB_Right
44 (Note 4)	High		16QAM	Outer_1RB_Right	CP-OFDM 64QAM	Edge_1RB_Left
45	Default		16QAM	Outer_Full	CP-OFDM 256QAM	Outer_Full
46 (Note 3)	Low		16QAM	Outer_1RB_Left	CP-OFDM 256QAM	Edge_1RB_Right
47 (Note 4)	High		16QAM	Outer_1RB_Right	CP-OFDM 256QAM	Edge_1RB_Left

NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].

NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same  $N_{RB\_agg}$ , select the combination to test as follows:

- Lowest ENBW: NR component with lowest  $N_{RB}$  is tested.
- Highest ENBW: NR component with highest  $N_{RB}$  is tested.

NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.

NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.

NOTE 5: Outer\_Full defined as the transmission bandwidth configuration  $N_{RB}$  per channel bandwidth for the E-UTRA component as indicated in TS 36.521 [10] Table 5.4.2-1. Outer\_1RB\_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer\_1RB\_Right defined as 1 RB allocated at the right edge of the E-UTRA component.

NOTE 6: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1.

**Table 6.2B.3.1.4.1-2: NR test configuration table for NS\_04**

Initial Conditions						
Test Environment as specified in TS 38.508-1 [6] subclause 4.1			NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1			Low range, High range (Note 7)			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1			Lowest N <sub>RB_agg</sub> , Highest N <sub>RB_agg</sub> (Note 2)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1			Lowest, Highest			
Test Parameters						
Test ID	Freq	Downlink Configuration	EN-DC Uplink Configuration			
			E-UTRA Cell		NR Cell	
			Modulation	RB allocation (Note 5)	Modulation	RB allocation (NOTE 1)
1	Default	N/A	16QAM	Outer_Full	DFT-s-OFDM PI/2 BPSK	Outer_Full
2 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
3 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	N/A
4 (Note 3)	High		16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
5 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
6 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
7 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	N/A
8	Default		16QAM	Outer_Full	DFT-s-OFDM QPSK	Outer_Full
9 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	Edge_1RB_Right
10 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	N/A
11 (Note 3)	High		16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Right
12 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	Edge_1RB_Left
13 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Left
14 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	N/A
15	Default		16QAM	Outer_Full	DFT-s-OFDM 16QAM	Outer_Full
16 (Note 3)	Default		16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	Edge_1RB_Right
17 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	N/A
18 (Note 3)	High		16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Right
19 (Note 4)	Default		16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	Edge_1RB_Left
20 (Note 4)	Low		16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Left
21 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	N/A
22	Default		16QAM	Outer_Full	DFT-s-OFDM 64QAM	Outer_Full
23 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 64QAM	Edge_1RB_Right
24 (Note 4)	High		16QAM	Outer_1RB_Right	DFT-s-OFDM 64QAM	Edge_1RB_Left
25	Default		16QAM	Outer_Full	DFT-s-OFDM 256QAM	Outer_Full
26 (Note 3)	Low		16QAM	Outer_1RB_Left	DFT-s-OFDM 256QAM	Edge_1RB_Right



27 (Note 4)	High	16QAM	Outer_1RB_Right	DFT-s-OFDM 256QAM	Edge_1RB_Left
28	Default	16QAM	Outer_Full	CP-OFDM QPSK	Outer_Full
29 (Note 3)	Default	16QAM	Outer_1RB_Left	CP-OFDM QPSK	Edge_1RB_Right
30 (Note 3)	Low	16QAM	Outer_1RB_Left	CP-OFDM QPSK	N/A
31 (Note 3)	High	16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Right
32 (Note 4)	Default	16QAM	Outer_1RB_Right	CP-OFDM QPSK	Edge_1RB_Left
33 (Note 4)	Low	16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Left
34 (Note 4)	High	16QAM	Outer_1RB_Right	CP-OFDM QPSK	N/A
35	Default	16QAM	Outer_Full	CP-OFDM 16QAM	Outer_Full
36 (Note 3)	Default	16QAM	Outer_1RB_Left	CP-OFDM 16QAM	Edge_1RB_Right
37 (Note 3)	Low	16QAM	Outer_1RB_Left	CP-OFDM 16QAM	N/A
38 (Note 3)	High	16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Right
39 (Note 4)	Default	16QAM	Outer_1RB_Right	CP-OFDM 16QAM	Edge_1RB_Left
40 (Note 4)	Low	16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Left
41 (Note 4)	High	16QAM	Outer_1RB_Right	CP-OFDM 16QAM	N/A
42	Default	16QAM	Outer_Full	CP-OFDM 64QAM	Outer_Full
43 (Note 3)	Low	16QAM	Outer_1RB_Left	CP-OFDM 64QAM	Edge_1RB_Right
44 (Note 4)	High	16QAM	Outer_1RB_Right	CP-OFDM 64QAM	Edge_1RB_Left
45	Default	16QAM	Outer_Full	CP-OFDM 256QAM	Outer_Full
46 (Note 3)	Low	16QAM	Outer_1RB_Left	CP-OFDM 256QAM	Edge_1RB_Right
47 (Note 4)	High	16QAM	Outer_1RB_Right	CP-OFDM 256QAM	Edge_1RB_Left

NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].  
 NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same  $N_{RB\_agg}$ , select the combination to test as follows:  
 - Lowest ENBW: NR component with lowest  $N_{RB}$  is tested.  
 - Highest ENBW: NR component with highest  $N_{RB}$  is tested.  
 NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.  
 NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.  
 NOTE 5: Outer\_Full defined as the transmission bandwidth configuration  $N_{RB}$  per channel bandwidth for the E-UTRA component as indicated in TS 36.521 [10] Table 5.4.2-1. Outer\_1RB\_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer\_1RB\_Right defined as 1 RB allocated at the right edge of the E-UTRA component.  
 NOTE 6: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1.  
 NOTE 7: Additional IM3 test frequencies may apply.

**Table 6.2B.3.1.4.1-3: Additional IM3 Test Frequencies for NS\_04 intra-band contiguous EN-DC**

Additional Initial Condition	
Additional IM3 Test Frequencies	if SCS 15 kHz, 15 kHz NR raster, and NR ChBw 40 MHz or 50 MHz then IM3 test frequencies as specified in Table 6.2B.3.1.4.1-4.  if SCS 30 kHz, 30 kHz NR raster, and NR ChBw 40 MHz, 50 MHz or 60 MHz then IM3 test frequencies as specified in Table 6.2B.3.1.4.1-5.  if SCS 60 kHz, 15 kHz NR raster, and NR ChBw 40 MHz, 50 MHz or 60 MHz then IM3 test frequencies as specified in Table 6.2B.3.1.4.1-6.

Table 6.2B.3.1.4.1-4: EN-DC combination DC\_(n)41AA, intra-band contiguous, SCS 15 kHz, 15 kHz NR raster, IM3 test frequencies.

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrier Bandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]	absolute Frequency Point A [ARFCN]	offset ToCarrier [Carrier PRBs]	SS block SCS [kHz]	GSCN	absoluteFrequencySSB [ARFCN]
				Downlink & Uplink	IM3								
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2600.400	40694	-	-	-	-	-	-
	NR CC1	40	216	Downlink & Uplink	IM3	2570.400	514080	2550.96	510192	0	15	6384	514080
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2620.400	40894	-	-	-	-	-	-
	NR CC1	50	270	Downlink & Uplink	IM3	2585.400	517080	2561.1	512220	0	15	6408	517080

Table 6.2B.3.1.4.1-5: EN-DC combination DC\_(n)41AA, intra-band contiguous, SCS 30 kHz, 30 kHz NR raster, IM3 test frequencies.

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrier Bandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]	absolute Frequency Point A [ARFCN]	offset ToCarrier [Carrier PRBs]	SS block SCS [kHz]	GSCN	absoluteFrequencySSB [ARFCN]
				Downlink & Uplink	IM3								
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2600.400	40694	-	-	-	-	-	-
	NR CC1	40	216	Downlink & Uplink	IM3	2570.400	514080	2550.96	510192	0	15	6384	514080
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2620.400	40894	-	-	-	-	-	-
	NR CC1	50	270	Downlink & Uplink	IM3	2585.400	517080	2561.1	512220	0	15	6408	517080
E-UTRA: 20MHz + NR: 60MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2640.500	41095	-	-	-	-	-	-
	NR CC1	60	162	Downlink & Uplink	IM3	2600.500	520100	2571.34	514268	0	30	6438	520100

Table 6.2B.3.1.4.1-6: EN-DC combination DC\_(n)41AA, intra-band contiguous, SCS 60 kHz, 15 kHz NR raster, IM3 test frequencies.

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrier Bandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]	absolute FrequencyPointA [ARFCN]	offset ToCarrier [Carrier PRBs]	SS block SCS [kHz]	GSCN	absoluteFrequencySSB [ARFCN]
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2600.400	40694	-	-	-	-	-	-
	NR CC1	40	51	Downlink & Uplink	IM3	2570.400	514080	2552.04	510408	0	15	6387	514080
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2620.400	40894	-	-	-	-	-	-
	NR CC1	50	65	Downlink & Uplink	IM3	2585.400	517080	2562	512400	0	15	6411	517080
E-UTRA: 20MHz + NR: 60MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2640.500	41095	-	-	-	-	-	-
	NR CC1	60	79	Downlink & Uplink	IM3	2600.500	520100	2572.06	514412	0	15	6435	520100

**Editor's note:** The following lines belong at the end of section 6.2B.3.1.4.1. As new tables are added to this section, these lines should always follow the tables.

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

- 1.1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
  - 1.2. The parameter settings for E-UTRA the cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
  - 1.3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
  - 1.4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS 38.521-1[8].
  - 1.5. The UL Reference Measurement channels are set according to TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG link respectively.
  - 1.6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
  - 1.7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.3.1.4.3.
  - 1.8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.
2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same initial condition as in clause 6.2.3.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Same initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8] with the following steps exception:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.2B.3.1.4.2 Test procedure

The test procedure part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's

- 1.1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to table 6.2B.3.1.4.1-1 or 6.2B.3.1.4.1-2 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
- 1.2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command for the UE to reach  $P_{UMAX}$  level.
- 1.3. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.2B.3.1.5.1-1 thru 6.2B.3.1.5.2-1. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms).

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.2B.3.1.4.1-1 or 6.2B.3.1.4.1-2, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-89 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same test procedure as in clause 6.2.3.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

#### 6.2B.3.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1, with the following exceptions for each network signalled value.

##### 6.2B.3.1.4.3.1 Message contents exceptions (network signalled value "NS\_04")

1. Information element additionalSpectrumEmission for E-UTRA is set to NS\_04. This can be set in the *SystemInformationBlockType2* as part of the cell broadcast message. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario.

**Table 6.2B.3.1.4.3.1-1: SystemInformationBlockType2: Additional spurious emissions test requirement for MCG and "NS\_04"**

Derivation Path: 36.508 [11] clause 4.6.3, Table 4.4.3.3-1			
Information Element	Value/remark	Comment	Condition
additionalSpectrumEmission	1 (NS_04)		

2. Information element AdditionalSpectrumEmission for NR is set to NS\_04. This can be set in *nr-SecondaryCellGroupConfig* according to TS 36.331[TBD]. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario

**Table 6.2B.3.1.4.3.1-2: AdditionalSpectrumEmission: Additional spurious emissions test requirement for SCG and "NS\_04"**

Derivation Path: TS 38.508-1 [6] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
additionalSpectrumEmission	1 (NS_04)		

## 6.2B.3.1.4.3.2 Message contents exceptions (network signalled value "NS\_35")

1. Information element `additionalSpectrumEmission` for E-UTRA is set to NS\_35. This can be set in the *SystemInformationBlockType2* as part of the cell broadcast message. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario.

**Table 6.2B.3.1.4.3.2-1: SystemInformationBlockType2: Additional spurious emissions test requirement for MCG and "NS\_35"**

Derivation Path: 36.508 [11] clause 4.6.3, Table 4.4.3.3-1			
Information Element	Value/remark	Comment	Condition
<code>additionalSpectrumEmission</code>	1 (NS_35)		

2. Information element `AdditionalSpectrumEmission` for NR is set to NS\_35. This can be set in *nr-SecondaryCellGroupConfig* according to TS 36.331[TBD]. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario

**Table 6.2B.3.1.4.3.2-2: AdditionalSpectrumEmission: Additional spurious emissions test requirement for for SCG "NS\_35"**

Derivation Path: TS 38.508-1 [5] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
<code>additionalSpectrumEmission</code>	1 (NS_35)		

## 6.2B.3.1.5 Test requirement

## 6.2B.3.1.5.1 Test requirement for network signalled value "NS\_35"

The maximum output power, derived in step 3 shall be within the range prescribed by the nominal maximum output power and tolerance in table 6.2B.3.1.5.1-1. The allowed A-MPR values specified in table 6.2B.3.1.3-1 are in addition to the allowed MPR requirements specified in clause 6.2B.1.1.3. For the UE maximum output power modified by MPR and/or A-MPR, the power limits specified in table 6.2B.1.1.3-1 apply.

**Table 6.2B.3.1.5.1-1: UE Power Class test requirements for network signalled value "NS\_35" for UEs not supporting dynamic power sharing**

Test ID	Test frequency	E-UTRA BW	NR BW	Modulation	$P_{PowerClass}$ (dBm)	$\Delta P_{PowerClass}$ (dB)	A-MPR <sub>c</sub> (dB)	$\Delta TC_{,c}$ (dB) Note 7	$P_{CMAX,c}$ (dBm)	$T(P_{CMAX_{L,f,c}})$ (dB)	$T_{L,c}$ (dB)	Upper limit	Lower limit
1, 8, 15, 22, 25	Low	5	5	E-UTRA/NR	23	0	6.0	0	17.0	5	+2/-3	25+TT	12-TT
1, 8, 15, 22, 25	Low	5	15	E-UTRA/NR	23	0	6.0	0	17.0	5	+2/-3	25+TT	12-TT
1, 8, 15, 22, 25	High	5	5	E-UTRA/NR	23	0	6.0	0	17.0	5	+2/-3	25+TT	12-TT
1, 8, 15, 22, 25	High	15	5	E-UTRA/NR	23	0	6.0	0	17.0	5	+2/-3	25+TT	12-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	5	E-UTRA/NR	23	0	10.5	0	12.5	6	+2/-3	25+TT	6.5-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	15	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	5	5	E-UTRA/NR	23	0	10.5	0	12.5	6	+2/-3	25+TT	6.5-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	15	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
3, 10, 17	Low	5	5	E-UTRA/NR	23	0	12.5	0	10.5	6	+2/-3	25+TT	4.5-TT
3, 14, 17	Low	5	15	E-UTRA/NR	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
4, 11, 18	High	5	5	E-UTRA/NR	23	0	12.5	0	10.5	12.5	+2/-3	25+TT	4.5-TT
4, 11, 18	High	15	5	E-UTRA/NR	23	0	16.0	0	7.0	16.0	+2/-3	25+TT	0-TT
6, 13, 20	Low	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
6, 13, 20	Low	5	15	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
7, 14, 21	High	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
7, 14, 21	High	15	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
28, 35, 42, 45	Low	5	5	E-UTRA/NR	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
28, 35, 42, 45	Low	5	15	E-UTRA/NR	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
28, 35, 42, 45	High	5	5	E-UTRA/NR	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
28, 35, 42, 45	High	15	5	E-UTRA/NR	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
29, 35, 42, 45	Low	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6.5-TT
29, 35, 42, 45	Low	5	15	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
29, 35, 42, 45	High	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6.5-TT
29, 35, 42, 45	High	15	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
30, 34, 37, 41	Low	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
30, 34, 37, 41	Low	5	15	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
31, 33, 38, 40	High	5	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
31, 33, 38, 40	High	15	5	E-UTRA/NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT

**Table 6.2B.3.1.5.1-1A: UE Power Class test requirements for network signalled value "NS\_35" for UEs supporting dynamic power sharing**



Test ID	Test freq. range	E-UTRA BW	NR BW	Modulation	$P_{PowerClass}$ (dBm)	$\Delta P_{PowerClass}$ (dB)	A-MPR <sub>c</sub> (dB)	$\Delta T_{C,c}$ (dB) Note 7	$P_{CMAX,c}$ (dBm)	$T(P_{CMAX,c})_{L,f,c}$ (dB)	$T_{L,c}$ (dB)	Upper limit	Lower limit
1, 8, 15, 22, 25	Low	5	5	E-UTRA	23	0	8.5	0	14.5	5	+2/-3	25+TT	9.5-TT
1, 8, 15, 22, 25	Low	5	5	NR	23	0	8.5	0	14.5	5	+2/-3	25+TT	9.5-TT
1, 8, 15, 22, 25	Low	5	15	E-UTRA	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
1, 8, 15, 22, 25	Low	5	15	NR	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
1, 8, 15, 22, 25	High	5	5	E-UTRA	23	0	8.5	0	14.5	5	+2/-3	25+TT	9.5-TT
1, 8, 15, 22, 25	High	5	5	NR	23	0	8.5	0	14.5	5	+2/-3	25+TT	9.5-TT
1, 8, 15, 22, 25	High	15	5	E-UTRA	23	0	6.5	0	16.5	5	+2/-3	25+TT	11.5-TT
1, 8, 15, 22, 25	High	15	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	5	E-UTRA	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	15	E-UTRA	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	Low	5	15	NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	5	5	E-UTRA	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	15	5	E-UTRA	23	0	11.5	0	11.5	6	+2/-3	25+TT	5.5-TT
2, 5, 9, 12, 16, 19, 23, 24, 2, 26, 27	High	15	5	NR	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
3, 10, 17	Low	5	5	E-UTRA/	23	0	12.5	0	10.5	6	+2/-3	25+TT	4.5-TT
3, 10, 17	Low	5	15	E-UTRA	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
4, 11, 18	High	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
4, 11, 18	High	15	5	NR	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
6, 17, 20	Low	5	5	E-UTRA/	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
6, 17, 20	Low	5	15	E-UTRA	23	0	16.5	0	6.5	7	+2/-3	25+TT	-0.5-TT
7, 14, 21	High	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
7, 14, 21	High	15	5	NR	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
28, 35, 42, 45	Low	5	5	E-UTRA	23	0	9.5	0	13.5	5	+2/-3	25+TT	8.5-TT
28, 35, 42, 45	Low	5	5	NR	23	0	9.5	0	13.5	5	+2/-3	25+TT	8.5-TT
28, 35, 42, 45	Low	5	15	E-UTRA	23	0	13.5	0	9.5	6	+2/-3	25+TT	3.5-TT

28, 35, 42, 45	Low	5	15	NR	23	0	7.0	0	16.0	5	+2/-3	25+TT	11-TT
28, 35, 42, 45	High	5	5	E-UTRA	23	0	9.5	0	13.5	5	+2/-3	25+TT	8.5-TT
28, 35, 42, 45	High	5	5	NR	23	0	9.5	0	13.5	5	+2/-3	25+TT	8.5-TT
28, 35, 42, 45	High	15	5	E-UTRA	23	0	7.0	0	16.0	5	+2/-3	25+TT	11-TT
28, 35, 42, 45	High	15	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
29, 36, 43, 46	Low	5	5	E-UTRA	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
29, 36, 43, 46	Low	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
29, 36, 43, 46	Low	5	15	E-UTRA	23	0	16.0	0	7.0	7	+2/-3	25+TT	0-TT
29, 36, 43, 46	Low	5	15	NR	23	0	11.0	0	12.0	6	+2/-3	25+TT	6-TT
29, 36, 43, 46	High	5	5	E-UTRA	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
29, 36, 43, 46	High	5	5	NR	23	0	13.0	0	10.0	6	+2/-3	25+TT	4-TT
29, 36, 43, 46	High	15	5	E-UTRA	23	0	11.5	0	11.5	6	+2/-3	25+TT	0-TT
29, 36, 43, 46	High	15	5	NR	23	0	16.0	0	7.0	7	+2/-3	25+TT	5.5-TT
30, 37	Low	5	5	E-UTRA/	23	0	<b>13.0</b>	0	10.0	6		25+TT	4-TT
30, 37	Low	5	15	E-UTRA	23	0	<b>16.0</b>	0	7.0	7		25+TT	0-TT
31, 38	High	5	5	NR	23	0	<b>13.0</b>	0	10.0	6		25+TT	4-TT
31, 38	High	15	5	NR	23	0	<b>16.0</b>	0	7.0	7		25+TT	0-TT
34, 41	High	5	5	NR	23	0	<b>13.0</b>	0	10.0	6		25+TT	4-TT
34, 41	High	15	5	NR	23	0	<b>16.0</b>	0	7.0	7		25+TT	0-TT
33,40	Low	5	5	E-UTRA/	23	0	<b>13.0</b>	0	10.0	6		25+TT	4-TT
33,40	Low	5	15	E-UTRA	23	0	<b>16.5</b>	0	6.5	7		25+TT	-0.5-TT

6.2B.3.1.5.2 Test requirement for network signalled value "NS\_04"

**Table 6.2B.3.1.5.2-1: UE Power Class 3 test requirements for network signalled value "NS\_04"**

Test ID	Modulation	$\Delta P_{\text{owerClass}}$ (dB)	MPR (dB)	A-MPR (dB)	A-MPR <sub>IM3</sub> (dB)	A-MPR <sub>c</sub> (dB)	$\Delta T_{C,c}$ (dB) Note 7	$P_{\text{C MAX,c}}$ (dBm)	$T(P_{\text{C MAX,L,f,c}})$ (dB)	$T_{L,c}$ (dB)	Upper limit	Lower limit
1, 8, 15, 22, 25, 28, 35, 42 and 45	E-UTRA Note 1	0	2	0	6	6	0 (1.5)	17 (15.5)	5 (5)	2 (3.5)	25+TT	12-TT (10.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	E-UTRA Note 2	0	2	0	11	11	0 (1.5)	12 (10.5)	6 (6)	2 (3.5)	25+TT	6+TT (4.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	NR, Note 1	0	-	Note 5	6	6	0 (1.5)	17 (15.5)	5 (5)	2 (3.5)	25+TT	12-TT (10.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	NR, Note 2	0	-	Note 5	11	11	0 (1.5)	12 (10.5)	6 (6)	2 (3.5)	25+TT	6+TT (4.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 1, 3	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 1, 4	0	1	Note 6	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 2	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 1, 3	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 1, 4	0	-	Note 5	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 2	0	-	Note 5	11	11	0 (1.5)	9 (7.5)	6 (6)	2 (3.5)	25+TT	3-TT (0.5-TT)
3, 7, 10, 14, 17, 21, 30, 34, 37, 41	E-UTRA Note 1	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
3, 7, 10, 14, 17, 21, 30, 34, 37 and 41	E-UTRA Note 2	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
4, 6, 11, 13, 18, 20, 31, 33, 38 and 40	NR Note 1, 3	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)

4, 6, 11, 13, 18, 20, 31, 33,38 and 40	NR Note 1,4	0	-	Note 5	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)
4, 6, 11, 13, 18, 20, 31, 33,38 and 40	NR Note 2	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (6)	2 (3.5)	25+TT	3-TT (0.5-TT)

NOTE 1: When  $F_{IM3,low\_block,low} \geq 2490.5$  MHz (Case A)  
 NOTE 2: When  $F_{IM3,low\_block,low} < 2490.5$  MHz (Case B)  
 NOTE 3: When NR SCS = 15kHz.  
 NOTE 4: When NR SCS = 30 kHz or 60 kHz.  
 NOTE 5: NR A-MPR values for NS\_04 are defined in Table 6.2.3.3.2-1.  
 NOTE 6: E-UTRA A-MPR= 3 dB for 1 RB and  $f_c < 2517.5$  MHz, otherwise 0 dB.  
 NOTE 7:  $\Delta T_{C,c} = 1.5$  dB for transmission bandwidths confined within  $F_{UL\_low}$  and  $F_{UL\_low} + 4$  MHz or  $F_{UL\_high} - 4$  MHz and  $F_{UL\_high}$ , otherwise 0 dB.  
 NOTE 8: TT for each frequency and channel bandwidth is specified in Table 6.2B.3.1.5.2-2.

**Table 6.2B.3.1.5.2-2: UE Power Class 2 test requirements for network signalled value "NS\_04" for UEs supporting dynamic power sharing with backoff applied equally to LTE and NR**

Configuration ID	$F_{IM3,low\_block,low}$	A-MPR <sub>IM3</sub> (dB)	A-MPR (dB)	TBD	$P_{CMAX,c}$ (dBm)	$T(P_{CMAX,L,c})$ (dB)	Upper limit (dBm)	Lower limit (dBm)
1	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD
2	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD
3	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD
4	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD
5	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD
6	TBD	TBD	TBD	TBD	TBD	TBD	TBD	TBD

**Table: 6.2B.3.1.5.2-2: Test Tolerance for UE maximum output power (LTE, NR TX seperately)**

Uplink TX		$f \leq 3.0GHz$	$3.0GHz < f \leq 4.2GHz$	$4.2GHz < f \leq 6GHz$
LTE	<b>BW ≤ 20MHz</b>	0.7	1.0	1.3
NR	<b>BW ≤ 40MHz</b>	0.7 dB	1.0 dB	1.0
	<b>40MHz &lt; BW ≤ 100MHz</b>	1.0 dB	1.0 dB	1.0

6.2B.3.2 UE Additional Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC

Editor’s note: This test case is incomplete. The following aspects are either missing or not yet determined:

- UE Power Class 2 test requirements
- Test frequencies for the Minimum  $W_{GAP}$

6.2B.3.2.1 Test purpose

Additional emission requirements can be signalled by the network with network signalling value indicated by the field *additionalSpectrumEmission*. To meet these additional requirements, additional maximum power reduction (A-MPR) is allowed for the maximum output power as specified in Table 6.2B.1.1.3-1. Unless stated otherwise, an A-MPR of 0 dB shall be used.

6.2B.3.2.2 Test applicability

The requirements of this test apply in test case 6.5B.2.1.2 Additional spectrum emission mask for network signalled values NS\_04 to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

## 6.2B.3.2.3 Minimum conformance requirements

For intra-band EN-DC band combinations with additional requirements the A-MPR allowed are specified in table 6.2B.3.2.3-1 for combinations of network signalling values indicated in E-UTRA or NR cell group(s). Unless otherwise stated the A-MPR specified in sub-clause 6.2B.3.2 for intra-band non-contiguous EN-DC configurations includes MPR.

**Table 6.2B.3.2.3-1: Allowed power reduction for intra-band non-contiguous EN-DC**

DC configuration	Requirement (sub-clause)	E-UTRA network signalling value	NR network signalling value	A-MPR (subclause)
DC_41A_n41 <sup>1</sup>	6.6.3.3.19 and 6.6.2.2.2 of TS 36.101 [5] and 6.5.2.3.2 and 6.5.3.3.1 of TS 38.101-1 [2]	NS_01 or NS_04	NS_04	6.2B.3.2.3.1
NOTE 1: Only applies to UEs that support dual UL transmission for this EN-DC combination. NOTE 2: The A-MPR is applied as MPR if NS_04 is not signalled				

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.3.2.

Exception requirements for both NR and E-UTRA are defined for this test when transmission on E-UTRA overlap in time with NR. LTE anchor agnostic approach is not applied for this case and referred to as sub-test 1. E-UTRA test point analysis is included and E-UTRA measurements are performed.

No exception requirements for NR or E-UTRA are defined for this test when transmission on E-UTRA doesn't overlap in time with NR. LTE anchor agnostic approach is applied for this case and referred to as sub-test 2.

## 6.2B.3.2.3.1 A-MPR for NS\_04

When the UE is configured for B41/n41 intra-band non-contiguous EN-DC and it receives IE NS\_04, the UE determines the total allowed maximum output power reduction as specified in this subclause. The A-MPR for EN-DC defined in this section is used instead of MPR defined in 6.2B.2.2, not additively, so EN-DC MPR=0 when NS\_04 is signalled.

For UE supporting dynamic power sharing the following:

- for the MCG,  $A-MPR_c$  in accordance with [4]
- for the SCG,

$$A-MPR'_c = A-MPR_{NR} = \text{MAX}(A-MPR_{\text{single, NR}}, A-MPR_{\text{EN-DC}})$$

- for the total configured transmission power,

$$A-MPR_{\text{tot}} = P_{\text{PowerClass, EN-DC}} - \min(P_{\text{PowerClass, EN-DC}}, 10 \cdot \log_{10}(10^{(P_{\text{PowerClass, E-UTRA}} - A-MPR_{\text{E-UTRA}})/10} + 10^{(P_{\text{PowerClass, NR}} - A-MPR_{\text{NR}})/10}))$$

where

$$A-MPR_{\text{E-UTRA}} = \text{MAX}(A-MPR_{\text{single, E-UTRA}} + MPR_{\text{single, E-UTRA}}, A-MPR_{\text{EN-DC}})$$

$$A-MPR_{\text{EN-DC}} = \text{MAX}(A-MPR_{\text{IM3}}, A-MPR_{\text{ACLROverlap}})$$

with

- $A-MPR_{\text{single, E-UTRA}}$  is the A-MPR defined for the E-UTRA transmission in [4]
- $A-MPR_{\text{single, NR}}$  is the A-MPR defined for the NR transmission in [2]
- $MPR_{\text{single, E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [4]

For UEs not supporting dynamic power sharing the following

- for the MCG,

$$A\text{-MPR}_c = \text{MAX}( A\text{-MPR}_{\text{single, E-UTRA}} + \text{MPR}_{\text{single,E-UTRA}}, A\text{-MPR}_{\text{IM3}}, A\text{-MPR}_{\text{ACLROverlap}})$$

- for the SCG,

$$A\text{-MPR}'_c = \text{MAX}( A\text{-MPR}_{\text{single,NR}}, A\text{-MPR}_{\text{IM3}}, A\text{-MPR}_{\text{ACLROverlap}})$$

where

- $A\text{-MPR}_{\text{single, E-UTRA}}$  is the A-MPR defined for the E-UTRA transmission in [5]
- $A\text{-MPR}_{\text{single,NR}}$  is the A-MPR defined for the NR transmission in [2]
- $\text{MPR}_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5]

The UE determines the Channel Configuration Case and the value of  $A\text{-MPR}_{\text{IM3}}$  as follows:

$$\text{If AND}( F_{\text{IM3,low\_block,high}} < F_{\text{filter,low}}, \text{MAX}( \text{SEM}_{\text{-13,high}}, F_{\text{IM3,high\_block,low}} ) > F_{\text{filter,high}} )$$

Channel Configuration Case C.  $A\text{-MPR}_{\text{IM3}}$  defined in Subclause 6.2B.3.1.3.2.1

Else

Channel Configuration Case D.  $A\text{-MPR}_{\text{IM3}}$  defined in Subclause 6.2B.3.1.3.2.2

where

- $F_{\text{IM3,low\_block,high}} = (2 * F_{\text{low\_channel,high\_edge}}) - F_{\text{high\_channel,low\_edge}}$
- $F_{\text{IM3,high\_block,low}} = (2 * F_{\text{high\_channel,low\_edge}}) - F_{\text{low\_channel,high\_edge}}$
- $F_{\text{low\_channel,low\_edge}}$  is the lowermost frequency of lower transmission bandwidth configuration.
- $F_{\text{low\_channel,high\_edge}}$  is the uppermost frequency of lower transmission bandwidth configuration.
- $F_{\text{high\_channel,low\_edge}}$  is the lowermost frequency of upper transmission bandwidth configuration.
- $F_{\text{high\_channel,high\_edge}}$  is the uppermost frequency of upper transmission bandwidth configuration.
- $F_{\text{filter,low}} = 2480$  MHz
- $F_{\text{filter,high}} = 2745$  MHz
- $\text{SEM}_{\text{-13,high}}$  = Threshold frequency where upper spectral emission mask for upper channel drops from -13 dBm / 1MHz to -25 dBm / 1MHz, as specified in Subclause 6.2B.3.1.3.2.2.

The UE determines the value of  $A\text{-MPR}_{\text{ACLROverlap}}$  as specified in Table 6.2B.3.2.3.1-1:

**Table 6.2B.3.2.3.1-1:  $A\text{-MPR}_{\text{ACLROverlap}}$**

$W_{\text{gap}}$	$A\text{-MPR}_{\text{ACLROverlap}}$
$< BW_{\text{channel,E-UTRA}} + BW_{\text{channel,NR}}$	4 dB
$\geq BW_{\text{channel,E-UTRA}} + BW_{\text{channel,NR}}$	0 dB
NOTE 1: $W_{\text{gap}} = F_{\text{high\_channel,low\_edge}} - F_{\text{low\_channel,high\_edge}}$	

The UE determines the total allowed maximum output power reduction as follows:

For UEs not supporting dynamic power sharing, with backoff applied independently

$$A\text{-MPR}_{\text{E-UTRA}} = \text{MAX}( A\text{-MPR}_{\text{single, E-UTRA}} + \text{MPR}_{\text{single,E-UTRA}}, A\text{-MPR}_{\text{IM3}}, A\text{-MPR}_{\text{ACLROverlap}} )$$

$$A\text{-MPR}_{\text{NR}} = \text{MAX}( A\text{-MPR}_{\text{single,NR}}, A\text{-MPR}_{\text{IM3}}, A\text{-MPR}_{\text{ACLROverlap}} )$$

For UEs supporting dynamic power sharing, with IM3 backoff applied equally to E-UTRA and NR

$$A\text{-MPR}_{\text{EN-DC}} = \text{MAX}(A\text{-MPR}_{\text{IM3}}, A\text{-MPR}_{\text{ACLRoverlap}})$$

$$A\text{-MPR}_{\text{E-UTRA}} = \text{MAX}(A\text{-MPR}_{\text{single,E-UTRA}} + \text{MPR}_{\text{single,E-UTRA}}, A\text{-MPR}_{\text{EN-DC}})$$

$$A\text{-MPR}_{\text{NR}} = \text{MAX}(A\text{-MPR}_{\text{single,NR}}, A\text{-MPR}_{\text{EN-DC}})$$

where

- $A\text{-MPR}_{\text{single,E-UTRA}}$  is the A-MPR defined for the E-UTRA transmission in TS 36.101 [5].
- $A\text{-MPR}_{\text{single,NR}}$  is the A-MPR defined for the NR transmission in TS 38.101-1 [2].
- $\text{MPR}_{\text{single,E-UTRA}}$  is the MPR defined for the E-UTRA transmission in [5].

#### 6.2B.3.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial condition part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

##### 1. Sub test: with transmission overlap for all UE's

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.3.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing, and are shown in test configuration table 6.2B.3.1.4.1-1 through 6.2B.3.1.4.1-2 with additional IM3 test frequencies for NS\_04 in 6.2B.3.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A2. Configurations of PDSCH and PDCCH before measurement are specified in Annex TS 36.521-1 [10] Annex C and in Annex C2 for LTE link and NR link respectively.

**Table 6.2B.3.2.4.1-0: E-UTRA test configuration table**

E-UTRA Test Parameters				
E-UTRA Channel Bandwidth	E-UTRA Test Frequency (Note 1)	Downlink	Uplink	
		N/A for A-MPR testing	Modulation	RB allocation
20 MHz	Low range and High range (Note 2)		QPSK	100

NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [6] subclause 4.3.1  
NOTE 2: NR carrier shall be the outermost carrier during test.

**Table 6.2B.3.2.4.1-1: Additional IM3 Test Frequencies for NS\_04 intra-band non-contiguous EN-DC**

Additional Initial Condition	
Additional IM3 Test Frequencies	<p>if maximum <math>W_{\text{GAP}} &gt; 88.4</math> MHz, and SCS 15 kHz, 15 kHz NR raster then IM3 test frequencies as specified in Table 6.2B.3.2.4.1-2.</p> <p>if maximum <math>W_{\text{GAP}} &gt; 88.4</math> MHz, and SCS 15 kHz, 30 kHz NR raster then IM3 test frequencies as specified in Table 6.2B.3.2.4.1-3.</p> <p>if maximum <math>W_{\text{GAP}} &gt; 88.4</math> MHz, and SCS 15 kHz, 60 kHz NR raster then IM3 test frequencies as specified in Table 6.2B.3.2.4.1-4.</p>



Table 6.2B.3.2.4.1-2: EN-DC combination DC\_41A\_n41A, intra-band non-contiguous, SCS 15 kHz, 15 kHz NR raster, IM3 test frequencies

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrierBandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]	absolute Frequency Point A [ARFCN]	offsetTo Carrier [Carrier PRBs]	SS block SCS [kHz]	GSC N	absolute Frequency SSB [ARFCN]
				Downlink & Uplink	IM3								
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-	-	-	-	-	-
	NR CC1	40	216	Downlink & Uplink	IM3	2548.300	509660	2528.86	505772	0	15	6327	509660
NR: 40MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2558.300	40273	-	-	-	-	-	-
	NR CC1	40	216	Downlink & Uplink	IM3	2676.700	535340	2657.26	531452	0	15	6648	535340
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2524.900	39939	-	-	-	-	-	-
	NR CC1	50	270	Downlink & Uplink	IM3	2665.000	533000	2640.7	528140	0	15	6606	533000
NR: 50MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-	-	-	-	-	-
	NR CC1	50	270	Downlink & Uplink	IM3	2543.300	508660	2519	503800	0	15	6303	508660

**Table 6.2B.3.2.4.1-3: EN-DC combination DC\_41A\_n41A, intra-band non-contiguous, SCS 30 kHz, 30 kHz NR raster, IM3 test frequencies**

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrierBandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]
				Downlink & Uplink	IM3			
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-
	NR CC1	40	106	Downlink & Uplink	IM3	2548.300	509660	2529.22
NR: 40MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2558.300	40273	-
	NR CC1	40	106	Downlink & Uplink	IM3	2676.700	535340	2657.62
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2524.900	39939	-
	NR CC1	50	133	Downlink & Uplink	IM3	2665.000	533000	2641.06
NR: 50MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-
	NR CC1	50	133	Downlink & Uplink	IM3	2543.300	508660	2519.36

**Table 6.2B.3.2.4.1-4: EN-DC combination DC\_41A\_n41A, intra-band non-contiguous, SCS 60 kHz, 15 kHz NR raster, IM3 test frequencies**

EN-DC channel bandwidth combination	CC	Bandwidth [MHz]	carrierBandwidth [PRBs]	Range		Carrier centre [MHz] Note 2	Carrier centre [ARFCN]	point A [MHz]
				Downlink & Uplink	IM3			
E-UTRA: 20MHz + NR: 40MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-
	NR CC1	40	51	Downlink & Uplink	IM3	2548.300	509660	2529.94
NR: 40MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2558.300	40273	-
	NR CC1	40	51	Downlink & Uplink	IM3	2676.700	535340	2658.34
E-UTRA: 20MHz + NR: 50MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2524.900	39939	-
	NR CC1	50	65	Downlink & Uplink	IM3	2665.000	535340	2653.3
NR: 50MHz + E-UTRA: 20MHz	E-UTRA CC1	20	100	Downlink & Uplink	IM3	2666.700	41357	-
	NR CC1	50	65	Downlink & Uplink	IM3	2543.300	508660	2519.9

**Editor's note:** The following lines belong at the end of section 6.2B.3.2.4.1. As new tables are added to this section, these lines should always follow the tables.

- 1.1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
  - 1.2. The parameter settings for the cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
  - 1.3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
  - 1.4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS 38.521-1[8].
  - 1.5. The UL Reference Measurement channels are set according to TS 36.521-1 [10] Annex A.2 and Annex A for LTE link and NR link respectively.
  - 1.6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
  - 1.7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.3.2.4.3.
  - 1.8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.
2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same initial condition as in clause 6.2.3.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Same initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8] with the following steps exception:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.2B.3.2.4.2 Test procedure

The test procedure part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's

- 1.1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to table 6.2B.3.2.4.1-1 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
- 1.2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.
- 1.3. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.2B.3.2.5-1. The period of the measurement shall be at least the continuous duration of one sub-frame (1ms).

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.2B.3.1.4.1-2, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-89 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same test procedure as in clause 6.2.3.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

#### 6.2B.3.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1, with the following exceptions for each network signalled value.

##### 6.2B.3.2.4.3.1 Message contents exceptions (network signalled value "NS\_04")

For "NS\_04" see A-MPR test case in table 6.2B.3.1.4.3.1-1 and table 6.2B.3.1.4.3.1-2.

#### 6.2B.3.2.5 Test requirement

The maximum output power, derived in step 3 shall be within the range prescribed by the nominal maximum output power and tolerance in table 6.2B.3.2.5-1. The allowed A-MPR values specified in table 6.2B.3.2.3-1 are in addition to the allowed MPR requirements specified in clause 6.2B.1.1.3. For the UE maximum output power modified by MPR and/or A-MPR, the power limits specified in table 6.2B.1.1.3-1 apply.

**Table 6.2B.3.2.5-1: UE Power Class 3 test requirements for network signalled value "NS\_04"**

Test ID	Modulation	$\Delta P_{\text{PowerClass}}$ (dB)	MPR (dB)	A-MPR (dB)	A-MPR <sub>EN-DC</sub> (dB)	A-MPR <sub>c</sub> (dB)	$\Delta T_{C,c}$ (dB) Note 7	$P_{\text{CMAX},c}$ (dBm)	$T(P_{\text{CMAX},L,f,c})$ (dB)	$T_{L,c}$ (dB)	Upper limit	Lower limit
1, 8, 15, 22, 25, 28, 35, 42 and 45	E-UTRA Note 1	0	2	0	6	6	0 (1.5)	17 (15.5)	5 (5)	2 (3.5)	25+TT	12-TT (10.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	E-UTRA Note 2	0	2	0	11	11	0 (1.5)	12 (10.5)	6 (6)	2 (3.5)	25+TT	6+TT (4.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	NR, Note 1	0	-	Note 5	6	6	0 (1.5)	17 (15.5)	5 (5)	2 (3.5)	25+TT	12-TT (10.5-TT)
1, 8, 15, 22, 25, 28, 35, 42 and 45	NR, Note 2	0	-	Note 5	11	11	0 (1.5)	12 (10.5)	6 (6)	2 (3.5)	25+TT	6+TT (4.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 1, 3	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 1, 4	0	1	Note 6	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	E-UTRA Note 2	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 1, 3	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 1, 4	0	-	Note 5	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)

2, 5, 9, 16, 19, 23, 24, 26, 27, 29, 32, 36, 39, 43, 44, 46, and 47	NR Note 2	0	-	Note 5	11	11	0 (1.5)	9 (7.5)	6 (6)	2 (3.5)	25+TT	3-TT (0.5-TT)
3, 7, 10, 14, 17, 21, 30, 34, 37, 41	E-UTRA Note 1	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
3, 7, 10, 14, 17, 21, 30, 34, 37 and 41	E-UTRA Note 2	0	1	Note 6	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
4, 6, 11, 13, 18, 20, 31, 33,38 and 40	NR Note 1, 3	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (7)	2 (3.5)	25+TT	3-TT (0.5-TT)
4, 6, 11, 13, 18, 20, 31, 33,38 and 40	NR Note 1,4	0	-	Note 5	9	9	0 (1.5)	14 (12.5)	5 (6)	2 (3.5)	25+TT	9-TT (6.5-TT)
4, 6, 11, 13, 18, 20, 31, 33,38 and 40	NR Note 2	0	-	Note 5	14	14	0 (1.5)	9 (7.5)	6 (6)	2 (3.5)	25+TT	3-TT (0.5-TT)

NOTE 1: When  $F_{IM3,low\_block,low} \geq 2490.5$  MHz (Case A)  
 NOTE 2: When  $F_{IM3,low\_block,low} < 2490.5$  MHz (Case B)  
 NOTE 3: When NR SCS = 15kHz.  
 NOTE 4: When NR SCS = 30 kHz or 60 kHz.  
 NOTE 5: NR A-MPR values for NS\_04 are defined in Table 6.2.3.3.2-1.  
 NOTE 6: E-UTRA A-MPR= 3 dB for 1 RB and  $f_c < 2517.5$  MHz, otherwise 0 dB.  
 NOTE 7:  $\Delta T_{C,c} = 1.5$  dB for transmission bandwidths confined within  $F_{UL,low}$  and  $F_{UL,low} + 4$  MHz or  $F_{UL,high} - 4$  MHz and  $F_{UL,high}$ , otherwise 0 dB.  
 NOTE 8: TT for each frequency and channel bandwidth is specified in Table 6.2B.3.2.5-2.

**Table 6.2B.3.2.5-2: Test Tolerance for UE maximum output power (LTE, NR TX seperately)**

Uplink TX		$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
LTE	<b>BW <math>\leq 20\text{MHz}</math></b>	0.7	1.0	1.3
NR	<b>BW <math>\leq 40\text{MHz}</math></b>	0.7 dB	1.0 dB	1.0
	<b><math>40\text{MHz} &lt; \text{BW} \leq 100\text{MHz}</math></b>	1.0 dB	1.0 dB	1.0

**6.2B.3.3 UE Additional Maximum Output Power reduction for Inter-Band EN-DC within FR1**

Editor’s note:

- Future optimization is possible by include this test case with corresponding ACLR test case
- The reason why minimum requirement doesn’t specify “sum of output power at each UE antenna connector”, as in corresponding MOP test case, needs to be understood.

#### 6.2B.3.3.1 Test purpose

Same test purpose as in clause 6.2.3.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.2B.3.3.2 Test applicability

The requirements of this test apply to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.2B.3.3.3 Minimum conformance requirements

For inter-band EN-DC between E-UTRA and FR1 NR, UE additional maximum output power reduction specified in TS 36.101 [5] and TS 38.101-1 [2] apply for E-UTRA and NR respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.3.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied

#### 6.2B.3.3.4 Test description

Same test description as in clause 6.2.3.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3 with E-UTRA channel bandwidth and test frequencies defined in Table 6.2B.3.3.4-1.
- 3.1. Downlink E-UTRA signals are initially set up according to TS 36.521-1 [10] Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0.
- 4.1. The E-UTRA UL Reference Measurement channels are set according to Table 6.2B.3.3.4-1.

Step 6 of Initial conditions as in clause 6.2.3.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.2.3.4.2 in TS 38.521-1 [8].

#### 6.2B.3.3.5 Test requirement

Same test requirement as in clause 6.2.2.5 in TS 38.521-1 [8].

#### 6.2B.3.4 UE Additional Maximum Output Power reduction for Inter-Band EN-DC including FR2

**Editor's Note: This test case is incomplete. Following aspects are missing or under discussion**

- **Measurement Uncertainties and Test Tolerances are FFS.**
- **This test is intended to be covered by Additional Spurious Emissions test case which is currently missing.**
- **Test configuration table in referenced TS38.521-2 test case is incomplete**
- **Test requirements in referenced TS38.521-2 test case is incomplete**

#### 6.2B.3.4.1 Test purpose

Same test purpose as in clause 6.2.3.1 in TS 38.521-2 [9] for the NR carrier.



## 6.2B.3.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

## 6.2B.3.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.2.2.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

## 6.2B.3.4.4 Test description

## 6.2B.3.4.4.1 Initial conditions

Same test description as in clause 6.2.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.2.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.2.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

## 6.2B.3.4.4.2 Test procedure

Same test procedure as in clause 6.2.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

## 6.2B.3.4.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6 with the following exceptions for each network signalled value.

1. Information element AdditionalSpectrumEmission for NR can be set in *nr-SecondaryCellGroupConfig* according to TS 36.331[15]. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario.

**Table 6.2B.3.4.4.3-1: AdditionalSpectrumEmission: Additional spurious emissions test requirement**

Derivation Path: TS 38.508-1 [5] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
AdditionalSpectrumEmission	1 (NS_201)	for band n258	

## 6.2B.3.4.5 Test requirement

Same test requirement as in clause 6.2.2.5 in TS 38.521-2 [9] for the NR carrier.

## 6.2B.3.5 UE Additional Maximum Output power reduction for inter-band EN-DC including both FR1 and FR2

## 6.2B.3.5.1 Test purpose

Same test purpose as in 6.2.3.1 in TS 38.521-1 [8] for NR FR1 carrier and 6.2.3.1 in TS 38.521-2 [9] for NR FR2 carrier.

### 6.2B.3.5.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 and E-UTRA in conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The NSA requirements for Additional Maximum Output Power apply and are tested as part of the EN-DC within FR1 and EN-DC including FR2 test cases in clause 6.2B.3.

## 6.2B.4 Configured Output Power for EN-DC

### 6.2B.4.1 Configured Output Power Level for EN-DC

#### 6.2B.4.1.0 Minimum Conformance Requirements

##### 6.2B.4.1.0.1 Configured output power level

##### 6.2B.4.1.0.1.1 Intra-band contiguous EN-DC

The following requirements apply for one component carrier per CG configured for synchronous DC.

For intra-band dual connectivity with one uplink serving cell per CG on E-UTRA and NR respectively, the UE is allowed to set its configured maximum output power  $P_{\text{CMAX},c(i),i}$  for serving cell  $c(i)$  of CG  $i$ ,  $i = 1, 2$ , and its total configured maximum transmission power for EN-DC operation  $\hat{P}_{\text{Total}}^{\text{EN-DC}}$ .

The configured maximum output power  $P_{\text{CMAX\_E-UTRA},c}(p)$  in sub-frame  $p$  for the configured E-UTRA uplink carrier shall be set within the bounds:

$$P_{\text{CMAX\_L\_E-UTRA},c}(p) \leq P_{\text{CMAX\_E-UTRA},c}(p) \leq P_{\text{CMAX\_H\_E-UTRA},c}(p)$$

where  $P_{\text{CMAX\_L\_E-UTRA},c}$  and  $P_{\text{CMAX\_H\_E-UTRA},c}$  are the limits for a serving cell  $c$  as specified in TS 36.101 [4] sub-clause 6.2.5 modified by  $P_{\text{LTE}}$  as follows:

$$P_{\text{CMAX\_L\_E-UTRA},c} = \text{MIN} \{ \text{MIN}(P_{\text{EMAX},c}, P_{\text{EMAX, EN-DC}}, P_{\text{LTE}}) - \Delta T_{\text{c\_E-UTRA},c}, (P_{\text{PowerClass}} - \Delta P_{\text{PowerClass}}) - \text{MAX}(M\text{PR}_c + \text{A-MPR}_c + \Delta T_{\text{IB},c} + \Delta T_{\text{c\_E-UTRA},c} + \Delta T_{\text{ProSe}}, P\text{-MPR}_c) \}$$

$$P_{\text{CMAX\_H\_E-UTRA},c} = \text{MIN} \{ P_{\text{EMAX},c}, P_{\text{EMAX, EN-DC}}, P_{\text{LTE}}, P_{\text{PowerClass}} - \Delta P_{\text{PowerClass}} \}$$

- for a UE indicating support of dynamicPowerSharing, the A-MPR<sub>c</sub> is determined in accordance with the DCI of serving cell  $c$  of the CG 1 and the specification in sub-clause 6.2.4 of [4];
- for a UE not indicating support of dynamicPowerSharing, the A-MPR<sub>c</sub> is determined in accordance with sub-clause 6.2B.3.1 with parameters applicable for UEs not indicating support of dynamicPowerSharing and MPR<sub>c</sub> = 0 dB;

The configured maximum output power  $P_{\text{CMAX\_NR},c}(q)$  in physical channel  $q$  for the configured NR carrier shall be set within the bounds:

$$P_{\text{CMAX\_L,f,c, NR}}(q) \leq P_{\text{CMAX,f,c, NR}}(q) \leq P_{\text{CMAX\_H,f,c, NR}}(q)$$

where  $P_{\text{CMAX\_L\_NR},c}$  and  $P_{\text{CMAX\_H\_NR},c}$  are the limits for a serving cell  $c$  as specified in sub-clause 6.2.4 of TS 38.101-1 [2] modified by  $P_{\text{NR}}$  as follows:

$$P_{\text{CMAX\_L,f,c, NR}} = \text{MIN} \{ \text{MIN}(P_{\text{EMAX},c}, P_{\text{EMAX, EN-DC}}, P_{\text{NR}}) - \Delta T_{\text{c\_NR},c}, (P_{\text{PowerClass}} - \Delta P_{\text{PowerClass}}) - \text{MAX}(M\text{PR}_c + \text{A-MPR}_c + \Delta T_{\text{IB},c} + \Delta T_{\text{c\_NR},c} + \Delta T_{\text{RxsRS}}, P\text{-MPR}_c) \}$$

$$P_{\text{CMAX\_H,f,c, NR}} = \text{MIN} \{ P_{\text{EMAX},c}, P_{\text{EMAX, EN-DC}}, P_{\text{NR}}, P_{\text{PowerClass}} - \Delta P_{\text{PowerClass}} \}$$

- $P_{\text{LTE}}$  and  $P_{\text{NR}}$  are the linear values for the  $P_{\text{LTE}}$  and  $P_{\text{NR}}$  respectively signalled by RRC defined in [7]
- $\Delta T_{\text{c\_E-UTRA},c} = 1.5\text{dB}$  when NOTE 2 in Table 6.2.2-1 in TS 36.101 [4] applies for a serving cell  $c$ , otherwise  $\Delta T_{\text{c\_E-UTRA},c} = 0\text{dB}$ ;

- $\Delta T_{c, NR, c} = 1.5\text{dB}$  when NOTE 3 in Table 6.2.1-1 in TS 38.101-1 [2] applies for a serving cell  $c$ , otherwise  $\Delta T_{c, NR, c} = 0\text{dB}$ ;
- $\Delta T_{IB, c}$  specified in sub-clause 6.2.7 for EN-DC, the individual Power Class defined in table 6.2B.1-3 and any other additional power reductions parameters specified in sub-clauses 6.2.3 and 6.2.4 for EN-DC are applicable to  $P_{CMAX\_E-UTRA, c}$  and  $P_{CMAX\_NR, c}$  evaluations.
- for a UE indicating support of dynamicPowerSharing,  $A\text{-MPR}_c = A\text{-MPR}'_c$  with  $A\text{-MPR}'_c$  determined in accordance with sub-clause 6.2B.3.1 and  $\text{MPR}_c = 0\text{ dB}$  if transmission(s) in subframe  $p$  on CG 1 overlap in time with physical channel  $q$  on CG 2;
- for a UE indicating support of dynamicPowerSharing,  $A\text{-MPR}_c$  is determined in accordance with [2] if transmission(s) in subframe  $p$  on CG 1 does not overlap in time with physical channel  $q$  on CG 2;
- for a UE not indicating support of dynamicPowerSharing, the  $A\text{-MPR}_c$  is determined in accordance with sub-clause 6.2B.3.1 with parameters applicable for UEs not indicating support of dynamicPowerSharing and  $\text{MPR}_c = 0\text{ dB}$ ;

If the transmissions from NR and E-UTRA do not overlap, then the complete sub-clauses for configured transmitted power for E-UTRA and NR respectively from their own specifications apply with the modifications specified above. The lower value between  $P_{\text{PowerClass, EN-DC}}$  or  $P_{\text{EMAX, EN-DC}}$  shall not be exceeded at any time by UE.

If the EN-DC UE is not supporting dynamic power sharing, then the complete sub-clauses for configured transmitted power for E-UTRA and NR respectively from their own specifications TS 36.101 [4] and TS 38.101-1 [2] respectively apply with the modifications specified above.

For UEs indicating support of dynamicPowerSharing in the *UE-MRDC-Capability* IE the UE can configure the total transmission power within the range

$$P_{\text{EN-DC, tot\_L}} \leq P_{\text{EN-DC, tot}} \leq P_{\text{EN-DC, tot\_H}}$$

where

$$P_{\text{EN-DC, tot\_L}}(p, q) = \text{MIN}\{P_{\text{PowerClass, EN-DC}} - A\text{-MPR}_{\text{tot}}, P_{\text{EMAX, EN-DC}}\}$$

$$P_{\text{EN-DC, tot\_H}}(p, q) = \text{MIN}\{P_{\text{PowerClass, EN-DC}}, P_{\text{EMAX, EN-DC}}\}$$

for sub-frame  $p$  on CG 1 overlapping with physical channel  $q$  on CG 2 and  $A\text{-MPR}_{\text{tot}}$  in accordance with sub-clause 6.2B.3.1.

The measured total maximum output power  $P_{\text{UMAX}}$  over both CGs/RATs, measured over the transmission reference time duration is

$$P_{\text{UMAX}} = 10 \log_{10} [p_{\text{UMAX, c, E-UTRA}} + p_{\text{UMAX, f, c, NR}}],$$

where  $p_{\text{UMAX, c, E-UTRA}}$  and  $p_{\text{UMAX, c, NR}}$  denotes the measured output power of serving cell  $c$  for E-UTRA and NR respectively, expressed in linear scale.

For UEs indicating support of dynamicPowerSharing, the measured total configured maximum output power  $P_{\text{UMAX}}$  shall be within the following bounds:

$$P_{\text{CMAX\_L}} - T_{\text{LOW}}(P_{\text{CMAX\_L}}) \leq P_{\text{UMAX}} \leq P_{\text{CMAX\_H}} + T_{\text{HIGH}}(P_{\text{CMAX\_H}})$$

with the tolerances  $T_{\text{LOW}}(P_{\text{CMAX\_L}})$  and  $T_{\text{HIGH}}(P_{\text{CMAX\_H}})$  for applicable values of  $P_{\text{CMAX\_L}}$  and  $P_{\text{CMAX\_H}}$  specified in Table 6.2B.4.1.0.1.1-2.

When an UL subframe transmission  $p$  from E-UTRA overlap with a physical channel  $q$  from the NR, then for  $P_{\text{UMAX}}$  evaluation, the E-UTRA subframe  $p$  is taken as reference period  $T_{\text{REF}}$  and always considered as the reference measurement duration and the following rules are applicable.

$T_{\text{REF}}$  and  $T_{\text{eval}}$  are specified in Table 6.2B.4.1.0.1.1-1 when same or different subframes and physical channel durations are used in aggregated carriers.  $P_{\text{PowerClass, EN-DC}}$  shall not be exceeded by the UE during any evaluation period of time.

**Table 6.2B.4.1.0.1.1-1: P<sub>CMAX</sub> evaluation window**

transmission duration	T <sub>REF</sub>	T <sub>eval</sub>
Different transmission duration in different RAT carriers	LTE Subframe	Min(T <sub>no_hopping</sub> , Physical Channel Length)

For each T<sub>REF</sub>, the P<sub>CMAX\_H</sub> is evaluated per T<sub>eval</sub> and given by the maximum value over the transmission(s) within the T<sub>eval</sub> as follows:

$$P_{CMAX\_H} = \text{MAX} \{ P_{CMAX\_EN-DC\_H}(p,q), P_{CMAX\_EN-DC\_H}(p,q+I), \dots, P_{CMAX\_EN-DC\_H}(p,q+n) \}$$

where P<sub>CMAX\_EN-DC\_H</sub> are the applicable upper limits for each overlapping scheduling unit pairs (p,q), (p, q+I), up to (p, q+n) for each applicable T<sub>eval</sub> duration, where q+n is the last NR UL physical channel overlapping with LTE subframe p.

While P<sub>CMAX\_L</sub> is computed as follows:

$$P_{CMAX\_L} = \text{MIN} \{ P_{CMAX\_EN-DC\_L}(p,q), P_{CMAX\_EN-DC\_L}(p,q+I), \dots, P_{CMAX\_EN-DC\_L}(p,q+n) \}$$

where P<sub>CMAX\_EN-DC\_L</sub> are the applicable lower limits for each overlapping scheduling unit pairs (p,q), (p, q+I), up to (p, q+n) for each applicable T<sub>eval</sub> duration, where q+n is the last NR UL physical channel overlapping with LTE subframe p.

With

$$P_{CMAX\_EN-DC\_H}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{CMAX\_H\_E-UTRA,c}(p) + p_{CMAX\_H,f,c,NR,c}(q)], P_{EMAX, EN-DC}, P_{PowerClass, EN-DC} \}$$

And:

$$a = 10 \log_{10} [p_{CMAX\_E-UTRA,c}(p) + p_{CMAX,f,c,NR}(q)] > P_{EN-DC,tot\_L}$$

$$b = 10 \log_{10} [p_{CMAX\_E-UTRA,c}(p) + p_{CMAX,f,c,NR}(q) / X\_scale] > P_{EN-DC,tot\_L}$$

If a= FALSE and the configured transmission power spectral density between the MCG and SCG differs by less than [6] dB

$$P_{CMAX\_EN-DC\_L}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{CMAX\_L\_E-UTRA,c}(p) + p_{CMAX\_L,f,c,NR,c}(q)], P_{EMAX, EN-DC}, P_{PowerClass, EN-DC} \}$$

ELSE If (a=TRUE) AND (b=FALSE) and the configured transmission power spectral density between the MCG and SCG differs by less than [6] dB

$$P_{CMAX\_EN-DC\_L}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{CMAX\_L\_E-UTRA,c}(p) + p_{CMAX\_L,f,c,NR,c}(q) / X\_scale ], P_{EMAX, EN-DC}, P_{PowerClass, EN-DC} \}$$

ELSE If b= TRUE or the configured transmission power spectral density between the MCG and SCG differs by more than [6] dB

$$P_{CMAX\_EN-DC\_L}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{CMAX\_L\_E-UTRA,c}(p) ], P_{EMAX, EN-DC}, P_{PowerClass, EN-DC} \}$$

where

- p<sub>CMAX\_H\_E-UTRA,c</sub>(p) is the E-UTRA higher limit of the maximum configured power expressed in linear scale;
- p<sub>CMAX\_H\_NR,c</sub>(q) is the NR higher limit of the maximum configured power expressed in linear scale;
- p<sub>CMAX\_L\_E-UTRA,c</sub>(p) is the E-UTRA lower limit of the maximum configured power expressed in linear scale;
- p<sub>CMAX\_L\_NR,c</sub>(q) is the NR lower limit of the maximum configured power expressed in linear scale;
- P<sub>PowerClass, EN-DC</sub> is defined in sub-clause 6.2B.1.1-1 for intra-band EN-DC;
- X<sub>scale</sub> is the linear value of X dB which is configured by RRC and can only take values [0, 6] dB
- p<sub>CMAX\_E-UTRA,c</sub>(p) is the linear value of P<sub>CMAX\_E-UTRA,c</sub>(p), the real configured max power for LTE
- p<sub>CMAX,f,c, NR</sub>(q) is the linear value of P<sub>CMAX,f,c, NR</sub>(q), the real configured max power of NR

**Table 6.2B.4.1.0.1.1-2: P<sub>CMAX</sub> tolerance for Dual Connectivity LTE-NR**

P <sub>CMAX</sub> (dBm)	Tolerance T <sub>LOW</sub> (P <sub>CMAX_L</sub> ) (dB)	Tolerance T <sub>HIGH</sub> (P <sub>CMAX_H</sub> ) (dB)
23 ≤ P <sub>CMAX</sub> ≤ 33	[3.0]	[2.0]
22 ≤ P <sub>CMAX</sub> < 23	[5.0]	[2.0]
21 ≤ P <sub>CMAX</sub> < 22	[5.0]	[3.0]
20 ≤ P <sub>CMAX</sub> < 21	[6.0]	[4.0]
16 ≤ P <sub>CMAX</sub> < 20		[5.0]
11 ≤ P <sub>CMAX</sub> < 16		[6.0]
-40 ≤ P <sub>CMAX</sub> < 11		[7.0]

If the UE supports dynamic power sharing, and when LTE and NR transmissions overlap and the condition (If (a=TRUE) AND (b=FALSE)) is met, SCG shall be transmitted and the following supplementary minimum requirement apply for the measured SCG power, P<sub>UMAX,f,c,NR</sub>(q), under nominal conditions and unless otherwise stated

$$10\log(p_{\text{CMAX}_{L,f,c,NR}(q)/X_{\text{scale}}}) - T_{\text{LOW}}(10\log(p_{\text{CMAX}_{L,f,c,NR}(q)/X_{\text{scale}}})) \leq P_{\text{UMAX},f,c,NR}(q) \leq P_{\text{UMAX},f,c,NR}(q) + T_{\text{HIGH}}(10\log(p_{\text{CMAX}_{H,f,c,NR}(q)}))$$

with the tolerances T<sub>LOW</sub> and T<sub>HIGH</sub> for applicable values of P<sub>CMAX</sub> specified in Table 6.2B.4.1.0.1.1-2.

If the UE supports dynamic power sharing, the measured maximum output power in subframe *p* on CG 1, p<sub>UMAX,c,E-UTRA</sub>, shall meet the requirements in subclause 6.2.5 in [4] with the limits P<sub>CMAX\_L,c</sub> and P<sub>CMAX\_H,c</sub> replaced by P<sub>CMAX\_L,E-UTRA,c</sub> and P<sub>CMAX\_H,E-UTRA,c</sub> as specified above, respectively.

If the configured transmission power spectral density between the MCG and SCG differs by more than [6] dB, then

$$P_{\text{UMAX},f,c,NR}(q) \leq 10\log(p_{\text{CMAX}_{H,f,c,NR}(q)}) + T_{\text{HIGH}}(10\log(p_{\text{CMAX}_{H,f,c,NR}(q)}))$$

#### 6.2B.4.1.0.1.2 Intra-band non-contiguous EN-DC

< equations for P<sub>cmx</sub> >

The following requirements apply for one component carrier per CG configured for synchronous DC. The CG(s) are indexed by *j* = 1 for MCG and *j* = 2 for SCG.

The configured maximum output power P<sub>CMAX\_E-UTRA,c</sub>(*p*) in sub-frame *p* for the configured E-UTRA uplink carrier shall be set in accordance with sub-clause 6.2B.4.1.0.1.1 but where

- for a UE not indicating support of dynamicPowerSharing, the A-MPR<sub>c</sub> determined in accordance with sub-clause 6.2B.3.2 with parameters applicable for UEs not indicating support of dynamicPowerSharing and MPR<sub>c</sub> = 0 dB;

The configured maximum output power P<sub>CMAX\_NR,c</sub>(*q*) in physical channel *q* for the configured NR carrier shall be set in accordance with sub-clause 6.2B.4.1.0.1.1 but where

- for a UE indicating support of dynamicPowerSharing, A-MPR<sub>c</sub> = A-MPR'<sub>c</sub> with A-MPR'<sub>c</sub> determined in accordance with sub-clause 6.2B.3.2 and MPR<sub>c</sub> = 0 dB if transmission(s) in subframe *p* on CG 1 overlap in time with physical channel *q* on CG 2;
- for a UE indicating support of dynamicPowerSharing, A-MPR<sub>c</sub> is determined in accordance with [2] if transmission(s) in subframe *p* on CG 1 does not overlap in time with physical channel *q* on CG 2;
- for a UE not indicating support of dynamicPowerSharing, the A-MPR<sub>c</sub> is determined in accordance with sub-clause 6.2B.3.2 with parameters applicable for UEs not indicating support of dynamicPowerSharing and MPR<sub>c</sub> = 0 dB;

For UEs indicating support of dynamicPowerSharing in the *UE-MRDC-Capability IE*, the UE can configure the total transmission power in accordance with sub-clause 6.2B.4.1.0.1.1 but with P<sub>powerclass,EN-DC</sub> the EN-DC power class of the intra-band non-contiguous band combination configured and A-MPR determined in accordance with sub-clause 6.2B.3.2.

The total maximum output power  $P_{UMAX}$  over both CGs is measured in accordance with sub-clause 6.2B.4.1.0.1.1 and shall be within the limits specified in sub-clause 6.2B.4.1.0.1.1 but with parameters applicable for the non-contiguous band combination configured.

*The maximum output power levels  $p_{UMAX,c,E-UTRA}$  and  $p_{UMAX,f,c,NR}$  for the CGs are measured in accordance with sub-clause 6.2B.4.1.0.1.1 and shall be within the limits specified in sub-clause 6.2B.4.1.0.1.1 but with parameters applicable for the non-contiguous band combination configured.*

### 6.2B.4.1.0.1.3 Inter-band EN-DC within FR1

For inter-band dual connectivity with one uplink serving cell per CG on E-UTRA and NR respectively, the UE is allowed to set its configured maximum output power  $P_{CMAX,c(i)}$  for serving cell  $c(i)$  of CG  $i$ ,  $i = 1,2$ , and its total configured maximum transmission power for EN-DC operation,  $\hat{P}_{Total}^{EN-DC}$ .

The configured maximum output power  $P_{CMAX\_E-UTRA,c}(p)$  in sub-frame  $p$  for the configured E-UTRA uplink carrier shall be set within the bounds:

$$P_{CMAX\_L\_E-UTRA,c}(p) \leq P_{CMAX\_E-UTRA,c}(p) \leq P_{CMAX\_H\_E-UTRA,c}(p)$$

where  $P_{CMAX\_L\_E-UTRA,c}$  and  $P_{CMAX\_H\_E-UTRA,c}$  are the limits for a serving cell  $c$  as specified in TS 36.101 [4] sub-clause 6.2.5 modified by  $P_{LTE}$  as follows:

$$P_{CMAX\_L\_E-UTRA,c} = \text{MIN} \{ P_{EMAX, EN-DC}, (P_{PowerClass, EN-DC} - \Delta P_{PowerClass}), \text{MIN}(P_{EMAX,c}, P_{LTE}) - \Delta T_{C\_E-UTRA,c}, (P_{PowerClass} - \Delta P_{PowerClass}) - \text{MAX}(MPR_c + A-MPR_c + \Delta T_{IB,c} + \Delta T_{C\_E-UTRA,c} + \Delta T_{ProSe}, P-MPR_c) \}$$

$$P_{CMAX\_H\_E-UTRA,c} = \text{MIN} \{ P_{EMAX,c}, P_{EMAX, EN-DC}, (P_{PowerClass, EN-DC} - \Delta P_{PowerClass}), P_{LTE}, P_{PowerClass} - \Delta P_{PowerClass} \}$$

The configured maximum output power  $P_{CMAX\_NR,c}(q)$  in physical-channel  $q$  for the configured NR carrier shall be set within the bounds:

$$P_{CMAX\_L,f,c,NR}(q) \leq P_{CMAX,f,c,NR}(q) \leq P_{CMAX\_H,f,c,NR}(q)$$

where  $P_{CMAX\_L\_NR,c}$  and  $P_{CMAX\_H\_NR,c}$  are the limits for a serving cell  $c$  as specified in sub-clause 6.2.4 of TS 38.101-1 [2] modified by  $P_{NR}$  as follows:

$$P_{CMAX\_L,f,c,NR} = \text{MIN} \{ P_{EMAX, EN-DC}, (P_{PowerClass, EN-DC} - \Delta P_{PowerClass}), \text{MIN}(P_{EMAX,c}, P_{NR}) - \Delta T_{C\_NR,c}, (P_{PowerClass} - \Delta P_{PowerClass}) - \text{MAX}(MPR_c + A-MPR_c + \Delta T_{IB,c} + \Delta T_{C\_NR,c} + \Delta T_{RxSRS}, P-MPR_c) \}$$

$$P_{CMAX\_H,f,c,NR} = \text{MIN} \{ P_{EMAX,c}, P_{EMAX, EN-DC}, (P_{PowerClass, EN-DC} - \Delta P_{PowerClass}), P_{NR}, P_{PowerClass} - \Delta P_{PowerClass} \}$$

- $P_{LTE}$  signalled by RRC as p-MaxEUTRA in [36.331]
- $P_{NR}$  signalled by RRC as p-NR-FR1 defined in [38.331]
- $\Delta T_{C\_E-UTRA,c} = 1.5\text{dB}$  when NOTE 2 in Table 6.2.2-1 in TS 36.101 [4] applies for a serving cell  $c$ , otherwise  $\Delta T_{C\_E-UTRA,c} = 0\text{dB}$ ;
- $\Delta T_{C\_NR,c} = 1.5\text{dB}$  when NOTE 3 in Table 6.2.1-1 in TS 38.101-1 [2] applies for a serving cell  $c$ , otherwise  $\Delta T_{C\_NR,c} = 0\text{dB}$ ;
- $\Delta T_{IB,c}$  specified in sub-clause 6.2.7 for EN-DC, the individual Power Class defined in table 6.2B.1-3 and any other additional power reductions parameters specified in sub-clauses 6.2.3 and 6.2.4 for EN-DC are applicable to  $P_{CMAX\_E-UTRA,c}$  and  $P_{CMAX\_NR,c}$  evaluations.

If the transmissions from NR and E-UTRA do not overlap, then the complete sub-clauses for configured transmitted power for E-UTRA and NR respectively from their own specifications apply with the modifications specified above. The lower value between  $P_{PowerClass, EN-DC}$  or  $P_{EMAX, EN-DC}$  shall not be exceeded at any time by UE.

The total configured maximum transmission power for both synchronous and non-synchronous operation is

$$P_{EN-DC\_Total} = \text{MIN} \{ P_{EMAX, EN-DC}, P_{PowerClass, EN-DC} - \Delta P_{PowerClass} \}$$

$P_{EN-DC\_Total}$  is the dB value of  $\hat{P}_{Total}^{EN-DC}$ , which is used in [38.213] and  $P_{EMAX, EN-DC}$  is p-maxUE-FR1-r15 value signalled by RRC and defined in [36.331];

If the UE does not support dynamic power sharing,

$$P_{\text{EN-DC\_Total}} = \text{MIN} \{ P_{\text{EMAX, EN-DC}}, P_{\text{PowerClass, EN-DC}} \} + 0.3 \text{ dB}$$

If the EN-DC UE does not support dynamic power sharing, then the complete sub-clauses for configured transmitted power for E-UTRA and NR respectively from their own specifications TS 36.101 [4] and TS 38.101-1 [2] respectively apply with the modifications specified above and  $P_{\text{EN-DC\_Total}}$  applies.

When a UE supporting dynamic sharing is configured for overlapping E-UTRA uplink and NR uplink transmissions, the UE can set its configured maximum output power  $P_{\text{CMAX\_E-UTRA},c}$  and  $P_{\text{CMAX\_NR},c}$  for the configured E-UTRA and NR uplink carriers, respectively, and its configured maximum transmission power for EN-DC operation,  $\hat{P}_{\text{Total}}^{\text{EN-DC}}$ , as specified above.

The measured total maximum output power  $P_{\text{UMAX}}$  over both CGs/RATs, measured over the transmission reference time duration is

$$P_{\text{UMAX}} = 10 \log_{10} [p_{\text{UMAX},c,E-UTRA} + p_{\text{UMAX},c,NR}],$$

where  $p_{\text{UMAX},c,E-UTRA}$  and  $p_{\text{UMAX},c,NR}$  denotes the measured output power of serving cell  $c$  for E-UTRA and NR respectively, expressed in linear scale.

The measured total configured maximum output power  $P_{\text{UMAX}}$  shall be within the following bounds:

$$P_{\text{CMAX\_L}} - T_{\text{LOW}}(P_{\text{CMAX\_L}}) \leq P_{\text{UMAX}} \leq P_{\text{CMAX\_H}} + T_{\text{HIGH}}(P_{\text{CMAX\_H}})$$

with the tolerances  $T_{\text{LOW}}(P_{\text{CMAX\_H}})$  and  $T_{\text{HIGH}}(P_{\text{CMAX\_H}})$  for applicable values of  $P_{\text{CMAX}}$  specified in Table 6.2B.4.1.0.1.3-2.

When an UL subframe transmission  $p$  from E-UTRA overlap with a physical-channel  $q$  from the NR, then for  $P_{\text{UMAX}}$  evaluation, the E-UTRA subframe  $p$  is taken as reference period  $T_{\text{REF}}$  and always considered as the reference measurement duration and the following rules are applicable.

$T_{\text{REF}}$  and  $T_{\text{eval}}$  are specified in Table 6.2B.4.1.0.1.3-1 when same or different subframe and physical-channel durations are used in aggregated carriers.  $P_{\text{PowerClass, EN-DC}}$  shall not be exceeded by the UE during any evaluation period of time.

**Table 6.2B.4.1.0.1.3-1:  $P_{\text{CMAX}}$  evaluation window**

transmission duration	$T_{\text{REF}}$	$T_{\text{eval}}$
Different transmission duration in different RAT carriers	LTE Subframe	Min( $T_{\text{no\_hopping}}$ , Physical Channel Length)

For each  $T_{\text{REF}}$ , the  $P_{\text{CMAX\_H}}$  is evaluated per  $T_{\text{eval}}$  and given by the maximum value over the transmission(s) within the  $T_{\text{eval}}$  as follows:

$$P_{\text{CMAX\_H}} = \text{MAX} \{ P_{\text{CMAX\_EN-DC\_H}}(p,q), P_{\text{CMAX\_EN-DC\_H}}(p,q+I), \dots, P_{\text{CMAX\_EN-DC\_H}}(p,q+n) \}$$

where  $P_{\text{CMAX\_EN-DC\_H}}$  are the applicable upper limits for each overlapping scheduling unit pairs  $(p,q)$ ,  $(p,q+I)$ , up to  $(p,q+n)$  for each applicable  $T_{\text{eval}}$  duration, where  $q+n$  is the last NR UL physical-channel overlapping with LTE subframe  $p$ .

While  $P_{\text{CMAX\_L}}$  is computed as follows:

$$P_{\text{CMAX\_L}} = \text{MIN} \{ P_{\text{CMAX\_EN-DC\_L}}(p,q), P_{\text{CMAX\_EN-DC\_L}}(p,q+I), \dots, P_{\text{CMAX\_EN-DC\_L}}(p,q+n) \}$$

where  $P_{\text{CMAX\_EN-DC\_L}}$  are the applicable lower limits for each overlapping scheduling unit pairs  $(p,q)$ ,  $(p,q+I)$ , up to  $(p,q+n)$  for each applicable  $T_{\text{eval}}$  duration, where  $q+n$  is the last NR UL physical-channel overlapping with LTE subframe  $p$ .

With

$$P_{\text{CMAX\_EN-DC\_H}}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{\text{CMAX\_H\_E-UTRA},c}(p) + p_{\text{CMAX\_H,f,c,NR},c}(q)], P_{\text{EMAX, EN-DC}}, P_{\text{PowerClass, EN-DC}} \}$$

And:

$$a = 10 \log_{10} [p_{\text{CMAX\_E-UTRA},c}(p) + p_{\text{CMAX,f,c,NR}}(q)] > P_{\text{EN-DC\_Total}}$$

$$b = 10 \log_{10} [p_{\text{CMAX\_E-UTRA},c}(p) + p_{\text{CMAX,f,c,NR}}(q) / X_{\text{scale}}] > P_{\text{EN-DC\_Total}}$$

If a= FALSE

$$P_{\text{CMAX\_EN-DC\_L}}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{\text{CMAX\_L\_E-UTRA},c}(p) + p_{\text{CMAX\_L,f,c, NR } c}(q)], P_{\text{EMAX, EN-DC}}, P_{\text{PowerClass, EN-DC}} \}$$

ELSE If (a=TRUE) AND (b=FALSE)

$$P_{\text{CMAX\_EN-DC\_L}}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{\text{CMAX\_L\_E-UTRA},c}(p) + p_{\text{CMAX\_L,f,c, NR } c}(q) / X_{\text{scale}} ], P_{\text{EMAX, EN-DC}}, P_{\text{PowerClass, EN-DC}} \}$$

ELSE If b= TRUE

$$P_{\text{CMAX\_EN-DC\_L}}(p,q) = \text{MIN} \{ 10 \log_{10} [p_{\text{CMAX\_L\_E-UTRA},c}(p) ], P_{\text{EMAX, EN-DC}}, P_{\text{PowerClass, EN-DC}} \}$$

where

- $p_{\text{CMAX\_H\_E-UTRA},c}(p)$  is the E-UTRA higher limit of the maximum configured power expressed in linear scale;
- $p_{\text{CMAX\_H\_NR},c}(q)$  is the NR higher limit of the maximum configured power expressed in linear scale;
- $p_{\text{CMAX\_L\_E-UTRA},c}(p)$  is the E-UTRA lower limit of the maximum configured power expressed in linear scale;
- $p_{\text{CMAX\_L\_NR},c}(q)$  is the NR lower limit of the maximum configured power expressed in linear scale;
- $P_{\text{PowerClass, EN-DC}}$  is defined in sub-clause 6.2B.1.3-1 for inter-band EN-DC;
- $X_{\text{scale}}$  is the linear value of X dB which is configured by RRC and can only take values [0 , 6]
- $p_{\text{CMAX\_E-UTRA},c}(p)$  is the linear value of  $P_{\text{CMAX\_E-UTRA},c}(p)$ , the real configured max power for LTE
- $p_{\text{CMAX,f,c, NR } c}(q)$  is the linear value of  $P_{\text{CMAX,f,c, NR } c}(q)$ , the real configured max power of NR

**Table 6.2B.4.1.0.1.3-2:  $P_{\text{CMAX}}$  tolerance for Dual Connectivity LTE-NR**

$P_{\text{CMAX}}(\text{dBm})$	Tolerance $T_{\text{LOW}}(P_{\text{CMAX\_L}})$ (dB)	Tolerance $T_{\text{HIGH}}(P_{\text{CMAX\_H}})$ (dB)
$23 \leq P_{\text{CMAX}} \leq 33$	[3.0]	[2.0]
$22 \leq P_{\text{CMAX}} < 23$	[5.0]	[2.0]
$21 \leq P_{\text{CMAX}} < 22$	[5.0]	[3.0]
$20 \leq P_{\text{CMAX}} < 21$	[6.0]	[4.0]
$16 \leq P_{\text{CMAX}} < 20$	[5.0]	
$11 \leq P_{\text{CMAX}} < 16$	[6.0]	
$-40 \leq P_{\text{CMAX}} < 11$	[7.0]	
NOTE 1: For UEs not indicating support of dynamic power sharing, the upper tolerance $T_{\text{high}}$ shall be reduced by 0.3 dB for $P \geq 20$ dBm.		

When LTE and NR transmissions overlap and the condition (If (a=TRUE) AND (b=FALSE)) is met, SCG shall be transmitted and the following supplementary minimum requirement apply for the measured SCG power,  $P_{\text{UMAX,f,c, NR } c}(q)$ , under nominal conditions.

$$10 \log(p_{\text{CMAX\_L,f,c, NR } c}(q) / X_{\text{scale}}) - T_{\text{LOW}}(10 \log(p_{\text{CMAX\_L,f,c, NR } c}(q) / X_{\text{scale}})) \leq P_{\text{UMAX,f,c, NR } c}(q) \leq 10 \log(p_{\text{CMAX\_H, f,c, NR } c}(q)) + T_{\text{HIGH}}(10 \log(p_{\text{CMAX\_H, f,c, NR } c}(q))).$$

with the tolerances  $T_{\text{LOW}}$  and  $T_{\text{HIGH}}$  for applicable values of  $P_{\text{CMAX}}$  specified in Table 6.2B.4.1.0.1.3-2.

#### 6.2B.4.1.0.1.4 Inter-band EN-DC including FR2

For inter-band dual connectivity with one uplink serving cell per CG on E-UTRA and NR respectively, with NR configured in FR2, the UE is allowed to set its configured maximum output power  $P_{\text{CMAX},c(i),i}$  for serving cell c(i) of CG i,  $i = 1, 2$ .

The UE maximum configured power  $P_{\text{CMAX},c(i)}$ , on E-UTRA for the subframe i shall be set according to subclause 6.2.5 from TS 36.101 [4]. Applicable inter-band  $\Delta T_{\text{IB},c}$  parameters shall be used according to the subclauses 6.2B.4.1.0.2.4 or 6.2B.4.1.0.2.5.



The UE maximum configured power  $PC_{MAX,c(j)}$ , on NR for the slot  $j$  shall be set according to subclause 6.2.4 from TS 38.101-2 [3].

For the configured power measurements TS 36.101 [4] subclause 6.2.5 and TS 38.101-2 [3] subclause 6.2.4 are applicable.

#### 6.2B.4.1.0.1.5 Inter-band EN-DC including both FR1 and FR2

< equations for  $P_{cmax}$  >

#### 6.2B.4.1.0.2 $\Delta T_{IB,c}$ for EN-DC

For the UE which supports inter-band EN-DC configuration,  $\Delta T_{IB,c}$  in Tables below applies where unless otherwise stated, the same  $\Delta T_{IB,c}$  is applicable to NR band(s) part for DC configurations which have the same NR operating band combination. Unless otherwise stated,  $\Delta T_{IB,c}$  is set to zero.

##### 6.2B.4.1.0.2.1 Intra-band contiguous EN-DC

$\Delta T_{IB,c}$  is not applicable for intra-band contiguous EN-DC.

##### 6.2B.4.1.0.2.2 Intra-band non-contiguous EN-DC

$\Delta T_{IB,c}$  is not applicable for intra-band non-contiguous EN-DC.

6.2B.4.1.0.2.3 Inter-band EN-DC within FR1

6.2B.4.1.0.2.3.1  $\Delta T_{IB,c}$  for EN-DC two bands

**Table 6.2B.4.1.0.2.3.1-1:  $\Delta T_{IB,c}$  due to EN-DC(two bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{B,c}$ (dB)
DC_1_n28		0.3
	n28	0.6
DC_1_n40	1	0.5
	n40	0.5
DC_1_n51	1	0.6
	n51	0.6
DC_1_n77	1	0.6
	n77	0.8
DC_1_n78	1	0.3
	n78	0.8
DC_2_n5	2	0.3
	n5	0.3
DC_2_n66	2	0.5
	n66	0.5
DC_2_n71	2	0.3
	n71	0.3
DC_2_n78	2	0.6
	n78	0.8
DC_3_n7	3	0.5
	n7	0.5
DC_3_n28	3	0.3
	n28	0.3
DC_3_n40	3	0.5
	n40	0.5
DC_3_n51	3	0.3
	n51	0.3
DC_3_n77	3	0.6
	n77	0.8
DC_3_n78	3	0.6
	n78	0.8
DC_5_n40	5	0.3
	n40	0.3
DC_5_n66	5	0.3
	n66	0.3
DC_5_n78	5	0.6
	n78	0.8
DC_7_n28	7	0.3
	n28	0.3
DC_7_n51	7	0.3
	n51	0.3
DC_7_n78	7	0.5
	n78	0.8
DC_8_n40	8	0.3
	n40	0.3
DC_8_n77	8	0.6
	n77	0.8
DC_8_n78	8	0.6
	n77	0.8
DC_11_n77	11	0.4
	n77	0.8
DC_11_n78	11	0.4
	n78	0.8
DC_12_n5	12	0.4
	n5	0.8
DC_12_n66	12	0.8
	n66	0.3
DC_18_n77	18	0.3
	n77	0.8
DC_18_n78	18	0.3
	n78	0.8
DC_19_n77	19	0.3
	n77	0.8
DC_19_n78	19	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{B,c}$ (dB)
	n78	0.8
DC_20_n8	20	0.4
	n8	0.4
DC_20_n28	20	0.5
	n28	0.5
DC_20_n51	20	0.5
	n51	0.5
DC_20_n77	20	0.6
	n77	0.8
DC_20_n78	20	0.6
	n78	0.8
DC_21_n77	21	0.4
	n77	0.8
DC_21_n78	21	0.4
	n78	0.8
	n77	0.8
DC_25_n41	25	0.5
	n41	0.3 <sup>1</sup>
		0.8 <sup>2</sup>
DC_26_n41	26	0.3
	n41	0.3
DC_26_n77	26	0.3
	n77	0.8
DC_26_n78	26	0.3
	n78	0.8
DC_28_n51	28	0.5
	n51	0.5
DC_28_n77	28	0.5
	n77	0.8
DC_28_n78	28	0.5
	n78	0.8
DC_30_n5	30	0.3
	n5	0.3
DC_30_n66	30	0.5
	n66	0.8
DC_38_n78	n78	0.5
DC_39_n78	39	0.3
	n78	0.8
DC_39_n79	39	0.3
	n79	0.8
DC_40_n77	n77	0.5
DC_41_n77	41	0.3
	n77	0.8
DC_41_n78	41	0.3
	n78	0.8
DC_41_n79	41	0.3
	n79	0.8
DC_42_n51	42	0.6
	n51	0.8
DC_66_n5	66	0.3
	n5	0.3
DC_66_n71	66	0.3
	n71	0.3
DC_66_n78	66	0.6
	n78	0.8

NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690MHz.  
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545MHz.

6.2B.4.1.0.2.3.2  $\Delta T_{IB,c}$  for EN-DC three bands

**Table 6.2B.4.1.0.2.3.2-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3_n28	1	0.3
	3	0.3
	n28	0.6
DC_1-3_n77	1	0.6
	3	0.6
	n77	0.8
DC_1-3_n78	1	0.6
	3	0.6
	n78	0.8
DC_1-3_n79	1	0.3
	3	0.3
DC_1-5_n78	1	0.3
	5	0.6
	n78	0.8
DC_1-7_n28	1	0.5
	7	0.6
	n28	0.6
DC_1-7_n78	1	0.6
	7	0.6
	n78	0.8
DC_1-7-7_n78	1	0.6
	7	0.6
	n78	0.8
DC_1-8_n78	1	0.3
	8	0.6
	n78	0.8
DC_1-1A_n77	1	0.3
	18	0.3
	n77	0.8
DC_1-18_n78	1	0.3
	18	0.3
	n78	0.8
DC_1-19_n77	1	0.3
	19	0.3
	n77	0.8
DC_1-19_n78	1	0.3
	19	0.3
	n78	0.8
DC_1-19_n79	1	0.3
	19	0.3
DC_1-20_n28	1	0.3
	20	0.6
	N28	0.6
DC_1-20_n78	1	0.3
	20	0.3
	n78	0.8
DC_1-21_n77	1	0.3
	21	0.3
	n77	0.8
DC_1-21_n78	1	0.6
	21	0.4
	n78	0.8
DC_1-21_n79	1	0.3
	21	0.3
DC_1-41_n77	1	0.5
	41	0.5
	n77	0.8
DC_1-41_n78	1	0.5
	41	0.5
	n78	0.8
DC_1-41_n79	1	0.5
	41	0.5
DC_1-28_n77	1	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	28	0.6
	n77	0.8
DC_1-28_n78	1	0.3
	28	0.6
	n78	0.8
DC_1_n28-n78	1	0.3
	n28	0.6
	n78	0.8
DC_1_n28-n79	1	0.3
	28	0.3
DC_1-42_n77	1	0.6
	42	0.8
	n77	0.8
DC_1-42_n78	1	0.3
	42	0.8
	n78	0.8
DC_1-42_n79	1	0.3
	42	0.8
DC_1_SUL_n78-n84	1	0.3
	n78	0.8
	n84	0.3
DC_1_n77-n79	1	0.6
	n77	0.8
	n79	0
DC_1_n78-n79	1	0.3
	n78	0.8
	n79	0.5
DC_2-(n)71	2	0.3
	71	0.3
	n71	
DC_2-5_n66	2	0.5
	5	0.3
	n66	0.5
DC_2-30_n66	2	0.5
	30	0.3
	n66	0.5
DC_2-66_n71	2	0.5
	66	0.5
	n71	0.3
DC_3_n3-n77	3	0.6
	n3	0.6
	n77	0.8
DC_3_n3-n78	3	0.6
	n3	0.6
	n78	0.8
DC_3-5_n78	3	0.6
	5	0.6
	n78	0.8
DC_3-7_n28	3	0.5
	7	0.5
	n28	0.3
DC_3-7_n78, DC_3-7-7_n78	3	0.6
	7	0.6
	n78	0.8
DC_3-8_n78	3	0.6
	8	0.6
	n78	0.8
DC_3-19_n77	3	0.6
	19	0.3
	n77	0.8
DC_3-19_n78	3	0.6
	19	0.3
	n78	0.8

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_3-19_n79	3	0.3
	19	0.3
DC_3-20_n28	3	0.3
	20	0.5
	n28	0.5
DC_3-20_n78	3	0.5
	20	0.3
	n78	0.8
DC_3-21_n77	3	0.8
	21	0.9
	n77	0.8
DC_3-21_n78	3	0.8
	21	0.9
	n78	0.8
DC_3-21_n79	3	0.8
	21	0.9
DC_3-28_n78	3	0.5
	28	0.3
	n78	0.8
DC_3_n28-n78	3	0.5
	n28	0.3
	n78	0.8
DC_3-38_n78	3	0.6
	n78	0.8
DC_3-41_n78	3	0.6
	41	0.3 <sup>1</sup>
	n78	0.8 <sup>2</sup>
DC_3-42_n77	3	0.6
	42	0.8
	n787	0.8
DC_3-42_n78	3	0.6
	42	0.8
	n78	0.8
DC_3-42_n79	3	0.6
	42	0.8
DC_3_n77-n79	3	0.6
	n77	0.8
	n79	0
DC_3_n78-n79	3	0.6
	n78	0.8
	n79	0.5
DC_3_SUL_n78-n80	3	0.6
	n78	0.8
	n80	0.6
DC_3_SUL_n78-n82	3	0.5
	n78	0.8
	n82	0.3
DC_5-7_n78, DC_5-7-7_n78	5	0.6
	7	0.6
	n78	0.8
DC_5_30_n66	5	0.3
	30	0.3
	n66	0.5
DC_7-7_n78	7	0.5
	n78	0.8
DC_7-20_n28	7	0.3
	20	0.6
	n28	0.6
DC_7-20_n78	7	0.3
	20	0.3
	n78	0.8
DC_7-28_n78	7	0.3



Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	28	0.3
	n78	0.8
DC_7_n28-n78	7	0.3
	n28	0.3
DC_7-46_n78	n78	0.8
	7	0.5
DC_8_SUL_n78- n81	n78	0.8
	n81	0.6
DC_18-28_n77	8	0.6
	18	0.5
DC_18-28_n78	28	0.5
	n77	0.8
DC_18-28_n79	18	0.5
	28	0.5
DC_18-28_n79	n78	0.8
	18	0.5
DC_19-21_n77	28	0.5
	19	0.3
DC_19-21_n78	21	0.4
	n77	0.8
DC_19-21_n79	19	0.3
	21	0.4
DC_19-42_n77	19	0.3
	21	0.4
DC_19-42_n78	n78	0.8
	19	0.3
DC_19-42_n79	42	0.8
	n77	0.8
DC_19-42_n79	19	0.3
	42	0.8
DC_19_n77-n79	19	0.3
	n77	0.8
DC_19_n78-n79	n79	0
	19	0.3
DC_20_n8-n75	n78	0.8
	n79	0.5
DC_20_n28-n75	20	0.4
	n8	0.4
DC_20_n28-n78	20	0.5
	n28	0.7
DC_20_n28-n78	20	0.6
	n28	0.6
DC_20_n75-n78	n78	0.8
	20	0.5
DC_20_n76-n78	n78	0.8
	20	0.5
DC_20_SUL_n78-n82	20	0.6
	n78	0.8
DC_20_SUL_n78-n83	n82	0.6
	20	0.8
DC_21-42_n77	n78	0.8
	n83	0.8
DC_21-42_n78	21	0.4
	42	0.8
DC_21-42_n78	n77	0.8
	21	0.4
DC_21-42_n78	42	0.8
	n78	0.8

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_21-42_n79	21	0.4
	42	0.8
DC_21_n77-n79	21	0.4
	n77	0.8
	n79	0
DC_21_n78-n79	21	0.4
	n78	0.8
	n79	0.5
DC_28-42_n77	28	0.5
	42	0.8
	n77	0.8
DC_28-42_n78	28	0.5
	42	0.8
	n78	0.8
DC_28-42_n79	28	0.5
	42	0.8
DC_28_SUL_n78-n83	28	0.5
	n78	0.8
	n83	0.5
DC_41-42_n77	41	0.5
	42	0.8
	n77	0.8
DC_41-42_n78	41	0.5
	42	0.8
	n78	0.8
DC_41-42_n79	41	0.
	42	0.8
DC_41_n77	41	0.3
	n77	0.8
DC_41_n78	41	0.3
	n78	0.8
DC_41_n79	41	0.3
	n79	0.8
DC_66_(n)71	66	0.3
	71	0.3
	n71	0.3
DC_66_SUL_n78-n86	66	0.6
	n78	0.8
	n86	0.6
NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690MHz.		
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545MHz.		

6.2B.4.1.0.2.3.3  $\Delta T_{IB,c}$  for EN-DC four bands

**Table 6.2B.4.1.0.2.3.3-1:  $\Delta T_{IB,c}$  due to EN-DC(four bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-5_n78	1	0.6
	3	0.6
	5	0.3
	n78	0.8
DC_1-3-7_n28	1	0.6
	3	0.6
	7	0.6
	n28	0.6
DC_1-3-7_n78 DC_1-3-7-7_n78	1	0.7
	3	0.7
	7	0.7
	n78	0.8
DC_1-3-8_n78	1	0.6
	3	0.6
	8	0.6
	n78	0.8
DC_1-3-28_n77	1	0.6
	3	0.6
	28	0.6
	n77	0.8
DC_1-3-28_n78	1	0.6
	3	0.6
	28	0.6
	n78	0.8
DC_1-3_n28-n78	1	0.6
	3	0.6
	n28	0.6
	n78	0.8
DC_1-3-28_n79	1	0.6
	3	0.6
	28	0.6
DC_1-3-19_n78	1	0.6
	3	0.6
	19	0.3
	n78	0.8
DC_1-3-19_n79	1	0.3
	3	0.3
	19	0.3
DC_1-3-20_n28	1	0.3
	3	0.3
	20	0.6
	n28	0.6
DC_1-3-20_n78	1	0.6
	3	0.6
	20	0.3
	n78	0.8
DC_1-3-21_n77	1	0.6
	3	0.8
	21	0.9
	n77	0.8
DC_1-3-21_n78	1	0.6
	3	0.8
	21	0.9
	n78	0.8
DC_1-3-21_n79	1	0.3
	3	0.8
	21	0.9
DC_1-3-42_n77	1	0.6
	3	0.6
	42	0.8
	n77	0.8
DC_1-3-42_n78	1	0.6
	3	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	42	0.8
	n78	0.8
DC_1-3-42_n79	1	0.6
	3	0.6
	42	0.8
DC_1-5-7_n78 DC_1-5-7-7_n78	1	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_1-7-20_n28	1	0.5
	7	0.6
	20	0.6
	n28	0.6
DC_1-7-20_n78	1	0.6
	7	0.7
	20	0.4
	n78	0.8
DC_1-7_n28-n78	1	0.6
	7	0.6
	n28	0.6
	n78	0.8
DC_1-18-28_n77	1	0.3
	18	0.5
	28	0.5
	n77	0.8
DC_1-18-28_n78	1	0.3
	18	0.5
	28	0.5
	n78	0.8
DC_1-18-28_n79	1	0.3
	18	0.5
	28	0.5
DC_1-19-42_n77	1	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_1-19-42_n78	1	0.3
	19	0.3
	42	0.8
	n78	0.8
DC_1-19-42_n79	1	0.3
	19	0.3
	42	0.8
DC_1-20_n28-n78	1	0.3
	20	0.6
	n28	0.6
	n78	0.8
DC_1-21-28_n77	1	0.6
	21	0.4
	28	0.6
	n77	0.8
DC_1-21-28_n78	1	0.3
	21	0.4
	28	0.6
	n78	0.8
DC_1-21-28_n79	1	0.3
	21	0.4
	28	0.6
DC_1-21-42_n77	1	0.6
	21	0.4
	42	0.8
	n77	0.8
DC_1-21-42_n78	1	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	21	0.4
	42	0.8
	n78	0.8
DC_1-21-42_n79	1	0.3
	21	0.4
	42	0.8
DC_1-28-42_n77	1	0.6
	28	0.6
	42	0.8
	n77	0.8
DC_1-28-42_n78	1	0.3
	28	0.6
	42	0.8
	n78	0.8
DC_1-28-42_n79	1	0.3
	28	0.6
	42	0.8
DC_1-41-42_n77	1	0.5
	41	0.5
	42	0.8
	n77	0.8
DC_1-41-42_n78	1	0.5
	41	0.5
	42	0.8
	n78	0.8
DC_1-41-42_n79	1	0.5
	41	0.5
	42	0.8
DC_2-66-(n)71	2	0.5
	66	0.5
	71	0.3
	n71	
DC_3-5-7_n78, DC_3-5-7-7_n78	3	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_3-7-20_n28	3	0.5
	7	0.5
	20	0.6
	n28	0.5
DC_3-7-20_n78	3	0.6
	7	0.6
	20	0.3
	n78	0.8
DC_3-7-28_n78	3	0.6
	7	0.6
	28	0.6
	n78	0.8
DC_3-7_n28-n78	3	0.6
	7	0.6
	n28	0.6
	n78	0.8
DC_3-19-21_n77	3	0.8
	19	0.3
	21	0.9
	n77	0.8
DC_3-19-21_n78	3	0.8
	19	0.3
	21	0.9
	n78	0.8
DC_3-19-21_n79	3	0.8
	19	0.3
	21	0.9

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_3-19-42_n77	3	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_3-19-42_n78	3	0.6
	19	0.3
	42	0.8
	n78	0.8
DC_3-19-42_n79	3	0.6
	19	0.3
	42	0.8
DC_3-20_n28-n78	3	0.6
	20	0.6
	n28	0.6
	n78	0.8
DC_3-28-42_n77	3	0.6
	28	0.5
	42	0.8
	n77	0.8
DC_3-28-42_n78	3	0.6
	28	0.5
	42	0.8
	n78	0.8
DC_3-28-42_n79	3	0.6
	28	0.5
	42	0.8
DC_3-21-42_n77	3	0.8
	21	0.9
	42	0.8
	n77	0.8
DC_3-21-42_n78	3	0.8
	21	0.9
	42	0.8
	n78	0.8
DC_3-21-42_n79	3	0.8
	21	0.9
	42	0.8
DC_7-20_n28-n78	7	0.3
	20	0.6
	n28	0.6
	n78	0.8
DC_19-21-42_n77	19	0.3
	21	0.4
	42	0.8
	n77	0.8
DC_19-21-42_n78	19	0.3
	21	0.4
	42	0.8
	n78	0.8
DC_19-21-42_n79	19	0.3
	21	0.4
	42	0.8
DC_21-28-42_n77	21	0.4
	28	0.5
	42	0.8
	n77	0.8
DC_21-28-42_n78	21	0.4
	28	0.5
	42	0.8
	n78	0.8
DC_21-28-42_n79	21	0.4
	28	0.5
	42	0.8

6.2B.4.1.0.2.3.4  $\Delta T_{IB,c}$  for EN-DC five bands

**Table 6.2B.4.1.0.2.3.4-1:  $\Delta T_{IB,c}$  due to EN-DC (five bands)**



Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-5-7_n78, DC_1-3-5-7-7_n78	1	0.6
	3	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_1-3-7-20_n28	1	0.6
	3	0.6
	7	0.6
	20	0.6
	n28	0.6
DC_1-3-7-20_n78	1	0.6
	3	0.6
	7	0.6
	20	0.6
	n78	0.6
DC_1-3-7_n28-n78	1	0.7
	3	0.7
	7	0.7
	n28	0.6
	n78	0.8
DC_1-3-19-21_n77	1	0.6
	3	0.8
	19	0.3
	21	0.9
	n77	0.8
DC_1-3-19-21_n78	1	0.6
	3	0.8
	19	0.3
	21	0.9
	n78	0.8
DC_1-3-19-21_n79	1	0.3
	3	0.8
	19	0.3
	21	0.9
DC_1-3-19-42_n77	1	0.6
	3	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_1-3-19-42_n78	1	0.6
	3	0.6
	19	0.3
	42	0.8
	n78	0.8
DC_1-3-19-42_n79	1	0.6
	3	0.6
	19	0.3
	42	0.8
DC_1-3-20_n28-n78	1	0.6
	3	0.6
	20	0.6
	n28	0.6
	n78	0.8
DC_1-3-21-42_n77	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n77	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-21-42_n78	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n78	0.6
DC_1-3-21-42_n79	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n79	0
DC_1-3-28-42_n77	1	0.6
	3	0.6
	28	0.6
	42	0.8
	n77	0.8
DC_1-3-28-42_n78	1	0.6
	3	0.6
	28	0.6
	42	0.8
	n78	0.8
DC_1-3-28-42_n79	1	0.6
	3	0.6
	28	0.6
	42	0.8
DC_1-7-20_n28-n78	1	0.6
	7	0.7
	20	0.6
	n28	0.6
	n78	0.8
DC_1-19-21-42_n77	1	0.3
	19	0.3
	21	0.4
	42	0.8
	n77	0.8
DC_1-19-21-42_n78	1	0.3
	19	0.3
	21	0.4
	42	0.8
	n78	0.8
DC_1-19-21-42_n79	1	0.3
	19	0.3
	21	0.4
	42	0.8
DC_1-21-28-42_n77	1	0.6
	21	0.4
	28	0.6
	42	0.8
	n77	0.8
DC_1-21-28-42_n78	1	0.3
	21	0.4
	28	0.6
	42	0.8
	n78	0.8
DC_1-21-28-42_n79	1	0.3
	21	0.4
	28	0.6
	42	0.8
DC_3-7-20_n28-n78	3	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	7	0.6
	20	0.6
	n28	0.6
	n78	0.8

6.2B.4.1.0.2.3.5  $\Delta T_{IB,c}$  for EN-DC six bands

**Table 6.2B.4.1.0.2.3.5-1:  $\Delta T_{IB,c}$  due to EN-DC (six bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-7-20_n28-n78	1	0.7
	3	0.7
	7	0.7
	20	0.6
	n28	0.6
	n78	0.8

6.2B.4.1.0.2.4 Inter-band EN-DC including FR2

6.2B.4.1.0.2.4.1  $\Delta T_{IB,c}$  for EN-DC two bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for E-UTRA and FR2 NR bands of inter-band EN-DC combinations defined in table 5.2B.5.1-1 is set to zero.

**Table 6.2B.4.1.0.2.4.1-1:  $\Delta T_{IB,c}$  due to EN-DC(two bands)**

FFS

6.2B.4.1.0.2.4.2  $\Delta T_{IB,c}$  for EN-DC three bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.2-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.1.0.2.4.2-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)**

FFS

6.2B.4.1.0.2.4.3  $\Delta T_{IB,c}$  for EN-DC four bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.3-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.1.0.2.4.3-1:  $\Delta T_{IB,c}$  due to EN-DC(four bands)**

FFS

6.2B.4.1.0.2.4.4  $\Delta T_{IB,c}$  for EN-DC five bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.4-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.1.0.2.4.4-1:  $\Delta T_{IB,c}$  due to EN-DC (five bands)****FFS**6.2B.4.1.0.2.4.5  $\Delta T_{IB,c}$  for EN-DC six bands

FFS

6.2B.4.1.0.2.5 Inter-band EN-DC including both FR1 and FR2

6.2B.4.1.0.2.5.1  $\Delta T_{IB,c}$  for EN-DC three bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.5B.6.2-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.1.0.2.3.

**Table 6.2B.4.1.0.2.5.1-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)****FFS**6.2B.4.1.0.2.5.2  $\Delta T_{IB,c}$  for EN-DC four bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.5B.6.3-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.1.0.2.3.

6.2B.4.1.0.2.5.3  $\Delta T_{IB,c}$  for EN-DC five bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.5B.6.4-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.1.0.2.3.

6.2B.4.1.0.2.5.4  $\Delta T_{IB,c}$  for EN-DC six bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.5B.6.5-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.1.0.2.3.

**6.2B.4.1.1 Configured Output Power Level for Intra-Band Contiguous EN-DC**

**Editor's note: The following aspects are either missing or not yet determined:**

- Test description is FFS.

- MU and TT are FFS.

6.2B.4.1.1.1 Test purpose

**Editor's Note: Explanatory test is needed.**

6.2B.4.1.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

6.2B.4.1.1.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 6.2B.4.1.0.1.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

6.2B.4.1.1.4 Test description

6.2B.4.1.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.2B.4.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.4.1.1.4.1-1: Test configurations table for intra-band contiguous EN-DC**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [5] subclause 4.1		Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies as specified in TS 38.508-1 [5] subclause 4.3.1 E-UTRA Test Frequencies as specified in TS 36.508-1 [11] subclause 4.3.1		Mid range			
Test EN-DC bandwidth combination as specified in TS 38.508-1 [5] subclause 4.3.1		Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]		Highest supported SCS			
NR/E-UTRA Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A for Configured	QPSK	Outer_Full	CP-OFDM QPSK	Outer_Full
2	transmitted power testing.	QPSK	Table 6.2B.4.1.1.4.1-2	DFT-s-OFDM QPSK	Inner Full
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].					
NOTE 2: Outer_Full defined as the transmission bandwidth configuration $N_{RB}$ per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1.					

**Table 6.2B.4.1.1.4.1-2: RB allocation table for LTE carrier**

LTE Ch BW	RB allocation
5MHz	8@0
10MHz	12@0
15MHz	16@0
20MHz	18@0

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.

4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.4.1.1.4.3.

6.2B.4.1.1.4.2 Test procedure

FFS

6.2B.4.1.1.4.3 Message contents

FFS

6.2B.4.1.1.5 Test requirement

FFS

#### 6.2B.4.1.2 Configured Output Power for Intra-Band Non-Contiguous EN-DC

**Editor's note: The following aspects are either missing or not yet determined:**

- Test description is FFS.

- MU and TT are FFS.

6.2B.4.1.2.1 Test purpose

**Editor's Note: Explanatory test is needed.**

6.2B.4.1.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

6.2B.4.1.2.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 6.2B.4.1.0.1.2.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

6.2B.4.1.2.4 Test description

6.2B.4.1.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.2B.4.1.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.4.1.2.4.1-1: Test configurations table for intra-band contiguous EN-DC**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [5] subclause 4.1		Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies and E-UTRA Test Frequencies as specified in TS 38.508-1 [5] subclause 4.3.1.		Refer to test points A: Maximum Wgap			
Test EN-DC bandwidth combination as specified in TS 38.508-1 [5] subclause 4.3.1		Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]		Highest supported SCS			
NR/E-UTRA Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A	QPSK	Outer_Full	CP-OFDM QPSK	Outer_Full
2		QPSK	Table 6.2B.4.1.2.4.1-2	DFT-s-OFDM QPSK	Inner Full
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8]. NOTE 2: Outer_Full defined as the transmission bandwidth configuration NRB per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1.					

**Table 6.2B.4.1.2.4.1-2: RB allocation table for LTE carrier**

LTE Ch BW	RB allocation
5MHz	8@0
10MHz	12@0
15MHz	16@0
20MHz	18@0

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.4.1.2.4.3.

6.2B.4.1.2.5 Test requirement

FFS

6.2B.4.1.3 Configured Output Power for Inter-Band EN-DC within FR1

**Editor's note: The following aspects are either missing or not yet determined:**

- Minimum requirements are pending RAN4.
- Test description is not complete.

6.2B.4.1.3.1 Test purpose

Editor’s Note: Explanatory test is needed.

6.2B.4.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

6.2B.4.1.3.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 6.2B.4.1.0.1.3.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

6.2B.4.1.3.4 Test description

6.2B.4.1.3.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.2B.4.1.3.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.2B.4.1.3.4.1-1: Test configurations table for intra-band contiguous EN-DC**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [5] subclause 4.1		Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies as specified in TS 38.508-1 [5] subclause 4.3.1		Mid range			
E-UTRA Test Frequencies as specified in TS 36.508-1 [11] subclause 4.3.1					
Test EN-DC bandwidth combination as specified in TS 38.508-1 [5] subclause 4.3.1		Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]		Highest supported SCS			
NR/E-UTRA Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation	Modulation	RB allocation (NOTE 1)
1	N/A for Configured transmitted power testing.	QPSK	Table 6.2B.4.1.3.4.1-2	DFT-s-OFDM QPSK	Inner Full
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].					



Table 6.2B.4.1.3.4.1-2: RB allocation table for LTE carrier

LTE Ch BW	RB allocation
5MHz	8@0
10MHz	12@0
15MHz	16@0
20MHz	18@0

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.4.1.3.4.3.

6.2B.4.1.3.5 Test requirement

FFS

6.2B.4.1.4 Configured Output Power for Inter-Band EN-DC including FR2

**Editor's note: The following aspects are either missing or not yet determined:**

- Minimum requirements are pending RAN4.
- Test description is FFS.
- MU and TT are FFS.

6.2B.4.1.4.1 Test purpose

**Editor's Note: Explanatory test is needed.**

6.2B.4.1.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

6.2B.4.1.4.3 Minimum conformance requirements

FFS

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.4.1.4.

6.2B.4.1.4.4 Test description

FFS

6.2B.4.1.4.5 Test requirement

FFS

#### 6.2B.4.1.5 Configured Output Power for Inter-Band EN-DC including both FR1 and FR2

Editor's note: The following aspects are either missing or not yet determined:

- Minimum requirements are pending RAN4.
- Test description is FFS.
- MU and TT are FFS.

##### 6.2B.4.1.5.1 Test purpose

Editor's Note: Explanatory test is needed.

##### 6.2B.4.1.5.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including both FR1 and FR2.

##### 6.2B.4.1.5.3 Minimum conformance requirements

FFS

The normative reference for this requirement is TS 38.101-3 [4] clause 6.2B.4.1.5.

##### 6.2B.4.1.5.4 Test description

FFS

##### 6.2B.4.1.5.5 Test requirement

FFS

#### 6.2B.4.2 $\Delta T_{IB,c}$ for EN-DC

For the UE which supports inter-band EN-DC configuration,  $\Delta T_{IB,c}$  in Tables below applies where unless otherwise stated, the same  $\Delta T_{IB,c}$  is applicable to NR band(s) part for DC configurations which have the same NR operating band combination. Unless otherwise stated,  $\Delta T_{IB,c}$  is set to zero.

##### 6.2B.4.2.1 Intra-Band Contiguous EN-DC

$\Delta T_{IB,c}$  is not applicable for intra-band contiguous EN-DC.

##### 6.2B.4.2.2 Intra-Band non-Contiguous EN-DC

$\Delta T_{IB,c}$  is not applicable for intra-band non-contiguous EN-DC.

6.2B.4.2.3 Inter-Band EN-DC within FR1

6.2B.4.2.3.1  $\Delta T_{IB,c}$  for EN-DC two bands

**Table 6.2B.4.2.3.1-1:  $\Delta T_{IB,c}$  due to EN-DC(two bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{B,c}$ (dB)
DC_1_n28	1	0.3
	n28	0.6
DC_1_n40	1	0.5
	n40	0.5
DC_1_n51	1	0.6
	n51	0.6
DC_1_n77	1	0.6
	n77	0.8
DC_1_n78	1	0.3
	n78	0.8
DC_2_n5	2	0.3
	n5	0.3
DC_2_n66	2	0.5
	n66	0.5
DC_2_n71	2	0.3
	n71	0.3
DC_2_n78	2	0.6
	n78	0.8
DC_3_n7	3	0.5
	n7	0.5
DC_3_n28	3	0.3
	n28	0.3
DC_3_n40	3	0.5
	n40	0.5
DC_3_n51	3	0.3
	n51	0.3
DC_3_n77	3	0.6
	n77	0.8
DC_3_n78	3	0.6
	n78	0.8
DC_5_n40	5	0.3
	n40	0.3
DC_5_n66	5	0.3
	n66	0.3
DC_5_n78	5	0.6
	n78	0.8
DC_7_n28	7	0.3
	n28	0.3
DC_7_n51	7	0.3
	n51	0.3
DC_7_n78	7	0.5
	n78	0.8
DC_8_n40	8	0.3
	n40	0.3
DC_8_n77	8	0.6
	n77	0.8
DC_8_n78	8	0.6
	n77	0.8
DC_11_n77	11	0.4
	n77	0.8
DC_11_n78	11	0.4
	n78	0.8
DC_12_n5	12	0.4
	n5	0.8
DC_12_n66	12	0.8
	n66	0.3
DC_18_n77	18	0.3
	n77	0.8
DC_18_n78	18	0.3
	n78	0.8
DC_19_n77	19	0.3
	n77	0.8
DC_19_n78	19	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{B,c}$ (dB)
	n78	0.8
DC_20_n8	20	0.4
	n8	0.4
DC_20_n28	20	0.5
	n28	0.5
DC_20_n51	20	0.5
	n51	0.5
DC_20_n77	20	0.6
	n77	0.8
DC_20_n78	20	0.6
	n78	0.8
DC_21_n77	21	0.4
	n77	0.8
DC_21_n78	21	0.4
	n78	0.8
	n77	0.8
DC_25_n41	25	0.5
	n41	0.4 <sup>1</sup>
		0.9 <sup>2</sup>
DC_26_n41	26	0.3
	n41	0.3
DC_26_n77	26	0.3
	n77	0.8
DC_26_n78	26	0.3
	n78	0.8
DC_28_n51	28	0.5
	n51	0.5
DC_28_n77	28	0.5
	n77	0.8
DC_28_n78	28	0.5
	n78	0.8
DC_30_n5	30	0.3
	n5	0.3
DC_30_n66	30	0.5
	n66	0.8
DC_38_n78	n78	0.5
DC_39_n78	39	0.3
	n78	0.8
DC_39_n79	39	0.3
	n79	0.8
DC_40_n77	n77	0.5
DC_41_n77	41	0.3
	n77	0.8
DC_41_n78	41	0.3
	n78	0.8
DC_41_n79	41	0.3
	n79	0.8
DC_42_n51	42	0.6
	n51	0.8
DC_66_n5	66	0.3
	n5	0.3
DC_66_n71	66	0.3
	n71	0.3
DC_66_n78	66	0.6
	n78	0.8

NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690 MHz.  
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545 MHz.

6.2B.4.2.3.2  $\Delta T_{IB,c}$  for EN-DC three bands

**Table 6.2B.4.2.3.2-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3_n28	1	0.3
	3	0.3
	n28	0.6
DC_1-3_n77	1	0.6
	3	0.6
	n77	0.8
DC_1-3_n78	1	0.6
	3	0.6
	n78	0.8
DC_1-3_n79	1	0.3
	3	0.3
DC_1-5_n78	1	0.3
	5	0.6
	n78	0.8
DC_1-7_n28	1	0.5
	7	0.6
	n28	0.6
DC_1-7_n78	1	0.6
	7	0.6
	n78	0.8
DC_1-7-7_n78	1	0.6
	7	0.6
	n78	0.8
DC_1-8_n78	1	0.3
	8	0.6
	n78	0.8
DC_1-18_n77	1	0.3
	18	0.3
	n77	0.8
DC_1-18_n78	1	0.3
	18	0.3
	n78	0.8
DC_1-19_n77	1	0.3
	19	0.3
	n77	0.8
DC_1-19_n78	1	0.3
	19	0.3
	n78	0.8
DC_1-19_n79	1	0.3
	19	0.3
DC_1-20_n28	1	0.3
	20	0.6
	n28	0.6
DC_1-20_n78	1	0.3
	20	0.3
	n78	0.8
DC_1-21_n77	1	0.3
	21	0.3
	n77	0.8
DC_1-21_n78	1	0.6
	21	0.4
	n78	0.8
DC_1-21_n79	1	0.3
	21	0.3
DC_1-41_n77	1	0.5
	41	0.5
	n77	0.8
DC_1-41_n78	1	0.5
	41	0.5
	n78	0.8
DC_1-41_n79	1	0.5
	41	0.5
DC_1-28_n77	1	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	28	0.6
	n77	0.8
DC_1-28_n78	1	0.3
	28	0.6
	n78	0.8
DC_1_n28-n78	1	0.3
	n28	0.6
	n78	0.8
DC_1_n28-n79	1	0.3
	n28	0.3
DC_1-42_n77	1	0.6
	42	0.8
	n77	0.8
DC_1-42_n78	1	0.3
	42	0.8
	n78	0.8
DC_1-42_n79	1	0.3
	42	0.8
DC_1_SUL_n78-n84	1	0.3
	n78	0.8
	n84	0.3
DC_1_n77-n79	1	0.6
	n77	0.8
	n79	0
DC_1_n78-n79	1	0.3
	n78	0.8
	n79	0.5
DC_2-(n)71	2	0.3
	71	0.3
	n71	
DC_2-5_n66	2	0.5
	5	0.3
	n66	0.5
DC_2-30_n66	2	0.5
	30	0.3
	n66	0.5
DC_2-66_n71	2	0.5
	66	0.5
	n71	0.3
DC_3_n3-n77	3	0.6
	n3	0.6
	n77	0.8
DC_3_n3-n78	3	0.6
	n3	0.6
	n78	0.8
DC_3-5_n78	3	0.6
	5	0.6
	n78	0.8
DC_3-7_n28	3	0.5
	7	0.5
	n28	0.3
DC_3-7_n78, DC_3-7-7_n78	3	0.6
	7	0.6
	n78	0.8
DC_3-8_n78	3	0.6
	8	0.6
	n78	0.8
DC_3-19_n77	3	0.6
	19	0.3
	n77	0.8
DC_3-19_n78	3	0.6
	19	0.3
	n78	0.8



Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_3-19_n79	3	0.3
	19	0.3
DC_3-20_n28	3	0.3
	20	0.5
DC_3-20_n78	n28	0.5
	3	0.5
	20	0.3
DC_3-21_n77	n78	0.8
	3	0.8
	21	0.9
DC_3-21_n78	n77	0.8
	3	0.8
	21	0.9
DC_3-21_n79	n78	0.8
	3	0.8
	21	0.9
DC_3-28_n78	3	0.5
	28	0.3
	n78	0.8
DC_3_n28-n78	3	0.5
	n28	0.3
	n78	0.8
DC_3-38_n78	3	0.6
	n78	0.8
DC_3-41_n78	3	0.6
	41	0.3 <sup>1</sup>
	n78	0.8 <sup>2</sup>
DC_3-42_n77	n78	0.8
	3	0.6
	42	0.8
DC_3-42_n78	n77	0.8
	3	0.6
	42	0.8
DC_3-42_n79	n78	0.8
	3	0.6
	42	0.8
DC_3_n77-n79	3	0.6
	n77	0.8
	n79	0
DC_3_n78-n79	3	0.6
	n78	0.8
	n79	0.5
DC_3_SUL_n78-n80	3	0.6
	n78	0.8
	n80	0.6
DC_3_SUL_n78-n82	3	0.5
	n78	0.8
	n82	0.3
DC_5-7_n78, DC_5-7-7_n78	5	0.6
	7	0.6
	n78	0.8
DC_5-30_n66	5	0.3
	30	0.3
	n66	0.5
DC_7-7_n78	7	0.5
	n78	0.8
DC_7-20_n28	7	0.3
	20	0.6
	n28	0.6
DC_7-20_n78	7	0.3
	20	0.3
	n78	0.8
DC_7-28_n78	7	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	28	0.3
	n78	0.8
DC_7_n28-n78	7	0.3
	n28	0.3
DC_7-46_n78	n78	0.8
	7	0.5
DC_8_SUL_n78- n81	n78	0.8
	8	0.6
DC_18-28_n77	n78	0.8
	18	0.5
DC_18-28_n78	28	0.5
	n78	0.8
DC_18-28_n79	18	0.5
	28	0.5
DC_19-21_n77	19	0.3
	21	0.4
DC_19-21_n78	n77	0.8
	19	0.3
DC_19-21_n79	21	0.4
	19	0.3
DC_19-42_n77	19	0.3
	42	0.8
DC_19-42_n78	n77	0.8
	19	0.3
DC_19-42_n79	42	0.8
	n78	0.8
DC_19_n77-n79	19	0.3
	n77	0.8
DC_19_n78-n79	n79	0
	19	0.3
DC_20_n8-n75	n78	0.8
	n79	0.5
DC_20_n28-n75	20	0.4
	n8	0.4
DC_20_n28-n78	20	0.5
	n28	0.7
DC_20_n75-n78	20	0.6
	n28	0.6
DC_20_n76-n78	n78	0.8
	20	0.5
DC_20_SUL_n78-n82	20	0.6
	n78	0.8
DC_20_SUL_n78-n83	n82	0.6
	20	0.8
DC_21-42_n77	n78	0.8
	n83	0.8
DC_21-42_n78	21	0.4
	42	0.8
	n77	0.8
	21	0.4
	42	0.8
	n78	0.8

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_21-42_n79	21	0.4
	42	0.8
DC_21_n77-n79	21	0.4
	n77	0.8
	n79	0
DC_21_n78-n79	21	0.4
	n78	0.8
	n79	0.5
DC_28-42_n77	28	0.5
	42	0.8
	n77	0.8
DC_28-42_n78	28	0.5
	42	0.8
	n78	0.8
DC_28-42_n79	28	0.5
	42	0.8
DC_28_SUL_n78-n83	28	0.5
	n78	0.8
	n83	0.5
DC_41-42_n77	41	0.5
	42	0.8
	n77	0.8
DC_41-42_n78	41	0.5
	42	0.8
	n78	0.8
DC_41-42_n79	41	0.
	42	0.8
DC_41_n77	41	0.3
	n77	0.8
DC_41_n78	41	0.3
	n78	0.8
DC_41_n79	41	0.3
	n79	0.8
DC_66_(n)71	66	0.3
	71	0.3
	n71	0.3
DC_66_SUL_n78-n86	66	0.6
	n78	0.8
	n86	0.6
NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690 MHz.		
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545 MHz.		

6.2B.4.2.3.3  $\Delta T_{IB,c}$  for EN-DC four bands

**Table 6.2B.4.2.3.3-1:  $\Delta T_{IB,c}$  due to EN-DC(four bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-5_n78	1	0.6
	3	0.6
	5	0.3
	n78	0.8
DC_1-3-7_n28	1	0.6
	3	0.6
	7	0.6
	n28	0.6
DC_1-3-7_n78 DC_1-3-7-7_n78	1	0.7
	3	0.7
	7	0.7
	n78	0.8
DC_1-3-8_n78	1	0.6
	3	0.6
	8	0.6
	n78	0.8
DC_1-3-28_n77	1	0.6
	3	0.6
	28	0.6
	n77	0.8
DC_1-3-28_n78	1	0.6
	3	0.6
	28	0.6
	n78	0.8
DC_1-3_n28-n78	1	0.6
	3	0.6
	n28	0.6
	n78	0.8
DC_1-3-28_n79	1	0.6
	3	0.6
	28	0.6
DC_1-3-19_n78	1	0.6
	3	0.6
	19	0.3
	n78	0.8
DC_1-3-19_n79	1	0.3
	3	0.3
	19	0.3
DC_1-3-20_n28	1	0.3
	3	0.3
	20	0.6
	n28	0.6
DC_1-3-20_n78	1	0.6
	3	0.6
	20	0.3
	n78	0.8
DC_1-3-21_n77	1	0.6
	3	0.8
	21	0.9
	n77	0.8
DC_1-3-21_n78	1	0.6
	3	0.8
	21	0.9
	n78	0.8
DC_1-3-21_n79	1	0.3
	3	0.8
	21	0.9
DC_1-3-42_n77	1	0.6
	3	0.6
	42	0.8
	n77	0.8
DC_1-3-42_n78	1	0.6
	3	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	42	0.8
	n78	0.8
DC_1-3-42_n79	1	0.6
	3	0.6
	42	0.8
DC_1-5-7_n78 DC_1-5-7-7_n78	1	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_1-7-20_n28	1	0.5
	7	0.6
	20	0.6
	n28	0.6
DC_1-7-20_n78	1	0.6
	7	0.7
	20	0.4
	n78	0.8
DC_1-7_n28-n78	1	0.6
	7	0.6
	n28	0.6
	n78	0.8
DC_1-18-28_n77	1	0.3
	18	0.5
	28	0.5
	n77	0.8
DC_1-18-28_n78	1	0.3
	18	0.5
	28	0.5
	n78	0.8
DC_1-18-28_n79	1	0.3
	18	0.5
	28	0.5
DC_1-19-42_n77	1	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_1-19-42_n78	1	0.3
	19	0.3
	42	0.8
	n78	0.8
DC_1-19-42_n79	1	0.3
	19	0.3
	42	0.8
DC_1-20_n28-n78	1	0.3
	20	0.6
	n28	0.6
	n78	0.8
DC_1-21-28_n77	1	0.6
	21	0.4
	28	0.6
	n77	0.8
DC_1-21-28_n78	1	0.3
	21	0.4
	28	0.6
	n78	0.8
DC_1-21-28_n79	1	0.3
	21	0.4
	28	0.6
DC_1-21-42_n77	1	0.6
	21	0.4
	42	0.8
	n77	0.8
DC_1-21-42_n78	1	0.3

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	21	0.4
	42	0.8
	n78	0.8
DC_1-21-42_n79	1	0.3
	21	0.4
	42	0.8
DC_1-28-42_n77	1	0.6
	28	0.6
	42	0.8
	n77	0.8
DC_1-28-42_n78	1	0.3
	28	0.6
	42	0.8
	n78	0.8
DC_1-28-42_n79	1	0.3
	28	0.6
	42	0.8
DC_1-41-42_n77	1	0.5
	41	0.5
	42	0.8
	n77	0.8
DC_1-41-42_n78	1	0.5
	41	0.5
	42	0.8
	n78	0.8
DC_1-41-42_n79	1	0.5
	41	0.5
	42	0.8
DC_2-66-(n)71	2	0.5
	66	0.5
	71	0.3
	n71	
DC_3-5-7_n78 DC_3-5-7-7_n78	3	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_3-7-20_n28	3	0.5
	7	0.5
	20	0.6
	n28	0.5
DC_3-7-20_n78	3	0.6
	7	0.6
	20	0.3
	n78	0.8
DC_3-7-28_n78	3	0.6
	7	0.6
	28	0.6
	n78	0.8
DC_3-7_n28-n78	3	0.6
	7	0.6
	n28	0.6
	n78	0.8
DC_3-19-21_n77	3	0.8
	19	0.3
	21	0.9
	n77	0.8
DC_3-19-21_n78	3	0.8
	19	0.3
	21	0.9
	n78	0.8
DC_3-19-21_n79	3	0.8
	19	0.3
	21	0.9

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_3-19-42_n77	3	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_3-19-42_n78	3	0.6
	19	0.3
	42	0.8
	n78	0.8
DC_3-19-42_n79	3	0.6
	19	0.3
	42	0.8
DC_3-20_n28-n78	3	0.6
	20	0.6
	n28	0.6
	n78	0.8
DC_3-28-42_n77	3	0.6
	28	0.5
	42	0.8
	n77	0.8
DC_3-28-42_n78	3	0.6
	28	0.5
	42	0.8
	n78	0.8
DC_3-28-42_n79	3	0.6
	28	0.5
	42	0.8
DC_3-21-42_n77	3	0.8
	21	0.9
	42	0.8
	n77	0.8
DC_3-21-42_n78	3	0.8
	21	0.9
	42	0.8
	n78	0.8
DC_3-21-42_n79	3	0.8
	21	0.9
	42	0.8
DC_7-20_n28-n78	7	0.3
	20	0.6
	n28	0.6
	n78	0.8
DC_19-21-42_n77	19	0.3
	21	0.4
	42	0.8
	n77	0.8
DC_19-21-42_n78	19	0.3
	21	0.4
	42	0.8
	n78	0.8
DC_19-21-42_n79	19	0.3
	21	0.4
	42	0.8
DC_21-28-42_n77	21	0.4
	28	0.5
	42	0.8
	n77	0.8
DC_21-28-42_n78	21	0.4
	28	0.5
	42	0.8
	n78	0.8
DC_21-28-42_n79	21	0.4
	28	0.5
	42	0.8



6.2B.4.2.3.4  $\Delta T_{IB,c}$  for EN-DC five bands

**Table 6.2B.4.2.3.4-1:  $\Delta T_{IB,c}$  due to EN-DC (five bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-5-7_n78, DC_1-3-5-7-7_n78	1	0.6
	3	0.6
	5	0.6
	7	0.6
	n78	0.8
DC_1-3-7-20_n28	1	0.6
	3	0.6
	7	0.6
	20	0.6
	n28	0.6
DC_1-3-7-20_n78	1	0.6
	3	0.6
	7	0.6
	20	0.6
	n78	0.6
DC_1-3-7_n28-n78	1	0.7
	3	0.7
	7	0.7
	n28	0.6
	n78	0.8
DC_1-3-19-21_n77	1	0.6
	3	0.8
	19	0.3
	21	0.9
	n77	0.8
DC_1-3-19-21_n78	1	0.6
	3	0.8
	19	0.3
	21	0.9
	n78	0.8
DC_1-3-19-21_n79	1	0.3
	3	0.8
	19	0.3
	21	0.9
DC_1-3-19-42_n77	1	0.6
	3	0.6
	19	0.3
	42	0.8
	n77	0.8
DC_1-3-19-42_n78	1	0.6
	3	0.6
	19	0.3
	42	0.8
	n78	0.8
DC_1-3-19-42_n79	1	0.6
	3	0.6
	19	0.3
	42	0.8
DC_1-3-20_n28-n78	1	0.6
	3	0.6
	20	0.6
	n28	0.6
	n78	0.8
DC_1-3-21-42_n77	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n77	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-21-42_n78	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n78	0.6
DC_1-3-21-42_n79	1	0.6
	3	0.8
	21	0.9
	42	0.8
	n79	0
DC_1-3-28-42_n77	1	0.6
	3	0.6
	28	0.6
	42	0.8
	n77	0.8
DC_1-3-28-42_n78	1	0.6
	3	0.6
	28	0.6
	42	0.8
	n78	0.8
DC_1-3-28-42_n79	1	0.6
	3	0.6
	28	0.6
	42	0.8
DC_1-7-20_n28-n78	1	0.6
	7	0.7
	20	0.6
	n28	0.6
	n78	0.8
DC_1-19-21-42_n77	1	0.3
	19	0.3
	21	0.4
	42	0.8
	n77	0.8
DC_1-19-21-42_n78	1	0.3
	19	0.3
	21	0.4
	42	0.8
	n78	0.8
DC_1-19-21-42_n79	1	0.3
	19	0.3
	21	0.4
	42	0.8
DC_1-21-28-42_n77	1	0.6
	21	0.4
	28	0.6
	42	0.8
	n77	0.8
DC_1-21-28-42_n78	1	0.3
	21	0.4
	28	0.6
	42	0.8
	n78	0.8
DC_1-21-28-42_n79	1	0.3
	21	0.4
	28	0.6
	42	0.8
DC_3-7-20_n28-n78	3	0.6

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
	7	0.6
	20	0.6
	n28	0.6
	n78	0.8

6.2B.4.2.3.5  $\Delta T_{IB,c}$  for EN-DC six bands**Table 6.2B.4.2.3.5-1:  $\Delta T_{IB,c}$  due to EN-DC (six bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta T_{IB,c}$ (dB)
DC_1-3-7-20_n28-n78	1	0.7
	3	0.7
	7	0.7
	20	0.6
	n28	0.6
	n78	0.8

## 6.2B.4.2.4 Inter-band EN-DC including FR2

6.2B.4.2.4.1  $\Delta T_{IB,c}$  for EN-DC two bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for E-UTRA and FR2 NR bands of inter-band EN-DC combinations defined in table 5.2B.5.1-1 is set to zero.

**Table 6.2B.4.2.4.1-1:  $\Delta T_{IB,c}$  due to EN-DC(two bands)**

FFS

6.2B.4.2.4.2  $\Delta T_{IB,c}$  for EN-DC three bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.2-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.2.4.2-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)**

FFS

6.2B.4.2.4.3  $\Delta T_{IB,c}$  for EN-DC four bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.3-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.2.4.3-1:  $\Delta T_{IB,c}$  due to EN-DC(four bands)**

FFS

6.2B.4.2.4.4  $\Delta T_{IB,c}$  for EN-DC five bands

Unless otherwise stated,  $\Delta T_{IB,c}$  for FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA bands for inter-band EN-DC defined in table 5.2B.5.4-1 is the same as those for the corresponding E-UTRA CA configuration specified in TS 36.101 [4], without the FR2 NR bands.

**Table 6.2B.4.2.4.4-1:  $\Delta T_{IB,c}$  due to EN-DC (five bands)**

FFS

6.2B.4.2.4.5  $\Delta T_{IB,c}$  for EN-DC six bands**Table 6.2B.4.2.4.5-1:  $\Delta T_{IB,c}$  due to EN-DC (six bands)**

Void

6.2B.4.2.5 Inter-band EN-DC including both FR1 and FR2

6.2B.4.2.5.1  $\Delta T_{IB,c}$  for EN-DC three bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.2B.6.2-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.2.3.

**Table 6.2B.4.2.5.1-1:  $\Delta T_{IB,c}$  due to EN-DC (three bands)**

FFS

6.2B.4.2.5.2  $\Delta T_{IB,c}$  for EN-DC four bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.2B.6.3-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.2.3.

6.2B.4.2.5.3  $\Delta T_{IB,c}$  for EN-DC five bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.2B.6.4-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.2.3.

6.2B.4.2.5.4  $\Delta T_{IB,c}$  for EN-DC six bands

Unless otherwise stated, for inter-band EN-DC configurations defined in table 5.2B.6.5-1,  $\Delta T_{IB,c}$  for constituent FR2 NR bands is set to zero, and  $\Delta T_{IB,c}$  for constituent E-UTRA and FR1 NR bands is the same as those for the corresponding inter band EN-DC configuration without the FR2 bands specified in 6.2B.4.2.3.

## 6.3 Output power dynamics

### 6.3B

#### 6.3B.1 Minimum Output Power for EN-DC

##### 6.3B.1.1 Minimum Output Power for intra-band contiguous EN-DC

Editor's note: The following aspects are either missing or not yet determined:

- Measurement uncertainty and TT is FFS.

Working assumption: E-UTRA is not tested during test procedure

## 6.3B.1.1.1 Test purpose

Same test purpose as in clause 6.3.1.1 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.1.1.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

## 6.3B.1.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

## 6.3B.1.1.4 Test description

Same test descriptions as in clause 6.3.1.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

**Table 6.3B.1.1.4-1: Test configuration table**

E-UTRA Test Parameters				
E-UTRA Channel Bandwidth	E-UTRA Test Frequency	Downlink	Uplink	
		N/A for min output power test	Modulation	RB allocation
5 MHz	MidRange		QPSK	25
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [11] subclause 4.3.1				

For Initial conditions as in clause 6.3.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS36.508 [11] subclause 4.4.3 with E-UTRA channel bandwidth and test frequencies defined in Table 6.3B.1.1.4-1.
- 3.1. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0.
- 4.1. The UL Reference Measurement channels are set according to Table 6.3B.1.1.4-1.

Step 6 of Initial conditions as in clause 6.3.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.1.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1. For E-UTRA component, SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to table 6.3B.1.1.4-1. Since the UE has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
- 2.1. For E-UTRA component, send continuously uplink power control "down" commands in every uplink scheduling information to the UE.

## 6.3B.1.1.5 Test requirements

Same test requirement as in clause 6.3.1.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.1.2 Minimum output power for intra-band non-contiguous EN-DC

**Editor's note: The following aspects are either missing or not yet determined:**

- Minimum requirement are pending RAN4.
- Initial condition is not complete.

- Message contents are not complete.

- The test tolerance is not complete.

#### 6.3B.1.2.1 Test purpose

Same test purpose as in clause 6.3.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.1.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

#### 6.3B.1.2.3 Minimum conformance requirements

FFS

The normative reference for this requirement is TS 38.101-1 [2] clause 6.3.

#### 6.3B.1.2.4 Test description

##### 6.3B.1.2.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table [TBD]. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.3B.1.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexes [TBD]. Configurations of PDSCH and PDCCH before measurement are specified in Annexes [TBD].

**Table 6.3B.1.2.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC, TL/VL, TL/VH, TH/VL, TH/VH			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		TBD			
Test CC Combinations setting ( $N_{RB\_agg}$ ) as specified in TS 38.508-1 [6] subclause 4.3.1		TBD			
Test SCS for the NR cell as specified in TS 38.508-1 [8] Table 5.3.5-1		TBD			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation	Modulation	RB allocation (Note 1)
1	N/A for min output power test	TBD	TBD	TBD	TBD
2		TBD	TBD		
3		TBD	TBD		
4		TBD	TBD		
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1.					

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the cell are set up according to [TBD].
3. Downlink signals are initially set up according to [TBD], and uplink signals according to [TBD].

4. The UL Reference Measurement channels are [TBD].
5. Propagation conditions are set according to [Annex B.0].
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.3B.1.2.4.3.

#### 6.3B.1.2.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to table 6.3B.1.2.4.1-1 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "down" commands to the UE for NR and E-UTRA carrier in every uplink scheduling information to the UE; allow at least 200ms to ensure that the UE transmits at its minimum output power.
3. Measure the mean power of the UE in the associated measurement bandwidth specified in Table 6.3B.1.2.5-1 for the specific channel bandwidth under test in the EN-DC. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

#### 6.3B.1.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 6.3B.1.2.5 Test requirements

FFS

### 6.3B.1.3 Minimum output power for inter-band EN-DC within FR1

#### 6.3B.1.3.1 Test purpose

Same test purpose as in clause 6.3.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.3B.1.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.3B.1.3.4 Test description

Same test descriptions as in clause 6.3.1.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

**Table 6.3B.1.3.4-1: Test configuration table**

E-UTRA Test Parameters				
E-UTRA Channel Bandwidth	E-UTRA Test Frequency	Downlink	Uplink	
		N/A for min output power test	Modulation	RB allocation
5 MHz	MidRange		QPSK	25
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [11] subclause 4.3.1				



For Initial conditions as in clause 6.3.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS36.508 [11] subclause 4.4.3 with E-UTRA channel bandwidth and test frequencies defined in Table 6.3B.1.3.4-1.
- 3.1. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0.
- 4.1. The UL Reference Measurement channels are set according to Table 6.3B.1.3.4-1.

Step 6 of Initial conditions as in clause 6.3.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.1.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1. For E-UTRA component, SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to table 6.3B.1.3.4-1. Since the UE has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
- 2.1. For E-UTRA component, send continuously uplink power control "down" commands in every uplink scheduling information to the UE.

#### 6.3B.1.3.5 Test requirements

Same test requirement as in clause 6.3.1.5 in TS 38.521-1 [8] for the NR carrier.

### 6.3B.1.4 Minimum Output Power for EN-DC Interband including FR2

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- The referred test case 6.3.1 in TS 38.521-2 is incomplete.
- Measurement Uncertainty and Test Tolerances are FFS.
- Measurement period is pending RAN4.
- The following aspects of the clause are for future consideration:
  - Testing of extreme conditions for FR2 is FFS.

#### 6.3B.1.4.1 Test purpose

Same test purpose as in clause 6.3.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.3B.1.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.3B.1.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 subclause 6.3B.1.

#### 6.3B.1.4.4 Test description

Same test description as in clause 6.3.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For initial conditions as in clause 6.3.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of initial conditions as in clause 6.3.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.3B.1.4.5 Test requirements

Same test requirement as in clause 6.3.1.5 in TS 38.521-2 [9] for the NR carrier.

## 6.3B.2 Transmit OFF Power for EN-DC

### 6.3B.2.1 Transmit OFF Power for intra-band contiguous EN-DC

**Editor's note: The following aspects are either missing or not yet determined:**

- Measurement uncertainty and TT is FFS.
- Initial condition & test procedure depends on Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC, this test case is incomplete now

**Editor's note: Working assumption: E-UTRA is not tested during test procedure**

#### 6.3B.2.1.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.2.1.2 Test applicability

The requirements of this test apply in Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.3B.2.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.3B.2.1.4 Test description

This test is covered by Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC.

#### 6.3B.2.1.5 Test requirements

Same test requirement as in clause 6.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.2.2 Transmit OFF Power for intra-band non-contiguous EN-DC

*Editor's note: The following aspects are either missing or not yet determined:*

- *Measurement uncertainty and TT is FFS.*
- *Initial condition & test procedure depends on Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC, this test case is incomplete now*

*Editor's note: Working assumption: E-UTRA is not tested during test procedure*

### 6.3B.2.2.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-1 [8] for the NR carrier.

### 6.3B.2.2.2 Test applicability

The requirements of this test apply in Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 6.3B.2.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

### 6.3B.2.2.4 Test description

This test is covered by Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC.

### 6.3B.2.2.5 Test requirements

Same test requirement as in clause 6.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.2.3 Transmit OFF Power for inter-band EN-DC within FR1

*Editor's note: The following aspects are either missing or not yet determined:*

- *Initial condition & test procedure depends on Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC, this test case is incomplete now*

*Editor's note: Working assumption: E-UTRA is not tested during test procedure*

### 6.3B.2.3.1 Test purpose

Same test purpose as in clause 6.3.2.1 in TS 38.521-1 [8] for the NR carrier.

### 6.3B.2.3.2 Test applicability

The requirements of this test apply in Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

### 6.3B.2.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.2.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

### 6.3B.2.3.4 Test description

This test is covered by Clause 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC.

### 6.3B.2.3.5 Test requirements

Same test requirement as in clause 6.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.3 Tx ON/OFF time mask/PUCCH time mask for EN-DC

### 6.3B.3.1 Tx ON/OFF time mask for intra-band contiguous EN-DC

#### 6.3B.3.1.1 Test purpose

Same test purpose as in clause 6.3.3.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.3.1.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.3B.3.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.2.3 in TS 38.521-1 [8] for the NR carrier.

No exception requirements applicable to NR or LTE . LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

#### 6.3B.3.1.4 Test description

Same test descriptions as in clause 6.3.3.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

2.1. The parameter settings for the E-UTRA cell are set up according to TS36.508 [11] subclause 4.4.3.

3.1. The E-UTRA Downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.3.2.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

1.1. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

### 6.3B.3.1.5 Test requirements

Same test requirement as in clause 6.3.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.3.2 Tx ON/OFF time mask for intra-band non-contiguous EN-DC

### 6.3B.3.2.1 Test purpose

Same test purpose as in clause 6.3.3.2.1 in TS 38.521-1 [8] for the NR carrier.

### 6.3B.3.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 6.3B.3.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.2.3 in TS 38.521-1 [8] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

### 6.3B.3.2.4 Test description

Same test descriptions as in clause 6.3.3.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA Downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.3.2.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

### 6.3B.3.2.5 Test requirements

Same test requirement as in clause 6.3.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.3.3 Tx ON/OFF time mask for inter-band EN-DC within FR1

### 6.3B.3.3.1 Test purpose

Same test purpose as in clause 6.3.3.2.1 in TS 38.521-1 [8] for the NR carrier.

### 6.3B.3.3.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

### 6.3B.3.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.2.3 in TS 38.521-1 [8] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

### 6.3B.3.3.4 Test description

Same test descriptions as in clause 6.3.3.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the E-UTRA cell are set up according to TS36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA Downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.3.3.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.3.3.2.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

### 6.3B.3.3.5 Test requirements

Same test requirement as in clause 6.3.3.2.5 in TS 38.521-1 [8] for the NR carrier.

## 6.3B.4 PRACH time mask for EN-DC

### 6.3B.4.1 PRACH time mask for intra-band contiguous EN-DC

#### 6.3B.4.1.1 Test purpose

Same test purpose as in clause 6.3.3.4.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.4.1.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.3B.4.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.4.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.3B.4.1.4 Test description

Same test description as in clause 6.3.3.4.4 in TS 38.521-1 [8] with the following exception:

**Table 6.3B.4.1.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1 for different DC bandwidth classes.	Mid range
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest NRB_agg (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg , only the combination with the highest NRB_SCG is tested	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 6.3B.4.1.4-1.

For Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 5 of Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8] is replaced by:

5. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.3.3.4.4.2 in TS 38.521-1 [8] for E-UTRA carrier with the following exception:

3. The SS measure the UE transmission OFF power during the slot preceding the PRACH preamble excluding a transient period of 10  $\mu$ s according to Table 4.6.3-129 in TS 38.508 [6].
4. Measure the output power of the transmitted PRACH preamble according to Table 4.6.3-129 in TS 38.508 [6].

#### 6.3B.4.1.5 Test requirements

Same test requirement as in clause 6.3.3.4.5 in TS 38.521-1 [8].

### 6.3B.4.2 PRACH Time Mask for intra-band non-contiguous EN-DC

#### 6.3B.4.2.1 Test purpose

Same test purpose as in clause 6.3.3.4.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.4.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

#### 6.3B.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.4.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.3B.4.2.4 Test description

Same test description as in clause 6.3.3.4.4 in TS 38.521-1 [8] with the following exception:

**Table 6.3B.4.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS36TS38.508-1 [76] subclause 4.3.1 for different EN-DC bandwidth classes	[MaxWGap]
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest NRB_agg (NOTE1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg , only the combination with the highest NRB_SCG is tested	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 6.3B.4.2.4-1.

For Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 5 of Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8] is replaced by:

5. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.3.3.4.4.2 in TS 38.521-1 [8] for E-UTRA carrier with the following exception:

3. The SS measure the UE transmission OFF power during the slot preceding the PRACH preamble excluding a transient period of 10  $\mu$ s according to Table 4.6.3-129 in TS 38.508 [6].
4. Measure the output power of the transmitted PRACH preamble according to Table 4.6.3-129 in TS 38.508 [6].

#### 6.3B.4.2.5 Test requirements

Same test requirement as in clause 6.3.3.4.5 in TS 38.521-1 [8].

### 6.3B.4.3 PRACH Time Mask for inter-band EN-DC within FR1

#### 6.3B.4.3.1 Test purpose

Same test purpose as in clause 6.3.3.4.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.3B.4.3.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.3B.4.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.3.3.4.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.3B.4.3.4 Test description

Same test description as in clause 6.3.3.4.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 5 of Initial conditions as in clause 6.3.3.4.4.1 in TS 38.521-1 [8] is replaced by:

5. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.3.3.4.4.2 in TS 38.521-1 [8] for E-UTRA carrier with the following exception:

3. The SS measure the UE transmission OFF power during the slot preceding the PRACH preamble excluding a transient period of 10  $\mu$ s according to Table 4.6.3-129 in TS 38.508 [6].



4. Measure the output power of the transmitted PRACH preamble according to Table 4.6.3-129 in TS 38.508 [6].

#### 6.3B.4.3.5 Test requirements

Same test requirement as in clause 6.3.3.4.5 in TS 38.521-1 [8].

### 6.3B.5 Output power dynamics for EN-DC with UL sharing from UE perspective

#### 6.3B.5.1 E-UTRA and NR switching time mask for TDM based UL sharing from UE perspective

No test case details are specified. Current test procedures for time masks are based on power measurement in relatively long period compared with transient period. For time masks between 2 active time slots with different power level, the test procedure can't provide enough resolution to identify non-conformant UEs. Therefore the minimum requirement is not testable.

### 6.3B.6 Output power dynamics for intra-band EN-DC without dual PA capability

No test case details are specified. Current test procedures for time masks are based on power measurement in relatively long period compared with transient period. For time masks between 2 active time slots with different power level, the test procedure can't provide enough resolution to identify non-conformant UEs. Therefore the minimum requirement is not testable.

### 6.3B.7 Output power dynamics for intra-band EN-DC with dual PA capability

No test case details are specified. Current test procedures for time masks are based on power measurement in relatively long period compared with transient period. For time masks between 2 active time slots with different power level, the test procedure can't provide enough resolution to identify non-conformant UEs. Therefore the minimum requirement is not testable.

## 6.4 Transmit signal quality

### 6.4A Transmit Signal Quality for inter-band NR CA between FR and FR2 without EN-DC

#### 6.4A.1 Frequency error for inter-band NR CA between FR 1 and FR 2 without EN-DC

##### 6.4A.1.1 Test purpose

Same test purpose as in clause 6.4.1 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.4.1 in TS 38.521-2 [9] for NR FR2 carrier(s).

##### 6.4A.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for frequency error apply and are tested in TS 38.521-1 [8] clauses 6.4 and 6.4A and TS 38.521-2 [9] clauses 6.4 and 6.4A

## 6.4A.2 Transmit Modulation Quality for inter-band NR CA without EN-DC

### 6.4A.2.1 Error Vector Magnitude for inter-band NR CA between FR 1 and FR 2 without EN-DC

#### 6.4A.2.1.1 Test purpose

Same test purpose as in clause 6.4.2.1 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.4.2.1 in TS 38.521-2 [9] for NR FR2 carrier(s).

#### 6.4A.2.1.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for error vector magnitude apply and are tested in TS 38.521-1 [8] clauses 6.4 and 6.4A and TS 38.521-2 [9] clauses 6.4 and 6.4A

### 6.4A.2.2 Carrier Leakage for inter-band NR CA between FR 1 and FR 2 without EN-DC

#### 6.4A.2.2.1 Test purpose

Same test purpose as in clause 6.4.2.2 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.4.2.2 in TS 38.521-2 [9] for NR FR2 carrier(s).

#### 6.4A.2.2.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for carrier leakage apply and are tested in TS 38.521-1 [8] clauses 6.4 and 6.4A and TS 38.521-2 [9] clauses 6.4 and 6.4A

### 6.4A.2.3 In-band Emissions for inter-band NR CA between FR 1 and FR 2 without EN-DC

#### 6.4A.2.3.1 Test purpose

Same test purpose as in clause 6.4.2.3 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.4.2.3 in TS 38.521-2 [9] for NR FR2 carrier(s).

#### 6.4A.2.3.1 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for in-band emissions apply and are tested in TS 38.521-1 [8] clauses 6.4 and 6.4A and TS 38.521-2 [9] clauses 6.4 and 6.4A

### 6.4A.2.4 EVM Equalizer Spectral Flatness for inter-band NR CA between FR 1 and FR 2 without EN-DC

#### 6.4A.2.4.1 Test purpose

Same test purpose as in clause 6.4.2.4 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.4.2.4 in TS 38.521-2 [9] for NR FR2 carrier(s).

#### 6.4A.2.4.1 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for EVM equalizer spectral flatness apply and are tested in TS 38.521-1 [8] clauses 6.4 and 6.4A and TS 38.521-2 [9] clauses 6.4 and 6.4A

## 6.4B

### 6.4B.1 Frequency error

#### 6.4B.1.1 Frequency error for Intra-band contiguous EN-DC

#### 6.4B.1.2 Frequency error for Intra-band non-contiguous EN-DC

#### 6.4B.1.3 Frequency error for Inter-band EN-DC within FR1

##### 6.4B.1.3.1 Test purpose

Same test purpose as in clause 6.4.1 in TS 38.521-1 [8] for the NR carrier.

##### 6.4B.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

##### 6.4B.1.3.3 Minimum conformance requirements

For inter-band EN-DC with uplink assigned to one E-UTRA band and one NR band, the requirements shall apply on each component carrier as defined in clause 6.5.1 in [5] and in clause 6.4.1 in [2], respectively, with all component carriers active. If multiple component carriers are assigned to one E-UTRA band, the requirements in subclauses 6.5.1A in [5] apply for those component carriers, and if multiple component carriers are assigned to one NR band, the requirements in subclauses 6.4A.1 in [2] apply for those component carriers.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this measurement is TS 38.101-3 [4] clause 6.4B.1.3.

##### 6.4B.1.3.4 Test description

Same test description as in clause 6.4.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

Notes defined in Table 6.4.1.4.1-1 will be updated as below.

NOTE 2: REFSENS refers to Table 7.3B.2.3.4.1-2a to Table 7.3B.2.3.4.1-3m which defines uplink RB configuration and start RB location for each SCS, channel BW and NR band.

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.4.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Step 6 of Initial conditions as in clause 6.4.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.

Step 3 of Test procedure as in clause 6.4.1.4.2 in TS 38.521-1 [8] is replaced by:

3. Set the Downlink signal level to the appropriate REFSENS value defined in Table 7.3B.2.3.5.1-1, 7.3B.2.3.5.2-1, and 7.3B.2.3.5.5-1. Send continuously uplink power control "up" commands to the UE in every uplink scheduling information to the UE so that the UE transmits at  $P_{UMAX}$  level for the duration of the test. Allow at least 200ms starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.

#### 6.4B.1.3.5 Test Requirement

The 20 frequency error  $\Delta f$  results must fulfil the test requirement defined in 6.4.1.5 TS 38.521-1 [8].

#### 6.4B.1.3.6 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.4B.1.4

#### 6.4B.1.5 Frequency Error for inter-band EN-DC including FR2

**Editor's note:**

- The following aspects of the clause are for future consideration:
- Testing of extreme conditions for FR2 is FFS.

#### 6.4B.1.5.1 Test purpose

Same test purpose as in clause 6.4.1.1 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.4B.1.5.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC including FR2.

#### 6.4B.1.5.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.

#### 6.4B.1.5.4 Test description

Same test description as in clause 6.4.1.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For initial conditions as in clause 6.4.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.1.5.5 Test requirements

Same test requirement as in clause 6.4.1.5 in TS 38.521-2 [9] for the *NR* carrier.

[IS: 5446 NTT created a 3. duplication!!]

#### 6.4B.1.5.2 Frequency Error for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.4A.1.1 in TS 38.521-2 is incomplete.

##### 6.4B.1.5.2.1 Test purpose

Same test purpose as in clause 6.4.1.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.4B.1.5.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

##### 6.4B.1.5.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

##### 6.4B.1.5.2.4 Test description

###### 6.4B.1.5.2.4.1 Initial condition

Same test description as in clause 6.4A.1.1.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.4A.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4A.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state *RRC\_CONNECTED* with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4A.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.1.5.2.5 Test Requirements

Same test requirement as in clause 6.4A.1.1.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.4B.1.5.3 Frequency Error for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.4A.1.2 in TS 38.521-2 is incomplete.

#### 6.4B.1.5.3.1 Test purpose

Same test purpose as in clause 6.4.1.1 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.4B.1.5.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4CCs.

#### 6.4B.1.5.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

#### 6.4B.1.5.3.4 Test description

##### 6.4B.1.5.3.4.1 Initial condition

Same test description as in clause 6.4A.1.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.4A.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4A.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state *RRC\_CONNECTED* with generic procedure parameters *Connectivity EN-DC*, *DC bearer MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4A.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.1.5.3.5 Test Requirements

Same test requirement as in clause 6.4A.1.2.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.4B.1.5.4 Frequency Error for Inter-band EN-DC including FR2 (5 CCs)

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.4A.1.3 in TS 38.521-2 is incomplete.

##### 6.4B.1.5.4.1 Test purpose

Same test purpose as in clause 6.4.1.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.4B.1.5.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5CCs.

##### 6.4B.1.5.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

##### 6.4B.1.5.4.4 Test description

###### 6.4B.1.5.4.4.1 Initial condition

Same test description as in clause 6.4A.1.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.4A.1.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4A.1.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4A.1.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

##### 6.4B.1.5.4.5 Test Requirements

Same test requirement as in clause 6.4A.1.3.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT end of 3. duplication!!]

## 6.4B.2

### 6.4B.2.1 Transmit Modulation Quality for intra-band contiguous EN-DC

#### 6.4B.2.1.1 Error Vector Magnitude for intra-band contiguous EN-DC

##### 6.4B.2.1.1.1 Test purpose

The Error Vector Magnitude is a measure of the difference between the reference waveform and the measured waveform. This difference is called the error vector. Before calculating the EVM the measured waveform is corrected by the sample timing offset and RF frequency offset. Then the carrier leakage shall be removed from the measured waveform before calculating the EVM.

The measured waveform is further equalised using the channel estimates subjected to the EVM equaliser spectrum flatness requirement specified in sub-clause 6.4B.2.1.4.3. For DFT-s-OFDM waveforms, the EVM result is defined after the front-end FFT and IDFT as the square root of the ratio of the mean error vector power to the mean reference power expressed as a %. For CP-OFDM waveforms, the EVM result is defined after the front-end FFT as the square root of the ratio of the mean error vector power to the mean reference power expressed as a %.

The basic EVM measurement interval in the time domain is one preamble sequence for the PRACH and the duration of PUCCH/PUSCH channel, or one hop, if frequency hopping is enabled for PUCCH and PUSCH in the time domain. The EVM measurement interval is reduced by any symbols that contains an allowable power transient as defined in subclause 6.3.3.3 of [8].

##### 6.4B.2.1.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC.

##### 6.4B.2.1.1.3 Minimum conformance requirements

For the intra-band contiguous EN-DC with one component carrier per CG the EVM requirement applies with PRB allocation in one of the CG and the other CG unallocated.

The EVM requirements for each CG are according to clause 6.5.2 of [5] for the MCG and 6.4.2 of [2] for the SCG with EN-DC configured.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.1.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.4B.2.1.1.4 Test description

Same test description as in clause 6.4.2.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

**Table 6.4B.2.1.1.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1	Mid range
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1	Highest NRB_agg (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg, only the combination with the highest NRB_SCG is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 6.4B.2.1.1.4-1.

For Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:



- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release  $On$  according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.4.2.1.4.2 in TS 38.521-1 [8].

#### 6.4B.2.1.1.5 Test requirements

Same test requirement as in clause 6.4.2.1.5 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.1.2 Carrier Leakage for intra-band contiguous EN-DC

##### 6.4B.2.1.2.1 Test purpose

Carrier leakage expresses itself as unmodulated sine wave with the carrier frequency or centre frequency of aggregated transmission bandwidth configuration. It is an interference of approximately constant amplitude and independent of the amplitude of the wanted signal. Carrier leakage interferes with the centre sub carriers of the UE under test (if allocated), especially, when their amplitude is small. The measurement interval is defined over one slot in the time domain.

The purpose of this test is to exercise the UE transmitter to verify its modulation quality in terms of carrier leakage.

##### 6.4B.2.1.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC.

##### 6.4B.2.1.2.3 Minimum conformance requirements

The carrier leakage requirements for each CG are according to clause 6.5.2 of [5] for the MCG and 6.4.2 of [2] for the SCG with EN-DC configured.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.1.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.4B.2.1.2.4 Test description

Same test description as in clause 6.4.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

**Table 6.4B.2.1.2.4-1: Test Configuration**

Initial Conditions	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1	Mid range
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1	Highest NRB_agg (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg , only the combination with the highest NRB_SCG is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 6.4B.2.1.2.4-1 For Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

#### 6.4B.2.1.2.5 Test requirements

Same test requirement as in clause 6.4.2.2.5 in TS 38.521-1 [8] for the NR carrier.

### 6.4B.2.1.3 In-band Emissions for intra-band contiguous EN-DC

#### 6.4B.2.1.3.1 Test purpose

The in-band emissions are a measure of the interference falling into the non-allocated resources blocks.

The in-band emission is defined as the average emission across 12 sub-carriers and as a function of the RB offset from the edge of the allocated UL transmission bandwidth. The in-band emission is measured as the ratio of the UE output power in a non-allocated RB to the UE output power in an allocated RB.

The basic in-band emissions measurement interval is defined over one slot in the time domain, however, the minimum requirement applies when the in-band emission measurement is averaged over 10 sub-frames. When the PUSCH or PUCCH transmission slot is shortened due to multiplexing with SRS, the in-band emissions measurement interval is reduced by one or more symbols, accordingly.

The purpose of this test is to exercise the UE transmitter to verify its modulation quality in terms of in-band emissions.

#### 6.4B.2.1.3.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.4B.2.1.3.3 Minimum conformance requirements

For the MCG the in-band emission requirements in Table 6.5.2A.3.1-1 and 6.5.2A.3.1-2 in [5] apply within the aggregated transmission bandwidth configuration of the EN-DC bandwidth with the carriers of both CGs active and one single contiguous PRB allocation of bandwidth  $L_{CRB}$  within the MCG at the edge of the said aggregated transmission bandwidth configuration.

For the SCG the in-band emission requirements in Table 6.5.2A.3.1-1 and 6.5.2A.3.1-2 in [5] apply within the aggregated transmission bandwidth configuration of the EN-DC bandwidth with the carriers of both CGs active and one single contiguous PRB allocation of bandwidth  $L_{CRB}$  within the SCG at the edge of the aggregated transmission bandwidth configuration.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.1.3

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.4B.2.1.3.4 Test description

##### 6.4B.2.1.3.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and test channel bandwidths based on NR operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.4B.2.1.3.4.1-1. The details of the uplink

reference measurement channels (RMCs) are specified in Annexes A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521.1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.4B.2.1.3.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, Mid range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1		Lowest NRB_agg, Highest NRB_agg (Note 2)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Smallest supported SCS per Channel Bandwidth			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation	Modulation	RB allocation (Note 1)
1 (Note3)	N/A for In-band emission test	QPSK	0	DFT-s-OFDM QPSK	Inner_1RB_Left
2 (Note 4)		QPSK	0	DFT-s-OFDM QPSK	Inner_1RB_Right
3 (Note3)		QPSK	0	CP-OFDM QPSK	Inner_1RB_Left
4 (Note 4)		QPSK	0	CP-OFDM QPSK	Inner_1RB_Right
5 (Note3)		QPSK	Outer_1RB_Right	DFT-s-OFDM QPSK	0
6 (Note 4)		QPSK	Outer_1RB_Left	DFT-s-OFDM QPSK	0
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].					
NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same NRB_agg, select the combination to test as follows:					
- Lowest ENBW: NR component with lowest NRB is tested.					
- Highest ENBW: NR component with highest NRB is tested.					
NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.					
NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.					
NOTE 5: Outer_1RB_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer_1RB_Right defined as 1 RB allocated at the right edge of the E-UTRA component.					

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operation band and test channel bandwidth as specified in Table 4.6-1.

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS 38.521-1[8].
5. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.

6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.4B.2.1.3.4.3.
8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.4B.2.1.3.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to Table 6.4B.2.1.3.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $0 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to Table 6.4B.2.1.3.4.2-1 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
3. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
4. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-30 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to Table 6.4B.2.1.3.4.2-2 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
5. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
6. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-40 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to 6.4B.2.1.3.4.2-2 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
7. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
8. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is 3.2 dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or 3.5 dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
9. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.
10. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-26.8$  dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or  $-26.5$  dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
11. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.
12. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-36.8$  dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or  $-36.5$  dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
13. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.4B.2.1.3.4.1-1, send an NR RRCReconfiguration message according to TS 38.508-1 [5] clause 4.6.3 Table 4.6.3-118 PUSCH-Config without CP-OFDM condition. When switching to CP-OFDM waveform, send an NR RRCReconfiguration message with CP-OFDM condition.

**Table 6.4B.2.1.3.4.2-1: Power Window (dB) for carrier leakage (steps 2)**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$BW \leq 20\text{MHz}$	[1.4]	[1.7]	[2]
$20\text{MHz} < BW \leq 40\text{MHz}$	[1.4]	[1.7]	[2.2]
$40\text{MHz} < BW \leq 100\text{MHz}$	[2.1]	[2.3]	[2.3]

**Table 6.4B.2.1.3.4.2-2: Power Window (dB) for carrier leakage (steps 4 and 6)**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$BW \leq 40\text{MHz}$	[1.7]	[2.0]	[2.2]
$40\text{MHz} < BW \leq 100\text{MHz}$	[2.1]	[2.3]	[2.5]

## 6.4B.2.1.3.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

## 6.4B.2.1.3.5 Test requirements

Each of the [20] In-band emissions results, derived in Annex E.4.3 shall not exceed the corresponding values in Table 6.4B.2.1.3.5-1.

**Table 6.4B.2.1.3.5-1: Test requirements for in-band emissions (allocated component carrier)**

Parameter	Unit	Limit	Applicable Frequencies
General	dB	$\max \left\{ -25 - 10 \cdot \log_{10} (N_{RB} / L_{CRB}), \right.$ $20 \cdot \log_{10} EVM - 3 - 5 \cdot ( \Delta_{RB}  - 1) / L_{CRB}, + TT$ $\left. - 57 \text{ dBm} / 180 \text{ kHz} - P_{RB} \right\}$	Any non-allocated (NOTE 2)
IQ Image	dB	-25	Exception for IQ image (NOTE 3)
Carrier leakage	dBc	25 + TT	Exception for Carrier frequency (NOTE 4)
		20 + TT	
		10 + TT	
NOTE 1: An in-band emissions combined limit is evaluated in each non-allocated RB. For each such RB, the minimum requirement is calculated as the higher of $P_{RB} - 30$ dB and the power sum of all limit values (General, IQ Image or Carrier leakage) that apply. $P_{RB}$ is defined in NOTE 9. The limit is evaluated in each non-allocated RB.			
NOTE 2: The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in one non-allocated RB to the measured average power per allocated RB, where the averaging is done across all allocated RBs			
NOTE 3: Exceptions to the general limit are allowed for up to $L_{CRBs} + 1$ RBs within a contiguous width of $L_{CRBs} + 1$ non-allocated RBs. The measurement bandwidth is 1 RB.			
NOTE 4: Exceptions to the general limit are allowed for up to two contiguous non-allocated RBs. The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in the non-allocated RB to the measured total power in all allocated RBs.			
NOTE 5: $L_{CRB}$ is the Transmission Bandwidth (see Figure 5.6-1) not exceeding $\lfloor N_{RB} / 2 - 1 \rfloor$			
NOTE 6: $N_{RB}$ is the Transmission Bandwidth Configuration (see Figure 5.6-1) of the component carrier with RBs allocated.			
NOTE 7: $EVM$ is the limit specified in Table 6.5.2.1.1-1 for the modulation format used in the allocated RBs.			
NOTE 8: $\Delta_{RB}$ is the starting frequency offset between the allocated RB and the measured non-allocated RB (e.g. $\Delta_{RB} = 1$ or $\Delta_{RB} = -1$ for the first adjacent RB outside of the allocated bandwidth).			
NOTE 9: $P_{RB}$ is the transmitted power per 180 kHz in allocated RBs, measured in dBm.			
NOTE 10: Test tolerance TT = 0.8 dB.			

The in-band emissions results, measured with the spectral test shall not exceed the corresponding values in Table 6.4B.2.1.3.5-2.

**Table 6.4B.2.1.3.5-2: Test requirements for in-band emissions (not allocated component carrier)**

Parameter	Unit	Meas BW NOTE 1	Limit	remark	Applicable Frequencies	
General	dB	BW of 1 RB (180KHz rectangular)	$\max \left\{ -25 - 10 \cdot \log_{10} (N_{RB} / L_{CRB}), \right.$ $20 \cdot \log_{10} EVM - 3 - 5 \cdot ( \Delta_{RB}  - 1) / L_{CRB},$ $\left. -57 \text{ dBm} / 180 \text{ kHz} - P_{RB} \right\}$	The reference value is the average power per allocated RB in the allocated component carrier	Any RB in the non allocated component carrier. The frequency raster of the RBs is derived when this component carrier is allocated with RBs	
IQ Image	dB	BW of 1 RB (180KHz rectangular)	-25 + TT	The reference value is the average power per allocated RB in the allocated component carrier	The frequencies of the $L_{CRB}$ contiguous non-allocated RBs are unknown. The frequency raster of the RBs is derived when this component carrier is allocated with RBs	
			NOTE 2			
Carrier leakage	dBc	BW of 1 RB (180KHz rectangular)	NOTE 3		The reference value is the total power of the allocated RBs in the allocated component carrier	The frequencies of the up to 2 non-allocated RBs are unknown. The frequency raster of the RBs is derived when this component carrier is allocated with RBs
			-25 + TT	Output power > 0 dBm		
			-20 + TT	-30 dBm ≤ Output power ≤ 0 dBm		
			-10 + TT	-40 dBm ≤ Output power < -30 dBm		
NOTE 1: Resolution BWs smaller than the measurement BW may be integrated to achieve the measurement bandwidth.						
NOTE 2: Exceptions to the general limit is are allowed for up to $L_{CRB} + 1$ RBs within a contiguous width of $L_{CRB} + 1$ non-allocated RBs.						
NOTE 3: Two Exceptions to the general limit are allowed for up to two contiguous non-allocated RBs						
NOTE 4: NOTES 1, 5, 6, 7, 8, 9 from Table 6.5.2A.3.1-1 apply for Table 6.5.2A.3.1-2 as well.						
NOTE 5: $\Delta_{RB}$ for measured non-allocated RB in the non allocated component carrier may take non-integer values when the carrier spacing between the CCs is not a multiple of RB.						
NOTE 6: Test tolerance TT = 0.8 dB.						

**6.4B.2.2 Transmit Modulation Quality for intra-band non-contiguous EN-DC**

Editor’s Note: Wgap is TBD in TS 38.101-3 for this test case

## 6.4B.2.2.1 Error Vector Magnitude for intra-band non-contiguous EN-DC

### 6.4B.2.2.1.1 Test purpose

Same test purpose as in clause 6.4.2.1.1 in TS 38.521-1 [8] for the NR carrier.

### 6.4B.2.2.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 6.4B.2.2.1.3 Minimum conformance requirements

For the intra-band non-contiguous EN-DC with one component carrier per CG the EVM requirement applies with PRB allocation in one of the CG and the other CG unallocated.

The EVM requirements for each CG are according to clause 6.5.2.1 of [5] for the MCG and 6.4.2.1.3 of [8] for the SCG with EN-DC configured.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.2.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 6.4B.2.2.1.4 Test description

Same test description as in clause 6.4.2.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.4.2.1.4.2 in TS 38.521-1 [8].

### 6.4B.2.2.1.5 Test requirement

Same test requirement as in clause 6.4.2.1.5 in TS 38.521-1 [8] for the NR carrier.

## 6.4B.2.2.2 Carrier Leakage for intra-band non-contiguous EN-DC

### 6.4B.2.2.2.1 Test purpose

Same test purpose as in clause 6.4.2.2.1 in TS 38.521-1 [8] for the NR carrier.

### 6.4B.2.2.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 6.4B.2.2.2.3 Minimum conformance requirements

The carrier leakage requirements for each CG are according to clause 6.5.2.2 of [5] for the MCG and 6.4.2.2.3 of [8] for the SCG with EN-DC configured and PRB allocation only in the CG being measured.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.2.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.2.2.4 Test description

Same test description as in clause 6.4.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.4B.2.2.2.5 Test requirement

Same test requirement as in clause 6.4.2.2.5 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.2.3 In-band Emissions for intra-band non-contiguous EN-DC

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **Measurement uncertainty and TT is FFS.**

##### 6.4B.2.2.3.1 Test purpose

Same test purpose as in clause 6.4.2.3.1 in TS 38.521-1 [8] for the NR carrier.

##### 6.4B.2.2.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

##### 6.4B.2.2.3.3 Minimum conformance requirements

For the MCG the in-band emission requirements in Table 6.5.2A.3.1-1 and 6.5.2A.3.1-2 in [5] apply within the transmission bandwidth configuration of the MCG with the carriers of both CGs active and one single contiguous PRB allocation of bandwidth  $L_{CRB}$  within the MCG at the edge of the transmission bandwidth configuration.

For the SCG the in-band emission requirements in Table 6.5.2A.3.1-1 and 6.5.2A.3.1-2 in [5] apply within the transmission bandwidth configuration of the SCG with the carriers of both CGs active and one single contiguous PRB allocation of bandwidth  $L_{CRB}$  within the SCG at the edge of the transmission bandwidth configuration.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.2.3.

No exception requirements applicable to NR or LTE.



6.4B.2.2.3.4 Test description

6.4B.2.2.3.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and test channel bandwidths based on NR operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC combination of test channel bandwidth and sub-carrier spacing, and are shown in table 6.4B.2.2.3.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annexes A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521.1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.4B.2.2.3.4-1: Test Configuration Table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, Mid range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.3-1		Lowest, Mid, Highest			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Smallest supported SCS per Channel Bandwidth			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 3)	Modulation	RB allocation (NOTE 1,2)
1	N/A for carrier leakage testing	QPSK	0	DFT-s-OFDM QPSK	Inner_1RB_Left
2		QPSK	0	DFT-s-OFDM QPSK	Inner_1RB_Right
3		QPSK	0	CP-OFDM QPSK	Inner_1RB_Left
4		QPSK	0	CP-OFDM QPSK	Inner_1RB_Right
5		QPSK	Outer_1RB_Left	DFT-s-OFDM QPSK	0
6		QPSK	Outer_1RB_Right	DFT-s-OFDM QPSK	0
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].					
NOTE 2: When the signalled DC carrier position is at Inner_1RB_Left, use Inner_1RB_Right for UL RB allocation.					
NOTE 3: Outer_1RB_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer_1RB_Right defined as 1 RB allocated at the right edge of the E-UTRA component.					

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, in Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. E-UTRA downlink signals are initially set up according to Annex C.0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS36.521-1[10].
6. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.

7. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
8. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.4B.2.2.3.4.3.
9. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.4B.2.2.3.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to Table 6.4B.2.2.3.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $0 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to Table 6.4B.2.2.3.4.2-1 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
3. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
4. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-30 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to Table 6.4B.2.2.3.4.2-2 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
5. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
6. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-40 + P_W$  dBm  $\pm P_W$  dB where  $P_W$  is the power window according to 6.4B.2.2.3.4.2-2 for the carrier frequency  $f$  and the channel bandwidth BW on NR CC.
7. Measure In-band emission on NR CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on E-UTRA CC. For TDD slots with transient periods are not under test.
8. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is 3.2 dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or 3.5 dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
9. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.
10. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-26.8$  dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or  $-26.5$  dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
11. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.
12. Send the appropriate TPC commands in the uplink scheduling information to the UE until UE output power is  $-36.8$  dBm  $\pm 3.2$  dB for carrier frequency  $f \leq 3.0$  GHz or  $-36.5$  dBm  $\pm 3.5$  dB for carrier frequency  $3.0$  GHz  $< f \leq 4.2$  GHz on E-UTRA CC.
13. Measure In-band emission on E-UTRA CC using Global In-Channel Tx-Test (Annex E). Measure power spectral density on NR CC. For TDD slots with transient periods are not under test.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.4B.2.2.3.4.1-1, send an NR RRCConnectionReconfiguration message containing NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-118 PUSCH-Config without CP-OFDM condition. When switching to CP-OFDM waveform, send an NR RRCConnectionReconfiguration message containing NR RRCReconfiguration message with CP-OFDM condition.

**Table 6.4B.2.2.3.4.2-1: Power Window (dB) for carrier leakage (step 2)**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 20\text{MHz}$	[1.4]	[1.7]	[2]
$20\text{MHz} < \text{BW} \leq 40\text{MHz}$	[1.4]	[1.7]	[2.2]
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	[2.1]	[2.3]	[2.3]

**Table 6.4B.2.2.3.4.2-2: Power Window (dB) for carrier leakage (step 4 and step 6)**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 40\text{MHz}$	[1.7]	[2.0]	[2.2]
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	[2.1]	[2.3]	[2.5]

#### 6.4B.2.2.3.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 6.4B.2.2.3.5 Test requirement

Each of the [20] In-band emissions results, derived in Annex E.4.3 shall not exceed the corresponding values in Tables 6.4B.2.2.3.5-1.

**Table 6.4B.2.2.3.5-1: Minimum requirements for in-band emissions (allocated component carrier)**

Parameter	Unit	Limit	Applicable Frequencies
General	dB	$\max \left\{ -25 - 10 \cdot \log_{10} (N_{RB} / L_{CRB}), \right.$ $20 \cdot \log_{10} EVM - 3 - 5 \cdot ( \Delta_{RB}  - 1) / L_{CRB},$ $\left. -57 \text{ dBm} / 180 \text{ kHz} - P_{RB} \right\}$	Any non-allocated (NOTE 2)
IQ Image	dB	-25	Exception for IQ image (NOTE 3)
Carrier leakage	dBc	-25	Exception for Carrier frequency (NOTE 4)
		-20	
		-10	
<p>NOTE 1: An in-band emissions combined limit is evaluated in each non-allocated RB. For each such RB, the minimum requirement is calculated as the higher of <math>P_{RB} - 30</math> dB and the power sum of all limit values (General, IQ Image or Carrier leakage) that apply. <math>P_{RB}</math> is defined in NOTE 9. The limit is evaluated in each non-allocated RB.</p> <p>NOTE 2: The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in one non-allocated RB to the measured average power per allocated RB, where the averaging is done across all allocated RBs.</p> <p>NOTE 3: Exceptions to the general limit are allowed for up to <math>L_{CRBs} + 1</math> RBs within a contiguous width of <math>L_{CRBs} + 1</math> non-allocated RBs. The measurement bandwidth is 1 RB.</p> <p>NOTE 4: Exceptions to the general limit are allowed for up to two contiguous non-allocated RBs. The measurement bandwidth is 1 RB and the limit is expressed as a ratio of measured power in the non-allocated RB to the measured total power in all allocated RBs.</p> <p>NOTE 5: <math>L_{CRB}</math> is the Transmission Bandwidth (see Figure [5.6-1]) not exceeding <math>\lfloor N_{RB} / 2 - 1 \rfloor</math></p> <p>NOTE 6: <math>N_{RB}</math> is the Transmission Bandwidth Configuration (see Figure [5.6-1]) of the component carrier with RBs allocated.</p> <p>NOTE 7: <math>EVM</math> is the limit specified in Table 6.4.2.1.3-1 for the modulation format used in the allocated RBs.</p> <p>NOTE 8: <math>\Delta_{RB}</math> is the starting frequency offset between the allocated RB and the measured non-allocated RB (e.g. <math>\Delta_{RB} = 1</math> or <math>\Delta_{RB} = -1</math> for the first adjacent RB outside of the allocated bandwidth).</p> <p>NOTE 9: <math>P_{RB}</math> is the transmitted power per 180 kHz in allocated RBs, measured in dBm.</p>			

**Table 6.4B.2.2.3.5-2: Minimum requirements for in-band emissions (not allocated component carrier)**

Parameter	Unit	Meas BW NOTE 1	Limit	remark	Applicable Frequencies	
General	dB	BW of 1 RB (180KHz rectangular)	$\max \left\{ -25 - 10 \cdot \log_{10} (N_{RB} / L_{CRB}), \right.$ $20 \cdot \log_{10} EVM - 3 - 5 \cdot ( \Delta_{RB}  - 1) / L_{CRB},$ $\left. -57 \text{ dBm} / 180 \text{ kHz} - P_{RB} \right\}$	The reference value is the average power per allocated RB in the allocated component carrier	Any RB in the non allocated component carrier. The frequency raster of the RBs is derived when this component carrier is allocated with RBs	
IQ Image	dB	BW of 1 RB (180KHz rectangular)	-25 NOTE 2	The reference value is the average power per allocated RB in the allocated component carrier	The frequencies of the $L_{CRB}$ contiguous non-allocated RBs are unknown. The frequency raster of the RBs is derived when this component carrier is allocated with RBs	
Carrier leakage	dBc	BW of 1 RB (180KHz rectangular)	NOTE 3		The reference value is the total power of the allocated RBs in the allocated component carrier	The frequencies of the up to 2 non-allocated RBs are unknown. The frequency raster of the RBs is derived when this component carrier is allocated with RBs
			-25	Output power > 0 dBm		
			-20	-30 dBm ≤ Output power ≤ 0 dBm		
			-10	-40 dBm ≤ Output power < -30 dBm		
NOTE 1: Resolution BWs smaller than the measurement BW may be integrated to achieve the measurement bandwidth.						
NOTE 2: Exceptions to the general limit is are allowed for up to $L_{CRB} + 1$ RBs within a contiguous width of $L_{CRB} + 1$ non-allocated RBs.						
NOTE 3: Two Exceptions to the general limit are allowed for up to two contiguous non-allocated RBs						
NOTE 4: NOTES 1, 5, 6, 7, 8, 9 from Table 6.4B.2.2.3.5-1 apply for Table 6.4B.2.2.3.5-2 as well.						
NOTE 5: $\Delta_{RB}$ for measured non-allocated RB in the non allocated component carrier may take non-integer values when the carrier spacing between the CCs is not a multiple of RB.						

**6.4B.2.2.4 EVM Equalizer Flatness for intra-band non-contiguous EN-DC**

**6.4B.2.2.4.1 Test purpose**

Same test purpose as in clause 6.4.2.4 in TS 38.521-1 [8] for the NR carrier.

## 6.4B.2.2.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

## 6.4B.2.2.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.2.4.3 in TS 38.521-1 [8] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

## 6.4B.2.2.4.4 Test description

Same test description as in clause 6.4.2.4.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

**Table 6.4B.2.2.4.4-1: Test Configuration Table**

Initial Conditions			
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		Normal, TL/VL, TL/VH, TH/VL, TH/VH	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		MaxWGap	
Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1		Highest $N_{RB\_agg}$ (NOTE 1, 2)	
Test SCS as specified in Table 5.3.5-1		Lowest	
Test parameters			
Test ID	Downlink Configuration	Uplink Configuration	
		Modulation	NR RB allocation (NOTE 3)
1	N/A for EVM equalizer flatness testing	DFT-s-OFDM QPSK	Outer Full
2		CP-OFDM QPSK	Outer Full
NOTE 1: Test Channel Bandwidths are checked separately for each NR band, which applicable channel bandwidths are specified in Table 5.3.5-1 of 38.521-1 [8].			
NOTE 2: Lowest and highest allowed NR channel BW as specified in Table 5.3B.1.3-1. If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.			
NOTE 3: The specific configuration of each RB allocation is defined in Table 6.1-1 of 38.521-1 [8].			

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.4.2.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.4.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

## 6.4B.2.2.4.5 Test requirement

Same test requirement as in clause 6.4.2.4.5 in TS 38.521-1 [8] for the NR carrier.

## 6.4B.2.3 Transmit Modulation Quality for inter-band EN-DC within FR1

### 6.4B.2.3.1 Error Vector Magnitude for inter-band EN-DC within FR1

#### 6.4B.2.3.1.1 Test purpose

Same test purpose as in clause 6.4.2.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.3.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.4B.2.3.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.2.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.3.1.4 Test description

Same test description as in clause 6.4.2.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.4.2.1.4.2 in TS 38.521-1 [8].

#### 6.4B.2.3.1.5 Test requirement

Same test requirement as in clause 6.4.2.1.5 in TS 38.521-1 [8] for the NR carrier.

### 6.4B.2.3.2 Carrier Leakage for inter-band EN-DC within FR1

#### 6.4B.2.3.2.1 Test purpose

Same test purpose as in clause 6.4.2.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.3.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.4B.2.3.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.2.2.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.3.2.4 Test description

Same test description as in clause 6.4.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.2.2.4.1 in TS 38.521-1 [8] is replaced by by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.4B.2.3.2.5 Test requirement

Same test requirement as in clause 6.4.2.2.5 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.3.3 In-band Emissions for inter-band EN-DC within FR1

##### 6.4B.2.3.3.1 Test purpose

Same test purpose as in clause 6.4.2.3.1 in TS 38.521-1 [8] for the NR carrier.

##### 6.4B.2.3.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

##### 6.4B.2.3.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.2.3.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.4B.2.3.3.4 Test description

Same test description as in clause 6.4.2.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-1 [8] is replaced by:



6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.4.2.3.4.2 in TS 38.521-1 [8].

#### 6.4B.2.3.3.5 Test requirement

Same test requirement as in clause 6.4.2.3.5 in TS 38.521-1 [8] for the NR carrier.

#### 6.4B.2.3.4 EVM Equalizer Flatness for inter-band EN-DC within FR1

##### 6.4B.2.3.4.1 Test purpose

Same test purpose as in clause 6.4.2.4 in TS 38.521-1 [8] for the NR carrier.

##### 6.4B.2.3.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

##### 6.4B.2.3.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.4.2.4.3 in TS 38.521-1 [8] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.4B.2.3.4.4 Test description

###### 6.4B.2.3.4.4.1 Initial conditions

Same test description as in clause 6.4.2.4.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.4.2.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.4.4.2 in TS 38.521-1 [8] with the following steps added for E-UTRA component:

- 1.1. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.4B.2.3.4.5 Test requirement

Same test requirement as in clause 6.4.2.4.5 in TS 38.521-1 [8] for the NR carrier.

## 6.4B.2.4 Transmit Modulation Quality for inter-band EN-DC including FR2

### 6.4B.2.4.1 Error Vector Magnitude for inter-band EN-DC including FR2

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- The referred test case 6.4.2.1 in TS 38.521-2 is incomplete.
- Measurement Uncertainty and Test Tolerance are FFS.
- 38.101-2 Clause 6.3.4.3: Relative power tolerances are in square brackets.

#### 6.4B.2.4.1.1 Test purpose

Same test purpose as in clause 6.4.2.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.4B.2.4.1.3 Minimum conformance requirements

For inter-band EN-DC including FR2 or both FR1 and FR2, transmit modulation quality for EN-DC operations in FR1 and FR2 as specified in TS 36.101 [5], 38.101-1 [2] and 38.101-2 [3] apply for E-UTRA, NR FR1 and NR FR2 respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

Same minimum conformance requirements as in clause 6.4.2.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.4.1.4 Test description

##### 6.4B.2.4.1.4.1 Initial conditions

Same test description as in clause 6.4.2.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.4.2.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.1.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.2.4.1.5 Test requirement

Same test requirement as in clause 6.4.2.1.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.2 Carrier Leakage for inter-band EN-DC including FR2

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- The referred test case 6.4.2.2 in TS 38.521-2 is incomplete.
- Measurement Uncertainty and Test Tolerance are FFS.
- 38.101-2 Clause 6.3.4.3: Relative power tolerances are in square brackets.

##### 6.4B.2.4.2.1 Test purpose

Same test purpose as in clause 6.4.2.2 in TS 38.521-2 [9] for the NR carrier.

##### 6.4B.2.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

##### 6.4B.2.4.2.3 Minimum conformance requirements

For inter-band EN-DC including FR2 or both FR1 and FR2, transmit modulation quality for EN-DC operations in FR1 and FR2 as specified in TS 36.101 [5], 38.101-1 [2] and 38.101-2 [3] apply for E-UTRA, NR FR1 and NR FR2 respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

Same minimum conformance requirements as in clause 6.4.2.2.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied

##### 6.4B.2.4.2.4 Test description

###### 6.4B.2.4.2.4.1 Initial conditions

Same test description as in clause 6.4.2.2.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.4.2.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.2.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

##### 6.4B.2.4.2.5 Test requirement

Same test requirement as in clause 6.4.2.2.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.3 In-band Emissions for inter-band EN-DC including FR2

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- The referred test case 6.4.2.3 in TS 38.521-2 is incomplete.
- Measurement Uncertainty and Test Tolerance are FFS.
- 38.101-2 Clause 6.3.4.3: Relative power tolerances are in square brackets.

#### 6.4B.2.4.3.1 Test purpose

Same test purpose as in clause 6.4.2.3 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.4B.2.4.3.3 Minimum conformance requirements

For inter-band EN-DC including FR2 or both FR1 and FR2, transmit modulation quality for EN-DC operations in FR1 and FR2 as specified in TS 36.101 [5], 38.101-1 [2] and 38.101-2 [3] apply for E-UTRA, NR FR1 and NR FR2 respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

Same minimum conformance requirements as in clause 6.4.2.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.4.3.4 Test description

##### 6.4B.2.4.3.4.1 Initial conditions

Same test description as in clause 6.4.2.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.4.2.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.3.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.2.4.3.5 Test requirement

Same test requirement as in clause 6.4.2.3.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.4 EVM Equalizer Flatness for inter-band EN-DC including FR2

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- The referred test case 6.4.2.4 in TS 38.521-2 is incomplete.
- Measurement Uncertainty and Test Tolerance are FFS.

- 38.101-2 Clause 6.3.4.3: Relative power tolerances are in square brackets.

#### 6.4B.2.4.4.1 Test purpose

Same test purpose as in clause 6.4.2.4 in TS 38.521-2 [9] for the NR carrier.

#### 6.4B.2.4.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.4B.2.4.4.3 Minimum conformance requirements

For inter-band EN-DC including FR2 or both FR1 and FR2, transmit modulation quality for EN-DC operations in FR1 and FR2 as specified in TS 36.101 [5], 38.101-1 [2] and 38.101-2 [3] apply for E-UTRA, NR FR1 and NR FR2 respectively.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

Same minimum conformance requirements as in clause 6.4.2.4.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.4B.2.4.4.4 Test description

##### 6.4B.2.4.4.4.1 Initial conditions

Same test description as in clause 6.4.2.4.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.4.2.4.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.4.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.4.2.4.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.4B.2.4.4.5 Test requirement

Same test requirement as in clause 6.4.2.4.5 in TS 38.521-2 [9] for the NR carrier.

## 6.5 Output RF spectrum emissions

### 6.5A Output RF spectrum emissions for CA

#### 6.5A.1 Occupied bandwidth for CA without EN-DC

### 6.5A.1.1 Test purpose

Same test purpose as in clause 6.5.1 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.5.1 in TS 38.521-2 [9] for NR FR2 carrier(s).

### 6.4A.2.4.1 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for occupied bandwidth apply and are tested in TS 38.521-1 [8] clause 6.5 and 6.5A and TS 38.521-2 [9] clauses 6.5 and 6.5A.

## 6.5A.2 Out-of-band emissions for CA without EN-DC

### 6.5A.2.2 Additional Spectrum emissions mask for CA without EN-DC

#### 6.5A.2.2.1 Test purpose

Same test purpose as in 6.5.2.3 in TS 38.521-1 [8] for NR FR1 carrier(s) and 6.5.2.2 in TS 38.521-2 [9] for NR FR2 carrier(s).

#### 6.5A.2.2.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for additional spectrum emissions mask apply and are tested in TS 38.521-1 [8] clause 6.5 and 6.5A and TS 38.521-2 [9] clause 6.5 and 6.5A.

### 6.5A.2.3 Adjacent channel leakage ratio for CA without EN-DC

No test case details specified as there are no exception requirements applicable to NR FR1 or NR FR2 as per TS 38.101-3 [4], clause 6.5A.2. The SA requirement for ACLR applies and is tested in TS 38.521-1 [8] and TS 38.521-2 [9] for FR1 and FR2 respectively.

## 6.5A.3 Spurious emissions for CA without EN-DC

### 6.5A.3.1 Test purpose

Same test purpose as in clause 6.5.3 in TS 38.521-1 [8] for NR FR1 carrier(s) and clause 6.5.3 in TS 38.521-2 [9] for NR FR2 carrier(s).

### 6.5A.3.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The SA requirements for occupied bandwidth apply and are tested in TS 38.521-1 [8] clauses 6.5 and 6.5A and TS 38.521-2 [9] clauses 6.5 and 6.5A.

## 6.5B Output RF spectrum emissions for DC

### 6.5B.1 Occupied bandwidth for EN-DC

#### 6.5B.1.1 Occupied bandwidth for Intra-Band Contiguous EN-DC

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- measurement uncertainty for ENBW > 100 MHz is FFS.

#### 6.5B.1.1.1 Test purpose

To verify that the UE occupied bandwidth for intra-band contiguous EN-DC for all transmission bandwidth configurations supported by the UE are less than their specific limits.

#### 6.5B.1.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.5B.1.1.3 Minimum conformance requirements

For intra-band contiguous EN-DC, the occupied bandwidth is a measure of the bandwidth containing the 99% of the total integrated power of the transmitted spectrum. The OBW shall be less than the aggregated channel bandwidth for EN-DC, denoted as EN-BW in sub-clause 5.3B.

The normative reference for this measurement is TS 38.101-3 [4] clause 6.5B.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.5B.1.1.4 Test description

##### 6.5B.1.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.5B.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.5B.1.1.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Mid range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1		All			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest SCS per Channel Bandwidth			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A for OBW testing.	QPSK	Outer_Full	CP-OFDM QPSK	Outer_Full
NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].					
NOTE 2: Outer_Full defined as the transmission bandwidth configuration $N_{RB}$ per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1.					

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.

#### 6.5B.1.1.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 6.5B.1.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command for the UE to reach  $P_{UMAX}$  level.
3. Measure the power spectrum distribution over all EN-DC component carriers in the EN-DC within two times or more range over the requirement for Occupied Bandwidth specification for intra-band contiguous EN-DC centring on the current carrier frequency in the EN-DC configuration. The characteristics of the filter shall be approximately Gaussian (typical spectrum analyser filter). Other methods to measure the power spectrum distribution are allowed. The measuring duration is at least 1ms over consecutive active uplink slots.
4. Calculate the total power within the range of all frequencies measured in step 3 and save this value as "Total power".
5. Sum up the power upward from the lower boundary of the measured frequency range in step 3 and seek the limit frequency point by which this sum becomes 0.5% of "Total power" and save this point as "Lower Frequency".
6. Sum up the power downward from the upper boundary of the measured frequency range in step 3 and seek the limit frequency point by which this sum becomes 0.5% of "Total power" and save this point as "Upper Frequency".
7. Calculate the difference "Upper Frequency" – "Lower Frequency" = "Occupied Bandwidth" between the two limit frequencies obtained in step 5 and step 6.

#### 6.5B.1.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 6.5B.1.1.5 Test requirements

The measured Occupied Bandwidth shall not exceed values of aggregated channel bandwidth as defined in section 5.3B.1.2 for intra-band contiguous EN-DC.

### 6.5B.1.2 Occupied bandwidth for Intra-Band Non-Contiguous EN-DC

**Editor's note:** This clause is incomplete. The following aspects are either missing or not yet determined:

- Wgap for intraband non-contiguous EN-DC is FFS in TS 38.508-1 due to dependencies with RAN4.



#### 6.5B.1.2.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.5B.1.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non contiguous EN-DC.

#### 6.5B.1.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.5B.1.2.4 Test description

Same test description as in clause 6.5.1.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 6.5.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.5.1.4.2 in TS 38.521-1 [8].

#### 6.5B.1.2.5 Test requirement

Same test requirement as in clause 6.5.1.5 in TS 38.521-1 [8] for the NR carrier.

### 6.5B.1.3 Occupied bandwidth for Inter-Band EN-DC within FR1

#### 6.5B.1.3.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.5B.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.5B.1.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.5B.1.3.4 Test description

Same test description as in clause 6.5.1.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 6.5.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for the cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.1.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.5B.1.3.5 Test requirement

Same test requirement as in clause 6.5.1.5 in TS 38.521-1 [8] for the NR carrier.

### 6.5B.1.4 Occupied bandwidth for Inter-Band EN-DC including FR2

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- The referred test case 6.5.1 in TS 38.521-2 is incomplete
- Measurement Uncertainty FFS.
- OBW core requirement and waveform defined in TS 38.101-2 is under discussion in RAN4.

#### 6.5B.1.4.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.5B.1.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.5B.1.4.4 Test description

##### 6.5B.1.4.4.1 Initial conditions

Same test description as in clause 6.5.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.5.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.1.4.5 Test requirement

Same test requirement as in clause 6.5.1.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT created a 4. duplication!!]

#### 6.5B.1.4.2 Occupied bandwidth for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.1.1 in TS 38.521-2 is incomplete.

#### 6.5B.1.4.2.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

#### 6.5B.1.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.1.

#### 6.5B.1.4.2.4 Test description

##### 6.5B.1.4.2.4.1 Initial condition

Same test description as in clause 6.5A.1.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.1.4.2.5 Test Requirements

Same test requirement as in clause 6.5A.1.1.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.3 Occupied bandwidth for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.1.2 in TS 38.521-2 is incomplete.

#### 6.5B.1.4.3.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4CCs.

#### 6.5B.1.4.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.1.

#### 6.5B.1.4.3.4 Test description

##### 6.5B.1.4.3.4.1 Initial condition

Same test description as in clause 6.5A.1.2.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.1.4.3.5 Test Requirements

Same test requirement as in clause 6.5A.1.2.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.4 Occupied bandwidth for Inter-band EN-DC including FR2 (5 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.1.1 in TS 38.521-2 is incomplete.

#### 6.5B.1.4.4.1 Test purpose

Same test purpose as in clause 6.5.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.1.4.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5CCs.

#### 6.5B.1.4.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.1.

#### 6.5B.1.4.4.4 Test description

##### 6.5B.1.4.4.4.1 Initial condition

Same test description as in clause 6.5A.1.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.1.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.1.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.1.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

## 6.5B.1.4.4.5 Test Requirements

Same test requirement as in clause 6.5A.1.3.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT end of the 4. duplication!!]

## 6.5B.2 Out-of-band emissions for EN-DC

## 6.5B.2.1 Out-of-band emissions for Intra-band contiguous EN-DC

## 6.5B.2.1.1 Spectrum emissions mask for intra-band contiguous EN-DC

## 6.5B.2.1.1.1 Test purpose

To verify that the power of any UE emissions shall not exceed specified level for the specified aggregated bandwidth for the EN-DC intra-band contiguous.

## 6.5B.2.1.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

## 6.5B.2.1.1.3 Minimum conformance requirements

The general spectrum emission for intra-band contiguous EN-DC is specified in Table 6.5B.2.1.1.3-1.

**Table 6.5B.2.1.1.3-1: General spectrum emission mask for intra-band contiguous EN-DC**

$\Delta f_{\text{foob}}$ (MHz)	Spectrum emission limit (dBm)	Measurement bandwidth
$\pm 0 - 1$	$\text{Max}(\text{Round}(10 \cdot \log(0.15/\text{ENBW})), -24)$	30 kHz
$\pm 1 - 5$	-10	1 MHz
$\pm 5 - \text{ENBW}$	-13	1 MHz
$\pm \text{ENBW} - (\text{ENBW} + 5)$	-25	1 MHz
NOTE: ENBW refers to the aggregated channel bandwidth in MHz as defined in sub-clause 5.3B.		

The normative reference for this measurement is TS 38.101-3 [4] clause 6.5B.2.1.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

## 6.5B.2.1.1.4 Test description

## 6.5B.2.1.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.5B.2.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.5B.2.1.1.4.1-1: Test configuration table**

Initial Conditions								
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				NC				
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1				Low range, High range				
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1				Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$ (Note 2)				
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1				Lowest, Highest				
Test Parameters								
Test ID	Freq	ChBw	SCS	Downlink Configuration	EN-DC Uplink Configuration			
					E-UTRA Cell		NR Cell	
					Modulation	RB allocation (Note 5)	Modulation	RB allocation (NOTE 1)
1	Default	Default	Default	N/A for SEM test case	16QAM	Outer_Full	DFT-s-OFDM PI/2 BPSK	Outer_Full
2 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
3 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	N/A
4 (Note 3)	High				16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
5 (Note 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
6 (Note 4)	Low				16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
7 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	N/A
8	Default				16QAM	Outer_Full	DFT-s-OFDM QPSK	Outer_Full
9 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	Edge_1RB_Right
10 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	N/A
11 (Note 3)	High				16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Right
12 (Note 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	Edge_1RB_Left
13 (Note 4)	Low				16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Left
14 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	N/A
15	Default				16QAM	Outer_Full	DFT-s-OFDM 16QAM	Outer_Full
16 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	Edge_1RB_Right
17 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	N/A
18 (Note 3)	High				16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Right
19 (Note 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	Edge_1RB_Left
20 (Note 4)	Low				16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Left
21 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	N/A
22	Default				16QAM	Outer_Full	DFT-s-OFDM 64QAM	Outer_Full
23 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM 64QAM	Edge_1RB_Right
24 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM 64QAM	Edge_1RB_Left
25	Default				16QAM	Outer_Full	DFT-s-OFDM 256QAM	Outer_Full



26 (Note 3)	Low				16QAM	Outer_1RB _Left	DFT-s-OFDM 256QAM	Edge_1RB_ Right
27 (Note 4)	High				16QAM	Outer_1RB _Right	DFT-s-OFDM 256QAM	Edge_1RB_ Left
28	Default				16QAM	Outer_Full	CP-OFDM PI/2 BPSK	Outer_Full
29 (Note 3)	Default				16QAM	Outer_1RB _Left	CP-OFDM PI/2 BPSK	Edge_1RB_ Right
30 (Note 3)	Low				16QAM	Outer_1RB _Left	CP-OFDM PI/2 BPSK	N/A
31 (Note 3)	High				16QAM	N/A	CP-OFDM PI/2 BPSK	Edge_1RB_ Right
32 (Note 4)	Default				16QAM	Outer_1RB _Right	CP-OFDM PI/2 BPSK	Edge_1RB_ Left
33 (Note 4)	Low				16QAM	N/A	CP-OFDM PI/2 BPSK	Edge_1RB_ Left
34 (Note 4)	High				16QAM	Outer_1RB _Right	CP-OFDM PI/2 BPSK	N/A
35	Default				16QAM	Outer_Full	CP-OFDM QPSK	Outer_Full
36 (Note 3)	Default				16QAM	Outer_1RB _Left	CP-OFDM QPSK	Edge_1RB_ Right
37 (Note 3)	Low				16QAM	Outer_1RB _Left	CP-OFDM QPSK	N/A
38 (Note 3)	High				16QAM	N/A	CP-OFDM QPSK	Edge_1RB_ Right
39 (Note 4)	Default				16QAM	Outer_1RB _Right	CP-OFDM QPSK	Edge_1RB_ Left
40 (Note 4)	Low				16QAM	N/A	CP-OFDM QPSK	Edge_1RB_ Left
41 (Note 4)	High				16QAM	Outer_1RB _Right	CP-OFDM QPSK	N/A
42	Default				16QAM	Outer_Full	CP-OFDM 16QAM	Outer_Full
43 (Note 3)	Default				16QAM	Outer_1RB _Left	CP-OFDM 16QAM	Edge_1RB_ Right
44 (Note 3)	Low				16QAM	Outer_1RB _Left	CP-OFDM 16QAM	N/A
45 (Note 3)	High				16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_ Right
46 (Note 4)	Default				16QAM	Outer_1RB _Right	CP-OFDM 16QAM	Edge_1RB_ Left
47 (Note 4)	Low				16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_ Left
48 (Note 4)	High				16QAM	Outer_1RB _Right	CP-OFDM 16QAM	N/A
49	Default				16QAM	Outer_Full	CP-OFDM 64QAM	Outer_Full
50 (Note 3)	Low				16QAM	Outer_1RB _Left	CP-OFDM 64QAM	Edge_1RB_ Right
51 (Note 4)	High				16QAM	Outer_1RB _Right	CP-OFDM 64QAM	Edge_1RB_ Left
52	Default				16QAM	Outer_Full	CP-OFDM 256QAM	Outer_Full
53 (Note 3)	Low				16QAM	Outer_1RB _Left	CP-OFDM 256QAM	Edge_1RB_ Right
54 (Note 4)	High				16QAM	Outer_1RB _Right	CP-OFDM 256QAM	Edge_1RB_ Left

NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].

NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same  $N_{RB\_agg}$ , select the combination to test as follows:

- Lowest ENBW: NR component with lowest  $N_{RB}$  is tested.
- Highest ENBW: NR component with highest  $N_{RB}$  is tested.

NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.

NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.

NOTE 5: Outer\_Full defined as the transmission bandwidth configuration  $N_{RB}$  per channel bandwidth for the E-UTRA component as indicated in TS 36.521 [10] Table 5.4.2-1. Outer\_1RB\_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer\_1RB\_Right defined as 1 RB allocated at the right edge of the E-UTRA component.

NOTE 2: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.

#### 6.5B.2.1.1.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 6.5B.1.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command for the UE to reach  $P_{UMAX}$  level.
3. Measure the mean power over all component carriers for the EN-DC configuration. The period of measurement shall be at least the continuous duration of 1ms over consecutive active uplink slots. For TDD, only slots consisting of only UL symbols are under test. .
4. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.2.1.1.5-1. The centre frequency of the filter shall be stepped in continuous steps according to the same table. The measured power shall be recorded for each step. The measurement period shall capture the active TSs.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.5B.2.1.1.4.1-1, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-118 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

#### 6.5B.2.1.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 6.5B.2.1.2.5 Test requirements

The power of any UE emissions shall fulfil requirements in Table 6.5B.2.1.2.5-1.

**Table 6.5B.2.1.1.5-1: General spectrum emission mask for intra-band contiguous EN-DC**

$\Delta f_{\text{foob}}$ (MHz)	Spectrum emission limit (dBm)	Measurement bandwidth
$\pm 0 - 1$	$\text{Max}(\text{Round}(10 \cdot \log(0.15/\text{ENBW})), -24)$	30 kHz
$\pm 1 - 5$	$-10 + \text{TT}$	1 MHz
$\pm 5 - \text{ENBW}$	$-13 + \text{TT}$	1 MHz
$\pm \text{ENBW} -$ ( $\text{ENBW} + 5$ )	$-25 + \text{TT}$	1 MHz
NOTE: ENBW refers to the aggregated channel bandwidth in MHz as defined in sub-clause 5.3B.		

**Table 6.5B.2.1.1.5-2: Test Tolerance (Spectrum Emission Mask)**

$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6.0\text{GHz}$
1.5 dB	1.8 dB	1.8 dB

### 6.5B.2.1.2 Additional spectrum emissions mask for intra-band contiguous EN-DC

#### 6.5B.2.1.2.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions under the deployment scenarios where additional requirements are specified.

#### 6.5B.2.1.2.2 Test applicability

This test case applies to all types of E-UTRA power class 3 and power class UE release 15 and forward, supporting intra-band contiguous EN-DC.

#### 6.5B.2.1.2.3 Minimum conformance requirements

##### 6.5B.2.1.2.3.1 Minimum requirement for network signalled value "NS\_35"

For contiguous intra-band EN-DC configuration of DC\_(n)71AA when NS\_35 is indicated for the UE the requirements in table 6.5B.2.1.2.3-1 apply in the frequency ranges immediately adjacent and outside the aggregation of the said sub-blocks

When NS\_35 is indicated in the MCG and NS\_35 is indicated in the SCG the requirements in table 6.5B.2.1.2.3.1-1 apply in the frequency ranges immediately adjacent and outside the aggregated sub-blocks of the EN-DC configuration for DC\_(n)71AA.

**Table 6.5B.2.1.2.3.1-1: Additional requirements**

	Frequency offset of measurement filter centre frequency, $f_{\text{offset}}$	Minimum requirement (dBm)	Measurement bandwidth
$0 \text{ MHz} \leq \Delta f < 0.1 \text{ MHz}$	$0.015 \text{ MHz} \leq f_{\text{offset}} < 0.085 \text{ MHz}$	-13	30 kHz
$0.1 \text{ MHz} \leq \Delta f < \text{ENBW}$	$0.15 \text{ MHz} \leq f_{\text{offset}} < \text{ENBW} - 0.05 \text{ MHz}$	-13	100 kHz
$\text{ENBW} \leq \Delta f < \text{ENBW} + 5 \text{ MHz}$	$\text{ENBW} + 0.5 \text{ MHz} \leq f_{\text{offset}} < \text{ENBW} + 4.5 \text{ MHz}$	-25	1 MHz
NOTE: ENBW is the aggregated bandwidth of an E-UTRA sub-block and an adjacent NR sub-block; there is no frequency separation between the said sub-blocks. The sub-block bandwidths include any internal guard bands.			

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.1.2.1.

Exception requirements for both NR and E-UTRA are defined for this test when transmission on E-UTRA overlap in time with NR.LTE and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

No exception requirements for NR or E-UTRA are defined for this test when transmission on E-UTRA doesn't overlap in time with NR. LTE anchor agnostic approach is applied for this case and referred to as sub-test 2.

#### 6.5B.2.1.2.3.2 Minimum requirement for network signalled value "NS\_04"

Additional spectrum emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

The Band 41/n41 SEM transition point from -13 dBm/MHz to -25 dBm/MHz is based on the emission bandwidth. The emission bandwidth is defined as the width of the signal between two points, one below the carrier center frequency and one above the carrier center frequency, outside of which all emissions are attenuated at least 26 dB below the transmitter power. Since the 26 dB emission bandwidth is implementation dependent, the transmission bandwidths occupied by RBs is used for the SEM. The emission bandwidth for LTE carriers is document in 36.101 [5], and the emission bandwidth for NR carriers is documented in 38.101-1 [2]. The total emission bandwidth for contiguous intra-band EN-DC is the sum of the emission bandwidth for each CC plus the guard band between contiguous CCs.

When "NS\_04" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.5B.2.1.2.3.2-1.

**Table 6.5B.2.1.2.3.2-1: n41 SEM with NS\_04**

$\Delta f_{OOB}$ MHz	Spectrum emission limit (dBm)/ measurement bandwidth for each channel bandwidth						Measurement bandwidth
	10 MHz	15 MHz	20 MHz	40 MHz	50 MHz	> 50 MHz	
$\pm 0 - 1$	-18	-20	-21	-24	-25		30 kHz
$\pm 1 - 5$	-10						1 MHz
$\pm 5 - X$	-13						
$\pm X - (BW_{Channel} + 5 \text{ MHz})$	-25						
NOTE 1: X is defined as the sum of the emission bandwidth of the component carriers plus the guard band between contiguous CCs.							

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.1.2.2

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.5B.2.1.2.4 Test description

##### 6.5B.2.1.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial condition part is separated in two sub tests to verify different aspects of MPR. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

1. Sub test: with transmission overlap for all UE's

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in test configuration table 6.2B.3.1.4.1-1 through 6.2B.3.1.4.1-26. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

Table 6.5B.2.1.2.4.1-0: E-UTRA test configuration table

E-UTRA Test Parameters				
E-UTRA Channel Bandwidth	E-UTRA Test Frequency (Note 1)	Downlink	Uplink	
		N/A for A-MPR testing.	Modulation	RB allocation
20 MHz	Low range and High range (Note 2)		QPSK	100
NOTE 1: E-UTRA Test Frequency as specified in TS 36.508 [6] subclause 4.3.1				
NOTE 2: NR carrier shall be the outermost carrier during test.				

**Editor's note:** The following lines belong at the end of section 6.5B.2.1.2.4.1. As new tables are added to this section, these lines should always follow the tables.

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

11. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.2.1 for SS diagram and section A.3.2.1 for UE diagram.
  - 1.2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
  - 1.3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
  - 1.4 NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS 38.521-1[8].
  - 1.5. The UL Reference Measurement channels are set according to TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG link and NR CG link respectively.
  - 1.6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG link and NR CG link respectively.
  - 1.7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.2.1.2.4.3.
  - 1.8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.
2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same initial condition as in clause 6.2.3.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For initial conditions as in clause 6.5.3.3.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Same initial conditions as in clause 6.5.3.3.4.1 in TS 38.521-1 [8] with the following steps exception:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.5B.2.1.2.4.2 Test procedure

The test procedure part is separated in two sub tests to verify different aspects of Additional spectrum emissions mask for intra-band contiguous EN-DC. Sub test 2 is only applicable to UE's supporting dynamic power sharing.

##### 1. Sub test: with transmission overlap for all UE's

- 1.1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to table 6.2B.3.1.4.1-1 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
- 1.2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms from the first TPC command starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.
- 1.3. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.5B.2.1.2.5.1-1 thru 6.5B.2.1.2.5.2-1. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms).
- 1.4. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.2.1.2.5-1 thru 6.5B.2.1.2.5.2-1. The centre frequency of the filter shall be stepped in contiguous steps according to the same table. The measured power shall be recorded for each step. The measurement period shall capture the active time slots.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.2B.3.1.4.1-2, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-89 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

##### 2. Sub test: without transmission overlap for UE's supporting dynamic power sharing

Same test procedure as in clause 6.2.3.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power over all component carriers for the EN-DC configuration, which shall meet the requirements described in table 6.5B.2.1.2.5.1-1 thru 6.5B.2.1.2.5.2-1. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms).
4. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.2.1.2.5-1 thru 6.5B.2.1.2.5.2-1. The centre frequency of the filter shall be stepped in contiguous steps according to the same table. The measured power shall be recorded for each step. The measurement period shall capture the active time slots.

#### 6.5B.2.1.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1, with the following exceptions for each network signalled value.

**Editor's note: Exceptions to network signal values should be added as sub-clauses below.**

##### 6.5B.2.1.2.4.3.1 Message contents exceptions for network signalled value "NS\_35"

For "NS\_35" see A-MPR test case in table 6.2B.3.1.4.3.2-1 and table 6.2B.3.1.4.3.2-2.

##### 6.5B.2.1.2.4.3.2 Message contents exceptions for network signalled value "NS\_04"

For "NS\_04" see A-MPR test case in table 6.2B.3.1.4.3.1-1 and table 6.2B.3.1.4.3.1-2.

#### 6.5B.2.1.2.5 Test requirement

##### 6.5B.2.1.2.5.1 Test requirement for network signalled value "NS\_35"

When "NS\_35" is indicated in the cell measured UE mean power in the channel bandwidth, derived in step 3, shall fulfil requirements in table 6.2B.3.1.5.1-1, and the power of any UE shall not exceed the described values in table

6.5B.2.1.2.5.1-1. The requirements in the table apply in the frequency ranges immediately adjacent and outside the aggregation of the sub-blocks.

**Table 6.5B.2.1.2.5.1-1: Additional requirements for “NS\_35”**

$\Delta f_{\text{OoB}}$	Frequency offset of measurement filter centre frequency, $f_{\text{offset}}$	Minimum requirement [dBm]	Measurement bandwidth
$0 \text{ MHz} \leq \Delta f < 0.1 \text{ MHz}$	$0.015 \text{ MHz} \leq f_{\text{offset}} < 0.085 \text{ MHz}$	-11.5	30 kHz
$0.1 \text{ MHz} \leq \Delta f < \text{ENBW}$	$0.15 \text{ MHz} \leq f_{\text{offset}} < \text{ENBW} - 0.05 \text{ MHz}$	-11.5	100 kHz
$\text{ENBW} \leq \Delta f < \text{ENBW} + 5 \text{ MHz}$	$\text{ENBW} + 0.5 \text{ MHz} \leq f_{\text{offset}} < \text{ENBW} + 4.5 \text{ MHz}$	-23.5	1 MHz
NOTE: ENBW is the aggregated bandwidth of an E-UTRA sub-block and an adjacent NR sub-block; there is no frequency separation between the said sub-blocks. The sub-block bandwidths include any internal guard bands.			

#### 6.5B.2.1.2.5.2 Test requirement for network signalled value “NS\_04”

When “NS\_04” is indicated in the cell measured UE mean power in the channel bandwidth, derived in step 3, shall fulfil requirements in tables 6.2B.3.1.5.2-1, and the power of any UE shall not exceed the described values in table 6.5B.2.1.2.5.2-1. The requirements in the table apply in the frequency ranges immediately adjacent and outside the aggregation of the sub-blocks.

**Table 6.5B.2.1.2.5.2-1: Additional requirements for n41 SEM with NS\_04**

$\Delta f_{\text{OoB}}$ MHz	Spectrum emission limit (dBm)/ measurement bandwidth for each channel bandwidth						Measurement bandwidth
	10 MHz	15 MHz	20 MHz	40 MHz	50 MHz	> 50 MHz	
$\pm 0 - 1$	-16.5	-18.5	-19.5	-22.5	-23.5		30 kHz
$\pm 1 - 5$	-8.5						1 MHz
$\pm 5 - X$	-11.5						
$\pm X - (\text{BW}_{\text{Channel}} + 5 \text{ MHz})$	-23.5						
NOTE 1: X is defined as the sum of the emission bandwidth of the component carriers plus the guard band between contiguous CCs.							

#### 6.5B.2.1.3 Adjacent channel leakage ratio for intra-band contiguous EN-DC

**Editor's note: Future optimization of this test case might be possible by combining ACLR measurement with MPR measurement**

##### 6.5B.2.1.3.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to adjacent channels in terms of Adjacent Channel Leakage Power Ratio (ACLR).

##### 6.5B.2.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC.

##### 6.5B.2.1.3.3 Minimum conformance requirements

For EN-DC operation with an E-UTRA sub-block immediately adjacent to an NR sub-block, the ACLR is defined as the ratio of the filtered mean power centred on the aggregated sub-block bandwidth ENBW to the filtered mean power centred on an adjacent bandwidth of the same size ENBW at nominal channel spacing. The UE shall meet the ACLR minimum requirement  $\text{EN-DC}_{\text{ACLR}}$  specified in Table 6.5B.2.1.3-1 with ENBW the sum of the sub-block bandwidths.

The assigned channel power and adjacent channel power are measured with rectangular filters with measurement bandwidths specified in 6.5B.2.1.3-1.

**Table 6.5B.2.1.3-1: ACLR for intra-band EN-DC (contiguous sub-blocks)**

Parameter	Unit	Value
EN-DC <sub>ACLR</sub>	dBc	30
Measurement bandwidth of EN-DC channel		1.00*ENBW
Measurement bandwidth of adjacent channel		0.95*ENBW
Frequency offset of adjacent channel		ENBW / -ENBW
NOTE 1: ENBW is the aggregated bandwidth in MHz as defined in sub-clause 5.3B.		
NOTE 2: The frequency offset is that in between the centre frequencies of the measurement filters		

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.1.3.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 6.5B.2.1.3.4 Test description

##### 6.5B.2.1.3.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.5B.2.1.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.



**Table 6.5B.2.1.3.4.1-1: Test Configuration Table**

Initial Conditions								
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				NC, TL/VL, TL/VH, TH/VL, TH/VH				
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1				Low range, High range				
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1				Lowest N <sub>RB_agg</sub> , Highest N <sub>RB_agg</sub> (Note 2)				
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1				Lowest, Highest				
Test Parameters								
Test ID	Freq	ChBw	SCS	Downlink Configuration	EN-DC Uplink Configuration			
					E-UTRA Cell		NR Cell	
					Modulation	RB allocation (Note 5)	Modulation	RB allocation (NOTE 1)
1	Default	Default	Default	N/A for ACLR test case	16QAM	Outer_Full	DFT-s-OFDM PI/2 BPSK	Outer_Full
2 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
3 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM PI/2 BPSK	N/A
4 (Note 3)	High				16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Right
5 (Note 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
6 (Note 4)	Low				16QAM	N/A	DFT-s-OFDM PI/2 BPSK	Edge_1RB_Left
7 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM PI/2 BPSK	N/A
8	Default				16QAM	Outer_Full	DFT-s-OFDM QPSK	Outer_Full
9 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	Edge_1RB_Right
10 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM QPSK	N/A
11 (Note 3)	High				16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Right
12 (Note 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	Edge_1RB_Left
13 (Note 4)	Low				16QAM	N/A	DFT-s-OFDM QPSK	Edge_1RB_Left
14 (Note 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM QPSK	N/A
15	Default				16QAM	Outer_Full	DFT-s-OFDM 16QAM	Outer_Full
16 (Note 3)	Default				16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	Edge_1RB_Right
17 (Note 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM 16QAM	N/A

18 (Not e 3)	High				16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Right
19 (Not e 4)	Default				16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	Edge_1RB_Left
20 (Not e 4)	Low				16QAM	N/A	DFT-s-OFDM 16QAM	Edge_1RB_Left
21 (Not e 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM 16QAM	N/A
22	Default				16QAM	Outer_Full	DFT-s-OFDM 64QAM	Outer_Full
23 (Not e 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM 64QAM	Edge_1RB_Right
24 (Not e 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM 64QAM	Edge_1RB_Left
25	Default				16QAM	Outer_Full	DFT-s-OFDM 256QAM	Outer_Full
26 (Not e 3)	Low				16QAM	Outer_1RB_Left	DFT-s-OFDM 256QAM	Edge_1RB_Right
27 (Not e 4)	High				16QAM	Outer_1RB_Right	DFT-s-OFDM 256QAM	Edge_1RB_Left
28	Default				16QAM	Outer_Full	CP-OFDM QPSK	Outer_Full
29 (Not e 3)	Default				16QAM	Outer_1RB_Left	CP-OFDM QPSK	Edge_1RB_Right
30 (Not e 3)	Low				16QAM	Outer_1RB_Left	CP-OFDM QPSK	N/A
31 (Not e 3)	High				16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Right
32 (Not e 4)	Default				16QAM	Outer_1RB_Right	CP-OFDM QPSK	Edge_1RB_Left
33 (Not e 4)	Low				16QAM	N/A	CP-OFDM QPSK	Edge_1RB_Left
34 (Not e 4)	High				16QAM	Outer_1RB_Right	CP-OFDM QPSK	N/A
35	Default				16QAM	Outer_Full	CP-OFDM 16QAM	Outer_Full
36 (Not e 3)	Default				16QAM	Outer_1RB_Left	CP-OFDM 16QAM	Edge_1RB_Right
37 (Not e 3)	Low				16QAM	Outer_1RB_Left	CP-OFDM 16QAM	N/A

38 (Note 3)	High				16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Right
39 (Note 4)	Default				16QAM	Outer_1RB_Right	CP-OFDM 16QAM	Edge_1RB_Left
40 (Note 4)	Low				16QAM	N/A	CP-OFDM 16QAM	Edge_1RB_Left
41 (Note 4)	High				16QAM	Outer_1RB_Right	CP-OFDM 16QAM	N/A
42	Default				16QAM	Outer_Full	CP-OFDM 64QAM	Outer_Full
43 (Note 3)	Low				16QAM	Outer_1RB_Left	CP-OFDM 64QAM	Edge_1RB_Right
44 (Note 4)	High				16QAM	Outer_1RB_Right	CP-OFDM 64QAM	Edge_1RB_Left
45	Default				16QAM	Outer_Full	CP-OFDM 256QAM	Outer_Full
46 (Note 3)	Low				16QAM	Outer_1RB_Left	CP-OFDM 256QAM	Edge_1RB_Right
47 (Note 4)	High				16QAM	Outer_1RB_Right	CP-OFDM 256QAM	Edge_1RB_Left

NOTE 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].

NOTE 2: If the UE supports multiple CC combinations in the EN-DC configuration with the same  $N_{RB\_agg}$ , select the combination to test as follows:

- Lowest ENBW: NR component with lowest  $N_{RB}$  is tested.
- Highest ENBW: NR component with highest  $N_{RB}$  is tested.

NOTE 3: Applicable when E-UTRA cell carrier frequency is lower than NR cell carrier.

NOTE 4: Applicable when NR cell carrier frequency is lower than E-UTRA cell carrier.

NOTE 5: Outer\_Full defined as the transmission bandwidth configuration  $N_{RB}$  per channel bandwidth for the E-UTRA component as indicated in TS 36.521 [10] Table 5.4.2-1. Outer\_1RB\_Left defined as 1 RB allocated at the left edge of the E-UTRA component. Outer\_1RB\_Right defined as 1 RB allocated at the right edge of the E-UTRA component.

NOTE 6: DFT-s-OFDM PI/2 BPSK test applies only for UEs which supports half Pi BPSK in FR1

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.

#### 6.5B.2.1.3.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5B.2.1.3.4.1-1 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Send continuously uplink power control "up" commands to the UE for NR and E-UTRA carrier until the UE transmits at its  $P_{UMAX}$  level; allow at least 200ms for the UE to reach  $P_{UMAX}$  level.
3. Measure the filtered mean power of the transmitted signal centered on the aggregated sub-block ENBW with a measurement filter of bandwidth according to Table 6.5B.2.1.3-1. The period of the measurement shall be at least the continuous duration of 1ms over consecutive active uplink slots. For TDD, only slots consisting of only UL symbols are under test. .
4. Measure the filtered mean power of the first adjacent channel on both lower and upper side of the assigned NR + E-UTRA channel, respectively with a frequency offset and measurement filter of bandwidth according to Table 6.5B.2.1.3-1.
5. Calculate the ratios of the power between the values measured in step 5 over step 6 for lower and upper side respectively.

NOTE 1: When switching to DFT-s-OFDM waveform, as specified in the test configuration table 6.5B.2.1.1.4.1-1, send an NR RRCReconfiguration message according to TS 38.508-1 [6] clause 4.6.3 Table 4.6.3-118 PUSCH-Config with TRANSFORM\_PRECODER\_ENABLED condition.

#### 6.5B.2.1.3.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.1.

#### 6.5B.2.1.3.5 Test requirement

The measured adjacent channel power ratio, derived in step 5, shall be less than or equal to  $30 + TT$  dBc , where

- $TT = 0.8$  dB for  $f \leq 4.0$ GHz,  $TT = 1.0$  dB for  $4.0$ GHz  $< f \leq 6.0$ GHz,

### 6.5B.2.2 Out-of-band emissions for Intra-band non-contiguous EN-DC

#### 6.5B.2.2.1 Spectrum emissions mask for intra-band non-contiguous EN-DC

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- For  $W_{gap} < NR \Delta f_{OOB} + E-UTRA \Delta f_{OOB}$ , test description and test requirements are FFS.

##### 6.5B.2.2.1.1 Test purpose

Same test purpose as in clause 6.5.2.2 in TS 38.521-1 [8] for the NR carrier.

##### 6.5B.2.2.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

##### 6.5B.2.2.1.3 Minimum conformance requirements

The spectral emission mask for intra-band non-contiguous EN-DC is a composite of the emission mask for each CC with the level set to the maximum value from each mask for each frequency outside of the transmission bandwidth of either carrier. A composite spectrum emission mask is a combination of individual CC spectrum emissions masks. Where two masks overlap the most relaxed limit is used. Composite spectrum emission mask applies to frequencies up to  $\pm \Delta f_{OOB}$  starting from the edges of the sub-blocks. If for some frequency an individual CC spectrum emission mask overlaps with the bandwidth of another CC then the emission mask does not apply for that frequency.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.2.1.

No exception requirements applicable to NR or LTE when  $W_{\text{gap}} > NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ . LTE anchor agnostic approach is applied when  $W_{\text{gap}} > NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ .

Exception requirements for both NR and E-UTRA are defined for this test when  $W_{\text{gap}} < NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$  and therefore LTE anchor agnostic approach is not applied when  $W_{\text{gap}} < NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ .

#### 6.5B.2.2.1.4 Test description

For  $W_{\text{gap}} > NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ :

Same test description as in clause 6.5.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.5.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 6.5.2.2.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.5.2.2.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of 1ms over consecutive active uplink slots. For TDD, only slots consisting of only UL symbols are under test.

For  $W_{\text{gap}} < NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ :

FFS.

#### 6.5B.2.2.1.5 Test requirement

For  $W_{\text{gap}} > NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ :

Power of any UE emission shall fulfil requirements in Table 6.5.2.2.5-1 defined in TS 38.521-1 [8] for the NR carrier.

For  $W_{\text{gap}} < NR \Delta f_{\text{OOB}} + E\text{-UTRA } \Delta f_{\text{OOB}}$ :

FFS.

#### 6.5B.2.2.3 Adjacent channel leakage ratio for intra-band non-contiguous EN-DC

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- For  $W_{\text{gap}} < NR \text{ adjacent channel} + E\text{-UTRA adjacent channel}$ , test description and test requirements are FFS.

#### 6.5B.2.2.3.1 Test purpose

Same test purpose as in clause 6.5.2.4.1.1 in TS 38.521-1 [8] for the NR carrier.

#### 6.5B.2.2.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

#### 6.5B.2.2.3.3 Minimum conformance requirements

For intra-band non-contiguous EN-DC, the EN-DC Adjacent Channel Leakage power Ratio (EN-DC<sub>ACLR</sub>) is the ratio of the sum of the filtered mean powers centred on the assigned E-UTRA and NR sub-block frequencies to the filtered mean power centred on an adjacent channel frequency at nominal channel spacing. In case the sub-block gap bandwidth  $W_{\text{gap}}$  is smaller than a E-UTRA or NR sub-block bandwidth, no EN-DC<sub>ACLR</sub> requirement is set for the corresponding sub-block for the gap. The assigned EN-DC sub-block power and adjacent channel power are measured with rectangular filters with measurement bandwidths specified in [4] for the E-UTRA sub-block, and [2],[3] for the NR sub-block. If the measured adjacent channel power is greater than  $-50\text{dBm}$  then the EN-DC<sub>ACLR</sub> shall be higher than the value specified in for E-UTRA<sub>ACLR</sub> and NR<sub>ACLR</sub>.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.2.3.

No exception requirements applicable to NR or LTE when  $W_{\text{gap}} > \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ . LTE anchor agnostic approach is applied when  $W_{\text{gap}} > \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ .

Exception requirements for both NR and E-UTRA are defined for this test when  $W_{\text{gap}} < \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$  and therefore LTE anchor agnostic approach is not applied when  $W_{\text{gap}} < \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ .

#### 6.5B.2.2.3.4 Test description

For  $W_{\text{gap}} > \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ :

Same test description as in clause 6.5.2.4.1.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.5.2.4.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 6.5.2.4.1.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.5.2.4.1.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of 1ms over consecutive active uplink slots. For TDD, only slots consisting of only UL symbols are under test.

For  $W_{\text{gap}} < \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ :

FFS.

#### 6.5B.2.2.3.5 Test requirement

For  $W_{\text{gap}} > \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ :

If the measured adjacent channel power is greater than  $-50\text{ dBm}$  then the measured NR ACLR shall be higher than the limits in table 6.5.2.4.1.5-2 defined in clause 6.5.2.4.1.5 in TS 38.521-1 [8] for the NR carrier.

For  $W_{\text{gap}} < \text{NR adjacent channel} + \text{E-UTRA adjacent channel}$ :

FFS.

### 6.5B.2.3 Out-of-band emissions for Inter-band EN-DC within FR1

#### 6.5B.2.3.1 Spectrum emissions mask for Inter-band EN-DC within FR1

##### 6.5B.2.3.1.1 Test purpose

Same test purpose as in clause 6.5.2.2 in TS 38.521-1 [8] for the NR carrier.

##### 6.5B.2.3.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

##### 6.5B.2.3.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.2.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.3.

##### 6.5B.2.3.1.4 Test description

Same test description as in clause 6.5.2.2.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.5.2.2.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 6.5.2.2.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.5.2.2.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

##### 6.5B.2.3.1.5 Test requirement

Power of any UE emission shall fulfil requirements in Table 6.5.2.2.5-1 defined in TS 38.521-1 [8] for the NR carrier.6.5B.2.3.2.

#### 6.5B.2.3.2 Additional Spectrum emissions mask for Inter-band EN-DC within FR1

#### 6.5B.2.3.3 Adjacent channel leakage ratio for inter-band EN-DC within FR1

##### 6.5B.2.3.3.1 Test purpose

Same test purpose as in clause 6.5.2.4.1.1 in TS 38.521-1 [8].



#### 6.5B.2.3.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.5B.2.3.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.4.1.3 in TS 38.521-1 [8] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.5B.2.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied

#### 6.5B.2.3.3.4 Test description

Same test description as in clause 6.5.2.4.1.4 in TS 38.521-1 [TBD] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1.

For Initial conditions as in clause 6.5.2.4.1.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 6.5.2.4.1.4.1 in TS 38.521-1 [8] is replaced by the following two steps:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Same test procedure as in clause 6.5.2.4.1.4.2 in TS 38.521-1 [8] with the following steps exception:

3. Measure the mean power of the UE in the channel bandwidth of the radio access mode according to the test configuration. The period of the measurement shall be at least the continuous duration of one active sub-frame (1ms) and in the uplink symbols. For TDD slots with transient periods are not under test.

#### 6.5B.2.3.3.5 Test requirement

If the measured adjacent channel power is greater than  $-50$  dBm then the measured NR ACLR shall be higher than the limits in table 6.5.2.4.1.5-2 defined in clause 6.5.2.4.1.5 in TS 38.521-1 [8] for the NR carrier.

### 6.5B.2.4 Out-of-band emissions for Inter-band EN-DC including FR2

#### 6.5B.2.4.1 Spectrum emissions mask for Inter-band EN-DC including FR2

##### 6.5B.2.4.1.1 Test purpose

Same test purpose as in clause 6.5.2.1.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.5B.2.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

##### 6.5B.2.4.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.5B.2.4.1.4 Test description

##### 6.5B.2.4.1.4.1 Initial conditions

Same test description as in clause 6.5.2.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.5.2.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.2.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.2.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.1.5 Test requirement

Same test requirement as in clause 6.5.2.1.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT created a 5. duplication!!]

#### 6.5B.2.4.1.2 Spectrum emissions mask for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **Test configuration table and Connection diagram in TS 38.521-2 are TBD**
- **The referred test case 6.5A.2.1.1 in TS 38.521-2 is incomplete.**

##### 6.5B.2.4.1.2.1 Test purpose

Same test purpose as in clause 6.5.2.1.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.5B.2.4.1.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

##### 6.5B.2.4.1.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

#### 6.5B.2.4.1.2.4 Test description

##### 6.5B.2.4.1.2.4.1 Initial condition

Same test description as in clause 6.5A.2.1.1.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.1.2.5 Test Requirements

Same test requirement as in clause 6.5A.2.1.1.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.5B.2.4.1.3 Spectrum emissions mask for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.2.1.2 in TS 38.521-2 is incomplete.

##### 6.5B.2.4.1.3.1 Test purpose

Same test purpose as in clause 6.5.2.1.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.5B.2.4.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4CCs.

##### 6.5B.2.4.1.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.1.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

##### 6.5B.2.4.1.3.4 Test description

###### 6.5B.2.4.1.3.4.1 Initial condition

Same test description as in clause 6.5A.2.1.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.1.3.5 Test Requirements

Same test requirement as in clause 6.5A.2.1.2.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.1.4 Spectrum emissions mask for Inter-band EN-DC including FR2 (5 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.2.1.3 in TS 38.521-2 is incomplete.

#### 6.5B.2.4.1.4.1 Test purpose

Same test purpose as in clause 6.5.2.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.1.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5CCs.

#### 6.5B.2.4.1.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.1.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.1.4.

#### 6.5B.2.4.1.4.4 Test description

##### 6.5B.2.4.1.4.4.1 Initial condition

Same test description as in clause 6.5A.2.1.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.1.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.1.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.1.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.1.4.5 Test Requirements

Same test requirement as in clause 6.5A.2.1.3.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT end of 5. duplication!!]

#### 6.5B.2.4.3 Adjacent channel leakage ratio for Inter-band EN-DC including FR2

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- The referred test case 6.5.2.3 in TS 38.521-2 is incomplete.

#### 6.5B.2.4.3.1 Test purpose

Same test purpose as in clause 6.5.2.3.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 6.5B.2.4.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 6.5B.2.4.3.4 Test description

##### 6.5B.2.4.3.4.1 Initial conditions

Same test description as in clause 6.5.2.3.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1. For Initial conditions as in clause 6.5.2.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.2.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.2.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.3.5 Test requirement

Same test requirement as in clause 6.5.2.3.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT created a 6. duplication!!]

#### 6.5B.2.4.3.2 Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.2.2.1 in TS 38.521-2 is incomplete.

#### 6.5B.2.4.3.2.1 Test purpose

Same test purpose as in clause 6.5.2.3.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.3.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

#### 6.5B.2.4.3.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

#### 6.5B.2.4.3.2.4 Test description

##### 6.5B.2.4.3.2.4.1 Initial condition

Same test description as in clause 6.5A.2.2.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.2.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.2.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.2.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.3.2.5 Test Requirements

Same test requirement as in clause 6.5A.2.2.1.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.3.3 Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.2.2.2 in TS 38.521-2 is incomplete.

#### 6.5B.2.4.3.3.1 Test purpose

Same test purpose as in clause 6.5.2.3.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.2.4.3.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4CCs.

#### 6.5B.2.4.3.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

#### 6.5B.2.4.3.3.4 Test description

##### 6.5B.2.4.3.3.4.1 Initial condition

Same test description as in clause 6.5A.2.2.2.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.2.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.2.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.2.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.3.3.5 Test Requirements

Same test requirement as in clause 6.5A.2.2.2.5 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.5B.2.4.3.4 Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (5 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.2.2.3 in TS 38.521-2 is incomplete.

#### 6.5B.2.4.3.4.1 Test purpose

Same test purpose as in clause 6.5.2.3.1 in TS 38.521-2 [9] for the *NR* carrier.

#### 6.5B.2.4.3.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5CCs.

#### 6.5B.2.4.3.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.2.3.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to *NR* or *LTE*. *LTE* anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.2.4.

#### 6.5B.2.4.3.4.4 Test description

##### 6.5B.2.4.3.4.4.1 Initial condition

Same test description as in clause 6.5A.2.2.3.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.2.2.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.2.2.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state *RRC\_CONNECTED* with generic procedure parameters *Connectivity EN-DC*, *DC bearer MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.2.2.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.2.4.3.4.5 Test Requirements

Same test requirement as in clause 6.5A.2.2.3.5 in TS 38.521-2 [9] for the *NR* carrier.



[IS: 5446 NTT end of 6 duplication!!]

### 6.5B.3 Spurious emissions for EN-DC

- Editor's note
- Working assumption: E-UTRA is not tested during test procedure.
- Spurious emission for intra-band non-contiguous EN-DC is FFS.

Spurious emissions are emissions which are caused by unwanted transmitter effects such as harmonics emission, parasitic emissions, intermodulation products and frequency conversion products, but exclude out of band emissions. The spurious emission limits are specified in terms of general requirements inline with SM.329 [3] and *NR* operating band requirement to address UE co-existence.

To improve measurement accuracy, sensitivity and efficiency, the resolution bandwidth may be smaller than the measurement bandwidth. When the resolution bandwidth is smaller than the measurement bandwidth, the result should be integrated over the measurement bandwidth in order to obtain the equivalent noise bandwidth of the measurement bandwidth.

#### 6.5B.3.1 Spurious Emissions for intra-band contiguous EN-DC

##### 6.5B.3.1.1 General spurious emissions for intra-band contiguous EN-DC

###### 6.5B.3.1.1.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions.

###### 6.5B.3.1.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band EN-DC.

###### 6.5B.3.1.1.3 Minimum conformance requirements

The general spurious emissions requirements specified in sub-clause 6.6.3.1 of TS36.521-1[10] and sub-clause 6.5.3.1 of TS38.521-1[8] apply beyond any frequencies for which the out-of-band emissions requirements in sub-clause 6.5B.2.1 of TS 38.101-3[4] apply.

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.3.1.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

###### 6.5B.3.1.1.4 Test description

###### 6.5B.3.1.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the Subscriber Station (SS) to take with the UE to reach the correct measurement state.

The initial test configurations for E-UTRA consist of the test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1, with the exception that the E-UTRA channel bandwidth is the lowest supported value in Table 5.3B.1.3-1 for the EN-DC contiguous configuration under test.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.2.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing are shown in Table 6.5B.3.1.1.4.1-1 for NR band. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 38.521-1 Annex C2.

Table 6.5B.3.1.1.4.1-1: NR test configuration table

Initial Conditions			
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		Normal	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Mid range	
Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1		Highest $N_{RB\_agg}$ (NOTE1, 2)	
Test SCS as specified in Table 5.3.5-1		Lowest	
Test parameters			
Test ID	Downlink Configuration	Uplink Configuration	
		Modulation	NR RB allocation
	N/A for Spurious emission testing.		
1		CP-OFDM QPSK	Edge_1RB_Left
2		CP-OFDM QPSK	Edge_1RB_Right
3		CP-OFDM QPSK	Outer Full
NOTE 1: Test Channel Bandwidths are checked separately for each NR band, which applicable channel bandwidths are specified in Table 5.3.5-1 of 38.521-1 [8].			
NOTE 2: Lowest and highest allowed NR channel BW as specified in Table 5.3B.1.3-1. If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested..			

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-URA cell are set up according to TS 36.508 [11] subclause 4.4.3. E-UTRA downlink signal level, and uplink signal level are set according to Table 4.6-1.
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. The NR UL Reference Measurement channels are set according to Table 6.5B.3.1.1.4.1-1.
6. Set up the NR and E-UTRA test frequencies so that NR carrier is located at the lower frequency side as specified in Table 5.3B.1.2-1. Repeat each testing with E-UTRA carrier frequency is located at the lower side as specified in Table 5.3B.1.2-1.
7. NR propagation conditions are set according to B.0 of TS38.521-1[8] E-UTRA propagation conditions are set according to B.0 of TS36.521-1[10].
8. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters *Connectivity* EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.3.1.1.4. 3.
9. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.5B.3.1.1.4.2 Test Procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5.3.1.4.1-1 of TS38.521-1[8]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC. 3. NR SS send continuously uplink power control "up" commands in the uplink scheduling information to the UE until the UE transmits at PUMAX level.
4. Measure the mean power of each component carriers for the EN-DC configuration, which shall meet the requirements described in table Table 6.2B.1.2.5-1. The period of the measurement shall be at least the continuous duration of one sub-frame (1ms).

5. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.3.1.1.5-1. The centre frequency of the filter shall be stepped in contiguous steps according to table 6.5B.3.1.1.5-1. The measured power shall be verified for each step. The measurement period shall capture the active time slots

#### 6.5B.3.1.1.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6

#### 6.5B.3.1.1.5 Test Requirement

The measured average power of spurious emission, derived in step 5, shall not exceed the described value in Table 6.5B.3.1.1.5-1.

Unless otherwise stated, the spurious emission limits apply for the frequency ranges that are more than  $\Delta f_{\text{OOB}}$  (MHz) from the edge of the channel bandwidth shown in Table 6.5.3.1.5-1 of TS38.521-1[8].

NOTE: For measurement conditions at the edge of each frequency range, the lowest frequency of the measurement position in each frequency range should be set at the lowest boundary of the frequency range plus MBW/2. The highest frequency of the measurement position in each frequency range should be set at the highest boundary of the frequency range minus MBW/2. MBW denotes the measurement bandwidth defined for the protected band.

**Table 6.5B.3.1.1.5-1: General spurious emissions test requirements**

Frequency Range	Maximum Level	Measurement bandwidth	NOTE
$9 \text{ kHz} \leq f < 150 \text{ kHz}$	-36 dBm	1 kHz	
$150 \text{ kHz} \leq f < 30 \text{ MHz}$	-36 dBm	10 kHz	
$30 \text{ MHz} \leq f < 1000 \text{ MHz}$	-36 dBm	100 kHz	
$1 \text{ GHz} \leq f < 12.75 \text{ GHz}$	-30 dBm	1 MHz	
	-25 dBm	1 MHz	3
$12.75 \text{ GHz} \leq f < 5\text{th}$ harmonic of the upper frequency edge of the UL operating band in GHz	-30 dBm	1 MHz	1
$12.75 \text{ GHz} < f < 26 \text{ GHz}$	-30 dBm	1 MHz	2
NOTE 1: Applies for Band that the upper frequency edge of the UL Band more than 2.69 GHz.			
NOTE 2: Applies for Band that the upper frequency edge of the UL Band more than 5.2 GHz.			
NOTE 3: Applies for Band n41, CA configurations including Band n41, and EN-DC configurations that include n41 specified in sub-clause 5.2B of [4] when NS_04 is signalled.			

#### 6.5B.3.1.2 Spurious emission band UE co-existence for intra-band contiguous EN-DC

##### 6.5B.3.1.2.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions for band UE co-existence for intra-band contiguous EN-DC.

##### 6.5B.3.1.2.2 Test applicability

This test case applies to all types of NR UE release 15 and forward supporting intra-band contiguous EN-DC.

##### 6.5B.3.1.2.3 Minimum conformance requirements

This clause specifies the requirements for the specified EN-DC configurations for coexistence with protected bands.

The requirements in Table 6.5B.3.1.2.3-1 apply on each component carrier with all component carriers are active.

**Table 6.5B.3.1.2.3-1: Requirements for intra band contiguous EN-DC**

EN-DC Configuration	Spurious emission						
	Protected band	Frequency range (MHz)			Maximum Level (dBm)	MBW (MHz)	NOTE
...							
DC_(n)71B	E-UTRA Band 4, 5, 12, 13, 14, 17, 24, 26, 30, 48, 66	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 2, 25, 41, 70	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 29	F <sub>DL_low</sub> F <sub>DL_low</sub>	-	F <sub>DL_high</sub> F <sub>DL_high</sub>	-38	1	3
	E-UTRA Band 71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	3
...	E-UTRA Band 40	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	[-40]	1	
<p>NOTE 1: F<sub>DL_low</sub> and F<sub>DL_high</sub> refer to each E-UTRA frequency band specified in Table 5.2-1 of TS36.121-1[10].</p> <p>NOTE 2: As exceptions, measurements with a level up to the applicable requirements defined in Table 6.5B.3.1.1.5-1 are permitted for each assigned E-UTRA carrier used in the measurement due to 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic spurious emissions. Due to spreading of the harmonic emission the exception is also allowed for the first 1 MHz frequency range immediately outside the harmonic emission on both sides of the harmonic emission. This results in an overall exception interval centred at the harmonic emission of (2MHz + N x L<sub>CRB</sub> x 180kHz), where N is 2, 3, 4, 5 for the 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic respectively. The exception is allowed if the measurement bandwidth (MBW) totally or partially overlaps the overall exception interval.</p> <p>NOTE 3: These requirements also apply for the frequency ranges that are less than F<sub>OOB</sub> (MHz) in Table 6.6.3.1-1 and Table 6.6.3.1A-1 [2] from the edge of the channel bandwidth.</p>							

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.3.1.2.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

6.5B.3.1.2.4 Test description

6.5B.3.1.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.2.1, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 6.5B.3.1.2.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 6.5B.3.1.2.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1		Lowest and Highest $N_{RB\_agg}$ (Note 3)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest SCS per Channel Bandwidth			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A for Spurious emission.	QPSK	Outer_Full	CP-OFDM QPSK	Edge_1RB_Left
2		QPSK	Outer_Full	CP-OFDM QPSK	Edge_1RB_Right
3		QPSK	Outer_Full	CP-OFDM QPSK	Outer Full
Note 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8]. Note 2: Outer_Full defined as the transmission bandwidth configuration $N_{RB}$ per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1. Note 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same aggregated channel BW, only the combination with the highest NR BW is tested.					

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. E-UTRA downlink signals are initially set up according to Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS 36.521-1 [10].
4. NR downlink signals are initially set up according to Annex C.0, C.1 and C.2, and uplink signals according to Annex G.0, G.1, G.2, G.3.0 of TS 38.521-1 [8].
5. The UL Reference Measurement channels are set up according to TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
6. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG, respectively.
7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.3.1.2.4.3.

#### 6.5B.3.1.2.4.2 Test Procedure

1. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to Table 6.6.3.1.4.1-1 of TS36.521-1[10]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5.3.1.4.1-1 of TS38.521-1[8]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Both NR and E-UTRA SS send continuously uplink power control "up" commands in the uplink scheduling information to the UE until the UE transmits at  $P_{UMAX}$  level.

4. Measure the mean power of each component carriers for the EN-DC configuration, which shall meet the requirements described in table Table 6.2B.1.2.5-1. The period of the measurement shall be at least the continuous duration of one sub-frame (1ms).
5. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table Table 6.5B.3.1.2.3-1. The centre frequency of the filter shall be stepped in contiguous steps according to table 6.5B.3.1.2.3-1. The measured power shall be verified for each step. The measurement period shall capture the active time slots.

#### 6.5B.3.2.1.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 6.5B.3.1.2.5 Test Requirement

Test requirements for Spurious Emissions UE Co-existence for intra-band contiguous EN-DC are the same as described in minimum requirements and are not repeated in this section.

### 6.5B.3.2 Spurious Emissions for intra-band non-contiguous EN-DC

**Editor's Note: Wgap is TBD in TS 38.101-3 for this test case**

#### 6.5B.3.2.1 General spurious emissions for Intra-band non-contiguous EN-DC

##### 6.5B.3.2.1.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions.

##### 6.5B.3.2.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward supporting intra-band non-contiguous EN-DC.

##### 6.5B.3.2.1.3 Minimum conformance requirements

The general spurious emissions requirements specified in sub-clause 6.6.3.1 of TS36.521-1[10] and sub-clause 6.5.3.1 of TS38.521-1[8] apply beyond any frequencies for which the out-of-band emissions requirements in sub-clause 6.5B.2.2 of TS 38.101-3[4] apply.

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.3.2.1.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.5B.3.2.1.4 Test description

###### 6.5B.3.2.1.4.1 Initial Conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations for E-UTRA consist of the test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1, with the exception that the E-UTRA channel bandwidth is the lowest supported value in Table 5.3B.1.3-1 for the EN-DC non-contiguous configuration under test and parameters specified in Table 6.5B.3.2.1.4.1-1.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.2.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing are shown in Table 6.5B.3.2.1.4.1-1 for NR band. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 38.521-1 Annex C2.

**Table 6.5B.3.2.1.4.1-1: Test configuration table**

Initial Conditions			
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		Normal	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		MaxWGap	
Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1		Highest N <sub>RB_agg</sub> (NOTE1, 2)	
Test SCS as specified in Table 5.3.5-1		Lowest	
Test parameters			
Test ID	Downlink Configuration	Uplink Configuration	
		Modulation	NR RB allocation
	N/A for Spurious emission testing.		
1		CP-OFDM QPSK	Edge_1RB_Left
2		CP-OFDM QPSK	Edge_1RB_Right
3		CP-OFDM QPSK	Outer Full
NOTE 1: Test Channel Bandwidths are checked separately for each NR band, which applicable channel bandwidths are specified in Table 5.3.5-1 of 38.521-1 [8].			
NOTE 2: Lowest and highest allowed NR channel BW as specified in Table 5.3B.1.3-1. If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg, only the combination with the highest NRB_SCG is tested.			

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1. and propagation conditions are set according to Annex B.0 of TS36.521-1[10].
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. The UL Reference Measurement channels for NR are set according to Table 6.5B.3.2.1.4.1-1.
6. NR propagation conditions are set according to Annex B.0 of TS 38.521-1 [8].
7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.3.2.1.4.3.
8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 6.5B.3.2.1.4.2 Test Procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5.3.1.4.1-1 of TS38.521-1[8]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. NR carrier sends continuously uplink power control "up" commands in the uplink scheduling information to the UE until the UE transmits at PUMAX level.
3. Measure the power of the transmitted NR signal with a measurement filter of bandwidths according to table 6.5.3.1.5-1 in TS 38.521-1 [8]. The centre frequency of the filter shall be stepped in contiguous steps according to table 6.5.3.1.5-1 in TS 38.521-1 [8]. The measured power shall be verified for each step. The measurement period shall capture the active time slots.

## 6.5B.3.2.1.4. 3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

## 6.5B.3.2.1.5 Test Requirement

Same test requirement as in clause 6.5B.3.1.1.5.

## 6.5B.3.2.2 Spurious emission band UE co-existence for intra-band non-contiguous EN-DC

**Editor's note: Wgap for intra-band non-contiguous EN-DC is FFS in TS 38.508-1.**

## 6.5B.3.2.2.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions for band UE co-existence for intra-band non-contiguous EN-DC.

## 6.5B.3.2.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward supporting intra-band non-contiguous EN-DC.

## 6.5B.3.2.2.3 Minimum conformance requirements

This clause specifies the requirements for the specified EN-DC configurations for co-existence with protected bands.

The requirements in Table 6.5B.3.2.2.3-1 apply with all component carriers are active.

**Table 6.5B.3.2.2.3-1: Requirements for intra-band non-contiguous EN-DC**

EN-DC Configuration	Spurious emission						
	Protected band	Frequency range (MHz)		Maximum Level (dBm)	MBW (MHz)	NOTE	
...							
DC_41A_n41A	E-UTRA Band 1, 2, 3, 4, 5, 8, 10, 12, 13, 14, 17, 24, 25, 26, 27, 28, 29, 34, 39, 42, 44, 45, 48, 50, 51, 66, 70, 71, 73, 74 NR Band n77, n78 and n79	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 30, 40	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	[-40]	1	
...							
NOTE 1: F <sub>DL_low</sub> and F <sub>DL_high</sub> refer to each E-UTRA frequency band specified in Table 5. 2-1 of TS36.121-1[10].							
NOTE 2: As exceptions, measurements with a level up to the applicable requirements defined in Table 6.5.3.1.3-2 of TS38.521-1[8] are permitted for each assigned E-UTRA carrier used in the measurement due to 2 <sup>nd</sup> , 3 <sup>rd</sup> , 4 <sup>th</sup> or 5 <sup>th</sup> harmonic spurious emissions. Due to spreading of the harmonic emission the exception is also allowed for the first 1 MHz frequency range immediately outside the harmonic emission on both sides of the harmonic emission. This results in an overall exception interval centred at the harmonic emission of (2MHz + N x L <sub>CRB</sub> x 180kHz), where N is 2, 3, 4, 5 for the 2 <sup>nd</sup> , 3 <sup>rd</sup> , 4 <sup>th</sup> or 5 <sup>th</sup> harmonic respectively. The exception is allowed if the measurement bandwidth (MBW) totally or partially overlaps the overall exception interval							
NOTE 3: Applicable when co-existence with PHS system operating in 1884.5 - 1915.7 MHz.							
NOTE 4: This requirement applies when the NR carrier is confined within 2545-2575MHz or 2595-2645MHz and the channel bandwidth is 10 or 20 MHz.							

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.3.2.2.

Exception requirements are applicable for NR but not for E-UTRA within this test. LTE anchor agnostic approach is not applied. E-UTRA configuration is included but E-UTRA measurements are not performed.



## 6.5B.3.2.2.4 Test description

## 6.5B.3.2.2.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.2.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing are shown in Table 6.5B.3.2.2.4.1-1 for E-UTRA and Table 6.5B.3.2.2.4.1-2 for NR. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in Annex TS 36.521-1 [10] Annex C and in TS 38.521-1 Annex C2 for LTE link and NR link respectively.

**Table 6.5B.3.2.2.4.1-1: Test configuration table**

Initial Conditions					
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1		Lowest and Highest $N_{RB\_agg}$ (Note 3)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest SCS per Channel Bandwidth			
Test Parameters					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A for Spurious emission.	QPSK	Outer_Full	CP-OFDM QPSK	Edge_1RB_Left
2		QPSK	Outer_Full	CP-OFDM QPSK	Edge_1RB_Right
3		QPSK	Outer_Full	CP-OFDM QPSK	Outer Full
Note 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8]. Note 2: Outer_Full defined as the transmission bandwidth configuration $N_{RB}$ per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1. Note 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same aggregated channel BW, only the combination with the highest NR BW is tested.					

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1.1 for SS diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for the cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. E-UTRA downlink signals are initially set up according to Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS 36.521-1 [10].
4. NR downlink signals are initially set up according to Annex C.0, C.1 and C.2, and uplink signals according to Annex G.0, G.1, G.2, G.3.0 of TS 38.521-1 [8].
5. The UL Reference Measurement channels are set according to TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
6. For each EN-DC combination specified in Table 5.3B.1.3-1, channel spacing between NR and E-UTRA is specified according to subclause 5.4B.1.
7. Propagation conditions are set according to TS 36.521-1 [10] Annex B and TS 38.521-1 [8] Annex B for E-UTRA link and NR link respectively.

8. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.3.2.2.4.3.

#### 6.5B.3.2.2.4.2 Test Procedure

1. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to Table 6.5B.3.2.2.4.1-1. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5B.3.2.2.4.1-1. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Send continuously uplink power control "up" commands to the UE for both NR and E-UTRA carriers until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.
4. Measure the mean power of each component carriers for the EN-DC configuration, which shall meet the requirements described in Table 6.2B.1.2.5-1. The period of the measurement shall be at least the continuous duration of one sub-frame (1ms).
5. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.3.2.2.3-1. The centre frequency of the filter shall be stepped in contiguous steps according to the same table. The measured power shall be recorded for each step. The measurement period shall capture the active time slots.

#### 6.5B.3.2.2.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 6.5B.3.2.2.5 Test Requirement

Test requirements for Spurious Emissions UE Co-existence for intra-band non-contiguous EN-DC are the same as the minimum requirements described in subclause 6.5B.3.2.2.3 and are not repeated in this section.

### 6.5B.3.3 Spurious Emissions for Inter-band EN-DC within FR1

#### 6.5B.3.3.1 General spurious emissions for Inter-band EN-DC within FR1

##### 6.5B.3.3.1.1 Test purpose

Same test purpose as in clause 6.5B.3.1.1.1.

##### 6.5B.3.3.1.2 Test applicability

This test case applies to all types of NR UE release 15 and forward supporting inter-band EN-DC.

##### 6.5B.3.3.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5B.3.1.1.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 6.5B.3.3.1.4 Test description

##### 6.5B.3.3.1.4.1 Initial condition

Same initial conditions as in clause 6.5B.3.1.1 with the following exceptions:

Instead of Table Table 6.5B.3.1.1.4.1-1 → use Table 6.5B.3.3.1.4-1

**Table 6.5B.3.3.1.4-1: NR test configuration table**

Initial Conditions			
Test Environment as specified in TS 38.508-1 [6] subclause 4.1		Normal	
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1		Low range, High range	
Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1		Lowest and Highest N <sub>RB_agg</sub> (Note 2)	
Test SCS as specified in Table 5.3.5-1		Lowest	
Test parameters			
Test ID	Downlink Configuration	Uplink Configuration	
		Modulation	NR RB allocation
	N/A for Spurious emission testing.		
1		CP-OFDM QPSK	Edge_1RB_Left
2		CP-OFDM QPSK	Edge_1RB_Right
3		CP-OFDM QPSK	Outer Full
Note 1: Test Channel Bandwidths are checked separately for each NR band, which applicable channel bandwidths are specified in Table 5.3.5-1 of 38.521-1 [8].			
Note 2: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same aggregated channel BW, only the combination with the highest NR BW is tested			

Same test procedure as in clause 6.5.3.1.4.2 in TS 38.521-1 [8].

#### 6.5B.3.3.1.4.2 Test procedure

Same test procedure as in clause 6.5B.3.1.1.4.2.

#### 6.5B.3.3.1.4.3 Message Contents

Same message Contents as in clause 6.5B.3.1.1.4.3.

#### 6.5B.3.3.1.5 Test Requirement

Same test requirement as in clause 6.5B.3.1.1.5.

### 6.5B.3.3.2 Spurious emission band UE co-existence for Inter-band within FR1

**Editor's note:**

The default and additional test configuration is analysed based on the assumption that only intermodulation products needs to be tested.

#### 6.5B.3.3.2.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions for band UE co-existence for inter-band EN-DC.

#### 6.5B.3.3.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward supporting inter-band EN-DC.

#### 6.5B.3.3.2.3 Minimum conformance requirements

The general spurious emissions requirements specified in sub-clause 6.6.3.1 of TS36.521-1[11] and sub-clause 6.5.3.1 of TS38.521-1[8] apply beyond any frequencies for which the out-of-band emissions requirements in sub-clause 6.5B.2.3 apply.

NOTE 1: For measurement conditions at the edge of each frequency range, the lowest frequency of the measurement position in each frequency range should be set at the lowest boundary of the frequency range plus MBW/2. The highest frequency of the measurement position in each frequency range should be set at the highest boundary of the frequency range minus MBW/2. MBW denotes the measurement bandwidth defined for the protected band.

For inter-band EN\_DC with the uplink assigned to both carriers, the requirements in Table 6.5B.3.3.2.3-1 apply on each component carrier with both component carriers are active.

**Table 6.5B.3.3.2.3-1: Requirements**

EN-DC Configuration	Spurious emission						
	Protected band	Frequency range (MHz)		Maximum Level (dBm)	MBW (MHz)	NOTE	
DC_1_n28	E-UTRA Band 5, 7, 8, 18, 19, 20, 26, 27, 31, 32, 38, 40, 41, 50, 51, 72, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 42, 43, 75, 76 NR band n78	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA band n3, n34	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 11
	E-UTRA Band 1, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 10
	Frequency range	470	-	694	-42	8	5, 17
	Frequency range	470	-	710	-26.2	6	14
	Frequency range	758	-	773	-32	1	5
	Frequency range	773	-	803	-50	1	
	Frequency range	662	-	694	-26.2	6	5
	Frequency range	1880	-	1895	-40	1	5, 16
	Frequency range	1895	-	1915	-15.5	5	5, 7, 16
	Frequency range	1915	-	1920	+1.6	5	5, 7, 16
Frequency range	1839.9	-	1879.9	-50	1	5	
Frequency range	1884.5	-	1915.7	-41	0.3	9, 15	
DC_1_n40	Band 1, 5, 7, 8, 11, 18, 19, 20, 21, 22, 26, 27, 28, 31, 32, 38, 40, 41, 42, 43, 44, 45, 50, 51, 52, 65, 67, 68, 69, 72, 73, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Band 3, 34	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	Frequency range	1880	-	1895	-40	1	5, 17
	Frequency range	1895	-	1915	-15.5	5	5, 7, 17
	Frequency range	1915	-	1920	+1.6	5	5, 7, 17
DC_1_n51	E-UTRA Band 7, 12, 13, 17, 20, 22, 27, 28, 29, 31, 38, 44, 48, 67, 68, 69, 72, 73	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3, 34	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5, 2
	Frequency range	1880	-	1895	-40	1	5, 16
	Frequency range	1895	-	1915	-15.5	5	5, 7, 16
	Frequency range	1915	-	1920	+1.6	5	5, 7, 16
	E-UTRA Band 5, 6, 8, 26, 30, 40, 41, 42, 43, 46 NR Band n77, n78, n79,	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_1_n77	E-UTRA Band 1, 3, 5, 7, 8, 11, 18, 19, 20, 21, 26, 28, 34, 39, 40, 41, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1880	-	1895	-40	1	5, 8
	Frequency range	1895	-	1915	-15.5	5	5, 7, 8
	Frequency range	1915	-	1920	+1.6	5	5, 7, 8
DC_1_n78 DC_1_n84_ULS UP-TDM_n78 DC_1_n84_ULS UP-FDM_n78	E-UTRA Band 1, 3, 5, 7, 8, 11, 18, 19, 20, 21, 26, 28, 34, 40, 41, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1880	-	1895	-40	1	5, 8
	Frequency range	1895	-	1915	-15.5	5	5, 7, 8
	Frequency range	1915	-	1920	+1.6	5	5, 7, 8
DC_1_n79	E-UTRA Band 1, 3, 5, 7, 8, 11, 18, 19, 21, 26, 28, 34, 40, 41, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1880	-	1895	-40	1	5, 8
	Frequency range	1895	-	1915	-15.5	5	5, 7, 8
	Frequency range	1915	-	1920	+1.6	5	5, 7, 8

DC_2_n5	E-UTRA Bands 4, 5, 10, 12, 13, 14, 17, 24, 28, 29, 30, 42, 48, 50, 51, 66, 70, 71, n71, 74, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Bands 2, 25, 48	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 41, 43	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_2_n66	E-UTRA Bands 4, 5, 10, 12, 13, 14, 17, 24, 26, 27, 28, 29, 30, 41, 50, 51, 66, 70, 71, n71, 74, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Bands 2, 25	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Bands 42, 48	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_2_n71	E-UTRA Band 4, 5, 12, 13, 14, 17, 24, 26, 29, 30, 48, 66	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 2, 25, 41, 70	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band n71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
DC_2_n78	E-UTRA Band 4, 5, 10, 12, 13, 14, 17, 24, 26, 27, 28, 29, 30, 41, 42, 48, 50, 51, 66, 70, 71, 74, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 2, 25	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_3_n7	E-UTRA Band 1, 5, 7, 8, 20, 26, 27, 28, 31, 32, 33, 34, 40, 43, 44, 50, 51, 65, 67, 72, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA band 3	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA band 22, 42	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	Frequency range	2570	-	2575	+1.6	5	5, 6, 7
	Frequency range	2575	-	2595	-15.5	5	5, 6, 7
DC_3_n28	E-UTRA Band 1, 42, 43, 50, 51, 65, 74, 75, 76 NR n78	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA band n1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 10
	E-UTRA band n3	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 5, 7, 8, 20, 26, 27, 31, 34, 38, 40, 41, 72	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 11, 18, 19, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	13
	Frequency range	1884.5	-	1915.7	-41	0.3	13
	Frequency range	470	-	710	-26.2	6	14
	Frequency range	758	-	773	-32	1	5
	Frequency range	773	-	803	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 9
DC_3_n40	34, 38, 40, 41, E-UTRA Band 1, 5, 7, 8, 20, 26, 27, 28, 31, 32, 33, 34, 38, 39, 41, 43, 44, 45, 50, 51, 65, 67, 68, 69, 72, 73, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 22, 42, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_3_n51	E-UTRA Band 7, 8, 12, 13, 17, 20, 27, 28, 31, 33, 38, 48, 67, 68, 69, 72, 73	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 1, 5, 6, 22, 26, 30, 34, 36, 40, 41, 42, 43, 44, 46, 65, 71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_3_n77	E-UTRA Band 1, 3, 5, 7, 8, 11, 18, 19, 20, 21, 26, 28, 34, 39, 40, 41, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_3_n78 DC_3_n80_ULS UP-TDM_n78, DC_3_n80_ULS UP-FDM_n78	E-UTRA Band 1, 3, 5, 7, 8, 11, 18, 19, 20, 21, 26, 28, 34, 39, 40, 41, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_3_n79 DC_3_n79 DC_3_n80_ULS UP-TDM_n79, DC_3_n80_ULS UP-FDM_n79	E-UTRA Band 1, 3, 5, 8, 11, 18, 19, 21, 28, 34, 39, 40, 41, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 42	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_3_n82	E-UTRA Band 1, 3, 7, 8, 20, 22, 31, 32, 33, 34, 38, 40, 43, 50, 51, 65, 67, 68, 69, 72, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 42	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2

DC_5_n40	E-UTRA Band 1, 3, 5, 7, 8, 28, 31, 34, 38, 42, 43, 45, 65, 73	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 41, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_5_n66	E-UTRA Band 1, 2, 3, 4, 5, 6, 7, 8, 10, 12, 13, 14, 17, 24, 25, 28, 29, 30, 34, 38, 40, 43, 45, 50, 51, 65, 66, 70, 71, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 41, 42, 48, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 18, 19	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-40	1	
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_5_n78	E-UTRA Band 1, 2, 3, 4, 5, 7, 8, 10, 12, 13, 14, 17, 24, 25, 28, 29, 30, 31, 34, 38, 40, 42, 43, 45, 48, 65, 66, 70	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 26	859	-	869	-27	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 4
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
	E-UTRA Band 41	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	7
	E-UTRA Band 18, 19	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-40	1	4
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	4
DC_7_n28	E-UTRA Band 2, 3, 5, 7, 8, 20, 26, 27, 31, 34, 40, 72 N	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 4, 10, 42, 43, 50, 65, 66, 74, 75, 76 NR band n78	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA band n1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 10
	Frequency range	758	-	773	-32	1	5
	Frequency range	773	-	803	-50	1	
	Frequency range	2570	-	2575	+1.6	5	5, 6, 7
	Frequency range	2575	-	2595	-15.5	5	5, 6, 7
	Frequency range	2595	-	2620	-40	1	5, 6
DC_7_n51	E-UTRA Band 2, 3, 5, 8, 26, 30, 31, 32, 33, 34, 40, 48, 72	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	2570	-	2575	+1.6	5	5, 7, 16
	Frequency range	2575	-	2595	-15.5	5	5, 7, 16
	Frequency range	2595	-	2620	-40	1	5, 21
	E-UTRA Band 1, 4, 10, 12, 13, 14, 17, 20, 22, 23, 27, 28, 29, 42, 43, 44, 46, 65, 66, 67, 68 NR Band n77, n78, n79,	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	DC_7_n78	E-UTRA Band 1, 2, 3, 4, 5, 7, 8, 10, 11, 18, 19, 20, 21, 26, 27, 28, 31, 32, 33, 34, 40, 50, 51, 65, 66, 67, 68, 72, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1
Frequency range	2570	-	2575	+1.6	5	5, 6, 7	
Frequency range	2575	-	2595	-15.5	5	5, 6, 7	
Frequency range	2595	-	2620	-40	1	5, 6	
DC_8_n40	E-UTRA Band 1, 20, 28, 31, 32, 33, 34, 38, 39, 40, 45, 50, 51, 65, 67, 68, 69, 72, 73, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3, 7, 22, 41, 42, 43, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 8	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	12
	Frequency range	860	-	890	-40	1	5, 12
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 12
DC_8_n77	E-UTRA Band 1, 20, 28, 31, 32, 33, 34, 38, 39, 40, 44, 45, 50, 51, 65, 67, 68, 69, 72, 73, 74, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA band 3, 7, 22, 41	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 8	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	12
	Frequency range	860	-	890	-40	1	5, 12
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 12
DC_8_n78 DC_8_n81_ULS UP-TDM_n78,	E-UTRA Band 1,8, 20, 28, 34, 39, 40, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3, 7,41	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	12

DC_8_n81_ULS UP-FDM_n78	Frequency range	860	-	890	-40	1	5, 12
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 12
DC_8_n79 DC_8_n81_ULS UP-TDM_n79,	E-UTRA Band 1,8,28,34,39,40,65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 3,41,42	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_8_n81_ULS UP-FDM_n79	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	12
	Frequency range	860	-	890	-40	1	5, 12
DC_11_n77	Frequency range	1884.5	-	1915.7	-41	0.3	3
	E-UTRA Band 1, 3, 18, 19, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_11_n78	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_11_n79	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_11_n78	E-UTRA Band 1, 3, 18, 19, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
DC_11_n79	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
DC_11_n79	Frequency range	2595	-	2645	-50	1	
	E-UTRA Band 1, 3, 18, 19, 28, 34, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_12_n5	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_12_n5	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_12_n5	E-UTRA Band 2, 5, 12, 13, 14, 17, 24, 25, 30, 42, 43 50, 51, 71, n71, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 4, 10, 41, 48, 66, 70	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_12_n66 DC_12_n5	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 12, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_12_n66 DC_12_n5	E-UTRA Band 2, 4, 5, 13, 14, 17, 24, 25, 26, 27, 29, 30, 41, 50, 51, 70, 71, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Bands 4, 10, 48	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_12_n66 DC_12_n5	E-UTRA Band 12, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 2, 5, 12, 13, 14, 17, 24, 25, 30, 42, 43 50, 51, 71, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_18_n77	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
DC_18_n78	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
DC_18_n78	Frequency range	2595	-	2645	-50	1	
	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_18_n79	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_18_n79	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_18_n79	E-UTRA Band 1, 3, 11, 21, 28, 34, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
DC_18_n79	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
DC_18_n79	Frequency range	2595	-	2645	-50	1	
	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_19_n77	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_19_n77	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_19_n78	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
DC_19_n78	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
DC_19_n78	Frequency range	2595	-	2645	-50	1	
	E-UTRA Band 1, 3, 11, 21, 28, 34, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
DC_19_n79	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_19_n79	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_20_n8	E-UTRA Band 1, 3, 7, 22, 28, 31, 32, 34, 38, 42, 43, 65, 75, 76, NR band n78	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 3, 7, 8, 22, 31, 32, 34, 38, 42, 43, 65, 75, 76	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	

DC_20_n51	E-UTRA Band 1, 3, 4, 8, 17, 22, 28, 29, 31, 40, 43, 48, 65, 66, 68, 72	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 20	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	Frequency range	758	-	788	-50	1	
	E-UTRA Band 2, 7, 25, 32, 33, 34, 35, 36, 37, 38, 39, 41, 42, 46, 69, 70 NR Band n77, n78, n79,	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_20_n77	E-UTRA Band 1, 3, 7, 8, 31, 32, 33, 34, 40, 50, 51, 65, 67, 68, 72, 74, 75, 76						
	E-UTRA Band 20	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 38, 69	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_20_n78 DC_20_n82_ULS UP-TDM_n78, DC_20_n82_ULS UP-FDM_n78	E-UTRA Band 1, 3, 7, 8, 22,, 31, 32, 33, 34, 40, 42, 43, 50, 51, 65, 67, 68, 72, 74, 75, 76						
	E-UTRA Band 20	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
	E-UTRA Band 38, 69	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_21_n77	E-UTRA Band 1, 3, 18, 19, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_21_n78	E-UTRA Band 1, 3, 18, 19, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_21_n79	E-UTRA Band 1, 3, 18, 19, 21, 28, 34, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_25_n41	E-UTRA band 4, 5, 10, 12, 13, 14, 17, 24, 26, 27, 28, 29, 30, 42, 45, 48, 66, 70,71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA/NR Band 2, 25	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	5
DC_26_n41	E-UTRA/NR Band 1, 2, 3, 4, 5, 10, 12, 13, 14, 17, 24, 25, 26, 28, 29, 30, 31, 34, 39, 40, 42, 43, 48, 50, 51, 65, 66, 70, 71, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 9, 11, 18, 19, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	19
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 19
	Frequency range	703	-	799	-50	1	
	Frequency range	799	-	803	-40	1	5
	Frequency range	945	-	960	-50	1	
DC_26_n77	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_26_n78	E-UTRA Band 1, 3, 11, 21, 28, 34, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
DC_26_n79	E-UTRA Band 1, 3, 11, 21, 28, 34, 42, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	945	-	960	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
	Frequency range	2545	-	2575	-50	1	
	Frequency range	2595	-	2645	-50	1	
DC_28_n51	E-UTRA Band 2, 3, 5, 7, 8, 25, 26, 31, 34, 38, 40, 41, 66, 72	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 4, 10, 20, 22, 24, 32, 42, 43, 45, 46, 65, 66, 71, 73 NR band n78, n79	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2, 9, 11
	Frequency range	470	-	694	-42	8	5, 17
	Frequency range	470	-	710	-26.2	6	14



	Frequency range	662	-	694	-26.2	6	5
	Frequency range	758	-	773	-32	1	5
	Frequency range	773	-	803	-50	1	
DC_28_n77	E-UTRA Band 3, 5, 7, 8, 18, 19, 20, 26, 34, 39, 40, 41	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 10
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 11
	Frequency range	758	-	773	-32	1	
	Frequency range	773	-	803	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_28_n78 DC_28_n83_ULS UP-TDM_n78, DC_28_n83_ULS UP-FDM_n78	E-UTRA Band 3, 5, 7, 8, 18, 19, 20, 26, 34, 39, 40, 41	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	10, 11
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	10, 12
	Frequency range	758	-	773	-32	1	
	Frequency range	773	-	803	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_28_n79	E-UTRA Band 3, 5, 8, 18, 19, 34, 39, 40, 41, 42	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 1	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 10
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	9, 11
	Frequency range	758	-	773	-32	1	
	Frequency range	773	-	803	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_30_n5	E-UTRA Band 1, 2, 3, 4, 5, 7, 8, 10, 12, 13, 14, 17, 24, 25, 28, 29, 30, 31, 34, 38, 40, 42, 43, 45, 48, 50, 51, 65, 66, 70, 71, 73, 74, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 41, 48, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 18, 19	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-40	1	
	E-UTRA Band 11, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_30_n66	E-UTRA Band 2, 4, 5, 10, 12, 13, 14, 17, 24, 25, 26, 27, 29, 30, 38, 41, 66, 70, 71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Bands 48	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_38_n78	N/A						
DC_39_n78	E-UTRA Band 1, 8, 34, 40, 41, 44, 45	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1805	-	1855	-40	1	18
	Frequency range	1855	-	1880	-15.5	5	18
DC_39_n79	E-UTRA Band 1, 8, 34, 40, 41, 44, 45	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1805	-	1855	-40	1	18
	Frequency range	1855	-	1880	-15.5	5	18
DC_40_n77	N/A						
DC_41_n77	E-UTRA Band 1, 3, 5, 8, 26, 28, 33, 34, 39, 40, 44, 45, 73, 74	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 9, 11, 18, 19, 21	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	19
	Frequency range	1884.5	-	1915.7	-41	0.3	3, 19
DC_41_n78	E-UTRA Band 1, 3, 8, 34, 39, 40, 44, 45	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-5	100	
DC_41_n79	E-UTRA Band 1, 3, 5, 8, 9, 11, 18, 19, 21, 28, 34, 40, 42, 44, 45, 65	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_42_n51	E-UTRA Band 3, 8, 20, 25, 30, 31, 34, 39, 41, 73	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 1, 2, 4, 5, 6, 7, 10, 12, 13, 14, 17, 23, 24, 26, 27, 28, 29, 32, 38, 40, 44, 46, 65, 66, 67, 68, 70, 71	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
DC_42_n77	N/A						
DC_42_n78	N/A						
DC_42_n79	N/A						
DC_66_n5	E-UTRA Band 1, 2, 3, 4, 5, 6, 7, 8, 10, 12, 13, 14, 17, 24, 25, 28, 29, 30, 34, 38, 40, 43, 45, 50, 51, 65, 66, 70, 71, n71, 85	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	
	E-UTRA Band 26	859	-	869	-27	1	
	E-UTRA Band 41, 42, 48, 52	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-50	1	2
	E-UTRA Band 18, 19	F <sub>DL_low</sub>	-	F <sub>DL_high</sub>	-40	1	

	E-UTRA Band 11, 21	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1	
	Frequency range	1884.5	-	1915.7	-41	0.3	3
DC_66_n71	E-UTRA Band 4, 5, 7, 10, 13, 14, 17, 22, 24, 26, 27, 29, 30, 43, -50, 51, 66, 74	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1	
	E-UTRA Band 2, 25, 41, 42, 48, 70	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1	2
	E-UTRA Band 71	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1	5
DC_66_n78, DC_66_n86_ULS UP-TDM_n78, DC_66_n86_ULS UP-FDM_n78	E-UTRA Band 1, 3, 5, 7, 8, 20, 26, 28, 34, 39, 40, 41, 65	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1	

- NOTE 1: FDL\_low and FDL\_high refer to each E-UTRA frequency band specified in Table 5.2-1 of TS36.121-1[10].
- NOTE 2: As exceptions, measurements with a level up to the applicable requirements defined in Table 6.5B.3.1.1.5-1 are permitted for each assigned E-UTRA carrier used in the measurement due to 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic spurious emissions. Due to spreading of the harmonic emission the exception is also allowed for the first 1 MHz frequency range immediately outside the harmonic emission on both sides of the harmonic emission. This results in an overall exception interval centred at the harmonic emission of  $(2\text{MHz} + N \times L_{\text{CRB}} \times 180\text{kHz})$ , where N is 2, 3, 4, 5 for the 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic respectively. The exception is allowed if the measurement bandwidth (MBW) totally or partially overlaps the overall exception interval.
- NOTE 3: Applicable when co-existence with PHS system operating in 1884.5 -1915.7MHz.
- NOTE 4: Applicable only when the assigned E-UTRA carrier is confined within 824 MHz and 849 MHz for UE category M1, M2 and UE category NB1 and NB2.
- NOTE 5: These requirements also apply for the frequency ranges that are less than  $F_{\text{OoB}}$  (MHz) in Table 6.6.3.1-1 and Table 6.6.3.1A-1 from the edge of the channel bandwidth.
- NOTE 6: This requirement is applicable for any channel bandwidths within the range 2500 - 2570 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 2560.5 - 2562.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 2552 - 2560 MHz the requirement is applicable only for an uplink transmission bandwidth less than or equal to 54 RB.
- NOTE 7: For these adjacent bands, the emission limit could imply risk of harmful interference to UE(s) operating in the protected operating band.
- NOTE 8: This requirement is applicable for any channel bandwidths within the range 1920 - 1980 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1927.5 - 1929.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1930 - 1938 MHz the requirement is applicable only for an uplink
- NOTE 9: Applicable when the assigned E-UTRA carrier is confined within 718 MHz and 748 MHz and when the channel bandwidth used is 5 or 10 MHz.
- NOTE 10: As exceptions, measurements with a level up to the applicable requirement of -36 dBm/MHz is permitted for each assigned E-UTRA carrier used in the measurement due to 2<sup>nd</sup> harmonic spurious emissions. An exception is allowed if there is at least one individual RB within the transmission bandwidth (see Figure 5.6-1) for which the 2<sup>nd</sup> harmonic totally or partially overlaps the measurement bandwidth (MBW).
- NOTE 11: As exceptions, measurements with a level up to the applicable requirement of -38 dBm/MHz is permitted for each assigned E-UTRA carrier used in the measurement due to 3<sup>rd</sup> harmonic spurious emissions. An exception is allowed if there is at least one individual RB within the transmission bandwidth (see Figure 5.6-1) for which the 3<sup>rd</sup> harmonic totally or partially overlaps the measurement bandwidth (MBW).
- NOTE 12: This requirement is applicable only for the following cases: - for carriers of 5 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is within the range  $902.5 \text{ MHz} \leq F_c < 907.5 \text{ MHz}$  with an uplink transmission bandwidth less than or equal to 20 RB - for carriers of 5 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is within the range  $907.5 \text{ MHz} \leq F_c \leq 912.5 \text{ MHz}$  without any restriction on uplink transmission bandwidth. - for carriers of 10 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is  $F_c = 910 \text{ MHz}$  with an uplink transmission bandwidth less than or equal to 32 RB with  $\text{RB}_{\text{start}} > 3$ .
- NOTE13: This requirement applies for 5, 10, 15 and 20 MHz E-UTRA channel bandwidth allocated within 1744.9MHz and 1784.9MHz.
- NOTE 14: This requirement is applicable for 5 and 10 MHz E-UTRA channel bandwidth allocated within 718-728MHz. For carriers of 10 MHz bandwidth, this requirement applies for an uplink transmission bandwidth less than or equal to 30 RB with  $\text{RB}_{\text{start}} > 1$  and  $\text{RB}_{\text{start}} < 48$ .
- NOTE 15: Applicable when NS\_05 in section 6.6.3.3.1 is signalled by the network.
- NOTE 16: This requirement is applicable for any channel bandwidths within the range 1920 - 1980 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1927.5 - 1929.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1930 - 1938 MHz the requirement is applicable only for an uplink transmission bandwidth less than or equal to 54 RB.
- NOTE 17: This requirement is applicable in the case of a 10 MHz E-UTRA carrier confined within 703 MHz and 733 MHz, otherwise the requirement of -25 dBm with a measurement bandwidth of 8 MHz applies.
- NOTE 18: This requirement is only applicable for E-UTRA carriers with bandwidth confined within 1885-1920 MHz (requirement for carriers with at least 1RB confined within 1880 - 1885 MHz is not specified). This requirement applies for an uplink transmission bandwidth less than or equal to 54 RB for E-UTRA carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1892.5 - 1894.5 MHz and for E-UTRA carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1895 - 1903 MHz.
- NOTE 19: This requirement applies when the E-UTRA and NR carriers are confined within 2545-2575MHz or 2595-2645MHz and the channel bandwidth is 10 or 20 MHz.

NOTE: To simplify the above Table, E-UTRA band numbers are listed for bands which are specified only for E-UTRA operation or both E-UTRA and NR operation. NR band numbers are listed for bands which are specified only for NR operation.

The normative reference for this requirement is TS 38.101-3 [1] subclause 6.5B.3.3.1, Table 6.5B.3.3.1-1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

6.5B.3.3.2.4 Test description

6.5B.3.3.2.4.1 Initial conditions

Same initial conditions as described in subclause 6.5B.3.1.2.4.1 with the following exceptions:

- Instead of Table 6.5B.3.1.2.4.1-1 → use Table 6.5B.3.3.2.4.1-1.

**Table 6.5B.3.3.2.4.1-1: Test Configuration Table**

Initial Conditions											
Test Environment as specified in TS 38.508-1 [6] subclause 4.1						NC					
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1						For test frequencies refer to “Range” columns.					
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1						Refer to “NR N <sub>RB</sub> ” and “E-UTRA N <sub>RB</sub> ” columns					
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1						Lowest SCS per Channel Bandwidth					
Test Parameters for DC Configurations											
ID	DC Configuration / N <sub>RB_agg</sub>					DL Allocation			UL Allocation (Note 1,2)		
	DC Configuration				E-UTRA Ch BW/N <sub>RB</sub>	NR Ch BW/N <sub>RB</sub>	CC MOD E-UTRA/NR	E-UTRA & NR RB allocation	CC MOD E-UTRA/NR	E-UTRA & NR allocations (L <sub>CRB</sub> @ RB <sub>start</sub> )	
	E-UTRA		NR								
	Band	Range	Band	Range							
Default Test Settings for a CA_XA-YA Configuration											
1	X	Low	Y	Low	Highest N <sub>RB_agg</sub> / Highest N <sub>RB</sub>	Highest N <sub>RB_agg</sub> / Highest N <sub>RB</sub>	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@0	1@0
2	X	High	Y	High	Highest N <sub>RB_agg</sub> / Highest N <sub>RB</sub>	Highest N <sub>RB_agg</sub> / Highest N <sub>RB</sub>	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@RB <sub>max</sub>	1@RB <sub>max</sub>
Test Settings for DC_3A-n79A Configuration											
1	3	Low	79	Low	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@0	1@0
2	3	High	79	Note 3	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@75	1@0
3	3	High	79	Low	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@RB <sub>max</sub>	1@136
4	3	High	79	Low	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@75	1@RB <sub>max</sub>
5	3	Low	79	Low	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@RB <sub>max</sub>	1@136
6	3	Low	79	Note 3	20/100	100/273	QPSK/CP -OFDM QPSK	NA	QPSK / CP-OFDM QPSK	1@RB <sub>max</sub>	1@RB <sub>max</sub>
Note 1: Use DC Configuration – specific test points if present in the table, otherwise use test points from matching Group Test Settings, if present in the table. Otherwise use the Default Test Settings test points. Note 2: X, Y correspond to the different bands in the DC Configuration. E.g. for DC_1A-n3A, X=1, Y=3. Note 3: Test Point ID 2 for DC_3A-n79A have the centre carrier frequency of 4480.5 MHz in Band 79 (NR ARFCN=698700). Test Point ID 6 for DC_3A-n79A have the centre carrier frequency of 4909.5 MHz in Band 79 (EARFCN=727300).											

6.5B.3.3.2.4.2 Test Procedure

Same test procedure as described in subclause 6.5B.3.1.2.4.2 with the following exceptions:

Instead of Table 6.2B.1.2.5-1 → use Table Table 6.2B.3.2.5-1.

For EN-DC only capable devices

Instead of Table 6.5B.3.1.2.3-1 → use Table 6.5B.3.3.2.3-1.

For Standalone and EN-DC capable devices

Instead of Table 6.5B.3.1.2.3-1 → use Table Table 6.5B.3.3.2.5-1.

#### 6.5B.3.3.2.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 6.5B.3.3.2.5 Test Requirement

For EN-DC only capable devices, test requirements for Spurious Emissions UE Co-existence are the same as the minimum requirements and are not repeated in this section.

For Standalone and EN-DC capable devices, the test requirements are in Table 6.5B.3.3.2.5-1.

**Table 6.5B.3.3.2.5-1: Requirements for inter-band within FR1**

EN-DC Configuration	Spurious emission					
	Protected band	Frequency range (MHz)		Maximum Level (dBm)	MBW (MHz)	NOTE
DC_3-n79	E-UTRA Band 5, 8, 11, 18, 19, 21, 41	$F_{DL\_low}$	-	$F_{DL\_high}$	-50	1
NOTE 1: $F_{DL\_low}$ and $F_{DL\_high}$ refer to each E-UTRA frequency band specified in Table 5.5-1 of TS 38.101-3 [1].						

- NOTE 2: As exceptions, measurements with a level up to the applicable requirements defined in Table 6.6.3.1-2 of TS 38.101-3 [1] are permitted for each assigned E-UTRA carrier used in the measurement due to 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic spurious emissions. Due to spreading of the harmonic emission the exception is also allowed for the first 1 MHz frequency range immediately outside the harmonic emission on both sides of the harmonic emission. This results in an overall exception interval centred at the harmonic emission of  $(2\text{MHz} + N \times L_{\text{CRB}} \times 180\text{kHz})$ , where N is 2, 3, 4, 5 for the 2<sup>nd</sup>, 3<sup>rd</sup>, 4<sup>th</sup> or 5<sup>th</sup> harmonic respectively. The exception is allowed if the measurement bandwidth (MBW) totally or partially overlaps the overall exception interval.
- NOTE 3: Applicable when co-existence with PHS system operating in 1884.5 -1915.7MHz
- NOTE 4: Applicable only when the assigned E-UTRA carrier is confined within 824 MHz and 849 MHz for UE category M1, M2 and UE category NB1 and NB2.
- NOTE 5: These requirements also apply for the frequency ranges that are less than  $F_{\text{OoB}}$  (MHz) in Table 6.6.3.1-1 and Table 6.6.3.1A-1 of TS 38.101-3 [1] from the edge of the channel bandwidth.
- NOTE 6: This requirement is applicable for any channel bandwidths within the range 2500 - 2570 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 2560.5 - 2562.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 2552 - 2560 MHz the requirement is applicable only for an uplink transmission bandwidth less than or equal to 54 RB.
- NOTE 7: For these adjacent bands, the emission limit could imply risk of harmful interference to UE(s) operating in the protected operating band.
- NOTE 8: This requirement is applicable for any channel bandwidths within the range 1920 - 1980 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1927.5 - 1929.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1930 - 1938 MHz the requirement is applicable only for an uplink.
- NOTE 9: Applicable when the assigned E-UTRA carrier is confined within 718 MHz and 748 MHz and when the channel bandwidth used is 5 or 10 MHz.
- NOTE 10: As exceptions, measurements with a level up to the applicable requirement of -36 dBm/MHz is permitted for each assigned E-UTRA carrier used in the measurement due to 2<sup>nd</sup> harmonic spurious emissions. An exception is allowed if there is at least one individual RB within the transmission bandwidth (see Figure 5.6-1) for which the 2<sup>nd</sup> harmonic totally or partially overlaps the measurement bandwidth (MBW).
- NOTE 11: As exceptions, measurements with a level up to the applicable requirement of -38 dBm/MHz is permitted for each assigned E-UTRA carrier used in the measurement due to 3<sup>rd</sup> harmonic spurious emissions. An exception is allowed if there is at least one individual RB within the transmission bandwidth (see Figure 5.6-1) for which the 3<sup>rd</sup> harmonic totally or partially overlaps the measurement bandwidth (MBW).
- NOTE 12: This requirement is applicable only for the following cases: - for carriers of 5 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is within the range  $902.5 \text{ MHz} \leq F_c < 907.5 \text{ MHz}$  with an uplink transmission bandwidth less than or equal to 20 RB - for carriers of 5 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is within the range  $907.5 \text{ MHz} \leq F_c \leq 912.5 \text{ MHz}$  without any restriction on uplink transmission bandwidth. - for carriers of 10 MHz channel bandwidth when carrier centre frequency ( $F_c$ ) is  $F_c = 910 \text{ MHz}$  with an uplink transmission bandwidth less than or equal to 32 RB with  $\text{RB}_{\text{start}} > 3$ .
- NOTE13: This requirement applies for 5, 10, 15 and 20 MHz E-UTRA channel bandwidth allocated within 1744.9MHz and 1784.9MHz.
- NOTE 14: This requirement is applicable for 5 and 10 MHz E-UTRA channel bandwidth allocated within 718-728MHz. For carriers of 10 MHz bandwidth, this requirement applies for an uplink transmission bandwidth less than or equal to 30 RB with  $\text{RB}_{\text{start}} > 1$  and  $\text{RB}_{\text{start}} < 48$ .
- NOTE 15: Applicable when NS\_05 in section 6.6.3.3.1 of TS 38.101-3 [1] is signalled by the network.
- NOTE 16: This requirement is applicable for any channel bandwidths within the range 1920 - 1980 MHz with the following restriction: for carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1927.5 - 1929.5 MHz and for carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1930 - 1938 MHz the requirement is applicable only for an uplink transmission bandwidth less than or equal to 54 RB.
- NOTE 17: This requirement is applicable in the case of a 10 MHz E-UTRA carrier confined within 703 MHz and 733 MHz, otherwise the requirement of -25 dBm with a measurement bandwidth of 8 MHz applies.
- NOTE 18: This requirement is only applicable for E-UTRA carriers with bandwidth confined within 1885-1920 MHz (requirement for carriers with at least 1RB confined within 1880 - 1885 MHz is not specified). This requirement applies for an uplink transmission bandwidth less than or equal to 54 RB for E-UTRA carriers of 15 MHz bandwidth when carrier centre frequency is within the range 1892.5 - 1894.5 MHz and for E-UTRA carriers of 20 MHz bandwidth when carrier centre frequency is within the range 1895 - 1903 MHz.
- NOTE 19: This requirement applies when the E-UTRA and NR carriers are confined within 2545-2575MHz or 2595-2645MHz and the channel bandwidth is 10 or 20 MHz.

#### 6.5B.3.4 Spurious Emissions for Inter-band including FR2

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- The referred test case 6.5.3 in TS 38.521-2 is incomplete.

### 6.5B.3.4.1 General Spurious Emissions for Inter-band including FR2

#### 6.5B.3.4.1.1 Test purpose

Same test purpose as in clause 6.5.3.1.1 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.3.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 6.5B.3.4.1.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.3.1.3 in TS 38.521-2 [9] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.3.4.

#### 6.5B.3.4.1.4 Test description

##### 6.4B.3.4.1.4.1 Initial conditions

Same test description as in clause 6.5.3.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.5.3.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.3.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.3.1.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.3.4.1.5 Test requirement

Same test requirement as in clause 6.5.3.1.5 in TS 38.521-2 [9] for the NR carrier.

[IS: 5446 NTT created a 7. duplication!!]

### 6.5B.3.4.1.2 Transmitter Spurious emissions for Inter-band EN-DC including FR2 (3 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.3.1.1 in TS 38.521-2 is incomplete.

#### 6.5B.3.4.1.2.1 Test purpose

Same test purpose as in clause 6.5.3.1 in TS 38.521-2 [9] for the NR carrier.



#### 6.5B.3.4.1.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 3CCs.

#### 6.5B.3.4.1.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.3.4.

#### 6.5B.3.4.1.2.4 Test description

##### 6.5B.3.4.1.2.4.1 Initial condition

Same test description as in clause 6.5A.3.1.1.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.3.1.1.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.3.1.1.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.3.1.1.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.3.4.1.2.5 Test Requirements

Same test requirement as in clause 6.5A.3.1.1.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.3.4.1.3 Transmitter Spurious emissions for Inter-band EN-DC including FR2 (4 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.3.1.2 in TS 38.521-2 is incomplete.

##### 6.5B.3.4.1.3.1 Test purpose

Same test purpose as in clause 6.5.3.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.5B.3.4.1.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 4CCs.

#### 6.5B.3.4.1.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.3.4.

#### 6.5B.3.4.1.3.4 Test description

##### 6.5B.3.4.1.3.4.1 Initial condition

Same test description as in clause 6.5A.3.1.2.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.3.1.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.3.1.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.3.1.2.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.3.4.1.3.5 Test Requirements

Same test requirement as in clause 6.5A.3.1.2.5 in TS 38.521-2 [9] for the NR carrier.

#### 6.5B.3.4.1.4 Transmitter Spurious emissions for Inter-band EN-DC including FR2 (5 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test configuration table and Connection diagram in TS 38.521-2 are TBD
- The referred test case 6.5A.3.1.3 in TS 38.521-2 is incomplete.

##### 6.5B.3.4.1.4.1 Test purpose

Same test purpose as in clause 6.5.3.1 in TS 38.521-2 [9] for the NR carrier.

##### 6.5B.3.4.1.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 with 5CCs.

##### 6.5B.3.4.1.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.3.3 in TS 38.521-2 [9] for the NR carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 [4] clause 6.4B.3.4.

#### 6.5B.3.4.1.4.4 Test description

##### 6.5B.3.4.1.4.4.1 Initial condition

Same test description as in clause 6.5A.3.1.3.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For Initial conditions as in clause 6.5A.3.1.3.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5A.3.1.3.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5A.3.1.3.4.2 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.3.4.1.4.5 Test Requirements

Same test requirement as in clause 6.5A.3.1.3.5 in TS 38.521-2 [9] for the *NR* carrier.

[IS: 5446 NTT end of a duplication!!]

#### 6.5B.3.4.2 Spurious emission band UE co-existence for Inter-band including FR2

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **The referred test case 6.5.3.2 in TS 38.521-2 is incomplete.**
- **Testability issue for 6GHz ~ [12.75GHz] is identified. How to treat this frequency range is TBD.**
- **TRP Measurement uncertainty is TBD**

##### 6.5B.3.4.2.1 Test purpose

Same test purpose as in clause 6.5.3.2.1 in TS 38.521-2 [9] for the *NR* carrier.

##### 6.5B.3.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

##### 6.5B.3.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5.3.2.3 in TS 38.521-2 [9] for the *NR* carrier.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this requirement is TS 38.101-3 subclause 6.5B.3.4.1.

#### 6.5B.3.4.2.4 Test description

Same Test description as in clause 6.5.3.2.4 in TS 38.521-2 [9] for the *NR* carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.7-1.

For initial conditions as in clause 6.5.3.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1 The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1 The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 6.5.3.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state `RRC_CONNECTED` with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.3.2.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set `TimeAlignmentTimerDedicated` IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 6.5B.3.4.2.5 Test requirement

Same Test requirement as in clause 6.5.3.2.5 in TS 38.521-2 [9] for the *NR* carrier.

### 6.5B.4 Additional Spurious Emissions for EN-DC

#### 6.5B.4.1 Additional Spurious Emissions for Intra-band contiguous EN-DC

##### 6.5B.4.1.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions under the deployment scenarios where additional requirements are specified.

##### 6.5B.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward supporting intra-band contiguous EN-DC.

##### 6.5B.4.1.3 Minimum conformance requirements

These requirements are specified in terms of an additional spectrum emission requirement. Additional spurious emission requirements are signalled by the network to indicate that the UE shall meet an additional requirement for a specific deployment scenario as part of the cell handover/broadcast message.

**NOTE:** For measurement conditions at the edge of each frequency range, the lowest frequency of the measurement position in each frequency range should be set at the lowest boundary of the frequency range plus  $MBW/2$ . The highest frequency of the measurement position in each frequency range should be set at the highest boundary of the frequency range minus  $MBW/2$ .  $MBW$  denotes the measurement bandwidth defined for the protected band.

##### 6.5B.4.1.3.1 Minimum requirement (network signalled value "NS\_04")

When "NS 04" is indicated in the cell, the power of any UE emission shall not exceed the levels specified in Table 6.5B.4. 1.3.1-1. This requirement also applies for the frequency ranges that are less than  $F_{OoB}$  (MHz) in Table 6.6.3.1-1 of TS 38.521-1 [8] from the edge of the channel bandwidth.

**Table 6.5B.4.1.3.1-1: Additional requirements**

Frequency band (MHz)	Channel bandwidth / Spectrum emission limit (dBm)	Measurement bandwidth
$2495 \leq f < 2496$	-13	1% of Channel BW for contiguous BW up to 100 MHz, 1 MHz for contiguous BW > 100 MHz
$2490.5 \leq f < 2495$	-13	1 MHz
$0 < f < 2490.5$	-25	1 MHz

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.5B.4.1.1.

Exception requirements are applicable for NR but not for E-UTRA within this test. LTE anchor agnostic approach is not applied. E-UTRA configuration is included but E-UTRA measurements are not performed.

6.5B.4.1.4 Test description

6.5B.4.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.2.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing are shown in Table 6.5B.4.1.4.1-1 for E-UTRA and Table 6.5B.4.1.4.1-2 for NR. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in Annex TS 36.521-1 [10] Annex C and in TS 38.521-1 Annex C2 for LTE link and NR link respectively.

**Table 6.5B.4.1.4.1-1: EN-DC test configuration table for NS\_04**

<b>Initial Conditions</b>
---------------------------

Test Environment as specified in TS 38.508-1 [6] subclause 4.1		NC			
NR Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1 E-UTRA Test Frequencies as specified in TS 36.508-1 [11] subclause 4.3.1		Low range, High range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1		E-UTRA: 20 MHz NR: 40 MHz, 100 MHz Lowest and Highest $N_{RB\_agg}$ (Note 3)			
Test SCS for the NR cell as specified in TS 38.521-1 [8] Table 5.3.5-1		Lowest SCS per Channel Bandwidth			
<b>Test Parameters</b>					
Test ID	Downlink Configuration	EN-DC Uplink Configuration			
		E-UTRA Cell		NR Cell	
		Modulation	RB allocation (NOTE 2)	Modulation	RB allocation (NOTE 1)
1	N/A for Spurious emission.	QPSK	1@0	Same as in Table 6.5.3.3.4.1-1 of TS 38.521-1[8]	Same as in Table 6.5.3.3.4.1-1 of TS 38.521-1[8]
2		QPSK	Full RB	Same as in Table 6.5.3.3.4.1-1 of TS 38.521-1[8]	Same as in Table 6.5.3.3.4.1-1 of TS 38.521-1[8]
3		QPSK	Outer_Full	CP-OFDM QPSK	Inner Full
4		QPSK	Outer_Full	CP-OFDM QPSK	Outer Full
<p>Note 1: The specific configuration of each RB allocation is defined in Table 6.1-1 in TS 38.521-1 [8].</p> <p>Note 2: Outer_Full defined as the transmission bandwidth configuration <math>N_{RB}</math> per channel bandwidth for the E-UTRA component as indicated in TS 36.521-1 [10] Table 5.4.2-1.</p> <p>Note 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same aggregated channel BW, only the combination with the highest NR BW is tested.</p> <p>Note 4: Bandwidth combination sets for intra-band contiguous EN-DC shall meet requirement specified in Table 5.3B.1.2-1.</p>					

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [6] Annex A, Figure A.3.1.1.1 for SS diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
4. E-UTRA downlink signals are initially set up according to Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS 36.521-1 [10].
5. NR downlink signals are initially set up according to Annex C.0, C.1 and C.2, and uplink signals according to Annex G.0, G.1, G.2, G.3.0 of TS 38.521-1 [8].
6. The UL Reference Measurement channels are set according to Table 6.5B.4.1.4.1-1.
7. NR propagation conditions are set according to B.0 of TS38.521-1[8]. E-UTRA propagation conditions are set according to B.0 of TS36.521-1[10].
8. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.5B.4.1.4.3.

#### 6.5B.4.1.4.2 Test Procedure

1. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to Table 6.5B.4.1.4.1-1. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 6.5B.4.1.4.1-1. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Send continuously uplink power control "up" commands to the UE for both NR and E-UTRA carriers until the UE transmits at its  $P_{UMAX}$  level; allow at least 200 ms starting from the first TPC command in this step for the UE to reach  $P_{UMAX}$  level.
3. Measure the mean power of each component carriers for the EN-DC configuration, which shall meet the requirements described in Table 6.2B.3.1.5.1 thru 6.5B.2.1.2.5.2 depending NS-values. The period of the measurement shall be at least the continuous duration of one sub-frame.
4. Measure the power of the transmitted signal with a measurement filter of bandwidths according to table 6.5B.4.1.3.1 -1. The centre frequency of the filter shall be stepped in contiguous steps according to the same table. The measured power shall be recorded for each step. The measurement period shall capture the active time slots.

#### 6.5B.4.1.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6 with the following exceptions for each network signalled value.

##### 6.5B.4.1.4.3.1 Message contents exceptions for network signalled value "NS\_04"

1. Information element `additionalSpectrumEmission` is set to NS\_04. This can be set in *SIB1* as part of the cell broadcast message. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario.

**Table 6.5B.4.1.4.3.1-1: *AdditionalSpectrumEmission*: Additional spurious emissions test requirement for "NS\_04"**

Derivation Path: TS 38.508-1 [5] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
<code>additionalSpectrumEmission</code>	1 (NS_04)		

#### 6.5B.4.1.5 Test Requirement

Test requirements for additional spurious emissions for intra-band contiguous EN-DC are the same as the minimum requirements described in clause 6.5B.4.1.3 and are not repeated in this section.

#### 6.5B.4.2 Additional Spurious Emissions for Intra-band non-contiguous EN-DC

**Editor's note: Wgap for intra-band non-contiguous EN-DC is FFS in TS 38.508-1**

##### 6.5B.4.2.1 Test purpose

Same minimum conformance requirements as in clause 6.5B.4.1.1.

##### 6.5B.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 6.5B.4.2.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5B.4.1.3.

### 6.5B.4.2.4 Test description

#### 6.5B.4.2.4.1 Initial conditions

Same initial conditions as described in subclause 6.5B.4.1.4.1 for both E-UTRA and NR carriers with the following exception:

1. For each EN-DC combination specified in Table 5.3B.1.3-1, channel spacing between NR and E-UTRA is specified according to subclause 5.4B.1.
2. Set up the NR and E-UTRA test frequencies so that NR carrier is located at the lower frequency side as specified in Table 5.3B.1.3-1. Repeat each testing with E-UTRA carrier frequency is located at the lower side as specified in Table 5.3B.1.3-1.

#### 6.5B.4.2.4.2 Test Procedure

Same test procedure as described in subclause 6.5B.4.1.4.2.

#### 6.5B.4.2.4.3 Message Contents

Message contents are according to TS 38.508-1 [5] subclause 4.6 with the following exceptions for each network signalled value.

##### 6.5B.4.2.4.3.1 Message contents exceptions for network signalled value "NS\_04"

1. Information element `additionalSpectrumEmission` is set to `NS_04`. This can be set in *SIB1* as part of the cell broadcast message. This exception indicates that the UE shall meet the additional spurious emission requirement for a specific deployment scenario.

**Table 6.5B.4.2.4.3.1-1: *AdditionalSpectrumEmission*: Additional spurious emissions test requirement for "NS\_04"**

Derivation Path: TS 38.508-1 [5] clause 4.6.3, Table 4.6.3-1			
Information Element	Value/remark	Comment	Condition
<code>additionalSpectrumEmission</code>	1 (NS_04)		

#### 6.5B.4.2.5 Test Requirement

Test requirements for Spurious Emissions for intra-band non-contiguous EN-DC are the same as the minimum requirements described in 6.5B.4.2.3 and are not repeated in this section.

## 6.5B.4.3 Additional Spurious Emissions for Inter-band EN-DC

### 6.5B.4.3.1 Test purpose

To verify that UE transmitter does not cause unacceptable interference to other channels or other systems in terms of transmitter spurious emissions under the deployment scenarios where additional requirements are specified.

### 6.5B.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward supporting inter-band EN-DC

### 6.5B.4.3.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 6.5B.4.1.3.



#### 6.5B.4.3.4 Test description

##### 6.5B.4.3.4.1 Initial conditions

Same initial conditions as described in subclause 6.5B.4.1.4.1

##### 6.5B.4.3.4.2 Test Procedure

Same test procedure as described in subclause 6.5B.4.1.4.2.

##### 6.5B.4.3.4.3 Message Contents

Same message contents as described in subclause 6.5B.4.1.4.3.

##### 6.5B.4.3.5 Test Requirement

Test requirements for additional spurious emissions for inter-band EN-DC are the same as the minimum requirements described in 6.5B.4.3.3 and are not repeated in this section.

### 6.5B.5 Transmit intermodulation

#### 6.5B.5.1 Intra-band contiguous EN-DC

#### 6.5B.5.2 Intra-band non-contiguous EN-DC

#### 6.5B.5.3 Inter-band EN-DC within FR1

##### 6.5B.5.3.1 Test purpose

Same test purpose as in clause 6.5.4 in TS 38.521-1 [8] for the NR carrier.

##### 6.5B.5.3.2 Te

editor's note

**Editor's note: wrong section starts here!**

##### 6.5B.5.3.3 Minimum conformance requirements

The transmit intermodulation requirement specified in sub-clauses 6.7.1 and 6.7.1A of [5] and sub-clauses 6.5.4 and 6.5A.4 of [2] apply for each component carrier in E-UTRA bands and NR bands, respectively.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

The normative reference for this measurement is TS 38.101-3 [4] clause 6.5B.5.3.

##### 6.5B.5.3.4 Test description

Same test description as in clause 6.5.4.4 in TS 38.521-1 [8] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 6.5.4.4.1 in TS 38.521-1 [8], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Step 6 of Initial conditions as in clause 6.5.4.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.

Same test procedure as in clause 6.5.4.4.2 in TS 38.521-1 [8].

#### 6.5B.5.3.5 Test Requirement

The ratio derived in step 6 and 8, shall not exceed the described value in Table 6.5.4.5-1 defined in TS 38.521-1 [8].

#### 6.5B.5.4 Inter-band EN-DC including FR2

#### 6.5B.5.5 Inter-band EN-DC including both FR1 and FR2

## 7 Receiver characteristics

### 7.1 General

**Editor's Note: Test configurations/environments that require new spherical scan shall be included in test procedure section and identifying such scenarios is currently FFS and owned by RAN5.**

For Rx test cases the identified beam peak direction can be stored and reused for a device under test in various configurations/environments for the full duration of device testing as long as beam peak direction is the same.

RX requirements for intra-band contiguous and non-contiguous EN-DC only apply for bands < 2.7GHz.

For intra-band non-contiguous EN-DC, the output power is configured as follows:

- One E-UTRA uplink carrier with the output power set to 4dB Below  $P_{\text{CMAX\_L}}$  and the NR band whose downlink is being tested has its uplink carrier output power set to minimum output power as defined in sub-clause 6.3.1 of [2].
- One NR uplink carrier with the output power set to 4dB Below  $P_{\text{CMAX\_L}}$  and the E-UTRA band whose downlink is being tested has its uplink carrier output power set to minimum output power as defined in sub-clause 6.3.2.1 of [4].

For the additional requirements for intra-band non-contiguous EN-DC of two sub-blocks, an in-gap test refers to the case when the interfering signal is located at a negative offset with respect to the assigned lowest channel frequency of the highest sub-block and located at a positive offset with respect to the assigned highest channel frequency of the lowest sub-block.

For the additional requirements for intra-band non-contiguous EN-DC of two sub-blocks, an out-of-gap test refers to the case when the interfering signal(s) is (are) located at a positive offset with respect to the assigned channel frequency of the highest carrier frequency or located at a negative offset with respect to the assigned channel frequency of the lowest carrier frequency.

For the additional requirements for intra-band non-contiguous EN-DC of two sub-blocks with channel bandwidth larger than or equal to 5 MHz, the existing adjacent channel selectivity requirements, in-band blocking requirements (for each case), and narrow band blocking requirements apply for in-gap tests only if the corresponding interferer frequency offsets with respect to the two measured carriers satisfy the following condition in relation to the sub-block gap size  $W_{\text{gap}}$  for at least one of the E-UTRA or NR sub-blocks, so that the interferer frequency position does not change the nature of the core requirement tested:

$$W_{\text{gap}} \geq 2 \cdot |F_{\text{Interferer (offset)}}| - BW_{\text{Channel}}$$

For the E-UTRA sub-block, the  $F_{\text{Interferer (offset)}}$ , for a sub-block with a single component carrier is the interferer frequency offset with respect to carrier as specified in subclause 7.5.1, subclause 7.6.1 and subclause 7.6.3 for the respective requirement in [4] and  $BW_{\text{Channel}}$ .  $F_{\text{Interferer (offset)}}$  for the E-UTRA sub-block with two or more contiguous component carriers is the interference frequency offset with respect to the carrier adjacent to the gap is specified in subclause 7.5.1A, 7.6.1A and 7.6.3A in [4].

For the NR sub-block, the  $F_{\text{Interferer (offset)}}$ , for a sub-block with a single component carrier is the interferer frequency offset with respect to carrier as specified in subclause 7.5.1, subclause 7.6.1 and subclause 7.6.3 for the respective requirement in [2] and  $BW_{\text{Channel}}$ .

The interferer frequency offsets for adjacent channel selectivity, each in-band blocking case and narrow-band blocking shall be tested separately with a single in-gap interferer at a time.

Unless otherwise stated the receiver characteristics are specified at the antenna connector(s) of the UE for the bands operating on frequency range 1 and over the air of the UE for the bands operating on frequency range 2. The requirements for frequency range 1 and frequency range 2 can be verified separately. For the carrier in frequency range 1, requirements can be verified with NR FR2 link disabled. For the carrier in frequency range 2, requirements can be verified in OTA mode with LTE connecting to the network by OTA without calibration.

The requirements defined in this clause are the extra requirements compared with the single carrier requirements defined in [2] and [3].

Unless otherwise stated, the UL and DL reference measurement channels are the same with the configurations specified in [2] and [3].

Unless otherwise stated, requirements for NR receiver written in TS 38.101-1 and TS 38.101-2 apply and are assumed anchor agnostic. Requirements are verified under conditions where anchor resources do not interfere NR operation.

Unless otherwise stated, Channel Bandwidth shall be prioritized in the selecting of test points. Subcarrier spacing shall be selected after Test Channel Bandwidth is selected.

For conformance testing involving FR2 test cases in this specification, the UE under test shall disable UL Tx diversity schemes.

## 7.2 Diversity characteristics

## 7.3 Reference sensitivity

### 7.3A Reference sensitivity for CA without EN-DC

#### 7.3A.1 General

FFS

#### 7.3A.2 Reference sensitivity power level for CA without EN-DC

FFS

#### 7.3A.3 $\Delta R_{\text{IB,c}}$ for CA without EN-DC

For the UE which supports inter-band NR CA configuration, the minimum requirement for reference sensitivity in subclause 7.3.2 in TS 38.101-1 [2] and subclause 7.3.2, 7.3A.2 in TS 38.101-2 [3] shall be increased by the amount given in  $\Delta R_{\text{IB,c}}$  in Tables below. Unless otherwise stated,  $\Delta R_{\text{IB,c}}$  is set to zero.

In case the UE supports more than one of band combinations for CA, SUL or DC, and an operating band belongs to more than one band combinations then

- When the operating band frequency range is  $\leq 1\text{GHz}$ , the applicable additional  $\Delta R_{\text{IB,c}}$  shall be the average value for all band combinations defined in subclause 7.3A, 7.3B, 7.3C in this specification and 7.3A, 7.3B in TS 38.101-3 [3], truncated to one decimal place that apply for that operating band among the supported band combinations. In case there is a harmonic relation between low band UL and high band DL, then the maximum  $\Delta R_{\text{IB,c}}$  among the different supported band combinations involving such band shall be applied

- When the operating band frequency range is > 1 GHz, the applicable additional  $\Delta R_{IB,c}$  shall be the maximum value for all band combinations defined in subclause 7.3A, 7.3B, 7.3C in this specification and 7.3A, 7.3B in TS 38.101-3 [3] for the applicable operating bands.

### 7.3A.3.1 Reference Sensitivity for Inter-band CA between FR1 and FR2 without EN-DC

(Void)

### 7.3A.4 Reference sensitivity exceptions due to UL harmonic interference for CA

Sensitivity degradation is allowed for a band in frequency range 2 if it is impacted by UL harmonic interference from the band in frequency range 1 of the same CA configuration. Reference sensitivity exceptions are specified in Table 7.3A.4-1 with uplink configuration specified in Table 7.3A.4-2.

**Table 7.3A.4-1: Reference sensitivity exceptions due to UL harmonic for NR CA of FR1+FR2**

UL Band	DL Band	50 MHz (dBm)	100 MHz (dBm)	200 MHz (dBm)	400 MHz (dBm)
X	Y				

## 7.3B Reference sensitivity level for DC

### 7.3B.1 General

For EN-DC, E-UTRA and NR single carrier REFSENS requirements defined in [2], [3] and [4] apply to all downlink bands of EN-DC configurations listed in clause 5.5B, unless sensitivity degradation exception is allowed in this clause of this specification, section 7.3 in TS 38.101-1 [2] or section 7.3 in TS 36.101 [4]. Allowed exceptions specified in this clause also apply to any higher order EN-DC configuration combination containing one of the band combinations that exception is allowed for. Reference sensitivity exceptions are specified by applying maximum sensitivity degradation (MSD) into applicable REFSENS requirement. EN-DC REFSENS requirements shall be met for NR uplink transmissions using QPSK DFT-s-OFDM waveforms as defined in clause 7.3.2 [2]. Unless otherwise specified UL allocation uses the lowest SCS allowable for a given channel BW.

In case of interband EN-DC the receiver REFSENS requirements in this clause do not apply for 1.4 and 3 MHz E-UTRA carriers.

### 7.3B.2 Reference sensitivity for EN-DC

*Editor's Note: Final section structure under further analysis and discussion.*

## 7.3B.2.0 Minimum Conformance Requirements of Reference sensitivity for EN-DC

## 7.3B.2.0.1 Intra-band contiguous EN-DC

For Intra-band contiguous EN-DC configurations listed in Table 7.3B.2.0.1-1, the reference sensitivity is defined only for the specific uplink and downlink test points which are specified in Table 7.3B.2.0.1-1 and E-UTRA and NR single carrier requirements do not apply. Table 7.3B.2.0.1-1: Reference sensitivity (MSD) for intra-band DC bandwidth class

EN-DC configuration/channel allocations/MSD							
DC configuration	E-UTRA/NR band	F <sub>c</sub> (UL) (MHz)	Channel bandwidth (MHz)	UL allocation (LCRB)	F <sub>c</sub> (DL) (MHz)	MSD (dB)	Duplex mode
DC_(n)71AA	71	665.5	5	5 (RB <sub>end</sub> = 24)	619.5	0	FDD
	n71	675.5	15	15 (RB <sub>start</sub> = 0)	629.5	1.8	
DC_(n)71AA	71	670.5	15	15 (RB <sub>end</sub> = 74)	624.5	0	
	n71	680.5	5	5 (RB <sub>start</sub> = 0)	634.5	1.6	
DC_(n)71AA	71	668	10	10 (RB <sub>end</sub> = 49)	622	0	
	n71	678	10	10 (RB <sub>start</sub> = 0)	632	1.7	
DC_(n)71AA	71	668	10	10 (RB <sub>start</sub> = 0)	622	17.2	
	n71	678	10	10 (RB <sub>end</sub> = 51)	632	29.4	

## 7.3B.2.0.2 Intra-band non-contiguous EN-DC

For DC\_3A\_n3A intra-band non-contiguous EN-DC combination, only single switched UL is supported in rel.15, therefore, no MSD is specified and E-UTRA and NR single carrier requirements apply.

## 7.3B.2.0.3 Inter-band EN-DC within FR1

Reference sensitivity exceptions are specified for the condition when there is uplink transmission only in the aggressor band.

*Editor's note: FFS how to clarify the issues of 1Tx may also exist for 2Tx mode, for example harmonic, etc.*

## 7.3B.2.0.3.1 Reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1

Sensitivity degradation is allowed for a band if it is impacted by UL harmonic interference from another band part of the same DC configuration. Reference sensitivity exceptions are specified in Table 7.3B.2.0.3.1-1 with uplink configuration specified in Table 7.3B.2.0.3.1-2.

**Table 7.3B.2.0.3.1-1: Reference sensitivity exceptions (MSD) due to UL harmonic for EN-DC in NR FR1**

E-UTRA or NR Band / Channel bandwidth of the affected DL band / MSD													
UL band	DL band	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	30 MHz (dB)	40 MHz (dB)	50 MHz (dB)	60 MHz (dB)	80 MHz (dB)	90 MHz (dB)	100 MHz (dB)
1, 3	n77 <sup>1,2</sup>		23.9	22.1	20.9			17.9	16.8	16.0	14.8	14.3	13.8
	n77 <sup>3</sup>		1.1	0.8	0.3			0	0	0	0	0	0
2	n78 <sup>1,2</sup>	27.1	23.9	22.1	20.9			17.9	16.8	16.0	14.8	14.3	13.8
	n78 <sup>3</sup>	1.9	1.1	0.8	0.3			0	0	0	0	0	0
3	n78 <sup>1,2</sup>		23.9	22.1	20.9			17.9	16.8	16.0	14.8	14.3	13.8
	n78 <sup>3</sup>		1.1	0.8	0.3			0	0	0	0	0	0
5	n78 <sup>6,7</sup>		10.5	8.9	7.8			5.4					
8	n77 <sup>6,7</sup> n78 <sup>6,7</sup>		10.8	9.1	8			5.1	4.2	3.5	2.3	2.1	1.4
8	n79 <sup>4,5</sup>							6.8	6.2	5.6	4.9		4.4
18, 19	n77 <sup>4,5</sup>		10.4	8.9	7.8			4.7	3.7	3	1.7	1.2	0.7
28	n77 <sup>4,5</sup> n78 <sup>4,5</sup>		10.4	8.9	7.8			4.7	3.7	3	1.7	1.2	0.7
20	n77 <sup>6,7</sup> n78 <sup>6,7</sup>		10.8	9.1	8			6	4.0	3.2	2.0	1.5	1.0
26	N41 <sup>8,9</sup>	NA	10.3	8.4	7.4			5	4.3	3.9	3.1	2.7	
26	n77 <sup>6,7</sup> n78 <sup>6,7</sup>		10.8	9.1	8			6	4.0	3.2	2.0	1.5	1.0
n28	1 <sup>8,9,10</sup>	10.2	7.6	6.2	5.3								
n71	2 <sup>11</sup>	4.6	1.0	0.7	0.6								
	2 <sup>12</sup>	1.7	1.0	0.7	0.6								
66	n78 <sup>1,2</sup>		23.9	22.1	20.9			17.9	16.8	16.0	14.8	14.3	13.8
	n78 <sup>3</sup>		1.1	0.8	0.3			0	0	0	0	0	0

- NOTE 1: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 2nd transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.
- NOTE 2: The requirements should be verified for UL EARFCN or NR ARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.2 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.
- NOTE 3: The requirements are only applicable to channel bandwidths with a carrier frequency at  $\pm (20 + BW_{Channel}^{HB} / 2)$  MHz offset from  $2f_{UL}^{LB}$  in the victim (higher) band with  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$ , whereand  $BW_{Channel}^{HB}$  are the channel bandwidths configured in the aggressor (lower) and victim (higher) bands in MHz, respectively.
- NOTE 4: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 5<sup>th</sup> transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.
- NOTE 5: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.5 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.
- NOTE 6: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 4<sup>th</sup> transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.
- NOTE 7: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.4 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.
- NOTE 8: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of a low band for which the 3rd transmitter harmonic is within the downlink transmission bandwidth of a high band.
- NOTE 9: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with the carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the low band.
- NOTE 10: Applicable for the operations with 2 or 4 antenna ports supported in the band with carrier aggregation configured.
- NOTE 11: These requirements apply when the lower edge frequency of the 5 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.
- NOTE 12: These requirements apply when the lower edge frequency of the 10 MHz, 15 MHz, or 20 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.
- NOTE 13: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 2nd transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band and a range  $\Delta F_{HD}$  above and below the edge of this downlink transmission bandwidth. The value  $\Delta F_{HD}$  depends on the EN-DC band combination:  $\Delta F_{HD} = 10$  MHz for DC\_3\_n77 and DC\_3\_n78;  $\Delta F_{HD} = 20$  MHz for DC\_1\_n77.



**Table 7.3B.2.0.3.1-2: Uplink configuration for reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1**

UL band	E-UTRA or NR Band / Channel bandwidth of the affected DL band / UL RB allocation of the agressor band												
	DL band	5 MHz	10 MHz	15 MHz	20 MHz	25 MHz	30 MHz	40 MHz	50 MHz	60 MHz	80 MHz	90 MHz	100 MHz
1	n77		25	36	50			100	100	100	100	100	100
2	n78	12	25	36	50			100	100	100	100	100	100
3	n77		25	36	50			50	50	50	50	50	50
3	n78		25	36	50			50	50	50	50	50	50
5	n78	8	16	25	25			25					
8	n77 n78		16	25	25			25	25	25	25	25	25
8	n79							25	25	25	25		25
18	n77		16	25	25			25	25	25	25	25	25
19	n77		16	25	25			25	25	25	25		25
20	n77 n78		16	25	25 <sup>1</sup> , 25 <sup>2</sup>			25	25	25	25	25	25
20	n41		16	25	25			25	25				
26	n77 n78		16	25	25			25	25	25	25	25	25
n28	1	8	16	25	25								
28	n77 n78		10	-15	20			25	25	25	25	25	25
66	n78		25	36	50			100	100	100	100	100	100
n71	2	25 <sup>4</sup> 8 <sup>5</sup>	25 <sup>4</sup> 8 <sup>5</sup>	20 <sup>4</sup> 8 <sup>5</sup>	20 <sup>4</sup> 8 <sup>5</sup>								

NOTE 1: The UL configuration applies regardless of the channel bandwidth of the UL band. UL resource blocks allocation in the table shall be further limited to that specified in Table 7.3.1-2 in TS 36.101 [4] or Table 7.3.2-3 in TS 38.101-1 [2]

NOTE 2: Void.

NOTE 3: The RB allocation is at the lower edge of the lowest channel of UL band.

NOTE 4: These requirements apply when the lower edge frequency of the 5 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

NOTE 5: These requirements apply when the lower edge frequency of the 10 MHz, 15 MHz, or 20 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

### 7.3B.2.0.3.2 Reference sensitivity exceptions due to receiver harmonic mixing for EN-DC in NR FR1

Sensitivity degradation is allowed for a band if it is impacted by receiver harmonic mixing due to another band part of the same EN-DC configuration. Reference sensitivity exceptions for the victim band (low) are specified in Table 7.3B.2.0.3.2-1 with uplink configuration of the agressor band (high) specified in Table 7.3B.2.0.3.2-2.

**Table 7.3B.2.0.3.2-1: Reference sensitivity exceptions (MSD) due to receiver harmonic mixing for EN-DC in NR FR1**

E-UTRA or NR Band / Channel bandwidth of the affected DL band / MSD												
UL band	DL band	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	40 MHz (dB)	50 MHz (dB)	60 MHz (dB)	80 MHz (dB)	90 MHz (dB)	100 MHz (dB)
2	n71 <sup>4</sup>	26.8	23.6	21.2	15.6							
n4126	26 <sup>4</sup>	24.3	24.3	22.5	N/A							
41	n77 <sup>7</sup>		8.3	8.0	6.9		3.9	3	2.3	1.2		0.4
41	n78 <sup>7</sup>		8.3	8.0	6.9		3.9	3	2.3	1.2		0.4
n71	2 <sup>5</sup>	4.6	1	0.7	0.6							
	2 <sup>6</sup>	1.7	1	0.7	0.6							
n77	41 <sup>8</sup>	10.4	10.4	10.4	10.4							N/A
n77	28 <sup>2</sup>	28	25	23.2	22							
n78	41 <sup>8</sup>	10.4	10.4	10.4	10.4							N/A
n79	19 <sup>2</sup>	29.5	26.5	24.7								
n79	21 <sup>3</sup>	39.3	36.3	34.5								
n79	26 <sup>2</sup>	27	24	22.2								

NOTE 1: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (higher) band for which the mixing product due to harmonic of victim (lower) band LO with leakage of aggressor (higher) band is within the downlink transmission bandwidth of a victim (lower) band.

NOTE 2: The requirements should be verified for DL EARFCN of the victim (lower) band (superscript LB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.5 \rfloor 0.1$  in MHz and  $F_{DL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{DL}^{LB} \leq F_{DL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with  $f_{DL}^{LB}$  carrier frequency in the victim (lower) band in MHz and the channel bandwidth configured in the lower band.

NOTE 3: The requirements should be verified for DL EARFCN of the victim (lower) band (superscript LB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.4 \rfloor 0.1$  in MHz and  $F_{DL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{DL}^{LB} \leq F_{DL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with  $f_{DL}^{LB}$  carrier frequency in the victim (lower) band in MHz and the channel bandwidth configured in the lower band.

NOTE 4: The requirements should be verified for UL EARFCN of the aggressor (higher) band (superscript HB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.3 \rfloor 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with the carrier frequency in the victim (lower) band and the channel bandwidth configured in the higher band.

NOTE 5: These requirements apply when the lower edge frequency of the 5 MHz uplink channel in Band n71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

NOTE 6: These requirements apply when the lower edge frequency of the 10 MHz, 15 MHz, or 20 MHz uplink channel in Band n71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

NOTE 7: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.15 \rfloor 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.

NOTE 8: The requirements should be verified for UL EARFCN of the aggressor (higher) band (superscript HB) such that  $f_{UL}^{LB} = \lfloor 15 * f_{DL}^{HB} \rfloor 0.1$  in MHz and  $F_{UL\_low}^{HB} + BW_{Channel}^{HB} / 2 \leq f_{UL}^{HB} \leq F_{UL\_high}^{HB} - BW_{Channel}^{HB} / 2$  with  $f_{UL}^{LB}$  carrier frequency in the victim (lower) band in MHz and  $BW_{Channel}^{LB}$  the channel bandwidth configured in the higher band.

**Table 7.3B.2.0.3.2-2: Uplink configuration for reference sensitivity exceptions due to receiver harmonic mixing for EN-DC in NR FR1**

E-UTRA or NR Band / SCS / Channel bandwidth of the affected DL band / UL RB allocation of the aggressor band													
UL band	DL band	SCS of UL band (kHz)	5 MHz (LCRB)	10 MHz (LCRB)	15 MHz (LCRB)	20 MHz (LCRB)	25 MHz (LCRB)	40 MHz (LCRB)	50 MHz (LCRB)	60 MHz (LCRB)	80 MHz (LCRB)	90 MHz (LCRB)	100 MHz (LCRB)
2	n71	15	25	50	50	50							
n41	26	15	25	50	75								
41	n77	15		25	25	25							
41	n78	15		25	25	25							
n77	28	15	25	50	75	100							
n77	41	30	N/A	50	50	50							
n78	41	30	N/A	50	50	50							
n79	19	15	25	50	75								
n79	21	15	25	50	75								
n79	26	15	25	50	75								

NOTE 1: These requirements apply when there is at least one individual RE within the downlink transmission bandwidth of the victim (lower) band for which the 3rd harmonic is within the uplink transmission bandwidth or the uplink adjacent channel's transmission bandwidth of an aggressor (higher) band.

NOTE 2: The requirements should be verified for UL EARFCN of the aggressor (higher) band (superscript HB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.3 \rfloor 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with the carrier frequency in the victim (lower) band and the channel bandwidth configured in the higher band.

NOTE 3: The UL configuration applies regardless of the channel bandwidth of the UL band. UL resource blocks allocation in the table shall be further limited to that specified in Table 7.3.1-2 in TS36.101 or Table 7.3.2-3 in TS38.101-1.

7.3B.2.0.3.3 Void

Table 7.3B.2.0.3.3-1: Void

**Table 7.3B.2.0.3-2: Void**

7.3B.2.0.3.4 Reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1

Sensitivity degradation is allowed for a band if it is impacted by UL of another band part of the same EN-DC configuration due to cross band isolation issues. Reference sensitivity exceptions for the victim band are specified in Table 7.3B.2.0.3.4-1 with uplink configuration of the aggressor band specified in Table 7.3B.2.0.3.4-2.

**Table 7.3B.2.0.3.4-1: Reference sensitivity exceptions (MSD) due to cross band isolation for EN-DC in NR FR1**

E-UTRA or NR Band / Channel bandwidth of the affected DL band /MSD												
UL band	DL band	5 MHz (dBm)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	40 MHz (dB)	50 MHz (dB)	60 MHz (dB)	80 MHz (dB)	90 MHz (dB)	100 MHz (dB)
n41	25	0.6	0.6	0.6	0.6							
n77	41 <sup>1</sup>	4.5	4.5	4.5	4.5							
n78	41 <sup>1</sup>	4.5	4.5	4.5	4.5							

NOTE 1: Applicable only when harmonic mixing MSD for this combination is not applied.

**Table 7.3B.2.0.3.4-2: Uplink configuration for reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1**

E-UTRA or NR Band / SCS / Channel bandwidth of the affected DL band / UL RB allocation of the agressor band													
UL band	DL band	SCS of UL band (kHz)	5 MHz (LCRB)	10 MHz (LCRB)	15 MHz (LCRB)	20 MHz (LCRB)	25 MHz (LCRB)	40 MHz (LCRB)	50 MHz (LCRB)	60 MHz (LCRB)	80 MHz (LCRB)	90 MHz (LCRB)	100 MHz (LCRB)
n41	25	30	160	160	160	160							
n77	41	30	270	270	270	270							
n78	41	30	270	270	270	270							

NOTE 1: The UL configuration applies regardless of the channel bandwidth of the UL band. UL resource blocks allocation in the table shall be further limited to that specified in Table 7.3.1-2 in TS36.101 or Table 7.3.2-3 in TS38.101-1 [2].

### 7.3B.2.0.3.5 MSD for intermodulation interference due to dual uplink operation for EN-DC in NR FR1

For EN-DC configurations in NR FR1 the UE may indicate capability of not supporting simultaneous dual uplink operation due to possible intermodulation interference overlapping in frequency to its own primary downlink channel bandwidth if

- the intermodulation order is 2;
- the intermodulation order is 3 when both operating bands are between 450 MHz – 960 MHz or between 1427 MHz – 2690 MHz

In case for the EN-DC in NR FR1 configurations the intermodulation products caused by dual uplink operation do not interfere with the own primary downlink channel bandwidth as defined in Annex-I the UE is mandated to operate in dual and triple uplink mode.

For EN-DC in NR FR1 with uplink and downlink assigned to E-UTRA and NR FR1 bands given in Table 7.3B.2.0.3.5.1-1, Table 7.3B.2.0.3.5.2-1 and Table 7.3B.2.0.3.5.3-1 the reference sensitivity is defined only for the specific uplink and downlink test points specified in Table 7.3B.2.0.3.5.1-1, Table 7.3B.2.0.3.5.2-1 and Table 7.3B.2.0.3.5.3-1. For these test points the reference sensitivity levels specified in clause 7.3.1 in [4] and 7.3.2.1 of [2] for the corresponding channel bandwidths or in clause 7.3.1 of [4] are relaxed by the amount of the parameter MSD given in Table 7.3B.2.0.3.5.1-1, Table 7.3B.2.0.3.5.2-1 and Table 7.3B.2.0.3.5.3-1.

The throughput on each of the CGs shall be  $\geq 95\%$  of the maximum throughput of the respective reference measurement channels as specified in ... with parameters specified in Table 7.3B.2.0.3.5-1 with dual UL transmissions overlapping in time unless otherwise stated.

For EN-DC configurations in Table 7.3B.2.0.3.5-1 with UL/DL channel assignments such that Single UL is allowed, the MSD requirement is verified with non-simultaneous uplink transmissions on the two CGs for UEs only indicating support of Single UL.

7.3B.2.0.3.5.1 MSD test points for intermodulation interference due to dual uplink operation for EN-DC in NR FR1 involving two bands

**Table 7.3B.2.0.3.5.1-1: MSD test points for PCell due to dual uplink operation for EN-DC in NR FR1 (two bands)**

NR or E-UTRA Band / Channel bandwidth / N <sub>RB</sub> / MSD								
EN-DC Configuration	EUTRA or NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)		IMD order
DC_1A_n77A	1	1950	5	25	2140	29.8		IMD2 <sup>3</sup>
						32.5 <sup>4</sup>		
DC_1A_n77A DC_1A_n78A, DC_1A_SUL_n78A- n84A	1	1950	5	25	2140	8.0		IMD4 <sup>3</sup>
						10.7 <sup>4</sup>		
DC_1A_n78A, DC_1A_SUL_n78A- n84A	n77	3710	10	50	3710	N/A		N/A
	1	1950	5	25	2140	8.0		IMD4 <sup>3</sup>
						10.7 <sup>4</sup>		
DC_2A_n66A	2	1855	5	25	1935	20		IMD3
	n66	1775	5	25	2175	N/A		N/A
DC_2A_n66A	2	1883.3	5	25	1963.3	N/A		N/A
	n66	1750	5	25	2150	4		IMD5
DC_2A_n78A	2	1855	5	25	1940	26		IMD2 <sup>3</sup>
						28.7 <sup>4</sup>		
DC_2A_n78A	n78	3795	10	50	3795	N/A		N/A
	2	1885	5	25	1955	8.0		IMD4 <sup>3</sup>
						10.7 <sup>4</sup>		
DC_3A_n7A	n78	3700	10	50	3700	N/A		N/A
	3	1730	5	25	1825	N/A		N/A
DC_3A_n7A	n7	2535	10	50	2655	10.2 <sup>5</sup>		IMD4
	3	1740	5	25	1835	26		IMD2 <sup>3</sup>
DC_3A_n77A DC_3A_n78A DC_3A-SUL_n78A- n80A, DC_3C_n78A						28.7 <sup>4</sup>		
	n77, n78	3575	10	50	3575	N/A		N/A
DC_3A_n77A DC_3A_n78A DC_3A-SUL_n78A- n80A, DC_3C_n78A	3	1765	5	25	1860	8.0		IMD4 <sup>3</sup>
						10.7 <sup>4</sup>		
DC_3A_n78A	n77, n78	3435	10	50	3435	N/A		N/A
	3	1712.5	5	25	1807.5	TBD <sup>5</sup>		IMD2
DC_3A_n78A	n78	3515	10	50	3515	N/A		N/A
	3	1762.5	5	25	1857.5	N/A		N/A
	n78	3465	10	50	3465	N/A		N/A
	3	1740	5	25	1835	26		IMD2 <sup>3</sup>
DC_3A-SUL_n78A- n80A						28.7 <sup>4</sup>		
	n78	3575	10	25	3575	N/A		N/A
DC_3A_SUL_n78A- n80A	3	1765	5	25	1860	8.0		IMD4 <sup>3</sup>
						10.7 <sup>4</sup>		
DC_3A_SUL_n78A- n80A	n78	3435	10	25	3435	N/A		N/A
	3	1740	5	25	1835	26		IMD2 <sup>4</sup>
DC_3C_n78A						28.7 <sup>5</sup>		
	n78	3575	10	25	3575	N/A		N/A
	n78	3710	10	25	3710	N/A		N/A
DC_3C_n78A	3	1765	5	25	1860	8.0		IMD4 <sup>4</sup>
						10.7 <sup>5</sup>		
DC_5A_n66A	n78	3435	10	25	3435	N/A		N/A
	5	838	5	25	883	30		IMD2 <sup>3</sup>
DC_5A_n66A	n66	1721	5	25	2121	N/A		N/A
	5	844	5	25	889	8.3		IMD4
DC_5A_n78A	n78	3421	10	50	3421	N/A		N/A
	8	897.5	5	25	942.5	8.3		IMD4
DC_8A_n77A DC_8A_n78A DC_8A-SUL_n78A- n81A	n77, n78	3635	10	50	3635	N/A		H4
	8	897.5	5	25	942.5	4.8		IMD5

DC_8A_n79A DC_8A-SUL_n79A-n81A	n79	4532.5	40	216	4532.5	N/A		N/A
DC_20A_n8A	20	849.5	5	25	808.5	21		IMD3
	n8	892.5	5	25	937.5	21		IMD3
DC_20A_n77A DC_20A_n78A, DC_20A-SUL_n78A-n82A	20	850	5	25	809	11		IMD4
	n77	3359	10	50	3359	N/A		N/A
DC_20A_n77A,	20	840	5	25	799	6.5		IMD5 <sup>4</sup>
	n77	4159	10	50	4159	N/A		N/A
DC_21A_n79A	21	1457.5	5	25	1505.5	18.4		IMD3
	n79	4420.5	40	216	4420.5	N/A		N/A
DC_26A_n41A	26	839	5	25	884	15.6		IMD3
	n41	2562	10	50	2562	N/A		N/A
DC_28A_n51A	28	742.3	5	25	797.3	5		IMD 4
	n51	1429.5	5	25	1429.5	N/A		N/A
DC_26A_n77A DC_26A_n78A	26	836.5	5	25	881.5	11.1		IMD4
	n77, n78	3391	10	50	3391	N/A		N/A
CA_28A_n77A, CA_28A_n78A, DC_28A-SUL_n78A-n83A	28	705.5	5	25	760.5	5.5		IMD5
	n77, n78	3582.5	10	50	3582.5	N/A		N/A
DC_66A_n5A	n5	838	5	25	883	30		IMD2 <sup>3</sup>
	66	1721	5	25	2121	N/A		N/A
DC_66A_n71A	66	1750	5	25	2150	5		IMD4
	n71	675	5	25	629	N/A		N/A
<p>NOTE 1: Both of the transmitters shall be set min(+20 dBm, P<sub>CMAX,L,c</sub>) as defined in subclause 6.2.5A.</p> <p>NOTE 2: RB<sub>START</sub> = 0</p> <p>NOTE 3: This band is subject to IMD5 also which MSD is not specified.</p> <p>NOTE 4: Applicable only if operation with 4 antenna ports is supported in the band with carrier aggregation configured.</p> <p>NOTE 5: Void.</p>								

7.3B.2.0.3.5.2 MSD test points for intermodulation interference due to dual uplink operation for EN-DC in NR FR1 involving three bands

**Table 7.3B.2.0.3.5.2-0: MSD test points for Pcell due to dual uplink operation for EN-DC in NR FR1 (three bands)**

EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)		IMD order
DC_66A_(n)71AA	66	1750	5	25	2150	5		IMD4
	n71	678	10	10 (RB <sub>start</sub> =0)	632	N/A		

**Table 7.3B.2.0.3.5.2-1: MSD test points for Scell due to dual uplink operation for EN-DC in NR FR1 (three bands)**



NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
DC_1A-3A_n28A	1	1975	5	25	2165	N/A		N/A
	n28	710.5	5	25	765.5	N/A		N/A
	3	1723.5	5	25	1818.5	4.0		IMD5
DC_1A-3A_n28A	3	1780	5	25	1875	N/A		N/A
	n28	710.5	5	25	765.5	N/A		N/A
	1	1949	5	25	2139	11.0		IMD4
DC_1A-7A_n28A	1	1935	5	25	2125	N/A		N/A
	n28	718	5	25	773	N/A		N/A
	7	2533	10	50	2653	30.0		IMD2
DC_1A-3A_n77A	1	1950	5	25	2140	N/A		N/A
	3	1712.5	5	25	1807.5	31.5		IMD2
	n77	3757.5	10	50	3757.5	N/A		N/A
	1	1950	5	25	2140	N/A		N/A
	3	1775	5	25	1870	8.5		IMD4
	n77	3980	10	50	3980	N/A		N/A
	1	1950	5	25	2140	31.0		IMD2
	3	1775	5	25	1870	N/A		N/A
	n77	3915	10	50	3915	N/A		N/A
DC_1A-3A_n78A DC_1A-3C_n78A								
	1	1950	5	25	2140	N/A		N/A
	3	1712.5	5	25	1807.5	31.2		IMD2  f <sub>B78</sub> -f <sub>B1</sub>
	n78	3757.5	10	50	3757.5	N/A		N/A
	1	1935	5	25	2125	2.8		IMD5  2*f <sub>B78</sub> -3*f <sub>B3</sub>
	3	1775	5	25	1870	N/A		N/A
	n78	3725	10	50	3725	N/A		N/A
	1	1932	5	25	2122	18.1		IMD3  f <sub>B78</sub> -2*f <sub>B5</sub>
	5	829	5	25	874	N/A		N/A
	n78	3780	10	50	3780	N/A		N/A
	1	1975	5	25	2165	N/A		N/A
	5	840	5	25	885	3.1		IMD5  2*f <sub>B78</sub> -3*f <sub>B1</sub>
	n78	3405	10	50	3405	N/A		N/A
	1	1977.5	5	25	2167.5	N/A		N/A
	7	2507.5	5	25	2627.5	9.1		IMD4  f <sub>B78</sub> -3*f <sub>B1</sub>
	n78	3305	10	50	3305	N/A		N/A
	1	1950	5	25	2140	8.7		IMD4  2*f <sub>B78</sub> -2*f <sub>B7</sub>
7	2510	10	50	2630	N/A		N/A	
n78	3310	10	50	3310	N/A		N/A	
DC_1A-3A_n79A	1	1950	5	25	2140	3.6		IMD5
	3	1750	5	25	1845	N/A		N/A
	n79	4860	40	216	4860	N/A		N/A
DC_1A-18A_n77A	1	1930	5	25	2120	16.4		IMD3
	18	825	5	25	870	N/A		N/A
	n77	3770	10	50	3770	N/A		N/A
DC_1A-18A_n78A	1	1930	5	25	2120	16.4		IMD3
	18	819	5	25	864	N/A		N/A
	n78	3758	10	50	3758	N/A		N/A
DC_1A-18A_n79A	1	1935	5	25	2125	N/A		N/A
	18	822.5	5	25	867.5	18.3		IMD3

NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
	n79	4782.5	40	216	4782.5	N/A		N/A
	1	1930	5	25	2120	N/A		N/A
	18	820	5	25	865	8.9		IMD4
	n79	4925	40	216	4925	N/A		N/A
	1	1935	5	25	2125	8.1		IMD4
	18	822.5	5	25	867.5	N/A		N/A
DC_1A-19A_n77A DC_1A-19A_n78A	n79	4782.5	40	216	4782.5	N/A		N/A
	1	1940	5	25	2130	17.8		IMD3
	19	832.5	5	25	877.5	N/A		N/A
DC_1A-19A_n79A	n77, n78	3795	10	50	3795	N/A		N/A
	1	1950	5	25	2140	N/A		N/A
	19	837.5	5	25	882.5	18.3		IMD3
	n79	4782.5	40	216	4782.5	N/A		N/A
	1	1950	5	25	2140	8.1		IMD4
	19	837.5	5	25	882.5	N/A		N/A
DC_1A-20A_n78A	n79	4652.5	40	216	4652.5	N/A		N/A
	1	1930	5	25	2120	20.3		IMD3
	20	835	5	25	794	N/A		N/A
DC_1A-20A_n78A	n78	3790	10	50	3790	N/A		N/A
	1	1950	5	25	2140	N/A		N/A
	20	851	5	25	810	3.0		IMD5
DC_1A-21A_n77A DC_1A-21A_n78A	n78	3330	10	50	3330	N/A		N/A
	1	1964.6	5	25	2154.6	30.6		IMD2
	21	1450.4	5	25	1498.4	N/A		N/A
	n77, n78	3605	10	50	3605	N/A		N/A
	1	1950	5	25	2140	N/A		N/A
	21	1452	5	25	1500	2.9		IMD5
DC_1A-28A_n77A	n77, n78	3675	10	50	3675	N/A		N/A
	1	1960	5	25	2150	15.8		IMD3
	28	740	5	25	795	N/A		N/A
DC_1A-28A_n77A	n77	3630	10	50	3630	N/A		N/A
	1	1960	5	25	2150	N/A		N/A
	28	725	5	25	780	4.3		IMD5
DC_1A-28A_n78A	n77	3330	10	50	3330	N/A		N/A
	1	1960	5	25	2150	15.7		IMD3
	28	740	5	25	795	N/A		N/A
DC_1A-28A_n78A	n78	3630	10	50	3630	N/A		N/A
	1	1970	5	25	2160	N/A		N/A
	28	739	5	25	794	4.2		IMD5
DC_1A_n28A_n78A	n78	3352	10	50	3352	N/A		N/A
	1	1950	5	25	2140	N/A		N/A
	n28	733	5	25	788	N/A		N/A
	n78	3416	10	50	3416	15.7		IMD3
	1	1950	5	25	2140	N/A		N/A
	n78	3320	10	50	3320	N/A		N/A
DC_1A-28A_n79A	n28	735	5	25	790	3.3		IMD5
	1	1930	5	25	2120	N/A		N/A
	28	733	5	25	788	15.2		IMD3
	n79	4648	40	216	4648	N/A		N/A
	1	1925	5	25	2115	N/A		N/A
	28	740	5	25	795	10.0		IMD4
	n79	4980	40	216	4980	N/A		N/A
	1	1977.5	5	25	2167.5	1.2		IMD4
	28	745.5	5	25	800.5	N/A		N/A
	n79	4420	40	216	4420	N/A		N/A
	1	1935	5	25	2125	4.5		IMD5
	28	718	5	25	773	N/A		N/A
DC_1A-41A_n77A	n79	4807	40	216	4807	N/A		N/A
	1	1970	5	25	2160	N/A		N/A
	n77	3400	10	50	3400			N/A
	41	2510	5	25	2510	11.0		IMD4

NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
	1	1930	5	25	2120	N/A		N/A
	n77	4150	10	50	4150			
	41	2510	5	25	2510	3.6		IMD5
DC_1A-41A_n78A	1	1975	5	25	2165	N/A		N/A
	41		5	25	2515	12		IMD4
	n78	3410	10	50	3410	N/A		N/A
DC_1A-41A_n79A	1	1970	5	25	2160	N/A		N/A
	n79	4500	40	216	4500			
	41	2530	5	25	2530	29.4		IMD2
	1	1922.5	5	25	2112.5	N/A		N/A
	n79	4980	40	216	4980			
DC_1A-42A_n79A	41	2687.5	5	25	2687.5	0.0		IMD5
	1	1977.5	5	25	2167.5	N/A		N/A
	n79	4420	40	216	4420			
	42	3490	5	25	3490	4.8		IMD5
	42	3402.5	5	25	3402.5	N/A		N/A
	n79	4640	40	216	4640			
	1	1975	5	25	2165	15.5		IMD3
	42	3450	5	25	3450	N/A		N/A
DC_1A_n78A-n79A	n79	4520	40	216	4520			
	1	1950	5	25	2140	9.3		IMD4
	1	1950	5	25	2140	N/A		N/A
	n78	3410	10	50	3410	N/A		N/A
	n79	4870	40	216	4870	15.9		IMD3
	1	1950	5	25	2140	N/A		N/A
	n79	4670	40	216	4670	N/A		N/A
DC_3A-7A_n28A	n78	3490	10	50	3490	4.6		IMD5
	3	1712.5	5	25	1807.5	N/A		N/A
	n28	743	5	25	798	N/A		N/A
	7	2562	10	50	2662	N/A		N/A
	7	2543	10	50	2663	N/A		N/A
	n28	710.5	5	25	765.5	N/A		N/A
DC_3C-7C_n78A	3	1737.5	5	25	1832.5	26.0		IMD2
	3	1725	5	25	1820	17.6		IMD3  f <sub>B78</sub> -2*f <sub>B7</sub>
	7	2565	5	25	2685	N/A		N/A
	n78	3310	10	50	3310	N/A		N/A
	3	1725	5	25	1820	8.6		IMD4  2*f <sub>B78</sub> -2*f <sub>B7</sub>
	7	2565	5	25	2685	N/A		N/A
DC_3A-20A_n28A	n78	3475	10	50	3475	N/A		N/A
	20	852	5	25	811	N/A		N/A
	n28	738	5	25	793	N/A		N/A
DC_3A-28A_n77A	3	1723	5	25	1818	9.4		IMD4
	3	1712.5	5	25	1807.5	N/A		N/A
	28	715	5	25	770	15.3		IMD3
	n77	4195	10	50	4195	N/A		N/A
	3	1755	5	25	1850	17.0		IMD3
	28	735	5	25	790	N/A		N/A
	n77	3320	10	50	3320	N/A		N/A
	3	1775	5	25	1870	17.3		IMD3
DC_3A-28A_n79A	28	740	5	25	760	N/A		N/A
	n78	3350	10	25	3350	N/A		N/A
	3	1770	5	25	1865	N/A		N/A
	28	725	5	25	780	10.3		IMD4
	n79	4530	40	216	4530	N/A		N/A
	3	1775	5	25	1870	5.7		IMD5
DC_3A-28A_n79A	28	725	5	25	780	N/A		N/A
	n79	4770	40	216	4770	N/A		N/A
	3	1775	5	25	1870	5.7		IMD5

NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
DC_3A_n28A-n78A	3	1750	5	25	1845	N/A		N/A
	n28	743	5	25	798	N/A		N/A
	n78	3764	10	50	3764	4.5		IMD5
DC_3A_n78A-n79A	3	1770	5	25	1865	N/A		N/A
	n78	3340	10	50	3340	N/A		N/A
	n79	4910	40	216	4910	16.3		IMD3
	3	1770	5	25	1865	N/A		N/A
	n79	4510	40	216	4510	N/A		N/A
DC_3A-SUL_n78A-n82A	3	1775	5	25	1870	4		IMD4
	n82	840	5	25		N/A		N/A
DC_3A-7A_n78A DC_3C-7A_n78A	3	1725	5	25	1820	17.6		IMD3 $ f_{B78}-2*f_{B7} $
	7	2565	5	25	2685	N/A		N/A
	n78	3310	10	50	3310	N/A		N/A
DC_3A-7A_n78A DC_3C-7A_n78A	3	1725	5	25	1820	8.6		IMD4 $ 2*f_{B78}-2*f_{B7} $
	7	2565	5	25	2685	N/A		N/A
	n78	3475	10	50	3475	N/A		N/A
DC_3A-19A_n79A	3	1782.5	5	25	1877.5	0.2		IMD4
	19	842.5	5	25	887.5	N/A		N/A
	n79	4420	40	216	4420	N/A		N/A
DC_3A-20A_n78A DC_3C-20A_n78A	3	1725	5	25	1820	17.3		IMD3 $ f_{B78}-2*f_{B20} $
	20	845	5	25	804	N/A		N/A
	n78	3510	10	50	3510	N/A		N/A
DC_3A-21A_n77A DC_3A-21A_n78A	3	1767.5	5	25	1862.5	N/A		N/A
	21	1459.5	5	25	1507.5	8.8		IMD4
	n77, n78	3795	10	50	3795	N/A		N/A
DC_3A-21A_n77A	3	1771.6	5	25	1866.6	3.4		IMD5
	21	1450.4	5	25	1498.4	N/A		N/A
	n77	3935	10	50	3935	N/A		N/A
DC_3A-21A_n79A	3	1774.2	5	25	1869.2	17.8		IMD3
	21	1450.4	5	25	1498.4	N/A		N/A
	n79	4770	40	216	4770	N/A		N/A
	5	844	5	25	889	N/A		N/A
	7	2525	5	25	2645	30.1		IMD2 $ f_{B78}-f_{B5} $
	n78	3489	10	50	3489	N/A		N/A
	5	834	5	25	879	30.2		IMD2 $ f_{B78}-f_{B7} $
	7	2550	5	25	2670	N/A		N/A
	n78	3429	10	50	3429	N/A		N/A
	5	830	5	25	875	3.3		IMD5 $ 2*f_{B78}-3f_{B7} $
DC_5A_41A_n78A	7	2525	5	25	2645	N/A		N/A
	n78	3350	10	50	3350	N/A		N/A
	5	860	5	25	885	30.2		IMD2
	41	2615	5	25	2615	N/A		N/A
	n78	3500	10	50	3500	N/A		N/A
	5	856.5	5	25	881.5	3.1		IMD5
DC_7A-20A_n28A	41	2620.5	5	25	2620.5	N/A		N/A
	n78	3490	10	50	3490	N/A		N/A
	20	852	5	25	811	N/A		N/A
	n28	738	5	25	793	N/A		N/A
	7	2550	10	50	2670	5.9		IMD5

NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
DC_7A-20A_n78A	7	2560	5	25	2680	N/A		N/A
	20	851	5	25	810	30.5		IMD2  f <sub>B78</sub> -f <sub>B7</sub>
	n78	3370	10	50	3370	N/A		N/A
DC_7A-20A_n7 DC_20A_n28A-n78A 8A	7	2560	5	25	2680	N/A		N/A
	20	851	5	25	810	3.0		IMD5  2*f <sub>B78</sub> -3*f <sub>B7</sub>
	n78	3435	10	50	3435	N/A		N/A
DC_7A-20A_n78A	7	2555	5	25	2675	30.8		IMD2  f <sub>B78</sub> -f <sub>B20</sub>
	20	845	5	25	804	N/A		N/A
	n78	3520	10	50	3520	N/A		N/A
DC_7A-28A_n78A	7	2570	5	25	2670	N/A		N/A
	28	720	5	25	780	8.3		IMD2
	n78	3350	10	50	3421	N/A		N/A
	7	2570	5	25	2670	N/A		N/A
	28	720	5	25	790	3.0		IMD5
	n78	3460	10	50	3421	N/A		N/A
	7	2570	5	25	2650	30.5		IMD2
	28	740	5	25	768	N/A		N/A
	n78	3390	10	50	3421	N/A		N/A
DC_7A_n28A-n78A	7	2565	5	25	2685	N/A		N/A
	n28	745	5	25	800	N/A		N/A
	n78	3310	10	50	3310	29.7		IMD2
	7	2565	5	25	2685	N/A		N/A
	n78	3365	10	50	3365	N/A		N/A
	n28	745	5	25	800	28.8		IMD2
DC_7A-46A_n78A <sup>6</sup>	7	N/A	N/A	N/A	N/A	N/A		N/A
	46	N/A	N/A	N/A	N/A	N/A		IMD2, IMD5
	n78	N/A	N/A	N/A	N/A	N/A		N/A
DC_18A-28A_n77A	18	820	5	25	865	N/A		N/A
	28	723	5	25	778	4.4		IMD5
	n77	4058	10	50	4058	N/A		N/A
DC_18A-28A_n77A	18	820	5	25	865	3.9		IMD5
	28	723	5	25	778	N/A		N/A
	n77	3757	10	50	3757	N/A		N/A
DC_18A-28A_n78A	18	819	5	25	864	3.8		IMD5
	28	723	5	25	778	N/A		N/A
	n78	3756	10	50	3756	N/A		N/A
DC_19A-21A_n77A DC_19A-21A_n78A	19	837.5	5	25	882.5	18.7		IMD3
	21	1450.4	5	25	1498.4	N/A		N/A
	n77, n78	3783.3	10	50	3783.3	N/A		N/A
DC_19A-21A_n77A	19	837.5	5	25	882.5	N/A		N/A
	21	1454.5	5	25	1502.5	9.0		IMD4
	n77	4015	10	50	4015	N/A		N/A
DC_19A-21A_n79A	19	837.5	5	25	882.2	N/A		N/A
	21	1452	5	25	1500	3.8		IMD5
	n79	4850	40	216	4850	N/A		N/A
DC_21A-28A_n77A	21	1452	5	25	1500	N/A		N/A
	28	730.5	5	25	785.5	16.9		IMD3
	n77	3689.5	10	50	3689.5	N/A		N/A
	21	1450.5	5	25	1498.5	9.9		IMD4
	28	730.5	5	25	785.5	N/A		N/A
	n77	3690	10	50	3690	N/A		N/A
DC_21A-28A_n79A	21	1450	5	25	1498	5.2		IMD5
	28	730.5	5	25	785.5	N/A		N/A
	n79	4420	40	216	4420	N/A		N/A
DC_28A-42A_79A	28	730	5	25	785	N/A		N/A

NR or E-UTRA Band / Channel bandwidth / NRB / MSD								
EN-DC Configuration	EUTRA/NR band	UL F <sub>c</sub> (MHz)	UL/DL BW (MHz)	UL L <sub>CRB</sub>	DL F <sub>c</sub> (MHz)	MSD (dB)	Duplex mode	IMD order
	42	3420	5	25	3420	15.3		IMD3
	n79	4880	40	216	4880	N/A		N/A
	28	745	5	25	800	16.2		IMD2
	42	3597.5	5	25	3597.5	N/A		N/A
	n79	4420	40	216	4420	N/A		N/A
DC_19A_n78A-n79A	19	835	5	25	880	N/A		N/A
	n78	3680	10	50	3680	N/A		N/A
	n79	4515	40	216	4515	29.3		IMD2
	19	835	5	25	880	N/A		N/A
	n79	4550	40	216	4550	N/A		N/A
DC_20A_n28A-n78A DC_20A_SUL_n78A-n83A	n78	3715	10	50	3715	28.8		IMD2
	20	857	5	25	816	N/A		N/A
	n28, n83	743	5	25	798	N/A		N/A
	n78	3314	10	50	3314	8.7		IMD4
	20	837	5	25	796	N/A		N/A
DC_21A_n78A-n79A	n78	3310	10	50	3310	N/A		N/A
	n28	744	5	25	799	9.4		IMD4
	21	1453	5	25	1501	N/A		N/A
	n78	3420	10	50	3420	N/A		N/A
	n79	4873	40	216	4873	30.1		IMD2
	21	1453	5	25	1501	N/A		N/A
	n79	4940	40	216	4940	N/A		N/A
	n78	3487	10	50	3487	29.8		IMD2

### 7.3B.2.0.3.5.3 MSD exceptions due to Tx leakage issue

**Table 7.3B.2.0.3.5.3-1: Void**

The normative reference for this requirement is TS 38.101-3 [4] subclause 7.3B.2.

## 7.3B.2.1 Reference sensitivity for Intra-band Contiguous EN-DC (2 CCs)

### 7.3B.2.1.1 Test purpose

To verify the ability of UE that support intra-band contiguous EN-DC configurations to receive data with a given average throughput for a specified reference measurement channel, under conditions of low signal level, ideal propagation and no added noise. A UE unable to meet the throughput requirement under these conditions will decrease the effective coverage area.

### 7.3B.2.1.2 Test applicability

This test applies to all types of NR UE release 15 and forward supporting intra-band EN-DC.

### 7.3B.2.1.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.3B.2.0.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

### 7.3B.2.1.4 Test description

#### 7.3B.2.1.4.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations for NR consist of environmental conditions test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in Table 5.3.5-1 of TS 38.521-1[8]. All of these configurations shall be tested with applicable test parameters for each channel bandwidth, and are shown in Table 7.3.2.4.1-1, Table 7.3.2.4.1-2, and Table 7.3.2.4.1-3 of TS 38.521-1[8]. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2 of TS 38.521-1[8]. Configurations of PDSCH and PDCCH before measurement are specified in Annex C.2 of TS 38.521-1[8].

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 5.4.2.1-1 of TS 36.521-1[10]. All of these configurations shall be tested with applicable test parameters for each channel bandwidth are shown in tables 7.3.4.1-1 and 7.3.4.1-2 of TS36.521-1[10]. The details of the downlink and uplink reference measurement channels (RMCs) are specified in Annexes A.2 and A.3 of TS36.521-1[10]. The details of the OCNG patterns used are specified in Annex A.5. Configurations of PDSCH and PDCCH before measurement are specified in Annex C.2 of TS36.521-1[10].

The channel bandwidths for E-UTRA and NR component carriers shall follow the values specified in Table 5.3B.1.2-1 for a given EN-DC combination.

**Table 7.3B.2.1.4.1-1: Test configurations table for intra-band DC\_(n)71AA**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [5] subclause 4.1				Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies as specified in TS 38.508-1 [5] subclause 4.3.1 E-UTRA Test Frequencies as specified in TS 36.508-1 [11] subclause 4.3.1				Low, mid and high range			
E-UTRA Test Channel Bandwidths as specified in TS 36.508 [11] subclause 4.3.1				5 MHz			
NR Test Channel Bandwidths as specified in TS 38.508-1 [5] subclause 4.3.1				5 MHz, 10 MHz, 15 MHz, 20 MHz			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]				Lowest supported SCS			
NR/E-UTRA Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	Specified in Table 7.3B.2.1.4.1-2	QPSK	Specified in Table 7.3B.2.1.4.1-2
Test Point configurations							
Test ID	E-UTRA/NR band	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	Channel BW (MHz)	UL allocation (LCRB)	F <sub>c</sub> (DL) (MHz) N <sub>DL</sub>	Duplex mode	
1	71	665.5MHz, N <sub>UL</sub> = 133147	5	5@19	619.5 MHz N <sub>DL</sub> = 68611	FDD	
	n71	675.5 N <sub>UL</sub> = 135100	15	15@0	629.5 N <sub>DL</sub> = 125900		
2	71	670.5 N <sub>UL</sub> = 133197	15	15@59	624.5 N <sub>DL</sub> = 68661		
	n71	680.5 N <sub>UL</sub> = 136100	5	5@0	634.5 N <sub>DL</sub> = 126900		
3	71	668 N <sub>UL</sub> = 133172	10	10@39	622 N <sub>DL</sub> = 68636		
	n71	678 N <sub>UL</sub> = 135600	10	10@0	632 N <sub>DL</sub> = 126400		
4	71	668 N <sub>UL</sub> = 133172	10	10@39	622 N <sub>DL</sub> = 68636		
	n71	678 N <sub>UL</sub> = 135600	10	10@41 (for CP ??)	632 N <sub>DL</sub> = 126400		
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							
NOTE 2: Test Channel Bandwidths are checked separately for each E-UTRA band, which applicable channel bandwidths are specified in Table 5.3B.1.2-1.							

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [5] subclause 4.4.3.
3. The parameter settings for E-URA cell are set up according to TS 36.508 [11] subclause 4.4.3.
4. NR downlink signals are initially set up according to Annex C.0, C.1, C.2, C.3.1, and uplink signals according to Annex G.0, G.1, G.2, and G.3.1 of TS38.521-1 [8].
5. E-UTRA downlink signals are initially set up according to Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS36.521-1[10].



6. The UL Reference Measurement channels for NR are set according to Table 7.3.2.4.1-1, Table 7.3.2.4.1-2, and Table 7.3.2.4.1-3 of TS38.521-1[8].
7. The UL Reference Measurement channels for E-UTRA are set according to Tables 7.3.4.1-1 and 7.3.4.1-2 of TS36.521-1[10].
8. NR propagation conditions are set according to Annex B.0 of TS38.521-1[8].
9. E-UTRA propagation conditions are set according to B.0 of TS36.521-1[10].
10. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters *Connectivity* EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.3B.2.1.4.3.
11. The UL Reference Measurement channels configurations for exceptional cases are set according to Table 7.3B.2.1.4.1-1.

#### 7.3B.2.1.4.2 Test procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 7.3B.2.3.4.1-1 on both EN-DC component carriers. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for C\_RNTI to schedule the UL RMC according to Table 6.6.3.1.4.1-1 of TS36.521-1[10]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level to the appropriate REFSSENS value defined in TS 38.521-1 [TBD], Table 7.3.3-1 for NR band and TS 36.521-1[10] Table 7.3.3-1 for E-UTRA band. Send continuously uplink power control "up" commands in the uplink scheduling information to both carriers to ensure the UE transmits PUMAX level for at least the duration of the Throughput measurement.
4. Measure the average throughput of both NR and E-UTRA for a duration sufficient to achieve statistical significance according to Annex H.2 of TS 38.521-1[8] for NR band, and Annex G.2 of TS36.521-1[10] for EUTRA band.

#### 7.3B.2.1.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6 for NR band. Message contents are according to TS 36.508 [7] subclause 4.6 for EUTRA band.

#### 7.3B.2.1.5 Test requirement

For intra-band contiguous EN-DC configurations, The throughput of each CG shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with reference receive power level specified in Tables 7.3.2.5-1 and parameters specified Tables 7.3.2.4.1-1, Tables 7.3.2.4.1-2 and Tables 7.3.2.4.1-3 of TS 38.521-1 for NR band, and reference measurement channels as specified in Annex A.3.2 of TS 36.521-1 [10] with parameters specified in Tables 7.3.5-1 and Table 7.3.5-2 of TS 36.521-1 [10] for E-UTRA band.

The maximum allowed degradation MSD of the reference sensitivity level, as specified for the applicable carrier bandwidths in accordance with [5] for the E-UTRA CG and [2] for the NR CG, is specified in Table 7.3B.2.1.5-1.

Table 7.3B.2.1.5-1: Reference sensitivity for intra-band DC\_(n)71AA

EN-DC	E-UTRA/ NR band	SCS (kHz)	Channel BW (MHz)	Ref sensitivity (dBm)	Note	Duplex mode
DC_(n)71AA	71	N/A	5	-97.2		FDD
	n71	15	5	-97.2 +TT		
	71	N/A	5	-97.2		
	n71	15	10	-94.0 +TT		
	B1	N/A	5	-97.2		
	n71	15	15	-91.6 +TT		
	71	N/A	5	-97.2		
	n71	15	20	-86.0 +TT		
	71	N/A	5	-96.5	Note 1	
	n71	15	15	-89.8 +TT		
	71	N/A	15	-91.3	Note 2	
	n71	15	5	-95.6 +TT		
	71	N/A	10	-93.5	Note 3	
	n71	15	10	-92.3 +TT		
	71	N/A	10	-76.3	Note 4	
n71	15	10	-64.6 +TT			
NOTE 1: For test configuration specified by Table 7.3B.2.1.4.1-2 Test ID 1						
NOTE 2: For test configuration specified by Table 7.3B.2.1.4.1-2 Test ID 2						
NOTE 3: For test configuration specified by Table 7.3B.2.1.4.1-2 Test ID 3						
NOTE 4: For test configuration specified by Table 7.3B.2.1.4.1-2 Test ID 4						

Table 7.3B.2.1.5-2: Test Tolerance (TT) for NR RX sensitivity level

$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 6.0\text{GHz}$
0.7 dB	1.0 dB

## 7.3B.2.2 Reference sensitivity for Intra-band non-contiguous EN-DC (2 CCs)

### 7.3B.2.2.1 Test purpose

Same as in clause 7.3B.2.1.1.

### 7.3B.2.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 7.3B.2.2.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.3B.2.0

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.3B.2.2.4 Test Description

#### 7.3B.2.2.4.1 Initial Condition

Initial conditions are a set of **test configurations the UE needs to be tested in and the steps for the SS** to take with the UE to reach the correct measurement state.

The initial test configurations for E-UTRA consist of the test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1, with the exception that the E-UTRA channel bandwidth is the lowest supported value in Table 5.3B.1.3-1 for the EN-DC non-contiguous configuration under test.

The initial test configurations consist of environmental conditions, test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in table 5.2B.2.1-1. All of these configurations shall be tested with applicable test parameters for each combination of test channel bandwidth and sub-carrier spacing are shown in Table 7.3B.2.2.4.1-1 for NR band. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 38.521-1 Annex C2.

**Table 7.3B.2.2.4.1-1: Test Configuration Table**

Initial Conditions				
Test Environment as specified in TS 38.508-1 [5] subclause 4.1		Normal, TL/VL, TL/VH, TH/VL, TH/VH		
Test Frequencies as specified in TS 38.508-1 [5] subclause 4.3.1		Low range, High range		
Test Channel Bandwidths as specified in TS 38.508-1 [5] subclause 4.3.1		Lowest, Highest (NOTE 4)		
Test SCS as specified in Table 5.3.5-1		Lowest supported SCS per test channel BW		
Test Parameters				
Test ID	Downlink Configuration		Uplink Configuration	
	Modulation	RB allocation	Modulation	RB allocation
1	CP-OFDM QPSK	Full RB (NOTE 1)	DFT-s-OFDM QPSK	REFSENS (NOTE 2)
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2.				
NOTE 2: REFSENS refers to Table 7.3.2.4.1-3 which defines uplink RB configuration and start RB location for each SCS, channel BW and NR band.				
NOTE 3: Test Channel Bandwidths are checked separately for each NR band, which applicable channel bandwidths are specified in Table 5.3.5-1 of 38.521-1 [8]				
NOTE 4: Lowest and highest allowed NR channel BW as specified in Table 5.3B.1.3-1				

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. E-UTRA downlink signal level, and uplink signal level are set according to Table 4.6-1.
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. The NR UL Reference Measurement channels for NR are set according to Table 7.3B.2.2.4.1-1.
6. Set up the NR and E-UTRA test frequencies so that NR carrier is located at the lower frequency side as specified in Table 5.3B.1.3-1. Repeat each testing with E-UTRA carrier frequency is located at the lower side as specified in Table 5.3B.1.3-1. 7
7. NR propagation conditions are set according to Annex B.0 of TS38.521-1[8]. E-UTRA propagation conditions are set according to B.0 of TS36.521-1[10].
8. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.3B.2.2.4.3.
9. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.3B.2.2.4.2 Test Procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 7.3B.2.2.4.1-1 Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Set the Downlink signal level to the appropriate REFSENS value defined in TS 38.521-1 [8], Table 7.3.3-1 for NR band and TS 36.521-1[10] Table 7.3.3-1 for E-UTRA band. Send continuously uplink power control "up"

commands in the uplink scheduling information to both carriers to ensure the UE transmits PUMAX level for at least the duration of the Throughput measurement.

3. Measure the average throughput on the NR carrier for a duration sufficient to achieve statistical significance according to Annex H.2 of TS 38.521-1[8] for NR band.

#### 7.3B.2.2.4.3 Message Contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 7.3B.2.2.5 Test Requirement

For intra-band non-contiguous EN-DC configurations, the measured throughput on the NR carrier shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A with reference receive power level specified in Table 7.3B.2.2.5-1, and parameters specified Tables 7.3.2.4.1-1, Tables 7.3.2.4.1-2 and Tables 7.3.2.4.1-3 of TS 38.521-1[8] for NR band.

**Table 7.3B.2.2.5-1: Reference sensitivity for intra-band Non-contiguous EN-DC**

EN-DC	E-UTRA/ NR band	SCS (kHz)	Channel BW (MHz)	Ref sensitivity (dBm)	Duplex mode
DC_3A_n3A	3	N/A	5	-96.3	FDD
	n3	15	5	-97.0 +TT	
	3	N/A	5	-96.3	
	n3	15	10	-93.8 +TT	
	3	N/A	5	-96.3	
	n3	15	15	-92.0 +TT	
	3	N/A	5	-96.3	
	n3	15	20	-90.8 +TT	
	3	N/A	5	-96.3	
	n3	15	25	-89.7 +TT	
DC_41A_n41A	3	N/A	5	-96.3	TDD
	n3	15	30	-88.9 +TT	
	41	N/A	20	-92.0	
	n41	15	40	-88.6 +TT	
	41	N/A	20	-92.0	
	n41	15	50	-87.6 +TT	
	41	N/A	20	-92.0	
	n41	30	60	-86.9 +TT	
	41	N/A	20	-92.0	
	n41	30	80	-85.6 +TT	
41	N/A	20	-92.0	TDD	
n41	30	100	-84.7 +TT		

Note: NR band Test tolerance (TT) is specified in Table 7.3B.2.2.5-2

**Table 7.3B.2.2.5-2: Test Tolerance (TT) for NR RX sensitivity level**

$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 6.0\text{GHz}$
0.7 dB	1.0 dB

#### 7.3B.2.3 Reference sensitivity for Inter-band EN-DC within FR1(2 CCs)

**Editor's Note:** This clause is incomplete. The following aspects are either missing or not yet determined:

- Reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1 is partially completed.

- Reference sensitivity test requirement exceptions due to receiver harmonic mixing for EN-DC in NR FR1 Reference sensitivity is partially completed.
- Reference sensitivity exceptions due to close proximity of bands for EN-DC in NR FR1 is FFS.- Reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1 is FFS.
- Test requirement and configuration tables for EN-DC configurations without exception requirements in 38.101-3 are complete.

#### 7.3B.2.3.1 Test purpose

Same as in clause 7.3B.2.1.1.

#### 7.3B.2.3.2 Test applicability

This test applies to all types of NR UE release 15 and forward supporting inter-band EN-DC.

#### 7.3B.2.3.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.3B.2.0.

For EN-DC with no exception requirements applicable to NR or LTE, LTE anchor agnostic approach is applied.

For EN-DC combination with exceptional requirements, LTE anchor agnostic approach is not applied.

#### 7.3B.2.3.4 Test description

##### 7.3B.2.3.4.1 Test description for Inter-band EN-DC without exceptions

##### 7.3B.2.3.4.1.1 Initial conditions

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations for E-UTRA consist of the test frequency based on E-UTRA operating band and test channel bandwidth as specified in clause 4.6. The details of the downlink and uplink reference measurement channels (RMCs) are specified in Annexes A.2 and A.3 of TS 36.521-1[10]. The details of the OCNG patterns used are specified in Annex A.5. Configurations of PDSCH and PDCCH before measurement are specified in Annex C.2 of TS 36.521-1[10].

For each supported inter-band EN-DC combination specified in subclause 5.2B.4.1, the initial test configurations for NR carrier consist of environmental conditions test frequencies, test channel bandwidths and sub-carrier spacing based on NR operating bands specified in Table 5.3.5-1 of TS 38.521-1[8]. All of these configurations shall be tested with applicable test parameters for each channel bandwidth, and are shown in Table 7.3.2.4.1-1, Table 7.3.2.4.1-2, and Table 7.3.2.4.1-3 of TS 38.521-1[8]. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2.2 of TS 38.521-1[8]. Configurations of PDSCH and PDCCH before measurement are specified in Annex C.2 of TS 38.521-1[8].

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram.
2. The parameter settings for NR cell are set up according to TS 38.508-1 [5] subclause 4.4.3.
3. NR downlink signals are initially set up according to Annex C.0, C.1, C.2, C.3.1, and uplink signals according to Annex G.0, G.1, G.2, and G.3.1 of TS38.521-1 [8].
4. NR downlink signals are initially set up according to Annex C.0, C.1, and C.2 and uplink signals according to Annex G.0, G.1, G.2, and G.3.0 of TS38.521-1[8].
5. The UL Reference Measurement channels for NR are set according to Table 7.3.2.4.1-1, Table 7.3.2.4.1-2, and Table 7.3.2.4.1-3 of TS38.521-1[8].
6. NR propagation conditions are set according to Annex B.0. E-UTRA propagation conditions are set according to Annex B.0 of TS 36.521-1 [10]
7. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* are set according to TS 38.508-1[6] clause 4.5. Message contents are defined in clause 7.3B.2.3.4.1.3.
8. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.3B.2.3.4.1.2 Test procedure

1. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format [0\_1] for C\_RNTI to schedule the UL RMC according to Table 7.3.2.4.1-1, Table 7.3.2.4.1-2, and Table 7.3.2.4.1-3 of TS38.521-1[8]. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level to the appropriate REFSENS value defined in TS 38.521-1 [8], Table 7.3.3-1 for NR band and TS 36.521-1[10] and Table 7.3.3-1 for E-UTRA band. Send continuously uplink power control "up" commands in the uplink scheduling information to both carriers to ensure the UE transmits PUMAX level for at least the duration of the Throughput measurement.
4. Measure the average throughput of NR carrier for a duration sufficient to achieve statistical significance according to Annex H.2 of TS 38.521-1[8] for NR band, and Annex G.2 of TS 36.521-1[10] for EUTRA band

#### 7.3B.2.3.4.1.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 7.3B.2.3.4.2 Test description for Inter-band EN-DC with exception requirement

##### 7.3B.2.3.4.2.1 Initial conditions

Same initial conditions with following exceptions:

1. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
2. E-UTRA downlink signals are initially set up according to Annex C0, C.1 and C.3.0, and uplink signals according to Annex H.1 and H.3.0 of TS 36.521-1 [10].
3. The initial test configurations for E-UTRA band and NR band consist of environmental conditions, test frequencies, and channel bandwidths and RB allocations for exceptional test scenarios are specified in Table 7.3B.2.3.4.2.1-2a to Table 7.3B.2.3.4.2.1-6.

**Table 7.3B.2.3.4.2.1-1: Initial test conditions for reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1 E-UTRA Test Frequencies as specified in TS 38.508-1 [11] subclause 4.3.1				Mid range for E-UTRA and NR, unless otherwise specified in Table 7.3B.2.3.4.2.1-2a to Table 7.3B.2.3.4.2.1-2t			
NR Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1 E-UTRA Test Channel Bandwidths as specified in TS 36.508 [11] subclause 4.3.1				Highest NRB_agg, unless otherwise specified in Table 7.3B.2.3.4.2.1-2a to Table 7.3B.2.3.4.2.1-2t			
NR Test SCS as specified in Table 5.3.5-1				Lowest supported SCS otherwise specified			
Test Parameters							
Downlink Configuration				Uplink Configuration			
E-UTRA Cell		NR Cell		E-UTRA Cell		NR Cell	
Modulation	RB allocation	Modulation	RB allocation	Modulation	RB allocation	Modulation	RB allocation
QPSK	Full RB	CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	Full RB (NOTE 1)
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							

**Table 7.3B.2.3.4.2.1-2a: Test configurations table for exceptions due to UL harmonic interference for EN-DC 1\_n77**

Test ID	E-UTRA Band 1		NR Band 77		
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1925MHz/18050	3850MHz/656666	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	100@0
2		1950 MHz/18300	3900 MHz/660000	5	12@0
				10	25@0
				15	36@0
				20	50@0
3		1975 MHz/18550	3950 MHz/663333	40	100@0
	5			12@0	
	10			25@0	
	15			36@0	
3	1975 MHz/18550	3950 MHz/663333	20	50@0	
			40	100@0	
Note: Test frequencies are selected to fulfil Note 1 and Note 2 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2b: Test configurations table for exceptions due to UL harmonic interference for EN-DC 1\_n77 (For Note 3 in Table 7.3B.2.0.3.1-1)**

E-UTRA Band 1			NR Band 77		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1925MHz/ 18050	3820 MHz/ 654666	5	12@0
				10	25@0
				15	36@0
				20	50@0
2		1950 MHz/ 18300	3870 MHz/ 658000	5	12@0
				10	25@0
				15	36@0
				20	50@0
3		1975 MHz/18550	3920 MHz/ 651333	5	12@0
				10	25@0
				15	36@0
				20	50@0
Note: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.1-1					

**Table 7.3B.2.3.4.2.1-2c: Test configurations table for exceptions due to UL harmonic interference for EN-DC 3\_n77**

E-UTRA Band 3			NR Band 77		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 19250	3430 MHz/ 628666	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
2		1747.5 MHz/ 19575	3495 MHz/ 633000	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
3		1780 MHz/ 19900	3560 MHz/ 637333	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
Note: Test frequencies are selected to fulfil Note 1 and Note 2 in Table 7.3B.2.0.3.1-1.					



**Table 7.3B.2.3.4.2.1-2d: Test configurations table for exceptions due to UL harmonic interference for EN-DC 3\_n77 (For Note 3 in Table 7.3B.2.0.3.1-1)**

Test ID	E-UTRA Band 3			NR Band 77	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 19250	3400 MHz/ 626666	5	12@0
				10	25@0
				15	36@0
				20	50@0
2		1747.5 MHz/ 19575	3465 MHz/ 631000	5	12@0
				10	25@0
				15	36@0
				20	50@0
3		1780 MHz/ 19900	3590 MHz/ 639333	5	12@0
				10	25@0
				15	36@0
				20	50@0
Note: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2e: Test configurations table for exceptions due to UL harmonic interference for EN-DC 2\_n78**

Test ID	E-UTRA Band 2			NR Band 78	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1855MHz/ 18650	3710 MHz/ 647333	5	12@0
				10	26@0
				15	39@0
				20	53@0
				40	100@0
2		1880 MHz/ 18900	3760 MHz/ 650666	5	12@0
				10	26@0
				15	39@0
				20	53@0
				40	100@0
3		1890 MHz/ 19000	3780 MHz/ 652000	5	12@0
				10	26@0
				15	39@0
				20	53@0
				40	100@0
Note: Test frequencies are selected to fulfil Note 1 and Note 2 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2f: Test configurations table for exceptions due to UL harmonic interference for EN-DC 2\_n78 (for Note 3 in Table 7.3B.2.0.3.1-1)**

Test ID	E-UTRA Band 2			NR Band 78	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1855MHz/ 18650	3680 MHz/ 645333	5	12@0
				10	26@0
				15	39@0
				20	53@0
2		1880 MHz/ 18900	3730 MHz/ 648666	5	12@0
				10	26@0
				15	39@0
				20	53@0
3		1880 MHz/ 18900	3790 MHz/ 652666	5	12@0
				10	26@0
				15	39@0
				20	53@0
Note: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2g: Test configurations table for exceptions due to UL harmonic interference for EN-DC 3\_n78 (Test frequencies are selected to fulfil Requirement for Note 1 and 2 in Table 7.3B.2.0.3.1-1)**

Test ID	E-UTRA Band 3			NR Band 78	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 19250	3430 MHz/ 628666	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
2		1747.5 MHz/ 19575	3495 MHz/ 633000	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
3		1780 MHz/ 19900	3560 MHz/ 637333	5	12@0
				10	25@0
				15	36@0
				20	50@0
				40	50@0
Note: Test frequencies are selected to fulfil Note 1 and 2 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2h: Test configurations table for exceptions due to UL harmonic interference for EN-DC 3\_n78 (Test frequencies are selected to fulfil Requirement for Note 3 in Table 7.3B.2.0.3.1-1)**

Test ID	E-UTRA Band 3			NR Band 78	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 19250	3400 MHz/ 626666	5	12@0
				10	25@0
				15	36@0
				20	50@0
2		1747.5 MHz/ 19575	3465 MHz/ 631000	5	12@0
				10	25@0
				15	36@0
				20	50@0
3		1780 MHz/ 19900	3590 MHz/ 639333	5	12@0
				10	25@0
				15	36@0
				20	50@0
Note: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2i: Test configurations table for exceptions due to UL harmonic interference for EN-DC 8\_n77 (Test frequencies are selected to fulfil Requirement of Note 6 and 7 in Table 7.3B.2.0.3.1-1)**

Test ID	E-UTRA Band 8			NR Band 77	
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	5	882.5 MHz/ 21475	3530 MHz/ 635333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
2		897.5 MHz/ 21625	3590 MHz/ 639333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
3		912.5 MHz/ 21775	3650 MHz/ 643333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
Note: Test frequencies are selected to fulfil Note 6 and 7 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2j: Test configurations table for exceptions due to UL harmonic interference for EN-DC 8\_n78 (Requirement of Note 6 and 7)**

E-UTRA Band 8			NR Band 78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	5	882.5 MHz/ 21475	3530 MHz/ 635333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
2		897.5 MHz/ 21625	3590 MHz/ 639333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
3		912.5 MHz/ 21775	3650 MHz/ 643333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
Note: Test frequencies are selected to fulfil Note 6 and 7 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2k: Test configurations table for exceptions due to UL harmonic interference for EN-DC 8\_n79 (Requirement of Note 4 and 5)**

E-UTRA Band 8			NR Band 79		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	5	882.5 MHz/ 21475	4412.5 MHz/ 694166	40	25@0
				50	25@0
				60	25@0
				80	25@0
				100	25@0
2		897.5 MHz/ 21625	4487.5 MHz/ 699166	40	25@0
				50	25@0
				60	25@0
				80	25@0
				100	25@0
3		912.5 MHz/ 21775	4652.5 MHz/ 704166	40	25@0
				50	25@0
				60	25@0
				80	25@0
				100	25@0
Note: Test frequencies are selected to fulfil Note 4 and 5 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2l: Test configurations table for exceptions due to UL harmonic interference for EN-DC 18\_n77 (Requirement of Note 4)**

E-UTRA Band 18			NR Band 77		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	820 MHz/ 23900	4100 MHz/ 673333	10	16@0
				15	25@0
				20	25@0
				40	25@0
2		822.5 MHz/ 23925	4112.5 MHz/ 674166	10	16@0
				15	25@0
				20	25@0
				40	25@0
3		825 MHz/ 23950	4125 MHz/ 675000	10	16@0
				15	25@0
				20	25@0
				40	25@0

Note: Test frequencies are selected to fulfil Note 4 in Table 7.3B.2.0.3.1-1.

**Table 7.3B.2.3.4.2.1-2m: Test configurations table for exceptions due to UL harmonic interference for EN-DC 19\_n77 (Requirement of Note 4 and 5)**

E-UTRA Band 19			NR Band 77		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	835 MHz/ 24050	4175 MHz/ 678333	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
				100	25@0
2		837.5 MHz/ 24075	4187.5 MHz/ 679166	10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
				100	25@0

Note: Test frequencies are selected to fulfil Note 4 and 5 in Table 7.3B.2.0.3.1-1.

**Table 7.3B.2.3.4.2.1-2n: Test configurations table for exceptions due to UL harmonic interference for EN-DC 28\_n77/n78 (Requirement of Note 4 and 5)**

E-UTRA Band 28			NR Band 77/78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	708 MHz/ 27260	3540 MHz/ 636000	10	10@0
				15	15@0
				20	20@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
				90	25@0
2		723 MHz/ 27410	3615 MHz/ 641000	100	25@0
				10	10@0
				15	15@0
				20	20@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
3		743 MHz/ 27610	3715 MHz/ 647666	90	25@0
				100	25@0
				10	10@0
				15	15@0
				20	20@0
				40	25@0
				50	25@0
				60	25@0
Note: Test frequencies are selected to fulfil Note 4 and 5 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2o: Test configurations table for exceptions due to UL harmonic interference for EN-DC 20\_n77/78 (Requirement of Note 6 and 7)**

E-UTRA Band 20			NR Band 77/78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	837 MHz/ 24200	3348 MHz/ 623300	5	8@0
				10	16@0
				15	25@0
				20	25@0
				40	25@0
2		847 MHz/ 24300	3388 MHz/ 625866	5	8@0
				10	16@0
				15	25@0
				20	25@0
				40	25@0
3		857 MHz/ 24400	3428 MHz/ 628533	5	8@0
				10	16@0
				15	25@0
				20	25@0
Note: Test frequencies are selected to fulfil Note 6 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2p: Test configurations table for exceptions due to UL harmonic interference for EN-DC 26\_n41 (Requirement of Note 8)**

E-UTRA Band 26			NR Band 41		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	835 MHz/ 26900	2505 MHz/ 501000	10	25@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
2	10	844 MHz/ 26990	2532 MHz/ 506400	90	25@0
				10	25@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
80	25@0				
				90	25@0

Note: Test frequencies are selected to fulfil Note 8 in Table 7.3B.2.0.3.1-1.

**Table 7.3B.2.3.4.2.1-2q: Test configurations table for exceptions due to UL harmonic interference for EN-DC 26\_n77/78 (Requirement of Note 6 and 7)**

E-UTRA Band 20			NR Band 77/78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	831.5 MHz/ 26865	3276 MHz/ 621733	5	8@0
				10	16@0
				15	25@0
				20	25@0
2	10	844 MHz/ 226990	3376 MHz/ 625066	40	25@0
				5	8@0
				10	16@0
				15	25@0
				20	25@0
				40	25@0

Note: Test frequencies are selected to fulfil Note 6 and 7 in Table 7.3B.2.0.3.1-1.

**Table 7.3B.2.3.4.2.1-2r: Test configurations table for exceptions due to UL harmonic interference for EN-DC 26\_n77 (Requirement of Note 4)**

E-UTRA Band 26			NR Band 77		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	819 MHz/ 26740	4095 MHz/ 673000	5	8@0
				10	16@0
				15	25@0
				20	25@0
				40	25@0
				50	25@0
				60	25@0
				80	25@0
2	10	831.5 MHz/ 26865	4158 MHz/ 677200	100	25@0
				5	8@0
				10	16@0
				15	25@0
				20	25@0
				40	25@0
				60	25@0
				80	25@0
Note: Test frequencies are selected to fulfil Note 4 in Table 7.3B.2.0.3.1-1.					

**Table 7.3B.2.3.4.2.1-2s: Test configurations table for exceptions due to UL harmonic interference for EN-DC 66\_n78 (Requirement of Note 1 and 2)**

E-UTRA Band 66			NR Band 78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 132022	3430 MHz/ 628666	10	26@0
				15	39@0
				20	53@0
				40	100@0
2	10	1755 MHz/ 132422	3510 MHz/ 634000	10	26@0
				15	39@0
				20	53@0
				40	100@0
3	10	1775 MHz/ 132622	3550 MHz/ 636666	10	26@0
				15	39@0
				20	53@0
				40	100@0
Note: Test frequencies are selected to fulfil Note 1 and 2 in Table 7.3B.2.0.3.1-1.					



**Table 7.3B.2.3.4.2.1-2t: Test configurations table for exceptions due to UL harmonic interference for EN-DC 66\_n78 (Requirement of Note 3)**

E-UTRA Band 66			NR Band 78		
Test ID	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	NR CBW	UL allocation (LCRB)
1	10	1715 MHz/ 132022	3390 MHz/ 626000 3470 MHz/ 631333	10	26@0
				15	39@0
				20	53@0
				40	100@0
2		1755 MHz/ 132422	3470 MHz/ 631333 3550 MHz/ 636666	10	26@0
				15	39@0
				20	53@0
				40	100@0
3		1775 MHz/ 132622	3510 MHz/ 634000 3590 MHz/ 639333	10	26@0
				15	39@0
				20	53@0
				40	100@0

Note: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.1-1.

**Table 7.3B.2.3.4.2.1-3a: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC 2\_n71**

E-UTRA Band 2			NR Band 71		
Test ID	Channel BW (MHz)/ RB allocation	F <sub>c</sub> (UL)	NR F <sub>c</sub> (UL)	NR Ch BW	UL allocation (LCRB)
1	5 25@0	Low, Mid, High	Low, Mid	5	25@0
				10	50@0
				15	75@0
				20	100@0
2	10 50@0	Low, Mid, High	Low, Mid	5	25@0
				10	50@0
				15	75@0
				20	100@0
3	15 50@0	Low, Mid, High	Low, Mid	5	25@0
				10	50@0
				15	75@0
				20	100@0
34	20 50@	Low, Mid, High	Low, Mid	5	25@0
				10	50@0
				15	75@0
				20	100@0

Note: Test frequencies are selected to fulfil Note 4 in Table 7.3B.2.0.3.2-1.

**Table 7.3B.2.3.4.2.1-3b: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n41\_26**

Test ID	NR Band n41		E-UTRA Band 46		
	Channel BW (MHz) / RB allocation	NR Fc (UL)	Fc (UL)	E-UTRA Ch BW	UL allocation (LCRB)
1	5 MHz/ 15@0	Mid	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
2	10 MHz 25@0	Mid	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
3	15 MHz 25@0	Mid	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
4	20 MHz 25@0	Mid	Low, Mid, High	5	25@0
				10	50@0
				15	75@0

Note: Test frequencies are selected to fulfil Note 4 in Table 7.3B.2.0.3.2-1.

**Table 7.3B.2.3.4.2.1-3c: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC 41\_n77**

Test ID	E-UTRA Band 41			NR Band n77		
	Channel BW (MHz)/ RB allocation	Fc (UL)	NR Fc (UL)	NR Ch BW	SCS (kHz)	UL allocation (LCRB)
1	5/ 25@0	Low, Mid, High	Mid, High	10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
				60	30	162@0
				80	30	216@0
2	10/ 25@0	Low, Mid, High	Mid, High	90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
				60	30	162@0
3	15/ 25@0	Low, Mid, High	Mid, High	80	30	216@0
				90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
4	20/ 25@0	Low, Mid, High	Mid, High	60	30	162@0
				80	30	216@0
				90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0

Note: Test frequencies are selected to fulfil Note 7 in Table 7.3B.2.0.3.2-1.

**Table 7.3B.2.3.4.2.1-3d: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC 41\_n78**

Test ID	E-UTRA Band 41		NR Band n78			
	Channel BW (MHz)/ RB allocation	F <sub>c</sub> (UL)	NR F <sub>c</sub> (UL)	NR Ch BW	SCS (kHz)	UL allocation (LCRB)
1	5/ 25@0	Low	High	10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
				60	30	162@0
				80	30	216@0
2	10/ 25@0	Low	High	90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
				60	30	162@0
3	15/ 25@0	Low	High	80	30	216@0
				90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0
				50	15	270@0
4	20/ 25@0	Low	High	60	30	162@0
				80	30	216@0
				90	30	243@0
				10	15	50@0
				15	15	75@0
				20	15	100@0
				40	15	216@0

Note: Test frequencies are selected to fulfil Note 7 in Table 7.3B.2.0.3.2-1.

**Table 7.3B.2.3.4.2.1-3e: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n71\_n2**

FFS

**Table 7.3B.2.3.4.2.1-3f: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n77\_41**

FFS –

**Table 7.3B.2.3.4.2.1-3g: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n77\_28**

Test ID	NR Band n77		E-UTRA Band 28		
	Channel BW (MHz)	NR F <sub>c</sub> (UL)	F <sub>c</sub> (UL)	E-UTRA Ch BW	UL allocation (LCRB)
1	10 MHz	Mid, High	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
				20	100@
2	15 MHz	Mid, High	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
				20	100@
3	20 MHz	Mid, High	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
				20	100@
Note: Test frequencies are selected to fulfil Note 2 in Table 7.3B.2.0.3.2-1.					

**Table 7.3B.2.3.4.2.1-3h: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n78\_41**

FFS –

**Table 7.3B.2.3.4.2.1-3i: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n79\_19**

Test ID	NR Band n79		E-UTRA Band 19		
	Channel BW (MHz)	NR F <sub>c</sub> (UL)	F <sub>c</sub> (UL)	E-UTRA Ch BW	UL allocation (LCRB)
1	40 MHz	Low	High	5	25@0
				10	50@0
				15	75@0
2	50 MHz	Low	High	5	25@0
				10	50@0
				15	75@0
Note: Test frequencies are selected to fulfil Note 2 in Table 7.3B.2.0.3.2-1.					

**Table 7.3B.2.3.4.2.1-3j: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n79\_21**

Test ID	NR Band n79		E-UTRA Band 19		
	Channel BW (MHz)	NR F <sub>c</sub> (UL)	F <sub>c</sub> (UL)	E-UTRA Ch BW	UL allocation (LCRB)
1	40 MHz	Low <sup>2</sup>	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
2	50 MHz	Low <sup>2</sup>	Low, Mid, High	5	25@0
				10	50@0
				15	75@0
Note 1: Test frequencies are selected to fulfil Note 3 in Table 7.3B.2.0.3.2-1.					
Note 2: Test point f <sub>UL/DL</sub> = 4510.2 MHz (N <sub>DL</sub> = 700680).					

**Table 7.3B.2.3.4.2.1-3k: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC n79\_26**

Test ID	NR Band n79		E-UTRA Band 26		
	Channel BW (MHz)	NR F <sub>c</sub> (UL)	F <sub>c</sub> (UL)	E-UTRA Ch BW	UL allocation (LCRB)
1	40 MHz	Low	High	5	25@0
				10	50@0
				15	75@0
2	50 MHz	Low	High	5	25@0
				10	50@0
				15	75@0

Note: Test frequencies are selected to fulfil Note 2 in Table 7.3B.2.0.3.2-1.

**Table 7.3B.2.3.4.2.1-3l: Test configurations table for exceptions due to receiver harmonic mixing for EN-DC 3\_n78**

Test ID	E-UTRA Band 3			NR Band 78		
	Channel BW (MHz)	F <sub>c</sub> (UL) (MHz) N <sub>UL</sub>	UL allocation (LCRB)	NR F <sub>c</sub> (DL) (MHz) N <sub>DL</sub>	NR CBW (MHz)	UL allocation (LCRB)
1	10	1715 MHz/ 19250	25@12	3430 MHz/ 628666	Lowest Mid Highest	REFSENS (NOTE 2)
2		1747.5 MHz/ 19575	25@12	3495 MHz/ 633000	Lowest Mid Highest	REFSENS (NOTE 2)
3		1780 MHz/ 19900	25@12	3560 MHz/ 637333	Lowest Mid Highest	REFSENS (NOTE 2)

NOTE 1: Test frequencies are selected to fulfil Note 2 and 13 in Table 7.3B.2.0.3.1-1.  
 NOTE 2: REFSENS refers to Table 7.3.2.4.1-3 in TS 38.521-1 [8] which defines uplink RB configuration and start RB location for each SCS, channel BW and NR band.

**Table 7.3B.2.3.4.2.1-4: Test configurations table for exceptions due to close proximity of bands for EN-DC**

FFS

**Table 7.3B.2.3.4.2.1-5: Test configurations table for exceptions due to cross band isolation for EN-DC FR1**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal, TL/VL, TL/VH, TH/VL, TH/VH			
NR Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1 E-UTRA Test Frequencies as specified in TS 36.508 [11] subclause 4.3.1				Mid ????			
NR Test Channel Bandwidths as specified in TS 38.508-1 [6] subclause 4.3.1 E-UTRA Test Channel Bandwidths as specified in TS 36.508 [11] subclause 4.3.1				Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$			
NR Test SCS as specified in Table 5.3.5-1				Lowest supported SCS per test channel BW unless specified			
NR Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	Table 7.3B.2.3.5.4-2	QPSK	Table 7.3B.2.3.5.4-2
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							

**Table 7.3B.2.3.4.2.1-5a: Test configurations table for exceptions due to cross band isolation for EN-DC 25\_n41**

FFS

**Table 7.3B.2.3.4.2.1-5b: Test configurations table for exceptions due to cross band isolation for EN-DC 41\_n77**

FFS

**Table 7.3B.2.3.4.2.1-5c: Test configurations table for exceptions due to cross band isolation for EN-DC 41\_n78**

FFS

**Table 7.3B.2.3.4.2.1-5d: Test configurations table for exceptions due to cross band isolation for EN-DC 3\_n41**

FFS

**Table 7.3B.2.3.4.2.1-5e: Test configurations table for exceptions due to cross band isolation for EN-DC n41\_3**

FFS

**Table 7.3B.2.3.4.2.1-6: Test Configuration Table Reference sensitivity exceptions due to dual uplink operation for EN-DC in NR FR1 (two bands)**

Initial Conditions												
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					NC, TL/VL, TL/VH, TH/VL, TH/VH							
NR Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1, E-UTRA Test Frequencies as specified in TS 36.508 [11] subclause 4.3.1					For test frequencies refer to "Range" columns.							
Test DC Combination setting (N <sub>RB_agg</sub> ) as specified in subclause [TBD] for the DC Configuration across bandwidth combination sets supported by the UE.					Refer to "NR N <sub>RB</sub> " and "E-UTRA N <sub>RB</sub> " columns							
Network signalling value					NS_01 Unless given by Table 7.3.3-3 for the band with active uplink carrier							
Test Parameters for DC Configurations												
ID	DC Configuration / N <sub>RB_agg</sub>					DL Allocation			UL Allocation (Note 2,3)			
	DC Configuration				E-UTRA Ch BW/N <sub>RB</sub>	NR Ch BW/N <sub>RB</sub>	CC MOD E-UTRA/NR	E-UTRA & NR RB allocation		CC MOD E-UTRA/NR	E-UTRA & NR allocations (L <sub>CRB</sub> @ RB <sub>start</sub> )	
	E-UTRA		NR					PCC	SCC			
	Band	Range	Band	Range								
Default Test Settings for a DC_XA-nYA Configuration												
1	X	Mid	Y	Mid	Mid/Lowest N <sub>RB</sub>	Mid/Lowest N <sub>RB</sub>	QPSK /CP-OFDM QPSK	All RBs	QPSK/DFT-s-OFDM QPSK	REFSENS	REFSENS	
2	X	Mid	Y	Mid	Mid/Highest N <sub>RB</sub>	Mid/Highest N <sub>RB</sub>	QPSK /CP-OFDM QPSK	All RBs	QPSK/DFT-s-OFDM QPSK	REFSENS	REFSENS	
Test Settings for DC_1A-n77A Configuration												
1	1	Note 5	77	Note 5	5/25	10/25	Note 7	All RBs	Note 7	25@0	25@0	
Test Settings for DC_1A-n78A Configuration												
1	1	Note 5	78	Note 5	5/25	10/25	Note 7	All RBs	Note 7	25@0	25@0	
Test Settings for DC_2A-n66A Configuration												
1	2	Note 5	66	Note 5	5/25	5/25	Note 7	All RBs	Note 7	25@0	25@0	
Test Settings for DC_2A-n78A Configuration												
1	2	Note 5	78	Note 5	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0	
Test Settings for DC_3A-n41A Configuration												
1	3	Note 5	41	Note 5	5/25	10/52	Note 7	All RBs	Note 7	25@0	52@0	
Test Settings for DC_3A-n77/n7878A Configuration												
1	3	Note 5	77/78	Note 5	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0	
Test Settings for DC_3A-n78A Configuration												
1	3	Note 5	78	Note 5	5/25	10/25	Note 7	All RBs	Note 7	50@0	25@0	
Test Settings for DC_5A-n78A Configuration												
1	5	Note 5	78	Note 5	5/25	10/52	Note 7	All RBs	Note 7	25@0	52@0	
Test Settings for DC_8A-n41A Configuration												
1	8	Low	41	High	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0	
Test Settings for DC_8A-n77A/n78A Configuration												
1	8	Note 5	77	Note 5	5/25	10/52	Note 7	All RBs	Note 7	25@0	52@0	
2	8	Note 5	78	Note 5	5/25	10/52	Note 7	All RBs	Note 7	25@0	52@0	
Test Settings for DC_8A-n79A Configuration												



1	8	Note 5	79	Note 5	5/25	40/216	Note 7	All RBs	Note 7	25@0	216@0
<b>Test Settings for DC_20A-n77A Configuration</b>											
1	20	Note 5	77	Note 5	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0
2	20	Note 5	77	Note 5	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0
<b>Test Settings for DC_20A-n78A Configuration</b>											
1	20	Note 5	78	Note 5	5/25	10/50	Note 7	All RBs	Note 7	25@0	50@0
<b>Test Settings for DC_21A- n79A Configuration</b>											
1	21	Note 5	79	Note 5	5/25	40/216	Note 7	All RBs	Note 7	25@0	216@0
<b>Test Settings for DC_28A- n77/n78A Configuration</b>											
1	28	Note 5	77	Note 5	5/25	10/25	Note 7	All RBs	Note 7	50@0	25@0
2	28	Note 5	78	Note 5	5/25	10/25	Note 7	All RBs	Note 7	50@0	25@0
<b>Test Settings for DC_66A-n78A Configuration</b>											
1	66	Note 5	78	Note 5	5/25	10/25	Note 7	All RBs	Note 7	50@0	25@0
<b>Test Settings for CA_7A-20A Configuration</b>											
1	7	Note 5	20	Note 5	50	25	QPSK	All RBs	QPSK	50@0	25@0
Note 1:	Both of the transmitters shall be set min(+20 dBm, $P_{\text{CMAX\_L,c}}$ ) as defined in subclause 6.2.5A. In case Single UL is allowed and the UE only indicates support of "Single UL" the output power of the active UL shall be set at $P_{\text{CMAX\_L,c}}$ or set to the maximum output power according to the UE power scaling capability.										
Note 2:	Use DC Configuration – specific test points if present in the table, otherwise use test points from matching Group Test Settings, if present in the table. Otherwise use the Default Test Settings test points.										
Note 3:	X,Y correspond to the different bands in the DC Configuration. E.g. for DC_1A-n3A, X=1, Y=3.										
Note 4:	REFSENS refers to the E_UTRA bands and NR band $N_{\text{RB}}$ 's single carrier Uplink RB allocation for reference sensitivity according to table 7.3.5-2 of TS 36.521-1 and Table 7.3.2.4.1-3 of TS 38.521-1, respectively										
Note 5:	Test frequency for each DC configuration shall follow Table 7.3B.2.3.3.5.1-1. If test configurations of each ID in a DC configuration are same, test frequency shall follow the order of Table 7.3B.2.3.3.5.1-1.										
Note 6:	Not applicable if the UE only supports Bandwidth Combination Set 1.										
Note 7:	Same as default.										
Note 8:	$\text{RB}_{\text{START}} = 0$										

### 7.3B.2.3.4.2.2 Test procedure

Same as in clause 7.3B.2.3.1.4.2 with following exceptions:

1. E-UTRA SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for  $C_{\text{RNTI}}$  to schedule the UL RMC according to Table 6.6.3.1.4.1-1 of TS 36.521-1[10]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
2. NR SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format [0\_1] for  $C_{\text{RNTI}}$  to schedule the UL RMC according to Tables 7.3.4.1-1 and 7.3.4.1-2 of TS38.521-1[8]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Both NR and E-UTRA SS send continuously uplink power control "up" commands in the uplink scheduling information to the UE until the UE transmits at  $P_{\text{UMAX}}$  level.

### 7.3B.2.3.2.4.2.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

### 7.3B.2.3.2.5 Test requirement

For inter-band EN-DC configurations, the throughput of each CG shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with reference receive power level specified in Tables Table 7.3.2.5-1 in TS 38.521-1 [8] and parameters specified Tables 7.3.2.4.1-1, Tables 7.3.2.4.1-2 and Tables 7.3.2.4.1-3 in TS 38.521-1 [8] for NR band.

- Note 1: Each EN-DC combination defined in Table 5.2B.4.1-1 shall be tested in anchor-agnostic mode as described in this section.

Note 2: Test procedure for exceptional test requirements for reference sensitivity for inter-band EN-DC within FR1 are defined in clause 7.3B.2.3.4.2.2. The test requirement is defined in Table 7.3B.2.3.2.5-1, Table 7.3B.2.3.2.5-2, Table 7.3B.2.3.2.5-3, Table 7.3B.2.3.2.5-4, and Table 7.3B.2.3.2.5-5.

Note 3: For the UE which supports inter-band EN-DC, the minimum requirement for reference sensitivity in Table 7.3.2.5-1 of TS 38.521-1 [8] for NR band and Table 7.3.5-1 of TS 36.521-1 [10] for EUTRA band, shall be increased by the amount given in  $\Delta R_{IB,c}$  defined in subclause 7.3B.3.3 for the applicable for two, three, four and five bands operation.

Reference sensitivity exceptions due to UL harmonic interference for EN-DC in NR FR1, are specified in Table 7.3B.2.3.2.5-1 with uplink configuration specified in Table 7.3B.2.3.4.2.1-2a to Table 7.3B.2.3.4.2.1-2t for each specific EN-DC combination scenario.

Table 7.3B.2.3.2.5-1: Reference sensitivity due to UL harmonic for EN-DC in NR FR1

UL band	DL band	SCS (kHz)	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	30 MHz (dB)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
1, 3	n77 <sup>1,2</sup>	15		-71.4 +TT	-71.4 +TT	-71.3 +TT			-71.2 +TT	-71.3 +TT				
		30		-71.7 +TT	-71.5 +TT	-71.5 +TT			-71.3 +TT	-71.4 +TT	-71.4 +TT	-71.3 +TT	-71.3 +TT	-71.3 +TT
		60		-72.1 +TT	-71.8 +TT	-71.7 +TT			-71.5 +TT	-71.5 +TT	-71.5 +TT	-71.4 +TT	-71.4 +TT	-71.4 +TT
	n77 <sup>3</sup>	15		-94.2 +TT	-92.7 +TT	-91.9 +TT			-89.1 +TT	-88.1 +TT				
		30		-94.5 +TT	-92.8 +TT	-92.1 +TT			-89.2 +TT	-88.2 +TT	-87.4 +TT	-86.1 +TT	-85.6 +TT	-85.1 +TT
		60		-94.9 +TT	-93.1 +TT	-92.3 +TT			-89.4 +TT	-88.3 +TT	-87.5 +TT	-86.2 +TT	-85.7 +TT	-85.2 +TT
2	n78 <sup>1,2</sup>	15		-71.4 +TT	-71.4 +TT	-71.3 +TT			-71.2 +TT					
		30		-71.7 +TT	-71.5 +TT	-71.5 +TT			-71.3 +TT					
		60		-72.1 +TT	-71.8 +TT	-71.7 +TT			-71.5 +TT					
2	n78 <sup>3</sup>	15		-94.2 +TT	-92.7 +TT	-91.9 +TT								
		30		-94.5 +TT	-92.8 +TT	-92.1 +TT								
		60		-94.9 +TT	-93.1 +TT	-92.3 +TT								
3	n78 <sup>1,2</sup>	15		-71.9 +TT	-71.9 +TT	-71.8 +TT			-71.7 +TT	-71.8 +TT				
		30		-72.2 +TT	-72.0 +TT	-72.0 +TT			-71.8 +TT	-71.9 +TT	-71.9 +TT	-71.8 +TT	-71.8 +TT	-71.8 +TT
		60		-72.6 +TT	-72.3 +TT	-72.2 +TT			-72.0 +TT	-72.0 +TT	-72.0 +TT	-71.9 +TT	-71.9 +TT	-71.9 +TT
	n78 <sup>3</sup>	15		-94.7 +TT	-93.2 +TT	-92.4 +TT			-89.6 +TT	-88.6 +TT				
		30		-95.0 +TT	-93.3 +TT	-92.6 +TT			-89.7 +TT	-88.7 +TT	-87.9 +TT	-86.6 +TT	-86.1 +TT	-85.6 +TT
		60		-95.4 +TT	-93.6 +TT	-92.8 +TT			-89.9 +TT	-88.8 +TT	-88.0 +TT	-86.7 +TT	-86.2 +TT	-85.7 +TT
8	n77 <sup>6,7</sup> n78 <sup>6,7</sup>	15		-84.5 +TT	-84.4 +TT	-84.2 +TT			-84.0 +TT	-83.9 +TT				
		30		-84.8 +TT	-84.5 +TT	-84.4 +TT			-84.1 +TT	-84.0 +TT	-83.9 +TT	-83.8 +TT	-83.5 +TT	-83.7 +TT

UL band	DL band	SCS (kHz)	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	30 MHz (dB)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
		60		-85.2 +TT	-84.8 +TT	-84.6 +TT			-84.3 +TT	-84.1 +TT	-84.0 +TT	-83.9 +TT	-83.6 +TT	-83.8 +TT
8	n79 <sup>4,5</sup>	15							-82.8 +TT	-82.4 +TT				
		30							-82.9 +TT	-82.5 +TT	-82.3 +TT	-81.7 +TT		-81.2 +TT
		60								-83.1 +TT	-82.6 +TT	-82.4 +TT	-81.8 +TT	
18, 19	n77 <sup>4,5</sup>	15		-84.9 +TT	-84.6 +TT	-84.4 +TT			-84.4 +TT	-84.4 +TT				
		30		-85.2 +TT	-84.7 +TT	-84.6 +TT			-84.5 +TT	-84.5 +TT	-84.4 +TT	-84.4 +TT		-84.4 +TT
		60		-85.6 +TT	-85.0 +TT	-84.8 +TT			-84.7 +TT	-84.6 +TT	-84.5 +TT	-84.5 +TT		-84.5 +TT
28	n77 <sup>4,5</sup> n78 <sup>4,5</sup>	15		-84.9 +TT	-84.6 +TT	-84.4 +TT			-84.4 +TT	-84.4 +TT				
		30		-85.2 +TT	-84.7 +TT	-84.6 +TT			-84.5 +TT	-84.5 +TT	-84.4 +TT	-84.4 +TT		-84.4 +TT
		60		-85.6 +TT	-85.0 +TT	-84.8 +TT			-84.7 +TT	-84.6 +TT	-84.5 +TT	-84.5 +TT		-84.5 +TT
20	n77 <sup>6,7</sup> n78 <sup>6,7</sup>	15		-84.5 +TT	-84.4 +TT	-84.2 +TT			-83.1 +TT					
		30		-84.8 +TT	-84.5 +TT	-84.4 +TT			-83.2 +TT					
		60		-85.2 +TT	-84.8 +TT	-84.6 +TT			-83.4 +TT					
26	n41			-84.5 +TT	-84.6 +TT	-84.4 +TT			-83.6 +TT	-83.3 +TT	3.9 +TT	3.1 +TT	2.7 +TT	
		30		-84.8 +TT	-84.7 +TT	-84.6 +TT			-83.7 +TT	-83.4 +TT	-83.0 +TT	-82.5 +TT	-82.4 +TT	
		60		-85.2 +TT	-85.0 +TT	-84.8 +TT			-83.9 +TT	-83.5 +TT	-83.2 +TT	-82.5 +TT	-82.4 +TT	
26	n77 <sup>6,7</sup> n78 <sup>6,7</sup>	15		-84.5 +TT	-84.4 +TT	-84.2 +TT			-83.1 +TT					
		30		-84.8 +TT	-84.5 +TT	-84.4 +TT			-83.2 +TT					
		60		-85.2 +TT	-84.8 +TT	-84.6 +TT			-83.4 +TT					
26	n77 <sup>4,5</sup>	15		-84.9 +TT	-84.6 +TT	-84.4 +TT			-84.4 +TT	-84.4 +TT				
		30		-85.2 +TT	-84.7 +TT	-84.6 +TT			-84.5 +TT	-84.5 +TT	-84.4 +TT	-84.4 +TT	-85.6 +TT	-84.4 +TT

UL band	DL band	SCS (kHz)	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	30 MHz (dB)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
		60		-85.6 +TT	-85.0 +TT	-84.8 +TT			-84.7 +TT	-84.6 +TT	-84.5 +TT	-84.5 +TT	-85.7 +TT	-84.5 +TT
n28	1 <sup>8,9,10</sup>	15	-89.1 +TT	-88.7 +TT	-88.3 +TT	-88.0 +TT								
	n75 <sup>1,2</sup>	15	TBD	TBD	TBD	TBD								
		30	TBD	TBD	TBD	TBD								
		60	TBD	TBD	TBD	TBD								
n71	2 <sup>11</sup>	15	-92.7 +TT	-93.3 +TT	-91.8 +TT	-90.7 +TT								
n71	2 <sup>12</sup>	15	-95.6 +TT	-93.3 +TT	-91.8 +TT	-90.7 +TT								
66	n78 <sup>1,2</sup>	15		-71.4 +TT	-71.4 +TT	-71.3 +TT			-71.2 +TT					
		30		-71.7 +TT	-71.5 +TT	-71.5 +TT			-71.3 +TT					
		60		-72.1 +TT	-71.8 +TT	-71.7 +TT			-71.5 +TT					
	n78 <sup>3</sup>	15		-94.2 +TT	-92.7 +TT	-91.9 +TT								
		30		-94.5 +TT	-92.8 +TT	-92.1 +TT								
		60		-94.9 +TT	-93.1 +TT	-92.3 +TT								

- NOTE 1: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 2nd transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.
- NOTE 2: The requirements should be verified for UL EARFCN or NR ARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.2 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.
- NOTE 3: The requirements are only applicable to channel bandwidths with a carrier frequency at  $\pm (20 + BW_{Channel}^{HB} / 2)$  MHz offset from  $2f_{UL}^{LB}$  in the victim (higher band) with  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$ , where and  $BW_{Channel}^{HB}$  are the channel bandwidths configured in the aggressor (lower) and victim (higher) bands in MHz, respectively.
- NOTE 4: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 5<sup>th</sup> transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.
- NOTE 5: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that  $f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.5 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.
- NOTE 6: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (lower) band for which the 4<sup>th</sup> transmitter harmonic is within the downlink transmission bandwidth of a victim (higher) band.

UL band	DL band	SCS (kHz)	5 MHz (dB)	10 MHz (dB)	15 MHz (dB)	20 MHz (dB)	25 MHz (dB)	30 MHz (dB)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
<p>NOTE 7: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that <math>f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.4 \rfloor 0.1</math> in MHz and <math>F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2</math> with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.</p> <p>NOTE 8: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of a low band for which the 3rd transmitter harmonic is within the downlink transmission bandwidth of a high band.</p> <p>NOTE 9: The requirements should be verified for UL EARFCN of a low band (superscript LB) such that in MHz and <math>F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2</math> with the carrier frequency of a high band in MHz and the channel bandwidth configured in the low band.</p> <p>NOTE 10: Applicable for the operations with 2 or 4 antenna ports supported in the band with carrier aggregation configured.</p> <p>NOTE 11: These requirements apply when the lower edge frequency of the 5 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.</p> <p>NOTE 12: These requirements apply when the lower edge frequency of the 10 MHz, 15 MHz, or 20 MHz uplink channel in Band 71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.</p> <p>NOTE 13: TT is the same as defined in Table 7.3B.2.3.2.5-1a.</p>														

Table 7.3B.2.3.2.5-1a: Test Tolerance (TT) for RX sensitivity level

$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 6.0\text{ GHz}$
0.7 dB	1.0 dB

Reference sensitivity exceptions due to receiver harmonic mixing for EN-DC in NR FR1, are specified in Table 7.3B.2.3.2.5-2 with uplink configuration specified in Table 7.3B.2.3.4.2.1-3a to Table 7.3B.2.3.4.2.1-3k for each specific EN-DC combination scenario.

Table 7.3B.2.3.2.5-2: Reference sensitivity due to receiver harmonic mixing for EN-DC in NR FR1

UL band	DL band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	15 MHz (dBm)	20 MHz (dBm)	25 MHz (dBm)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
2	n71 <sup>4</sup>	15	-70.4 +TT	-70.4 +TT	-70.4 +TT	-70.4 +TT							
		30		-70.7 +TT	-70.7 +TT	-71.8 +TT							
		60		-72.4 +TT	-72.7 +TT	-77.0 +TT							
26	n41 <sup>4</sup>		-72.5 +TT	-69.5 +TT	-69.5 +TT	N/A							
41	n77 <sup>7</sup>		N/A	-87.0 +TT	-85.5 +TT	-85.3 +TT	N/A	-86.1 +TT	-85.8 +TT				
			N/A	-87.3 +TT	-85.6 +TT	-85.5 +TT	N/A	-86.2 +TT	-85.9 +TT	-86.2 +TT	-85.7 +TT	-85.2 +TT	
			N/A	-87.7 +TT	-85.9 +TT	-85.7 +TT	N/A	-86.4 +TT	-86.0 +TT	-86.3 +TT	-85.8 +TT	-85.3 +TT	
41	n78 <sup>7</sup>		N/A	-87.0 +TT	-85.5 +TT	-85.3 +TT	N/A	-86.1 +TT	-85.8 +TT				
			N/A	-87.3 +TT	-85.6 +TT	-85.5 +TT	N/A	-86.2 +TT	-85.9 +TT	-86.2 +TT	-85.7 +TT	-85.2 +TT	
			N/A	-87.7 +TT	-85.9 +TT	-85.7 +TT	N/A	-86.4 +TT	-86.0 +TT	-86.3 +TT	-85.8 +TT	-85.3 +TT	
n71	2 <sup>5</sup>		TBD	TBD	TBD	TBD							
	2 <sup>6</sup>		TBD	TBD	TBD	TBD							
n77	41 <sup>8</sup>		-86.9 +TT	-83.9 +TT	-82.1 +TT	-80.9 +TT	N/A	N/A	N/A	N/A	N/A	N/A	N/A
n77	28 <sup>2</sup>		-69.8 +TT	-69.8 +TT	-69.8 +TT	-68.3 +TT							
n78	41 <sup>8</sup>		-86.9 +TT	-83.9 +TT	-82.1 +TT	-80.9 +TT	N/A	N/A	N/A	N/A	N/A	N/A	N/A
n79	19 <sup>2</sup>		-69.8 +TT	-69.8 +TT	-69.8 +TT								
n79	21 <sup>3</sup>		-60.0 +TT	-60.0 +TT	-60.0 +TT								
n79	26 <sup>2</sup>		-69.8 +TT	-69.8 +TT	-69.8 +TT	N/A	N/A	N/A	N/A	N/A	N/A		N/A

NOTE 1: These requirements apply when there is at least one individual RE within the uplink transmission bandwidth of the aggressor (higher) band for which the mixing product due to harmonic of victim (lower) band LO with leakage of aggressor (higher) band is within the downlink transmission bandwidth of a victim (lower) band.

NOTE 2: The requirements should be verified for DL EARFCN of the victim (lower) band (superscript LB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.5 \rfloor \cdot 0.1$  in MHz and  $F_{DL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{DL}^{LB} \leq F_{DL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with  $f_{DL}^{LB}$  carrier frequency in the victim (lower) band in MHz and the channel bandwidth configured in the lower band.

NOTE 3: The requirements should be verified for DL EARFCN of the victim (lower) band (superscript LB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.4 \rfloor \cdot 0.1$  in MHz and  $F_{DL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{DL}^{LB} \leq F_{DL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with  $f_{DL}^{LB}$  carrier frequency in the victim (lower) band in MHz and the channel bandwidth configured in the lower band.

NOTE 4: The requirements should be verified for UL EARFCN of the aggressor (higher) band (superscript HB) such that  $f_{DL}^{LB} = \lfloor f_{UL}^{HB} / 0.3 \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2$  with the carrier frequency in the victim (lower) band and the channel bandwidth configured in the higher band.

NOTE 5: These requirements apply when the lower edge frequency of the 5 MHz uplink channel in Band n71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

NOTE 6: These requirements apply when the lower edge frequency of the 10 MHz, 15 MHz, or 20 MHz uplink channel in Band n71 is located at or below 668 MHz and the downlink channel in Band 2 is located with its upper edge at 1990 MHz.

NOTE 7: The requirements should be verified for UL EARFCN of the aggressor (lower) band (superscript LB) such that

$$f_{UL}^{LB} = \lfloor f_{DL}^{HB} / 0.15 \rfloor \cdot 0.1 \text{ in MHz and } F_{UL\_low}^{LB} + BW_{Channel}^{LB} / 2 \leq f_{UL}^{LB} \leq F_{UL\_high}^{LB} - BW_{Channel}^{LB} / 2 \text{ with carrier frequency in the victim (higher) band in MHz and the channel bandwidth configured in the lower band.}$$

NOTE 8: The requirements should be verified for UL EARFCN of the aggressor (higher) band (superscript HB) such that  $f_{UL}^{LB} = \lfloor 15 * f_{DL}^{HB} \rfloor \cdot 0.1$  in MHz and  $F_{UL\_low}^{HB} + BW_{Channel}^{HB} / 2 \leq f_{UL}^{HB} \leq F_{UL\_high}^{HB} - BW_{Channel}^{HB} / 2$  with  $f_{DL}^{LB}$  carrier frequency in the victim (lower) band in MHz and  $BW_{Channel}^{LB}$  the channel bandwidth configured in the higher band.

NOTE 9: TT is the same as defined in Table 7.3B.2.3.2.5-1a.

Reference sensitivity exceptions due to close proximity of bands for EN-DC in NR FR1, are specified in Table 7.3B.2.3.2.5-3 with uplink configuration specified in Table 7.3B.2.3.4.2.1-4.

**Table 7.3B.2.3.2.5-3: Reference sensitivity exceptions due to close proximity of bands for EN-DC in NR FR1**

FFS

Reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1, are specified in Table 7.3B.2.3.2.5-4 with uplink configuration specified in Table 7.3B.2.3.4.2.1-5a to Table 7.3B.2.3.4.2.1-5e.

**Table 7.3B.2.3.2.5-4: Reference sensitivity exceptions due to cross band isolation for EN-DC in NR FR1**

E-UTRA or NR Band / Channel bandwidth of the affected DL band													
UL band	DL band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	15 MHz (dBm)	20 MHz (dBm)	25 MHz (dBm)	40 MHz (dBm)	50 MHz (dBm)	60 MHz (dBm)	80 MHz (dBm)	90 MHz (dBm)	100 MHz (dBm)
3	n41	15		-90.5 +TT	-89.0 +TT	-87.9 +TT			-84.1 +TT				
		30		-90.8 +TT	-89.1 +TT	-88.1 +TT			-84.2 +TT	-83.6 +TT	-82.4 +TT	-82.0 +TT	-81.7 +TT
		60		-91.2 +TT	-89.4 +TT	-88.3 +TT			-84.3 +TT	-83.8 +TT	-82.4 +TT	-82.0 +TT	-81.7 +TT
n41	3		-93.3	-90.3	-88.5	-87.2							
n77	41 <sup>1</sup>		-93.5	-90.5	-88.7	-87.5							
n78	41 <sup>1</sup>		-93.5	-90.5	-88.7	-87.5							
NOTE 1: Applicable only when harmonic mixing MSD for this combination is not applied.													
NOTE 2: TT is the same as defined in Table 7.3B.2.3.2.5-1a..													

Reference sensitivity exceptions due to dual uplink operation for EN-DC in NR FR1, are specified in Table 7.3B.2.3.2.5-5 with uplink configuration specified in Table 7.3B.2.3.4.2.1-6.



**Table 7.3B.2.3.2.5-5: Reference sensitivity exceptions due to dual uplink operation for EN-DC in NR FR1 (two bands)**

EN-DC Configuration	EUTRA or NR band	SCS (kHz)	NR or E-UTRA Band / Channel bandwidth						IMD order)	Duplex mode
			5 MHz (dBm)	10 MHz (dBm)	15 MHz (dBm)	20 MHz (dBm)	40 MHz (dBm)			
DC_1A_n77A	1	N/A	-69.5	-	-	-	-	IMD2 <sup>3</sup>	FDD	
	n77	15	-	REFSENS	-	-	-	N/A	TDD	
DC_1A_n77A	1	N/A	-91.3	-	-	-	-	IMD4-	FDD	
	n77	15	-	REFSENS	-	-	-	N/A	TDD	
DC_2A_n66A	2	N/A	-77.3	-	-	-	-	IMD3		
	n66	15	REFSENS	-	-	-	-	N/A		
DC_2A_n66A	2	N/A	REFSENS	-	-	-	-	N/A		
	n66	15	-95.5 +TT	-	-	-	-	IMD5		
DC_2A_n78A	2	N/A	-71.3	-	-	-	-	IMD2 <sup>3</sup>	FDD	
	n78	15	-	REFSENS	-	-	-	-	TDD	
DC_2A_n78A	2	N/A	-89.3	-	-	-	-	N/A		
	n78	15	-	REFSENS	-	-	-	IMD4 <sup>3</sup>	TDD	
DC_3A_n7A	3	N/A	REFSENS	-	-	-	-	-		
	n7	15	-	-84.6 +TT <sup>5</sup>	-	-	-	-		
DC_3A_n41A	3	N/A	-88.1	-	-	-	-	IMD4	FDD	
	n41	15	-	REFSENS	-	-	-	IMD4	TDD	
DC_3A_n77A DC_3A_n78A	3	N/A	-70.3	-	-	-	-	IMD2 <sup>3</sup>		
	n77, n78	15	-	REFSENS	-	-	-	-	TDD	
DC_3A_n77A DC_3A_n78A	3	N/A	-88.3	-	-	-	-	IMD4 <sup>3</sup>		
	n77, n78	15	-	REFSENS	-	-	-	N/A	TDD	
DC_3A_n78A	3	N/A	TBD <sup>5</sup>	-	-	-	-	IMD2		
	n78	15	-	REFSENS	-	-	-	N/A	TDD	
	3	N/A	-	-	-	-	-	N/A	No	
	n78	15	-	REFSENS	-	-	-	N/A		
DC_3C_n78A	3	N/A	-70.3	-	-	-	-	IMD2 <sup>4</sup>		
	n78	15	-	REFSENS	-	-	-	N/A		
	n78	15	-	REFSENS	-	-	-	N/A		
DC_3C_n78A	3	N/A	-88.3	-	-	-	-	IMD4 <sup>4</sup>		
	n78	15	-	REFSENS	-	-	-	N/A		
DC_5A_n78A	5	N/A	-89.0	-	-	-	-	IMD4	FDD	
	n78	15	-	REFSENS	-	-	-	N/A	TDD	
DC_8A_n41A	8	N/A	-84.2	-	-	-	-	IMD3 <sup>3</sup>	FDD	
	n41	15	-	REFSENS	-	-	-	N/A	TDD	
DC_8A_n77A DC_8A_n78A DC_8A- SUL_n78A-n81A	8	N/A	-88.0	-	-	-	-	IMD4	FDD	
	n77, n78	15	-	REFSENS	-	-	-	H4	TDD	
DC_8A_n79A DC_8A- SUL_n79A-n81A	8	N/A	-91.5	-	-	-	-	IMD5	FDD	
	n79	15	-	-	-	-	REFSENS	N/A	TDD	
DC_20A_n77A	20	N/A	-85.3	-	-	-	-	IMD4	FDD	
	n77	15	-	REFSENS	-	-	-	N/A	TDD	
	20	N/A	-89.8	-	-	-	-	IMD5	FDD	
	n77	15	-	REFSENS	-	-	-	N/A	TDD	
DC_20A_n78A, DC_20A- SUL_n78A-n82A	20	N/A	-74.6	-	-	-	-	IMD4 <sup>4</sup>	FDD	
	n78	15	-	REFSENS	-	-	-	N/A	TDD	
DC_21A_n79A	21	N/A	-80.9	-	-	-	-	IMD3	FDD	
	n79	15	-	-	-	-	REFSENS	N/A	TDD	
	28	N/A	-92.3	-	-	-	-	IMD5	FDD	

CA_28A_n77A, CA_28A_n78A, DC_28A- SUL_n78A-n83A	n77, n78	15	-	REFSENS	-	-	-	N/A	TDD
DC_66A_n78A	66	1740	-72.8	-	-	-	-	IMD2 <sup>3</sup>	FDD
	n78	3575	-	REFSENS	-	-	-	N/A	TDD
	66	1765	-90.8	-	-	-	-	IMD4 <sup>3</sup>	FDD
	n78	3435	-	REFSENS	-	-	-	N/A	TDD
NOTE 1: Both of the transmitters shall be set min(+20 dBm, P <sub>CMAX_L,c</sub> ) as defined in subclause 6.2.5A. In case Single UL is allowed and the UE only indicates support of "Single UL" the output power of the active UL shall be set at P <sub>CMAX_L,c</sub> or set to the maximum output power according to the UE power scaling capability.									
NOTE 2: RB <sub>START</sub> = 0									
NOTE 3: This band is subject to IMD5 also which MSD is not specified.									
NOTE 4: The symbol "REFSENS" in this table refers to the reference sensitivity values for single carrier specified in Table 7.3.5-2 of TS 36.521-1 for 2 antenna port E-UTRA band, Table 7.3_1.5-1 of TS 36.521-1 for 4 antenna port E-UTRA band, Table 7.3.2.5-1 for 2 antenna port NR band and Table 7.3.2_1.5-1 for 4 antenna port NR band.									
NOTE 5: For UEs only indicating support of Single UL, this requirement is verified with non-simultaneous uplink transmissions on the E-UTRA and NR CGs.									
NOTE 6: TT is the same as defined in Table 7.3B.2.3.2.5-1a.									

### 7.3B.2.4 Reference sensitivity for Inter-band EN-DC including FR2

#### 7.3B.2.4.1 Test purpose

Same test purpose as in clause 7.3.2.1 in TS 38.521-2 [9] for the NR carrier.

#### 7.3B.2.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

#### 7.3B.2.4.3 Minimum conformance requirements

Same minimum conformance requirements as in clause 7.3.2.3 in TS 38.521-2 [9] for the NR carrier.

The normative reference for this requirement is TS 38.101-3 [4] subclause 6.3B.2.4.

#### 7.3B.2.4.4 Test description

##### 7.3B.2.4.4.1 Initial conditions

Same test description as in clause 7.3.2.4 in TS 38.521-2 [9] for the NR carrier with the following exception:

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1. For Initial conditions as in clause 7.3.2.4.1 in TS 38.521-2 [9], the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.7-1 and propagation conditions are set according to Annex B.0 of TS36.521-1 [10].

Step 6 of Initial conditions as in clause 7.3.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

Same test procedure as in clause 6.5.3.1.4.1 in TS 38.521-2 [9] with the following steps added for E-UTRA component:

- 1.1 On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.7-1 under clause 4.7.

#### 7.3B.2.4.5 Test requirement

Same test requirement as in clause 7.3.2.5 in TS 38.521-2 [9] for the NR carrier.

#### 7.3B.2.5 Reference sensitivity for Inter-band EN-DC including FR1 and FR2 (3 CCs)

FFS

#### 7.3B.2.6 Reference sensitivity for EN-DC within FR1(3 CCs)

##### 7.3B.2.6.1 Test purpose

Same as in clause 7.3B.2.3.1.1.

##### 7.3B.2.6.2 Test applicability

This test applies to all types of NR UE release 15 and forward supporting inter-band EN-DC.

##### 7.3B.2.6.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.3B.2.0

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

##### 7.3B.2.6.4 Test description

###### 7.3B.2.6.4.1 Initial conditions

Same initial conditions as in subclause 7.3B.2.3.2.4.1 with following exceptions:

The initial test configurations for E-UTRA band and NR band consist of environmental conditions, test frequencies, and channel bandwidths and RB allocations for exceptional test scenarios are specified in Table 7.3B.2.6.4.1-1.

**Table 7.3B.2.6.4.1-1: Test Configuration Table Reference sensitivity exceptions due to dual uplink operation for EN-DC in NR FR1 (three bands)**

Initial Conditions												
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					NC, TL/VL, TL/VH, TH/VL, TH/VH							
NR Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1, E-UTRA Test Frequencies as specified in TS 36.508 [11] subclause 4.3.1					For test frequencies refer to “Range” columns. For mapping within Band refer to “CC” columns							
Test DC Combination setting (NRB_agg) as specified in subclause [TBD] for the DC Configuration across bandwidth combination sets supported by the UE.					Refer to “NR NRB” and “E-UTRA NRB” columns							
Network signalling value					NS_01 by default, exceptions listed in Table 7.3.3-3, dependent on PCC Band							
Test Parameters for DC Configurations												
ID	PCC – E-UTRA				SCC1 – EUTRA/NR				CG -NR			
	Band	Range	NRB		Band	Range	NRB		Band	Range	NRB	
	UL MOD	DL MOD	CH BW/UL alloc (Note 2,3,4)	DLalloc	UL MOD	DL MOD	UL/DL Ch BW alloc	DLalloc ULalloc	UL MOD	UL Ch BW RAlloc	DL Ch BW	DLalloc
Default Test Settings for a DC_XA-YA-ZA Configuration (Inter-band)												
1	X	Note 0	REFSENS	All RBs	Y	Mid	Mid	All RBs	Z	Mid	Mid	All RBs
	QPSK	QPSK		Highest N <sub>RB</sub>	N/A	QPSK /CP-OFDM QPSK		All RBs	CP-OFDM QPSK	REFSENS		Highest N <sub>RB</sub>
2	Y	Mid	REFSENS	All RBs	Y	Mid	Mid	All RBs	Z	Mid	Mid	All RBs
	QPSK	QPSK		Highest N <sub>RB</sub>	N/A	QPSK /CP-OFDM QPSK		All RBs <sub>B</sub>	CP-OFDM QPSK	REFSENS		Highest N <sub>RB</sub>
3	Z	Mid	REFSENS	All RBs	Y	Mid	Mid	All RBs	XX	Mid	Mid	All RBs
	QPSK	QPSK		Highest N <sub>RB</sub>	N/A	QPSK /CP-OFDM QPSK		All RBs	CP-OFDM QPSK	REFSENS		Highest N <sub>RB</sub>
Test Settings for DC_1A-3A-n78A Configuration												
1	1	Note 0	5 MHz 25@0	All RBs	3	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
2	1	Note 0	5 MHz 25@0	All RBs	3	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
3	1	Note 0	5 MHz 25@0	All RBs	3	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
Test Settings for DC_1A-5A-n78A Configuration												
1	1	Note 0	5 MHz	All RBs	5	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs

	QPSK	QPSK	25@0	100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_1A-7A-n78A Configuration</b>												
1	1	Note 0	5 MHz 25@0	All RBs	7	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
2	1	Note 0	5 MHz 25@0	All RBs	7	Note 0	10 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		50@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_1A-20A-n78A Configuration</b>												
1	1	Note 0	5 MHz 25@0	All RBs	20	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_3A-5A-n78A Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	5	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
2	3	Note 0	5 MHz 25@0	All RBs	5	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 25@0		52@0
<b>Test Settings for DC_3C-7C-n78A with UL CA Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	7	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_3A-7A_n78A Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	7	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_3C-7A_n78A Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	7	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_3A-20A_n78A Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	20	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	N/A	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
<b>Test Settings for DC_3C-20A_n78A Configuration</b>												
1	3	Note 0	5 MHz 25@0	All RBs	20	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	QPSK	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0

Test Settings for DC_5A-7A_n78A Configuration												
1	5	Note 0	5 MHz 25@0	All RBs	7	Note 0	5 MHz	All RBs	n78	Note 0	10 Mhz	All RBs
	QPSK	QPSK		100	QPSK	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
Test Settings for DC_7A-20A_n78A Configuration												
1	7	Note 0	5 MHz 25@0	All RBs	20	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	QPSK	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0
Test Settings for DC_7A-28A_n78A Configuration												
1	7	Note 0	5 MHz 25@0	All RBs	28	Note 0	5 MHz	All RBs	n78	Note 0	10 MHz	All RBs
	QPSK	QPSK		100	QPSK	QPSK		25@0	CP-OFDM QPSK	10 MHz 52@0		52@0

- Note 0: Test frequency for each DC configuration shall follow Table 7.3B.2.0.3.5.2-1. If test configurations of each ID in a DC configuration are same, test frequency shall follow the order of Table 7.3B.2.0.3.5.2-1.
- Note 1: CA Configuration Test CC Combination test settings are checked separately for each CA Configuration.
- Note 2: Intra-band contiguous & Intra-band contiguous + Inter-band: Use CA Configuration – specific test points if present in the table, otherwise use Default Test Settings test points.
- Note 3: Inter-band: Use CA Configuration – specific test points if present in the table, Otherwise use test points from matching Group Test Settings, if present in the table. Otherwise use the Default Test Settings test points.
- Note 4: Inter-band & Intra-band contiguous + Inter-band: If, according to the UE declared capability, UE does not support UL in an individual band within the CA Configuration, test points with that individual band as PCC are not applicable.
- Note 5: Intra-band contiguous: X corresponds to the band of the CA Configuration. E.g. for CA\_41D, X=41
- Note 6: Inter-band: X,Y,Z correspond to the different bands in the CA Configuration. E.g. for CA\_1A-3A-19A, X=1,Y=3,Z=19
- Note 7: Intra-band contiguous + Inter-band: X,Y correspond to the different bands in the CA Configuration, e.g. for CA\_1C-3A, X=1,Y=3, for CA\_1A\_42C, X=1,Y=42
- Note 8: REFSSENS refers to the PCC bands and PCC  $N_{RB}$  's single carrier Uplink RB allocation for reference sensitivity according to table 7.3.5-2.
- Note 9: Intra-band contiguous: If in the CA Configuration UE supports multiple CC Combinations with the same  $N_{RB\_agg}$ , choose for testing the Combination with maximum  $N_{RB\_PCC}$  and then select maximum  $N_{RB\_SCC1}$  for the chosen  $N_{RB\_PCC}$
- Note 10: Band 12:  $f_{UL} = 706.7$  MHz ( $N_{UL} = 23087$ ),  $f_{DL} = 736.7$  MHz ( $N_{DL} = 5087$ )  
Band 4:  $f_{DL} = 2120.1$  MHz ( $N_{DL} = 2051$ )
- Note 11: Band 12:  $f_{UL} = 710.9$  MHz ( $N_{UL} = 23129$ ),  $f_{DL} = 740.9$  MHz ( $N_{DL} = 5129$ )  
Band 4:  $f_{DL} = 2132.7$  MHz ( $N_{DL} = 2177$ )
- Note 12: N/A
- Note 13: Test points that fulfil criteria of Note 4 in Table 7.3A.5.5-3.
- Note 14: Only Band 1 and Band 42 need to be tested and Band 3 does not need to be tested.
- Note 15: Only Band 1 and Band 3 need to be tested and Band 42 does not need to be tested.
- Note 16: Band 3:  $f_{UL} = 1720$ MHz ( $N_{UL} = 19300$ ),  $f_{DL} = 1815$ MHz ( $N_{DL} = 1300$ )  
Band 42:  $f_{UL/DL} = 3440$ MHz ( $N_{UL/DL} = 41990$ )
- Note 17: Band 3:  $f_{UL} = 1775$ MHz ( $N_{UL} = 19850$ ),  $f_{DL} = 1870$ MHz ( $N_{DL} = 1850$ )  
Band 42:  $f_{UL/DL} = 3520$ MHz ( $N_{DL} = 42790$ )
- Note 18: N/A
- Note 19: Only Band 1 and Band 19 need to be tested and Band 28 does not need to be tested.
- Note 20: Intra-band contiguous + Inter-band: If in the CA Configuration UE supports multiple CC Combinations with the same  $N_{RB\_agg}$ , choose the Combination with  $N_{RB\_PCC} = N_{RB\_SCC1}$  for testing. If no such combination is supported, choose Combination with maximum  $N_{RB\_PCC}$  for testing.
- Note 21: Band 42:  $f_{UL/DL}$  for SCC1 = 3430.2MHz ( $N_{UL/DL} = 41892$ ),  $f_{UL/DL}$  for SCC2 = 3450MHz ( $N_{UL/DL} = 42090$ ).
- Note 22: Band 42:  $f_{UL/DL}$  for SCC1 = 3500.2MHz ( $N_{UL/DL} = 42592$ ),  $f_{UL/DL}$  for SCC2 = 3520MHz ( $N_{UL/DL} = 42790$ ).
- Note 23: Band 28:  $f_{UL} = 719.3$ MHz ( $N_{UL} = 27373$ ),  $f_{DL} = 774.3$ MHz ( $N_{DL} = 9373$ ).
- Note 24: Band 42:  $f_{UL/DL}$  for SCC1 = 3515.8MHz ( $N_{UL} = 42748$ ),  $f_{UL/DL}$  for SCC2 = 3527.5MHz ( $N_{DL} = 42865$ ).
- Note 25: Band 8:  $f_{UL} = 897.5$ MHz ( $N_{UL} = 21625$ ),  $f_{DL} = 942.5$ MHz ( $N_{DL} = 3625$ ), Band 42:  $f_{UL/DL} = 3590$ MHz ( $N_{UL/DL} = 43490$ ).
- Note 26: Band 28:  $f_{UL} = 722.5$  MHz ( $N_{UL} = 27405$ ),  $f_{DL} = 777.5$  MHz ( $N_{DL} = 9405$ ), Band 1:  $f_{DL} = 2167.5$  MHz ( $N_{DL} = 575$ ).
- Note 27: Band 28:  $f_{UL} = 743$  MHz ( $N_{UL} = 27610$ ),  $f_{DL} = 798$  MHz ( $N_{DL} = 9610$ ). Band 11:  $f_{DL} = 1480.9$  MHz ( $N_{DL} = 4800$ ).
- Note 28: Band 12:  $f_{UL} = 704$ MHz ( $N_{UL} = 23060$ ),  $f_{DL} = 734$ MHz ( $N_{DL} = 5060$ )  
Band 66:  $f_{UL} = 1712.5$ MHz ( $N_{UL} = 131997$ ),  $f_{DL} = 2112.5$ MHz ( $N_{DL} = 66461$ )
- Note 29: Band 12:  $f_{UL} = 707.5$ MHz ( $N_{UL} = 23095$ ),  $f_{DL} = 737.5$ MHz ( $N_{DL} = 5095$ )  
Band 66:  $f_{UL} = 1720$ MHz ( $N_{UL} = 132072$ ),  $f_{DL} = 2120$ MHz ( $N_{DL} = 66536$ )
- Note 30: Band 12:  $f_{UL} = 711$ MHz ( $N_{UL} = 23130$ ),  $f_{DL} = 741$ MHz ( $N_{DL} = 5130$ )  
Band 66:  $f_{UL} = 1717.5$ MHz ( $N_{UL} = 132047$ ),  $f_{DL} = 2117.5$ MHz ( $N_{DL} = 66511$ ).



- Note 31: Band 3:  $f_{UL} = 1757.4\text{MHz}$  ( $N_{UL} = 19674$ ),  $f_{DL} = 1852.4\text{MHz}$  ( $N_{DL} = 1674$ ),  
Band 11:  $f_{DL} = 1480.9\text{MHz}$  ( $N_{DL} = 4800$ ).
- Note 32: Band 3:  $f_{DL} = 1852.4\text{MHz}$  ( $N_{DL} = 1674$ ),  
Band 11:  $f_{UL} = 1432.9\text{MHz}$  ( $N_{UL} = 22800$ ),  $f_{DL} = 1480.9\text{MHz}$  ( $N_{DL} = 4800$ ).
- Note 33: Band 2:  $f_{UL} = 1868.3\text{MHz}$  ( $N_{UL} = 18783$ ),  $f_{DL} = 1948.3\text{MHz}$  ( $N_{DL} = 783$ ).  
Band 4:  $f_{UL} = 1735\text{MHz}$  ( $N_{UL} = 20200$ ),  $f_{DL} = 2135\text{MHz}$  ( $N_{DL} = 2200$ ).
- Note 34: The orders and numbering of SCCs in this table does not imply any order in test implementation of SCCs.
- Note 35: Band 3:  $f_{UL} = 1737\text{MHz}$  ( $N_{UL} = 19470$ ),  $f_{DL} = 1832\text{MHz}$  ( $N_{DL} = 1470$ ).  
Band 7:  $f_{UL} = 2543\text{MHz}$  ( $N_{UL} = 23430$ ),  $f_{DL} = 2663\text{MHz}$  ( $N_{DL} = 3180$ ).  
Band 20:  $f_{UL} = 847\text{MHz}$  ( $N_{UL} = 24300$ ),  $f_{DL} = 806\text{MHz}$  ( $N_{DL} = 6300$ ).
- Note 36: Band 3:  $f_{UL} = 1775\text{MHz}$  ( $N_{UL} = 19850$ ),  $f_{DL} = 1870\text{MHz}$  ( $N_{DL} = 1850$ ).  
Band 7:  $f_{UL} = 2510\text{MHz}$  ( $N_{UL} = 23100$ ),  $f_{DL} = 2630\text{MHz}$  ( $N_{DL} = 2850$ ).  
Band 20:  $f_{UL} = 855\text{MHz}$  ( $N_{UL} = 24380$ ),  $f_{DL} = 814\text{MHz}$  ( $N_{DL} = 6380$ ).
- Note 37: Band 7:  $f_{UL} = 2512\text{MHz}$  ( $N_{UL} = 23120$ ),  $f_{DL} = 2632\text{MHz}$  ( $N_{DL} = 2512$ ).  
Band 20:  $f_{UL} = 851\text{MHz}$  ( $N_{UL} = 24340$ ),  $f_{DL} = 851\text{MHz}$  ( $N_{DL} = 6340$ ).
- Note 38: Test frequency for each CA configuration shall follow Table 7.3A.0-0f. If test configurations of each ID in a CA configuration are same, test frequency shall follow the order of Table 7.3A.0-0f.
- Note 39: Test frequency for each CA configuration shall follow Table 7.3A.0-0g. If test configurations of each ID in a CA configuration are same, test frequency shall follow the order of Table 7.3A.0-0g.

#### 7.3B.2.6.4.2 Test procedure

Same as in clause 7.3B.2.6.0.4.2

#### 7.3B.2.6.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6.

#### 7.3B.2.6.5 Test requirement

Reference sensitivity exceptions for intermodulation interference due to dual uplink operation for EN-DC in NR FR1, are specified in Table 7.3B.2.6.5-1 with uplink configuration specified in Table 7.3B.2.6.4.1-1.

**Table 7.3B.2.6.5-1: Reference sensitivity exceptions for Scell due to dual uplink operation for EN-DC in NR FR1 (three bands)**

EN-DC Configuration	EUTRA/ NR band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	20 MHz (dBm)	40 MHz (dBm)	Duplex mode	IMD order	Single UL allowed
DC_1A-3A_n77A	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	3	N/A	-64.8	-	-	-		IMD2	
	n77	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	3	N/A	-87.8	-	-	-		IMD4	
	n77	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	-68.3	-	-	-	FDD	IMD2	
	3	N/A	REFSE NS	-	-	-		N/A	
n77	15	-	REFSE NS	-	-	TDD	N/A		
DC_1A-3A_n78A DC_1A-3C_n78A	1	N/A	-91.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B1} $	
	3	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	3	N/A	-65.1	-	-	-		IMD2 $ f_{B78}-f_{B1} $	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	-96.5	-	-	-	FDD	IMD5 $ 2*f_{B78}-3*f_{B3} $	
	3	N/A	REFSE NS	-	-	-		N/A	
n78	15	-	REFSE NS	-	-	TDD	N/A		
DC_1A-5A_n78A	1	N/A	-91.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B1} $	
	5	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	5	N/A	-89.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B5} $	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	-81.2	-	-	-	FDD	IMD3 $ f_{B78}-2*f_{B5} $	
	5	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	5	N/A	-94.2	-	-	-	FDD	IMD5 $ 2*f_{B78}-3*f_{B1} $	
	n78	15	-	REFSE NS	-	-	TDD	N/A	

EN-DC Configuration	EUTRA/NR band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	20 MHz (dBm)	40 MHz (dBm)	Duplex mode	IMD order	Single UL allowed
DC_1A-7A_n78A	1	N/A	-91.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B1} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	7	N/A	-88.2	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B1} $	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	1	N/A	-90.6	-	-	-	FDD	IMD4 $ 2*f_{B78}-2*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_1A-20A_n78A	1	N/A	-79.0	-	-	-	FDD	IMD3	
	20	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_1A-20A_n78A	1	N/A	REFSE NS	-	-	-	FDD	N/A	
	20	N/A	-93.3	-	-	-	FDD	IMD5	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_3A-5A_n78A	3	N/A	REFSE NS	-	-	-	FDD	N/A	
	5	N/A	-89.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B5} ^4$	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	3	N/A	-70.3	-	-	-	FDD	IMD2 $ f_{B78}-f_{B3} $	
	5	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	3	N/A	-88.3	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B3} ^4$	
				[TBD]			10.7 <sup>5</sup>		
DC_3C-7C_n78A	3	N/A	-78.7	-	-	-	FDD	IMD3 $ f_{B78}-2*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	3	N/A	-87.7	-	-	-	FDD	IMD4 $ 2*f_{B78}-2*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	

EN-DC Configuration	EUTRA/NR band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	20 MHz (dBm)	40 MHz (dBm)	Duplex mode	IMD order	Single UL allowed
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_3A-7A_n78A DC_3C-7A_n78A	3	N/A	-78.7	-	-	-	FDD	IMD3 $ f_{B78}-2*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_3A-7A_n78A DC_3C-7A_n78A	3	N/A	-87.7	-	-	-	FDD	IMD4 $ 2*f_{B78}-2*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_3A-20A_n78A DC_3C-20A_n78A	3	N/A	-79.0	-	-	-	FDD	IMD3 $ f_{B78}-2*f_{B20} $	
	20	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_5A-7A_n78A	5	N/A	-89.0	-	-	-	FDD	IMD4 $ f_{B78}-3*f_{B5} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	5	N/A	REFSE NS	-	-	-	FDD	N/A	
	7	N/A	-67.2	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	5	N/A	-67.1	-	-	-	FDD	IMD2 $ f_{B78}-f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	5	N/A	-94.0	-	-	-	FDD	IMD5 $ 2*f_{B78}-3*f_{B7} $	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_7A-20A_n78A	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	20	N/A	-65.8	-	-	-	FDD	IMD2 $ f_{B78}-f_{B7} $	
	n78	3370	-	REFSE NS	-	-	TDD	N/A	
DC_7A-20A_n78A	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	20	N/A	-93.3	-	-	-	FDD	IMD5 $ 2*f_{B78}-3*f_{B7} $	
	n78	15	-	REFSE NS	-	-	TDD	N/A	

EN-DC Configuration	EUTRA/ NR band	SCS (kHz)	5 MHz (dBm)	10 MHz (dBm)	20 MHz (dBm)	40 MHz (dBm)	Duplex mode	IMD order	Single UL allowed
DC_7A-20A_n78A	7	N/A	-66.5	-	-	-	FDD	IMD2 [f <sub>B78</sub> - f <sub>B20</sub> ]	
	20	N/A	REFSE NS	-	-	-	FDD	N/A	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
DC_7A-28A_n78A	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	28	N/A	-89.5	-	-	-		IMD2	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	7	N/A	REFSE NS	-	-	-	FDD	N/A	
	28	N/A	-94.8	-	-	-		IMD5	
	n78	15	-	REFSE NS	-	-	TDD	N/A	
	7	N/A	-66.8	-	-	-	FDD	IMD2	
	28	N/A	REFSE NS	-	-	-		N/A	
n78	15	-	REFSE NS	-	-	TDD	N/A		

NOTE 1: Both of the transmitters shall be set min (+20 dBm, P<sub>CMAX\_L,c</sub>) as defined in subclause 6.2.5A. In case Single UL is allowed and the UE only indicates support of "Single UL" the output power of the active UL shall be set at P<sub>CMAX\_L,c</sub> or set to the maximum output power according to the UE power scaling capability.

NOTE 2: RB<sub>START</sub> = 0

NOTE 3: For UEs only indicating support of Single UL, this requirement is verified with non-simultaneous uplink transmissions on the E-UTRA and NR CGs.

NOTE 4: This band is subject to IMD5 also which MSD is not specified.

NOTE 5: The symbol "REFSENS" in this table refers to the reference sensitivity values for single carrier specified in Table 7.3.5-1 of TS 36.521-1 for 2 antenna port E-UTRA band, Table 7.3\_1.5-1 of TS 36.521-1 for 4 antenna port E-UTRA band, Table 7.3.2.5-1 for 2 antenna port NR band and Table 7.3.2.5-2 for 4 antenna port NR band.

NOTE 6: No requirements apply when there is at least one individual RE within the intermodulation generated by the dual uplink is within the downlink transmission bandwidth of the Band 46. The reference sensitivity should only be verified when this is not the case (the requirements for Band 46 specified in the CA\_7A-46A in clause 7.3.1 of 36.101 apply).

Test tolerance is the same as given in Table 7.3B.2.3.1.5-2.

### 7.3B.3 $\Delta R_{IB,c}$ $\Delta R_{IBNC}$ for EN-DC

**Editor's Note:** Table number to be updated.

For the UE which supports inter-band EN-DC configuration, the minimum requirement for reference sensitivity in Table 7.3.1-1 and Table 7.3.1-1a in TS.36101[5], subclause 7.3.2, 7.3A.2, 7.3C.2 in TS 38.101-1[2] and subclause 7.3.2, 7.3A.2 in TS 38.101-2 [3] shall be increased by the amount given in  $\Delta R_{IB,c}$   $\Delta R_{IBNC}$  in Tables below where unless otherwise stated, the same  $\Delta R_{IB,c}$ ,  $\Delta R_{IBNC}$  are applicable to NR band(s) part for DC configurations which have the same NR operating band combination. Unless otherwise stated,  $\Delta R_{IB,c}$  or  $\Delta R_{IBNC}$  is set to zero.

In case the UE supports more than one of band combinations for CA, SUL or DC, and an operating band belongs to more than one band combinations then

- When the operating band frequency range is  $\leq 1$  GHz, the applicable additional  $\Delta R_{IB,c}$  shall be the average value for all band combinations defined in subclause 7.3A, 7.3B, 7.3C in this specification and 7.3A, 7.3B in TS 38.101-3 [4], truncated to one decimal place that apply for that operating band among the supported band combinations. In case there is a harmonic relation between low band UL and high band DL, then the maximum  $\Delta R_{IB,c}$  among the different supported band combinations involving such band shall be applied.
- When the operating band frequency range is  $> 1$  GHz, the applicable additional  $\Delta R_{IB,c}$  shall be the maximum value for all band combinations defined in subclause 7.3A, 7.3B, 7.3C in this specification and 7.3A, 7.3B in TS 38.101-3 [4] for the applicable operating bands.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.3B.3.

### 7.3B.3.1 Reference sensitivity $\Delta R_{IB,c}$ for Intra-band Contiguous EN-DC

FFS



7.3B.3.2 Reference sensitivity  $\Delta R_{IB,C}$  for Intra-band non-contiguous EN-DC

Table 7.3B.3.2-1: Intra-band non-contiguous EN-DC with one uplink configuration for reference sensitivity

DC configuration	Aggregated channel bandwidth (LTE+NR)	$W_{gap}$ / (MHz)	UL LTE allocation	$\Delta R_{IBNC}$ (dB)	Duplex mode
DC_3A_n3A	5MHz+5MHz	$45.0 < W_{gap} \leq 65.0$	12 <sup>1</sup>	4.7	FDD
		$0.0 < W_{gap} \leq 45.0$	25 <sup>1</sup>	0	
	5MHz+10MHz	$40.0 < W_{gap} \leq 60.0$	12 <sup>1</sup>	3.8	
		$0.0 < W_{gap} \leq 40.0$	25 <sup>1</sup>	0	
	5MHz+15MHz	$35.0 < W_{gap} \leq 55.0$	12 <sup>1</sup>	3.6	
		$0.0 < W_{gap} \leq 35.0$	25 <sup>1</sup>	0	
	5MHz+20MHz	$30.0 < W_{gap} \leq 50.0$	12 <sup>1</sup>	3.4	
		$0.0 < W_{gap} \leq 30.0$	25 <sup>1</sup>	0	
	5MHz+25MHz	$25.0 < W_{gap} \leq 45.0$	12 <sup>1</sup>	3.2	
		$0.0 < W_{gap} \leq 25.0$	25 <sup>1</sup>	0	
	5MHz+30MHz	$20.0 < W_{gap} \leq 40.0$	12 <sup>1</sup>	3.0	
		$0.0 < W_{gap} \leq 20.0$	25 <sup>1</sup>	0	
	10MHz+5MHz	$30.0 < W_{gap} \leq 60.0$	12 <sup>5</sup>	5.1	
		$0.0 < W_{gap} \leq 30.0$	32 <sup>1</sup>	0	
	10MHz+10MHz	$25.0 < W_{gap} \leq 55.0$	12 <sup>5</sup>	4.3	
		$0.0 < W_{gap} \leq 25.0$	32 <sup>1</sup>	0	
	10MHz+15MHz	$20.0 < W_{gap} \leq 50.0$	12 <sup>5</sup>	3.8	
		$0.0 < W_{gap} \leq 20.0$	32 <sup>1</sup>	0	
	10MHz+20MHz	$15.0 < W_{gap} \leq 45.0$	12 <sup>5</sup>	3.5	
		$0.0 < W_{gap} \leq 15.0$	32 <sup>1</sup>	0	
	10MHz+25MHz	$10.0 < W_{gap} \leq 40.0$	12 <sup>5</sup>	3.2	
		$0.0 < W_{gap} \leq 10.0$	32 <sup>1</sup>	0	
	10MHz+30MHz	$5.0 < W_{gap} \leq 35.0$	12 <sup>5</sup>	2.8	
		$0.0 < W_{gap} \leq 5.0$	32 <sup>1</sup>	0	
	15MHz+5MHz	$25.0 < W_{gap} \leq 55.0$	12 <sup>6</sup>	6.0	
		$0.0 < W_{gap} \leq 25.0$	32 <sup>1</sup>	0	
	15MHz+10MHz	$20.0 < W_{gap} \leq 50.0$	12 <sup>6</sup>	4.7	
		$0.0 < W_{gap} \leq 20.0$	32 <sup>1</sup>	0	
	15MHz+15MHz	$15.0 < W_{gap} \leq 45.0$	12 <sup>6</sup>	4.2	
		$0.0 < W_{gap} \leq 15.0$	32 <sup>1</sup>	0	
	15MHz+20MHz	$10.0 < W_{gap} \leq 40.0$	12 <sup>6</sup>	3.8	
		$0.0 < W_{gap} \leq 10.0$	32 <sup>1</sup>	0	
15MHz+25MHz	$5.0 < W_{gap} \leq 35.0$	12 <sup>6</sup>	3.5		
	$0.0 < W_{gap} \leq 5.0$	32 <sup>1</sup>	0		
15MHz+30MHz	$0.0 < W_{gap} \leq 30.0$	12 <sup>6</sup>	3.3		
20MHz+5MHz	$15.0 < W_{gap} \leq 50.0$	16 <sup>7</sup>	6.5		
	$0.0 < W_{gap} \leq 15.0$	32 <sup>1</sup>	0		
20MHz+10MHz	$10.0 < W_{gap} \leq 45.0$	16 <sup>7</sup>	5.1		
	$0.0 < W_{gap} \leq 10.0$	32 <sup>1</sup>	0		
20MHz+15MHz	$5.0 < W_{gap} \leq 40.0$	16 <sup>7</sup>	4.5		
	$0.0 < W_{gap} \leq 5.0$	32 <sup>1</sup>	0		
20MHz+20MHz	$0.0 < W_{gap} \leq 35.0$	16 <sup>7</sup>	4.1		
20MHz+25MHz	$0.0 < W_{gap} \leq 30.0$	16 <sup>7</sup>	3.8		
20MHz+30MHz	$0.0 < W_{gap} \leq 25.0$	16 <sup>7</sup>	3.6		

NOTE 1: <sup>1</sup> refers to the UL resource blocks shall be located as close as possible to the downlink operating band but confined within the transmission.  
 NOTE 2:  $W_{gap}$  is the sub-block gap between the two sub-blocks.  
 NOTE 3: The carrier centre frequency of PCC in the UL operating band is configured closer to the DL operating band.  
 NOTE 4: All combinations of channel bandwidths defined in Table 5.3B.1.3-1.  
 NOTE 5: <sup>5</sup> refers to the UL resource blocks shall be located at  $RB_{start}=25$ .  
 NOTE 6: <sup>6</sup> refers to the UL resource blocks shall be located at  $RB_{start}=35$ .  
 NOTE 7: <sup>7</sup> refers to the UL resource blocks shall be located at  $RB_{start}=50$ .

7.3B.3.3  $\Delta R_{IB,c}$  for Inter-band EN-DC within FR1

7.3B.3.3.1  $\Delta R_{IB,c}$  for Inter-band EN-DC in two bands within FR1

**Table 7.3B.3.3.1-1:  $\Delta R_{IB,c}$  due to EN-DC(two bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{B,c}$ (dB)
DC_1_n28	n28	0.2
DC_1_n51	n51	0.1
DC_1_n77	1	0.2
	n77	0.5
DC_1_n78	n78	0.5
DC_2_n66	2	0.3
	n66	0.3
DC_2_n78	2	0.2
	n78	0.5
DC_3_n51	3	0.2
	n51	0.2
DC_3_n77	3	0.2
	n77	0.5
DC_3_n78	3	0.2
	n78	0.5
DC_5_n78	5	0.2
	n78	0.5
DC_7_n51	n51	0.2
DC_7_n77	n77	0.5
DC_7_n78	n78	0.5
DC_8_n77	8	0.2
	n77	0.5
DC_8_n78	3	0.2
	n78	0.5
DC_11_n77	n77	0.5
DC_11_n78	n78	0.5
DC_12A_n5A	12	0.3
	n5	0.5
DC_12A_n66A	12	0.5
DC_18_n77	n77	0.5
DC_19_n77	n77	0.5
DC_19_n78	n78	0.5
DC_20_n51	n51	0.2
DC_20_n77	n77	0.5
DC_20_n78	n78	0.5
DC_21_n77	n77	0.5
DC_21_n78	n78	0.5
DC_25_n41	n41	0 <sup>f</sup>
		0.5 <sup>2</sup>
DC_26A_n77A	n77	0.5
DC_26_n78	n78	0.5
DC_28A_n51	n51	0.2
DC_28_n77	28	0.2
	n77	0.5
DC_28_n78	28	0.2
	n78	0.5
DC_28_n78	28	0.2
	n78	0.5
DC_30_n66	30	0.5
	n66	0.4
DC_38_n78	38	0.4
	n78	0.5
DC_39_n78	n78	0.5
DC_39_n79	n79	0.5
DC_40_n77	40	0.4
	n77	0.5
DC_41_n77	n77	0.5
DC_41_n78	n78	0.5
DC_41_n79	n79	0.5
DC_42_n51	n51	0.2
DC_66A_n78A	66	0.2
	n78	0.5

<p>NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690MHz. NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545MHz.</p>
--

7.3B.3.3.2  $\Delta R_{IB,c}$  for Inter-band EN-DC in three bands within FR1

**Table 7.3B.3.3.2-1:  $\Delta R_{IB,c}$  due to EN-DC (three bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-3_n28	n28	0.2
DC_1-3_n77	1	0.2
	3	0.2
	n77	0.5
DC_1-3_n78	1	0.2
	3	0.2
	n78	0.5
DC_1-5_n78	1	0.2
	5	0.2
	n78	0.5
DC_1-7_n28	n28	0.2
DC_1-7_n78	1	0.2
	7	0.2
	n78	0.5
DC_1-8_n78	8	0.2
	n78	0.5
DC_1-18_n77	n77	0.5
DC_1-18_n78	n78	0.5
DC_1-19_n77	n77	0.5
DC_1-19_n78	n78	0.5
DC_1-19_n79	1	0.3
	19	0.3
DC_1-20_n28	1	0.0
	20	0.2
	n28	0.2
DC_1-20_n78	n78	0.5
DC_1-21_n77	n77	0.5
DC_1-21_n78	1	0.2
	n78	0.5
DC_1-28_n77	28	0.2
	n77	0.5
DC_1-28_n78	28	0.2
	n78	0.5
DC_1_n28-n78	1	0
	n28	0.2
	n78	0.5
DC_1_n28-n79	1	0.3
	28	0.3
DC_1-42_n77	1	0.2
	42	0.5
	n77	0.5
DC_1-41_n77	n77	0.5
DC_1-41_n78	n78	0.5
DC_1-42_n78	1	0.2
	42	0.5
	n78	0.5
DC_1-42_n79	42	0.5
DC_1_n77-n79	1	0.2
	n77	0.5
	n79	0.0
DC_1_n78-n79	1	0.0
	n78	0.5
	n79	0.0
DC_1-SUL_n78-n84	n78	0.5
DC_2_5_n66	2	0.3
	n66	0.3
DC_2_30_n66	2	0.4
	30	0.5
	n66	0.4
DC_2-66_n71B	2	0.3
	66	0.3
DC_3_n3-n77	3	0.2
	n3	0.2

	n77	0.5
DC_3_n3-n78	3	0.2
	n3	0.2
	n78	0.5
DC_3-5_n78	3	0.2
	5	0.2
	n78	0.5
DC_3-7_n78, DC_3-7-7_n78	3	0.2
	7	0.2
	n78	0.5
DC_3-8_n78	3	0.2
	8	0.2
	n78	0.5
DC_3-19_n77	3	0.2
	n77	0.5
DC_3-19_n78	3	0.2
	n78	0.5
DC_3-19_n79	3	0
	19	0
	n79	0
DC_3-20_n78	3	0.2
	n78	0.5
DC_3-21_n77	3	0.3
	21	0.5
	n77	0.5
DC_3-21_n78	3	0.3
	21	0.5
	n78	0.5
DC_3-21_n79	3	0.3
	21	0.5
DC_3-28_n78	3	0.2
	n78	0.5
DC_3_n28-n78	3	0.2
	n28	0
	n78	0.5
DC_3-38_n78	3	0.2
	38	0.4
	n78	0.5
DC_3-41_n78	3	0.2
	41	0 <sup>1</sup>
	n78	0.5 <sup>2</sup>
DC_3-42_n77	3	0.2
	42	0.5
	n77	0.5
DC_3-42_n78	3	0.2
	42	0.5
	n78	0.5
DC_3-42_n79	3	0.2
	42	0.5
	n79	0
DC_3_n77-n79	3	0.2
	n77	0.5
	n79	0.0
DC_3_n78-n79	3	0.2
	n78	0.5
	n79	0.0
DC_3-SUL_n78-n80	3	0.2
	n78	0.5
DC_3-SUL_n78-n82	3	0.2
	n78	0.5
DC_5-7_n78	5	0.2
	7	0.2
	n78	0.5

DC_5_30_n66	30	0.5
	n66	0.4
DC_7-7_n78	7	0.0
	n78	0.5
DC_7-20_n28	20	0.2
	n28	0.2
DC_7-20_n78	n78	0.5
DC_7-28_n78	n78	0.5
DC_7_n28-n78	n78	0.5
DC_7-46_n78	n78	0.5
DC_8A-SUL_n78-n81	8	0.2
	n78	0.2
DC_18-28_n77	n77	0.5
	n78	0.5
	n77	0.5
DC_18-28_n78	n78	0.5
DC_19-21_n77	n77	0.5
DC_19-21_n78	n78	0.5
DC_19-42_n77	42	0.5
	n77	0.5
DC_19-42_n78	42	0.5
	n78	0.5
DC_19-42_n79	42	0.5
DC_19_n77-n79	19	0.0
	n77	0.5
	N79	0
DDC_19_n78-n79	19	0.0
	N78	0.5
	n79	0.0
DC_20_n8-n75	20	0.0
	n8	0.0
	n75	0.0
DC_20_n28-n75	20	0.0
	n28	0.2
	n75	0.0
DC_20_n28-n78	20	0.2
	n28	0.2
	n78	0.5
DC_20_n75-n78	20	0.0
	n75	0.0
	n78	0.5
DC_20_n76-n78	20	0.0
	n76	0.0
	n78	0.5
DC_20-SUL_n78-n82	n78	0.5
DC_20-SUL_n78-n83	20	0.2
	n78	0.5
DC_21-42_n77	42	0.5
	n77	0.5
DC_21-42_n78	42	0.5
	n78	0.5
DC_21-42_n79	42	0.5
DC_21_n77-n79	21	0.0
	n77	0.5
	n79	0.0
DC_21_n78-n79	21	0.0
	n78	0.5
	n79	0.0
DC_28-SUL_n78-n83	28	0.2
	n78	0.5
	n83	0.2
DC_28-42_n77	28	0.2
	42	0.5



	n77	0.5
DC_28-42_n78	28	0.2
	42	0.5
	n78	0.5
DC_28-42_n79	28	0.2
	42	0.5
DC_41-42_n77	42	0.5
	n77	0.5
DC_41-42_n78	42	0.5
	n78	0.5
DC_41-42_n79	42	0.5
DC_41_n77	n77	0.5
DC_41_n78	n78	0.5
DC_41_n79	n79	0.5
DC_66-SUL_n78-n86	66	0.2
	n78	0.5
NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690MHz.		
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545MHz.		

7.3B.3.3.3  $\Delta R_{IB,c}$  for Inter-band EN-DC in four bands within FR1

**Table 7.3B.3.3.3-1:  $\Delta R_{IB,c}$  due to EN-DC (four bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ [dB]
DC_1-3-5_n78	1	0.2
	3	0.2
	n78	0.5
DC_1-3-7_n28	n28	0.2
DC_1-3-7_n78 DC_1-3-7-7_n78	1	0.3
	3	0.3
	7	0.3
	n78	0.5
DC_1-3-8_n78	1	0.2
	3	0.2
	8	0.2
	n78	0.5
DC_1-3-28_n77	1	0.2
	3	0.2
	28	0.2
	n77	0.5
DC_1-3-28_n78 DC_1-3_n28-n78	1	0.2
	3	0.2
	28 or n28	0.2
	n78	0.5
DC_1-3-28_n79	1	0.2
	3	0.2
	28	0.2
DC_1-3-19_n78	1	0.2
	3	0.2
	n78	0.5
DC_1-3-20_n28	20	0.2
	n28	0.2
DC_1-3-20_n78	1	0.2
	3	0.2
	n78	0.5
DC_1-3-21_n77	1	0.2
	3	0.3
	21	0.5
	n77	0.5
DC_1-3-21_n78	1	0.2
	3	0.3
	21	0.5
	n78	0.5
DC_1-3-21_n79	3	0.3
	21	0.5
DC_1-3-42_n77	1	0.2
	3	0.2
	42	0.5
	n77	0.5
DC_1-3-42_n78	1	0.2
	3	0.2
	42	0.5
	n78	0.5
DC_1-3-42_n79	1	0.2
	3	0.2
	42	0.5
DC_1-5-7_n78 DC_1-5-7-7_n78	1	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_1-7-20_n28	20	0.2
	n28	0.2
DC_1-7-20_n78	1	0.2
	7	0.2
	20	0.2
	n78	0.5
DC_1-7_n28-n78	1	0.2

	7	0.2
	n28	0.2
	n78	0.5
DC_1-18-28_n77	n77	0.5
DC_1-18-28_n78	n78	0.5
DC_1-19-42_n77	1	0.2
	42	0.5
	n77	0.5
DC_1-19-42_n78	42	0.5
	n78	0.5
DC_1-19-42_n79	42	0.5
DC_1-20_n28-n78	1	0.0
	20	0.2
	n28	0.2
	n78	0.5
DC_1-21-42_n77	1	0.2
	42	0.5
	n77	0.5
DC_1-21-42_n78	42	0.5
	n78	0.5
DC_1-21-42_n79	42	0.5
DC_1-28-42_n77	1	0.2
	28	0.2
	42	0.5
	n77	0.5
DC_1-28-42_n78	28	0.2
	42	0.5
	n78	0.5
DC_1-28-42_n79	28	0.2
	42	0.5
DC_1-41-42_n78	42	0.5
	n78	0.5
DC_1-41-42_n79	42	0.5
DC_1-41-42_n79	42	0.5
DC_2-66-(n)71	2	0.3
	66	0.3
DC_3-5-7_n78, DC_3-5-7-7_n78	3	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_3-7-7_n78	3	0.2
	7	0.2
	n78	0.5
DC_3-7-20_n28	20	0.2
	n28	0.1
DC_3-7-20_n78	3	0.2
	7	0.2
	n78	0.5
DC_3-7-28_n78 DC_3-7_n28-n78	3	0.2
	7	0.2
	28 or n28	0.2
DC_3-19-21_n77	n78	0.5
	3	0.3
	21	0.5
DC_3-19-21_n78	n77	0.5
	3	0.3
	21	0.5
DC_3-19-21_n79	n78	0.5
	3	0.3
DC_3-19-21_n79	21	0.5
	3	0.2
	42	0.5
DC_3-19-42_n77	n77	0.5
	3	0.2
	42	0.5
DC_3-19-42_n78	0.2	0.2
	0.5	0.5

	0.5	0.5
DC_3-19-42_n79	3	0.2
	42	0.5
DC_3-20_n28-n78	3	0.2
	20	0.2
	n28	0.2
	n78	0.5
DC_3-21-42_n77	3	0.3
	21	0.5
	42	0.5
	n77	0.5
DC_3-21-42_n78	3	0.3
	21	0.5
	42	0.5
	n78	0.5
DC_3-21-42_n79	3	0.3
	21	0.5
	42	0.5
DC_3-28-42_n77	3	0.2
	28	0.2
	42	0.5
	n77	0.5
DC_3-28-42_n78	3	0.2
	28	0.2
	42	0.5
	n78	0.5
DC_3-28-42_n79	3	0.2
	28	0.2
	42	0.5
DC_5-7-7_n78	5	0.2
	7	0.2
	n78	0.5
DC_7-20_n28-n78	7	0.0
	20	0.2
	n28	0.2
	n78	0.5
DC_19-21-42_n77	42	0.5
	n77	0.5
DC_19-21-42_n78	42	0.5
	n78	0.5
DC_19-21-42_n79	42	0.5
DC_21-28-42_n77	28	0.2
	42	0.5
	n77	0.5
DC_21-28-42_n78	28	0.2
	42	0.5
	n78	0.5
DC_21-28-42_n79	28	0.2
	42	0.5

7.3B.3.3.4  $\Delta R_{IB,c}$  for Inter-band EN-DC in five bands within FR1

**Table 7.3B.3.3.4-1:  $\Delta R_{IB,c}$  due to EN-DC (five bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ [dB]
DC_1-3-5-7_n78, DC_1-3-5-7-7_n78	1	0.2
	3	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_1-3-7-20_n28	20	0.2
	n28	0.2
DC_1-3-7-20_n78	1	0.2
	3	0.2
	7	0.2
	n78	0.5
DC_1-3-7_n28-n78	1	0.2
	3	0.2
	7	0.2
	n28	0.2
DC_1-3-7_n78	n78	0.5
	1	0.2
	3	0.2
	7	0.2
DC_1-3-19-21-n77	1	0.2
	3	0.3
	21	0.5
	n77	0.5
DC_1-3-19-21_n78	1	0.2
	3	0.3
	21	0.5
	n78	0.5
DC_1-3-19-21_n79	3	0.3
	21	0.5
DC_1-3-19-42_n77	1	0.2
	3	0.2
	42	0.5
	n77	0.5
DC_1-3-19-42_n79	1	0.2
	3	0.2
	42	0.5
DC_1-3-28-42_n77	1	0.2
	3	0.2
	28	0.2
	42	0.5
DC_1-3-28-42_n78	n77	0.5
	1	0.2
	3	0.2
	28	0.2
DC_1-3-28-42_n79	42	0.5
	1	0.2
	3	0.2
	28	0.2
DC_1-3-20_n28-n78	42	0.5
	1	0.2
	3	0.2
	20	0.2
	n28	0.2
DC_1-3-21-42_n77	n78	0.5
	1	0.2
	3	0.3
	21	0.5
	42	0.5
DC_1-3-21-42_n78	n77	0.2
	1	0.2
	3	0.3
	21	0.5
	42	0.5
DC_1-3-21-42_n79	n78	0.2
	1	0.2
	3	0.3
	3	0.3

	21	0.5
	42	0.5
	n79	0.0
DC_1-7-20_n28-n78 DC	1	0.2
	7	0.2
	20	0.2
	n28	0.2
	n78	0.5
DC_1-19-21-42_n77	1	0.2
	42	0.5
	n77	0.5
DC_1-19-21-42_n78	42	0.5
	n78	0.5
DC_1-19-21-42_n79	42	0.5
DC_1-21-28-42_n77	1	0.2
	28	0.2
	42	0.5
	n77	0.5
DC_1-21-28-42_n78	28	0.2
	42	0.5
	n78	0.5
DC_1-21-28-42_n79 DC	28	0.2
	42	0.5
DC_3-7-20_n28-n78	3	0.2
	7	0.2
	20	0.2
	n28	0.2

7.3B.3.3.5  $\Delta R_{IB,c}$  for Inter-band EN-DC six bands within FR1

**Table 7.3B.3.3.5-1:  $\Delta R_{IB,c}$  due to EN-DC (six bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-3-7-20_n28-n78	1	0.2
	3	0.2
	7	0.2
	20	0.2
	n28	0.2
	n78	0.5

7.3B.3.4 Reference sensitivity for  $\Delta R_{IB,c}$  Inter-band EN-DC including FR2

FFS

7.3B.3.4.1 Reference sensitivity for  $\Delta R_{IB,c}$  Inter-band EN-DC in two bands including FR2

**Table 7.3B.3.4.1-1:  $\Delta R_{IB,c}$  due to EN-DC(two bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)



7.3B.3.4.2 Reference sensitivity for  $\Delta R_{IB,c}$  Inter-band EN-DC in three bands including FR2Table 7.3B.3.4.2-1:  $\Delta R_{IB,c}$  due to EN-DC (three bands)

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-18_n257	1	0.3
	18	0.3
DC_1-28_n257	28	0.2
DC_1-41_n257	1	0.5
	41	0.5
DC_1-42_n257	1	0
	42	0.5
DC_1-77_n257	1	0.2
	n77	0.5
DC_1-78_n257	1	0
	n78	0.5
DC_1-79_n257	1	0.0
	n79	0.0
DC_2-66_n257	2	0.3
	66	0.3
DC_3-21_n257	3	0.3
	21	0.5
DC_3-28_n257	n257	0.5
DC_3-41_n257	41	0 <sup>1</sup> /0.5 <sup>2</sup>
DC_3-42_n257	3	0.2
	42	0.5
DC_3-77_n257	3	0.2
	n77	0.5
DC_3-78_n257	3	0.2
	n78	0.5
DC_3-79_n257	3	0.0
	n79	0.0
DC_5_n78-n257	5	0.2
	n78	0.5
DC_7_n78-n257	7	0
	n78	0.5
DC_13-66_n260	13	0.3
	66	0.3
DC_19-42_n257	42	0.5
DC_19-77_n257	19	0.0
	n77	0.5
DC_19-78_n257	19	0.0
	n78	0.5
DC_19-79_n257	19	0.0
	n79	0.0
DC_21-42_n257	42	0.5
DC_21-77_n257	21	0.0
	n77	0.5
DC_21-78_n257	21	0.0
	n78	0.5
DC_21-79_n257	21	0.0
	n79	0.0
DC_28-42_n257	28	0.2
	42	0.5
DC_41-42_n257	42	0.5
NOTE 1: The requirement is applied for UE transmitting on the frequency range of 2545-2690MHz.		
NOTE 2: The requirement is applied for UE transmitting on the frequency range of 2496-2545MHz.		

7.3B.3.4.3 Reference sensitivity for  $\Delta R_{IB,c}$  Inter-band EN-DC in four bands including FR2Table 7.3B.3.4.3-1:  $\Delta R_{IB,c}$  due to EN-DC (four bands)

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-3-21_n257	3	0.3
	21	0.5
DC_1-3-28_n257	1	0.2
	3	0.2
	28	0.2
DC_1-3-42_n257	1	0.2
	3	0.2
	42	0.5
DC_1-3_n78-n257	1	0.2
	3	0.2
	n78	0.5
DC_1-5_n78-n257	1	0.2
	5	0.2
	n78	0.5
DC_1-7_n78-n257	1	0.2
	7	0.2
	n78	0.5
DC_1-19-42_n257	42	0.5
DC_1-21-28_n257	28	0.2
DC_1-21-42_n257	42	0.5
DC_1-28-42_n257	28	0.2
DC_1-41-42_n257	42	0.5
DC_3-5_n78-n257	3	0.2
	5	0.2
	n78	0.5
DC_3-7_n78-n257	3	0.2
	7	0.2
	n78	0.5
DC_19-21-42_n257	42	0.5
DC_3-19-21_n257	3	0.3
	21	0.5
DC_3-19-42_n257	3	0.2
	42	0.5
DC_3-21-42_n257	3	0.3
	21	0.5
	42	0.5
DC_3-28-42_n257	3	0.2
	28	0.2
	42	0.5
DC_5-7_n78-n257	5	0.2
	7	0.2
	n78	0.5
DC_7-7_n78-n257	n78	0.5
DC_21-28-42_n257	28	0.2
	42	0.5

7.3B.3.4.4 Reference sensitivity for  $\Delta R_{IB,c}$  Inter-band EN-DC in five bands including FR2**Table 7.3B.3.4.4-1:  $\Delta R_{IB,c}$  due to EN-DC (five bands)**

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-3-5_n78-n257	1	0.2
	3	0.2
	5	0.2
	n78	0.5
DC_1-3-7_n78-n257	1	0.3
	3	0.3
	7	0.3
	n78	0.5
DC_1-3-19-21_n257	3	0.3
	21	0.5
DC_1-3-19-42_n257	1	0.2
	3	0.2
	42	0.5
DC_1-3-21-42_n257	1	0.2
	3	0.3
	21	0.5
	42	0.5
DC_1-3-28-42_n257	1	0.2
	3	0.2
	28	0.2
	42	0.5
DC_1A-3A-28A-42C_n257A	1	0.2
	3	0.2
	28	0.2
	42	0.5
DC_1-5-7_n78-n257	1	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_1-7-7_n78-n257	1	0.2
	7	0.2
DC_1-7-7_n78-n257	n78	0.5
	DC_1-19-21-42_n257	42
DC_1-21-28-42_n257	28	0.2
	42	0.5
DC_3-5-7_n78-n257	3	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_3-7-7_n78-n257	3	0.2
	7	0.2
	n78	0.5
DC_5-7-7_n78-n257	5	0.2
	7	0.2
	n78	0.5

7.3B.3.4.5  $\Delta R_{IB,c}$  for EN-DC six bandsTable 7.3B.3.4.5-1:  $\Delta R_{IB,c}$  due to EN-DC (six bands)

Inter-band EN-DC configuration	E-UTRA or NR Band	$\Delta R_{IB,c}$ (dB)
DC_1-3-5-7_n78-n257	1	0.2
	3	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_1-3-7-7_n78-n257	1	0.3
	3	0.3
	7	0.3
	n78	0.5
DC_1-5-7-7_n78-n257	1	0.2
	5	0.2
	7	0.2
	n78	0.5
DC_3-5-7-7_n78-n257	3	0.2
	5	0.2
	7	0.2
	n78	0.5

## 7.4 Maximum Input Level

## 7.4B Maximum Input Level for EN-DC

## 7.4B.0 Minimum conformance requirement

## 7.4B.0.1 Intra-band contiguous EN-DC in FR1

Intra-band contiguous EN-DC maximum input level requirement and parameters are defined in Table 7.4B.0.1-1.

Table 7.4B.0.1-1: Maximum Input

Power in Largest CC, E-UTRA or NR, dBm	$X^1$
Power in each other CC, dBm	$X^1 - 10 \cdot \log_{10}(N_x \text{SCS}_x / N_y \text{SCS}_y)$
NOTE 1: Power in Largest E-UTRA or NR bandwidth CC, listed in Table 7.4-1 [2]	
NOTE 2: $N_x$ , $\text{SCS}_x$ is the number of RB's and Sub carrier spacing in the largest carrier bandwidth and could be LTE or NR carrier	
NOTE 3: $N_y$ , $\text{SCS}_y$ is the number of RB's in any other carrier.	
NOTE 4: For NR carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX}_L}$ at the minimum uplink configuration specified in Table 7.3.2-3 [2] with $P_{\text{CMAX}_L}$ as defined in subclause 6.2B.4.	
NOTE 5: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX}_L}$ at the minimum uplink configuration specified in Table 7.3.1-2 [5] with $P_{\text{CMAX}_L}$ as defined in subclause 6.2B.4.	

## 7.4B.0.2 Intra-band non-contiguous EN-DC in FR1

For the E-UTRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.4.1 for single carrier operation and in sub-clause 7.4.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.4 in [2].

## 7.4B.0.3 Inter-band EN-DC within FR1

Maximum input level requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.4.1 and 7.4.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.4 and 7.4A of [2] apply.

#### 7.4B.0.4 Inter-band EN-DC including FR2

Maximum input level requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.4.1 and 7.4.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.4 and 7.4A of [3] apply.

#### 7.4B.0.5 Inter-band EN-DC including both FR1 and FR2

Maximum input level requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.4.1 and 7.4.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.4 and 7.4A of [2] and [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.4B.

### 7.4B.1 Maximum Input Level for Intra-Band Contiguous EN-DC (2 CCs)

#### 7.4B.1.1 Test purpose

Maximum input level for intra-band contiguous EN-DC tests the UE's ability to receive data with a given average throughput for a specified reference measurement channel, under conditions of high signal level, ideal propagation and no added noise.

A UE unable to meet the throughput requirement under these conditions will decrease the coverage area near to an e-NodeB or a gNB.

#### 7.4B.1.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC operating in FR1.

#### 7.4B.1.3 Minimum conformance requirements

Refer to Clause 7.4B.0.1 for the intra-band contiguous EN-DC maximum input level requirement.

Exception requirements are defined for this test, therefore LTE agnostic approach is not applied, E-UTRA test point analysis is included and E-UTRA measurements are performed.

The normative reference for this requirement is TS 38.101-3 [4] Clause 7.4B.1

#### 7.4B.1.4 Test Description

##### 7.4B.1.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each intra-band contiguous EN-DC configuration specified in clause 5.3B.1.2, and are shown in table 7.4B.3.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2 for E-UTRA RMC for TDD, TS 36.521-1 [10] Annex A.2 for E-UTRA RMC for FDD, and TS 38.521-1 [8] Annex A.2 for NR RMC Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

Table 7.4B.1.4.1-1: Test configuration table

Initial Conditions								
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					Normal			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1					Mid range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE					Lowest, Mid, Highest			
Test SCS for the NR cell as specified in 38.521-1 [8] Table 5.3.5-1					Lowest			
Test Parameters for Intra-band Contiguous EN-DC Configuration								
Downlink Configuration					Uplink Configuration			
Test ID	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
1	CP-OFDM 64QAM	Full RB (NOTE 1)	CP-OFDM 64QAM	Full RB	DFT-s-OFDM QPSK	NOTE 2	QPSK	NOTE 3
2	CP-OFDM 256QAM	Full RB (NOTE 1)	CP-OFDM 256QAM	Full RB	DFT-s-OFDM QPSK	NOTE 2	QPSK	NOTE 3
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].								
NOTE 2: Same RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].								
NOTE 3: Same RB allocation shall be used per the E-UTRA band and channel BW as specified in Table 7.3.3-2 of TS 36.521[10].								

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508[11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0, C.1,C.2,C3.1 and TS 38.521-1 [8] Annex C.0,C.1,C.2,C3.1for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H.0,H.1,H.2,H.3.1 and TS 38.521-1 [8] Annex G.0,G.1,G.2,G.3.1 for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.4B.1.4.3.

#### 7.4B.1.4.2 Test Procedure

1. SS transmits PDSCH via PDCCH DCI format 1A and PDCCH DCI format 1\_1 for C\_RNTI to transmit the DL RMC according to Tables 7.4B.1.4.1 on the E-UTRA CC and NR CC, The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and PDCCH DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to Table 7.4B.1.4.1-1on the E-UTRA CC and NR CC. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
3. SS sets the Downlink signal level for the E-UTRA CC and NR CC to the value defined in Table 7.4B.1.5-1. SS sends continuously uplink power control "up" commands to the UE for the E-UTRA CC and NR CC until the E-

UTRA CC and NR CC output power are within  $-P_W \pm P_W$  dB of target level in Table 7.4B.1.5-1,  $P_W$  is the power window according to Table 7.4B.1.4.2-1 for the carrier frequency  $f$  and the channel bandwidth  $BW$ .

4. Measure the average throughput for each component carrier for duration sufficient to achieve statistical significance according to Annex H in TS 38.521-1 [8].

**Table 7.4B.1.4.2-1: Power Window (dB) for Maximum input level**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$BW \leq 20\text{MHz}$	1.4	1.7	2
$20\text{MHz} < BW \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < BW \leq 100\text{MHz}$	2.1	2.3	2.3

#### 7.4B.1.4.3 Message Contents

Message contents are according to TS 36.508-1[11] subclause 4.6.1 and TS 38.508-1 [6] subclause 4.6.1.

#### 7.4B.1.5 Test Requirement

For the NR CC, the throughput measurement of the carrier derived in test procedure shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels with parameters specified in Table 7.4B.1.5-1

Table 7.4B.1.5-1: Maximum input level requirement for each CC

Channel bandwidth of Largest BW CC	Rx Parameter			
	Power in the Largest CC	Power in the other CC	Power in the Largest CC	Power in the other CC
5 MHz	$-25^2 - TT$	$-25^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-27^3 - TT$	$-27^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
10 MHz	$-25^2 - TT$	$-25^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-27^3 - TT$	$-27^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
15 MHz	$-25^2 - TT$	$-25^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-27^3 - TT$	$-27^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
20 MHz	$-25^2 - TT$	$-25^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-27^3 - TT$	$-27^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
25 MHz	$-24^2 - TT$	$-24^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-26^3 - TT$	$-26^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
30 MHz	$-23^2 - TT$	$-23^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-25^3 - TT$	$-25^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
40 MHz	$-22^2 - TT$	$-22^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-24^3 - TT$	$-24^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
50 MHz	$-21^2 - TT$	$-21^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-23^3 - TT$	$-23^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
60 MHz	$-20^2 - TT$	$-20^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-22^3 - TT$	$-22^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
80 MHz	$-20^2 - TT$	$-20^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-22^3 - TT$	$-22^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
90 MHz	$-20^2 - TT$	$-20^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-22^3 - TT$	$-22^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$
100 MHz	$-20^2 - TT$	$-20^2 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$	$-22^3 - TT$	$-22^3 - 10 \cdot \log_{10}(N_x SCS_x / N_y SCS_y) - TT$

NOTE 1:  $N_x, SCS_x$  is the number of RB's and Sub carrier spacing in the largest carrier bandwidth and could be LTE or NR carrier.

NOTE 2: Reference measurement channel refers to Clauses A.3.2.3 or A.3.3.3 in TS 38.521-1[8] for 64-QAM NR Carrier, and to Tables A.3.2-3, A.3.2-4 for 64QAM in TS 36.521-1[10] for E-UTRA Carrier.

NOTE 3: Reference measurement channel refers to Clauses A.3.2.4 or A.3.3.4 in TS 38.521-1[8] for 256QAM NR Carrier, and Tables A.3.2-5, A.3.2-6 in TS 36.521-1[10] for 256QAM E-UTRA Carrier.

NOTE 4:  $N_y, SCS_y$  is the number of RB's in any other carrier

NOTE 5: For NR carrier, the transmitter shall be set to 4dB below  $P_{CMAX\_L}$  at the minimum uplink configuration specified in Table 7.3.2-3 in [2] with  $P_{CMAX\_L}$  as defined in subclause 6.2B.4.

NOTE 6: For E-UTRA carrier, the transmitter shall be set to 4dB below  $P_{CMAX\_L}$  at the minimum uplink configuration specified in Table 7.3.1-2 in [4] with  $P_{CMAX\_L}$  as defined in subclause 6.2B.4 for single carrier.

NOTE 7: TT for each frequency is specified in Table 7.4B.1.5-2

Table 7.4B.1.5-2: Test Tolerance (Maximum input level)

$f \leq 3.0\text{GHz}$	$3.0\text{GHz} < f \leq 6.0\text{GHz}$
0.7 dB	1.0 dB

## 7.4B.2 Maximum Input Level for Intra-Band Non-Contiguous EN-DC (2 CCs)

### 7.4B.2.1 Test purpose

Maximum input level for intra-band non-contiguous EN-DC tests the UE's ability to receive data with a given average throughput for a specified reference measurement channel, under conditions of high signal level, ideal propagation and no added noise.

A UE unable to meet the throughput requirement under these conditions will decrease the coverage area near to an e-NodeB or a gNB.



### 7.4B.2.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non contiguous EN-DC.

### 7.4B.2.3 Minimum conformance requirements

Refer to Clause 7.4B.0.2 for the intra-band non-contiguous EN-DC maximum input level requirement.

The normative reference for this requirement is TS 38.101-3 [4] Clause 7.4B.2, and 3GPP TS 38.101-1 [2] Clause 7.4, and 3GPP TS 36.101-1 [5] Clauses 7.4 and 7.4A

No exception requirements for E-UTRA CG and NR CG, LTE agnostic approach applies.

### 7.4B.2.4 Test Description

Same test description as in clause 7.4.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions in the initial test configuration.

- The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.3, all of these configurations shall be tested with applicable test parameters for each intra-band non-contiguous EN-DC configuration specified in clause 5.3B.1.3, and are shown in table 7.4B.2.4.1-1.

**Table 7.4B.2.4.1-1: Test configuration table**

Initial Conditions								
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					Normal			
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1					MaxWGap for intra-band non-contiguous EN-DC			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.3-1 across bandwidth combination sets supported by the UE					Lowest, Mid, Highest of Channel BW for NR CC			
Test SCS for the NR cell as specified in 38.521-1 [8] Table 5.3.5-1					Lowest			
Test Parameters for EN-DC Configuration								
Downlink Configuration					Uplink Configuration			
Test ID	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
1	CP-OFDM 64QAM	NOTE 1	NOTE 2	NOTE 2	DFT-s-OFDM QPSK	NOTE 1	NOTE 2	NOTE 2
2	CP-OFDM 256QAM	NOTE 1	NOTE 2	NOTE 2	DFT-s-OFDM QPSK	NOTE 1	NOTE 2	NOTE 2
NOTE 1: Same RB allocation shall be used per modulation as specified in Table 7.4.4.1-1 of TS 38.521-1[8].								
NOTE 2: Modulation and RB allocation for E-UTRA CC refers to the Table 4.6-2.								

The initial test configurations for E-UTRA band consist of environmental conditions, test frequencies, and channel bandwidths based on E-UTRA bands specified in Table 4.6-1 with the exception that

- E-UTRA test frequency are specified in Table 7.4B.2.4.1-1 based on intra-band non-contiguous EN-DC configuration specified in clause 5.3B.1.3.

For Initial conditions as in clause 7.4.4.1 in TS 38.521-1 [8] with the the following steps will be added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

Step 6 of Initial conditions as in clause 6.4.1.4.1 in TS 38.521-1 [8] is replaced by:

- 6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG according to TS 38.508 [6] clause 4.5.

7.4B.2.5 Test Requirement

Same test requirement as in clause 7.4.5 in TS 38.521-1 [8] for NR carrier.

7.4B.3 Maximum Input Level for Inter-band EN-DC within FR1

7.4B.3.1 Test purpose

Maximum input level for inter-band EN-DC tests the UE's ability to receive data with a given average throughput for a specified reference measurement channel, under conditions of high signal level, ideal propagation and no added noise.

A UE unable to meet the throughput requirement under these conditions will decrease the coverage area near to an e-NodeB or a gNB.

7.4B.3.2 Test applicability

This test applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC.

7.4B.3.3 Minimum conformance requirements

For inter-band EN-DC maximum input level is defined as the powers received at the UE antenna port over the Transmission bandwidth configuration of each CC in each CG, at which the specified relative throughput shall meet or exceed the minimum requirements for the specified reference measurement channel over each CC in each CG.

Maximum input level is defined as the maximum mean power received at the UE antenna port, at which the specified relative throughput shall meet or exceed the minimum requirements for the specified reference measurement channel. The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 (with one sided dynamic OCNG Pattern OP.1 FDD/TDD as described in Annex A.5.1.1/A.5.2.1) with parameters specified in Table 7.4-1.

Table 7.4-1: Maximum input level

Rx Parameter	Units	Channel bandwidth											
		5 MHz	10 MHz	15 MHz	20 MHz	25 MHz	30 MHz	40 MHz	50 MHz	60 MHz	80 MHz	90 MHz	100 MHz
Power in Transmission Bandwidth Configuration	dBm	-25 <sup>2</sup>				-24 <sup>2</sup>	-23 <sup>2</sup>	-22 <sup>2</sup>	-21 <sup>2</sup>	-20 <sup>2</sup>			
		-27 <sup>3</sup>				-26 <sup>3</sup>	-25 <sup>3</sup>	-24 <sup>3</sup>	-23 <sup>3</sup>	-22 <sup>3</sup>			
NOTE 1: The transmitter shall be set to 4dB below P <sub>CMAX,L</sub> at the minimum uplink configuration specified in Table 7.3-3 with P <sub>CMAX,L</sub> as defined in subclause 6.2.4.													
NOTE 2: Reference measurement channel is [TBD] for 64-QAM.													
NOTE 3: Reference measurement channel is [TBD] for 256-QAM.													

There is no exceptional requirement, LTE agnostic way is applied in the test.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.4B.3 and TS 38.101-1 clause 7.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

## 7.4B.3.4 Test Description

### 7.4B.3.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.4, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC configuration specified in clause 5.5B.4, and the configurations for NR carrier are shown in TS 38.521-1 [8] table 7.4.4.1-1, the configurations for E-UTRA carrier are shown in Table 4.6-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

1. Connect the SS to the UE antenna connectors as shown in TS 38.508-1 [5] Annex A, Figure A.3.1.1.1 for TE diagram and section A.3.2.1 for UE diagram. .
2. The parameter settings for the cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0, C.1,C.2,C3.1 and TS 38.521-1 [8] Annex C.0,C.1,C.2,C3.1 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H.0,H.1,H.2,H.3.1 and TS 38.521-1 [8] Annex G.0,G.1,G.2,G.3.1 for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.4B.3.4.3.
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

### 7.4B.3.4.2 Test Procedure

Same test procedure as specified in clause 7.4.4.2

### 7.4B.3.4.3 Message Contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

## 7.4B.3.5 Test Requirement

Same test requirement as specified in TS 38.521-1 [8] table 7.4.5.

## 7.5 Adjacent channel selectivity

### 7.5B Adjacent channel selectivity for EN-DC

#### 7.5B.0 Minimum Conformance Requirements

##### 7.5B.0.1 Intra-band contiguous EN-DC in FR1

Intra-band contiguous EN-DC ACS requirement and parameters are defined for test case 1 in Table 7.5B.0.1-1 and for test case 2 in Table 7.5B.0.1-2.

**Table 7.5B.0.1-1: ACS test case 1**

EN-DC Aggregated Bandwidth, MHz	<=100	>100, <=120	>120, <=140	>140, <=160
ACS, dB	X <sup>1</sup>	19.2	18.5	17.9
P <sub>interferer</sub> , dBm	P <sub>i</sub> <sup>2</sup>	Aggregated power + 17.7 dB	Aggregated power + 17 dB	Aggregated power + 16.4dB
P <sub>w</sub> in Transmission BW configuration, per CC, dBm	REFSENS +14dB			
NOTE 1: X is ACS level at the specified EN-DC aggregated Bandwidth from Table 7.5.1A-1 in [5]				
NOTE 2: P <sub>i</sub> is from Table 7.5.1A-2 in [5]				
NOTE 3: Jammer BW and offset is from Table 7.5.1A-2 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier				
NOTE 4: For NR carrier, the transmitter shall be set to 4dB below P <sub>CMAX_L,f,c</sub> at the minimum uplink configuration specified in Table 7.3.2-3 in [2] with P <sub>CMAX_L,f,c</sub> as defined in subclause 6.2B.4 from [4].				
NOTE 5: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>CMAX_L,c</sub> at the minimum uplink configuration specified in Table 7.3.1-2 in [5] with P <sub>CMAX_L,c</sub> as defined in subclause 6.2B.4 from [4] for single carrier.				

**Table 7.5B.0.1-2: ACS test case 2**

EN-DC Aggregated Bandwidth, BW <sub>agg</sub> , MHz	<=100	>100, <=120	>120, <=140	>140, <=160
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	P <sub>w</sub> <sup>1</sup>	-42.7 +10log <sub>10</sub> (N <sub>RB,cSCS/BW<sub>agg</sub></sub> )	-42 +10log <sub>10</sub> (N <sub>RB,cSCS/BW<sub>agg</sub></sub> )	-41.4 +10log <sub>10</sub> (N <sub>RB,cSCS/BW<sub>agg</sub></sub> )
P <sub>interferer</sub> , dBm	-25			
NOTE 1: P <sub>w</sub> is wanted signal power level at the specified EN-DC aggregated Bandwidth from Table 7.5.1A-3 in [5]				
NOTE 2: Jammer BW and offset is from Table 7.5.1A-3 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier				
NOTE 3: For NR carrier, the transmitter shall be set to 4dB below P <sub>CMAX_L,f,c</sub> at the minimum uplink configuration specified in Table 7.3.2-3 in [2] with P <sub>CMAX_L,f,c</sub> as defined in subclause 6.2B.4 from [4].				
NOTE 4: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>CMAX_L,c</sub> at the minimum uplink configuration specified in Table 7.3.1-2 in [5] with P <sub>CMAX_L,c</sub> as defined in subclause 6.2B.4 from [4] for single carrier.				

##### 7.5B.0.2 Intra-band non-contiguous EN-DC in FR1

For the E-UTRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.5.1 for single carrier operation and in sub-clause 7.5.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.5 in [2].

The blocker configuration is defined in the general sub-clause 7.1 in [4].

### 7.5B.0.3 Inter-band EN-DC within FR1

Adjacent channel selectivity requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.5.1 and 7.5.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.5 and 7.5A of [2] apply.

### 7.5B.0.4 Inter-band EN-DC including FR2

Adjacent channel selectivity requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.5.1 and 7.5.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.5 and 7.5A of [3] apply.

### 7.5B.0.5 Inter-band EN-DC including both FR1 and FR2

Adjacent channel selectivity requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.5.1 and 7.5.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.5 and 7.5A of [2] and [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.5B.1, 7.5B.2, 7.5B.3, 7.5B.4 and 7.5B.5.

## 7.5B.1 Adjacent Channel Selectivity for intra-band contiguous EN-DC (2 CCs)

**Editor's note: this clause is incomplete. The following aspects are either missing or not yet determined:**

- **The test point selection analysis is incomplete;**
- **Test configuration needs further investigation**
- **Test tolerance analysis is incomplete**
- **The modulated interferer bandwidth used in Test Procedure Step 4 has not been defined in Annex.**

### 7.5B.1.1 Test purpose

Adjacent channel selectivity (ACS) is a measure of a receiver's ability to receive an NR and E-UTRA signal at its assigned channel frequency in the presence of an adjacent channel signal at a given frequency offset from the centre frequency of the assigned channel. ACS is the ratio of the receive filter attenuation on the assigned channel frequency to the receive filter attenuation on the adjacent channel(s).

### 7.5B.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC.

### 7.5B.1.3 Minimum conformance requirements

Refer to Clause 7.5B.0.1 for the intra-band contiguous EN-DC in FR1.

Exception requirements are applicable for NR but not for E-UTRA within this test. LTE anchor agnostic approach is not applied. E-UTRA test points are defined and measurements performed over the aggregated EN-DC bandwidth.

### 7.5B.1.4 Test description

#### 7.5B.1.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10]

clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each intra-band contiguous EN-DC configuration specified in clause 5.5B.2, and are shown in table 7.5B.1.4.1-1.

The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2 for E-UTRA RMC for TDD, TS 36.521-1 [10] Annex A.2 for E-UTRA RMC for FDD, TS 38.521-1 [8] Annex A.2 for NR UL RMC and TS 38.521-1 [8] Annex A.3 for NR DL RMC. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 7.5B.1.4.1-1: Test configuration table**

Initial Conditions	
Test Environment as specified in TS 38.508-1 [6] subclause 4.1	TBD
Test Frequencies as specified in TS 38.508-1 [6] subclause 4.3.1	TBD
Test CC Combinations setting ( $N_{RB\_agg}$ ) as specified in TS 38.508-1 [6] subclause 4.3.1	TBD
Test SCS for the NR cell as specified in 38.521-1 [8] Table 5.3.5-1	TBD
Test Parameters for EN-DC Configuration	
FFS	

1. Connect the SS to the UE antenna connectors as shown in A.3.1.1 for SS diagram and A.3.2.1 for UE diagram in TS 38.508-1 [6].
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508[11] subclause 4.4.3, and parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.5B.1.4.3.

#### 7.5B.1.4.2 Test Procedure

1. SS transmits PDSCH via PDCCH DCI format 1\_1 for  $C\_RNTI$  to transmit the DL RMC on the NR CC according to Table 7.5B.1.4.1-1. SS transmits PDSCH via PDCCH DCI format 1A for  $C\_RNTI$  to transmit the DL RMC on the E-UTRA CC according to Table 7.5.4.1-1 in TS 36.521-1 [10]. The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0\_1 for  $C\_RNTI$  to schedule the UL RMC on the NR CC according to Table 7.5B.1.4.1-1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 for  $C\_RNTI$  to schedule the UL RMC on the E-UTRA CC according to Table 7.5.4.1-1 in TS 36.21-1 [10]. Since the UE has no payload data to send, the UE transmits uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level on the NR CC to the value as defined in Table 7.5.5-2 or Table 7.5.5-5 as appropriate in TS 38.521-1[8] (Case 1). Set the Downlink signal level on the E-UTRA CC to the value as defined in Table 7.5.5-2 in TS 36.521-1 [10] (Case 1). Send Uplink power control commands to the UE for the NR CC and E-UTRA CC (less or equal to 1dB step size should be used), to ensure that the UE output power is within  $-P_W \pm P_W$  dB of the target level in Table 7.5 B.0.11- (Case 1) for at least the duration of the Throughput measurement.

$P_W$  is the power window according to Table 7.5B.1.4.2-1 for the carrier frequency  $f$  and the channel bandwidth  $BW$ .

4. Set the Interferer signal level to the value as defined in Table 7.5B.0.1-1 (Case 1) and frequency below the wanted signal on the NR CC and E-UTRA CC, using a modulated interferer bandwidth as defined in Annex [TBD].
5. Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H.
6. Repeat steps from 3 to 5, using an interfering signal above the wanted signal in Case 1 at step 4.
7. Set the Downlink signal level on the NR CC to the value as defined in Table 7.5.5-3 or Table 7.5.5-6 as appropriate in TS 38. 521-1[8] (Case 2) . Set the Downlink signal level on the E-UTRA CC to the value as defined in Table 7.5.5-3 in TS 36.521-1 [10] (Case 2). Send Uplink power control commands to the UE for the NR CC and E-UTRA CC (less or equal to 1dB step size should be used), to ensure that the UE output power is within- $P_W \pm P_W$  dB of the target level in Table 7.5 B.0.1-2 (Case 2) for at least the duration of the Throughput measurement.

$P_W$  is the power window according to Table 7.5B.1.4.2-1 for the carrier frequency  $f$  and the channel bandwidth  $BW$ .

8. Set the Interferer signal level to the value as defined in Table 7.5B.0.1-2 (Case 2) and frequency below the wanted signal on the NR CC and E-UTRA CC, using a modulated interferer bandwidth as defined in Annex [TBD].
9. Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H
10. Repeat steps from 7 to 9, using an interfering signal above the wanted signal in Case 2 at step 8.
11. Repeat for applicable channel bandwidths and operating band combinations in both Case 1 and Case 2.

#### Table 7.5B.1.4.2-1: Power Window (dB) for ACS

[TBD]

#### 7.5B.1.4.3 Message Contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 7.5B.1.5 Test requirement

For the NR CC, the throughput measurement of the carrier derived in test procedure shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A.3 under the conditions specified in Table 7.5B.0.1-1, and also under the conditions specified in Table 7.5B.0.1-2.

## 7.5B.2 Adjacent Channel Selectivity for intra-band non-contiguous EN-DC (2 CCs)

**Editor's note: this clause is incomplete. The following aspects are either missing or not yet determined:**

- The test point selection analysis is incomplete
- Test configuration needs further investigation
- "MaxWGap" in "Table 7.5B.2.4.1-1: Test Configuration Table" need FFS

#### 7.5B.2.1 Test purpose

Same test purpose as sub-clause 7.5B.1.1

#### 7.5B.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC.

### 7.5B.2.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.5B.2.4 Test description

#### 7.5B.2.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.3, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each intra-band non-contiguous EN-DC configuration specified in clause 5.5B.3, and the configuration for NR carrier are shown in TS 38.521-1 [8] clause 7.5.4.1 with the following exceptions:

**Table 7.5B.2.4.1-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508 [7] subclause 4.3.1 for different DC bandwidth classes	[MaxWGap]
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 7.5B.2.4.1-1.

For Initial conditions as in clause 7.5.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.5.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state *RRC\_CONNECTED* with generic procedure parameters *Connectivity EN-DC*, *DC bearer MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

#### 7.5B.2.4.2 Test Procedure

Same test procedure as specified in clause 7.5.4.2 in TS 38.521-1 [8] with the following exceptions for E-UTRA anchor

On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.5B.2.4.3 Message Contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.



#### 7.5B.2.5 Test requirement

Same test requirement as specified in TS 38.521-1 [8] Clause 7.5.5.

### 7.5B.3 Adjacent Channel Selectivity for inter-band EN-DC within FR1 (2 CCs)

#### 7.5B.3.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

#### 7.5B.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.5B.3.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.5B.3.4 Test description

Same test description as in clause 7.5.4.2 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.5.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.5.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.5.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.5B.3.5 Test requirement

Same test requirement as specified in TS 38.521-1 [8] Clause 7.5.5.

### 7.5B.4 Adjacent Channel Selectivity for inter-band EN-DC including FR2

#### 7.5B.4.1 Adjacent Channel Selectivity for inter-band EN-DC including FR2 (2CCs)

**Editor's note: This test case is not complete. Following aspects are either missing or not yet determined:**

- MU and TT are FFS.
- Testability issue due to high PSD interferer has been identified.

#### 7.5B.4.1.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

#### 7.5B.4.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

#### 7.5B.4.1.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.5B.4.1.4 Test description

##### 7.5B.4.1.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.5.1, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-2 [9] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC including FR2 configuration specified in clause 5.5B.5.1, and the configuration for NR carrier are shown in TS 38.521-2 [9] Table 7.5.4.1-1.

For initial conditions as in clause 7.5.4.1 in TS 38.521-2 [9], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of initial conditions as in clause 7.5.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

##### 7.5B.4.1.4.2 Test Procedure

Same test procedure as specified in clause 7.5.4.2 in TS 38.521-2 [9] with the following exceptions for E-UTRA anchor

On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

##### 7.5B.4.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

##### 7.5B.4.1.5 Test requirement

Same test requirement as specified in TS 38.521-2 [9] Clause 7.5.5.

## 7.5B.4.2 Adjacent Channel Selectivity for inter-band EN-DC including FR2 (3CCs)

Editor's note: This test case is not complete. Following aspects are either missing or not yet determined:

- Working assumption: to avoid LTE CA testing in inter-band EN-DC including FR2 and only PCC band is configured.
- MU and TT are FFS.
- [Table 7.5A.4.1-1] in TS 38.521-2 [9] where the configuration for NR CA carriers are shown is FFS.
- [clause 7.5A.4.1] in TS 38.521-2 [9] where the initial conditions for NR CA is FFS.
- [clause 7.5A.4.2] in TS 38.521-2 [9] where the test procedure for NR CA is FFS.
- [Clause 7.5A.5] in TS 38.521-2 [9] where the test requirements for NR CA is FFS.
- [Clause 7.5A] in TS 38.521-2 [9] where the test description for NR CA is FFS.
- How to choose the LTE anchor when LTE CA is implemented is FFS.

### 7.5B.4.2.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

### 7.5B.4.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 (3CCs).

### 7.5B.4.2.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.5B.4.2.4 Test description

- For inter-band of “single carrier LTE + 2DL FR2 CA”, the test description of 2DL FR2 CA for adjacent channel selectivity is the same as in corresponding section [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “2DL LTE CA + single carrier FR2”, the test description of single carrier FR2 for adjacent channel selectivity is the same as in corresponding section 7.5 in TS 38.521-2 [9] for FR2 with the exceptions described below.

#### 7.5B.4.2.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.5.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-2 [9] clause 5.3 or clause 5.3A and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2 or clause 5.4.2A. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC including FR2 configuration specified in clause 5.5B.5.2, and the configuration for NR carrier are shown in TS 38.521-2 [9] Table 7.5.4.1-1 or [Table 7.5A.4.1-1].

For initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state *RRC\_CONNECTED* with generic procedure parameters *Connectivity EN-DC*, *DC bearer MCG* and *SCG*, *Connected without release On* according to TS 38.508-1 [6] clause 4.5.

#### 7.5B.4.2.4.2 Test Procedure

Same test procedure as specified in clause 7.5.4.2 or [clause 7.5A.4.2] in TS 38.521-2 [9] with the following exceptions for E-UTRA anchor

On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set *TimeAlignmentTimerDedicated* IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.5B.4.2.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6.1.

#### 7.5B.4.2.5 Test requirement

Same test requirement as specified in TS 38.521-2 [9] Clause 7.5.5 or [Clause 7.5A.5].

### 7.5B.4.3 Adjacent Channel Selectivity for inter-band EN-DC including FR2 (4CCs)

**Editor's note: This test case is not complete. Following aspects are either missing or not yet determined:**

- Working assumption: to avoid LTE CA testing in inter-band EN-DC including FR2 and only PCC band is configured.
- MU and TT are FFS.
- [Table 7.5A.4.1-1] in TS 38.521-2 [9] where the configuration for NR CA carriers are shown in FFS.
- [clause 7.5A.4.1] in TS 38.521-2 [9] where the initial conditions for NR CA in FFS.
- [clause 7.5A.4.2] in TS 38.521-2 [9] where the test procedure for NR CA in FFS.
- [Clause 7.5A.5] in TS 38.521-2 [9] where the test requirements for NR CA in FFS.
- [Clause 7.5A] in TS 38.521-2 [9] where the test description for NR CA is FFS.
- How to choose the LTE anchor when LTE CA is implemented is FFS.

#### 7.5B.4.3.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

#### 7.5B.4.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 (4CCs).

#### 7.5B.4.3.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.5B.4.3.4 Test description

- For inter-band of “single carrier LTE + 3DL FR2 CA”, the test description of 3DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “2DL LTE CA + 2DL FR2 CA”, the test description of 2DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “3DL LTE CA + single carrier FR2”, the test description of single carrier FR2 for adjacent channel selectivity is the same as in corresponding section of clause 7.5 in TS 38.521-2 [9] for FR2 with the exceptions described below.

#### 7.5B.4.3.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.5.3, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-2 [9] clause 5.3 or clause 5.3A and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2 or clause 5.4.2A. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC including FR2 configuration specified in clause 5.5B.5.3, and the configuration for NR carrier are shown in TS 38.521-2 [9] Table 7.5.4.1-1 or [Table 7.5A.4.1-1].

For initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

#### 7.5B.4.3.4.2 Test Procedure

Same test procedure as specified in clause 7.5B.4.2.4.2.

#### 7.5B.4.3.4.3 Message contents

Same message contents as specified in clause 7.5B.4.2.4.3.

#### 7.5B.4.3.5 Test requirement

Same test requirement as specified in clause 7.5B.4.2.5.

### 7.5B.4.4 Adjacent Channel Selectivity for inter-band EN-DC including FR2 (5CCs)

**Editor's note:** This test case is not complete. Following aspects are either missing or not yet determined:

- Working assumption: to avoid LTE CA testing in inter-band EN-DC including FR2 and only PCC band is configured.
- MU and TT are FFS.
- [Table 7.5A.4.1-1] in TS 38.521-2 [9] where the configuration for NR CA carriers are shown is FFS.

- [clause 7.5A.4.1] in TS 38.521-2 [9] where the initial conditions for NR CA is FFS.
- [clause 7.5A.4.2] in TS 38.521-2 [9] where the test procedure for NR CA is FFS.
- [Clause 7.5A.5] in TS 38.521-2 [9] where the test requirements for NR CA is FFS.
- [Clause 7.5A] in TS 38.521-2 [9] where the test description for NR CA is FFS.
- How to choose the LTE anchor when LTE CA is implemented is FFS.

#### 7.5B.4.4.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

#### 7.5B.4.4.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 (5CCs).

#### 7.5B.4.4.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.5B.4.4.4 Test description

- For inter-band of “single carrier LTE + 4DL FR2 CA”, the test description of 4DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “2DL LTE CA + 3DL FR2 CA”, the test description of 3DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “3DL LTE CA + 2DL FR2 CA”, the test description of 2DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “4DL LTE CA + single carrier FR2”, the test description of single carrier FR2 for adjacent channel selectivity is the same as in corresponding section of clause 7.5 in TS 38.521-2 [9] for FR2 with the exceptions described below.

##### 7.5B.4.4.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.2B.5.4, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-2 [9] clause 5.3 or clause 5.3A and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2 or clause 5.4.2A. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC including FR2 configuration specified in clause 5.5B.5.4, and the configuration for NR carrier are shown in TS 38.521-2 [9] Table 7.5.4.1-1 or [Table 7.5A.4.1-1].

For initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

#### 7.5B.4.4.4.2 Test Procedure

Same test procedure as specified in clause 7.5B.4.2.4.2.

#### 7.5B.4.4.4.3 Message contents

Same message contents as specified in clause 7.5B.4.2.4.3.

#### 7.5B.4.4.5 Test requirement

Same test requirement as specified in clause 7.5B.4.2.5.

### 7.5B.4.5 Adjacent Channel Selectivity for inter-band EN-DC including FR2 (6CCs)

**Editor's note:** This test case is not complete. Following aspects are either missing or not yet determined:

- Working assumption: to avoid LTE CA testing in inter-band EN-DC including FR2 and only PCC band is configured.
- MU and TT are FFS.
- [Table 7.5A.4.1-1] in TS 38.521-2 [9] where the configuration for NR CA carriers are shown is FFS.
- [clause 7.5A.4.1] in TS 38.521-2 [9] where the initial conditions for NR CA is FFS.
- [clause 7.5A.4.2] in TS 38.521-2 [9] where the test procedure for NR CA is FFS.
- [Clause 7.5A.5] in TS 38.521-2 [9] where the test requirements for NR CA is FFS.
- [clause 5.2B.5.5] where EN-DC operating bands have been specified is FFS.
- [Clause 7.5A] in TS 38.521-2 [9] where the test description for NR CA is FFS.
- How to choose the LTE anchor when LTE CA is implemented is FFS.

#### 7.5B.4.5.1 Test purpose

Same test purpose as in clause 7.5B.1.1.

#### 7.5B.4.5.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2 (6CCs).

#### 7.5B.4.5.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.5B.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.5B.4.5.4 Test description

- For inter-band of “single carrier LTE + 5DL FR2 CA”, the test description of 5DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “2DL LTE CA + 4DL FR2 CA”, the test description of 4DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “3DL LTE CA + 3DL FR2 CA”, the test description of 3DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “4DL LTE CA + 2DL FR2 CA”, the test description of 2DL FR2 CA for adjacent channel selectivity is the same as in corresponding section of clause [7.5A] in TS 38.521-2 [9] for FR2 with the exceptions described below.
- For inter-band of “5DL LTE CA + single carrier FR2”, the test description of single carrier FR2 for adjacent channel selectivity is the same as in corresponding section of clause 7.5 in TS 38.521-2 [9] for FR2 with the exceptions described below.

#### 7.5B.4.5.4.1 Initial Condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in [clause 5.2B.5.5], channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-2 [9] clause 5.3 or clause 5.3A and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2 or clause 5.4.2A. All of these configurations shall be tested with applicable test parameters for each inter-band EN-DC including FR2 configuration specified in clause 5.5B.5.5, and the configuration for NR carrier are shown in TS 38.521-2 [9] Table 7.5.4.1-1 or [Table 7.5A.4.1-1].

For initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS 36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of initial conditions as in clause 7.5.4.1 or [clause 7.5A.4.1] in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5.

#### 7.5B.4.5.4.2 Test Procedure

Same test procedure as specified in clause 7.5B.4.2.4.2.

#### 7.5B.4.5.4.3 Message contents

Same message contents as specified in clause 7.5B.4.2.4.3.

#### 7.5B.4.5.5 Test requirement

Same test requirement as specified in clause 7.5B.4.2.5.



## 7.5B.5 Adjacent Channel Selectivity for inter-band EN-DC including both FR1 and FR2 (3 CCs)

### 7.5B.5.1 Test purpose

Same test purpose as in 7.5.1 in TS 38.521-1 [8] for NR FR1 carrier and 7.5.1 in TS 38.521-2 [9] for NR FR2 carrier.

### 7.5B.5.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 and E-UTRA in conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The NSA requirements for adjacent channel selectivity apply and are tested as part of the EN-DC within FR1 and EN-DC including FR2 test cases in clause 7.5B.

## 7.6 Blocking characteristics

### 7.6B Blocking characteristics for EN-DC

#### 7.6B.1 General

The blocking characteristic for EN-DC in FR1 is a measure of the receiver's ability of an UE that support EN-DC in FR1 to receive a wanted signal at its assigned channel frequency in the presence of an unwanted interferer on frequencies other than those of the spurious response or the adjacent channels, without this unwanted input signal causing a degradation of the performance of the receiver beyond a specified limit. The blocking performance shall apply at all frequencies except those at which a spurious response occur.

#### 7.6B.2 Inband blocking for EN-DC

##### 7.6B.2.0 Minimum Conformance Requirements

##### 7.6B.2.0.1 Intra-band contiguous EN-DC

Intra-band contiguous EN-DC in-band blocking requirement and parameters are defined in Table 7.6B.2.0.1-1.

**Table 7.6B.2.0.1-1: In-band blocking for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	<=100	>100, <=120	>120, <=140	>140, <=160
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	P <sub>w</sub> <sup>1</sup>	16.8	17.5	18
NOTE 1: P <sub>w</sub> is wanted signal power level at the specified EN-DC aggregated Bandwidth from Table 7.6.1.1A-1 in [5].				
NOTE 2: Interferer values are specified from Table 7.6.1.1A-2 in [5].				
NOTE 3: Jammer BW and offset is from Table 7.6.1.1A-1 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier.				
NOTE 4: For NR carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,f,c</sub> at the minimum uplink configuration specified in Table 7.3.2-3 [2] with P <sub>C<sub>MAX</sub>L,f,c</sub> as defined in subclause 6.2.B.				
NOTE 5: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,c</sub> at the minimum uplink configuration specified in Table 7.3.1-2 [5] with P <sub>C<sub>MAX</sub>L,c</sub> as defined in subclause 6.2.B.4 for single carrier.				

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.2.1.

### 7.6B.2.0.2 Intra-band non-contiguous EN-DC

For the E-TRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.6.1.1 for single carrier operation and in sub-clause 7.6.1.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.6.2 in [2].

The blocker configuration is defined in the general sub-clause 7.1.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.2.2.

### 7.6B.2.0.3 Inter-band EN-DC within FR1

Inband blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.1.1 and 7.6.1.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.2 and 7.6A.2 of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.2.3.

### 7.6B.2.0.4 Inter-band EN-DC including FR2

Inband blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.1.1 and 7.6.1.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.2 and 7.6A.2 of [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.2.4.

### 7.6B.2.0.5 Inter-band EN-DC including both FR1 and FR2

Inband blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.1.1 and 7.6.1.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.2 and 7.6A.2 of [2] and [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.2.5.

### 7.6B.2.1 Inband blocking for intra-band contiguous EN-DC (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- MU is TBD in Annex F

#### 7.6B.2.1.1 Test Purpose

In-band blocking is defined for an unwanted interfering signal falling into the range from 15MHz below to 15MHz above the UE receive band, at which the relative throughput shall meet or exceed the requirement for the specified measurement channels. The lack of in-band blocking ability will decrease the coverage area when other NodeB transmitters exist (except in the adjacent channels and spurious response).

#### 7.6B.2.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC in FR1.

#### 7.6B.2.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.2.0.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

## 7.6B.2.1.4 Test Description

## 7.6 B.2.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 7.6B.2.1.4.1-1. The details of the uplink and downlink reference measurement channels (RMCs) are specified in Annex A.2 and A.3 respectively. The details of the OCNG patterns used are specified in TS 36.521-1 [10] Annex A.5 and in TS 38.521-1 [8] Annex A.5 for E-UTRA CG and NR CG respectively. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 7.6B.2.1.4.1-1: Test configuration table**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal			
Test Frequencies as specified in TS38.508-1 [6] clause 4.3.1 for different EN-DC bandwidth classes				Mid range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE				Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$ (NOTE 3)			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]				Lowest			
NR/E-UTRA Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	REFSENS	QPSK	REFSENS
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							
NOTE 2: Test Channel Bandwidths are checked separately for each EN-DC band, which applicable channel bandwidths are specified in Table 5.3B.1.2-1.							
NOTE 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.							
NOTE 4: REFSENS refers to Uplink configuration in Table 7.3.2.3-3 in [8] and Table 7.3.3-2 in [10] for NR and E-UTRA CC respectively.							

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 Annex A, in Figure [A.3.1.4.1] for SS diagram and section A.3.2 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C and TS 38.521-1 [8] Annex C for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL and DL Reference Measurement channels are TS 36.521-1 [10] Annex A.2, A.3 and TS 38.521-1 [8] Annex A.2, A.3 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.6B.2.1.4.3.

7.6B.2.1.4.2 Test procedure

1. SS transmits PDSCH via PDCCH DCI format 1A and PDCCH DCI format 1\_1 for C\_RNTI to transmit the DL RMC according to Table 7.6B.2.1.4.1-1 on E-UTRA CC and NR CC respectively. The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 7.6B.2.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level to the value as defined in Table 7.6B.2.1.5-1. Send Uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that for at least the duration of the Throughput measurement:

The E-UTRA CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.2.1.5-1 +  $[10\log(P_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.2.1.5-2 for the carrier frequency  $f$ . The NR CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.2.1.5-1 +  $[10\log(S_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.2.1.5-3 for the carrier frequency  $f$  and the channel bandwidth BW.

4. Set the parameters of the signal generator for an interfering signal below the aggregated component carriers in Case 1 according to Table 7.6B.2.1.5-1.
5. Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H.2.
6. Repeat steps from 4 to 5, using an interfering signal above the aggregated component carriers in Case 1 at step 4.
7. Repeat steps from 4 to 6, using interfering signals in Case 2 at step 4 and 6.

7.6B.2.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6 Table 4.6.3-118 with condition TRANSFORM\_PRECODER\_ENABLED.

7.6B.2.1.5 Test Requirement

The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in TS 36.521-1 [10] Annex A.3 and TS 38.521-1 [8] Annex A.3 for E-UTRA CG and NR CG respectively with parameters specified in Table 7.6B.2.1.5-1 for the specified wanted signal mean power in the presence of interfering signals.

**Table 7.6B.2.1.5-1: In-band blocking for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	P <sub>w</sub> <sup>1</sup>	16.8	17.5	18

NOTE 1:	$P_w$ is wanted signal power level at the specified EN-DC aggregated Bandwidth from Table 7.6.1.1A-1 in [5].
NOTE 2:	Interferer values are specified from Table 7.6.1.1A-2 in [5].
NOTE 3:	Jammer BW and offset is from Table 7.6.1.1A-1 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier.
NOTE 4:	For NR carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,f,c}}$ at the minimum uplink configuration specified in Table 7.3.2-3 with $P_{\text{CMAX\_L,f,c}}$ as defined in subclause 6.2.4 from [2].
NOTE 5:	For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,c}}$ at the minimum uplink configuration specified in Table 7.3.1-2 with $P_{\text{CMAX\_L,c}}$ as defined in subclause 6.2.5 for single carrier and in Table 7.3.1A-1 with $P_{\text{CMAX\_L}}$ as defined in subclause 6.2.5A for LTE-CA from [5].

**Table 7.6B.2.1.5-2: Power Window (dB) for E-UTRA CC**

$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$
1.7	2.0
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.	

**Table 7.6B.2.1.5-3: Power Window (dB) for NR CC**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 20\text{MHz}$	1.4	1.7	2.0
$20\text{MHz} < \text{BW} \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	2.1	2.3	2.3
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.			

## 7.6B.2.2 Inband blocking for intra-band non-contiguous EN-DC (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **MU is TBD in Annex F**

### 7.6B.2.2.1 Test Purpose

Same test purpose as in clause 7.6.2.1 in TS 38.521-1 [8] for the NR carrier.

### 7.6B.2.2.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC in FR1.

### 7.6B.2.2.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.2.0.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.6B.2.2.4 Test Description

Same test description as in clause 7.6.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

**Table 7.6B.2.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different EN-DC bandwidth classes	High with maxWGap
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1 except for the parameters specified in Table 7.6B.2.2.4-1.

For Initial conditions as in clause 7.6.2.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.2.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.2.2.5 Test Requirement

Same test requirement as in clause 7.6.2.5 in TS 38.521-1 [8].

### 7.6B.2.3 Inband blocking for inter-band EN-DC within FR1 (2 CCs)

#### 7.6B.2.3.1 Test Purpose

Same test purpose as in clause 7.6.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.6B.2.3.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.6B.2.3.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.2.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.6B.2.3.4 Test Description

Same test description as in clause 7.6.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.6.2.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.2.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.2.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.2.3.5 Test Requirement

Same test requirement as in clause 7.6.2.5 in TS 38.521-1 [8].

### 7.6B.2.4 Inband blocking for inter-band EN-DC including FR2

#### 7.6B.2.4.1 Inband blocking for inter-band EN-DC including FR2 (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- MU/TT are FFS.
- UL power level configuration is TBD.
- Throughput calculation procedure is TBD (measurement period as well as dependencies with polarizations).

##### 7.6B.2.4.1.1 Test Purpose

Same test purpose as in clause 7.6.2.1 in TS 38.521-2 [9] for the NR carrier.

##### 7.6B.2.4.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC including FR2.

##### 7.6B.2.4.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.2.0.4.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 7.6B.2.4.1.4 Test Description

Same test description as in clause 7.6.2.4 in TS 38.521-2 [9] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.6.2.4.1 in TS 38.521-2 [9], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.2.4.1 in TS 38.521-2 [9] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.2.4.1 in TS 38.521-2 [9] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.2.4.1.5 Test Requirement

Same test requirement as in clause 7.6.2.5 in TS 38.521-2 [9].

### 7.6B.2.5 Inband blocking for inter-band EN-DC including both FR1 and FR2

#### 7.6B.2.5.1 Test purpose

Same test purpose as in clause 7.6.2.1 in TS 38.521-1 [8] for NR FR1 carrier and clause 7.6.2.1 in TS 38.521-2 [9] for NR FR2 carrier.

#### 7.6B.2.5.2 Test applicability

The requirements in this test are not testable due to issues with combined testing of NR FR1 and E-UTRA in conducted mode with NR FR2 in radiated mode. Therefore, the conducted and radiated requirements are tested separately.

No test case details are specified. The NSA requirements for Inband blocking apply and are tested as part of the EN-DC within FR1 and EN-DC including FR2 test cases in clause 7.6B.2.

## 7.6B.3 Out-of-band blocking for EN-DC

### 7.6B.3.0 Minimum Conformance Requirements

#### 7.6B.3.0.1 Intra-band contiguous EN-DC

Intra-band contiguous EN-DC out-of-band requirement and parameters are defined in Table 7.6B.3.1-1.

**Table 7.6B.3.0-1: Out-of-band blocking for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
Pw in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	9			
NOTE 1: Interferer values and offsets are specified from Table 7.6.2.1A-2 in [5].				
NOTE 2: For NR carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,f,c}}$ at the minimum uplink configuration specified in Table 7.3.2-3 [2] with $P_{\text{CMAX\_L,f,c}}$ as defined in subclause 6.2B.4.				
NOTE 3: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,c}}$ at the minimum uplink configuration specified in Table 7.3.1-2 [5] with $P_{\text{CMAX\_L,c}}$ as defined in subclause 6.2B.4 for single carrier.				

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.3.1.

#### 7.6B.3.0.2 Intra-band non-contiguous EN-DC

For the E-UTRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.6.2.1 for single carrier operation and in sub-clause 7.6.2.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.6.3 in [2].

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.3.2.



### 7.6B.3.0.3 Inter-band EN-DC within FR1

Out-of-band blocking requirements for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.2.1 and 7.6.2.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.3 and 7.6A.3 of [2] apply for lowest level EN-DC fallbacks (two bands) in section 5.2B.4.1 with following conditions:

- one E-UTRA uplink carrier with the output power set to 4dB below  $P_{\text{CMAX}_L}$  and the NR band whose downlink is being tested has its uplink carrier output power set to minimum output power as defined in sub-clause 6.3.1 of [2].
- one NR uplink carrier with the output power set to 4dB below  $P_{\text{CMAX}_L}$  on the NR band with both E-UTRA and NR downlinks being tested with E-UTRA output power set to minimum output power as defined in sub-clause 6.3.2.1 of [5].

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.3.3.

### 7.6B.3.0.4 Inter-band EN-DC including FR2

Out-of-band blocking requirements specified for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.2.1 and 7.6.2.1A of [5] apply for lowest level EN-DC fallbacks (two bands) in section 5.2B.5.1 with only E-UTRA UL with output power as in TS 36.101 [5] (4dB below  $P_{\text{CMAX}_L}$ ).

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.3.4.

### 7.6B.3.0.5 Inter-band EN-DC including both FR1 and FR2

Out-of-band blocking requirements specified for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.2.1 and 7.6.2.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.3 and 7.6A.3 of [2] apply for lowest level EN-DC fallbacks (three bands) in section 5.2B.6.2 with only E-UTRA UL with output power as in TS 36.101 [5] (4dB below  $P_{\text{CMAX}_L}$ ).

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.3.5.

### 7.6B.3.1 Out-of-band blocking for intra-band contiguous EN-DC (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **MU is TBD in Annex F**

#### 7.6B.3.1.1 Test Purpose

Out-of-band band blocking is defined for an unwanted CW interfering signal falling more than 15 MHz below or above the UE receive band, at which a given average throughput shall meet or exceed the requirement for the specified measurement channels.

For the first 15 MHz below or above the UE receive band the appropriate in-band blocking or adjacent channel selectivity in sub-clause 7.6B.2.1 and sub-clause 7.5B.1 shall be applied.

The lack of out-of-band blocking ability will decrease the coverage area when other NodeB transmitters exist (except in the adjacent channels and spurious response).

#### 7.6B.3.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC in FR1.

#### 7.6B.3.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.3.0.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

## 7.6B.3.1.4 Test Description

## 7.6B.3.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 7.6B.3.1.4.1-1. The details of the uplink and downlink reference measurement channels (RMCs) are specified in Annex A.2 and A.3 respectively. The details of the OCNG patterns used are specified in TS 36.521-1 [10] Annex A.5 and in TS 38.521-1 [8] Annex A.5 for E-UTRA CG and NR CG respectively. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 7.6B.3.1.4.1-1: Test configuration table**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal			
Test Frequencies as specified in TS38.508-1 [6] clause 4.3.1 for different EN-DC bandwidth classes				One frequency chosen arbitrarily from low or high range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE				Highest $N_{RB\_agg}$ (NOTE 3)			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]				Lowest			
NR/E-UTRA Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	REFSENS	QPSK	REFSENS
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							
NOTE 2: Test Channel Bandwidths are checked separately for each EN-DC band, which applicable channel bandwidths are specified in Table 5.3B.1.2-1.							
NOTE 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.							
NOTE 4: REFSENS refers to Uplink configuration in Table 7.3.2.3-3 in [8] and Table 7.3.3-2 in [10] for NR and E-UTRA CC respectively.							

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 Annex A, in Figure [A.3.1.4.2] for SS diagram and section A.3.2 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C and TS 38.521-1 [8] Annex C for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL and DL Reference Measurement channels are TS 36.521-1 [10] Annex A.2, A.3 and TS 38.521-1 [8] Annex A.2, A.3 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release On according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.6B.3.1.4.3.

7.6B.3.1.4.2 Test procedure

1. SS transmits PDSCH via PDCCH DCI format 1A and PDCCH DCI format 1\_1 for C\_RNTI to transmit the DL RMC according to Table 7.6B.3.1.4.1-1 on E-UTRA CC and NR CC respectively. The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 7.6B.3.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level to the value as defined in Table 7.6B.3.1.5-1. Send Uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that for at least the duration of the Throughput measurement:

The E-UTRA CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.3.1.5-1 +  $[10\log(P_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.3.1.5-2 for the carrier frequency  $f$ . The NR CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.3.1.5-1 +  $[10\log(S_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.3.1.5-3 for the carrier frequency  $f$  and the channel bandwidth BW.

4. Set the parameters of the CW signal generator for an interfering signal below the aggregated component carriers according to Table 7.6B.3.1.5-1. The frequency step size is 1MHz.
5. Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H.2.
6. Repeat steps from 4 to 5, using an interfering signal above the aggregated component carriers at step 4.

7.6B.3.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6 Table 4.6.3-118 with condition TRANSFORM\_PRECODER\_ENABLED.

7.6B.3.1.5 Test Requirement

The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in TS 36.521-1 [10] Annex A.3 and TS 38.521-1 [8] Annex A.3 for E-UTRA CG and NR CG respectively with parameters specified in Table 7.6B.3.1.5-1 for the specified wanted signal mean power in the presence of interfering signals.

**Table 7.6B.3.1.5-1: Out-of-band blocking for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
Pw in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	9			
NOTE 1: Interferer values and offsets are specified from Table 7.6.2.1A-2 in [5]				
NOTE 2: For NR carrier, the transmitter shall be set to 4dB below $P_{C_{MAX\_L,f,c}}$ at the minimum uplink configuration specified in Table 7.3.2-3 with $P_{C_{MAX\_L,f,c}}$ as defined in subclause 6.2.4 from [2].				
NOTE 3: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{C_{MAX\_L,c}}$ at the minimum uplink configuration specified in Table 7.3.1-2 with $P_{C_{MAX\_L,c}}$ as defined in subclause 6.2.5 for single carrier and in Table 7.3.1A-1 with $P_{C_{MAX\_L}}$ as defined in subclause 6.2.5A for LTE-CA from [5].				

**Table 7.6B.3.1.5-2: Power Window (dB) for E-UTRA CC**

$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$
1.7	2.0
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.	

**Table 7.6B.3.1.5-3: Power Window (dB) for NR CC**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 20\text{MHz}$	1.4	1.7	2.0
$20\text{MHz} < \text{BW} \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	2.1	2.3	2.3
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.			

### 7.6B.3.2 Out-of-band blocking for intra-band non-contiguous EN-DC (2 CCs)

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- MU is TBD in Annex F

#### 7.6B.3.2.1 Test Purpose

Same test purpose as in clause 7.6.3.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.6B.3.2.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC in FR1.

#### 7.6B.3.2.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.3.0.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.6B.3.2.4 Test Description

Same test description as in clause 7.6.3.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

**Table 7.6B.3.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different EN-DC bandwidth classes	High with maxWGap
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1 except for the parameters specified in Table 7.6B.3.2.4-1.

For Initial conditions as in clause 7.6.3.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.

- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.3.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.3.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.3.2.5 Test Requirement

Same test requirement as in clause 7.6.3.5 in TS 38.521-1 [8].

### 7.6B.3.3 Out-of-band blocking for inter-band EN-DC within FR1 (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Test description for the second condition in 7.6B.3.0.3 is FFS

#### 7.6B.3.3.1 Test Purpose

Same test purpose as in clause 7.6.3.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.6B.3.3.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.6B.3.3.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.3.0.3.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 7.6B.3.3.4 Test Description

For the first condition in 7.6B.3.0.3 the following test description applies:

Same test description as in clause 7.6.3.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.6.3.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level is set according to Table 4.6-1, uplink signal level is set by sending uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that the UE output power is within +0, - 3.4 dB of the 4dB below  $P_{\text{CMAX\_L}}$  with  $P_{\text{CMAX\_L}}$  as defined in clause 6.2.5 of TS36.521-1[10] for carrier frequency  $f \leq 3.0\text{GHz}$  or within +0, -4.0 dB of the target level for carrier frequency  $3.0\text{GHz} < f \leq 4.2\text{GHz}$ , for at least the duration of the throughput measurement, and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.3.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.3.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 4 of Test Procedure as in clause 7.6.3.4.2 in TS 38.521-1 [8] is replaced by:

4. Set the NR downlink signal level according to the table 7.6.3.5-1 or 7.6.3.5-3 in TS 38.521-1 [8]. Send continuously uplink power control "down" commands in every uplink scheduling information to the UE; allow at least 200ms starting from the first TPC command in this step to ensure that the UE transmits at its minimum output power for at least the duration of the throughput measurement.

For the second condition in 7.6B.3.0.3 the test description is FFS.

#### 7.6B.3.3.5 Test Requirement

For NR carrier same test requirement as in clause 7.6.3.5 in TS 38.521-1 [8] with the exceptions of uplink carrier output power as defined in 7.6B.3.3.3.

For E-UTRA carrier same test requirement as in clause 7.6.2.5 in TS 36.521-1 [10] with the exceptions of uplink carrier output power as defined in 7.6B.3.3.3.

### 7.6B.4 Narrow band blocking for EN-DC in FR1

#### 7.6B.4.0 Minimum Conformance Requirements

##### 7.6B.4.0.1 Intra-band contiguous EN-DC

Intra-band contiguous EN-DC narrow band blocking requirement and parameters are defined in Table 7.6B.4.0.1-1.

**Table 7.6B.4.0.1-1: Narrow band blocking parameters for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	<=100	>100, <=120	>120, <=140	>140, <=160
Pw in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
P <sub>uw</sub> , dBm (CW)	-55			
NOTE 1: Jammer offset is from Table 7.6.3.1A-1 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier.				
NOTE 2: For NR carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,f,c</sub> at the minimum uplink configuration specified in Table 7.3.2-3 [2] with P <sub>C<sub>MAX</sub>L,f,c</sub> as defined in subclause 6.2B.4.				
NOTE 3: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,c</sub> at the minimum uplink configuration specified in Table 7.3.1-2 [5] with P <sub>C<sub>MAX</sub>L,c</sub> as defined in subclause 6.2B.4 for single carrier.				
NOTE 4: If NR carrier BW > 40M, no narrow band blocking requirements apply when blocker is applied at the edge of the NR carrier.				

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.4.1.

##### 7.6B.4.0.2 Intra-band non-contiguous EN-DC

For the E-TRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.6.3.1 for single carrier operation and in sub-clause 7.6.3.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.6.4 in [2].

The blocker configuration is defined in the general sub-clause 7.1.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.4.2.

### 7.6B.4.0.3 Inter-band EN-DC within FR1

Narrow band blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.3.1 and 7.6.3.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.4 and 7.6A.4 of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.4.3.

### 7.6B.4.0.4 Inter-band EN-DC including FR2

Narrow band blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.3.1 and 7.6.3.1A of [5] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.4.4.

### 7.6B.4.0.5 Inter-band EN-DC including both FR1 and FR2

Narrow band blocking requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.6.3.1 and 7.6.3.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.6.4 and 7.6A.4 of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.6B.4.5.

## 7.6B.4.1 Narrow band blocking for intra-band contiguous EN-DC (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **MU is TBD in Annex F**

### 7.6B.4.1.1 Test Purpose

Verifies a receiver's ability to receive EN-DC signals at its assigned channel frequencies in the presence of an unwanted narrow band CW interferer at a frequency, which is less than the nominal channel spacing.

The lack of narrow-band blocking ability will decrease the coverage area when other NodeB transmitters exist (except in the adjacent channels and spurious response).

### 7.6B.4.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC in FR1.

### 7.6B.4.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.4.0.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

### 7.6B.4.1.4 Test Description

#### 7.6B.4.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 7.6B.4.1.4.1-1. The details of the uplink and downlink reference measurement channels (RMCs) are specified in Annex A.2 and A.3 respectively. The details of the OCNG patterns used are specified in TS 36.521-1 [10] Annex A.5 and in TS 38.521-1 [8] Annex A.5 for E-UTRA CG and NR CG

respectively. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

**Table 7.6B.4.1.4.1-1: Test configuration table**

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal			
Test Frequencies as specified in TS38.508-1 [6] clause 4.3.1 for different EN-DC bandwidth classes				Mid range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE				Lowest $N_{RB\_agg}$ , Highest $N_{RB\_agg}$ (NOTE 3)			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]				Lowest			
NR/E-UTRA Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	REFSENS	QPSK	REFSENS
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							
NOTE 2: Test Channel Bandwidths are checked separately for each EN-DC band, which applicable channel bandwidths are specified in Table 5.3B.1.2-1.							
NOTE 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $NRB\_SCG$ is tested.							
NOTE 4: REFSENS refers to Uplink configuration in Table 7.3.2.3-3 in [8] and Table 7.3.3-2 in [10] for NR and E-UTRA CC respectively.							

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 Annex A, in Figure [A.3.1.4.2] for SS diagram and section A.3.2 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C and TS 38.521-1 [8] Annex C for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL and DL Reference Measurement channels are TS 36.521-1 [10] Annex A.2, A.3 and TS 38.521-1 [8] Annex A.2, A.3 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 7.6B.4.1.4.3.

#### 7.6B.4.1.4.2 Test procedure

1. SS transmits PDSCH via PDCCH DCI format 1A and PDCCH DCI format 1\_1 for  $C\_RNTI$  to transmit the DL RMC according to Table 7.6B.4.1.4.1-1 on E-UTRA CC and NR CC respectively. The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for  $C\_RNTI$  to schedule the UL RMC according to table 7.6B.4.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.



- Set the Downlink signal level to the value as defined in Table 7.6B.4.1.5-1. Send Uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that for at least the duration of the Throughput measurement:

The E-UTRA CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.4.1.5-1 +  $[10\log(P_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.4.1.5-2 for the carrier frequency  $f$ . The NR CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.6B.4.1.5-1 +  $[10\log(S_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.6B.4.1.5-3 for the carrier frequency  $f$  and the channel bandwidth BW.

- Set the parameters of the CW signal generator for an interfering signal below the aggregated component carriers according to Table 7.6B.4.1.5-1.
- Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H.2.
- Repeat steps from 4 to 5, using an interfering signal above the aggregated component carriers at step 4.

#### 7.6B.4.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6 Table 4.6.3-118 with condition TRANSFORM\_PRECODER\_ENABLED.

#### 7.6B.4.1.5 Test Requirement

The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in TS 36.521-1 [10] Annex A.3 and TS 38.521-1 [8] Annex A.3 for E-UTRA CG and NR CG respectively with parameters specified in Table 7.6B.4.1.5-1 for the specified wanted signal mean power in the presence of interfering signals.

**Table 7.6B.4.1.5-1: Narrow band blocking for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
Pw in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	16			
$P_{uw}$ , dBm (CW)	-55			
NOTE 1: Jammer offset is from Table 7.6.3.1A-1 in [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier.				
NOTE 2: For NR carrier, the transmitter shall be set to 4dB below $P_{CMAX\_L,f,c}$ at the minimum uplink configuration specified in Table 7.3.2-3 with $P_{CMAX\_L,f,c}$ as defined in subclause 6.2.4 from [2].				
NOTE 3: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{CMAX\_L,c}$ at the minimum uplink configuration specified in Table 7.3.1-2 with $P_{CMAX\_L,c}$ as defined in subclause 6.2.5 for single carrier and in Table 7.3.1A-1 with $P_{CMAX\_L}$ as defined in subclause 6.2.5A for LTE-CA from [5].				
NOTE 4: If NR carrier BW $> 40M$ , no narrow band blocking requirements apply when blocker is applied at the edge of the NR carrier.				

**Table 7.6B.4.1.5-2: Power Window (dB) for E-UTRA CC**

$f \leq 3GHz$	$3GHz < f \leq 4.2GHz$
1.7	2.0
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.	

**Table 7.6B.4.1.5-3: Power Window (dB) for NR CC**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 20\text{MHz}$	1.4	1.7	2.0
$20\text{MHz} < \text{BW} \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	2.1	2.3	2.3
NOTE:	Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.		

#### 7.6B.4.2 Narrow band blocking for intra-band non-contiguous EN-DC (2 CCs)

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- MU is TBD in Annex F

##### 7.6B.4.2.1 Test Purpose

Same test purpose as in clause 7.6.4.1 in TS 38.521-1 [8] for the NR carrier.

##### 7.6B.4.2.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC in FR1.

##### 7.6B.4.2.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.4.0.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

##### 7.6B.4.2.4 Test Description

Same test description as in clause 7.6.4.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

**Table 7.6B.4.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different EN-DC bandwidth classes	High with maxWGap
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1 except for the parameters specified in Table 7.6B.4.2.4-1.

For Initial conditions as in clause 7.6.4.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.4.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release  $On$  according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.4.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.4.2.5 Test Requirement

Same test requirement as in clause 7.6.4.5 in TS 38.521-1 [8].

### 7.6B.4.3 Narrow band blocking for inter-band EN-DC within FR1 (2 CCs)

#### 7.6B.4.3.1 Test Purpose

Same test purpose as in clause 7.6.4.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.6B.4.3.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.6B.4.3.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.6B.4.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.6B.4.3.4 Test Description

Same test description as in clause 7.6.4.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.6.4.4.1 in TS 38.521-1 [8], add step 2.1 and step 3.1 as follows:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3.
- 3.1. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].

Step 6 of Initial conditions as in clause 7.6.4.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Add step 7 to Initial conditions in clause 7.6.4.4.1 in TS 38.521-1 [8] as follows:

7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

#### 7.6B.4.3.5 Test Requirement

Same test requirement as in clause 7.6.4.5 in TS 38.521-1 [8].

## 7.7

### 7.7B Spurious response for EN-DC in FR1

#### 7.7B.0 Minimum Conformance Requirements

##### 7.7B.0.1 Intra-band contiguous EN-DC

Intra-band contiguous EN-DC spurious response requirement and parameters are defined in Table 7.7B.0.1-1.

**Table 7.7B.0.1-1: Spurious Response Parameters for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	<=100	>100, <=120	>120, <=140	>140, <=160
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
	9			
P <sub>interferer</sub> , dBm (CW)	-44			
NOTE 1: For NR carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,f,c</sub> at the minimum uplink configuration specified in Table 7.3.2-3 [2] with P <sub>C<sub>MAX</sub>L,f,c</sub> as defined in subclause 6.2B.4.				
NOTE 2: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,c</sub> at the minimum uplink configuration specified in Table 7.3.1-2 [5] with P <sub>C<sub>MAX</sub>L,c</sub> as defined in subclause 6.2B.4 for single carrier.				

The normative reference for this requirement is TS 38.101-3 [4] clause 7.7B.1.

##### 7.7B.0.2 Intra-band non-contiguous EN-DC

For the E-UTRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.7.1 for single carrier operation and in sub-clause 7.7.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.7 is [2].

The normative reference for this requirement is TS 38.101-3 [4] clause 7.7B.2.

##### 7.7B.0.3 Inter-band EN-DC within FR1

Spurious response requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.7.1 and 7.7.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.7 and 7.7A of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.7B.3.

##### 7.7B.0.4 Inter-band EN-DC including FR2

Spurious response requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.7.1 and 7.7.1A of [5] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.7B.4.

##### 7.7B.0.5 Inter-band EN-DC including both FR1 and FR2

Spurious response requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.7.1 and 7.7.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.7 and 7.7A of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.7B.5.

## 7.7B.1 Spurious Response for intra-band contiguous EN-DC (2 CCs)

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- MU is TBD in Annex F

### 7.7B.1.1 Test Purpose

Spurious response for EN-DC verifies the receiver's ability to receive a wanted aggregated signal on its assigned channel frequency without exceeding a given degradation due to the presence of an unwanted CW interfering signal at any other frequency at which a response is obtained i.e. for which the out of band blocking limit as specified in sub-clause 7.6B.3.1 is not met.

The lack of the spurious response ability decreases the coverage area when other unwanted interfering signal exists at any other frequency.

### 7.7B.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC in FR1.

### 7.7B.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.7B.0.1.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

### 7.7B.1.4 Test Description

#### 7.7B.1.4.1 Initial condition

The initial conditions shall be the same as in clause 7.6B.3.1.4.1 in order to test spurious responses obtained in clause 7.6B.3.1 under the same conditions.

#### 7.7B.1.4.2 Test procedure

1. SS transmits PDSCH via PDCCH DCI format 1A and PDCCH DCI format 1\_1 for C\_RNTI to transmit the DL RMC according to Table 7.6B.3.1.4.1-1 on E-UTRA CC and NR CC respectively. The SS sends downlink MAC padding bits on the DL RMC.
2. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 7.6B.3.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
3. Set the Downlink signal level to the value as defined in Table 7.7B.1.5-1. Send Uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that for at least the duration of the Throughput measurement:

The E-UTRA CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.7B.1.5-1 +  $[10\log(P_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.7B.1.5-2 for the carrier frequency  $f$ . The NR CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.7B.1.5-1 +  $[10\log(S_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.7B.1.5-3 for the carrier frequency  $f$  and the channel bandwidth BW.

4. Set the parameters of the CW signal generator for an interfering signal according to Table 7.7B.1.5-1. The spurious frequencies are taken from records in the final step of test procedures in clause 7.6B.3.1.4.2.
5. For each spurious frequency, Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex H.2.

## 7.7B.1.4.3 Message contents

Message contents are according to TS 38.508-1 [6] subclause 4.6 Table 4.6.3-118 with condition TRANSFORM\_PRECODER\_ENABLED.

## 7.7B.1.5 Test Requirement

The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in TS 36.521-1 [10] Annex A.3 and TS 38.521-1 [8] Annex A.3 for E-UTRA CG and NR CG respectively with parameters specified in Table 7.7B.1.5-1 for the specified wanted signal mean power in the presence of interfering signals.

**Table 7.7B.1.5-1: Spurious Response for intra-band contiguous EN-DC**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100,$ $\leq 120$	$>120,$ $\leq 140$	$>140,$ $\leq 160$
Pw in Transmission Bandwidth Configuration, perCC, dBm	REFSENS + Aggregated BW specific value below			
$P_{\text{interferer}}$ , dBm (CW)	9			
$P_{\text{interferer}}$ , dBm (CW)	-44			
NOTE 1: For NR carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,f,c}}$ at the minimum uplink configuration specified in Table 7.3.2-3 with $P_{\text{CMAX\_L,f,c}}$ as defined in subclause 6.2.4 from [2].				
NOTE 2: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{\text{CMAX\_L,c}}$ at the minimum uplink configuration specified in Table 7.3.1-2 with $P_{\text{CMAX\_L,c}}$ as defined in subclause 6.2.5 for single carrier and in Table 7.3.1A-1 with $P_{\text{CMAX\_L}}$ as defined in subclause 6.2.5A for LTE-CA from [5].				

**Table 7.7B.1.5-2: Power Window (dB) for E-UTRA CC**

$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$
1.7	2.0
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.	

**Table 7.7B.1.5-3: Power Window (dB) for NR CC**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$\text{BW} \leq 20\text{MHz}$	1.4	1.7	2.0
$20\text{MHz} < \text{BW} \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < \text{BW} \leq 100\text{MHz}$	2.1	2.3	2.3
NOTE: Power Window comprises two parts, UE Power step tolerance and test system power measurement uncertainty.			

## 7.7B.2 Spurious Response for intra-band non-contiguous EN-DC (2 CCs)

Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:

- MU is TBD in Annex F

## 7.7B.2.1 Test Purpose

Same test purpose as in clause 7.7.1 in TS 38.521-1 [8] for the NR carrier.

## 7.7B.2.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC in FR1.

### 7.7B.2.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.7B.0.2.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.7B.2.4 Test Description

Same test description as in clause 7.7.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial conditions shall be the same as the initial conditions in clause 7.6B.3.2.4 in order to test spurious responses obtained in clause 7.6B.3.2 under the same conditions.

### 7.7B.2.5 Test Requirement

Same test requirement as in clause 7.7.5 in TS 38.521-1 [8].

## 7.7B.3 Spurious Response for inter-band EN-DC within FR1 (2 CCs)

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- Exceptions of uplink carrier output power is as defined in 7.6B.3.3.3. (Exceptions of uplink carrier output power is defined for OOB in RAN4 spec but not defined for Spurious Response in RAN4 spec, uplink carrier output power should be defined the same way as OOB.)

### 7.7B.3.1 Test Purpose

Same test purpose as in clause 7.7.1 in TS 38.521-1 [8] for the NR carrier.

### 7.7B.3.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

### 7.7B.3.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.7B.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.7B.3.4 Test Description

For the first condition in 7.6B.3.3.3 the following test description applies:

Same test description as in clause 7.7.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial conditions shall be the same as the initial conditions in clause 7.6B.3.3.4 in order to test spurious responses obtained in clause 7.6B.3.3 under the same conditions.

Step 4 of Test Procedure as in clause 7.7.4.2 in TS 38.521-1 [8] is replaced by:

4. Set the NR downlink signal level according to the table 7.6.3.5-1 or 7.6.3.5-3 in TS 38.521-1 [8]. Send continuously uplink power control "down" commands in every uplink scheduling information to the UE; allow at least 200ms starting from the first TPC command in this step to ensure that the UE transmits at its minimum output power for at least the duration of the throughput measurement.

For the second condition in 7.6B.3.3.3 the test description is FFS.

### 7.7B.3.5 Test Requirement

Same test requirement as in clause 7.7.5 in TS 38.521-1 [8].

For NR carrier same test requirement as in clause 7.7.5 in TS 38.521-1 [8] with the exceptions of uplink carrier output power as defined in 7.6B.3.3.3.

For E-UTRA carrier same test requirement as in clause 7.7.5 in TS 36.521-1 [10] with the exceptions of uplink carrier output power as defined in 7.6B.3.3.3.

## 7.8 Intermodulation characteristics

### 7.8B Intermodulation characteristics for EN-DC in FR1

#### 7.8B.1 General

#### 7.8B.2 Wide band Intermodulation

##### 7.8B.2.0 Minimum Conformance Requirements

##### 7.8B.2.0.1 Intra-band contiguous EN-DC in FR1

Intra-band contiguous EN-DC wide band intermodulation requirement and parameters are defined in Table 7.8B.2.0.1-1.

**Table 7.8B.2.0.1-1: Wide band intermodulation**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	P <sub>w</sub> <sup>1</sup>	16.8	17.5	18.0
P <sub>interferer 1</sub> , dBm (CW) <sup>2</sup>	-46			
P <sub>interferer 2</sub> , dBm (Modulated) <sup>2</sup>	-46			
NOTE 1: P <sub>w</sub> is wanted signal power level from Table 7.8.1A-1 in [5]				
NOTE 2: Jammer BW and offsets is from Table 7.8.1A-1 [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier				
NOTE 3: For NR carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,f,c</sub> at the minimum uplink configuration specified in Table 7.3-3 with P <sub>C<sub>MAX</sub>L,f,c</sub> as defined in subclause 6.2B.4.				
NOTE 4: For E-UTRA carrier, the transmitter shall be set to 4dB below P <sub>C<sub>MAX</sub>L,c</sub> at the minimum uplink configuration specified in Table 7.3-1-2 with P <sub>C<sub>MAX</sub>L,c</sub> as defined in subclause 6.2B.4 for single carrier.				

The normative reference for this requirement is TS 38.101-3 [4] clause 7.8B.2.1.

##### 7.8B.2.0.2 Intra-band non-contiguous EN-DC in FR1

For the E-UTRA sub-block containing one or multiple CC's, the requirement is defined in sub-clause 7.8.1 for single carrier operation and in sub-clause 7.8.1A for CA in [5].

For the NR sub-block, the requirement is defined in sub-clause 7.8.2 in [2].

The blocker configuration is defined in the general sub-clause 7.1 and the requirement only apply for out of gap interferers.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.8B.2.2.

##### 7.8B.2.0.3 Inter-band EN-DC within FR1

Wide band Intermodulation requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.8.1 and 7.8.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.8.2 and 7.8A.2 of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.8B.2.3.



#### 7.8B.2.0.4 Inter-band EN-DC including FR2

Wide band Intermodulation requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.8.1 and 7.8.1A of [5] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.8B.2.4.

#### 7.8B.2.0.5 Inter-band EN-DC including both FR1 and FR2

Wide band Intermodulation requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.8.1 and 7.8.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.8.2 and 7.8A.2 of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.8B.2.5.

### 7.8B.2.1 Wideband Intermodulation for intra-band contiguous EN-DC in FR1

**Editor's note: This clause is incomplete. The following aspects are either missing or not yet determined:**

- **UL Power configuration is TBD**

#### 7.8B.2.1.1 Test Purpose

Intermodulation response tests the UE's ability to receive data with a given average throughput for a specified reference measurement channel, in the presence of two or more interfering signals which have a specific frequency relationship to the wanted signal, under conditions of ideal propagation and no added noise.

A UE unable to meet the throughput requirement under these conditions will decrease the coverage area when two or more interfering signals exist which have a specific frequency relationship to the wanted signal.

#### 7.8B.2.1.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC within FR1.

#### 7.8B.2.1.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.8B.2.0.

Exception requirements for both NR and E-UTRA are defined for this test and therefore LTE anchor agnostic approach is not applied. E-UTRA test point analysis is included and E-UTRA measurements are performed.

#### 7.8B.2.1.4 Test Description

##### 7.8B.2.1.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 7.8B.2.1.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

Table 7.8B.2.1.4.1-1: Test configuration table

Initial Conditions							
Test Environment as specified in TS 38.508-1 [6] subclause 4.1				Normal			
Test Frequencies as specified in TS38.508-1 [6] clause 4.3.1 for different EN-DC bandwidth classes				Mid range			
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE				Lowest NRB_agg, Highest NRB_agg (NOTE 3)			
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]				Highest			
NR/E-UTRA Test Parameters							
Downlink Configuration				Uplink Configuration			
NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation	NR Modulation	NR RB allocation	E-UTRA Modulation	E-UTRA RB allocation
CP-OFDM QPSK	Full RB (NOTE 1)	QPSK	Full RB	DFT-s-OFDM QPSK	REFSENS	QPSK	REFSENS
NOTE 1: Full RB allocation shall be used per each SCS and channel BW as specified in Table 7.3.2.4.1-2 of TS 38.521-1[8].							
NOTE 2: Test Channel Bandwidths are checked separately for each E-UTRA band, which applicable channel bandwidths are specified in Table 5.3B.1.2-1.							
NOTE 3: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same NRB_agg, only the combination with the highest NRB_SCG is tested.							
NOTE 4: REFSENS refers to Uplink configuration in Table 7.3.2-3 in [8] and Table 7.3.3-2 in [10] for NR and E-UTRA CC respectively.							

1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.

#### 7.8B.2.1.4.2 Test procedure

1. SS sends uplink scheduling information for each UL HARQ process via PDCCH DCI format 0 and DCI format 0\_1 for C\_RNTI to schedule the UL RMC according to table 7.8B.2.1.4.1-1 on E-UTRA CC and NR CC respectively. Since the UL has no payload and no loopback data to send the UE sends uplink MAC padding bits on the UL RMC.
2. Set the Downlink signal level to the value as defined in Table 7.8B.2.1.5-1. Send Uplink power control commands to the UE (less or equal to 1dB step size should be used), to ensure that for at least the duration of the Throughput measurement:

The E-UTRA CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.8B.2.1.5-1 +  $[10\log(P_{L_{CRB}}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.8B.2.1.5-2 for the carrier frequency  $f$  and the channel bandwidth BW.

The NR CC output power is within  $-P_W \pm P_W$  dB of (target level in Table 7.8B.2.1.5-1 +

$[10\log(S_{LCRB}/N_{RB\_alloc})]$ ).  $P_W$  is the power window according to Table 7.8B.2.1.5-2 for the carrier frequency  $f$  and the channel bandwidth  $BW$ .

3. Set the Interfering signal levels to the values as defined in Table 7.8B.2.1.5-1 and frequency below the wanted signal
4. Measure the average throughput for a duration sufficient to achieve statistical significance according to Annex G.2.
5. Repeat steps from 2 to 4, using an interfering signal above the wanted signal at step 3.

#### 7.8B.2.1.4.3 Message contents

Message contents are according to TS 38.508-1 [5] subclause 4.6 with DFT-s-OFDM condition in Table 4.6.3-118 PUSCH-Config.

#### 7.8B.2.1.5 Test Requirement

The throughput shall be  $\geq 95\%$  of the maximum throughput of the reference measurement channels as specified in Annex A.3.2 with parameters specified in Table 7.8B.2.1.5-1 for the specified wanted signal mean power in the presence of two interfering signals.

**Table 7.8B.2.1.5-1: Wide band intermodulation**

EN-DC Aggregated Bandwidth, MHz	$\leq 100$	$>100, \leq 120$	$>120, \leq 140$	$>140, \leq 160$
P <sub>w</sub> in Transmission Bandwidth Configuration, perCC, dBm	$P_W^1$	16.8	17.5	18.0
P <sub>interferer 1</sub> , dBm (CW) <sup>2</sup>	-46			
P <sub>interferer 2</sub> , dBm (Modulated) <sup>2</sup>	-46			
NOTE 1: $P_W$ is wanted signal power level from Table 7.8.1A-1 in [5]				
NOTE 2: Jammer BW and offsets is from Table 7.8.1A-1 [5] and is applied from the lowest edge of the lowest carrier and the highest edge of the highest carrier				
NOTE 3: For NR carrier, the transmitter shall be set to 4dB below $P_{C_{MAX\_L,f,c}}$ at the minimum uplink configuration specified in Table 7.3-3 with $P_{C_{MAX\_L,f,c}}$ as defined in subclause 6.2.4 from [2].				
NOTE 4: For E-UTRA carrier, the transmitter shall be set to 4dB below $P_{C_{MAX\_L,c}}$ at the minimum uplink configuration specified in Table 7.3-1-2 with $P_{C_{MAX\_L,c}}$ as defined in subclause 6.2.5 for single carrier and in Table 7.3-1A-1 with $P_{C_{MAX\_L}}$ as defined in subclause 6.2.5A for LTE-CA from [5].				

**Table 7.8B.2.1.5-2: Power Window (dB) for Wideband Intermodulation**

	$f \leq 3\text{GHz}$	$3\text{GHz} < f \leq 4.2\text{GHz}$	$4.2\text{GHz} < f \leq 6\text{GHz}$
$BW \leq 20\text{MHz}$	1.4	1.7	2.0
$20\text{MHz} < BW \leq 40\text{MHz}$	1.4	1.7	2.2
$40\text{MHz} < BW \leq 100\text{MHz}$	2.1	2.3	2.3

### 7.8B.2.2 Wideband Intermodulation for intra-band non-contiguous EN-DC in FR1

#### 7.8B.2.2.1 Test Purpose

Same test purpose as in clause 7.8.2.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.8B.2.2.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band non-contiguous EN-DC within FR1.

### 7.8B.2.2.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.8B.2.0.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.8B.2.2.4 Test Description

Same test description as in clause 7.8.2.4 in TS 38.521-1 [8] with the following exceptions:

**Table 7.8B.2.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different EN-DC bandwidth classes	High with maxWGap
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 7.9B.2.4-1.

For Initial conditions as in clause 7.8.2.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.8.2.4.2 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

Step 4 of Test procedure is replaced by:

4. Set the Interfering signal levels to the values as defined in Table 7.8.2.5-1 and frequency at the out-of-gap of the sub-blocks.

Step 6 of Test procedure is removed.

### 7.8B.2.2.5 Test Requirement

Same test requirement as in clause 7.8.2.5 in TS 38.521-1 [8].

## 7.8B.2.3 Wideband Intermodulation for inter-band EN-DC in FR1 (2 CCs)

### 7.8B.2.3.1 Test Purpose

Same test purpose as in clause 7.8.2.1 in TS 38.521-1 [8] for the NR carrier.

### 7.8B.2.3.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

### 7.8B.2.3.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.8B.2.0. No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.8B.2.3.4 Test Description

Same test description as in clause 7.8.2.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.8.2.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.8.2.4.2 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

### 7.8B.2.3.5 Test Requirement

Same test requirement as in clause 7.8.2.5 in TS 38.521-1 [8].

### 7.8B.2.4 Wideband Intermodulation for EN-DC including FR2 (2 CCs)

TBD

### 7.8B.2.5 Wideband Intermodulation for inter-band EN-DC including both FR1 and FR2 (3 CCs)

TBD

### 7.8B.2.6 Wideband Intermodulation for EN-DC including FR1 (3 CCs)

**Editor's Note : This test case is incomplete. The following aspects are either missing or not yet determined:**

- Test procedure is TBD
- Message contents is TBD
- Test requirement is TBD
- Test applicability in 38.522 is missing
- MU/TT is TBD

#### 7.8B.2.6.1 Test Purpose

Intermodulation response tests the UE's ability to receive data with a given average throughput for a specified reference measurement channel, in the presence of two or more interfering signals which have a specific frequency relationship to the wanted signal, under conditions of ideal propagation and no added noise.

A UE unable to meet the throughput requirement under these conditions will decrease the coverage area when two or more interfering signals exist which have a specific frequency relationship to the wanted signal.

#### 7.8B.2.6.2 Test Applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting EN-DC within FR1 (3 CCs).

#### 7.8B.2.6.3 Minimum Conformance Requirements

The minimum conformance requirements are defined in clause 7.8B.2.0.

#### 7.8B.2.6.4 Test Description

##### 7.8B.2.6.4.1 Initial condition

Initial conditions are a set of test configurations the UE needs to be tested in and the steps for the SS to take with the UE to reach the correct measurement state.

The initial test configurations consist of environmental conditions, test frequencies and channel bandwidths based on EN-DC operating bands specified in clause 5.3B.1.2, channel bandwidths and sub-carrier spacings for the NR cell specified in TS 38.521-1 [8] clause 5.3 and channel bandwidth for the E-UTRA cell are specified in TS 36.521-1 [10] clause 5.4.2. All of these configurations shall be tested with applicable test parameters for each EN-DC configuration specified in clause 5.3B.1.2 and are shown in table 7.8B.2.6.4.1-1. The details of the uplink reference measurement channels (RMCs) are specified in Annex A.2. Configurations of PDSCH and PDCCH before measurement are specified in TS 36.521-1 [10] Annex C.2 and in TS 38.521-1 [8] Annex C.2 for E-UTRA CG and NR CG respectively.

Table 7.8B.2.6.4.1-1: Test configuration table

Initial Conditions									
Test Environment as specified in TS 38.508-1 [6] subclause 4.1					NC				
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different EN-DC bandwidth classes					For test frequencies refer to "Range" columns. For mapping within Band refer to "CC" columns				
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE					Refer to "NRB" column				
NR Test SCS as specified in Table 5.3.5-1 in TS 38.521-1[8]					Refer to "SCS" column				
Network signalling value					NS_01 by default				
Test Parameters for EN-DC Configurations									
ID	CC (NOTE1)	Band	SCS	NRB	Range/Wgap	UL MOD	DL MOD	UL Alloc	DL Alloc
Default Test Settings for a DC_XA-nYA-nZA Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2
	PCC(S)	As per CA_nXA-nZA in 7.8A.2.1 of 38.521-1 [1]							
	SCC1(S)								
Default Test Settings for a DC_XA-nYC Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2
	PCC(S)	As per CA_nYC in 7.8A.2.1 of 38.521-1 [1]							
	SCC1(S)								
Default Test Settings for a DC_XA-XA-nYA Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2
	SCC1(M)	X <sup>3</sup>	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	PCC(S)	As per 7.8.2.1 of 38.521-1[1]							
Default Test Settings for a DC_XC-nYA Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2
	SCC1(M)	X <sup>3</sup>	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	PCC(S)	As per 7.8.2.1 of 38.521-1[1]							
Default Test Settings for a DC_XA-YA-nZA Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2	NOTE2
	SCC1(M)	Y <sup>3</sup>	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	PCC(S)	As per 7.8.2.1 of 38.521-1[1]							
Default Test Settings for a DC_XC-nXA Configuration									
1	PCC(M)	X <sup>2</sup>	N/A	Highest NRB_agg	TBD	NOTE2	NOTE2	NOTE2	NOTE2
	SCC1(M)	X <sup>2</sup>	N/A		TBD	NOTE2	NOTE2	NOTE2	NOTE2
	PCC(S)	nX	Highest		TBD	As per 7.8.2.1 of 38.521-1[1]			
Default Test Settings for a DC_(n)XCA Configuration									
1	PCC(M)	X	N/A	Lowest NRB_agg	Mid/CC1	QPSK	QPSK	REFSENS	All RBs
	SCC1(M)	X	N/A		Mid/CC2	QPSK	QPSK	N/A	All RBs
	PCC(S)	nX	Highest		Mid/CC1	DFT-s-OFDM QPSK	CP-OFDM QPSK	REFSENS	All RBs
2	PCC(M)	X	N/A	Highest NRB_agg	Mid/CC1	QPSK	QPSK	REFSENS	All RBs
	SCC1(M)	X	N/A		Mid/CC2	QPSK	QPSK	N/A	All RBs

	PCC(S)	nX	Highest		Mid/CC1	DFT-s-OFDM QPSK	CP-OFDM QPSK	REFSENS	All RBs
<b>Default Test Settings for a DC_XA-nXA-nYA Configuration</b>									
1	PCC(M)	X <sup>2</sup>	N/A	Highest	High with maxWGap	NOTE2	NOTE2	NOTE2	NOTE2
	PCC(S)	nX	Highest	N <sub>RB_agg</sub>	Mid	As per CA_nXA-nYA in 7.8A.2.1 of 38.521-1 [1]			
	SCC1(S)	nY	Highest	Highest	Mid	As per CA_nXA-nYA in 7.8A.2.1 of 38.521-1 [1]			
2	PCC(M)	X <sup>2</sup>	N/A	Highest	High with maxWGap	NOTE2	NOTE2	NOTE2	NOTE2
	SCC1(S)	nX	Highest	N <sub>RB_agg</sub>	Mid	As per CA_nXA-nYA in 7.8A.2.1 of 38.521-1 [1]			
	PCC(S)	nY	Highest	Highest	Mid	As per CA_nXA-nYA in 7.8A.2.1 of 38.521-1 [1]			
<b>Default Test Settings for a DC_YA-(n)XAA Configuration</b>									
1	PCC(M)	X	N/A	Lowest	Mid/CC1	QPSK	QPSK	REFSENS	All RBs
	PCC(S)	nX	Highest	N <sub>RB_agg</sub>	Mid/CC1	QPSK	QPSK	REFSENS	All RBs
	SCC1(M)	Y <sup>3</sup>	N/A	N/A	N/A	N/A	N/A	N/A	N/A
2	PCC(M)	X	N/A	Highest	Mid/CC1	QPSK	QPSK	REFSENS	All RBs
	PCC(S)	nX	Highest	N <sub>RB_agg</sub>	Mid/CC1	QPSK	QPSK	N/A	All RBs
	SCC1(M)	Y <sup>3</sup>	N/A	N/A	N/A	N/A	N/A	N/A	N/A
<p>NOTE 1: (M) and (S) indicate MCG and SCG respectively.</p> <p>NOTE 2: Anchor agnostic approach applies. Configurations as per section 4.6.</p> <p>NOTE 3: Note configured</p> <p>NOTE 4: X, Y and Z in this table correspond to different bands i.e. X != Y != Z</p> <p>NOTE 5: The band combinations with difference appearance order of bands/sub-blocks in the band combination string are not distinguished. E.g. DC_YA-(n)XAA represents the set of DC_YA-(n)XAA and DC_(n)XAA-YA</p>									



1. Connect the SS to the UE antenna connectors as shown in [6] TS 38.508-1 A.3.1.2.1 for SS diagram and A.3.2.1 for UE diagram.
2. The parameter settings for the E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3, and the parameter settings for the NR cell are set up according to TS 38.508-1 [6] subclause 4.4.3.
3. Downlink signals are initially set up according to TS 36.521-1 [10] Annex C.0 and TS 38.521-1 [8] Annex C.0 for E-UTRA CG and NR CG respectively, and uplink signals according to TS 36.521-1 [10] Annex H and TS 38.521-1 [8] Annex G for E-UTRA CG and NR CG respectively.
4. The UL Reference Measurement channels are TS 36.521-1 [10] Annex A.2 and TS 38.521-1 [8] Annex A.2 for E-UTRA CG and NR CG respectively.
5. Propagation conditions are set according to TS 36.521-1 [10] Annex B.0 and TS 38.521-1 [8] Annex B.0 for E-UTRA CG and NR CG respectively.
6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer *MCG* and *SCG*, Connected without release *On* according to TS 38.508-1 [6] clause 4.5. Message contents are defined in clause 6.2B.1.1.4.3.

7.8B.2.6.4.2 Test procedure

TBD

7.8B.2.6.4.3 Message contents

TBD

7.8B.2.6.5 Test Requirement

TBD

7.8B.2.7 Wideband Intermodulation for EN-DC including FR1 (4 CCs)

TBD

7.8B.2.8 Wideband Intermodulation for EN-DC including FR1 (5 CCs)

TBD

7.8B.2.9 Wideband Intermodulation for EN-DC including FR1 (6 CCs)

TBD

## 7.9 Spurious emissions

### 7.9B Spurious emissions for EN-DC in FR1

#### 7.9B.0 Minimum Conformance Requirements

##### 7.9B.0.1 Intra-band contiguous EN-DC in FR1

The requirement is defined in sub-clause 7.9A.1 in [2].

The normative reference for this requirement is TS 38.101-3 [4] clause 7.9B.1.

### 7.9B.0.2 Intra-band non-contiguous EN-DC in FR1

Spurious emissions requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.9.1 and 7.9.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.9 and 7.9A of [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.9B.2.

### 7.9B.0.3 Inter-band EN-DC within FR1

E-UTRA requirements from TS 36.101 [5] and NR requirements from TS 38.101-1 [2] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.9B.3.

### 7.9B.0.4 Inter-band EN-DC including FR2

Spurious emissions requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.9.1 and 7.9.1A of [5] and for NR single carrier and CA operation specified in sub-clause 7.9 of [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.9B.4.

### 7.9B.0.5 Inter-band EN-DC including both FR1 and FR2

Spurious emissions requirement for E-UTRA single carrier and CA operation specified in sub-clauses 7.9.1 and 7.9.1A of [5] and for NR single carrier and CA operation specified in sub-clauses 7.9 and 7.9A of [2] and [3] apply.

The normative reference for this requirement is TS 38.101-3 [4] clause 7.9B.5.

## 7.9B.1 Spurious Emissions for intra-band contiguous EN-DC in FR1(2 CCs)

### 7.9B.1.1 Test purpose

Same test purpose as in clause 7.9.1 in TS 38.521-1 [8] for the NR carrier.

### 7.9B.1.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting intra-band contiguous EN-DC within FR1.

### 7.9B.1.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.9B.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

### 7.9B.1.4 Test description

Same test description as in clause 7.9.4 in TS 38.521-1 [8] with the following exceptions:

**Table 7.9B.1.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different DC bandwidth classes.	Mid range
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest $N_{RB\_agg}$ (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same $N_{RB\_agg}$ , only the combination with the highest $N_{RB\_SCG}$ is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 7.9B.1.4-1.

For Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

#### 7.9B.1.5 Test requirement

Same test requirement as in clause 7.9.5 in TS 38.521-1 [8].

### 7.9B.2 Spurious Emissions for intra-band non-contiguous EN-DC in FR1(2 CCs)

#### 7.9B.2.1 Test purpose

Same test purpose as in clause 7.9.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.9B.2.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.9B.2.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.9B.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.9B.2.4 Test description

Same test description as in clause 7.9.4 in TS 38.521-1 [8] with the following exceptions:

**Table 7.9B.2.4-1: Test Configuration Table**

Initial Conditions	
Test Frequencies as specified in TS38.508-1 [6] subclause 4.3.1 for different DC bandwidth classes	[MaxWGap]
Test EN-DC bandwidth combination as specified in Table 5.3B.1.2-1 across bandwidth combination sets supported by the UE	Highest N <sub>RB_agg</sub> (NOTE 1)
NOTE 1: If the UE supports multiple CC Combinations in the EN-DC Configuration with the same N <sub>RB_agg</sub> , only the combination with the highest N <sub>RB_SCG</sub> is tested.	

The initial test configurations for E-UTRA as specified in Table 4.6-1 except for the parameters specified in Table 7.9B.2.4-1.

For Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

#### 7.9B.2.5 Test requirement

Same test requirement as in clause 7.9.5 in TS 38.521-1 [8].

### 7.9B.3 Spurious Emissions for inter-band EN-DC within FR1(2 CCs)

#### 7.9B.3.1 Test purpose

Same test purpose as in clause 7.9.1 in TS 38.521-1 [8] for the NR carrier.

#### 7.9B.3.2 Test applicability

This test case applies to all types of E-UTRA UE release 15 and forward, supporting inter-band EN-DC within FR1.

#### 7.9B.3.3 Minimum conformance requirements

The minimum conformance requirements are defined in clause 7.9B.0.3.

No exception requirements applicable to NR or LTE. LTE anchor agnostic approach is applied.

#### 7.9B.3.4 Test description

Same test description as in clause 7.9.4 in TS 38.521-1 [8] for the NR carrier with the following exceptions:

The initial test configurations for E-UTRA consist of test frequency based on E-UTRA operating band and test channel bandwidth as specified in Table 4.6-1.

For Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8], the following steps are added to configure E-UTRA component:

- 2.1. The parameter settings for E-UTRA cell are set up according to TS 36.508 [11] subclause 4.4.3. The E-UTRA downlink signal level, uplink signal level are set according to Table 4.6-1 and propagation conditions are set according to Annex B.0 of TS36.521-1[10].
7. On the E-UTRA carrier, disable periodic and aperiodic CQI reports, disable SRS, set TimeAlignmentTimerDedicated IE to infinity and disable downlink and uplink scheduling, all as per Table 4.6-1 under clause 4.6.

Step 6 of Initial conditions as in clause 7.9.4.1 in TS 38.521-1 [8] is replaced by:

6. Ensure the UE is in state RRC\_CONNECTED with generic procedure parameters Connectivity EN-DC, DC bearer MCG and SCG, Connected without release *On* according to TS 38.508 [6] clause 4.5.

#### 7.9B.3.5 Test requirement

Same test requirement as in clause 7.9.5 in TS 38.521-1 [8].

7.9B.4 Spurious Emissions for inter-band EN-DC including FR2 (2 CCs)

TBD

7.9B.5 Spurious Emissions for inter-band EN-DC including both FR1 and FR2 (3 CCs)

TBD

7.9B.6 Spurious Emissions for EN-DC (3 CCs)

TBD

7.9B.7 Spurious Emissions for EN-DC (4 CCs)

TBD

7.9B.8 Spurious Emissions for EN-DC (5 CCs)

TBD

7.9B.9 Spurious Emissions for EN-DC (6 CCs)

TBD

---

## Annex A (normative): Measurement Channels

Please refer to Annex A in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

### A.1 General

The throughput values defined in the measurement channels specified in Annex A, are calculated and are valid per datastream (codeword). For multi-stream (more than one codeword) transmissions, the throughput referenced in the minimum requirements is the sum of throughputs of all datastreams (codewords).

The UE category entry in the definition of the reference measurement channel in Annex A is only informative and reveals the UE categories, which can support the corresponding measurement channel. Whether the measurement channel is used for testing a certain UE category or not is specified in the individual minimum requirements.

---

### A.2 UL reference measurement channels for E-UTRA TDD Config 2

#### A.2.1 General

The measurement channels in the following subclauses are defined to derive the requirements in clause 6 (Transmitter Characteristics) and clause 7 (Receiver Characteristics). The measurement channels represent example configurations of physical channels for different data rates.

## A.2.2 Reference measurement channels for E-UTRA

### A.2.2.1 Full RB allocation

#### A.2.2.1.1 QPSK

**Table A.2.2.1.1-1: Reference Channels for QPSK with full RB allocation**

Parameter	Unit	Value					
		1.4	3	5	10	15	20
Channel bandwidth	MHz	1.4	3	5	10	15	20
Allocated resource blocks		6	15	25	50	75	100
Uplink-Downlink Configuration (Note 2)		2	2	2	2	2	2
Special subframe configuration (Note 3)		7	7	7	7	7	7
DFT-OFDM Symbols per Sub-Frame		12	12	12	12	12	12
Modulation		QPSK	QPSK	QPSK	QPSK	QPSK	QPSK
Target Coding rate		1/3	1/3	1/3	1/3	1/5	1/6
Payload size							
For Sub-Frame 2,7	Bits	600	1544	2216	5160	4392	4584
Transport block CRC	Bits	24	24	24	24	24	24
Number of code blocks per Sub-Frame (Note 1)							
For Sub-Frame 2,7		1	1	1	1	1	1
Total number of bits per Sub-Frame							
For Sub-Frame 2,7	Bits	1728	4320	7200	14400	21600	28800
Total symbols per Sub-Frame							
For Sub-Frame 2,7		864	2160	3600	7200	10800	14400
UE Category		≥ 1	≥ 1	≥ 1	≥ 1	≥ 1	≥ 1
Note 1:	If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)						
Note 2:	As per Table 4.2-2 in TS 36.211 [13]						
Note 3:	As per Table 4.2-1 in TS 36.211 [13]						

#### A.2.2.1.2 16-QAM

**Table A.2.2.1.2-1: Reference Channels for 16-QAM with full RB allocation**

Parameter	Unit	Value					
		1.4	3	5	10	15	20
Channel bandwidth	MHz	1.4	3	5	10	15	20
Allocated resource blocks		6	15	25	50	75	100
Uplink-Downlink Configuration (Note 2)		2	2	2	2	2	2
Special subframe configuration (Note 3)		7	7	7	7	7	7
DFT-OFDM Symbols per Sub-Frame		12	12	12	12	12	12
Modulation		16QAM	16QAM	16QAM	16QAM	16QAM	16QAM
Target Coding rate		3/4	1/2	1/3	3/4	1/2	1/3
Payload size							
For Sub-Frame 2,7	Bits	2600	4264	4968	21384	21384	19848
Transport block CRC	Bits	24	24	24	24	24	24
Number of code blocks per Sub-Frame (Note 1)							
For Sub-Frame 2,7		1	1	1	4	4	4
Total number of bits per Sub-Frame							
For Sub-Frame 2,7	Bits	3456	8640	14400	28800	43200	57600
Total symbols per Sub-Frame							
For Sub-Frame 2,7		864	2160	3600	7200	10800	14400
UE Category		≥ 1	≥ 1	≥ 1	≥ 2	≥ 2	≥ 2
Note 1:	If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)						
Note 2:	As per Table 4.2-2 in TS 36.211 [13]						
Note 3:	As per Table 4.2-1 in TS 36.211 [13]						

## A.2.2.1.3 64-QAM

Table A.2.2.1.3-1: Reference Channels for 64-QAM with full RB allocation

Parameter	Unit	Value					
Channel bandwidth	MHz	1.4	3	5	10	15	20
Allocated resource blocks		6	15	25	50	75	100
Uplink-Downlink Configuration (Note 2)		2	2	2	2	2	2
Special subframe configuration (Note 3)		7	7	7	7	7	7
DFT-OFDM Symbols per Sub-Frame		12	12	12	12	12	12
Modulation		64QAM	64QAM	64QAM	64QAM	64QAM	64QAM
Target Coding rate		3/4	3/4	3/4	3/4	3/4	3/4
Payload size							
For Sub-Frame 2,7	Bits	3752	9528	15840	31704	46888	63776
Transport block CRC	Bits	24	24	24	24	24	24
Number of code blocks per Sub-Frame (Note 1)							
For Sub-Frame 2,7		1	2	3	6	8	11
Total number of bits per Sub-Frame							
For Sub-Frame 2,7	Bits	5184	12960	21600	43200	64800	86400
Total symbols per Sub-Frame							
For Sub-Frame 2,7		864	2160	3600	7200	10800	14400
UE Category (Note 4)		5, 8	5, 8	5, 8	5, 8	5, 8	5, 8
UE UL Category (Note 4)		5, 8, 13, 14	5, 8, 13, 14	5, 8, 13, 14	5, 8, 13, 14	5, 8, 13, 14	5, 8, 13, 14
<p>Note 1: If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)</p> <p>Note 2: As per Table 4.2-2 in TS 36.211 [13]</p> <p>Note 3: As per Table 4.2-1 in TS 36.211 [13]</p> <p>Note 4: If UE does not report UE UL category, then the applicability of reference channel is determined by UE category. If UE reports UE UL category, then the applicability of reference channel is determined by UE UL category.</p>							



## A.2.2.1.4 256 QAM

Table A.2.2.1.4-1: Reference Channels for 256 QAM with full RB allocation

Parameter	Unit	Value					
Channel bandwidth	MHz	1.4	3	5	10	15	20
Allocated resource blocks		6	15	25	50	75	100
Uplink-Downlink Configuration (Note 2)		2	2	2	2	2	2
Special subframe configuration (Note 3)		7	7	7	7	7	7
DFT-OFDM Symbols per Sub-Frame		12	12	12	12	12	12
Modulation		256QAM	256QAM	256QAM	256QAM	256QAM	256QAM
Target Coding rate		3/4	3/4	3/4	3/4	3/4	3/4
Payload size							
For Sub-Frame 2,7	Bits	5160	12960	21384	42368	63776	84760
Transport block CRC	Bits	24	24	24	24	24	24
Number of code blocks per Sub-Frame (Note 1)							
For Sub-Frame 2,7		1	3	4	8	11	15
Total number of bits per Sub-Frame							
For Sub-Frame 2,7	Bits	6912	17280	28800	57600	86400	115200
Total symbols per Sub-Frame							
For Sub-Frame 2,7		864	2160	3600	7200	10800	14400
UE UL Category		≥ 15	≥ 15	≥ 15	≥ 15	≥ 15	≥ 15
Note 1: If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)							
Note 2: As per Table 4.2-2 in TS 36.211 [13]							
Note 3: As per Table 4.2-1 in TS 36.211 [13]							

## A.2.2.2 Partial RB allocation

## A.2.2.2.1 QPSK

Table A.2.2.2.1-1: Reference Channels for QPSK with partial RB allocation

Parameter	Ch BW	Allocated RBs	UL-DL Configuration (Note 2)	Special subframe configuration (Note 3)	DFT-OFDM Symbols per Sub-Frame	Mod'n	Target Coding rate	Payload size for Sub-Frame 2, 7	Transport block CRC	Number of code blocks per Sub-Frame (Note 1)	Total number of bits per Sub-Frame for Sub-Frame 2, 7	Total symbols per Sub-Frame for Sub-Frame 2, 7	UE Category
Unit	MHz							Bits	Bits		Bits		
	1.4 - 20	1	2	7	12	QPSK	1/3	72	24	1	288	144	≥ 1
	1.4 - 20	2	2	7	12	QPSK	1/3	176	24	1	576	288	≥ 1
	1.4 - 20	3	2	7	12	QPSK	1/3	256	24	1	864	432	≥ 1
	1.4 - 20	4	2	7	12	QPSK	1/3	392	24	1	1152	576	≥ 1
	1.4 - 20	5	2	7	12	QPSK	1/3	424	24	1	1440	720	≥ 1
	3-20	6	2	7	12	QPSK	1/3	600	24	1	1728	864	≥ 1
	3-20	8	2	7	12	QPSK	1/3	808	24	1	2304	1152	≥ 1
	3-20	9	2	7	12	QPSK	1/3	776	24	1	2592	1296	≥ 1
	3-20	10	2	7	12	QPSK	1/3	872	24	1	2880	1440	≥ 1
	3-20	12	2	7	12	QPSK	1/3	1224	24	1	3456	1728	≥ 1
	5-20	15	2	7	12	QPSK	1/3	1320	24	1	4320	2160	≥ 1
	5-20	16	2	7	12	QPSK	1/3	1384	24	1	4608	2304	≥ 1
	5-20	18	2	7	12	QPSK	1/3	1864	24	1	5184	2592	≥ 1
	5-20	20	2	7	12	QPSK	1/3	1736	24	1	5760	2880	≥ 1
	5-20	24	2	7	12	QPSK	1/3	2472	24	1	6912	3456	≥ 1
	10-20	25	2	7	12	QPSK	1/3	2216	24	1	7200	3600	≥ 1
	10-20	27	2	7	12	QPSK	1/3	2792	24	1	7776	3888	≥ 1
	10-20	30	2	7	12	QPSK	1/3	2664	24	1	8640	4320	≥ 1
	10-20	32	2	7	12	QPSK	1/3	2792	24	1	9216	4608	≥ 1
	10-20	36	2	7	12	QPSK	1/3	3752	24	1	10368	5184	≥ 1
	10-20	40	2	7	12	QPSK	1/3	4136	24	1	11520	5760	≥ 1
	10-20	45	2	7	12	QPSK	1/3	4008	24	1	12960	6480	≥ 1
	10-20	48	2	7	12	QPSK	1/3	4264	24	1	13824	6912	≥ 1
	15 - 20	50	2	7	12	QPSK	1/3	5160	24	1	14400	7200	≥ 1
	15 - 20	54	2	7	12	QPSK	1/3	4776	24	1	15552	7776	≥ 1
	15 - 20	60	2	7	12	QPSK	1/4	4264	24	1	17280	8640	≥ 1
	15 - 20	64	2	7	12	QPSK	1/4	4584	24	1	18432	9216	≥ 1
	15 - 20	72	2	7	12	QPSK	1/4	5160	24	1	20736	10368	≥ 1
	20	75	2	7	12	QPSK	1/5	4392	24	1	21600	10800	≥ 1
	20	80	2	7	12	QPSK	1/5	4776	24	1	23040	11520	≥ 1
	20	81	2	7	12	QPSK	1/5	4776	24	1	23328	11664	≥ 1
	20	90	2	7	12	QPSK	1/6	4008	24	1	25920	12960	≥ 1
	20	96	2	7	12	QPSK	1/6	4264	24	1	27648	13824	≥ 1
Note 1:	If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)												
Note 2:	As per Table 4.2-2 in TS 36.211 [13]												
Note 3:	As per Table 4.2-1 in TS 36.211 [13]												

A.2.2.2.2 16-QAM

Table A.2.2.2-1: Reference Channels for 16QAM with partial RB allocation

Parameter	Ch BW	Allocated RBs	UL-DL Configuration (Note 2)	Special subframe configuration (Note 3)	DFT-OFDM Symbols per Sub-Frame	Mod'n	Target Coding rate	Payload size for Sub-Frame 2, 7	Transport block CRC	Number of code blocks per Sub-Frame (Note 1)	Total number of bits per Sub-Frame for Sub-Frame 2, 7	Total symbols per Sub-Frame for Sub-Frame 2, 7	UE Category
Unit	MHz							Bits	Bits		Bits		
	1.4 - 20	1	2	7	12	16QAM	3/4	408	24	1	576	144	≥ 1
	1.4 - 20	2	2	7	12	16QAM	3/4	840	24	1	1152	288	≥ 1
	1.4 - 20	3	2	7	12	16QAM	3/4	1288	24	1	1728	432	≥ 1
	1.4 - 20	4	2	7	12	16QAM	3/4	1736	24	1	2304	576	≥ 1
	1.4 - 20	5	2	7	12	16QAM	3/4	2152	24	1	2880	720	≥ 1
	3-20	6	2	7	12	16QAM	3/4	2600	24	1	3456	864	≥ 1
	3-20	8	2	7	12	16QAM	3/4	3496	24	1	4608	1152	≥ 1
	3-20	9	2	7	12	16QAM	3/4	3880	24	1	5184	1296	≥ 1
	3-20	10	2	7	12	16QAM	3/4	4264	24	1	5760	1440	≥ 1
	3-20	12	2	7	12	16QAM	3/4	5160	24	1	6912	1728	≥ 1
	5-20	15	2	7	12	16QAM	1/2	4264	24	1	8640	2160	≥ 1
	5-20	16	2	7	12	16QAM	1/2	4584	24	1	9216	2304	≥ 1
	5-20	18	2	7	12	16QAM	1/2	5160	24	1	10368	2592	≥ 1
	5-20	20	2	7	12	16QAM	1/3	4008	24	1	11520	2880	≥ 1
	5-20	24	2	7	12	16QAM	1/3	4776	24	1	13824	3456	≥ 1
	10-20	25	2	7	12	16QAM	1/3	4968	24	1	14400	3600	≥ 1
	10-20	27	2	7	12	16QAM	1/3	4776	24	1	15552	3888	≥ 1
	10-20	30	2	7	12	16QAM	3/4	12960	24	3	17280	4320	≥ 2
	10-20	32	2	7	12	16QAM	3/4	13536	24	3	18432	4608	≥ 2
	10-20	36	2	7	12	16QAM	3/4	15264	24	3	20736	5184	≥ 2
	10-20	40	2	7	12	16QAM	3/4	16992	24	3	23040	5760	≥ 2
	10-20	45	2	7	12	16QAM	3/4	19080	24	4	25920	6480	≥ 2
	10-20	48	2	7	12	16QAM	3/4	20616	24	4	27648	6912	≥ 2
	15 - 20	50	2	7	12	16QAM	3/4	21384	24	4	28800	7200	≥ 2
	15 - 20	54	2	7	12	16QAM	3/4	22920	24	4	31104	7776	≥ 2
	15 - 20	60	2	7	12	16QAM	2/3	23688	24	4	34560	8640	≥ 2
	15 - 20	64	2	7	12	16QAM	2/3	25456	24	4	36864	9216	≥ 2
	15 - 20	72	2	7	12	16QAM	1/2	20616	24	4	41472	10368	≥ 2
	20	75	2	7	12	16QAM	1/2	21384	24	4	43200	10800	≥ 2
	20	80	2	7	12	16QAM	1/2	22920	24	4	46080	11520	≥ 2
	20	81	2	7	12	16QAM	1/2	22920	24	4	46656	11664	≥ 2
	20	90	2	7	12	16QAM	2/5	20616	24	4	51840	12960	≥ 2
	20	96	2	7	12	16QAM	2/5	22152	24	4	55296	13824	≥ 2
Note 1:	If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)												
Note 2:	As per Table 4.2-2 in TS 36.211 [13]												
Note 3:	As per Table 4.2-1 in TS 36.211 [13]												

A.2.2.2.3 64-QAM

**Table A.2.2.2.3-1: Reference Channels for 64-QAM with partial RB allocation**

Parameter	Ch BW	Allocated RBs	UL-DL Configuration (Note 2)	Special subframe configuration (Note 3)	DFT-OFDM Symbols per Sub-Frame	Mod'n	Target Coding rate	Payload size for Sub-Frame 2, 7	Transport block CRC	Number of code blocks per Sub-Frame (Note 1)	Total number of bits per Sub-Frame for Sub-Frame 2, 7	Total symbols per Sub-Frame for Sub-Frame 2, 7	UE Category (Note 4)	UE UL Category (Note 4)
Unit	M Hz							Bits	Bits		Bits			
	1.4 - 20	1	2	7	12	64QAM	3/4	616	24	1	864	144	5,8	5, 8, 13, 14
	1.4 - 20	2	2	7	12	64QAM	3/4	1256	24	1	1728	288	5,8	5, 8, 13, 14
	1.4 - 20	3	2	7	12	64QAM	3/4	1864	24	1	2592	432	5,8	5, 8, 13, 14
	1.4 - 20	4	2	7	12	64QAM	3/4	2536	24	1	3456	576	5,8	5, 8, 13, 14
	1.4 - 20	5	2	7	12	64QAM	3/4	3112	24	1	4320	720	5,8	5, 8, 13, 14
	3-20	6	2	7	12	64QAM	3/4	3752	24	1	5184	864	5,8	5, 8, 13, 14
	3-20	8	2	7	12	64QAM	3/4	5160	24	1	6912	1152	5,8	5, 8, 13, 14
	3-20	9	2	7	12	64QAM	3/4	5736	24	1	7776	1296	5,8	5, 8, 13, 14
	3-20	10	2	7	12	64QAM	3/4	6200	24	2	8640	1440	5,8	5, 8, 13, 14
	3-20	12	2	7	12	64QAM	3/4	7480	24	2	10368	1728	5,8	5, 8, 13, 14
	5-20	15	2	7	12	64QAM	3/4	9528	24	2	12960	2160	5,8	5, 8, 13, 14
	5-20	16	2	7	12	64QAM	3/4	10296	24	2	13824	2304	5,8	5, 8, 13, 14
	5-20	18	2	7	12	64QAM	3/4	11448	24	2	15552	2592	5,8	5, 8, 13, 14
	5-20	20	2	7	12	64QAM	3/4	12576	24	3	17280	2880	5,8	5, 8, 13, 14
	5-20	24	2	7	12	64QAM	3/4	15264	24	3	20736	3456	5,8	5, 8, 13, 14
	10-20	25	2	7	12	64QAM	3/4	15840	24	3	21600	3600	5,8	5, 8, 13, 14
	10-20	27	2	7	12	64QAM	3/4	16992	24	3	23328	3888	5,8	5, 8, 13, 14
	10-20	30	2	7	12	64QAM	3/4	19080	24	4	25920	4320	5,8	5, 8, 13, 14
	10-20	32	2	7	12	64QAM	3/4	20616	24	4	27648	4608	5,8	5, 8, 13, 14
	10-20	36	2	7	12	64QAM	3/4	22920	24	4	31104	5184	5,8	5, 8, 13, 14
	10-20	40	2	7	12	64QAM	3/4	25456	24	5	34560	5760	5,8	5, 8, 13, 14

	10-20	45	2	7	12	64Q AM	3/4	2833 6	24	5	3888 0	6480	5,8	5, 8, 13, 14
	10-20	48	2	7	12	64Q AM	3/4	3057 6	24	5	4147 2	6912	5,8	5, 8, 13, 14
	15-20	50	2	7	12	64Q AM	3/4	3170 4	24	6	4320 0	7200	5,8	5, 8, 13, 14
	15-20	54	2	7	12	64Q AM	3/4	3400 8	24	6	4665 6	7776	5,8	5, 8, 13, 14
	15-20	60	2	7	12	64Q AM	3/4	3788 8	24	7	5184 0	8640	5,8	5, 8, 13, 14
	15-20	64	2	7	12	64Q AM	3/4	4057 6	24	7	5529 6	9216	5,8	5, 8, 13, 14
	15-20	72	2	7	12	64Q AM	3/4	4535 2	24	8	6220 8	1036 8	5,8	5, 8, 13, 14
	20	75	2	7	12	64Q AM	3/4	4688 8	24	8	6480 0	1080 0	5,8	5, 8, 13, 14
	20	80	2	7	12	64Q AM	3/4	5102 4	24	9	6912 0	1152 0	5,8	5, 8, 13, 14
	20	81	2	7	12	64Q AM	3/4	5102 4	24	9	6998 4	1166 4	5,8	5, 8, 13, 14
	20	90	2	7	12	64Q AM	3/4	5102 4	24	9	7776 0	1296 0	5,8	5, 8, 13, 14
	20	96	2	7	12	64Q AM	3/4	6166 4	24	11	8294 4	1382 4	5,8	5, 8, 13, 14
Note 1:	If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bit)													
Note 2:	As per Table 4.2-2 in TS 36.211 [13]													
Note 3:	As per Table 4.2-1 in TS 36.211 [13]													
Note 4:	If UE does not report UE UL category, then the applicability of reference channel is determined by UE category. If UE reports UE UL category, then the applicability of reference channel is determined by UE UL category													

A.2.2.2.4 256 QAM

Table A.2.2.2.4-1: Reference Channels for 256 QAM with partial RB allocation

Parameter	Ch BW	Allocated RBs	UL-DL Configuration (Note 2)	Special Slot Configuration (Note 3)	DFT-OFDM Symbols per Sub-Frame	Mod'n	Target Coding rate	Payload size for Sub-Frame 2, 7	Transport block CRC	Number of code blocks per Sub-Frame (Note 1)	Total number of bits per Sub-Frame for Sub-Frame 2, 7	Total symbols per Sub-Frame for Sub-Frame 2, 7	UE U Category
Unit	MHz							Bits	Bits		Bits		
	1.4 - 20	1	2	7	12	256QAM	3/4	840	24	1	1152	144	≥ 1E
	1.4 - 20	2	2	7	12	256QAM	3/4	1672	24	1	2304	288	≥ 1E
	1.4 - 20	3	2	7	12	256QAM	3/4	2536	24	1	3456	432	≥ 1E
	1.4 - 20	4	2	7	12	256QAM	3/4	3368	24	1	4608	576	≥ 1E
	1.4 - 20	5	2	7	12	256QAM	3/4	4264	24	1	5760	720	≥ 1E
	3-20	6	2	7	12	256QAM	3/4	5160	24	1	6912	864	≥ 1E
	3-20	8	2	7	12	256QAM	3/4	6712	24	2	9216	1152	≥ 1E
	3-20	9	2	7	12	256QAM	3/4	7736	24	2	10368	1296	≥ 1E
	3-20	10	2	7	12	256QAM	3/4	8504	24	2	11520	1440	≥ 1E
	3-20	12	2	7	12	256QAM	3/4	10296	24	2	13824	1728	≥ 1E
	5-20	15	2	7	12	256QAM	3/4	12960	24	3	17280	2160	≥ 1E
	5-20	16	2	7	12	256QAM	3/4	13536	24	3	18432	2304	≥ 1E
	5-20	18	2	7	12	256QAM	3/4	15264	24	3	20736	2592	≥ 1E
	5-20	20	2	7	12	256QAM	3/4	16992	24	3	23040	2880	≥ 1E
	5-20	24	2	7	12	256QAM	3/4	20616	24	4	27648	3456	≥ 1E
	10-20	25	2	7	12	256QAM	3/4	21384	24	4	28800	3600	≥ 1E
	10-20	27	2	7	12	256QAM	3/4	22920	24	4	31104	3888	≥ 1E
	10-20	30	2	7	12	256QAM	3/4	25456	24	5	34560	4320	≥ 1E
	10-20	32	2	7	12	256QAM	3/4	27376	24	5	36864	4608	≥ 1E
	10-20	36	2	7	12	256QAM	3/4	30576	24	6	41472	5184	≥ 1E
	10-20	40	2	7	12	256QAM	3/4	34008	24	6	46080	5760	≥ 1E
	10-20	45	2	7	12	256QAM	3/4	37888	24	7	51840	6480	≥ 1E
	10-20	48	2	7	12	256QAM	3/4	40576	24	8	55296	6912	≥ 1E
	15 - 20	50	2	7	12	256QAM	3/4	42368	24	8	57600	7200	≥ 1E
	15 - 20	54	2	7	12	256QAM	3/4	46888	24	8	62208	7776	≥ 1E
	15 - 20	60	2	7	12	256QAM	3/4	51024	24	9	69120	8640	≥ 1E
	15 - 20	64	2	7	12	256QAM	3/4	55056	24	9	73728	9216	≥ 1E
	15 - 20	72	2	7	12	256QAM	3/4	61664	24	11	82944	10368	≥ 1E
	20	75	2	7	12	256QAM	3/4	63776	24	11	86400	10800	≥ 1E
	20	80	2	7	12	256QAM	3/4	68808	24	12	92160	11520	≥ 1E
	20	81	2	7	12	256QAM	3/4	68808	24	12	93312	11664	≥ 1E
	20	90	2	7	12	256QAM	3/4	76208	24	13	103680	12960	≥ 1E
	20	96	2	7	12	256QAM	3/4	81176	24	14	110592	13824	≥ 1E

Note 1: If more than one Code Block is present, an additional CRC sequence of L = 24 Bits is attached to each Code Block (otherwise L = 0 Bits)  
 Note 2: As per Table 4.2-2 in TS 36.211 [13]  
 Note 3: As per Table 4.2-1 in TS 36.211 [13]

## A.3 DL reference measurement channels for E-UTRA

### A.3.1 General

The number of available channel bits varies across the sub-frames due to PBCH and PSS/SSS overhead. The payload size per sub-frame is varied in order to keep the code rate constant throughout a frame.

Unless otherwise stated, no user data is scheduled on subframes #5 in order to facilitate the transmission of system information blocks (SIB).

The algorithm for determining the payload size  $A$  is as follows; given a desired coding rate  $R$  and radio block allocation  $N_{RB}$

1. Calculate the number of channel bits  $N_{ch}$  that can be transmitted during the first transmission of a given sub-frame.

2. Find  $A$  such that the resulting coding rate is as close to  $R$  as possible, that is,

$$\min |R - (A + 24 * (N_{CB} + 1)) / N_{ch}|, \text{ where } N_{CB} = \begin{cases} 0, & \text{if } C = 1 \\ C, & \text{if } C > 1 \end{cases},$$

subject to

- a)  $A$  is a valid TB size according to section 7.1.7 of TS 36.213 [6] assuming an allocation of  $N_{RB}$  resource blocks.
  - b)  $C$  is the number of Code Blocks calculated according to section 5.1.2 of TS 36.212 [5].
3. If there is more than one  $A$  that minimizes the equation above, then the larger value is chosen per default and the chosen code rate should not exceed 0.93.
4. For TDD, the measurement channel is based on DL/UL configuration ratio of 3DL+DwPTS (10 OFDM symbol SSF7); 1UL



---

## Annex B (normative): Propagation Conditions

Please refer to Annex B in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

## Annex C (normative): Downlink Physical Channels

Please refer to Annex C in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

## Annex D (normative): Characteristics of the Interfering Signal

Please refer to Annex D in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

## Annex E (normative): Global In-Channel Tx Test

Please refer to Annex E in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

## Annex F (informative): Measurement uncertainties and Test Tolerances

### F.1 Acceptable uncertainty of Test System (normative)

TBD

#### F.1.1 Measurement of test environments

TBD

## F.1.2 Measurement of transmitter

**Table F.1.2-1: Maximum Test System Uncertainty for transmitter tests**

Subclause	Maximum Test System Uncertainty	Derivation of Test System Uncertainty
6.2B.1.1 UE Maximum Output Power for Intra-Band Contiguous EN-DC	$f \leq 3.0\text{GHz}$ $\pm 0.7\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.4\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $3.0\text{GHz} < f \leq 4.2\text{GHz}$ $\pm 1.0\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $4.2\text{GHz} < f \leq 6.0\text{GHz}$ $\pm 1.3\text{ dB, BW} \leq 20\text{MHz}$ $\pm 1.5\text{ dB, } 20\text{MHz} < \text{BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$	
6.2B.1.2 UE Maximum Output Power for Intra-Band Non-Contiguous EN-DC	MAX ( $\text{MU}_{\text{LTE}}$ , $\text{MU}_{\text{SA}}$ )  $\text{MU}_{\text{LTE}}$ $\pm 0.7\text{ dB, } f \leq 3.0\text{GHz}$ $\pm 1.0\text{ dB, } 3.0\text{GHz} < f \leq 4.2\text{GHz}$  $\text{MU}_{\text{SA}}$ $f \leq 3.0\text{GHz}$ $\pm 0.7\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.4\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $3.0\text{GHz} < f \leq 4.2\text{GHz}$ $\pm 1.0\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $4.2\text{GHz} < f \leq 6.0\text{GHz}$ $\pm 1.3\text{ dB, BW} \leq 20\text{MHz}$ $\pm 1.5\text{ dB, } 20\text{MHz} < \text{BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$	$\text{MU}_{\text{LTE}}$ is MU of LTE specified in 6.2.2 in TS 36.521-1.  $\text{MU}_{\text{SA}}$ is MU of FR1 SA specified in 6.2.1 in TS 38.521-1.
6.2B.1.3 UE Maximum Output Power for Inter-Band EN-DC within FR1	MAX ( $\text{MU}_{\text{LTE}}$ , $\text{MU}_{\text{SA}}$ )  $\text{MU}_{\text{LTE}}$ $\pm 0.7\text{ dB, } f \leq 3.0\text{GHz}$ $\pm 1.0\text{ dB, } 3.0\text{GHz} < f \leq 4.2\text{GHz}$  $\text{MU}_{\text{SA}}$ $f \leq 3.0\text{GHz}$ $\pm 0.7\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.4\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $3.0\text{GHz} < f \leq 4.2\text{GHz}$ $\pm 1.0\text{ dB, BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$  $4.2\text{GHz} < f \leq 6.0\text{GHz}$ $\pm 1.3\text{ dB, BW} \leq 20\text{MHz}$ $\pm 1.5\text{ dB, } 20\text{MHz} < \text{BW} \leq 40\text{MHz}$ $\pm 1.6\text{ dB, } 40\text{MHz} < \text{BW} \leq 100\text{MHz}$	$\text{MU}_{\text{LTE}}$ is MU of LTE specified in 6.2.2 in TS 36.521-1.  $\text{MU}_{\text{SA}}$ is MU of FR1 SA specified in 6.2.1 in TS 38.521-1.
6.2B.1.4 UE Maximum Output Power for Inter-Band EN-DC including FR2	Same as 6.2.1 in TS 38.521-2	
6.2B.2.1 UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	Same as 6.2B.1.1	
6.2B.2.2 UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.2.3 UE Maximum Output Power reduction for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	

6.2B.3.1 UE Additional Maximum Output Power reduction for Intra-band contiguous EN-DC	Same as 6.2B.1.1	
6.2B.3.2 UE Additional Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.3.3 UE Additional Maximum Output Power reduction for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	
6.2B.4.1.1 Configured Output Power Level for Intra-Band Contiguous EN-DC	Same as 6.2B.1.1	
6.2B.4.1.2 Configured Output Power for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.4.1.3 Configured Output Power for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	
6.3B.1.1 Minimum Output Power for intra-band contiguous EN-DC	Same as 6.3.1 in TS 38.521-1	
6.3B.1.2 Minimum output power for intra-band non-contiguous EN-DC	Same as 6.3.1 in TS 38.521-1	
6.3B.1.3 Minimum output power for inter-band EN-DC within FR1	Same as 6.3.1 in TS 38.521-1	
6.3B.1.4 Minimum Output Power for EN-DC Interband including FR2	Same as 6.3.1 in TS 38.521-1	
6.3B.2.1 Transmit OFF Power for intra-band contiguous EN-DC	Same as 6.3.2 in TS 38.521-1	
6.3B.2.2 Transmit OFF Power for intra-band non-contiguous EN-DC	Same as 6.3.2 in TS 38.521-1	
6.3B.2.3 Transmit OFF Power for inter-band EN-DC within FR1	Same as 6.3.2 in TS 38.521-1	
6.3B.3.1 Tx ON/OFF time mask for intra-band contiguous EN-DC	Same as 6.3.3 in TS 38.521-1	
6.3B.3.2 Tx ON/OFF time mask for intra-band non-contiguous EN-DC	Same as 6.3.3 in TS 38.521-1	
6.3B.3.3 Tx ON/OFF time mask for inter-band EN-DC within FR1	Same as 6.3.3 in TS 38.521-1	
6.4B.1.1 Frequency Error for intra-band contiguous EN-DC	TBD	
6.4B.1.2 Frequency Error for intra-band non-contiguous EN-DC	TBD	
6.4B.1.3 Frequency Error for inter-band EN-DC within FR1	Same as 6.4.1 in TS 38.521-1	
6.4B.1.5 Frequency Error for inter-band EN-DC including FR2	Same as 6.4.1 in TS 38.521-2	
6.4B.2.1.1 Error Vector Magnitude for intra-band contiguous EN-DC	TBD	



6.4B.2.1.2 Carrier Leakage for intra-band contiguous EN-DC	TBD	
6.4B.2.1.3 In-band Emissions for intra-band contiguous EN-DC	TBD	
6.4B.2.1.4 EVM Equalizer Flatness for intra-band contiguous EN-DC	TBD	
6.4B.2.2.1 Error Vector Magnitude for intra-band non-contiguous EN-DC	TBD	
6.4B.2.2.2 Carrier Leakage for intra-band non-contiguous EN-DC	TBD	
6.4B.2.2.3 In-band Emissions for intra-band non-contiguous EN-DC	TBD	
6.4B.2.2.4 EVM Equalizer Flatness for intra-band non-contiguous EN-DC	TBD	
6.4B.2.3.1 Error Vector Magnitude for inter-band EN-DC within FR1	Same as 6.4.2.1 in TS 38.521-1	
6.4B.2.3.2 Carrier Leakage for inter-band EN-DC within FR1	Same as 6.4.2.2 in TS 38.521-1	
6.4B.2.3.3 In-band Emissions for inter-band EN-DC within FR1	Same as 6.4.2.3 in TS 38.521-1	
6.4B.2.3.4 EVM Equalizer Flatness for inter-band EN-DC within FR1	Same as 6.4.2.4 in TS 38.521-1	
6.4B.2.4.1 Error Vector Magnitude for inter-band EN-DC including FR2	Same as 6.4.2.1 in TS 38.521-2	
6.4B.2.4.2 Carrier Leakage for inter-band EN-DC including FR2	Same as 6.4.2.2 in TS 38.521-2	
6.4B.2.4.3 In-band Emissions for inter-band EN-DC including FR2	Same as 6.4.2.3 in TS 38.521-2	
6.4B.2.4.4 EVM Equalizer Flatness for inter-band EN-DC including FR2	Same as 6.4.2.4 in TS 38.521-2	
6.5B.1.1 Occupied bandwidth for Intra-Band Contiguous EN-DC	1.5% of aggregated channel bandwidth	
6.5B.1.2 Occupied bandwidth for Intra-Band Non-Contiguous EN-DC	Same as 6.5.1 in TS 38.521-1	
6.5B.1.3 Occupied bandwidth for Inter-Band EN-DC within FR1	Same as 6.5.1 in TS 38.521-1	
6.5B.2.1.1 Spectrum emissions mask for intra-band contiguous EN-DC	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.1.2 Additional spectrum emissions mask for intra-band contiguous EN-DC	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.1.3 Adjacent channel leakage ratio for intra-band contiguous EN-DC	Same as 6.5.2.3 in TS 38.521-1	
6.5B.1.4 Occupied bandwidth for Inter-Band EN-DC including FR2	Same as 6.5.1 in TS 38.521-2	

6.5B.2.2.1 Spectrum emissions mask for intra-band non-contiguous EN-DC	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.2.2 Additional Spectrum emissions mask for intra-band non-contiguous EN-DC	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.2.3 Adjacent channel leakage ratio for intra-band non-contiguous EN-DC	TBD	
6.5B.2.3.1 Spectrum emissions mask for Inter-band EN-DC within FR1	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.3.2 Additional Spectrum emissions mask for Inter-band EN-DC within FR1	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.3.3 Adjacent channel leakage ratio for inter-band EN-DC within FR1	Same as 6.5.2.4.1 in TS 38.521-1	
6.5B.2.4.1 Spectrum emissions mask for Inter-band EN-DC including FR2	Same as 6.5.2.1 in TS 38.521-2	
6.5B.2.4.3 Adjacent channel leakage ratio for Inter-band EN-DC including FR2	Same as 6.5.2.3 in TS 38.521-2	
6.5B.3.1.1 General spurious emissions for intra-band contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.1.2 Spurious emission band UE co-existence for intra-band contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.2.1 General spurious emissions for Intra-band non-contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.2.2 Spurious Emission band UE co-existence for intra-band non-contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.3.1 General spurious emissions for Inter-band EN-DC within FR1	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.3.2 Spurious emission band UE co-existence for Inter-band within FR1	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.4.2 Spurious emission band UE co-existence for Inter-band including FR2	Same as 6.5.3.2 in TS 38.521-2	
6.5B.5.3 Transmit intermodulation for Inter-band EN-DC within FR1	Same as 6.5.4.3 in TS 38.521-1	

## F.1.3 Measurement of receiver

**Table F.1.3-1: Maximum Test System Uncertainty for receiver tests**

Subclause	Maximum Test System Uncertainty	Derivation of Test System Uncertainty
7.3B.2.1 Reference sensitivity for Intra-band Contiguous EN-DC	Same as 7.3.2 in TS 38.521-1	
7.3B.2.2 Reference sensitivity for Intra-band non-contiguous EN-DC	Same as 7.3.2 in TS 38.521-1	
7.3B.2.3 Reference sensitivity for Inter-band EN-DC within FR1	Same as 7.3.2 in TS 38.521-1	
7.4B.1 Maximum Input Level for Intra-Band Contiguous EN-DC	Same as 7.4 in TS 38.521-1	
7.4B.2 Maximum Input Level for Intra-Band Non-Contiguous EN-DC	Same as 7.4 in TS 38.521-1	
7.4B.3 Maximum Input Level for Inter-band EN-DC within FR1	Same as 7.4 in TS 38.521-1	
7.5B.1 Adjacent Channel Selectivity for intra-band contiguous EN-DC	TBD	
7.5B.2 Adjacent Channel Selectivity for intra-band non-contiguous EN-DC	TBD	
7.5B.3 Adjacent Channel Selectivity for inter-band EN-DC within FR1	Same as 7.5 in TS 38.521-1	
7.6B.2.1 Inband blocking for intra-band contiguous EN-DC in FR1	TBD	
7.6B.2.2 Inband blocking for intra-band non-contiguous EN-DC in FR1	TBD	
7.6B.2.3 Inband blocking for inter-band EN-DC within FR1	Same as 7.6.2 in TS 38.521-1	
7.6B.3.1 Out-of-band blocking for intra-band contiguous EN-DC in FR1	TBD	
7.6B.3.2 Out-of-band blocking for intra-band non-contiguous EN-DC in FR1	TBD	
7.6B.3.3 Out-of-band blocking for inter-band EN-DC within FR1	Same as 7.6.3 in TS 38.521-1	
7.6B.4.1 Narrow band blocking for intra-band contiguous EN-DC in FR1	TBD	
7.6B.4.2 Narrow band blocking for intra-band non-contiguous EN-DC in FR1	TBD	
7.6B.4.3 Narrow band blocking for inter-band EN-DC within FR1	Same as 7.6.4 in TS 38.521-1	
7.7B.1 Spurious Response for intra-band contiguous EN-DC in FR1	TBD	
7.7B.2 Spurious Response for intra-band non-contiguous EN-DC in FR1	TBD	
7.7B.3 Spurious Response for inter-band EN-DC within FR1	Same as 7.7 in TS 38.521-1	

7.8B.2.1 Wideband Intermodulation for intra-band contiguous EN-DC in FR1	Same as 7.8.2 in TS 38.521-1	
7.8B.2.2 Wideband Intermodulation for intra-band non-contiguous EN-DC in FR1	Same as 7.8.2 in TS 38.521-1	
7.8B.2.3 Wideband Intermodulation for inter-band EN-DC within FR1	Same as 7.8.2 in TS 38.521-1	
7.9B.1 Spurious Emissions for intra-band contiguous EN-DC within FR1	Same as 7.9 in TS 38.521-1	
7.9B.2 Spurious Emissions for intra-band non-contiguous EN-DC within FR1	Same as 7.9 in TS 38.521-1	
7.9B.3 Spurious Emissions for inter-band EN-DC within FR1	Same as 7.9 in TS 38.521-1	

## F.2 Interpretation of measurement results (normative)

TBD

## F.3 Test Tolerance and Derivation of Test Requirements (informative)

TBD

### F.3.1 Measurement of test environments

TBD

## F.3.2 Measurement of transmitter

**Table F.3.2-1: Derivation of Test Requirements (Transmitter tests)**

Sub clause	Test Tolerance (TT)	Formula for test requirement
6.2B.1.1 UE Maximum Output Power for Intra-Band Contiguous EN-DC	Same as 6.2.1 in TS 38.521-1	
6.2B.1.2 UE Maximum Output Power for Intra-Band Non-Contiguous EN-DC	<p>MAX (<math>TT_{LTE}</math>, <math>TT_{SA}</math>)</p> <p><math>TT_{LTE}</math>  <math>\pm 0.7</math> dB, <math>f \leq 3.0</math>GHz  <math>\pm 1.0</math> dB, <math>3.0</math>GHz &lt; <math>f \leq 4.2</math>GHz</p> <p><math>TT_{SA}</math>  <math>f \leq 3.0</math>GHz  0.7 dB, <math>BW \leq 40</math>MHz  1.0 dB, <math>40</math>MHz &lt; <math>BW \leq 100</math>MHz  3.0GHz &lt; <math>f \leq 6.0</math>GHz  1.0 dB, <math>BW \leq 100</math>MHz</p>	<p><math>TT_{LTE}</math> is TT of LTE specified in 6.2.2 in TS 36.521-1.</p> <p><math>TT_{SA}</math> is TT of FR1 SA specified in 6.2.1 in TS 38.521-1.</p>
6.2B.1.3 UE Maximum Output Power for Inter-Band EN-DC within FR1	<p>MAX (<math>TT_{LTE}</math>, <math>TT_{SA}</math>)</p> <p><math>TT_{LTE}</math>  <math>\pm 0.7</math> dB, <math>f \leq 3.0</math>GHz  <math>\pm 1.0</math> dB, <math>3.0</math>GHz &lt; <math>f \leq 4.2</math>GHz</p> <p><math>TT_{SA}</math>  <math>f \leq 3.0</math>GHz  0.7 dB, <math>BW \leq 40</math>MHz  1.0 dB, <math>40</math>MHz &lt; <math>BW \leq 100</math>MHz  3.0GHz &lt; <math>f \leq 6.0</math>GHz  1.0 dB, <math>BW \leq 100</math>MHz</p>	<p><math>TT_{LTE}</math> is TT of LTE specified in 6.2.3 in TS 36.521-1.</p> <p><math>TT_{SA}</math> is TT of FR1 SA specified in 6.2.2 in TS 38.521-1.</p>
6.2B.1.4 UE Maximum Output Power for Inter-Band EN-DC including FR2	Same as 6.2.1 in TS 38.521-2	
6.2B.2.1 UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	Same as 6.2.2 in TS 38.521-1	
6.2B.2.2 UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.2.3 UE Maximum Output Power reduction for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	
6.2B.3.1 UE Additional Maximum Output Power reduction for Intra-band contiguous EN-DC	Same as 6.2.3 in TS 38.521-1	
6.2B.3.2 UE Additional Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.3.3 UE Additional Maximum Output Power reduction for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	
6.2B.4.1.1 Configured Output Power Level for Intra-Band Contiguous EN-DC	Same as 6.2.4 in TS 38.521-1	
6.2B.4.1.2 Configured Output Power for Intra-Band Non-Contiguous EN-DC	Same as 6.2B.1.2	
6.2B.4.1.3 Configured Output Power for Inter-Band EN-DC within FR1	Same as 6.2B.1.3	
6.3B.1.1 Minimum Output Power for intra-band contiguous EN-DC	Same as 6.3.1 in TS 38.521-1	

6.3B.1.2 Minimum output power for intra-band non-contiguous EN-DC	Same as 6.3.1 in TS 38.521-1	
6.3B.1.3 Minimum output power for inter-band EN-DC within FR1	Same as 6.3.1 in TS 38.521-1	
6.3B.1.4 Minimum Output Power for EN-DC Interband including FR2	Same as 6.3.1 in TS 38.521-2	
6.3B.2.1 Transmit OFF Power for intra-band contiguous EN-DC	Same as 6.3.2 in TS 38.521-1	
6.3B.2.2 Transmit OFF Power for intra-band non-contiguous EN-DC	Same as 6.3.2 in TS 38.521-1	
6.3B.2.3 Transmit OFF Power for inter-band EN-DC within FR1	Same as 6.3.2 in TS 38.521-1	
6.3B.3.1 Transmit OFF Power for intra-band contiguous EN-DC	Same as 6.3.3 in TS 38.521-1	
6.3B.3.2 Transmit OFF Power for intra-band non-contiguous EN-DC	Same as 6.3.3 in TS 38.521-1	
6.3B.3.3 Transmit OFF Power for inter-band EN-DC within FR1	Same as 6.3.3 in TS 38.521-1	
6.4B.1.1 Frequency Error for intra-band contiguous EN-DC	Same as 6.4.1 in TS 38.521-1	
6.4B.1.2 Frequency Error for intra-band non-contiguous EN-DC	Same as 6.4.1 in TS 38.521-1	
6.4B.1.3 Frequency Error for inter-band EN-DC within FR1	Same as 6.4.1 in TS 38.521-1	
6.4B.1.5 Frequency Error for inter-band EN-DC including FR2	Same as 6.4.1 in TS 38.521-2	
6.4B.2.1.1 Error Vector Magnitude for intra-band contiguous EN-DC	Same as 6.4.2.1 in TS 38.521-1	
6.4B.2.1.2 Carrier Leakage for intra-band contiguous EN-DC	Same as 6.4.2.2 in TS 38.521-1	
6.4B.2.1.3 In-band Emissions for intra-band contiguous EN-DC	Same as 6.4.2.3 in TS 38.521-1	
6.4B.2.1.4 EVM Equalizer Flatness for intra-band contiguous EN-DC	Same as 6.4.2.4 in TS 38.521-1	
6.4B.2.2.1 Error Vector Magnitude for intra-band non-contiguous EN-DC	Same as 6.4.2.1 in TS 38.521-1	
6.4B.2.2.2 Carrier Leakage for intra-band non-contiguous EN-DC	Same as 6.4.2.2 in TS 38.521-1	
6.4B.2.2.3 In-band Emissions for intra-band non-contiguous EN-DC	Same as 6.4.2.3 in TS 38.521-1	
6.4B.2.2.4 EVM Equalizer Flatness for intra-band non-contiguous EN-DC	Same as 6.4.2.4 in TS 38.521-1	
6.4B.2.3.1 Error Vector Magnitude for inter-band EN-DC within FR1	Same as 6.4.2.1 in TS 38.521-1	
6.4B.2.3.2 Carrier Leakage for inter-band EN-DC within FR1	Same as 6.4.2.2 in TS 38.521-1	



6.4B.2.3.3 In-band Emissions for inter-band EN-DC within FR1	Same as 6.4.2.3 in TS 38.521-1	
6.4B.2.3.4 EVM Equalizer Flatness for inter-band EN-DC within FR1	Same as 6.4.2.4 in TS 38.521-1	
6.4B.2.4.1 Error Vector Magnitude for inter-band EN-DC including FR2	Same as 6.4.2.1 in TS 38.521-2	
6.4B.2.4.2 Carrier Leakage for inter-band EN-DC including FR2	Same as 6.4.2.2 in TS 38.521-2	
6.4B.2.4.3 In-band Emissions for inter-band EN-DC including FR2	Same as 6.4.2.3 in TS 38.521-2	
6.4B.2.4.4 EVM Equalizer Flatness for inter-band EN-DC including FR2	Same as 6.4.2.4 in TS 38.521-2	
6.5B.1.1 Occupied bandwidth for Intra-Band Contiguous EN-DC	Same as 6.5.1 in TS 38.521-1	
6.5B.1.2 Occupied bandwidth for Intra-Band Non-Contiguous EN-DC	Same as 6.5.1 in TS 38.521-1	
6.5B.1.3 Occupied bandwidth for Inter-Band EN-DC within FR1	Same as 6.5.1 in TS 38.521-1	
6.5B.1.4 Occupied bandwidth for Inter-Band EN-DC including FR2	Same as 6.5.1 in TS 38.521-2	
6.5B.2.1.1 Spectrum emissions mask for intra-band contiguous EN-DC	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.1.2 Additional spectrum emissions mask for intra-band contiguous EN-DC	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.1.3 Adjacent channel leakage ratio for intra-band contiguous EN-DC	Same as 6.5.2.4.1 in TS 38.521-1	
6.5B.2.2.1 Spectrum emissions mask for intra-band non-contiguous EN-DC	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.2.2 Additional Spectrum emissions mask for intra-band non-contiguous EN-DC	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.2.3 Adjacent channel leakage ratio for intra-band non-contiguous EN-DC	Same as 6.5.2.4.1 in TS 38.521-1	
6.5B.2.3.1 Spectrum emissions mask for Inter-band EN-DC within FR1	Same as 6.5.2.2 in TS 38.521-1	
6.5B.2.3.2 Additional Spectrum emissions mask for Inter-band EN-DC within FR1	Same as 6.5.2.3 in TS 38.521-1	
6.5B.2.3.3 Adjacent channel leakage ratio for inter-band EN-DC within FR1	Same as 6.5.2.4.1 in TS 38.521-1	
6.5B.2.4.1 Spectrum emissions mask for Inter-band EN-DC including FR2	Same as 6.5.2.1 in TS 38.521-2	
6.5B.2.4.3 Adjacent channel leakage ratio for Inter-band EN-DC including FR2	Same as 6.5.2.3 in TS 38.521-2	
6.5B.3.1.1 General spurious emissions for intra-band contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	

6.5B.3.1.2 Spurious emission band UE co-existence for intra-band contiguous EN-DC	Same as 6.5.3.2 in TS 38.521-1	
6.5B.3.2.1 General spurious emissions for Intra-band non-contiguous EN-DC	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.2.2 Spurious Emission band UE co-existence for intra-band non-contiguous EN-DC	Same as 6.5.3.2 in TS 38.521-1	
6.5B.3.3.1 General spurious emissions for Inter-band EN-DC within FR1	Same as 6.5.3.1 in TS 38.521-1	
6.5B.3.3.2 Spurious emission band UE co-existence for Inter-band within FR1	Same as 6.5.3.2 in TS 38.521-1	
6.5B.3.4.2 Spurious emission band UE co-existence for Inter-band including FR2	Same as 6.5.3.2 in TS 38.521-2	
6.5B.5.3 Transmit intermodulation for Inter-band EN-DC within FR1	Same as 6.5.4 in TS 38.521-1	

### F.3.3 Measurement of receiver

**Table F.3.3-1: Derivation of Test Requirements (Receiver tests)**

Sub clause	Test Tolerance (TT)	Formula for test requirement
7.3B.2.1 Reference sensitivity for Intra-band Contiguous EN-DC	Same as 7.3.2 in TS 38.521-1	
7.3B.2.2 Reference sensitivity for Intra-band non-contiguous EN-DC	Same as 7.3.2 in TS 38.521-1	
7.3B.2.3 Reference sensitivity for Inter-band EN-DC within FR1	Same as 7.3.2 in TS 38.521-1	
7.4B.1 Maximum Input Level for Intra-Band Contiguous EN-DC	Same as 7.4 in TS 38.521-1	
7.4B.2 Maximum Input Level for Intra-Band Non-Contiguous EN-DC	Same as 7.4 in TS 38.521-1	
7.4B.3 Maximum Input Level for Inter-band EN-DC within FR1	Same as 7.4 in TS 38.521-1	
7.5B.1 Adjacent Channel Selectivity for intra-band contiguous EN-DC	Same as 7.5 in TS 38.521-1	
7.5B.2 Adjacent Channel Selectivity for intra-band non-contiguous EN-DC	Same as 7.5 in TS 38.521-1	
7.5B.3 Adjacent Channel Selectivity for inter-band EN-DC within FR1	Same as 7.5 in TS 38.521-1	
7.6B.2.1 Inband blocking for intra-band contiguous EN-DC in FR1	Same as 7.6.2 in TS 38.521-1	
7.6B.2.2 Inband blocking for intra-band non-contiguous EN-DC in FR1	Same as 7.6.2 in TS 38.521-1	
7.6B.2.3 Inband blocking for inter-band EN-DC within FR1	Same as 7.6.2 in TS 38.521-1	
7.6B.3.1 Out-of-band blocking for intra-band contiguous EN-DC in FR1	Same as 7.6.3 in TS 38.521-1	
7.6B.3.2 Out-of-band blocking for intra-band non-contiguous EN-DC in FR1	Same as 7.6.3 in TS 38.521-1	
7.6B.3.3 Out-of-band blocking for inter-band EN-DC within FR1	Same as 7.6.3 in TS 38.521-1	
7.6B.4.1 Narrow band blocking for intra-band contiguous EN-DC in FR1	Same as 7.6.4 in TS 38.521-1	
7.6B.4.2 Narrow band blocking for intra-band non-contiguous EN-DC in FR1	Same as 7.6.4 in TS 38.521-1	
7.6B.4.3 Narrow band blocking for inter-band EN-DC within FR1	Same as 7.6.4 in TS 38.521-1	
7.7B.1 Spurious Response for intra-band contiguous EN-DC in FR1	Same as 7.7 in TS 38.521-1	
7.7B.2 Spurious Response for intra-band non-contiguous EN-DC in FR1	Same as 7.7 in TS 38.521-1	
7.7B.3 Spurious Response for inter-band EN-DC within FR1	Same as 7.7 in TS 38.521-1	
7.8B.2.1 Wideband Intermodulation for intra-band contiguous EN-DC in FR1	Same as 7.8.2 in TS 38.521-1	

7.8B.2.2 Wideband Intermodulation for intra-band non-contiguous EN-DC in FR1	Same as 7.8.2 in TS 38.521-1	
7.8B.2.3 Wideband Intermodulation for inter-band EN-DC within FR1	Same as 7.8.2 in TS 38.521-1	
7.9B.1 Spurious Emissions for intra-band contiguous EN-DC within FR1	Same as 7.9 in TS 38.521-1	
7.9B.2 Spurious Emissions for intra-band non-contiguous EN-DC within FR1	Same as 7.9 in TS 38.521-1	
7.9B.3 Spurious Emissions for inter-band EN-DC within FR1	Same as 7.9 in TS 38.521-1	

---

## Annex G (normative): Uplink Physical Channels

Please refer to Annex G in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. EN-DC exceptions will be added.

---

# Annex H (normative): Statistical Testing

## Editor's Note:

- Further investigate the technical details behind this statistical method to ensure that this is applicable for FR2 radiated test cases.

## H.1 General

FFS.

## H.2 Statistical testing of receiver characteristics

### H.2.1 General

The test of receiver characteristics is twofold.

1. A signal or a combination of signals is offered to the RX port(s) of the receiver.
2. The ability of the receiver to demodulate /decode this signal is verified by measuring the throughput.

In (2) is the statistical aspect of the test and is treated here.

The minimum requirement for all receiver tests is >95% of the maximum throughput.

All receiver tests are performed in static propagation conditions. No fading conditions are applied.

### H.2.2 Mapping throughput to error ratio

- a) The measured information bit throughput  $R$  is defined as the sum (in kilobits) of the information bit payloads successfully received during the test interval, divided by the duration of the test interval (in seconds).
- b) In measurement practice the UE indicates successfully received information bit payload by signalling an ACK to the SS.  
If payload is received, but damaged and cannot be decoded, the UE signals a NACK.
- c) Only the ACK and NACK signals, not the data bits received, are accessible to the SS.  
The number of bits is known in the SS from knowledge of what payload was sent.
- d) For the reference measurement channel, applied for testing, the number of bits is different in different subframes, however in a radio frame it is fixed during one test.
- e) The time in the measurement interval is composed of successfully received subframes (ACK), unsuccessfully received subframes (NACK) and no reception at all (DTX-subframes).
- f) DTX-subframes may occur regularly according the applicable reference measurement channel (regDTX).  
In real live networks this is the time when other UEs are served. In TDD these are the UL and special subframes. regDTX vary from test to test but are fixed within the test.
- g) Additional DTX-subframes occur statistically when the UE is not responding ACK or NACK where it should. (statDTX)  
This may happen when the UE was not expecting data or decided that the data were not intended for it.

The pass / fail decision is done by observing the:

- number of NACKs
- number of ACKs and
- number of statDTXs (regDTX is implicitly known to the SS)

The ratio  $(NACK + statDTX)/(NACK + statDTX + ACK)$  is the Error Ratio (ER). Taking into account the time consumed by the ACK, NACK, and DTX-TTIs (regular and statistical), ER can be mapped unambiguously to throughput for any single reference measurement channel test.

### H.2.3 Design of the test

The test is defined by the following design principles (see clause H.x, Theory...):

1. The early decision concept is applied.
2. A second limit is introduced: Bad DUT factor  $M > 1$
3. To decide the test pass:  
Supplier risk is applied based on the Bad DUT quality  
To decide the test fail  
Customer Risk is applied based on the specified DUT quality

The test is defined by the following parameters:

1. Limit ER = 0.05 (Throughput limit = 95%)
2. Bad DUT factor  $M = 1.5$  (selectivity)
3. Confidence level CL = 95% (for specified DUT and Bad DUT-quality)



## H.2.4 Numerical definition of the pass fail limits

Table H.2.4-1: pass fail limits

ne	ns <sub>p</sub>	ns <sub>f</sub>	ne	ns <sub>p</sub>	ns <sub>f</sub>	ne	ns <sub>p</sub>	ns <sub>f</sub>	ne	ns <sub>p</sub>	ns <sub>f</sub>
0	67	NA	39	763	500	78	1366	1148	117	1951	1828
1	95	NA	40	778	516	79	1381	1166	118	1965	1845
2	119	NA	41	794	532	80	1396	1183	119	1980	1863
3	141	NA	42	810	548	81	1412	1200	120	1995	1881
4	162	NA	43	826	564	82	1427	1217	121	2010	1899
5	183	NA	44	842	580	83	1442	1234	122	2025	1916
6	202	NA	45	858	596	84	1457	1252	123	2039	1934
7	222	NA	46	873	612	85	1472	1269	124	2054	1952
8	241	NA	47	889	629	86	1487	1286	125	2069	1969
9	259	NA	48	905	645	87	1502	1303	126	2084	1987
10	278	76	49	920	661	88	1517	1321	127	2099	2005
11	296	88	50	936	678	89	1532	1338	128	2113	2023
12	314	100	51	952	694	90	1547	1355	129	2128	2040
13	332	113	52	967	711	91	1562	1373	130	2143	2058
14	349	126	53	983	727	92	1577	1390	131	2158	2076
15	367	140	54	998	744	93	1592	1407	132	2172	2094
16	384	153	55	1014	760	94	1607	1425	133	2187	2111
17	401	167	56	1029	777	95	1623	1442	134	2202	2129
18	418	181	57	1045	793	96	1637	1459	135	2217	2147
19	435	195	58	1060	810	97	1652	1477	136	2231	2165
20	452	209	59	1076	827	98	1667	1494	137	2246	2183
21	469	224	60	1091	844	99	1682	1512	138	2261	2201
22	486	238	61	1106	860	100	1697	1529	139	2275	2218
23	503	253	62	1122	877	101	1712	1547	140	2290	2236
24	519	268	63	1137	894	102	1727	1564	141	2305	2254
25	536	283	64	1153	911	103	1742	1582	142	2320	2272
26	552	298	65	1168	928	104	1757	1599	143	2334	2290
27	569	313	66	1183	944	105	1772	1617	144	2349	2308
28	585	328	67	1199	961	106	1787	1634	145	2364	2326
29	602	343	68	1214	978	107	1802	1652	146	2378	2344
30	618	359	69	1229	995	108	1817	1669	147	2393	2361
31	634	374	70	1244	1012	109	1832	1687	148	2408	2379
32	650	389	71	1260	1029	110	1847	1704	149	2422	2397
33	667	405	72	1275	1046	111	1861	1722	150	2437	2415
34	683	421	73	1290	1063	112	1876	1740	151	2452	2433
35	699	436	74	1305	1080	113	1891	1757	152	2466	2451
36	715	452	75	1321	1097	114	1906	1775	153*)	NA	2469
37	731	468	76	1336	1114	115	1921	1793			
38	747	484	77	1351	1131	116	1936	1810	*) note 2 in H.2.5		

NOTE 1: The first column is the number of errors (ne = number of NACK + statDTX)

NOTE 2: The second column is the number of samples for the pass limit (ns<sub>p</sub>, ns=Number of Samples= number of NACK + statDTX + ACK)

NOTE 3: The third column is the number of samples for the fail limit (ns<sub>f</sub>)

## H.2.5 Pass fail decision rules

The pass fail decision rules apply for a single test, comprising one component in the test vector. The over all Pass /Fail conditions are defined in clause H.2.6 and H.2.A.6

Having observed 0 errors, pass the test at 67+ samples, otherwise continue

Having observed 1 error, pass the test at 95+ otherwise continue

Having observed 2 errors, pass the test at 119+ samples, fail the test at 2- samples, otherwise continue

Etc. etc.

Having observed 151 errors, pass the test at 2452+ samples, fail the test at 2433- samples, otherwise continue

Having observed 152 errors, pass the test at 2466+ samples, fail the test at 2451- samples.

Where x+ means: x or more, x- means x or less

NOTE 1: an ideal DUT passes after 67 samples. The maximum test time is 2466 samples.

NOTE 2: It is allowed to deviate from the early decision concept by postponing the decision (pass/fail or continue). Postponing the decision to or beyond the end of Table H.2.4-1 requires a pass fail decision against the test limit: pass the DUT for  $ER < 0.0618$ , otherwise fail.

## Annex I (normative): Void

---

## Annex J (normative): Test applicability per permitted test method

Please refer to Annex J in TS 38.521-1 [8] and 38.521-2 [9] for appropriate details as needed for test cases in this test specification. Exceptions for EN-DC may be added as needed.

---

## Annex K (normative): EIRP, TRP, and EIS measurement procedures

Please refer to Annex K in 38.521-2 [9] for appropriate details as needed for test cases in this test specification. Exceptions for EN-DC may be added as needed.

## Annex L (normative): Void

---

## Annex M (normative): Dual uplink interferer

UE is mandated to support operation in dual uplink mode also in EN-DC configuration for FR1 listed in Table 7.3.2.1.5-1 and indicated by column single uplink allowed if the intermodulation products caused by the dual uplink operation do not interfere own primary downlink transmission channel bandwidth. For intermodulation products falling into LTE secondary downlink channel bandwidth, UE single UL capability is not considered.

Formula for determining if the EN-DC in NR FR1 configuration with dual uplink operation interferes own downlink reception.

Interference bandwidth:  $IBW = |a| * CBW1 + |b| * CBW2$

- $|a| + |b| = 2$  (or 3)
- CBW1 and CBW2 are the transmission bandwidth configurations of the UL channels

Center frequency of IBW:  $f_{IBW} = |a * f1 + b * f2|$

- f1 and f2 are center frequency of the transmission bandwidth configurations of each UL channel

The range of IMD 2 (or 3):  $[f_{IBW} - IBW/2, f_{IBW} + IBW/2]$

NOTE 1: UE shall be able to apply operations which are configured by RRC reconfiguration and corresponding HARQ timing on the transmission bandwidth.

NOTE 2: For identified difficult band combination, during two adjacent RRC reconfiguration, the changing of transmission bandwidth should not introduce IM2 and IM3, which will result in UE changing from 2Tx to 1Tx. Otherwise, UE behavior is not specified.

For DC\_3A\_n3A intra-band non-contiguous EN-DC combination, only single switched UL is supported in rel.15.

## Annex N (informative): Change history



Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-08	RAN5#76	R5-174710	-	-	-	Draft skeleton	0.0.1
2018-01	RAN5#1-5G-NR Adhoc	R5-180086	-	-	-	TP to add clause 6.2B.3.3 UE A-MPR intra-band EN-DC to 38.521-3	0.1.0
2018-01	RAN5#1-5G-NR Adhoc	R5-180087	-	-	-	TP to add clause 6.5B.2.1.2 Additional Spectrum emissions mask (contiguous sub-blocks) for intra-band EN-DC to 38.521-3	0.1.0
2018-02	RAN5#78	R5-181509	-	-	-	Updated 38.521-3 for new Annex A Dual uplink interferer information	0.2.0
2018-02	RAN5#78	R5-181690	-	-	-	Updated 38.521-3 for channel bandwidth information	0.2.0
2018-03	RAN5#2-5G-NR Adhoc	R5-181760	-	-	-	Draft TS 38.521-3 0.3.0	0.3.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182035	-	-	-	5G-NR Text Proposal to add spurious emissions test case to 38.521-3	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182016	-	-	-	TP for new test case: 6.5B.2.1.3, Adjacent channel leakage ratio for intra-band contiguous EN-DC	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182017	-	-	-	TP to update clause 6.2B.3.1 UE A-MPR intra-band EN-DC to 38.521-3	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182018	-	-	-	TP to update clause 6.5B.2.1.2 Additional spectrum emission mask to 38.521-3	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-181807	-	-	-	Update to Operating bands of 38.521-3	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-181808	-	-	-	Update to section 3 and section 4 of 38.521-3	0.4.0
2018-04	RAN5#2-5G-NR Adhoc	R5-181828	-	-	-	Updated 38.521-3 for channel bandwidth information with new structure	0.4.0
2018-07	RAN5#79	R5-183961	-	-	-	5G_FR1_EN_DC_RF_sensitivity_for_DC	0.5.0
2018-07	RAN5#79	R5-183962	-	-	-	Introduction of TC 6.2B.1.3 for EN-DC	0.5.0
2018-07	RAN5#79	R5-183949	-	-	-	Statistical Testing Annex for 38.521-3	0.5.0
2018-07	RAN5#79	<a href="#">R5-182995</a>	-	-	-	Corrections annex for EIRP and TRP metric definition in TS 38.521-3	0.5.0
2018-07	RAN5#79	<a href="#">R5-183707</a>	-	-	-	TP for updating test case 6.2B.2.1, UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	0.5.0
2018-07	RAN5#79	<a href="#">R5-183708</a>	-	-	-	Updated clause 5.5B Configuration for DC to 38.521-3	0.5.0
2018-07	RAN5#79	<a href="#">R5-183709</a>	-	-	-	TP to add Occupied BW EN-DC test case	0.5.0
2018-07	RAN5#79	<a href="#">R5-183710</a>	-	-	-	TP to add SEM EN-DC test case	0.5.0
2018-07	RAN5#79	<a href="#">R5-183711</a>	-	-	-	TP to add ACLR EN-DC test case	0.5.0
2018-09	RAN5#80	<a href="#">R5-185563</a>	-	-	-	FR2_StoreTxRxBeamPeakCoordinates_38.521-3	1.0.0
2018-09	RAN5#80	R5-185520	-	-	-	Addition of TRx MU and TT in TS 38.521-3 Annex	1.0.0
2018-09	RAN5#80	R5-185503	-	-	-	Add Clause 7.5B.1 into TS 38.521-3	1.0.0
2018-09	RAN5#80	R5-185504	-	-	-	Add Clause 7.5B.2 into TS 38.521-3	1.0.0
2018-09	RAN5#80	R5-185505	-	-	-	Add Clause 7.5B.3 into TS 38.521-3	1.0.0
2018-09	RAN5#80	<a href="#">R5-184579</a>	-	-	-	Updated EN-DC configuration information in clause 5	1.0.0
2018-09	RAN5#80	<a href="#">R5-184580</a>	-	-	-	TIB value add for EN-DC band in 38.521-3	1.0.0
2018-09	RAN5#80	<a href="#">R5-184671</a>	-	-	-	Update of References in Section 2 of 38.521-3 spec	1.0.0
2018-09	RAN5#80	<a href="#">R5-184672</a>	-	-	-	Updates to Operating Bands in Section 5.2	1.0.0
2018-09	RAN5#80	<a href="#">R5-184737</a>	-	-	-	Dual uplink interferer updated to 38.521-3	1.0.0
2018-09	RAN5#80	<a href="#">R5-184737</a>	-	-	-	Dual uplink interferer updated to 38.521-3	1.0.0
2018-09	RAN5#80	<a href="#">R5-185332</a>	-	-	-	Addition of 6.2B.4.1.1 Configured OP for Intra-Band Contiguous EN-DC	1.0.0
2018-09	RAN5#80	<a href="#">R5-185333</a>	-	-	-	Addition of 6.2B.4.1.2 Configured OP for Intra-Band Non-Contiguous EN-DC	1.0.0
2018-09	RAN5#80	<a href="#">R5-185507</a>	-	-	-	Addition of 6.2B.4.1.3 Configured OP for Inter-Band within FR1	1.0.0
2018-09	RAN5#80	R5-185198	-	-	-	Addition of 6.2B.4.1.4 Configured OP for Inter-Band EN-DC including FR2	1.0.0
2018-09	RAN5#80	R5-185199	-	-	-	Addition of 6.2B.4.1.5 Configured OP for Inter-Band EN-DC including both FR1 and FR2	1.0.0
2018-09	RAN5#80	R5-185469	-	-	-	TP for updating test case 6.2B.3.1 UE AMPR for Intra-band contiguous EN-DC	1.0.0
2018-09	RAN5#80	R5-185470	-	-	-	TP for updating test case 6.2B.3.2 UE AMPR for Intra-band non-contiguous EN-DC	1.0.0
2018-09	RAN5#80	R5-185200	-	-	-	TP for updating test case 6.5B.2.1.2 Additional spectrum emission mask for intra-band contiguous EN-DC	1.0.0

2018-09	RAN5#80	<a href="#">R5-185556</a>	-	-	-	FR2_UE_BeamlockInvoke_38.521-3	1.0.0
2018-09	RAN5#80	<a href="#">R5-185472</a>	-	-	-	Update of TC 6.2B.1.1	1.0.0
2018-09	RAN5#80	<a href="#">R5-185473</a>	-	-	-	Introduction of TC 6.2B.1.2	1.0.0
2018-09	RAN5#80	<a href="#">R5-185474</a>	-	-	-	Update of 6.2B.1.3	1.0.0
2018-09	RAN5#80	R5-185201	-	-	-	Introduction of TC 7.4B.1	1.0.0
2018-09	RAN5#80	R5-185202	-	-	-	Introduction of 7.4B.2	1.0.0
2018-09	RAN5#80	R5-185203	-	-	-	Introduction of 7.4B.3	1.0.0
2018-09	RAN5#80	<a href="#">R5-185479</a>	-	-	-	Update Occupied Bandwidth for interband EN-DC within FR1	1.0.0
2018-09	RAN5#80	<a href="#">R5-185480</a>	-	-	-	Update SEM interband EN-DC within FR1	1.0.0
2018-09	RAN5#80	<a href="#">R5-185481</a>	-	-	-	Update ACLR for interband EN-DC within FR1	1.0.0
2018-09	RAN5#80	R5-185204	-	-	-	5G NR_EN_DC with FR1_Text update for RX sensitivity	1.0.0
2018-09	RAN5#80	R5-185205	-	-	-	5G NR_EN_DC with FR1_Text_proposal for_TX_Spurious_emission	1.0.0
2018-09	RAN5#80	<a href="#">R5-185422</a>	-	-	-	Alignment of Annex numbering with core spec	1.0.0
2018-09	RAN5#80	<a href="#">R5-184897</a>	-	-	-	Updates to Channel Arrangement section in 38.521-3	1.0.0
2018-09	RAN5#80	R5-185206	-	-	-	Addition of TC6.3B.1.1 Minimum Output power for intra-band contiguous EN-DC	1.0.0
2018-09	RAN5#80	R5-185207	-	-	-	Addition of TC6.3B.1.2 Minimum output power for intra-band non-contiguous EN-DC	1.0.0
2018-09	RAN5#80	R5-185208	-	-	-	Addition of TC6.3B.1.3 Minimum output power for inter-band EN-DC within FR1	1.0.0
2018-09	RAN5#80	<a href="#">R5-185351</a>	-	-	-	Update across EN-DC RF test cases in TS 38.521-3	1.0.0
2018-09	RAN#81	-	-	-	-	raised to v15.0.0 with editorial changes only	15.0.0
2018-12	RAN#82	R5-186503	0033	-	F	FR2 Spurious Emission test case updates	15.1.0
2018-12	RAN#82	R5-186506	0034	-	F	Update Text on Store Beam Peak Coordinate	15.1.0
2018-12	RAN#82	R5-186507	0035	-	F	38.521-3 Applicability Rules	15.1.0
2018-12	RAN#82	R5-186601	0039	-	F	5G NR_EN_DC with FR1_Text update for Intra-Band Contiguous RX sensitivity	15.1.0
2018-12	RAN#82	R5-186602	0040	-	F	5G NR_Text update for TX spurious emission intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-186608	0042	-	F	Spurious emission band UE co-existence for Inter-band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-186672	0044	-	F	Updating test case 6.2B.3.1 Additional Maximum Output Power reduction for Intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-186673	0045	-	F	Updating test case 6.5B.2.1.2 Additional spectrum emissions mask for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-186681	0046	-	F	Updates to EN-DC test case 6.2B.2.1, UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-186684	0047	-	F	Updates to test case 6.2B.2.3, UE Maximum Output Power reduction for Inter-Band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-186788	0049	-	F	Minor update OBW, SEM and ACLR inter-band FR1 test cases	15.1.0
2018-12	RAN#82	R5-187153	0061	-	F	Updated EN-DC configuration information in clause 5	15.1.0
2018-12	RAN#82	R5-187371	0076	-	F	Addition of TC6.3B.2.1 Transmit OFF Power for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187372	0077	-	F	Addition of TC6.3B.2.3 Transmit OFF Power for inter-band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-187373	0078	-	F	Addition of TC6.3B.2.2 Transmit OFF Power for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187552	0083	-	F	Updates to TS 38.521-3 common sections 1-4 to align with core spec	15.1.0
2018-12	RAN#82	R5-187559	0084	-	F	Updates to TS 38.521-3 Section 5 to align with core spec	15.1.0
2018-12	RAN#82	R5-187562	0085	-	F	Update to TC6.5B.3.2.1 - General Spurious Emissions for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187563	0086	-	F	Update to 7.3B.2.2 - REFSENS for Intra-band Non-Contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187565	0087	-	F	Updates to TS 38.521-3 Section 4 with LTE anchor details	15.1.0
2018-12	RAN#82	R5-187614	0094	-	F	Updates to EN-DC test case 6.2B.2.2, UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187816	0048	1	F	Adding test case 6.2B.2.4, UE Maximum Output Power reduction for Inter-Band EN-DC including FR2	15.1.0
2018-12	RAN#82	R5-187819	0053	1	F	Update general parameter Connection without release in initial conditions in TS 38.521-3	15.1.0
2018-12	RAN#82	R5-187820	0043	1	F	Updates to test case 6.5B.2.1.3, Adjacent channel leakage ratio for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187821	0052	1	F	Addition OBW intraband non contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187822	0055	1	F	Introduction of New test case 6.4B.2.2.1 Error Vector Magnitude for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187823	0056	1	F	Introduction of New test case 6.4B.2.2.2 Carrier Leakage for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187825	0058	1	F	Introduction of New test case 6.4B.2.3.1 Error Vector Magnitude for inter-band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-187826	0059	1	F	Introduction of New test case 6.4B.2.3.2 Carrier Leakage for inter-band EN-DC within FR1	15.1.0

2018-12	RAN#82	R5-187827	0060	1	F	Introduction of New test case 6.4B.2.3.3 In-band Emissions for inter-band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-187828	0070	1	F	Introduction of Error Vector Magnitude for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187829	0071	1	F	Introduction of Carrier Leakage for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-187831	0088	1	F	FR2 General Spurious Emission test case update	15.1.0
2018-12	RAN#82	R5-187832	0089	1	F	FR2 Reference Sensitivity test case update	15.1.0
2018-12	RAN#82	R5-187833	0092	1	F	Updates to clause 7.3B.3.4 in TS 38.521-3	15.1.0
2018-12	RAN#82	R5-187834	0090	1	F	Updates to sections 1-4 in TS 38.521-3 to align with core spec	15.1.0
2018-12	RAN#82	R5-187835	0091	1	F	Updates to Clause 5 in TS 38.521-3	15.1.0
2018-12	RAN#82	R5-187913	0067	1	F	Addition of notes to clarify test point selection into general section of TS 38.521-3	15.1.0
2018-12	RAN#82	R5-188012	0057	1	F	Introduction of New test case 6.4B.2.2.3 In-band Emissions for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188013	0050	1	F	Addition OBW intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188014	0051	1	F	Addition SEM intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188015	0064	1	F	Additional Spurious Emissions for Intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188016	0065	1	F	Additional Spurious Emissions for Intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188017	0066	1	F	Additional Spurious emission for inter-band EN-DC	15.1.0
2018-12	RAN#82	R5-188018	0068	1	F	Spurious emission band UE co-existence for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188019	0072	1	F	Introduction of In-band Emissions for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188020	0073	1	F	Addition of TC6.3B.3.1 Tx ON/OFF time mask for intra-band contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188021	0074	1	F	Addition of TC6.3B.3.2 Tx ON/OFF time mask for intra-band non-contiguous EN-DC	15.1.0
2018-12	RAN#82	R5-188022	0075	1	F	Addition of TC6.3B.3.3 Tx ON/OFF time mask for inter-band EN-DC within FR1	15.1.0
2018-12	RAN#82	R5-188023	0080	1	F	Update of test case 6.5B.2.1.2 Additional spectrum emission mask for intra-band contiguous EN-DC for NS_04	15.1.0
2018-12	RAN#82	R5-188024	0081	1	F	Update of test case 6.2B.3.1 UE A-MPR for Intra-band contiguous EN-DC for NS_04	15.1.0
2018-12	RAN#82	R5-188025	0038	1	F	Update Clause 7.5B.3 in TS 38.521-3	15.1.0
2018-12	RAN#82	R5-188026	0041	1	F	5G NR_EN_DC with FR1_Text update for Inter-Band RX sensitivity	15.1.0
2018-12	RAN#82	R5-188027	0082	1	F	Update TC 7.4B.3	15.1.0
2018-12	RAN#82	R5-188028	0036	1	F	Updates of MU in TS 38.521-3 Annex F during RAN5#81	15.1.0
2018-12	RAN#82	R5-188029	0037	1	F	Updates of TT in TS 38.521-3 Annex F during RAN5#81	15.1.0
2018-12	RAN#82	R5-188039	0093	1	F	LTE Anchor Link configuration for FR2	15.1.0
2018-12	RAN#82	R5-188219	0062	1	F	Introduction of receiver spurious emission tests for FR1 inter-band EN-DC	15.1.0
2018-12	RAN#82	R5-188220	0063	1	F	Introduction of wideband intermodulation tests for FR1 inter-band EN-DC	15.1.0
2018-12	RAN#82	R5-188221	0054	1	F	LTE TDD configuration for UE Tx test in EN-DC	15.1.0
2018-12	RAN#82	R5-188222	0069	1	F	Core alignment CR to capture TS 38.101-3 updates during RAN4#89	15.1.0
2019-03	RAN#83	R5-191057	0165	-	F	Introduction of TC 7.5B.0	15.2.0
2019-03	RAN#83	R5-191157	0174	-	F	Updated EN-DC configuration information in clause 5	15.2.0
2019-03	RAN#83	R5-191231	0175	-	F	Adding missing reference to 38.521-3	15.2.0
2019-03	RAN#83	R5-191336	0176	-	F	Updates to EN-DC test case 6.2B.2.1, UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-191339	0177	-	F	Updates to EN-DC test case 6.2B.2.2, UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-191340	0178	-	F	Adding test case 6.5A.2.3, Adjacent channel leakage ratio for CA without EN-DC	15.2.0
2019-03	RAN#83	R5-191510	0183	-	F	Shared Risk clarification in TS 38.521-3	15.2.0
2019-03	RAN#83	R5-191637	0193	-	F	Updates of TT in TS38.521-3 Annex F during RAN5#NR4	15.2.0
2019-03	RAN#83	R5-191845	0200	-	F	Text update for 7.3B.3 deltaRIB,c deltaRIBNC for EN-DC	15.2.0
2019-03	RAN#83	R5-191867	0205	-	F	Addition of 7.3B.2.0 Reference sensitivity Minimum Conformance Requirements for EN-DC	15.2.0
2019-03	RAN#83	R5-192004	0215	-	F	Update of TC 6.2B.1.1	15.2.0
2019-03	RAN#83	R5-192005	0216	-	F	Update of TC 6.2B.1.2	15.2.0

2019-03	RAN#83	R5-192006	0217	-	F	Update of TC 6.2B.1.3	15.2.0
2019-03	RAN#83	R5-192176	0224	-	F	TIB,c updated for CA and EN-DC cases	15.2.0
2019-03	RAN#83	R5-192177	0225	-	F	Updated to Annex M Dual uplink interferer	15.2.0
2019-03	RAN#83	R5-192206	0228	-	F	38.521-3 Common Section updates to clarify leverage across architecture options	15.2.0
2019-03	RAN#83	R5-192207	0229	-	F	Formatting updates and index correction in TS 38.521-3	15.2.0
2019-03	RAN#83	R5-192208	0230	-	F	38.521-1 Common Section updates to clarify leverage across architecture options	15.2.0
2019-03	RAN#83	R5-192209	0231	-	F	38.521-2 Common Section updates to clarify leverage across architecture options	15.2.0
2019-03	RAN#83	R5-192242	0237	-	F	Update of test case 6.2B.3.1 UE A-MPR for Intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192243	0238	-	F	Update of test case 6.2B.3.4 UE A-MPR for Inter-Band EN-DC including FR2	15.2.0
2019-03	RAN#83	R5-192244	0239	-	F	Update of test case 6.5B.2.1.2 UE Additional spectrum emissions mask for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192423	0157	1	F	Update of TC 7.5B.1	15.2.0
2019-03	RAN#83	R5-192424	0159	1	F	Introduction of TC 7.5B.4	15.2.0
2019-03	RAN#83	R5-192425	0166	1	F	Update of TC 7.5B.3	15.2.0
2019-03	RAN#83	R5-192427	0180	1	F	Introduction of NSA FR1 7.6B.2.1 Inband blocking for intra-band contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192428	0182	1	F	Introduction of NSA FR1 7.6B.2.3 Inband blocking for inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192429	0184	1	F	Introduction of NSA FR1 7.6B.3.1 Out-of-band blocking for intra-band contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192430	0185	1	F	Introduction of NSA FR1 7.6B.3.2 Out-of-band blocking for intra-band non-contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192431	0186	1	F	Introduction of NSA FR1 7.6B.3.3 Out-of-band blocking for inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192432	0187	1	F	Introduction of NSA FR1 7.6B.4.1 Narrow band blocking for intra-band contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192433	0188	1	F	Introduction of NSA FR1 7.6B.4.2 Narrow band blocking for intra-band non-contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192434	0189	1	F	Introduction of NSA FR1 7.6B.4.3 Narrow band blocking for inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192435	0190	1	F	Introduction of NSA FR1 7.7B.1 Spurious Response for intra-band contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192436	0191	1	F	Introduction of NSA FR1 7.7B.2 Spurious Response for intra-band non-contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192437	0192	1	F	Introduction of NSA FR1 7.7B.3 Spurious Response for inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192438	0207	1	F	Text Update for 7.3B.2.2 Reference sensitivity for Intra-band non-contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192439	0234	1	F	TS 38.521-3 corrections and clean-up to TC categories within Clause 7	15.2.0
2019-03	RAN#83	R5-192440	0179	1	F	Editorial: Band combinations for Inter-band CA between FR1 and FR2	15.2.0

2019-03	RAN#83	R5-192441	0232	1	F	TS 38.521-3 Section 5 updates to align with core specification	15.2.0
2019-03	RAN#83	R5-192442	0195	1	F	Addition of TC6.3B.4.3 PRACH Time Mask for inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192443	0220	1	F	Update of EN-DC 6.2B.4.1.3 Configured transmitted power inter-band within FR1	15.2.0
2019-03	RAN#83	R5-192445	0233	1	F	TS 38.521-3 corrections and clean-up to TC categories within Clause 6	15.2.0
2019-03	RAN#83	R5-192453	0198	1	F	FR2 NSA Spurious Emission Coexistence test case	15.2.0
2019-03	RAN#83	R5-192454	0199	1	F	FR2 NSA Frequency Error test case	15.2.0
2019-03	RAN#83	R5-192455	0221	1	F	Addition of transmit modulation quality test cases for inter-band EN-DC including FR2	15.2.0
2019-03	RAN#83	R5-192456	0222	1	F	Introduction 6.5B.1.4 OBW interband EN-DC including FR2	15.2.0
2019-03	RAN#83	R5-192457	0223	1	F	Introduction 6.5B.2.4.1 SEM interband EN-DC including FR2	15.2.0
2019-03	RAN#83	R5-192458	0226	1	F	Introduction 6.5B.2.4.3 ACLR interband EN-DC including FR2	15.2.0
2019-03	RAN#83	R5-192459	0236	1	F	Addition of TC6.3B.1.4 - Minimum Output Power for EN-DC Interband including FR2	15.2.0
2019-03	RAN#83	R5-192535	0194	1	F	Clean up of occupied bandwidth for EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192600	0196	1	F	Addition of TC6.3B.4.1 PRACH Time Mask for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192601	0197	1	F	Addition of TC6.3B.4.2 PRACH Time Mask for intra-band non-contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192603	0201	1	F	Text Update for 6.5B.3.2 Spurious Emissions for intra-band non-contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192604	0202	1	F	Text Update for 6.5B.3.1 Spurious Emissions for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192605	0203	1	F	Text Update for 6.5B.3.3 Spurious Emissions for Inter-band EN-DC within FR1	15.2.0
2019-03	RAN#83	R5-192606	0204	1	F	Text Update for 6.5B.4 Additional Spurious Emissions for EN-DC	15.2.0
2019-03	RAN#83	R5-192607	0209	1	F	Update to Carrier Leakage for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192608	0210	1	F	Introduction of Error Vector Magnitude for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192609	0211	1	F	Update to In-band Emissions for intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192610	0227	1	F	Clarification on UL slots in OBW, SEM and ACLR in TS 38.521-3	15.2.0
2019-03	RAN#83	R5-192611	0158	1	F	Update of TC 7.5B.2	15.2.0
2019-03	RAN#83	R5-192617	0167	1	F	Introducing Wideband Intermodulation for intra-band EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192618	0168	1	F	Introducing receiver spurious emission for intra-band EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192619	0181	1	F	Introduction of NSA FR1 7.6B.2.2 Inband blocking for intra-band non-contiguous EN-DC in FR1	15.2.0
2019-03	RAN#83	R5-192620	0206	1	F	Text Update for 7.3B.2.1 Reference sensitivity for Intra-band Contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192622	0170	1	F	Updates of MU in TS38.521-3 Annex F during RAN5#82	15.2.0
2019-03	RAN#83	R5-192623	0171	1	F	Updates of TT in TS38.521-3 Annex F during RAN5#82	15.2.0
2019-03	RAN#83	R5-192626	0214	1	F	Update of TC 7.4B.2	15.2.0

2019-03	RAN#83	R5-192681	0235	1	F	Addition of TC6.2B.1.4 - Max Output Power for EN-DC Interband including FR2	15.2.0
2019-03	RAN#83	R5-192689	0218	1	F	Update of 6.2B.4.1.1 Configured output power Intra-band contiguous EN-DC	15.2.0
2019-03	RAN#83	R5-192690	0219	1	F	Update of EN-DC 6.2B.4.1.2 Configured transmitted power Intra-band non-contiguous	15.2.0
2019-03	RAN#83	R5-192844	0213	2	F	Update of TC 7.4B.1	15.2.0
2019-03	RAN#83	R5-192847	0212	1	F	Addition of 7.4B.0	15.2.0
2019-03	RAN#83	R5-192863	0172	1	F	Introduction of TxIM (inter-band EN-DC within FR1)	15.2.0
2019-03	RAN#83	-	-	-	-	Editorial correction of references to TS 38.508-1 clause 4.6 tables	15.2.0
2019-06	RAN#84	R5-193539	0294	-	F	Adding missing reference in 38.521-3	15.3.0
2019-06	RAN#84	R5-193546	0295	-	F	Updates to 6.2B.2.3, UE Maximum Output power reduction for inter-band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-193547	0296	-	F	Adding test case 6.2B.2.5, UE Maximum Output power reduction for inter-band EN-DC including both FR1 and FR2	15.3.0
2019-06	RAN#84	R5-193548	0297	-	F	Update of test case 6.2B.2.1, UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-193714	0309	-	F	Update of Clause 5.5B Configuration for DC	15.3.0
2019-06	RAN#84	R5-193719	0311	-	F	Update of TC 7.5B.2 ACS for intra-band non-contiguous 2CC	15.3.0
2019-06	RAN#84	R5-193720	0312	-	F	Update of TC 7.5B.3 ACS for inter-band FR1 2CC	15.3.0
2019-06	RAN#84	R5-193722	0314	-	F	Update of TC 7.5B.4.1 ACS for inter-band FR2 2CC	15.3.0
2019-06	RAN#84	R5-193724	0316	-	F	Introduction of TC 7.5B.4.3 ACS for inter-band FR2 4CC	15.3.0
2019-06	RAN#84	R5-193725	0317	-	F	Introduction of TC 7.5B.4.4 ACS for inter-band FR2 5CC	15.3.0
2019-06	RAN#84	R5-193726	0318	-	F	Introduction of TC 7.5B.4.5 ACS for inter-band FR2 6CC	15.3.0
2019-06	RAN#84	R5-193727	0319	-	F	Introduction of TC 7.5B.5 inter-band FR1 FR2 3CC	15.3.0
2019-06	RAN#84	R5-193886	0320	-	F	Introduction of NSA FR2 7.6B.2.4.1	15.3.0
2019-06	RAN#84	R5-193888	0322	-	F	Update of NSA FR1 7.6B.2.0	15.3.0
2019-06	RAN#84	R5-193896	0324	-	F	Update of NSA FR1 7.6B.2.2	15.3.0
2019-06	RAN#84	R5-193899	0326	-	F	Update of NSA FR1 7.6B.3.1	15.3.0
2019-06	RAN#84	R5-193900	0327	-	F	Update of NSA FR1 7.6B.3.2	15.3.0
2019-06	RAN#84	R5-193901	0328	-	F	Update of NSA FR1 7.6B.4.0	15.3.0
2019-06	RAN#84	R5-193902	0329	-	F	Update of NSA FR1 7.6B.4.1	15.3.0
2019-06	RAN#84	R5-193903	0330	-	F	Update of NSA FR1 7.6B.4.2	15.3.0
2019-06	RAN#84	R5-193904	0331	-	F	Update of NSA FR1 7.7B.0	15.3.0
2019-06	RAN#84	R5-193905	0332	-	F	Update of NSA FR1 7.7B.1	15.3.0
2019-06	RAN#84	R5-193906	0333	-	F	Update of NSA FR1 7.7B.2	15.3.0
2019-06	RAN#84	R5-193947	0343	-	F	Removing invalid test IDs from test case 6.5B.2.1.3	15.3.0
2019-06	RAN#84	R5-194016	0344	-	F	38.521-3 Annex re-alignment	15.3.0
2019-06	RAN#84	R5-194128	0347	-	F	Addition SEM intraband non-contiguous EN-DC in TS 38.521-3	15.3.0
2019-06	RAN#84	R5-194129	0348	-	F	Addition ACLR intraband non-contiguous EN-DC in TS 38.521-3	15.3.0
2019-06	RAN#84	R5-194164	0351	-	F	Update of test case 6.2B.3.1 UE A-MPR for Intra-band contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-194166	0353	-	F	Update of test case 6.2B.3.3 UE A-MPR for Inter-Band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-194317	0359	-	F	Text Update for 7.3B.2.3 Reference sensitivity for Inter-band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-194318	0360	-	F	Text Update for 7.3B.2.1 Ref sensitivity for Intra-band Contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-194319	0361	-	F	Text Update for 6.5B.4 Additional Spurious Emissions for EN-DC	15.3.0
2019-06	RAN#84	R5-194320	0362	-	F	Text Update for 7.3B.3	15.3.0
2019-06	RAN#84	R5-194374	0366	-	F	Text Update for 6.5B.3.3.2 Spurious emission band UE co-existence for Inter-band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-194375	0367	-	F	Text Update for 7.3B.2.2 Ref sensitivity for Intra-band Non-Contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-194376	0368	-	F	Text Update for 7.3B.2.0 Min Requirements of Ref sensitivity for EN-DC	15.3.0
2019-06	RAN#84	R5-194400	0372	-	F	Update to Carrier Leakage and In-band Emissions for intra-band contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-194463	0378	-	F	Update to 6.2.3 A-MPR FR2 NSA	15.3.0
2019-06	RAN#84	R5-194484	0380	-	F	Update EN-DC Transmit modulation quality test cases	15.3.0
2019-06	RAN#84	R5-194621	0381	-	F	Update of transmit modulation quality test cases for inter-band EN-DC including FR2	15.3.0
2019-06	RAN#84	R5-194706	0382	-	F	TS 38.521-3 Section 5 updates to align with core specification	15.3.0
2019-06	RAN#84	R5-194707	0383	-	F	TS 38.521-3 updates across section 6 test cases	15.3.0

2019-06	RAN#84	R5-194708	0384	-	F	TS 38.521-3 updates across section 7 test cases	15.3.0
2019-06	RAN#84	R5-194725	0388	-	F	Update to clarify number of LTE CCs config for anchor agnostic EN-DC RF tests	15.3.0
2019-06	RAN#84	R5-194934	0334	1	F	Update of NSA FR1 RF 6.2B.1.1 MOP	15.3.0
2019-06	RAN#84	R5-194935	0335	1	F	Update of NSA FR1 RF 6.2B.1.2 MOP	15.3.0
2019-06	RAN#84	R5-194936	0337	1	F	Update of NSA FR1 RF 7.4B.1	15.3.0
2019-06	RAN#84	R5-194937	0338	1	F	Update of NSA FR1 RF 7.4B.2	15.3.0
2019-06	RAN#84	R5-194938	0298	1	F	Adding test case 6.5A.2.2, Additional Spectrum emissions mask for CA without EN-DC	15.3.0
2019-06	RAN#84	R5-194941	0350	1	F	Introduction of New test case 6.4B.2.3.4 EVM Equalizer Flatness for inter-band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-194942	0373	1	F	Update of test case 6.2A.2.1, UE maximum output power reduction for inter-band NR CA between FR1 and FR2 without EN-DC	15.3.0
2019-06	RAN#84	R5-194943	0374	1	F	Update of 6.2B.3.1 A-MPR Intra-band contiguous for NS_35	15.3.0
2019-06	RAN#84	R5-194944	0375	1	F	Update of 6.2B.3.2 A-MPR for Intra-band non-contiguous with additional test frequencies	15.3.0
2019-06	RAN#84	R5-194945	0376	1	F	Correction of editorial note in 6.5B.2.1.2	15.3.0
2019-06	RAN#84	R5-194946	0377	1	F	Update to 6.2.3 A-MPR FR1 and FR2	15.3.0
2019-06	RAN#84	R5-194947	0389	1	F	Updates to E-UTRA, FR1,FR2 IW tests in line with agreed way forward	15.3.0
2019-06	RAN#84	R5-194948	0369	1	F	Addition of msg content in TC 6.3B.4.1	15.3.0
2019-06	RAN#84	R5-194949	0370	1	F	Addition of msg content in TC 6.3B.4.2	15.3.0
2019-06	RAN#84	R5-194950	0371	1	F	Addition of msg content in TC 6.3B.4.3	15.3.0
2019-06	RAN#84	R5-194951	0310	1	F	Update of TC 7.5B.0 ACS for EN-DC	15.3.0
2019-06	RAN#84	R5-194952	0321	1	F	Introduction of NSA FR2 7.6B.2.5	15.3.0
2019-06	RAN#84	R5-194953	0323	1	F	Update of NSA FR1 7.6B.2.1	15.3.0
2019-06	RAN#84	R5-194954	0363	1	F	Updated to EN-DC band and TIB information	15.3.0
2019-06	RAN#84	R5-194955	0385	1	F	TS 38.521-3 Section 5 updates to align with core specification	15.3.0
2019-06	RAN#84	R5-194975	0315	1	F	Introduction of TC 7.5B.4.2 ACS for inter-band FR2 3CC	15.3.0
2019-06	RAN#84	R5-195046	0356	1	F	Update to Wideband Intermodulation for EN-DC in FR1- 2CCs	15.3.0
2019-06	RAN#84	R5-195047	0379	1	F	Update to 6.2.3 A-MPR FR1 and FR2 NSA	15.3.0
2019-06	RAN#84	R5-195049	0357	1	F	Correction to 6.5B.3.3.2 Spurious emission band UE co-existence for Inter-band within FR1	15.3.0
2019-06	RAN#84	R5-195050	0358	1	F	Introducing Wideband Intermodulation for EN-DC including FR1 - 3 CCs	15.3.0
2019-06	RAN#84	R5-195051	0391	-	F	Update of 6.5B.3.3.2 spurious co-existence inter-band EN-DC FR1	15.3.0
2019-06	RAN#84	R5-195091	0392	1	F	Update of EN-DC ON_ON time mask test cases	15.3.0
2019-06	RAN#84	R5-195162	0349	1	F	Introduction of New test case 6.4B.2.2.4 EVM Equalizer Flatness for intra-band non-contiguous EN-DC	15.3.0
2019-06	RAN#84	R5-195163	0364	1	F	Clean up FR2 Inter-band EN-DC test cases	15.3.0
2019-06	RAN#84	R5-195164	0390	1	F	Update to UE Maximum Output Power for Inter-Band EN-DC within FR1	15.3.0
2019-06	RAN#84	R5-195165	0325	1	F	Update of NSA FR1 7.6B.3.0	15.3.0
2019-06	RAN#84	R5-195411	0386	1	F	TS 38.521-3 updates across section 6 test cases	15.3.0
2019-06	RAN#84	R5-195412	0387	1	F	TS 38.521-3 updates across section 7 test cases	15.3.0
2019-06	RAN#84	R5-195419	0393	1	F	EN-DC implementation of FR2 UL demod OTA tests using single pol Rx TE	15.3.0
2019-06	RAN#84	R5-195436	0336	1	F	Update of NSA FR1 RF 6.2B.1.3 MOP	15.3.0
2019-06	RAN#84	R5-195437	0299	1	F	Updates of MU and TT in TS 38.521-3	15.3.0
2019-06	RAN#84	R5-195446	0394	1	F	Introduction of Tx test cases for FR2 NSA UL CA	15.3.0
2020-03	RAN#87	R5-201191	0580	1	F	Update of 7.3B.2 Reference sensitivity for EN-DC	15.4.0
2020-03	RAN#87	-	-	-	-	Wrong old version was uploaded in 15.4.0	15.4.1

---

# History

<b>Document history</b>		
V15.0.0	October 2018	Publication
V15.1.0	April 2019	Publication
V15.2.0	May 2019	Publication
V15.3.0	July 2019	Publication
V15.4.1	May 2020	Publication