

ETSI TS 126 102 V3.0.0 (2000-01)

Technical Specification

**Universal Mobile Telecommunications System (UMTS);
Mandatory speech codec;
AMR speech codec; Interface to lu and Uu
(3G TS 26.102 version 3.0.0 Release 1999)**



Reference

DTS/TSGS-0426102U

Keywords

UMTS

ETSI

Postal address

F-06921 Sophia Antipolis Cedex - FRANCE

Office address

650 Route des Lucioles - Sophia Antipolis
Valbonne - FRANCE
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16
Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Internet

secretariat@etsi.fr
Individual copies of this ETSI deliverable
can be downloaded from
<http://www.etsi.org>
If you find errors in the present document, send your
comment to: editor@etsi.fr

Important notice

This ETSI deliverable may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2000.
All rights reserved.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by the ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables. The mapping of document identities is as follows:

For 3GPP documents:

3G TS | TR nn.nnn "<title>" (with or without the prefix 3G)

is equivalent to

ETSI TS | TR 1nn nnn "[Digital cellular telecommunications system (Phase 2+) (GSM);] Universal Mobile Telecommunications System; <title>

For GSM document identities of type "GSM xx.yy", e.g. GSM 01.04, the corresponding ETSI document identity may be found in the Cross Reference List on www.etsi.org/key

Contents

Intellectual Property Rights.....	4
Foreword.....	4
1 Scope.....	5
2 Normative References.....	5
3 Definitions and abbreviations	5
3.1 Definitions	5
3.2 Abbreviations.....	5
4 General.....	6
5 RAB aspects.....	6
6 Iu Interface User Plane (RAN)	6
6.1 Frame structure on the Iu UP transport protocol.....	6
6.1.1 Initialisation.....	6
6.1.2 Time Alignment Procedure	7
6.2 Mapping of the bits.....	7
6.3 Frame handlers.....	9
6.3.1 Handling of frames from TC to Iu interface (downlink)	9
6.3.2 Handling of frames from Iu interface to TC (uplink).....	10
7 Uu Interface User Plane (UE).....	11
8 Other aspects.....	11
History.....	12

Intellectual Property Rights

<IPR notice shall be provided once correct notice is available within 3GPP.>

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project, Technical Specification Group Services and System Aspects, Working Group 4 (Codec).

The contents of this mandatory TS may be subject to continuing work within the 3GPP and may change following formal TSG-S4 approval. Should TSG-S4 modify the contents of this TS, it will be re-released with an identifying change of release date and an increase in version number as follows:

Version m.t.e

where:

- m indicates [major version number]
- x the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- y the third digit is incremented when editorial only changes have been incorporated into the specification.

1 Scope

The present document specifies the mapping of the AMR generic frame format (TS 26.101) to the Iu Interface (TS 25.415) and the Uu Interface.

2 Normative References

This TS incorporates by dated and undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this TS only when incorporated in it by amendment or revision. For undated references, the latest edition of the publication referred to applies.

[1] 3G TS 25.415 : "Iu Interface CN-UTRAN User plane Protocols"

[2] 3G TS 26.101 : "AMR Speech Codec, Frame structure".

[Editor's note : To add references to the 3G TS 28.062 (TFO), GSM EFR, IS-641 and PDC 6,70]

3 Definitions and abbreviations

3.1 Definitions

AMR Generic Frame Interface: this interface transports the AMR IF1 generic frame as defined in TS 26.101.

3.2 Abbreviations

For the purposes of this TS, the following abbreviations apply:

AAL2	ATM Adaptation Layer 2
ACS	Active Codec Set
AMR	Adaptive Multi-Rate
AS	Access Stratum
ATM	Asynchronous Transfer Mode
BFH	Bad Frame Handling
CMR/CMC	Codec Mode Request or Codec Mode Command
CMI	Codec Mode Indication
CN	Core Network
CDMA	Code Division Multiple Access
DRC	Downlink Rate Command
FDD	Frequency Duplex Division
FQC	Frame Quality Classification (IU Interface)
FQI	Frame Quality Indication (AMR IF1)
GSM	Global System for Mobile communications
ITU-T	International Telecommunication Union – Telecommunication standardisation sector (former CCITT)
PDC	Personal Digital Communication
PLMN	Public Land Mobile Network
RAN	Radio Access Network
RAB	Radio Access Bearer
RF	Radio Frequency
RFC	Rab sub Flow Combination
RFCI	RFC Indicator
RFCS	RFC Set
RX	Receive

SCR	Source Controlled Rate
SID	Silence Insertion Descriptor
SMpSDU	Support Mode for Predefined SDU sizes
SPD	SPeech Decoder
SPE	SPeech Encoder
TC	Transcoder
TDD	Time Duplex Division
TFO	Tandem Free Operation
TrFO	Transcoder Free Operation
TX	Transmit
UE	User Equipment (terminal)
URC	Uplink Rate Command

4 General

The mapping of the Speech Codec parameters to the Iu interface specifies the frame structure of the speech data exchanged between the RNC and the TC in case of normal operation and Tandem Free Operation, respectively between RNC 1 and RNC 2 in case of Transcoder Free Operation . This mapping is independent from the radio interface in the sense that it has the same structure for both FDD and TDD modes of the UTRAN.

The mapping between the Speech Codec and the MAC layer within the UE is not an open interface and need not to be detailed.

5 RAB aspects

During the RAB Assignment procedure initiated by the CN to establish the RAB for AMR, the RAB parameters are defined. The AMR RAB is established with one or more RAB co-ordinated sub flows with predefined sizes and QoS parameters. In this way, each Transport Format Combination between sub flows corresponds to one AMR frame type. On the Iu interface, these RAB parameters define the corresponding parameters regarding the transport of AMR frames.

6 Iu Interface User Plane (RAN)

The data structure exchanged on the Iu interface are symmetrical, i.e. the structure of the uplink data frames is identical to that of the downlink data frames. This facilitates Tandem Free Operation and Transcoder Free Operation.

6.1 Frame structure on the Iu UP transport protocol

6.1.1 Initialisation

At the initialisation of the SMpSDU mode of operation, several parameters are set by the CN. The initialisation procedure is described in TS 25.415 [1].

- RFCS

In the case of AMR, the RFCS corresponds to the Active Codec Set (ACS) authorised in the communication. Annex A of [1] gives an illustration of the usage of RFCI for AMR speech RAB.

- Delivery of erroneous SDUs

This parameter shall be set to YES. Erroneous speech frames may be used to assist the error concealment procedures.

- [Editor's note : this might need to be specified in another specifications]PDU type

The PDU type 0 shall be used for the transport of AMR data.

[Editor's note : this might need to be specified in another specifications]

6.1.2 Time Alignment Procedure

[ffs as in [1]]

6.2 Mapping of the bits

The mapping of the bits between the generic AMR frames and the PDU is the same for both uplink and downlink frames.

The following table gives the correspondence of the bit fields between the generic AMR frames at the TC interface and the PDU exchanged with the Iu transport layer.

PDU field	Corresponding AMR generic frame field	Comment
PDU Type	N/A	Type 0
Frame Number	N/A	
FQC	Frame Quality Indicator	
RFCI	AMR Frame Type	
Payload CRC	N/A	
Header CRC	N/A	
Payload Fields (N Sub Flows)	Class A or SID payload Class B Class C	
SDU #1	Most important speech bits come first	Mandatory
SDU #2	Next bits follow	Optional
...	...	Optional
SDU #N	Least important speech bits	Optional

Table 0-1 : Mapping of generic AMR frames onto Iu PDUs

The number of RAB sub flows, their corresponding sizes, and their attributes such as "Delivery of erroneous SDUs" and "PDU type" shall be defined at the RAB establishment and signalled in the RANAP RAB establishment request. The number of RAB sub flows are corresponding to the desired bit protection classes. Their respective sizes and their respective QoS are left open to specification at RAB establishment. The total number of bits in all sub flows for one RFC shall correspond to the total number given in TS 26.101 for the corresponding Codec Mode respectively Frame Type.

Guidance for setting the number of bits in each RAB Sub Flow according to their relative subjective importance is given in TS 26.101.

The following two tables are examples of mapping of RAB sub flows.

Table 6-2 gives three examples of sub flow mapping.

The RFCI definition is given in order of increasing SDU sizes.

TS 26.102 V3.0.0 (1999-12)

- Example 1 describes Codec Type UMTS_AMR, with all eight codec modes foreseen in the Active Codec Set (ACS) and provision for Source Controlled Rate operation (SCR). In this example, Blind Transport Format Detection is supported and the sub flow mapping follows the 26.101 class division guidance.
- Example 2 describes Codec Type GSM_EFR, with one codec mode, including SCR.
- Example 3 describes Codec Type GSM_AMR, including AMR SCR

UMTS_AMR	GSM_EFR	GSM_AMR	RAB sub-flows			Total size of bits/RAB sub-flows combination (Mandatory)	Source rate
RFCI Example 1	RFCI Example 2	RFCI Example 3	RAB sub-Flow 1 (Optional)	RAB sub-Flow 2 (Optional)	RAB sub-Flow 3 (Optional)		
2		2	42	53	0	95	AMR 4.75kbps
3			49	54	0	103	AMR 5.15kbps
4		3	55	63	0	118	AMR 5.9kbps
5			58	76	0	134	AMR 6.7kbps
6		4	61	87	0	148	AMR 7.4kbps
7			75	84	0	159	AMR 7.95kbps
8		5	65	99	40	204	AMR 10.2kbps
9	2		81	103	60	244	AMR 12.2kbps
1		1	39	0	0	39	AMR SID
	1		47	0	0	47	GSM EFR SID
			0	0	0	0	NO DATA

Table 6-2 : Example for AMR with SCR and three sub flows, according to subjective class division indication of TS 26.101.

Table 6-3 gives one examples of sub flow mapping that supports Equal Error Protection. The RFCI definition is given in order of increasing SDU sizes.

- Example 4 describes Codec Type PDC_EFR and the corresponding Source Controlled Rate operation (SCR).

PDC_EFR	RAB sub-flow	Total size of bits/RAB sub-flows combination (Mandatory)	Source rate
RFCI Example 4	RAB sub-Flow 1 (Mandatory)		
	95	95	AMR 4.75kbps
	103	103	AMR 5.15kbps
	118	118	AMR 5.9kbps
2	134	134	AMR 6.7kbps
	148	148	AMR 7.4kbps
	159	159	AMR 7.95kbps
	204	204	AMR 10.2kbps
	244	244	AMR 12.2kbps
	39	39	AMR SID
	47	47	GSM EFR SID
	42	42	IS-641 SID
1	41	41	PDC 6,7 SID
	0	0	NO DATA

Table 6-3 : Example of SDU sizes for PDC_EFR with SCR and Equal Error Protection

6.3 Frame handlers

Iu PDU Frame handling functions are described in TS 25.415. This sections describes the mandatory frame handling functions at the AMR Generic frame interface.

6.3.1 Handling of frames from TC to Iu interface (downlink)

The frames from the TC in AMR generic frame format are mapped onto the Iu PDU as follows.

6.3.1.1 Frame Quality Indicator

The Frame Quality Indicator from the TC, respectively from the distant TFO partner, is directly mapped to the Frame Quality Classification of the IU frame according to Table 6-6.

FQI AMR	FQC PDU	FQC value
GOOD	GOOD	0
BAD	BAD	1

Table 6-4 : FQI AMR to FQC Iu PDU mapping

6.3.1.2 Frame Type

The received Frame Type Index is mapped onto the RFCI thanks to the assigned RFCS table: The correspondence between Codec Mode, Frame Type Index and RFCI is defined at RAB assignment.

6.3.1.3 Codec Mode Indication

The Codec Mode Indication is not used because it is redundant to the Frame Type.

6.3.1.4 Codec Mode Request

Codec Mode Request (CMR) in downlink direction is forwarded to the rate control procedure if it changes.

6.3.1.5 Optional internal 8 bits CRC

The internal AMR CRC is not used on the Iu interface.

6.3.1.6 Mapping of Speech or Comfort Noise parameter bits

Let define the N payload fields of the N Sub flows for RFCI j as follow :

- $U_i(k)$ shall be the bits in Sub Flow i, for $k = 1$ to M_i
- M_i shall be the size of Sub Flow i, for $i = 1$ to N
- $S(k)$ shall be the bits of the speech or comfort noise parameters of the corresponding Frame Type j in decreasing subjective importance.

Then the following mapping in pseudo code applies:

$$\begin{aligned}
 U_1(k) &= S(k) && \text{with } k = 1, \dots M_1 \\
 U_2(k) &= S(k + M_1) && \text{with } k = 1, \dots M_2 \\
 U_3(k) &= S(k + M_2) && \text{with } k = 1, \dots M_3 \\
 &\dots && \\
 U_N(k) &= S(k + M_{N-1}) && \text{with } k = 1 \dots M_N
 \end{aligned}$$

6.3.2 Handling of frames from Iu interface to TC (uplink)

The uplink Iu frames are mapped onto generic AMR frames as follow :

6.3.2.1 Frame Quality Indicator

At reception of Iu PDU the Iu frame handler function set the Frame Quality Classification according to the received FQC, Header-CRC check, and Payload-CRC check (see 25.415). AMR Frame Type and Frame Quality Indicator are determined according to the following table:

FQC	Resulting FQI	resulting Frame Type
GOOD	GOOD	from RFCI
BAD	BAD	NO_DATA
BAD Radio	BAD	from RFCI
Reserved	Reserved	Reserved

Table 6-5 : FQC Iu PDU type 0 to AMR FQI and AMR Frame Type mapping

6.3.2.2 Frame Type

The received RFCI is mapped onto the Frame Type thanks to the RFCS table. I.e. the Type_Index is set according to the AMR mode.

6.3.2.3 Codec Mode Indication

The Codec Mode Indication is not used because it is redundant to the Frame Type.

6.3.2.4 Codec Mode Request

The received Downlink Rate Control command is mapped onto the Codec Mode Request. In case a new DRC is received it is mapped into the corresponding CMR AMR generic frame format. It is remembered by the TC until the next DRC is received. In each new frame that is sent to the AMR Codec, the stored CMR is resent, in order to control the Codec Mode for the downlink direction.

6.3.2.5 Optional internal 8 bits CRC

The internal AMR CRC is not used on the Iu interface.

6.3.2.6 Speech and Comfort noise parameter bits

The speech and Comfort noise parameter bits are mapped from the sub flows to the payload of the generic AMR frames with the reverse function of subclause 6.3.1.6.

7 Uu Interface User Plane (UE)

The interface between the UE AMR speech codec (see TS 26.101) and the Radio Access Network is an internal UE interface and is not detailed. The mapping is corresponding to the mapping described in chapter 6 for the IU interface.

8 Other aspects

[ffs]

History

Document history		
V3.0.0	January 2000	Publication