

ETSI TS 126 111 V17.0.0 (2022-05)



**Digital cellular telecommunications system (Phase 2+) (GSM);
Universal Mobile Telecommunications System (UMTS);
Codec for circuit switched multimedia telephony service;
Modifications to H.324
(3GPP TS 26.111 version 17.0.0 Release 17)**



Reference

RTS/TSGS-0426111vh00

Keywords

GSM,UMTS

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our
Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2022.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	4
Introduction	4
1 Scope	5
2 References	5
3 Definitions and abbreviations.....	6
3.1 Definitions	6
3.2 Abbreviations	6
4 General	6
5 Document structure	6
6 Functional requirements	7
6.1 Required elements	7
6.2 Information streams.....	7
6.3 Modem	7
6.4 Multiplex	7
6.5 Control channel	7
6.6 Video channels	7
6.6.1 MPEG-4 interface to multiplex.....	10
6.6.2 H.264 (MPEG-4 AVC) interface to multiplex.....	10
6.7 Audio channels	11
6.8 Data channels	11
7 Terminal procedures.....	11
8 Optional enhancements	11
9 Interoperation with other terminals	11
10 Multipoint considerations.....	11
11 Maintenance	12
Annex A (informative): Change History	13
History	14

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Introduction

In the present document is described additions, deletions, and changes made to ITU-T Recommendation H.324 [10] with annex C for the purpose of using that recommendation as a basis for the technical specification for circuit switched multimedia service in 3GPP networks. The present document does not address call setup procedures, but references to the specifications which cover call setup are found in 3GPP TS 26.110 [11].

1 Scope

In ITU-T Recommendation H.324 [10] with annex C describes a generic multimedia codec for use in error-prone, wireless networks. The scope of the present document are the changes, deletions, and additions to those texts necessary to fully specify a multimedia codec for use in 3GPP networks. Note that this implicitly excludes the network interface and call setup procedures. Also excluded are any general introductions to the system components.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] ITU-T Recommendation H.223: "Multiplexing protocol for low bit rate multimedia communication".
- [2] ITU-T Recommendation H.223 - Annex A: "Multiplexing protocol for low bit rate multimedia mobile communication over low error-prone channels".
- [3] ITU-T Recommendation H.223 - Annex B: "Multiplexing protocol for low bit rate multimedia mobile communication over moderate error-prone channels".
- [4] ITU-T Recommendation H.223 - Annex C: "Multiplexing protocol for low bit rate multimedia mobile communication over highly error-prone channels".
- [5] ITU-T Recommendation H.223 - Annex D: "Optional multiplexing protocol for low bit rate multimedia mobile communication over highly error-prone channels".
- [6] ITU-T Recommendation H.245: "Control protocol for multimedia communication".
- [7] ITU-T Recommendation G.723.1: "Dual rate speech coder for multimedia communication transmitting at 5,3 and 6,3 kbit/s".
- [8] ITU-T Recommendation H.263: "Video coding for low bitrate communication".
- [9] ITU-T Recommendation H.261: "Video CODEC for audiovisual services at px64 kbit/s".
- [10] ITU-T Recommendation H.324: "Terminal for low bitrate multimedia communication".
- [11] 3GPP TS 26.110: "Codec for Circuit Switched Multimedia Telephony Service; General description".
- [12] 3GPP TR 26.911: "Codec for circuit switched multimedia telephony service; terminal implementor's Guide (Release 4)".
- [13] ITU-T Recommendation X.691: "Information Technology - ASN.1 Encoding Rules - Specification of Packed Encoding Rules (PER)".
- [14] ISO/IEC 14496-2: "Information technology - Coding of audio-visual objects - Part 2: Visual".
- [15] 3GPP TS 26.071: "General description".
- [16] 3GPP TS 26.090: "Transcoding functions".
- [17] 3GPP TS 26.073: "Adaptive Multi-Rate (AMR); ANSI C source code".

- [18] 3GPP TS 26.171: "AMR Wideband Speech codec; General Description".
- [19] ITU-T Recommendation H.264 (2003): "Advanced video coding for generic audiovisual services" | ISO/IEC 14496-10:2003: "Information technology – Coding of audio-visual objects – Part 10: Advanced Video Coding".
- [20] ITU-T Recommendation H.241 (2003): "Extended video procedures and control signals for H.300 series terminals".
- [21] ITU-T Recommendation G.722.2 Annex F (2002): "AMR-WB usage in H.245".
- [22] 3GPP TS 26.201 : "Adaptive Multi-Rate – Wideband (AMR-WB) speech codec ; Frame Structure."

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

H.324: ITU-T H.324 [10] with annex C

3G-324M terminal: based on ITU-T H.324 [10] recommendation modified by 3GPP for purposes of 3GPP circuit switched network based video telephony

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

AMR	Adaptive Multi-Rate
AMR-WB	AMR Wide-Band
AVC	Advanced Video Codec
FLC	Fixed Length Code
RVLC	Reverse Variable Length Code
DP	Data Partitioning
RM	Resynchronization Marker
MCU	Multipoint Control Unit

4 General

The present document contains any deviations to ITU-T H.324 [10] required for the specification of 3G-324M Terminals.

5 Document structure

The structure of H.324 [10] is followed in the present document. Where there are no differences in a specific section, that section is skipped. Where differences are minor, only the differences are described. Where major differences exist, the section is rewritten in the present document. It is important to note that for wireless terminals, Annex C of H.324 [10] supersedes respective portions of the main body of H.324 [10] For the present document, these modifications are treated as if they are part of the main body of H.324 [10] Therefore, a reader must keep in mind both the main body and Annex C of H.324 [10] when reading the present document.

6 Functional requirements

6.1 Required elements

3G-324M implementations are not required to have each functional element except a wireless interface, H.223 [1] with Annex A and B multiplex, and H.245 [6] version 3 or later versions for system control protocol.

3G-324M terminals offering audio communication shall support the AMR audio codec. Support for G.723.1 [7] is not mandatory, but recommended.

3G-324M terminals offering video communication shall support the H.263 [8] video codec. Support for MPEG-4 simple profile and H.261 [9] is optional.

3G-324M terminals shall support H.223 [1] with annex A and annex B.

3G-324M terminals shall support at least 32 kbit/s minimum bit rate at the mux to wireless network interface.

6.2 Information streams

V.25ter discussion does not apply.

6.3 Modem

Does not apply.

6.4 Multiplex

3G-324M terminals shall support H.223 [1] with annex A and annex B. All other aspects shall follow H.324 [10] with annex C. H.223 [1] Annex C and D are optional.

6.5 Control channel

No differences with H.324 [10].

Should it not be possible to signal an element of the 3G-324M terminal using a published version of H.245 [6], a procedure will be defined here.

6.6 Video channels

Support for H.261 [9] is optional.

Support for MPEG-4 Visual is optional. When supported, MPEG-4 Visual codecs shall support Simple Profile @ Level 0. The FLC code 0000 1000 in Table G-1 – "FLC table for profile_and_level_indication" in ISO/IEC 14496-2 [14] is assigned to it. Additional information can be found in [14].

MPEG-4 Visual Simple Profile @ level 0 provides error concealment as part of the simple profile through Data Partitioning (DP), Reversible Variable Length Coding (RVLC), Resynchronization Marker (RM) and header extension code. MPEG-4 Visual is baseline compatible with H.263 [8].

When opening a logical channel for MPEG-4 Visual, configuration information (Visual Object Sequence Header, Visual Object Header, and Video Object Layer Header) shall be sent in the decoderConfigurationInformation parameter. The same information shall also be sent in the MPEG-4 video bitstream. If the operational mode of MPEG-4 Visual encoder needs to be changed, the existing MPEG-4 video logical channel shall be closed and H.245 [6] procedures for opening a new MPEG-4 video logical channel shall be started. The new operational mode shall be indicated in the parameters of the new logical channel.

Support for H.264 (MPEG-4 AVC) [19] is optional. When supported, H.264 codecs shall support Baseline level 1, without requirements on output timing conformance (Annex C of [19]).

Support for H.264 [19] shall be signalled according to H.241 chapter 8 "Capability Exchange signalling" [20].

When opening a logical channel for H.264 [19], initial sequence parameter set(s) and picture parameter set(s) should be sent in a H.264 DecoderConfigurationInformation (DCI) defined in Table 1 below, amending H.241 parameters [20]. Additionally, decoder capabilities may be sent in a H.264 AcceptRedundantSlices and a H.264 ProfileIOP defined in Table 2 and 3 below, amending H.241 parameters [20].

NOTE: The H.264 DCI parameter can also be used when either party signals a H.245 [6] MasterSlaveDetermination terminalType parameter greater than 128, such as e.g. a Multipoint Conference Unit (MCU).

A sequence parameter set or a picture parameter set with a particular value of seq_parameter_set_id or pic_parameter_set_id, respectively, sent in the H.264 [19] DCI shall be identical to the earliest occurrence of the sequence parameter set or picture parameter set with the same value of seq_parameter_set_id or pic_parameter_set_id, respectively, sent in the H.264 bitstream.

If DCI was used when a H.264 [19] logical channel was opened and H.264 sequence parameter sets need to be changed or new sets need to be added during the session, the existing H.264 logical channel shall be closed and H.245 [6] procedures for opening a new H.264 logical channel shall be started, in which sequence parameter set(s) and picture parameter set(s) shall be sent in a DCI. Each sequence parameter set of H.264 [19] shall contain the vui_parameters syntax structure including the num_reorder_frames syntax element set equal to 0.

If H.264 picture parameter sets need to be changed or new sets need to be added during a session, it may be done either by opening a new logical channel using the same procedure as described above or within the current channel, by including picture parameter set NAL units directly in the bitstream.

Table 1 / TS 26.111 – H.264 Capability Parameter – DecoderConfigurationInformation (DCI)

Parameter name	DecoderConfigurationInformation
Parameter description	This is a nonCollapsing GenericParameter. DecoderConfigurationInformation indicates how to configure the decoder for a particular H.264 video sequence [19]. It contains sequence parameter set NAL units, picture parameter set NAL units, or both, using the byte stream format specified in Annex B/H.264, separating NAL units with a start code. The use of a start code before the first parameter set NAL unit is optional.
Parameter identifier value	43
Parameter status	Optional. Shall not be present for Capability Exchange and Mode Request. May be present exactly once for Logical Channel Signalling.
Parameter type	OctetString
Supersedes	-

A decoder may indicate its' capability to make use of H.264 redundant slices by the following parameter.

Table 2 / TS 26.111 – H.264 Capability Parameter – AcceptRedundantSlices

Parameter name	AcceptRedundantSlices
Parameter description	<p>This is a collapsing GenericParameter.</p> <p>AcceptRedundantSlices indicates the capability to use H.264 redundant slices and corresponds to the MIME video/H264 parameter "redundant-pic-cap".</p> <p>When False or when the parameter is not present, it indicates that the receiver makes no attempt to use redundant coded pictures to correct incorrectly decoded primary coded pictures and a sender should not send redundant slices.</p> <p>When True, it indicates that the receiver is capable of decoding any such redundant slice that covers a corrupted area in a primary decoded picture (at least partly), and a sender may send redundant slices.</p> <p>When using a H.264 profile (or subset of a profile as indicated by the H.264 ProfileIOP parameter defined in Table 3) and level that disallows the use of redundant slices, this parameter shall be ignored.</p>
Parameter identifier value	44
Parameter status	Optional. May be present exactly once for Capability Exchange Signalling.
Parameter type	Logical
Supersedes	-

NOTE: An encoder should only code redundant slices if it knows that the far-end decoder makes use of this feature. Encoders should also pay attention to potential implications on end-to-end delay.

A decoder may indicate additional limitations that only the common subset of the algorithmic features and limitations of the Baseline level 1 are supported by the following parameter.

Table 3 / TS 26.111 – H.264 Capability Parameter – ProfileIOP

Parameter name	ProfileIOP
Parameter description	<p>ProfileIOP indicates that the capability to decode H.264 streams is limited to a common subset of the algorithmic features included in the indicated profile and level.</p> <p>This parameter is a Boolean array.</p> <p>bit 1 (value 128) is constraint_set0_flag.</p> <p>bit 2 (value 64) is constraint_set1_flag.</p> <p>bit 3 (value 32) is constraint_set2_flag.</p> <p>All other bits are reserved, shall be set to 0, and shall be ignored by receivers.</p> <p>constraint_set0_flag, constraint_set1_flag and constraint_set2_flag are defined in [18].</p> <p>As an example, a receiver indicating decoding support of the intersection of the baseline and main profile will signal value 11000000 (constraint_set0_flag = 1, constraint_set1_flag = 1, constraint_set2_flag = 0).</p>
Parameter identifier value	46
Parameter status	Optional. May be present exactly once for Capability Exchange Signalling.
Parameter type	BooleanArray
Supersedes	-

A terminal supporting H.264 encoding should respond to all videoFastUpdatePicture commands received via the H.245 control channel. If an H.264 encoder responds to videoFastUpdatePicture, it shall use the procedure specified in subclause 6.2.2 of H.241.

A terminal supporting H.264 shall start decoding immediately when it receives data (even if the stream does not start with an IDR access unit) or alternatively no later than it receives the next IDR access unit or the next recovery point SEI message, whichever is earlier in decoding order. The decoding process for a stream not starting with an IDR access unit shall be the same as for a valid H.264 bitstream. However, the client shall be aware that such a stream may contain references to picture not available in the decoded picture buffer. The display behaviour of the client is out of scope of this specification.

NOTE: Terminals may use full-frame freeze and full-frame freeze release SEI messages of H.264 to control the display process.

6.6.1 MPEG-4 interface to multiplex

As H.263 [8] encoders align picture start codes with the start of an AL-SDU, the same concept applies to MPEG-4 encoders. The following are the requirements of the MPEG-4 interface to the H.223 [1] multiplex.

- a) Each 3G-324M MPEG-4 encoder shall align each visual_object_sequence_start_code with the start of an AL-SDU.
- b) Each 3G-324M MPEG-4 encoder shall align each group_of_vop_start_code (the beginning of a GOV field) with the start of an AL-SDU unless the GOV field immediately follows configuration information.
- c) Each 3G-324M MPEG-4 encoder shall align each vop_start_code with the start of an AL-SDU unless the vop_start_code immediately follows configuration information or a GOV field.

In these requirements, GOV stands for Group_of_VideoObjectPlane() and Configuration information consists of Visual Object Sequence Header, Visual Object Header, and Video Object Layer Header.

6.6.2 H.264 (MPEG-4 AVC) interface to multiplex

Shall conform to the byte stream format according to H.241 chapter 7.1.5 "Transport of H.264 streams in H.324 systems" [20].

More strict alignment of AL-SDU and NAL units may optionally be used. To signal capability for and use of this mode, the generic parameter described in Table 3 shall be used, amending the H.264 Generic Capability in H.241 [20].

Table 3 / TS 26.111 – H.264 Capability Parameter – NalAlignedMode

Parameter name	NalAlignedMode
Parameter description	This is a collapsing GenericParameter. NalAlignedMode indicates that every AL-SDU carrying H.264 shall contain an integer number of NAL units and that the start of the AL-SDU shall be aligned with the start of a NAL. Individual NAL units within the AL-SDU shall be separated by start codes as described in Annex B/H.264. The use of a start code before the first NAL in an AL-SDU is optional.
Parameter identifier value	45
Parameter status	Optional. May be present exactly once for Capability Exchange, Logical Channel, or Mode Request Signalling.
Parameter type	Logical
Supersedes	-

6.7 Audio channels

AMR is the mandatory speech codec. Support for G.723.1 [7] is not mandatory, but recommended. Support for AMR-WB [18] is also recommended.

When AMR-WB is supported, the AMR-WB speech data shall be carried in IF2 frame format as defined in Annex A of 3GPP TS 26.201 [22], and the signalling for AMR-WB shall be according to G.722.2 Annex F [21] with the following additional restrictions:

- octetAlign shall be present
- The following parameters are not compatible with IF2 frame format, and so shall not be used:
 - crc
 - robustSorting
 - interleaving

When both the receiving and transmitting terminals support multiple codecs in common, the use of AMR and AMR-WB is preferred:

- If both the receiving and transmitting terminals support AMR and other codecs (e.g. G.723.1) but not AMR-WB, then AMR shall be used.
- If both the receiving and transmitting terminals support AMR and other codecs including AMR-WB, either AMR or AMR-WB shall be used.

Asymmetric configurations with one codec in one direction and another one in the other direction (e.g. AMR in one direction and AMR-WB in the other direction) are allowed, if supported by both terminals.

This applies to connections without an Multipoint Control Unit (MCU).

6.8 Data channels

No differences with H.324 [10].

7 Terminal procedures

See 3GPP TS 26.110 [11].

8 Optional enhancements

No differences with H.324 [10].

9 Interoperation with other terminals

For further study.

10 Multipoint considerations

For further study.

11 Maintenance

No differences with H.324 [10].

Annex A (informative): Change History

History							
TSG_#	TSG_DOC	SPEC	VERS_CURRE NT	VERS_ NEW	CR	REV	SUBJECT
SP-05	SP-99359	26.111	3.0.1	3.0.2	001		Changes to editorial notes.
SP-06	SP-99434	26.111	3.0.2	3.1.0	002	2	Specification of coding parameters for MPEG-4 video codec
SP-06	SP-99514	26.111	3.0.2	3.1.0	003		Transmission of MPEG-4 configuration information in 3G-324M
SP-08	SP-00263	26.111	3.1.0	3.2.0	004		Changes to editorial notes
SP-09	SP-000396	26.111	3.2.0	3.3.0	006		MPEG-4 interface to multiplex
SP-10	SP-000653	26.111	3.3.0	3.4.0	005	1	MPEG4 visual simple profile @ level 0
SP-11				4.0.0			Version for Release 4
SP-16		26.111	4.0.0	5.0.0			Version for Release 5
SP-20	SP-030215	26.111	5.0.0	5.1.0	009	1	Removal of Reference to TS 26.112
SP-25	SP-040659	26.111	5.1.0	6.0.0	010	3	3G-324M Improvements
SP-25	SP-040648	26.111	5.1.0	6.0.0	011	1	3G-324M Improvements: Addition of optional AMR-WB support
SP-26	SP-040842	26.111	6.0.0	6.1.0	012	1	Addition of the missing signalling of H.264 decoder capabilities
SP-26	SP-040842	26.111	6.0.0	6.1.0	013	1	Reference Corrections
SP-36		26.111	6.1.0	7.0.0			Version for Release 7
SP-40	SP-080247	26.111	7.0.0	7.1.0	0015	1	Use of AMR-WB in 3G-324M
SP-42		26.111	7.1.0	8.0.0			Version for Release 8
SP-46		26.111	8.0.0	9.0.0			Version for Release 9
SP-51		26.111	9.0.0	10.0.0			Version for Release 10
SP-57		26.111	10.0.0	11.0.0			Version for Release 11
SP-65		26.111	11.0.0	12.0.0			Version for Release 12
SP-70		26.111	12.0.0	13.0.0			Version for Release 13

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-03	75					Version for Release 14	14.0.0
2018-06	80					Version for Release 14	15.0.0
2020-07	-	-	-	-	-	Update to Rel-16 version (MCC)	16.0.0
2022-04	-	-	-	-	-	Update to Rel-17 version (MCC)	17.0.0

History

Document history		
V17.0.0	May 2022	Publication