

ETSI TS 128 515 V14.1.0 (2017-07)



TECHNICAL SPECIFICATION

LTE;
Telecommunication management;
Fault Management (FM) for mobile networks
that include virtualized network functions;
Requirements
(3GPP TS 28.515 version 14.1.0 Release 14)



Reference

RTS/TSGS-0528515ve10

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommiteeSupportStaff.aspx>

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2017.

All rights reserved.

DECT™, PLUGTESTS™, UMTS™ and the ETSI logo are trademarks of ETSI registered for the benefit of its Members.

3GPP™ and LTE™ are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M logo is protected for the benefit of its Members.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

| | |
|---|-----------|
| Intellectual Property Rights | 2 |
| Foreword..... | 2 |
| Modal verbs terminology..... | 2 |
| Foreword..... | 4 |
| Introduction | 4 |
| 1 Scope | 5 |
| 2 References | 5 |
| 3 Definitions and abbreviations..... | 5 |
| 3.1 Definitions | 5 |
| 3.2 Abbreviations | 5 |
| 4 Concepts and background | 6 |
| 4.1 Fault Management in the context of NFV | 6 |
| 5 Business level requirements | 6 |
| 5.1 Requirements..... | 6 |
| 5.2 Actor roles | 6 |
| 5.3 Telecommunications resources | 6 |
| 5.4 High-level use cases | 7 |
| 5.4.1 NE alarm correlation in the context of NFV | 7 |
| 5.4.2 NFVI Maintenance coordination | 7 |
| 6 Specification level requirements | 8 |
| 6.1 Requirements..... | 8 |
| 6.1.1 Requirements for Itf-N..... | 8 |
| 6.1.2 Requirements for Os-Ma-nfvo | 8 |
| 6.1.3 Requirements for Ve-Vnfm-em | 8 |
| 6.1.4 Requirements for Ve-Vnfm-vnf..... | 8 |
| 6.2 Actor roles | 8 |
| 6.3 Telecommunications resources | 8 |
| 6.4 Use cases | 9 |
| 6.4.1 NE alarm correlation in the context of NFV | 9 |
| 6.4.2 VNF Healing through operation request to VNFM by EM | 9 |
| 6.4.3 Virtualization-specific aspect failure detection and notification by VNFM | 10 |
| 6.4.4 Virtualization-specific aspect failure detection and notification by EM..... | 11 |
| 6.4.5 NE alarm reporting in the context of NFV | 11 |
| 6.4.6 Virtualization-specific aspect failure notification by VNFM | 12 |
| Annex A (informative): Change history | 13 |
| History | 14 |

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Introduction

The present document is part of a TS-family covering the 3rd Generation Partnership Project; Technical Specification Group Services and System Aspects; Telecommunication management, as identified below:

TS 28.515 "Fault Management (FM) for mobile networks that include virtualized network functions; Requirements".

TS 28.516 "Fault Management (FM) for mobile networks that include virtualized network functions; Procedures".

TS 28.517 "Fault Management (FM) for mobile networks that include virtualized network functions; Stage 2".

TS 28.518 "Fault Management (FM) for mobile networks that include virtualized network functions; Stage 3".

1 Scope

The present document (together with the relevant requirements described in [2], [3], [4] and [5]) specifies the requirements applicable to Fault Management (FM) of mobile networks that include virtualized network functions which can be part of EPC or IMS.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 28.500: "Telecommunication management; Management concept, architecture and requirements for mobile networks that include virtualized network functions".
- [3] 3GPP TS 32.101: "Telecommunication management; Principles and high level requirements".
- [4] 3GPP TS 32.102: "Telecommunication management; Architecture".
- [5] 3GPP TS 32.111-1: "Telecommunication management; Fault Management; Part 1: 3G fault management requirements".
- [6] ETSI GS NFV-IFA 010 (V2.2.1): "Network Functions Virtualisation (NFV); Management and Orchestration; Functional Requirements Specification".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [1] and in 3GPP TS 28.500 [2] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [1] or in 3GPP TS 28.500 [2].

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in 3GPP TR 21.905 [1] and in 3GPP TS 28.500 [2] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in 3GPP TR 21.905 [1] or in 3GPP TS 28.500 [2].

| | |
|-------|--------------------------------|
| VM | Virtual Machine |
| vNIC | virtual Network Interface Card |
| vPORT | virtual Port |

4 Concepts and background

4.1 Fault Management in the context of NFV

Fault Management functionality traditionally includes fault detection, generation of alarms, clearing of alarms, alarm forwarding and filtering, storage and retrieval of alarms, correlation of alarms and events, alarm root cause analysis and fault recovery. With introduction of virtualized network functions (VNFs) into mobile networks, Fault Management functionality is distributed over different functional blocks. These different functional blocks may be located at different levels such as NFV Infrastructure (NFVI) level, NE level, NFV Management and Orchestration level and 3GPP network management level.

The decoupling of software from hardware by means of virtualization changes the way in which the faults were managed in non-virtualized NE deployments:

- Physical hardware faults of NFVI are detected by NFVI and corrected jointly with the support from NFV-MANO. Only information about those faults (e.g. faults corresponding to the virtualized resources) that affect the proper functioning of VNF needs to be provided to 3GPP management system.
- VNF-related virtualized resource fault information needs to be sent from NFV-MANO to 3GPP management system, and then 3GPP management system can take some necessary actions.
- VNF application fault information needs to be sent from the VNF instance to the corresponding 3GPP management system that is responsible for taking some necessary actions.
- VNF virtualization-specific fault information is detected by VNF and needs to be sent from the VNF instance to both the VNFM and the corresponding 3GPP management system so that they can take necessary actions accordingly.

5 Business level requirements

5.1 Requirements

REQ-NFV_FM-CON-1 The faulty virtualization-specific aspect of a virtualized network function shall be able to be recovered.

REQ-NFV_FM-CON-2 3GPP management system shall be able to get VNF application fault reports about a faulty NE.

REQ-NFV_FM-CON-3 3GPP management system shall be able to get VNF virtualization-related fault reports from NFV-MANO.

REQ-NFV_FM-CON-4 The content of the fault information from VNF application fault reports and VNF virtualization-related fault reports shall enable 3GPP management system to correlate VNF application fault(s) with VNF virtualization-related fault(s).

REQ-NFV_FM-CON-5 EM shall be able to send to VNFM a request to recover the faulty virtualization-specific aspect of a virtualized network function.

5.2 Actor roles

See actors and roles of each use case in clause 5.4.

5.3 Telecommunications resources

See telecom resources of each use case in clause 5.4.

5.4 High-level use cases

5.4.1 NE alarm correlation in the context of NFV

| Use Case Stage | Evolution / Specification | <<Uses>> Related use |
|-------------------|---|-------------------------|
| Goal | To correlate NE alarms in a mobile network that includes virtualized network functions. | |
| Actors and Roles | 3GPP management system (EM, NM) correlates NE alarms. NFV MANO functional entity VNFM notifies virtualized resource alarms to 3GPP management system. | |
| Telecom resources | VNFM, 3GPP management system (EM, NM) | |
| Assumptions | - 3GPP management system can get VNF application alarms of the faulty NE, and - VNFM can get virtualized resource alarms and identify the corresponding VNF instance. | |
| Pre conditions | N/A | |
| Begins when | There is a new failure which may impact the virtualized resource and the corresponding NE application. | |
| Step 1 (M) | 3GPP management system gets VNF application alarm(s) of a faulty NE. VNFM gets virtualized resource alarm(s) and notifies the corresponding VNF instance related virtualized resource alarm(s) to 3GPP management system. | |
| Step 2 (M) | Based on the virtualized resource alarm(s) sent from VNFM and those VNF application alarms reported from NE, 3GPP management system makes alarm correlation. | |
| Ends when | Ends when all mandatory steps identified above are successfully completed or when an exception occurs. | |
| Exceptions | One of the steps identified above fails. | |
| Post Conditions | The virtualized resource alarm(s) and VNF application alarm(s) are correlated by 3GPP management system. | |
| Traceability | REQ-MAMO_FM-CON-3, REQ-MAMO_FM-CON-4, REQ-MAMO_FM-CON-5 | |

5.4.2 NFVI Maintenance coordination

| Use Case Stage | Evolution / Specification | <<Uses>> Related use |
|-------------------|---|-------------------------|
| Goal | To avoid the unwanted impact to VNF application from NFVI maintenance | |
| Actors and Roles | NM, NFVO, VNFM, VIM | |
| Telecom resources | NFVO, VNFM VIM, NFVI | |
| Assumptions | There is an agreement that NFV-MANO system should get permission from NM before scheduled NFVI maintenance, managed by NFV-MANO, can start. | |
| Pre conditions | N/A | |
| Begins when | NFVO receives a notification from VIM informing about NFVI maintenance impacting the VRs (Virtualised Resources) that are used by a NS instance (e.g. the subordinative VNF instances and Virtual Links). | |
| Step 1 (M) | NFVO informs NM about the NFVI maintenance. | |
| Step 2 (M) | NM confirms the NFVI maintenance positively or not positively. | |
| Step 3 (M) | NFVO acts according to the response from NM. | |
| Ends when | Ends when all mandatory steps identified above are successfully completed or when an exception occurs. | |
| Exceptions | One of the steps identified above fails. | |
| Post Conditions | NFVI maintenance activity has been coordinated between NM and NFVO. | |
| Traceability | FFS | |

6 Specification level requirements

6.1 Requirements

6.1.1 Requirements for Itf-N

REQ-NFV_FM_Itf-N-FUN-1 IRPAgent shall have the capability to send VNF application alarms to IRPManager.

REQ-NFV_FM_Itf-N-FUN-2 IRPAgent should have the capability to send VNF instance related virtualized resource alarms to IRPManager.

REQ-NFV_FM_Itf-N-FUN-3 The existing AlarmIRP should be reused as much as possible.

6.1.2 Requirements for Os-Ma-nfvo

None.

6.1.3 Requirements for Ve-Vnfm-em

REQ-NFV_FM_Ve-Vnfm-em-FUN-1 The Ve-Vnfm-em reference point shall support a capability allowing VNFM to notify EM the VNF and/or VNFC instance related virtualized resource failure reports, in which information (e.g. VM Identifier, vNIC/vPORT Identifier) of faulty VNF and/or VNFC instance is included.

REQ-NFV_FM_Ve-Vnfm-em-FUN-2 The Ve-Vnfm-em reference point shall support a capability allowing VNFM to notify EM and other authorized consumers who can play the role of EM, the virtualization-specific aspect failure reports, in which information of faulty VNF and VNFC instance(s) is included.

REQ-NFV_FM_Ve-Vnfm-em-FUN-3 The Ve-Vnfm-em reference point shall support the EM to send to VNFM a request to execute the VNF Healing of a virtualized network function indicating the corresponding healing procedure and VNFC instance(s).

REQ-NFV_FM_Ve-Vnfm-em-FUN-4 The Ve-Vnfm-em reference point shall support a capability allowing EM to subscribe/unsubscribe to VNF and VNFC instance related alarm notification provided by the VNFM.

6.1.4 Requirements for Ve-Vnfm-vnf

REQ-NFV_FM_Ve-Vnfm-vnf-FUN-1 The Ve-Vnfm-vnf reference point shall support the capability for the VNF virtualization-specific component to notify about faulty virtualization-specific aspects to VNFM.

6.2 Actor roles

See actors and roles of each use case in clause 6.4.

6.3 Telecommunications resources

See telecom resources of each use case in clause 6.4.

6.4 Use cases

6.4.1 NE alarm correlation in the context of NFV

| Use Case Stage | Evolution / Specification | <<Uses>> Related use |
|-------------------|--|-------------------------|
| Goal | To correlate NE alarms in a mobile network that includes virtualized network functions. | |
| Actors and Roles | EM or NM correlates NE alarms. VNFM notifies virtualized resource alarms to EM. EM sends VNF application failure reports and VNF instance related virtualized failure reports to NM. | |
| Telecom resources | NM, EM, VNFM | |
| Assumptions | 3GPP management system (EM, NM) can get VNF application alarms of the faulty NE. VNFM can get virtualized resource alarms and identify the corresponding VNF instance. | |
| Pre conditions | N/A | |
| Begins when | There is a new failure which may impact the virtualized resource and the corresponding NE application. | |
| Step 1 (M) | EM sends VNF application failure reports of a fault NE to NM. | |
| Step 2 (M) | VNFM sends VNF instance related virtualized failure reports to EM, in which information of the failed VNF instance is included. EM reports VNF instance related virtualized failure reports to NM. NOTE: Sequence of step 1 and step 2 may be reversed. | |
| Step 3 (M) | Based on the virtualized resource failure reports sent from VNFM and VNF application alarms, EM or NM makes the alarm correlation. | |
| Ends when | Ends when all steps identified above are successfully completed or when an exception occurs. | |
| Exceptions | One of the steps identified above fails. | |
| Post Conditions | Failure reports of a faulty NE are reported and correlated by 3GPP management system. | |
| Traceability | REQ-NFV_FM_Itf-N-FUN-1, REQ-NFV_FM_Itf-N-FUN-2, REQ-NFV_FM_Ve-Vnfm-em-FUN-1 | |

6.4.2 VNF Healing through operation request to VNFM by EM

NOTE: In the context of this use case, VNF Healing [6] refers to corrective actions performed by the VNFM to recover a VNF which fails to perform as expected, and/or its VNFC instances and internal VNF Virtual Link(s), and it concerns the actions for which the VNFM is responsible, i.e., corrective action(s) toward virtualised resources, instantiation of VNFC, configuration of VNF deployment specific parameters, etc.

| Use case stage | Evolution/Specification | <<Uses>> Related use |
|-------------------|--|-------------------------|
| Goal | To recover the faulty virtualization-specific aspect of a virtualized network function by executing a VNF Healing through an operation request to VNFM by EM and notify about the execution of the VNF healing through reference point Ve-Vnfm-em. | |
| Actors and Roles | EM requests the VNFM to execute the VNF healing based on the information included in the request. | |
| Telecom resources | EM. VNFM. VNF. | |
| Assumptions | EM is subscribed to VNF lifecycle change notifications from the VNFM. | |
| Pre-conditions | The subject VNF instance is not being healed at the moment. | |
| Begins when | A faulty virtualization-specific aspect of the VNF has been notified to EM. | |
| Step 1 (M) | EM determines that VNF Healing is needed. | |
| Step 2 (M) | EM requests the VNFM to execute the VNF Healing with indication of VNF Components to recover and indication of the healing procedure to execute with input parameters as required. | |
| Step 3 (O) | VNFM sends to EM a notification about the start of the VNF healing execution. | |
| Step 4 (M) | The VNFM executes the procedure to heal the VNF instance. | |
| Step 5 (M) | VNFM sends to EM a notification about the end and the result of the VNF Healing execution. | |
| Ends when | All the steps identified above are successfully completed. | |
| Exceptions | The VNF Healing procedure in step 4 fails. | |
| Post-conditions | The faulty virtualization-specific aspect of the VNF is recovered. | |
| Traceability | REQ-NFV_FM_Ve-Vnfm-em-FUN-3 | |

6.4.3 Virtualization-specific aspect failure detection and notification by VNFM

| Use case stage | Evolution/Specification | <<Uses>> Related use |
|-------------------|--|-------------------------|
| Goal | To notify the EM about a virtualization-specific failure of a virtualized network function through Ve-Vnfm-em reference point. | |
| Actors and Roles | VNF virtualization-specific component. | |
| Telecom resources | EM. VNFM. VNF. | |
| Assumptions | - VNFM receives virtualised resource fault reports from VIM. - VNF application-specific fault is reported to the EM. - EM is subscribed to VNF-related virtualization fault reports from the VNFM. | |
| Pre-conditions | N/A | |
| Begins when | The virtualization-specific failure is detected by the VNF virtualization-specific component. | |
| Step 1 (M) | VNF virtualization-specific component sends virtualization-specific fault notification to VNFM over Ve-Vnfm-vnf reference point. | |
| Step 2 (M) | VNFM creates VNF virtualization-related fault report about the VNF and its VNF Components. | |
| Step 3 (M) | VNFM sends the VNF virtualization-related fault report to the EM over Ve-Vnfm-em reference point. | |
| Ends when | All the steps identified above are successfully completed. | |
| Exceptions | | |
| Post-conditions | The EM is notified about the virtualization-specific failure of the subject VNF. | |
| Traceability | REQ-NFV_FM_Ve-Vnfm-vnf-FUN-1, REQ-NFV_FM_Ve-Vnfm-em-FUN-2 | |

6.4.4 Virtualization-specific aspect failure detection and notification by EM

| Use case stage | Evolution/Specification | <<Uses>> Related use |
|-------------------|--|-------------------------|
| Goal | To notify the EM about a virtualization-specific failure of a virtualized network function. | |
| Actors and Roles | VNF virtualization-specific component | |
| Telecom resources | EM. VNFM. VNF. | |
| Assumptions | - VNF application-specific fault is reported to the EM. - EM is subscribed to VNF-related virtualization fault reports. | |
| Pre-conditions | N/A | |
| Begins when | The virtualization-specific failure is detected by the VNF virtualization-specific component. | |
| Step 1 (M) | VNF virtualization-specific component sends virtualization-specific fault notification to EM. | |
| Ends when | All the steps identified above are successfully completed. | |
| Exceptions | | |
| Post-conditions | The EM is notified about the virtualization-specific failure of the subject VNF. | |
| Traceability | | |

6.4.5 NE alarm reporting in the context of NFV

| Use Case Stage | Evolution / Specification | <<Uses>> Related use |
|-------------------|---|-------------------------|
| Goal | To send or notify NE alarms in a mobile network that includes virtualized network functions. | |
| Actors and Roles | EM reports NE alarms to NM. NFV MANO functional entity VNFM notifies VNF instance alarms related to virtualized resource to 3GPP management system EM. | |
| Telecom resources | VNFM, EM, NM | |
| Assumptions | EM can detect VNF application alarms of the faulty NE, and VNFM can get virtualized resource alarms, identify the corresponding VNF instance and notify the corresponding VNF instance alarm to EM. | |
| Pre conditions | N/A | |
| Begins when | There is a failure which impacts the NE application and/or the corresponding virtualized resources. | |
| Step 1 (M) | EM detects VNF application alarm(s) of a faulty NE. | |
| Step 2 (M) | If there is virtualized resource alarm(s), VNFM notifies the corresponding VNF instance alarm(s) with related virtualized resource information to EM. | |
| Step 3 (M) | EM reports the NE application alarm(s) and/or the VNF instance alarm(s) sent from VNFM to NM over Itf-N. | |
| Ends when | Ends when all mandatory steps identified above are successfully completed or when an exception occurs. | |
| Exceptions | One of the steps identified above fails. | |
| Post Conditions | NE alarms are sent from EM to NM. | |
| Traceability | REQ-NFV_FM_Itf-N-FUN-3 | |

6.4.6 Virtualization-specific aspect failure notification by VNFM

| Use case stage | Evolution/Specification | <<Uses>> Related use |
|-------------------|---|-------------------------|
| Goal | To notify authorized consumer who can play the role of EM about virtualization-specific aspect alarms. | |
| Actors and Roles | The consumer | |
| Telecom resources | VNFM | |
| Assumptions | The consumer that requires the VNF-related virtualization fault information produced by VNFM, has a subscription to receive such information, | |
| Pre-conditions | N/A | |
| Begins when | VNFM is aware of a VNF virtualization-specific aspect problem. | |
| Step 1 (M) | VNFM creates an alarm record. | |
| Step 2 (M) | VNFM sends the alarm record to the consumer(s) which has subscribed to receiving such information. | |
| Ends when | All the steps identified above are successfully completed. | |
| Exceptions | | |
| Post-conditions | The consumer(s) has received the virtualization-specific aspects failure information. | |
| Traceability | REQ-NFV_FM_Ve-Vnfm-em-FUN-2 | |

Annex A (informative): Change history

| Change history | | | | | | | |
|----------------|---------|-----------|------|-----|-----|--|-------------|
| Date | Meeting | TDoc | CR | Rev | Cat | Subject/Comment | New version |
| 2017-03 | SA#75 | SP-170117 | | | | Presented for approval | 2.0.0 |
| 2017-03 | SA#75 | | | | | Upgrade to change control version | 14.0.0 |
| 2017-06 | SA#76 | SP-170505 | 0001 | - | F | Update text in the scope to align with other NFV TSs | 14.1.0 |

History

| Document history | | |
|-------------------------|-----------|-------------|
| V14.0.0 | May 2017 | Publication |
| V14.1.0 | July 2017 | Publication |
| | | |
| | | |
| | | |