

# ETSI TS 128 623 V17.2.2 (2022-07)



**Universal Mobile Telecommunications System(UMTS) ;**

**LTE ;**

**5G ;**

**Telecommunication management;**

**Generic Network Resource Model (NRM)**

**Integration Reference Point (IRP);**

**Solution Set (SS) definitions**

**(3GPP TS 28.623 version 17.2.2 Release 17)**



---

Reference

RTS/TSGS-0528623vh22

---

Keywords

5G,LTE,UMTS

***ETSI***

650 Route des Lucioles  
 F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B  
 Association à but non lucratif enregistrée à la  
 Sous-Préfecture de Grasse (06) N° w061004871

---

***Important notice***

The present document can be downloaded from:  
<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at [www.etsi.org/deliver](http://www.etsi.org/deliver).

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at  
<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:  
<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our  
 Coordinated Vulnerability Disclosure Program:  
<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

---

***Notice of disclaimer & limitation of liability***

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use or inability to use the software.

---

***Copyright Notification***

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2022.  
 All rights reserved.

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

**DECT™, PLUGTESTS™, UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

# Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

---

# Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

---

## Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	5
Introduction .....	5
1    Scope .....	6
2    References .....	6
3    Definitions and abbreviations.....	7
3.1    Definitions .....	7
3.2    Abbreviations .....	7
4    Solution Set (SS) definitions .....	7
<b>Annex A (normative):        CORBA Solution Set .....</b>	<b>8</b>
A.0    General .....	8
A.1    Architectural features .....	8
A.1.1    Syntax for Distinguished Names .....	8
A.1.2    Rules for NRM extensions .....	8
A.1.2.0    Introduction.....	8
A.1.2.1    Allowed extensions.....	8
A.1.2.2    Extensions not allowed .....	8
A.2    Mapping .....	10
A.2.1    General mapping .....	10
A.2.2    Information Object Class (IOC) mapping .....	10
A.2.2.1    IOC SubNetwork .....	10
A.2.2.2    IOC ManagedElement .....	10
A.2.2.3    IOC MeContext .....	10
A.2.2.4    IOC ManagementNode .....	11
A.2.2.5    IOC VsDataContainer .....	11
A.2.2.6    IOC ManagedFunction .....	11
A.2.2.7    IOC IRPAgent .....	11
A.2.2.8    IOC Top .....	11
A.2.2.9    IOC Link .....	12
A.2.2.10    IOC EP_RP .....	12
A.2.2.11    IOC ThresholdMonitoringCapability .....	12
A.2.2.12    IOC ThresholdMonitor .....	12
A.2.2.13    IOC TraceJob.....	13
A.3    Solution Set (SS) definitions .....	14
A.3.1    IDL definition structure .....	14
A.3.2    IDL specification "GenericNetworkResourcesIRPSystem.idl" .....	14
A.3.3    IDL specification "GenericNetworkResourcesNRMDefs.idl" .....	17
<b>Annex B (normative):        XML Definitions .....</b>	<b>20</b>
B.0    General .....	20
B.1    Architectural features .....	20
B.1.0    Introduction .....	20
B.1.1    Syntax for Distinguished Names .....	20
B.2    Mapping .....	20
B.2.1    General mapping .....	20
B.2.2    Information Object Class (IOC) mapping .....	20

B.3	Solution Set (SS) definitions .....	21
B.3.1	XML definition structure.....	21
B.3.2	Graphical Representation .....	21
B.3.3	XML schema "genericNrm.xsd" .....	22
<b>Annex C (normative):</b>	<b>OpenAPI definitions .....</b>	<b>32</b>
C.1	General .....	32
C.2	Void.....	32
C.3	Void.....	32
C.4	Solution Set (SS) definitions .....	32
C.4.1	Void.....	32
C.4.2	Void.....	32
C.4.2a	OpenAPI document "TS28623_ComDefs.yaml" .....	32
C.4.3	OpenAPI document "TS28623_GenericNrm.yaml".....	35
<b>Annex D (normative):</b>	<b>YANG definitions.....</b>	<b>64</b>
D.1	General .....	64
D.2	Modules .....	64
D.2.1	module _3gpp-common-ep-rp.yang .....	64
D.2.2	module _3gpp-common-managed-element.yang .....	65
D.2.3	module _3gpp-common-managed-function.yang.....	68
D.2.4	module _3gpp-common-measurements.yang .....	72
D.2.5	module _3gpp-common-subnetwork.yang .....	80
D.2.6	module _3gpp-common-top@2019-06-17.yang .....	82
D.2.6a	module _3gpp-common-subscription-control.yang.....	83
D.2.7	module _3gpp-common-yang-extensions@2019-06-23.yang.....	86
D.2.8	module _3gpp-common-yang-types.yang .....	87
D.2.9	module _3gpp-common-fm.yang .....	96
D.2.10	module _3gpp-common-trace.yang .....	102
D.2.11	module _3gpp-common-mnsregistry.yang .....	116
D.2.12	module _3gpp-common-mnsregistry.yang .....	117
D.2.13	module _3gpp-common-filemanagement.yang .....	118
D.3	Void.....	120
<b>Annex E (informative):</b>	<b>Change history .....</b>	<b>121</b>
History .....	124	

---

## Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

## Introduction

The present document is part of a TS-family covering the 3<sup>rd</sup> Generation Partnership Project; Technical Specification Group Services and System Aspects; Telecommunication management; as identified below:

28.621 Generic Network Resource Model (NRM) Integration Reference Point (IRP); Requirements.

28.622 Generic Network Resource Model (NRM) Integration Reference Point (IRP); Information Service (IS).

**28.623 Generic Network Resource Model (NRM) Integration Reference Point (IRP); Solution Set (SS) definitions.**

---

## 1 Scope

The TS 28.62x-series (Generic Network Resources IRP) define an Integration Reference Point (IRP) through which an "IRPAgent" (typically an Element Manager or Network Element) can communicate Network Management related information to one or several "IRPManagers" (typically Network Managers).

This TS-family specifies a generic Network Resource Model, NRM (also referred to as a Management Information Model - MIM) with definitions of Information Object Classes (IOCs) and Managed Object Classes (MOCs).

The present document specifies the Solution Set definition for the Generic NRM IRP.

The Solution Set definition is related to 3GPP TS 28.622 V16.4.X [4].

---

## 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 32.101: "Telecommunication management; Principles and high level requirements".
- [2] 3GPP TS 32.102: "Telecommunication management; Architecture".
- [3] 3GPP TS 32.600: "Telecommunication management; Configuration Management (CM); Concept and high-level requirements".
- [4] 3GPP TS 28.622: "Generic Network Resource Model (NRM) Integration Reference Point (IRP); Information Service (IS)".
- [5] 3GPP TS 32.300: "Telecommunication management; Configuration Management (CM); Name convention for Managed Objects".
- [6] Void
- [7] 3GPP TS 32.616: "Telecommunication management; Configuration Management (CM); Bulk CM Integration Reference Point (IRP); Solution Set (SS) definitions".
- [8] W3C REC-xml11-20060816: "Extensible Markup Language (XML) 1.1 (Second Edition)".
- [9] Void.
- [10] W3C XML Schema Definition Language (XSD) 1.1 Part 1: Structures.
- [11] W3C XML Schema Definition Language (XSD) 1.1 Part 2: Datatypes.
- [12] W3C REC-xml-names-20060816: "Namespaces in XML 1.1 (Second Edition)".
- [13] 3GPP TS 32.158: "Management and orchestration; Design rules for REpresentational State Transfer (REST) Solution Sets (SS) ".
- [14] 3GPP TS 32.160: "Management and orchestration; Management Service Template".
- [15] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

---

## 3 Definitions and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [15], 3GPP TS 32.101 [1], 3GPP TS 32.102 [2], 3GPP TS 32.600 [3], 3GPP TS 28.622 [4] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [15] and 3GPP TS 32.101 [1], 3GPP TS 32.102 [2] and 3GPP TS 32.600 [3] and 3GPP TS 28.622 [4].

### 3.2 Abbreviations

For the purposes of the present document, the abbreviations given in 3GPP TR 21.905 [15], 3GPP TS 32.600 [3] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in 3GPP TR 21.905 [15] and 3GPP TS 32.600 [3].

JSON	JavaScript Object Notation
SS	Solution Set

---

## 4 Solution Set (SS) definitions

This specification defines the following 3GPP Generic NRM IRP Solution Set Definitions:

- 3GPP Generic NRM IRP CORBA SS (Annex A).
- 3GPP Generic NRM IRP XML Definitions (Annex B).
- 3GPP Generic NRM IRP JSON Definitions (Annex C).
- 3GPP Generic NRM IRP YANG Definitions (Annex D).

---

## Annex A (normative): CORBA Solution Set

### A.0 General

This annex contains the CORBA Solution Set for the IRP whose semantics is specified in Generic NRM IRP: Information Service (3GPP TS 28.622 [4]).

---

### A.1 Architectural features

The overall architectural feature of Generic Network Resources IRP is specified in 3GPP TS 28.622 [4]. This clause specifies features that are specific to the CORBA SS.

#### A.1.1 Syntax for Distinguished Names

The syntax of a Distinguished Name is defined in 3GPP TS 32.300 [5].

#### A.1.2 Rules for NRM extensions

##### A.1.2.0 Introduction

This clause discusses how the models and IDL definitions provided in the present document can be extended for a particular implementation and still remain compliant with 3GPP SA5's specifications.

##### A.1.2.1 Allowed extensions

Vendor-specific MOCs may be supported. The vendor-specific MOCs may support new types of attributes. The 3GPP SA5-specified notifications may be issued referring to the vendor-specific MOCs and vendor-specific attributes. New MOCs shall be distinguishable from 3GPP SA5 MOCs by name. 3GPP SA5-specified and vendor-specific attributes may be used in vendor-specific MOCs. Vendor-specific attribute names shall be distinguishable from existing attribute names.

NRM MOCs may be subclassed. Subclassed MOCs shall maintain the specified behaviour of the 3GPP SA5's superior classes. They may add vendor-specific behaviour with vendor-specific attributes. When subclassing, naming attributes cannot be changed. The subclassed MOC shall support all attributes of its superior class. Vendor-specific attributes cannot be added to 3GPP SA5 NRM MOCs without subclassing.

When subclassing, the 3GPP SA5-specified containment rules and their specified cardinality shall still be followed. As an example, ManagementNode (or its subclasses) shall be contained under SubNetwork (or its subclasses).

Managed Object Instances may be instantiated as CORBA objects. This requires that the MOCs be represented in IDL. 3GPP SA5's NRM MOCs are not currently specified in IDL, but may be specified in IDL for instantiation or subclassing purposes. However, management information models should not require that IRPManagers access the instantiated managed objects other than through supported methods in the present document.

Extension rules related to notifications (Notification categories, Event Types, Extended Event Types etc.) are for further study.

##### A.1.2.2 Extensions not allowed

The IDL specifications in the present document cannot be edited or altered. Any additional IDL specifications shall be specified in separate IDL files.

IDL interfaces (note: not MOCs) specified in the present document may not be subclassed or extended. New interfaces may be defined with vendor-specific methods.

## A.2 Mapping

### A.2.1 General mapping

Attributes modelling associations as defined in the NRM (here also called "reference attributes") are in this SS mapped to attributes. The names of the reference attributes in the NRM are mapped to the corresponding attribute names in the MOC. When the cardinality for an association is 0..1 or 1..1 the datatype for the reference attribute is defined as an MOReference. The value of an MO reference contains the distinguished name of the associated MO. When the cardinality for an association allows more than one referred MO, the reference attribute will be of type MOReferenceSet, which contains a sequence of MO references.

### A.2.2 Information Object Class (IOC) mapping

This Solution Set supports reference attributes for relations other than containment relations between objects. Reference attributes are therefore introduced in each MOC where needed.

#### A.2.2.1 IOC SubNetwork

##### **Mapping from NRM IOC SubNetwork attributes to SS equivalent MOC SubNetwork attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
dnPrefix	dnPrefix	string
userLabel	userLabel	string
userDefinedNetworkType	userDefinedNetworkType	string
setOfMcc	setOfMcc	GenericNetworkResourcesIRPSystem::AttributeTypes::StringSet

#### A.2.2.2 IOC ManagedElement

##### **Mapping from NRM IOC ManagedElement attributes and association roles to SS equivalent MOC ManagedElement attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
dnPrefix	dnPrefix	string
userLabel	userLabel	string
locationName	locationName	string
vendorName	vendorName	string
userDefinedState	userDefinedState	string
managedElementType	managedElementType	GenericNetworkResourcesIRPSystem::AttributeTypes::StringSet
managedBy	managedBy	GenericNetworkResourcesIRPSystem::AttributeTypes::MOReferenceSet
swVersion	swVersion	string

#### A.2.2.3 IOC MeContext

##### **Mapping from NRM IOC MeContext attributes to SS equivalent MOC MeContext attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
dnPrefix	dnPrefix	string

### A.2.2.4 IOC ManagementNode

**Mapping from NRM IOC ManagementNode attributes and association roles to SS equivalent MOC ManagementNode attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
userLabel	userLabel	string
locationName	locationName	string
vendorName	vendorName	string
userDefinedState	userDefinedState	string
managedElements	managedElements	GenericNetworkResourcesIRPSys::AttributeTypes::MOResourceSet
swVersion	swVersion	string

### A.2.2.5 IOC VsDataContainer

**Mapping from NRM IOC VsDataContainer attributes and association roles to SS equivalent MOC VsDataContainer attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
vsDataType	vsDataType	string
vsData	vsData	any
vsDataFormatVersion	vsDataFormatVersion	string

### A.2.2.6 IOC ManagedFunction

**Mapping from NRM IOC ManagedFunction attributes and association roles to SS equivalent MOC ManagedFunction attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
peeParametersList	peeParametersList	GenericNetworkResourcesIRPSys::AttributeTypes::PEEParametersListType
userLabel	userLabel	string
vnfParametersList	vnfParametersList	GenericNetworkResourcesIRPSys::AttributeTypes::VNFPParametersListType

### A.2.2.7 IOC IRPAgent

**Mapping from NRM IOC IRPAgent attributes to SS equivalent MOC IRPAgent attributes**

IS Attributes	SS Attributes	SS Type
id	id	string
systemDN	systemDN	string

### A.2.2.8 IOC Top

**Mapping from NRM IOC Top attributes to SS equivalent attributes in all MOCs**

IS Attributes	SS Attributes	SS Type
objectClass	CLASS	string
objectInstance	No direct mapping	

### A.2.2.9 IOC Link

#### Mapping from NRM IOC Link attributes to SS equivalent MOC IRP Agent attributes

IS Attributes	SS Attributes	SS Type
id	id	string
userLabel (see note 2)	userLabel	string
aEnd	aEnd	GenericNetworkResourcesIRPSys tem::AttributeTypes::MOReference
zEnd	zEnd	GenericNetworkResourcesIRPSys tem::AttributeTypes::MOReference
linkType	linkType	LinkTypeType
protocolName	protocolName	string
protocolVersion	protocolVersion	string

NOTE 1: Void.

NOTE 2: Void.

### A.2.2.10 IOC EP\_RP

#### Mapping from NRM IOC EP\_RP attributes to SS equivalent MOC EP\_RP attributes

IS Attributes	SS Attributes	SS Type
id	id	string
userLabel	userLabel	string
farEndEntity	farEndEntity	GenericNetworkResourcesIRPSys tem::AttributeTypes::MOReference

### A.2.2.11 IOC ThresholdMonitoringCapability

#### Mapping from NRM IOC ThresholdMonitoringCapability attributes to SS equivalent MOC ThresholdMonitoringCapability attributes

IS Attributes	SS Attributes	SS Type
supportedMonitoringGPs	supportedMonitoringGPs	GenericNetworkResourcesIRPSys tem::AttributeTypes::LongSe t

### A.2.2.12 IOC ThresholdMonitor

#### Mapping from NRM IOC ThresholdMonitor attributes to SS equivalent MOC ThresholdMonitor attributes

IS Attributes	SS Attributes	SS Type
thresholdInfoList	thresholdInfoList	GenericNetworkResourcesIRPSys tem::AttributeTypes::ThresholdInfoListType
monitoringGP	monitoringGP	long
monitoringNotifTarget	monitoringNotifTarget	string
monitoredIOCName	monitoredIOCName	string
monitoredObjectDNs	monitoredObjectDNs	GenericNetworkResourcesIRPSys tem::AttributeTypes::DNListType

## A.2.2.13 IOC TraceJob

### Mapping from NRM IOC TraceJob attributes to SS equivalent MOC TraceJob attributes

IS Attributes	SS Attributes	SS Type
tjJobType	tjJobType	tjJobType-Type
tjListOfInterfaces	tjListOfInterfaces	tjListOfInterfaces-Type
tjListOfNeTypes	tjListOfNeTypes	tjListOfNeTypes-Type
tjPLMNTarget	tjPLMNTarget	tjPLMNTarget-Type
tjStreamingTraceConsumerURI	tjTraceConsumer	StreamingTraceConsumerURI-Type
tjTraceCollectionEntityAddress	tjTraceConsumer	TraceCollectionEntityAddress-Type
tjTraceDepth	tjTraceDepth	tjTraceDepth-Type
tjTraceReference	tjTraceReference	tjTraceReference-Type
tjTraceReportingFormat	tjTraceReportingFormat	tjTraceReportingFormat-Type
tjTraceTarget	tjTraceTarget	tjTraceTarget-Type
tjTriggeringEvent	tjTriggeringEvent	tjTriggeringEvent-Type
tjMDTAnonymizationOfData	tjMDTAnonymizationOfData	tjMDTAnonymizationOfData-Type
tjMDTAreaConfigurationForNeighCell	tjMDTAreaConfigurationForNeighCell	tjMDTAreaConfigurationForNeighCell-Type
tjMDTAreaScope	tjMDTAreaScope	tjMDTAreaScope-Type
tjMDTCollectionPeriodRrmLte	tjMDTCollectionPeriodRrmLte	tjMDTCollectionPeriodRrmLte-Type
tjMDTCollectionPeriodRrmUmts	tjMDTCollectionPeriodRrmUmts	tjMDTCollectionPeriodRrmUmts-Type
tjMDTCollectionPeriodRrmNR	tjMDTCollectionPeriodRrmNR	tjMDTCollectionPeriodRrmNR-Type
tjMDTEventListForTriggeredMeasurement	tjMDTEventListForTriggeredMeasurement	tjMDTEventListForTriggeredMeasurement-Type
tjMDTEventThreshold	tjMDTEventThreshold	tjMDTEventThreshold-Type
tjMDTListOfMeasurements	tjMDTListOfMeasurements	tjMDTListOfMeasurements-Type
tjMDTLoggingDuration	tjMDTLoggingDuration	tjMDTLoggingDuration-Type
tjMDTLoggingInterval	tjMDTLoggingInterval	tjMDTLoggingInterval-Type
tjMDTMBSFNAreaList	tjMDTMBSFNAreaList	tjMDTMBSFNAreaList-Type
tjMDTMeasurementPeriodLTE	tjMDTMeasurementPeriodLTE	tjMDTMeasurementPeriodLTE-Type
tjMDTMeasurementPeriodUMTS	tjMDTMeasurementPeriodUMTS	tjMDTMeasurementPeriodUMTS-Type
tjMDTMeasurementQuantity	tjMDTMeasurementQuantity	tjMDTMeasurementQuantity-Type
tjMDTPLMList	tjMDTPLMList	tjMDTPLMList-Type
tjMDTPositioningMethod	tjMDTPositioningMethod	tjMDTPositioningMethod-Type
tjMDTReportAmount	tjMDTReportAmount	tjMDTReportAmount-Type
tjMDTReportingTrigger	tjMDTReportingTrigger	tjMDTReportingTrigger-Type
tjMDTReportInterval	tjMDTReportInterval	tjMDTReportInterval-Type
tjMDTReportType	tjMDTReportType	tjMDTReportType-Type
tjMDTSensorInformation	tjMDTSensorInformation	tjMDTSensorInformation-Type
tjMDTTraceCollectionEntityID	tjMDTTraceCollectionEntityID	tjMDTTraceCollectionEntityID-Type

## A.3 Solution Set (SS) definitions

### A.3.1 IDL definition structure

Clause A.3.2 defines the types which are used by the Generic NRM IRP.

Clause A.3.3 defines the MO classes for the Generic NRM IRP.

### A.3.2 IDL specification "GenericNetworkResourcesIRPSysytem.idl"

```
//File: GenericNetworkResourcesIRPSysytem.idl
#ifndef _GENERIC_NETWORK_RESOURCES_IRP_SYSTEM_IDL_
#define _GENERIC_NETWORK_RESOURCES_IRP_SYSTEM_IDL_

// This statement must appear after all include statements
#pragma prefix "3gppsa5.org"

module GenericNetworkResourcesIRPSysytem
{
    /**
     * The format of Distinguished Name (DN) is specified in "Name Convention
     * for Managed Objects (3GPP TS 32.300 [5])".
     */
    typedef string DN;

    /**
     * This module adds datatype definitions for types
     * used in the NRM which are not basic datatypes defined
     * already in CORBA.
     */
    module AttributeTypes
    {
        /**
         * An MO reference refers to an MO instance.
         * "otherMO" contains the distinguished name of the referred MO.
         * A conceptual "null" reference (meaning no MO is referenced)
         * is represented as an empty string ("").
         */
        struct MOReference
        {
            DN otherMO;
        };

        /**
         * MOReferenceSet represents a set of MO references.
         * This type is used to hold 0..n MO references.
         * A referred MO is not allowed to be repeated (therefore
         * it is denoted as a "Set")
         */
        typedef sequence<MOReference> MOReferenceSet;

        /**
         * A set of strings.
         */
        typedef sequence<string> StringSet;

        /**
         * A set of long.
         */
        typedef sequence<long> LongSet;
        /*
         * The LinkListSet represents the Link_X_Y objects (or subclasses of
         * Link_X_Y objects) that have a relationship with this object instance.
         * Each Link_X_Y object models interface(s) between objects of class X and
         * Y. The object containing this attribute must either be a class of type X,
         * Y, XFunction, YFunction or a subclass of one of those classes. The
         * LinkListSet may be empty, or there may be no instances for a particular
         * Link_X_Y class name.
         */
        typedef MOReferenceSet LinkListSet;
    }
}
```

```

/**
 * VNFParameters includes several attributes of a VNF instance.
 * The detailed definition of the attributes, see clause 4.4.1 of [4].
 */
struct VNFParameters
{
    string vnfInstanceId;
    string vnfId;
    string flavourId;
    boolean autoScalable;
};

/**
 * VNFParametersListType represents a list of VNFParameters.
 * The detailed definition of vnfParametersListType, see clause 4.4.1 of [4].
 */
typedef sequence<VNFParameters> VNFParametersListType;
struct PEEParameters
{
    string siteIdentification;
    float siteLatitude;
    float siteLongitude;
    string siteDescription;
    string equipmentType;
    string environmentType;
    string powerInterface;
};

/**
 * PEEParametersListType represents a list of PEEParameters.
 * The detailed definition of PEEParametersListType, see clause 4.4.1 of [4].
 */
typedef sequence<PEEParameters> PEEParametersListType;

typedef any ThresholdValueType;
enum Direction {INCREASING, DECREASING};
union HysteresisType switch(boolean)
{
    case TRUE: long long_value;
    case FALSE: float float_value;
};
struct ThresholdPackElement
{
    ThresholdValueType thresholdValue;
    short thresholdLevel;
    HysteresisType hysteresis;
};
typedef sequence<ThresholdPackElement> ThresholdPackType;
struct ThresholdInfo
{
    string measurementType;
    Direction direction_;
    ThresholdPackType thresholdPack;
};
typedef sequence<ThresholdInfo> ThresholdInfoListType;

};

/**
 * This module adds datatype definitions for PM Control
 */
module PMControlTypes
{
    Struct Measurements
    {
        measurementTypes StringSet,
        gPs LongSet
    };
    typedef sequence <Measurements> Measurements;

    enum PMAAdministrativeStateType
    {
        LOCKED,
        SHUTTINGDOWN,
        UNLOCKED
    };
}

```

```
enum PMOperationalStateType
{
    ENABLED,
    DISABLED
};

typedef MOPreferenceSet ManagedObjectDNsType;

typedef MOPreferenceSet ManagedObjectDNsBasicType;

typedef integer DefaultFileBasedGPType;
typedef integer DefaultFileReportPeriodType;
typedef string DefaultFileLocationType;
typedef integer DefaultStreamBasedGPType;
typedef string DefaultStreamTargetType;

typedef integer FileBasedGPType;
typedef integer FileReportingPeriodType;
typedef string FileLocationType;
typedef integer StreamBasedGPType;
typedef string StreamTargetType;

};

};

#endif // _GENERIC_NETWORK_RESOURCES_IRP_SYSTEM_IDL_
```

### A.3.3 IDL specification "GenericNetworkResourcesNRMDefs.idl"

```

//File: GenericNetworkResourcesNRMDefs.idl
#ifndef _GENERIC_NETWORK_RESOURCES_NRM_DEFS_IDL_
#define _GENERIC_NETWORK_RESOURCES_NRM_DEFS_IDL_
// This statement must appear after all include statements
#pragma prefix "3gppsa5.org"
/**
 * This module defines constants for each MO class name and
 * the attribute names for each defined MO class.
 */
module GenericNetworkResourcesNRMDefs
{
    /**
     * Definitions for MO class Top
     */
    interface Top
    {
        // Attribute Names
        //
        const string CLASS = "Top";
    };
    /**
     * Definitions for MO class SubNetwork
     */
    interface SubNetwork : Top
    {
        const string CLASS = "SubNetwork";
        // Attribute Names
        //
        const string id = "id";
        const string dnPrefix = "dnPrefix";
        const string userLabel = "userLabel";
        const string userDefinedNetworkType = "userDefinedNetworkType";
        const string setOfMcc = "setOfMcc";
    };

    /**
     * Definitions for MO class ManagedElement
     */
    interface ManagedElement : Top
    {
        const string CLASS = "ManagedElement";
        // Attribute Names
        //
        const string id = "id";
        const string dnPrefix = "dnPrefix";
        const string managedElementType = "managedElementType";
        const string userLabel = "userLabel";
        const string vendorName = "vendorName";
        const string userDefinedState ="userDefinedState";
        const string locationName ="locationName";
        const string managedBy = "managedBy";
        const string swVersion = "swVersion";
    };

    /**
     * Definitions for MO class MeContext
     */
    interface MeContext : Top
    {
        const string CLASS = "MeContext";
        // Attribute Names
        //
        const string id = "id";
        const string dnPrefix = "dnPrefix";
    };
    /**
     * Definitions for MO class ManagementNode
     */
    interface ManagementNode : Top
    {
        const string CLASS = "ManagementNode";

        // Attribute Names
        //
        const string id = "id";

```

```

    const string userLabel = "userLabel";
    const string vendorName = "vendorName";
    const string userDefinedState = "userDefinedState";
    const string locationName = "locationName";
    const string managedElements = "managedElements";
    const string swVersion = "swVersion";
}

/***
 * Definitions for abstract MO class ManagedFunction
 */
interface ManagedFunction : Top
{
    const string CLASS = "ManagedFunction";
    // Attribute Names
    //
    const string id = "id";
    const string peeParametersList = "peeParametersList";
    const string userLabel = "userLabel";
    const string vnfParametersList = "vnfParametersList";
}

/***
 * Definitions for MO class IRPAGent
 */
interface IRPAGent : Top
{
    const string CLASS = "IRPAGent";
    // Attribute Names
    //
    const string id = "id";
    const string systemDN = "systemDN";
};

/***
 * Definitions for abstract MO class Link
 * This inherits from ManagedFunction
 * The attributes aEnd and zEnd are populated with the DNs
 * of the entities associated via the link class.
 * The aEnd takes the DN of the 1st entity in alphabetical order,
 * the zEnd takes the 2nd entity in alphabetical order of the class
 * names.
 */
interface Link : ManagedFunction
{
    const string CLASS = "Link";
    // Attribute Names
    //
    const string aEnd = "aEnd";
    const string zEnd = "zEnd";
    const string linkType = "linkType";
    const string protocolName = "protocolName";
    const string protocolVersion = "protocolVersion";
};

/***
 * Definitions for MO class VsDataContainer
 */
interface VsDataContainer : Top
{
    const string CLASS = "VsDataContainer";
    // Attribute Names
    //
    const string id = "id";
    const string vsDataType = "vsDataType";
    const string vsData = "vsData";
    const string vsDataFormatVersion = "vsDataFormatVersion";
};

/***
 * Definitions for abstract MO class EP_RP
 */
interface EP_RP : Top
{
    const string CLASS = "EP_RP";
    // Attribute Names
    //
    const string farEndEntity = "farEndEntity";
    const string id = "id";
    const string userLabel = "userLabel";
}

```

```

};

/***
 * Definitions for MO class ThresholdMonitoringCapability
 */
interface ThresholdMonitoringCapability : Top
{
    const string CLASS = "ThresholdMonitoringCapability";
    // Attribute Names
    //
    const string supportedMonitoringGPs = "supportedMonitoringGPs";
}

/***
 * Definitions for MO class ThresholdMonitor
 */
interface ThresholdMonitor : Top
{
    const string CLASS = "ThresholdMonitor";
    // Attribute Names
    //
    const string thresholdInfoList = "thresholdInfoList";
    const string monitoringGP = "monitoringGP";
    const string monitoringNotifTarget = "monitoringNotifTarget";
    const string monitoredIOCName = "monitoredIOCName";
    const string monitoredObjectDNs = "monitoredObjectDNs";
}

/***
 * This module adds datatypes definitions for the Link Class
 * These attributes are not the basic datatypes already defined
 */
module LinkAttributeTypes
{
    enum LinkType
    {
        SIGNALLING,
        BEARER,
        OAM_AND_P,
        OTHER
    };
    typedef sequence <LinkType> LinkTypeType;
};

#endif // _GENERIC_NETWORK_RESOURCES_NRM_DEFS_IDL_

```

---

## Annex B (normative): XML Definitions

### B.0 General

This annex contains the XML Definitions for the Generic NRM IRP as it applies to Itf-N, in accordance with Generic NRM IRP IS definitions TS 28.622 [4].

The XML file formats are based on XML W3C REC-xml11-20060816 [8], W3C XML Schema Definition Language (XSD) 1.1 Part 1: Structures [10] W3C XML Schema Definition Language (XSD) 1.1 Part 2: Datatypes [11] and W3C REC-xml-names-20060816 [12] standards.

---

### B.1 Architectural features

#### B.1.0 Introduction

The overall architectural feature of Generic Network Resources IRP is specified in 3GPP TS 28.622 [4].

This clause specifies features that are specific to the Schema definitions.

#### B.1.1 Syntax for Distinguished Names

The syntax of a Distinguished Name is defined in 3GPP TS 32.300 [5].

---

### B.2 Mapping

#### B.2.1 General mapping

An IOC maps to an XML element of the same name as the IOC's name in the IS. An IOC attribute maps to a sub-element of the corresponding IOC's XML element, and the name of this sub-element is the same as the attribute's name in the IS.

#### B.2.2 Information Object Class (IOC) mapping

The mapping is not present in the current version of this specification.

---

## B.3 Solution Set (SS) definitions

### B.3.1 XML definition structure

The overall description of the file format of configuration data XML files is provided by 3GPP TS 28.616 [7].

Annex B.3.3 of the present document defines the NRM-specific XML schema `genericNrm.xsd` for the Generic Network Resources IRP NRM defined in 3GPP TS 28.622 [4].

XML schema `genericNrm.xsd` explicitly declares NRM-specific XML element types for the related NRM.

The definition of those NRM-specific XML element types complies with the generic mapping rules defined in 3GPP TS 28.616 [7], with the following exception: as defined in 3GPP TS 28.616 [7], the `vsData` XML element type has an empty XML content.

Additionally, XML schema `genericNrm.xsd` also provides the following global XML declarations and definitions:

- XML complex type `NrmClass`: derivation base type (see [8], [10] and [11]) for all NRM class associated XML element types (see 3GPP TS 28.616 [7]);
- XML element type `vsData`: derivation base type (see [8], [10] and [11]) for all vendor-specific XML element types (see 3GPP TS 28.616 [7]);
- XML element type `SubNetworkOptionallyContainedNrmClass`: substitution group head (see [8], [10] and [11]) for all XML element types associated to further NRM classes optionally contained under SubNetwork NRM class;
- XML element type `ManagedElementOptionallyContainedNrmClass`: substitution group head (see [8], [10] and [11]) for all XML element types associated to further NRM classes optionally contained under ManagedElement NRM class.

### B.3.2 Graphical Representation

The graphical representation is not present in the current version of this specification.

### B.3.3 XML schema "genericNrm.xsd"

```

<?xml version="1.1" encoding="UTF-8"?>

<!--
  3GPP TS 28.623 Generic Network Resources IRP
  Bulk CM Configuration data file NRM-specific XML schema
  genericNrm.xsd
-->

<schema
  targetNamespace="http://www.3gpp.org/ftp/specs/archive/28_series/28.623#genericNrm"
  elementFormDefault="qualified"
  attributeFormDefault="unqualified"
  xmlns="http://www.w3.org/2001/XMLSchema"
  xmlns:xn="http://www.3gpp.org/ftp/specs/archive/28_series/28.623#genericNrm"
  xmlns:sp="http://www.3gpp.org/ftp/specs/archive/28_series/28.629#sonPolicyNrm"
>
<import namespace="http://www.3gpp.org/ftp/specs/archive/28_series/28.629#sonPolicyNrm"/>
<!-- Base XML type for all NRM class associated XML elements -->

<complexType name="NrmClass">
  <attribute name="id" type="string" use="required"/>
  <attribute name="modifier" use="optional">
    <simpleType>
      <restriction base="string">
        <enumeration value="create"/>
        <enumeration value="delete"/>
        <enumeration value="update"/>
      </restriction>
    </simpleType>
  </attribute>
</complexType>

<!-- Generic Network Resources IRP NRM attribute related XML types -->

<simpleType name="dn">
  <restriction base="string">
    <maxLength value="400"/>
  </restriction>
</simpleType>

<complexType name="dnList">
  <sequence minOccurs="0" maxOccurs="unbounded">
    <element name="dn" type="xn:dn"/>
  </sequence>
</complexType>

<simpleType name="linkType">
  <list>
    <simpleType>
      <restriction base="string">
        <enumeration value="Signalling"/>
        <enumeration value="Bearer"/>
        <enumeration value="OAM_AND_P"/>
        <enumeration value="Other"/>
      </restriction>
    </simpleType>
  </list>
</simpleType>

<complexType name="linkListType">
  <sequence minOccurs="0" maxOccurs="unbounded">
    <element name="dn" type="xn:dn"/>
  </sequence>
</complexType>

<complexType name="managedElementTypeListType">
  <sequence minOccurs="0" maxOccurs="unbounded">
    <element name="managedElementType" type="string"/>
  </sequence>
</complexType>

<complexType name="vnfParametersListType">
  <sequence minOccurs="1" maxOccurs="unbounded">
    <element name="vnfInstanceId" type="string"/>
    <element name="vnfdId" type="string" minOccurs="0"/>
  </sequence>
</complexType>

```

```

<element name="flavourId" type="string" minOccurs="0" />
<element name="autoScalable" type="boolean" />
</sequence>
</complexType>

<simpleType name="latitude">
<restriction base="decimal">
<fractionDigits value="4"/>
<minInclusive value="-90.0000"/>
<maxInclusive value="90.0000"/>
</restriction>
</simpleType>

<simpleType name="longitude">
<restriction base="decimal">
<fractionDigits value="4"/>
<minInclusive value="-180.0000"/>
<maxInclusive value="180.0000"/>
</restriction>
</simpleType>

<complexType name="peeParametersListType">
<sequence minOccurs="1" maxOccurs="unbounded">
<element name="siteIdentification" type="string" />
<element name="siteLatitude" type="xn:latitude" minOccurs="0" />
<element name="siteLongitude" type="xn:longitude" minOccurs="0" />
<element name="siteDescription" type="string" />
<element name="equipmentType" type="string" />
<element name="environmentType" type="string" />
<element name="powerInterface" type="string" />
</sequence>
</complexType>

<simpleType name="pMAdministrativeStateType">
<restriction base="string">
<enumeration value="LOCKED" />
<enumeration value="SHUTTINGDOWN" />
<enumeration value="UNLOCKED" />
</restriction>
</simpleType>

<simpleType name="pMOperationalStateType">
<restriction base="string">
<enumeration value="ENABLED" />
<enumeration value="DISABLED" />
</restriction>
</simpleType>

<simpleType name="nFServiceType">
<restriction base="string">
<enumeration value="Namf_Communication" />
<enumeration value="Namf_EventExposure" />
<enumeration value="Namf_MT" />
<enumeration value="Namf_Location" />
<enumeration value="Nsmf_PDUSession" />
<enumeration value="Nsmf_EventExposure" />
<enumeration value="others" />
</restriction>
</simpleType>

<simpleType name="usageStateType">
<restriction base="string">
<enumeration value="IDLE" />
<enumeration value="ACTIVE" />
<enumeration value="BUSY" />
</restriction>
</simpleType>

<simpleType name="registrationStateType">
<restriction base="string">
<enumeration value="LOCKED" />
<enumeration value="SHUTTING_DOWN" />
<enumeration value="UNLOCKED" />
</restriction>
</simpleType>

<simpleType name="NFType">
```

```

<restriction base="string">
  <enumeration value="NRF" />
  <enumeration value="UDM" />
  <enumeration value="AMF" />
  <enumeration value="SMF" />
  <enumeration value="AUSF" />
  <enumeration value="NEF" />
  <enumeration value="PCF" />
  <enumeration value="SMSF" />
  <enumeration value="NSSF" />
  <enumeration value="UDR" />
  <enumeration value="GMLC" />
  <enumeration value="5G EIR" />
  <enumeration value="SEPP" />
  <enumeration value="UPF" />
  <enumeration value="N3IWF" />
  <enumeration value="AF" />
  <enumeration value="UDSF" />
  <enumeration value="DN" />
</restriction>
</simpleType>

<simpleType name="operationSemanticsType">
  <restriction base="string">
    <enumeration value="REQUEST_RESPONSE" />
    <enumeration value="SUBSCRIBE_NOTIFY" />
  </restriction>
</simpleType>

<complexType name="SAP">
  <sequence>
    <element name="host" type="xn:hostType" />
    <element name="port" type="integer" />
  </sequence>
</complexType>

<complexType name="hostType">
  <sequence>
    <element name="ipv4Address" type="string" />
    <element name="ipv6Address" type="string" />
    <element name="fqdn" type="string" />
  </sequence>
</complexType>

<complexType name="operationsList">
  <sequence>
    <element name="operation" type="xn:operationType" minOccurs="1" maxOccurs="unbounded" />
  </sequence>
</complexType>

<complexType name="operationType">
  <sequence>
    <element name="name" type="string" />
    <element name="allowedNFTypes" type="xn:NFType" />
    <element name="operationSemantics" type="xn:operationSemanticsType" />
  </sequence>
</complexType>

<complexType name="MeasurementTypeList">
  <sequence minOccurs="1" maxOccurs="unbounded">
    <element name="measurementType" type="string" />
  </sequence>
</complexType>

<complexType name="GPList">
  <sequence minOccurs="1" maxOccurs="unbounded">
    <element name="gP" type="integer" />
  </sequence>
</complexType>

<complexType name="Measurements">
  <sequence>
    <element name="measurementTypes" type="xn:MeasurementTypeList" />
    <element name="GPs" type="xn:GPList" />
  </sequence>
</complexType>

<complexType name="MeasurementsList">

```

```

<sequence>
  <element name="measurements" type="xn:Measurements" minOccurs="1" maxOccurs="unbounded" />
</sequence>
</complexType>

<complexType name="GPListType">
  <sequence minOccurs="1" maxOccurs="unbounded" >
    <element name="GP" type="integer" />
  </sequence>
</complexType>

<complexType name="KPINameList">
  <sequence minOccurs="1" maxOccurs="unbounded" >
    <element name="kPIName" type="string" />
  </sequence>
</complexType>

<complexType name="KPIs">
  <sequence>
    <element name="kPITypes" type="xn:KPINameList" />
    <element name="GPs" type="xn:GPList" />
  </sequence>
</complexType>

<complexType name="KPIsList">
  <sequence>
    <element name="kPIs" type="xn:KPIs" minOccurs="1" maxOccurs="unbounded" />
  </sequence>
</complexType>

<simpleType name="directionType">
  <list>
    <simpleType>
      <restriction base="string">
        <enumeration value="increasing"/>
        <enumeration value="decreasing"/>
      </restriction>
    </simpleType>
  </list>
</simpleType>

<complexType name="thrsholdPackType">
  <sequence minOccurs="1" maxOccurs="unbounded" >
    <element name="thresholdPackElement" type="xn:thresholdPackElementType" />
  </sequence>
</complexType>

<complexType name="thresholdPackElementType">
  <all>
    <element name="thresholdValue" type="string" />
    <element name="thresholdLevel" type="integer" />
    <element name="hysteresis" type="decimal" minOccurs="0" />
  </all>
</complexType>

<complexType name="thresholdInfoType">
  <all>
    <element name="measurementType" type="string" />
    <element name="direction" type=" xn:directionType" />
    <element name="thresholdPack" type=" xn:thrsholdPackType" />
  </all>
</complexType>

<complexType name="thresholdInfoListType">
  <sequence minOccurs="1" maxOccurs="unbounded" >
    <element name="ThresholdInfoElement" type="xn:thresholdInfoType" />
  </sequence>
</complexType>

<simpleType name="ScopeType">
  <restriction base="string">
    <enumeration value="BASE_ONLY" />
    <enumeration value="BASE_ALL" />
    <enumeration value="BASE_NTH_LEVEL" />
    <enumeration value="BASE_SUBTREE" />
  </restriction>

```

```

</simpleType>

<complexType name="Scope">
  <sequence>
    <element name="scopeType" type="xn:ScopeType"/>
    <element name="scopeLevel" type="integer" minOccurs="0"/>
  </sequence>
</complexType>

<!-- Generic Network Resources IRP NRM class associated XML elements -->

<element name="SubNetwork">
  <complexType>
    <complexContent>
      <extension base="xn:NrmClass">
        <sequence>
          <element name="attributes" minOccurs="0">
            <complexType>
              <all>
                <element name="dnPrefix" minOccurs="0"/>
                <element name="userLabel"/>
                <element name="userDefinedNetworkType"/>
                <element name="setOfMcc" minOccurs="0"/>
                <element name="priority" type="integer" minOccurs="0"/>
                <element name="measurementsList" type="xn:MeasurementsList" minOccurs="0"/>
                <element name="kPIsList" type="xn:KPIsList" minOccurs="0"/>
              </all>
            </complexType>
          </element>
        </sequence>
      </extension>
    </complexContent>
  </complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
  <element ref="xn:SubNetwork"/>
  <element ref="xn:ManagedElement"/>
  <element ref="xn:MeContext"/>
  <element ref="xn:ManagementNode"/>
  <element ref="xn:IRPAgent"/>
  <element ref="xn:SubNetworkOptionallyContainedNrmClass"/>
  <element ref="xn:VsDataContainer"/>
  <element ref="xn:ThresholdMonitoringCapability"/>
  <element ref="xn:ThresholdMonitor"/>
  <element ref="xn:MeasurementControl"/>
  <element ref="xn:NtfSubscriptionControl"/>
</choice>
<choice minOccurs="0" maxOccurs="1">
  <element ref="sp:ESPolicies"/>
</choice>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="ManagedElement">
  <complexType>
    <complexContent>
      <extension base="xn:NrmClass">
        <sequence>
          <element name="attributes" minOccurs="0">
            <complexType>
              <all>
                <element name="dnPrefix"/>
                <element name="managedElementTypeList" type="xn:managedTypeListType" minOccurs="0"/>
                <element name="userLabel"/>
                <element name="vendorName"/>
                <element name="userDefinedState"/>
                <element name="locationName"/>
                <element name="swVersion"/>
                <element name="managedBy" type="xn:dnList" minOccurs="0"/>
                <element name="priority" type="integer" minOccurs="0"/>
                <element name="measurementsList" type="xn:MeasurementsList" minOccurs="0"/>
              </all>
            </complexType>
          </element>
        </sequence>
      </extension>
    </complexContent>
  </complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
  <element ref="xn:IRPAgent"/>
  <element ref="xn:ManagedElementOptionallyContainedNrmClass"/>
  <element ref="xn:VsDataContainer"/>
</choice>

```

```

<element ref="xn:ThresholdMonitoringCapability"/>
<element ref="xn:ThresholdMonitor"/>
<element ref="xn:MeasurementControl"/>
<element ref="xn:NtfSubscriptionControl"/>
</choice>

</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="ManagedFunction">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>
<all>
<element name="userLabel" type="string"/>
<element name="vnfParametersList" type="xn:vnfParametersListType"/>
<element name="peeParametersList" type="xn:peeParametersListType"/>
<element name="priority" type="integer" minOccurs="0"/>
<element name="measurementsList" type="xn:MeasurementsList" minOccurs="0"/>
</all>
</complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
<element ref="xn:VsDataContainer"/>
<element ref="xn:EP_RP"/>
<element ref="xn:ThresholdMonitoringCapability"/>
<element ref="xn:ThresholdMonitor"/>
<element ref="xn:MeasurementControl"/>
</choice>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="ManagedNFService">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>
<all>
<element name="userLabel" type="string"/>
<element name="nFServiceType" type="xn:nFServiceType"/>
<element name="AdministrativeState" type="xn:pMAdministrativeStateType"/>
<element name="OperationalState" type="xn:pMOperationalStateType"/>
<element name="usageState" type="xn:usageStateType"/>
<element name="registrationState" type="xn:registrationStateType"/>
<element name="sAP" type="xn:SAP" minOccurs="0"/>
<element name="operations" type="xn:operationsList" minOccurs="0"/>
</all>
</complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
<element ref="xn:VsDataContainer"/>
<element ref="xn:ThresholdMonitoringCapability"/>
<element ref="xn:ThresholdMonitor"/>
</choice>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="MeContext">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>

```

```

<all>
    <element name="dnPrefix" minOccurs="0" />
</all>
</complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
    <element ref="xn:ManagedElement" />
</choice>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="ManagementNode" >
<complexType>
<complexContent>
<extension base="xn:NrmClass">
    <sequence>
        <element name="attributes" minOccurs="0" >
            <complexType>
                <all>
                    <element name="userLabel"/>
                    <element name="vendorName"/>
                    <element name="locationName" />
                    <element name="managedElements" type="xn:dnList" minOccurs="0" />
                    <element name="swVersion"/>
                    <element name="userDefinedState" />
                </all>
            </complexType>
        </element>
        <choice minOccurs="0" maxOccurs="unbounded">
            <element ref="xn:IRPAgent" />
            <element ref="xn:VsDataContainer" />
        </choice>
    </sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="MeasurementControl" >
<complexType>
<complexContent>
<extension base="xn:NrmClass">
    <sequence>
        <element name="attributes" minOccurs="0" >
            <complexType>
                <all>
                    <element name="pMAdministrativeState" type="xn:pMAdministrativeStateType" />
                    <element name="pMOperationalState" type="xn:pMOperationalStateType" />
                    <element name="defaultFileBasedGP" type="integer" />
                    <element name="defaultFileReportingPeriod" type="integer" />
                    <element name="defaultFileLocation" type="string" />
                    <element name="defaultStreamBasedGP" type="integer" />
                    <element name="defaultStreamTarget" type="string" />
                </all>
            </complexType>
        </element>
        <choice minOccurs="0" maxOccurs="unbounded">
            <element ref="xn:MeasurementReader" />
        </choice>
    </sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="MeasurementReader" >
<complexType>
<complexContent>
<extension base="xn:NrmClass">
    <sequence>
        <element name="attributes" minOccurs="0" >
            <complexType>
                <all>
                    <element name="measurementTypes" />
                    <element name="fileBasedGP" type="integer" minOccurs="0" />
                </all>
            </complexType>
        </element>
    </sequence>
</extension>
</complexContent>
</complexType>
</element>

```

```

<element name="fileReportingPeriod" type="integer" minOccurs="0" />
<element name="fileLocation" type="string" minOccurs="0" />
<element name="streamBasedGP" type="integer" minOccurs="0" />
<element name="streamTarget" type="string" minOccurs="0" />
<element name="managedObjectDNsBasic" type="xn:dnList" minOccurs="0" />
<element name="managedObjectDNs" type="xn:dnList" minOccurs="0" />
</all>
</complexType>
</element>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="IRPAgent">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>
<all>
<element ref="xn:systemDN" minOccurs="0" />
</all>
</complexType>
</element>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="EP_RP">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>
<all>
<element name="farEndEntity" type="xn:dn" minOccurs="0" />
<element name="userLabel" type="string" minOccurs="0" />
<element name="measurementsList" type="xn:MeasurementsList" minOccurs="0" />
</all>
</complexType>
</element>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="VsDataContainer">
<complexType>
<complexContent>
<extension base="xn:NrmClass">
<sequence>
<element name="attributes" minOccurs="0">
<complexType>
<all>
<element name="vsDataType" />
<element name="vsDataFormatVersion" />
<element ref="xn:vsData" />
</all>
</complexType>
</element>
<choice minOccurs="0" maxOccurs="unbounded">
<element ref="xn:VsDataContainer" />
</choice>
</sequence>
</extension>
</complexContent>
</complexType>
</element>

<element name="ThresholdMonitoringCapability">
<complexType>

```

```

<complexContent>
  <extension base="xn:NrmClass">
    <sequence>
      <element name="attributes" minOccurs="0">
        <complexType>
          <all>
            <element name="supportedMonitoringGPs" type="xn:GPListType"/>
          </all>
        </complexType>
      </element>
      <choice minOccurs="0" maxOccurs="unbounded">
        <element ref="xn:ThresholdMonitoringCapabilityOptionallyContainedNrmClass"/>
      </choice>
    </sequence>
  </extension>
</complexContent>
</complexType>
</element>

<element name="HeartbeatControl">
<complexType>
<complexContent>
  <extension base="xn:NrmClass">
    <sequence>
      <element name="attributes" minOccurs="0">
        <complexType>
          <all>
            <element name="heartbeatNtfPeriod" type="integer"/>
            <element name="triggerHeartbeatNtf" type="boolean"/>
          </all>
        </complexType>
      </element>
    </sequence>
  </extension>
</complexContent>
</complexType>
</element>

<element name="ThresholdMonitor">
<complexType>
<complexContent>
  <extension base="xn:NrmClass">
    <sequence>
      <element name="attributes" minOccurs="0">
        <complexType>
          <all>
            <element name="thresholdInfoList" type="xn:thresholdInfoListType"/>
            <element name="monitoringGP" type="integer"/>
            <element name="monitoringNotifTarget" type="string"/>
            <element name="monitoredIOCName" type="string"/>
            <element name="monitoredObjectDNs" type="xn:dnList"/>
          </all>
        </complexType>
      </element>
      <choice minOccurs="0" maxOccurs="unbounded">
        <element ref="xn:ThresholdMonitorOptionallyContainedNrmClass"/>
      </choice>
    </sequence>
  </extension>
</complexContent>
</complexType>
</element>

<element name="NtfSubscriptionControl">
<complexType>
<complexContent>
  <extension base="xn:NrmClass">
    <sequence>
      <element name="attributes" minOccurs="0">
        <complexType>
          <all>
            <element name="notificationRecipientAddress" type="string"/>
            <element name="notificationTypes" type="string" minOccurs="0" />
            <element name="scope" type="xn:Scope"/>
            <element name="notificationFilter" type="string" minOccurs="0" />
          </all>
        </complexType>
      </element>
    </sequence>
  </extension>
</complexContent>
</complexType>
</element>

```

```

        <choice minOccurs="0" maxOccurs="1">
            <element ref="xn:HeartbeatControl"/>
        </choice>
    </sequence>
</complexType>
</element>

<!--
    IRPAGent IOC attributes
-->

<element name="systemDN" type="xn:dn"/>

<!--
    VsDataContainer NRM class vsData attribute associated empty XML element
-->

<complexType name="vsData"/>
<element name="vsData" type="xn:vsData"/>

<!--
    Abstract head XML element for all XML elements associated to further
    NRM classes optionally contained under SubNetwork NRM class
-->

<element
    name="SubNetworkOptionallyContainedNrmClass"
    type="xn:NrmClass"
    abstract="true"
/>

<!--
    Abstract head XML element for all XML elements associated to further
    NRM classes optionally contained under ManagedElement NRM class
-->

<element
    name="ManagedElementOptionallyContainedNrmClass"
    type="xn:NrmClass"
    abstract="true"
/>

<!--
    Abstract head XML element for all XML elements associated to further
    NRM classes optionally contained under ThresholdMonitoringCapability NRM class
-->

<element
    name="ThresholdMonitoringCapabilityOptionallyContainedNrmClass"
    type="xn:NrmClass"
    abstract="true"
/>

<!--
    Abstract head XML element for all XML elements associated to further
    NRM classes optionally contained under ThresholdMonitor NRM class
-->

<element
    name="ThresholdMonitorOptionallyContainedNrmClass"
    type="xn:NrmClass"
    abstract="true"
/>

</schema>
```

---

## Annex C (normative): OpenAPI definitions

### C.1 General

This annex contains the OpenAPI definition of the Generic NRM in YAML format.

The Information Service (IS) of the Generic NRM is defined in 3GPP TS 28.622 [4].

Mapping rules to produce the OpenAPI definition based on the IS are defined in 3GPP TS 32.160 [14].

---

### C.2 Void

### C.3 Void

### C.4 Solution Set (SS) definitions

#### C.4.1 Void

#### C.4.2 Void

#### C.4.2a OpenAPI document "TS28623\_ComDefs.yaml"

```

openapi: 3.0.1
info:
  title: Common Type Definitions
  version: 17.2.0
  description: >-
    OAS 3.0.1 specification of common type definitions in the Generic NRM
    © 2022, 3GPP Organizational Partners (ARIB, ATIS, CCSA, ETSI, TSDSI, TTA, TTC).
    All rights reserved.
  externalDocs:
    description: 3GPP TS 28.623; Generic NRM; Common type definitions
    url: http://www.3gpp.org/ftp/Specs/archive/28_series/28.623/
paths: {}
components:
  schemas:
    Float:
      type: number
      format: float
    DateTime:
      type: string
      format: date-time
    Latitude:
      type: number
      format: float
      minimum: -90
      maximum: 90
    Longitude:
      type: number
      format: float
      minimum: -180
      maximum: 180

    Dn:
      type: string
    DnList:
  
```

```

type: array
items:
  $ref: '#/components/schemas/Dn'

Mcc:
  type: string
  pattern: '^[0-9]{3}$'
Mnc:
  type: string
  pattern: '^[0-9]{2,3}$'
Nid:
  type: string
  pattern: '^[A-Fa-f0-9]{11}$'
PlmnId:
  type: object
  properties:
    mcc:
      $ref: '#/components/schemas/Mcc'
    mnc:
      $ref: '#/components/schemas/Mnc'
Tac:
  type: string
  pattern: '^(A-Fa-f0-9){4}$|([A-Fa-f0-9]{6})'
UltraCellId:
  type: integer
EutraCellId:
  type: string
  pattern: '^[A-Fa-f0-9]{7}$'
NrCellId:
  type: string
  pattern: '^[A-Fa-f0-9]{9}$'
TimeWindow:
  type: object
  properties:
    startTime:
      $ref: '#/components/schemas/DateTime'
    endTime:
      $ref: '#/components/schemas/DateTime'
GeoCoordinate:
  type: object
  properties:
    latitude:
      $ref: '#/components/schemas/Latitude'
    longitude:
      $ref: '#/components/schemas/Longitude'
ConvexGeoPolygon:
  type: array
  items:
    $ref: '#/components/schemas/GeoCoordinate'
GeoAreaToCellMapping:
  type: object
  properties:
    convexGeoPolygon:
      $ref: '#/components/schemas/ConvexGeoPolygon'
    associationThreshold:
      type: integer
AreaOfInterest:
  oneOf:
    - $ref: '#/components/schemas/GeoAreaToCellMapping'
    - type: array
      items:
        $ref: 'genericNrm.yaml#/components/schemas/Tai'
    - type: array
      items:
        $ref: '#/components/schemas/NrCellId'
    - type: array
      items:
        $ref: '#/components/schemas/EutraCellId'
    - type: array
      items:
        $ref: '#/components/schemas/UtraCellId'
Fqdn:
  type: string
Ipv4Addr:
  type: string
  pattern: '^(([0-9]|1[0-9][0-9]|2[0-9][0-9]|2[0-4][0-9]|25[0-5])\.)\{3\}([0-9]|1[0-9][0-9]|2[0-4][0-9]|25[0-5])$'
  example: '198.51.100.1'

```

```

Ipv6Addr:
  type: string
  allOf:
    - pattern: '^(:|(0?|([1-9a-f][0-9a-f]{0,3})))):(0?|([1-9a-f][0-9a-f]{0,3})):{0,6}(:|(0?|([1-9a-f][0-9a-f]{0,3})))$'
      - pattern: '^(([^\:]+){7}([^\:]+))|(([^\:]+)*[^\:]+)?::(([^\:]+)*[^\:]+)?))$'
        example: '2001:db8:85a3::8a2e:370:7334'
Ipv6Prefix:
  type: string
  allOf:
    - pattern: '^(:|(0?|([1-9a-f][0-9a-f]{0,3})))):(0?|([1-9a-f][0-9a-f]{0,3})):{0,6}(:|(0?|([1-9a-f][0-9a-f]{0,3})))|(\|[0-9]|([0-9]{2})|(1[0-1][0-9])|(12[0-8])))$'
      - pattern: '^(([^\:]+){7}([^\:]+))|(([^\:]+)*[^\:]+)?::(([^\:]+)*[^\:]+)?))(\|.+)$'
        example: '2001:db8:abcd:12::/64'
IpAddress:
  oneOf:
    - $ref: '#/components/schemas/Ipv4Addr'
    - $ref: '#/components/schemas/Ipv6Addr'
HostAddr:
  # This definition will be deprecated, when all occurrences of HostAddr
  # are replaced by Host.
  oneOf:
    - $ref: '#/components/schemas/Ipv4Addr'
    - $ref: '#/components/schemas/Ipv6Addr'
    - $ref: '#/components/schemas/Fqdn'
Host:
  oneOf:
    - $ref: '#/components/schemas/IpAddress'
    - $ref: '#/components/schemas/Fqdn'
Uri:
  type: string

AdministrativeState:
  type: string
  enum:
    - LOCKED
    - UNLOCKED
OperationalState:
  type: string
  enum:
    - ENABLED
    - DISABLED
UsageState:
  type: string
  enum:
    - IDEL
    - ACTIVE
    - BUSY

AttributeNameValuePairSet:
  description: >-
    The key of this map is the attribute name, and the value the attribute value.
  type: object
  minProperties: 1
  additionalProperties:
    nullable: true
AttributeValueChangeSet:
  description: >-
    The first array item contains the attribute name value pairs with the new values,
    and the second array item the attribute name value pairs with the optional old values.
  type: array
  items:
    $ref: '#/components/schemas/AttributeNameValuePairSet'
  minItems: 1
  maxItems: 2

Filter:
  description: >-
    The filter format shall be compliant to XPath 1.0.
  type: string
SystemDN:
  type: string

NotificationId:
  type: integer
NotificationType:
  oneOf:
    - $ref: 'TS28532_FaultMnS.yaml#/components/schemas/AlarmNotificationTypes'

```

```

- $ref: 'TS28532_ProvMnS.yaml#/components/schemas/CmNotificationTypes'
- $ref: 'TS28532_PerfMnS.yaml#/components/schemas/PerfNotificationTypes'
- $ref: 'TS28532_HeartbeatNtf.yaml#/components/schemas/HeartbeatNotificationTypes'
- $ref: 'TS28532_FileDataReportingMnS.yaml#/components/schemas/FileNotificationTypes'

NotificationHeader:
  type: object
  properties:
    href:
      $ref: '#/components/schemas/Uri'
    notificationId:
      $ref: '#/components/schemas/NotificationId'
    notificationType:
      $ref: '#/components/schemas/NotificationType'
    eventTime:
      $ref: '#/components/schemas/DateTime'
    systemDN:
      $ref: '#/components/schemas/SystemDN'
  required:
    - href
    - notificationId
    - notificationType
    - eventTime
    - systemDN

ErrorResponse:
  description: >-
    Default schema for the response message body in case the request
    is not successful.
  type: object
  properties:
    error:
      type: object
      properties:
        errorInfo:
          type: string

```

### C.4.3 OpenAPI document "TS28623\_GenericNrm.yaml"

```

openapi: 3.0.1
info:
  title: Generic NRM
  version: 17.2.0
  description: >-
    OAS 3.0.1 definition of the Generic NRM
    © 2022, 3GPP Organizational Partners (ARIB, ATIS, CCSA, ETSI, TSDSI, TTA, TTC).
    All rights reserved.
externalDocs:
  description: 3GPP TS 28.623; Generic NRM
  url: http://www.3gpp.org/ftp/Specs/archive/28_series/28.623/
paths: {}
components:
  schemas:

----- Definition of types-----

RegistrationState:
  type: string
  enum:
    - REGISTERED
    - DREGISTERED
VnfParameter:
  type: object
  properties:
    vnfInstanceId:
      type: string
    vnfdId:
      type: string
    flavourId:
      type: string
    autoScalable:
      type: boolean
PeeParameter:
  type: object
  properties:
    siteIdentification:
      type: string

```

```

siteDescription:
  type: string
siteLatitude:
  $ref: 'TS28623_ComDefs.yaml#/components/schemas/Latitude'
siteLongitude:
  $ref: 'TS28623_ComDefs.yaml#/components/schemas/Longitude'
siteAltitude:
  type: number
  format: float
equipmentType:
  type: string
environmentType:
  type: string
powerInterface:
  type: string
ThresholdInfo:
  type: object
  properties:
    thresholdDirection:
      type: string
      enum:
        - UP
        - DOWN
        - UP_AND_DOWN
thresholdValue:
  oneOf:
    - type: integer
    - $ref: 'TS28623_ComDefs.yaml#/components/schemas/Float'
hysteresis:
  oneOf:
    - type: integer
      minimum: 0
    - type: number
      format: float
      minimum: 0
Operation:
  type: object
  properties:
    name:
      type: string
    allowedNFTypes:
      $ref: '#/components/schemas/NFType'
    operationSemantics:
      $ref: '#/components/schemas/OperationSemantics'
NFType:
  type: string
  description: ' NF name defined in TS 23.501'
  enum:
    - NRF
    - UDM
    - AMF
    - SMF
    - AUSF
    - NEF
    - PCF
    - SMSF
    - NSSF
    - UDR
    - LMF
    - GMLC
    - 5G_EIR
    - SEPP
    - UPF
    - N3IWF
    - AF
    - UDSF
    - DN
OperationSemantics:
  type: string
  enum:
    - REQUEST_RESPONSE
    - SUBSCRIBE_NOTIFY
SAP:
  type: object
  properties:
    host:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/HostAddr'
    port:

```

```

    type: integer
NfServiceType:
    type: string
    enum:
        - Namf_Communication
        - Namf_EventExposure
        - Namf_MT
        - Namf_Location
        - Nsmf_PDUSession
        - Nsmf_EventExposure
        - Others
TransportProtocol:
    anyOf:
        - type: string
          enum:
            - TCP
        - type: string
SupportedPerfMetricGroup:
    type: object
    properties:
        performanceMetrics:
            type: array
            items:
                type: string
granularityPeriods:
    type: array
    items:
        type: integer
        minimum: 1
reportingMethods:
    type: array
    items:
        type: string
        enum:
            - FILE_BASED_LOC_SET_BY_PRODUCER
            - FILE_BASED_LOC_SET_BY_CONSUMER
            - STREAM_BASED
monitorGranularityPeriods:
    type: array
    items:
        type: integer
        minimum: 1
ReportingCtrl:
    oneOf:
        - type: object
          properties:
              fileReportingPeriod:
                  type: integer
        - type: object
          properties:
              fileReportingPeriod:
                  type: integer
              fileLocation:
                  $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
        - type: object
          properties:
              streamTarget:
                  $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
Scope:
    type: object
    properties:
        scopeType:
            type: string
            enum:
                - BASE_ONLY
                - BASE_ALL
                - BASE_NTH_LEVEL
                - BASE_SUBTREE
        scopeLevel:
            type: integer
ProcessMonitor:
    description: >-
        This data type is the "ProcessMonitor" data type without specialisations.
    type: object
    properties:
        jobId:
            type: string
        status:

```

```

type: string
enum:
  - NOT_STARTED
  - RUNNING
  - FINSHED
  - FAILED
  - PARTIALLY_FAILED
  - CANCELLING
  - CANCELLED
progressPercentage:
  type: integer
  minimum: 0
  maximum: 100
progressStateInfo:
  type: string
resultStateInfo:
  type: string
startTime:
  $ref: 'TS28623_CoMDefs.yaml#/components/schemas/DateTime'
endTime:
  $ref: 'TS28623_CoMDefs.yaml#/components/schemas/DateTime'
timer:
  type: integer
FileDownloadJobProcessMonitor:
description: >-
  This data type is the "ProcessMonitor" data type with specialisations
  for usage in the "FileDownloadJob".
type: object
properties:
  jobId:
    type: string
  status:
    type: string
    enum:
      - NOT_STARTED
      - RUNNING
      - FINSHED
      - FAILED
      - CANCELLING
      - CANCELLED
  progressPercentage:
    type: integer
    minimum: 0
    maximum: 100
  progressStateInfo:
    type: string
  resultStateInfo:
    oneOf:
      - type: string
        enum:
          - NULL
          - UNKNOWN
          - NO_STORAGE
          - LOW_MEMORY
          - NO_CONNECTION_TO_REMOTE_SERVER
          - FILE_NOT_AVAILABLE
          - DNS_CANNOT_BE_RESOLVED
          - TIMER_EXPIRED
          - OTHER
      - type: string
  startTime:
    $ref: 'TS28623_CoMDefs.yaml#/components/schemas/DateTime'
  endTime:
    $ref: 'TS28623_CoMDefs.yaml#/components/schemas/DateTime'
  timer:
    type: integer
AreaScope:
oneOf:
  - type: array
    items:
      $ref: '#/components/schemas/EutraCellId'
  - type: array
    items:
      $ref: '#/components/schemas/NrCellId'
  - type: array
    items:
      $ref: '#/components/schemas/Tac'
  - type: array

```

```

  items:
    $ref: '#/components/schemas/Tai'
  Tai:
    type: object
    properties:
      mcc:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mcc'
      mnc:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mnc'
      tac:
        $ref: '#/components/schemas/Tac'
  AreaConfig:
    type: object
    properties:
      freqInfo:
        $ref: '#/components/schemas/FreqInfo'
      pciList:
        type: array
        items:
          type: integer
  FreqInfo:
    description: specifies the carrier frequency and bands used in a cell.
    type: object
    properties:
      arfcn:
        type: integer
      freqBands:
        type: array
        items:
          type: integer
  MbsfnArea:
    type: object
    properties:
      mbsfnAreaId:
        type: integer
        minimum: 1
      earfcn:
        type: integer
        minimum: 1
  Tac:
    type: string
    pattern: '^(A-Fa-f0-9){4}$|^(A-Fa-f0-9){6}$'
  EutraCellId:
    type: string
    pattern: '^(A-Fa-f0-9){7}$'
  NrCellId:
    type: string
    pattern: '^(A-Fa-f0-9){9}$'
  IpAddr:
    oneOf:
      - $ref: 'TS28623_ComDefs.yaml#/components/schemas/Ipv4Addr'
      - $ref: 'TS28623_ComDefs.yaml#/components/schemas/Ipv6Addr'
  ManagementData:
    oneOf:
      - type: array
        items:
          type: string
          enum:
            - COVERAGE
            - CAPACITY
            - ENERGY_EFFICIENCY
            - MOBILITY
            - ACCESSIBILITY
      - type: array
        items:
          type: string
  NodeFilter:
    type: object
    properties:
      areaOfInterest:
        $ref: 'comDefs.yaml#/components/schemas/AreaOfInterest'
      networkDomain:
        type: string
        enum:
          - CN
          - RAN
  cpUpType:
    type: string

```

```

enum:
  - CP
  - UP
sst:
  type: integer

----- Definition of types used in Trace control NRM fragment-----

jobType-Type:
  type: string
  description: Specifies whether the TraceJob represents only MDT, Logged MBSFN MDT, Trace or a combined Trace and MDT job. Applicable for Trace, MDT, RCEF and RLF reporting. See 3GPP TS 32.422 clause 5.9a for additional details.
  enum:
    - IMMEDIATE_MDT_ONLY
    - LOGGED_MDT_ONLY
    - TRACE_ONLY
    - IMMEDIATE_MDT_AND_TRACE
    - RLF_REPORT_ONLY
    - RCEF_REPORT_ONLY
    - LOGGED_MBSFN_MDT

listOfInterfaces-Type:
  description: The interfaces to be recorded in the Network Element. See 3GPP TS 32.422 clause 5.5 for additional details.
  type: object
  properties:
    MSCServerInterfaces:
      type: array
      items:
        type: string
        enum:
          - A
          - Iu-CS
          - Mc
          - MAP-G
          - MAP-B
          - MAP-E
          - MAP-F
          - MAP-D
          - MAP-C
          - CAP
    MGWInterfaces:
      type: array
      items:
        type: string
        enum:
          - Mc
          - Nb-UP
          - Iu-UP
    RNCInterfaces:
      type: array
      items:
        type: string
        enum:
          - Iu-CS
          - Iu-PS
          - Iur
          - Iub
          - Uu
    SGSNInterfaces:
      type: array
      items:
        type: string
        enum:
          - Gb
          - Iu-PS
          - Gn
          - MAP-Gr
          - MAP-Gd
          - MAP-Gf
          - Ge
          - Gs
          - S6d
          - S4
          - S3
          - S13
    GGSNInterfaces:

```

```

type: array
items:
  type: string
  enum:
    - Gn
    - Gi
    - Gmb
S-CSCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Mw
      - Mg
      - Mr
      - Mi
P-CSCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Gm
      - Mw
I-CSCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Cx
      - Dx
      - Mg
      - Mw
MRFCInterfaces:
  type: array
  items:
    type: string
    enum:
      - Mp
      - Mr
MGCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Mg
      - Mj
      - Mn
IBCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Ix
      - Mx
E-CSCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Mw
      - Ml
      - Mm
      - Mi/Mg
BGCFInterfaces:
  type: array
  items:
    type: string
    enum:
      - Mi
      - Mj
      - Mk
ASInterfaces:
  type: array
  items:
    type: string
    enum:
      - Dh
      - Sh

```

```

        - ISC
        - Ut
HSSInterfaces:
  type: array
  items:
    type: string
    enum:
      - MAP-C
      - MAP-D
      - Gc
      - Gr
      - Cx
      - S6d
      - S6a
      - Sh
      - N70
      - N71
      - NU1
EIRInterfaces:
  type: array
  items:
    type: string
    enum:
      - MAP-F
      - S13
      - MAP-Gf
BM-SCIInterfaces:
  type: array
  items:
    type: string
    enum:
      - Gmb
MMEInterfaces:
  type: array
  items:
    type: string
    enum:
      - S1-MME
      - S3
      - S6a
      - S10
      - S11
      - S13
SGWInterfaces:
  type: array
  items:
    type: string
    enum:
      - S4
      - S5
      - S8
      - S11
      - Gxc
PDN_GWInterfaces:
  type: array
  items:
    type: string
    enum:
      - S2a
      - S2b
      - S2c
      - S5
      - S6b
      - Gx
      - S8
      - SGi
eNBInterfaces:
  type: array
  items:
    type: string
    enum:
      - S1-MME
      - X2
en-gNBInterfaces:
  type: array
  items:
    type: string
    enum:

```

```

        - S1-MME
        - X2
        - Uu
        - F1-C
        - E1
    AMFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N1
                - N2
                - N8
                - N11
                - N12
                - N14
                - N15
                - N20
                - N22
                - N26
    AUSFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N12
                - N13
    NEFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N29
                - N30
                - N33
    NRFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N27
    NSSFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N22
                - N31
    PCFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N5
                - N7
                - N15
    SMFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N4
                - N7
                - N10
                - N11
                - S5-C
    SMSFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N20
                - N21
    UDMInterfaces:
        type: array
        items:
            type: string
            enum:

```

```

        - N8
        - N10
        - N13
        - N21
        - NU1
    UPFInterfaces:
        type: array
        items:
            type: string
            enum:
                - N4
    ng-eNBInterfaces:
        type: array
        items:
            type: string
            enum:
                - NG-C
                - Xn-C
                - Uu
    gNB-CU-CPInterfaces:
        type: array
        items:
            type: string
            enum:
                - NG-C
                - Xn-C
                - Uu
                - F1-C
                - E1
                - X2-C
    gNB-CU-UPInterfaces:
        type: array
        items:
            type: string
            enum:
                - E1
    gNB-DUInterfaces:
        type: array
        items:
            type: string
            enum:
                - F1-C

listOfNeTypes-Type:
    description: The Network Element types where Trace Session activation is needed. See 3GPP TS 32.422 clause 5.4 for additional details.
    type: array
    items:
        type: string
        enum:
            - MSC_SERVER
            - SGSN
            - MGW
            - GGSN
            - RNC
            - BM_SC
            - MME
            - SGW
            - PGW
            - ENB
            - EN_GNB
            - GNB_CU_CP
            - GNB_CU_UP
            - GNB_DU
            - AMF
            - PCF
            - SMF
            - UPF
            - AUSF
            - SMSF
            - HSS
            - UDM

plmnTarget-Type:
    type: object
    description: The PLMN for which sessions shall be selected in the Trace Session in case of management based activation when several PLMNs are supported in the RAN (this means that shared cells and not shared cells are allowed for the specified PLMN. Note that the PLMN Target might

```

differ from the PLMN specified in the Trace Reference, as that specifies the PLMN that is containing the management system requesting the Trace Session from the NE. See 3GPP TS 32.422 clause 5.9b for additional details.

```

properties:
  mcc:
    $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mcc'
  mnc:
    $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mnc'
required:
  - mcc
  - mnc

traceDepth-Type:
  description: Specifies how detailed information should be recorded in the Network Element. The Trace Depth is a parameter for Trace Session level, i.e., the Trace Depth is the same for all of the NES to be traced in the same Trace Session. See 3GPP TS 32.422 clause 5.3 for additional details.
  type: string
  enum:
    - MINIMUM
    - MEDIUM
    - MAXIMUM
    - VENDORMINIMUM
    - VENDORMEDIUM
    - VENDORMAXIMUM

traceReference-Type:
  type: object
  description: The Trace Reference parameter shall be globally unique, therefore the Trace Reference shall compose as follows - MCC+MNC+Trace ID, where the MCC and MNC are coming with the Trace activation request from the management system to identify one PLMN containing the management system, and Trace ID is a 3 byte Octet String. See 3GPP TS 32.422 clause 5.6 for additional details.
  properties:
    mcc:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mcc'
    mnc:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mnc'
    traceId:
      type: string
  required:
    - mcc
    - mnc
    - traceId

traceReportingFormat-Type:
  type: string
  description: Specifies whether file-based or streaming reporting shall be used for this Trace Session. See 3GPP TS 32.422 clause 5.11 for additional details.
  enum:
    - FILE-BASED
    - STREAMING

traceTarget-Type:
  type: object
  description: Trace target conveying both the type and value of the target ID. For additional details see 3GPP TS 32.422
  properties:
    TargetIdType:
      type: string
      enum:
        - IMSI
        - IMEI
        - IMEISV
        - PUBLIC_ID
        - UTRAN_CELL
        - E-UTRAN_CELL
        - NG-RAN_CELL
        - eNB
        - RNC
        - gNB
        - SUPI
    TargetIdValue:
      type: string
  required:
    - TargetIdType
    - TargetIdValue

triggeringEvents-Type:
  type: object

```

**description:** Specifies when to start a Trace Recording Session and which message shall be recorded first, when to stop a Trace Recording Session and which message shall be recorded last respectively. See 3GPP TS 32.422 clause 5.1 for additional details.

```

properties:
  MSC_SERVER:
    type: array
    items:
      type: string
      enum:
        - MO_MT_CALLS
        - MO_MT_SMS
        - LU_IMSIattach_IMSIdetach
        - HANOVER
        - SS
  SGSN:
    type: array
    items:
      type: string
      enum:
        - PDPcontext
        - MO_MT_SMS
        - RAU_GPRSAttach_GPRSdetach
        - MBMScontext
  MGW:
    type: array
    items:
      type: string
      enum:
        - CONTEXT
  GGSN:
    type: array
    items:
      type: string
      enum:
        - PDPcontext
        - MBMScontext
  IMS:
    type: array
    items:
      type: string
      enum:
        - SIPsession_StandaloneTransaction
  BM_SC:
    type: array
    items:
      type: string
      enum:
        - MBMSactivation
  MME:
    type: array
    items:
      type: string
      enum:
        - UEinitiatedPDNconnectivityRequest
        - ServiceRequest
        - InitialAttach_TAU_Detach
        - UEinitiatedPDNdisconnection
        - BearerActivationModificationDeletion
        - Handover
  SGW:
    type: array
    items:
      type: string
      enum:
        - PDNconnectionCreation
        - PDNconnectionTermination
        - BearerActivationModificationDeletion
  PGW:
    type: array
    items:
      type: string
      enum:
        - PDNconnectionCreation
        - PDNconnectionTermination
        - BearerActivationModificationDeletion
  AMF:
    type: array
    items:

```

```

type: string
enum:
  - Registration
  - ServiceRequest
  - Handover
  - UEderegistration
  - NetworkDeregistration
  - UEMobilityFromEPC
  - UEMobilityToEPC

SMF:
  type: array
  items:
    type: string
    enum:
      - PDUsessionEstablishment
      - PDUsessionModification
      - PDUsessionRelease
      - PDUsessionUPactivationDeactivation
      - MobilityBtw3gppAndN3gppTo5GC
      - MobilityFromEpc

PCF:
  type: array
  items:
    type: string
    enum:
      - AMpolicy
      - SMpolicy
      - Authorization
      - BDTpolicy

UPF:
  type: array
  items:
    type: string
    enum:
      - N4Session

AUSF:
  type: array
  items:
    type: string
    enum:
      - UEauthentication

NEF:
  type: array
  items:
    type: string
    enum:
      - EventExposure
      - PFDmanagement
      - ParameterProvision
      - Trigger

NRF:
  type: array
  items:
    type: string
    enum:
      - NFmanagement
      - NFdiscovery

NSSF:
  type: array
  items:
    type: string
    enum:
      - NSSelection
      - NSSAI

SMSF:
  type: array
  items:
    type: string
    enum:
      - SMservice

UDM:
  type: array
  items:
    type: string
    enum:
      - UEcontext
      - SubscriberData
      - UEauthentication

```

```

        - EventExposure

anonymizationOfMdtData-Type:
  description: Specifies level of MDT anonymization. For additional details see 3GPP TS 32.422
  clause 5.10.12.
  type: string
  enum:
    - NO_IDENTITY
    - TAC_OF_IMEI

beamLevelMeasurement-Type:
  description: Determines whether beam level measurements shall be included in case of immediate
  MDT M1 measurement in NR. For additional details see 3GPP TS 32.422 clause 5.10.40.
  type: boolean

collectionPeriodRrmLte-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.20.
  type: string
  enum:
    - 100ms
    - 1000ms
    - 1024ms
    - 1280ms
    - 2048ms
    - 2560ms
    - 5120ms
    - 10000ms
    - 10240ms
    - 60000ms

collectionPeriodM6Lte-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.32.
  type: string
  enum:
    - 1024ms
    - 2048ms
    - 5120ms
    - 10240ms

collectionPeriodM7Lte-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.33.
  type: integer
  minimum: 1
  maximum: 60

collectionPeriodRrmUmts-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.21.
  type: string
  enum:
    - 100ms
    - 250ms
    - 500ms
    - 1000ms
    - 2000ms
    - 3000ms
    - 4000ms
    - 6000ms

collectionPeriodRrmNr-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.30.
  type: string
  enum:
    - 1024ms
    - 2048ms
    - 5120ms
    - 10240ms
    - 60000ms

collectionPeriodM6Nr-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.34.
  type: string
  enum:
    - 120ms
    - 240ms
    - 480ms
    - 640ms
    - 1024ms
    - 2048ms

```

```

- 5120ms
- 10240ms
- 20480ms
- 40960ms
- 1min
- 6min
- 12min
- 30min

collectionPeriodM7Nr-Type:
description: See details in 3GPP TS 32.422 clause 5.10.35.
type: integer
minimum: 1
maximum: 60

eventListForEventTriggeredMeasurement-Type:
description: See details in 3GPP TS 32.422 clause 5.10.28.
type: string
enum:
- OUT_OF_COVERAGE
- A2_EVENT

eventThreshold-Type:
description: See details in 3GPP TS 32.422 clause 5.10.7, 5.10.7a, 5.10.13 and 5.10.14.
type: object
properties:
  EventThresholdRSRP:
    oneOf:
    - type: integer
      minimum: 0
      maximum: 97
    - type: integer
      minimum: 0
      maximum: 127
  EventThresholdRSRQ:
    oneOf:
    - type: integer
      minimum: 0
      maximum: 34
    - type: integer
      minimum: 0
      maximum: 127
  EventThreshold1F:
    type: object
    properties:
      CPICH_RSCP:
        type: integer
        minimum: -120
        maximum: 25
      CPICH_EcNo:
        type: integer
        minimum: -24
        maximum: 0
      PathLoss:
        type: integer
        minimum: 30
        maximum: 165
  EventThreshold1I:
    type: integer
    minimum: -120
    maximum: 25

listOfMeasurements-Type:
description: See details in 3GPP TS 32.422 clause 5.10.3 for details.
type: object
properties:
  UMTS:
    type: array
    items:
      type: string
      enum:
        - M1
        - M2
        - M3
        - M4
        - M5
        - M6_DL
        - M6_UL

```

```

        - M7_DL
        - M7_UL
LTE:
  type: array
  items:
    type: string
    enum:
      - M1
      - M2
      - M3
      - M4
      - M5
      - M1_EVENT_TRIGGERED
      - M6
      - M7
      - M8
      - M9
NR:
  type: array
  items:
    type: string
    enum:
      - M1
      - M2
      - M3
      - M4
      - M5
      - M6
      - M7
      - M1_EVENT_TRIGGERED
      - M8
      - M9

loggingDuration-Type:
description: See details in 3GPP TS 32.422 clause 5.10.9.
type: string
enum:
  - 600s
  - 1200s
  - 2400s
  - 3600s
  - 5400s
  - 7200s

loggingInterval-Type:
description: See details in 3GPP TS 32.422 clause 5.10.8.
type: object
properties:
  UMTS:
    type: array
    items:
      type: string
      enum:
        - 1.28s
        - 2.56s
        - 5.12s
        - 10.24s
        - 20.48s
        - 30.72s
        - 40.96s
        - 61.44s
  LTE:
    type: array
    items:
      type: string
      enum:
        - 1.28s
        - 2.56s
        - 5.12s
        - 10.24s
        - 20.48s
        - 30.72s
        - 40.96s
        - 61.44s
NR:
  type: array
  items:
    type: string

```

```

enum:
  - 0.32s
  - 0.64s
  - 1.28s
  - 2.56s
  - 5.12s
  - 10.24s
  - 20.48s
  - 30.72s
  - 40.96s
  - 61.44s
  - INFINITY

eventThresholdL1-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.X.
  type: object
  properties:
    RSRP:
      type: integer
      minimum: 0
      maximum: 127
    RSRQ:
      type: integer
      minimum: 0
      maximum: 127

hysteresisL1-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.Y.
  type: integer
  minimum: 0
  maximum: 30

timeToTriggerL1-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.Z.
  type: string
  enum:
    - 0ms
    - 40ms
    - 64ms
    - 80ms
    - 100ms
    - 128ms
    - 160ms
    - 256ms
    - 320ms
    - 480ms
    - 512ms
    - 640ms
    - 1024ms
    - 1280ms
    - 2560ms
    - 5120ms

measurementPeriodLte-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.23.
  type: string
  enum:
    - 1024ms
    - 2048ms
    - 5120ms
    - 10240ms
    - 1min

measurementPeriodUmts-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.22.
  type: string
  enum:
    - 1000ms
    - 2000ms
    - 3000ms
    - 4000ms
    - 6000ms
    - 8000ms
    - 12000ms
    - 16000ms
    - 20000ms
    - 24000ms
    - 28000ms

```

```

- 32000ms
- 64000ms

measurementQuantity-Type:
description: See details in 3GPP TS 32.422 clause 5.10.15.
type: string
enum:
- CPICH_EcNo
- CPICH_RSCP
- PathLoss

eventThresholdUphUmts-Type:
description: See details in 3GPP TS 32.422 clause 5.10.A.
type: integer
minimum: 0
maximum: 31

plmnList-Type:
description: See details in 3GPP TS 32.422 clause 5.10.24.
type: array
items:
type: object
properties:
mcc:
$ref: 'TS28623_ComDefs.yaml#/components/schemas/Mcc'
mnc:
$ref: 'TS28623_ComDefs.yaml#/components/schemas/Mnc'
required:
- mcc
- mnc
maxItems: 16

positioningMethod-Type:
description: See details in 3GPP TS 32.422 clause 5.10.19.
type: string
enum:
- GNSS
- E-CELL_ID

reportAmount-Type:
description: See details in 3GPP TS 32.422 clause 5.10.6.
type: string
enum:
- 1
- 2
- 4
- 8
- 16
- 32
- 64
- INFINITY

reportingTrigger-Type:
description: See details in 3GPP TS 32.422 clause 5.10.4.
type: array
items:
type: string
enum:
- PERIODICAL
- A2_FOR_LTE_NR
- 1F_FOR_UMTS
- 1I_FOR_UMTS_MCPS_TDD
- A2_TRIGGERED_PERIODIC_FOR_LTE_NR
- ALL_CONFIGURED_RRM_FOR_LTE_NR
- ALL_CONFIGURED_RRM_FOR_UMTS

reportInterval-Type:
description: See details in 3GPP TS 32.422 clause 5.10.5.
type: object
properties:
UMTS:
type: array
items:
type: string
enum:
- 250ms
- 500ms
- 1000ms

```

```

        - 2000ms
        - 3000ms
        - 4000ms
        - 6000ms
        - 8000ms
        - 12000ms
        - 16000ms
        - 20000ms
        - 24000ms
        - 28000ms
        - 32000ms
        - 64000ms

LTE:
  type: array
  items:
    type: string
    enum:
      - 120ms
      - 240ms
      - 480ms
      - 640ms
      - 1024ms
      - 2048ms
      - 5120ms
      - 10240ms
      - 60000ms
      - 360000ms
      - 720000ms
      - 1800000ms
      - 3600000ms

NR:
  type: array
  items:
    type: string
    enum:
      - 120ms
      - 240ms
      - 480ms
      - 640ms
      - 1024ms
      - 2048ms
      - 5120ms
      - 10240ms
      - 20480ms
      - 40960ms
      - 60000ms
      - 360000ms
      - 720000ms
      - 1800000ms

reportType-Type:
  description: Report type for logged NR MDT. See details in 3GPP TS 32.422 clause 5.10.27.
  type: string
  enum:
    - PERIODICAL
    - EVENT_TRIGGERED

sensorInformation-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.29.
  type: array
  items:
    type: string
    enum:
      - BAROMETRIC_PRESSURE
      - UE_SPEED
      - UE_ORIENTATION

traceCollectionEntityId-Type:
  description: See details in 3GPP TS 32.422 clause 5.10.11. Only TCE Id value may be sent over
the air to the UE being configured for Logged MDT.
  type: integer

----- end of Definition of types used in Trace control NRM fragment -----

----- Definition of abstract IOC Top -----

```

```

Top-Attr:
  # This definition will be deprecated, when all occurrences of Top-Attr
  # are replaced by Top.
  type: object
  properties:
    id:
      type: string
      nullable: true
    objectClass:
      type: string
    objectInstance:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
    VsDataContainer:
      $ref: '#/components/schemas/VsDataContainer-Multiple'
  required:
    - id

Top:
  type: object
  properties:
    id:
      type: string
      nullable: true
    objectClass:
      type: string
    objectInstance:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
    VsDataContainer:
      $ref: '#/components/schemas/VsDataContainer-Multiple'
  required:
    - id

----- Definition of IOCs with new name-containments defined in other TS -----

SubNetwork-Attr:
  type: object
  properties:
    dnPrefix:
      type: string
    userLabel:
      type: string
    userDefinedNetworkType:
      type: string
    setOfMcc:
      type: array
      items:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/Mcc'
    priorityLabel:
      type: integer
    supportedPerfMetricGroups:
      type: array
      items:
        $ref: '#/components/schemas/SupportedPerfMetricGroup'
    supportedTraceMetrics:
      type: array
      items:
        type: string

ManagedElement-Attr:
  type: object
  properties:
    dnPrefix:
      type: string
    managedElementTypeList:
      type: array
      items:
        type: string
    userLabel:
      type: string
    locationName:
      type: string
    managedBy:
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
    vendorName:
      type: string
    userDefinedState:
      type: string
    swVersion:
      type: string
    priorityLabel:

```

```

    type: integer
supportedPerfMetricGroups:
    type: array
    items:
        $ref: '#/components/schemas/SupportedPerfMetricGroup'
supportedTraceMetrics:
    type: array
    items:
        type: string

SubNetwork-nc0:
type: object
properties:
    ManagementNode:
        $ref: '#/components/schemas/ManagementNode-Multiple'
    MnsAgent:
        $ref: '#/components/schemas/MnsAgent-Multiple'
    MeContext:
        $ref: '#/components/schemas/MeContext-Multiple'
    PerfMetricJob:
        $ref: '#/components/schemas/PerfMetricJob-Multiple'
    ThresholdMonitor:
        $ref: '#/components/schemas/ThresholdMonitor-Multiple'
    TraceJob:
        $ref: '#/components/schemas/TraceJob-Multiple'
    ManagementDataCollection:
        $ref: '#/components/schemas/ManagementDataCollection-Multiple'
    NtfSubscriptionControl:
        $ref: '#/components/schemas/NtfSubscriptionControl-Multiple'
    AlarmList:
        $ref: '#/components/schemas/AlarmList-Single'
    Files:
        $ref: '#/components/schemas/Files-Multiple'
    FileDownloadJob:
        $ref: '#/components/schemas/FileDownloadJob-Multiple'
    MnsRegistry:
        $ref: '#/components/schemas/MnsRegistry-Single'

ManagedElement-nc0:
type: object
properties:
    MnsAgent:
        $ref: '#/components/schemas/MnsAgent-Multiple'
    PerfMetricJob:
        $ref: '#/components/schemas/PerfMetricJob-Multiple'
    ThresholdMonitor:
        $ref: '#/components/schemas/ThresholdMonitor-Multiple'
    TraceJob:
        $ref: '#/components/schemas/TraceJob-Multiple'
    NtfSubscriptionControl:
        $ref: '#/components/schemas/NtfSubscriptionControl-Multiple'
    AlarmList:
        $ref: '#/components/schemas/AlarmList-Single'
    FileDownloadJob:
        $ref: '#/components/schemas/FileDownloadJob-Multiple'
    Files:
        $ref: '#/components/schemas/Files-Multiple'

----- Definition of abstract IOCs -----

ManagedFunction-Attr:
type: object
properties:
    userLabel:
        type: string
    vnfParametersList:
        type: array
        items:
            $ref: '#/components/schemas/VnfParameter'
    peeParametersList:
        type: array
        items:
            $ref: '#/components/schemas/PeeParameter'
    priorityLabel:
        type: integer
    supportedPerfMetricGroups:
        type: array
        items:
            $ref: '#/components/schemas/SupportedPerfMetricGroup'

```

```

supportedTraceMetrics:
  type: array
  items:
    type: string

EP_RP-Attr:
  type: object
  properties:
    userLabel:
      type: string
    farEndEntity:
      type: string
  supportedPerfMetricGroups:
    type: array
    items:
      $ref: '#/components/schemas/SupportedPerfMetricGroup'

TraceJob-Attr:
  type: object
  description: abstract class used as a container of all TraceJob attributes
  properties:
    jobType:
      $ref: '#/components/schemas/jobType-Type'
    listOfInterfaces:
      $ref: '#/components/schemas/listOfInterfaces-Type'
    listOfNeTypes:
      $ref: '#/components/schemas/listOfNeTypes-Type'
    plmnTarget:
      $ref: '#/components/schemas/plmnTarget-Type'
    traceReportingConsumerUri:
      $ref: 'TS28623_CondDefs.yaml#/components/schemas/Uri'
    traceCollectionEntityIpAddress:
      $ref: '#/components/schemas/IpAddr'
    traceDepth:
      $ref: '#/components/schemas/traceDepth-Type'
    traceReference:
      $ref: '#/components/schemas/traceReference-Type'
    traceRecordingSessionReference:
      type: string
    jobId:
      type: string
    traceReportingFormat:
      $ref: '#/components/schemas/traceReportingFormat-Type'
    traceTarget:
      $ref: '#/components/schemas/traceTarget-Type'
    triggeringEvents:
      $ref: '#/components/schemas/triggeringEvents-Type'
    anonymizationOfMdtData:
      $ref: '#/components/schemas/anonymizationOfMdtData-Type'
    areaConfigurationForNeighCell:
      $ref: '#/components/schemas/AreaConfig'
    areaScope:
      type: array
      items:
        $ref: '#/components/schemas/AreaScope'
    beamLevelMeasurement:
      $ref: '#/components/schemas/beamLevelMeasurement-Type'
    collectionPeriodRrmLte:
      $ref: '#/components/schemas/collectionPeriodRrmLte-Type'
    collectionPeriodM6Lte:
      $ref: '#/components/schemas/collectionPeriodM6Lte-Type'
    collectionPeriodM7Lte:
      $ref: '#/components/schemas/collectionPeriodM7Lte-Type'
    collectionPeriodRrmUmts:
      $ref: '#/components/schemas/collectionPeriodRrmUmts-Type'
    collectionPeriodRrmNr:
      $ref: '#/components/schemas/collectionPeriodRrmNr-Type'
    collectionPeriodM6Nr:
      $ref: '#/components/schemas/collectionPeriodM6Nr-Type'
    collectionPeriodM7Nr:
      $ref: '#/components/schemas/collectionPeriodM7Nr-Type'
    eventListForEventTriggeredMeasurement:
      $ref: '#/components/schemas/eventListForEventTriggeredMeasurement-Type'
    eventThreshold:
      $ref: '#/components/schemas/eventThreshold-Type'
    listOfMeasurements:
      $ref: '#/components/schemas/listOfMeasurements-Type'
    loggingDuration:

```

```

    $ref: '#/components/schemas/loggingDuration-Type'
loggingInterval:
    $ref: '#/components/schemas/loggingInterval-Type'
eventThresholdL1:
    $ref: '#/components/schemas/eventThresholdL1-Type'
hysteresisL1:
    $ref: '#/components/schemas/hysteresisL1-Type'
timeToTriggerL1:
    $ref: '#/components/schemas/timeToTriggerL1-Type'
mbsfnAreaList:
    type: array
    items:
        $ref: '#/components/schemas/MbsfnArea'
measurementPeriodLte:
    $ref: '#/components/schemas/measurementPeriodLte-Type'
measurementPeriodUmts:
    $ref: '#/components/schemas/measurementPeriodUmts-Type'
measurementQuantity:
    $ref: '#/components/schemas/measurementQuantity-Type'
eventThresholdUphUmts:
    $ref: '#/components/schemas/eventThresholdUphUmts-Type'
plmnList:
    $ref: '#/components/schemas/plmnList-Type'
positioningMethod:
    $ref: '#/components/schemas/positioningMethod-Type'
reportAmount:
    $ref: '#/components/schemas/reportAmount-Type'
reportingTrigger:
    $ref: '#/components/schemas/reportingTrigger-Type'
reportInterval:
    $ref: '#/components/schemas/reportInterval-Type'
reportType:
    $ref: '#/components/schemas/reportType-Type'
sensorInformation:
    $ref: '#/components/schemas/sensorInformation-Type'
traceCollectionEntityId:
    $ref: '#/components/schemas/traceCollectionEntityId-Type'

ManagedFunction-nc0:
    type: object
    properties:
        PerfMetricJob:
            $ref: '#/components/schemas/PerfMetricJob-Multiple'
        ThresholdMonitor:
            $ref: '#/components/schemas/ThresholdMonitor-Multiple'
        ManagedNFSService:
            $ref: '#/components/schemas/ManagedNFSService-Multiple'
        TraceJob:
            $ref: '#/components/schemas/TraceJob-Multiple'

MnsRegistry-Single:
    type: object
    properties:
        MnsInfo:
            $ref: '#/components/schemas/MnsInfo-Multiple'

----- Definition of concrete IOCs -----
VsDataContainer-Single:
    type: object
    properties:
        id:
            type: string
        attributes:
            type: object
            properties:
                vsDataType:
                    type: string
                vsDataFormatVersion:
                    type: string
                vsData:
                    nullable: true
        VsDataContainer:
            $ref: '#/components/schemas/VsDataContainer-Multiple'
ManagedNFSService-Single:
    allOf:
        - $ref: '#/components/schemas/Top'

```

```

- type: object
  properties:
    attributes:
      type: object
      properties:
        userLabel:
          type: string
        nFServiceType:
          $ref: '#/components/schemas/NFServiceType'
        SAP:
          $ref: '#/components/schemas/SAP'
        operations:
          type: array
          items:
            $ref: '#/components/schemas/Operation'
        administrativeState:
          $ref: 'TS28623_ComDefs.yaml#/components/schemas/AdministrativeState'
        operationalState:
          $ref: 'TS28623_ComDefs.yaml#/components/schemas/OperationalState'
        usageState:
          $ref: 'TS28623_ComDefs.yaml#/components/schemas/UsageState'
        registrationState:
          $ref: '#/components/schemas/RegistrationState'
  ManagementNode-Single:
    allOf:
      - $ref: '#/components/schemas/Top'
      - type: object
        properties:
          attributes:
            type: object
            properties:
              userLabel:
                type: string
              managedElements:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
              vendorName:
                type: string
              userDefinedState:
                type: string
              locationName:
                type: string
              swVersion:
                type: string
            MnsAgent:
              $ref: '#/components/schemas/MnsAgent-Multiple'
  MnsAgent-Single:
    allOf:
      - $ref: '#/components/schemas/Top'
      - type: object
        properties:
          attributes:
            type: object
            properties:
              systemDN:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
  MeContext-Single:
    allOf:
      - $ref: '#/components/schemas/Top'
      - type: object
        properties:
          attributes:
            type: object
            properties:
              dnPrefix:
                type: string
  PerfMetricJob-Single:
    allOf:
      - $ref: '#/components/schemas/Top'
      - type: object
        properties:
          attributes:
            type: object
            properties:
              administrativeState:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/AdministrativeState'
              operationalState:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/OperationalState'
              jobId:

```

```

        type: string
    performanceMetrics:
        type: array
        items:
            type: string
    granularityPeriod:
        type: integer
        minimum: 1
    objectInstances:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
    rootObjectInstances:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
    reportingCtrl:
        $ref: '#/components/schemas/ReportingCtrl'
    Files:
        $ref: '#/components/schemas/Files-Multiple'
ThresholdMonitor-Single:
    allOf:
        - $ref: '#/components/schemas/Top'
        - type: object
            properties:
                attributes:
                    type: object
                    properties:
                        administrativeState:
                            $ref: 'TS28623_ComDefs.yaml#/components/schemas/AdministrativeState'
                        operationalState:
                            $ref: 'TS28623_ComDefs.yaml#/components/schemas/OperationalState'
                        performanceMetrics:
                            type: array
                            items:
                                type: string
            thresholdInfoList:
                type: array
                items:
                    $ref: '#/components/schemas/ThresholdInfo'
            monitorGranularityPeriod:
                type: integer
                minimum: 1
            objectInstances:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
            rootObjectInstances:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/DnList'
NtfSubscriptionControl-Single:
    allOf:
        - $ref: '#/components/schemas/Top'
        - type: object
            properties:
                attributes:
                    type: object
                    properties:
                        notificationRecipientAddress:
                            $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
                        notificationTypes:
                            type: array
                            items:
                                $ref: 'TS28623_ComDefs.yaml#/components/schemas/NotificationType'
            scope:
                $ref: '#/components/schemas/Scope'
            notificationFilter:
                $ref: 'TS28623_ComDefs.yaml#/components/schemas/Filter'
        HeartbeatControl:
            $ref: '#/components/schemas/HeartbeatControl-Single'
HeartbeatControl-Single:
    allOf:
        - $ref: '#/components/schemas/Top'
        - type: object
            properties:
                attributes:
                    type: object
                    properties:
                        heartbeatNtfPeriod:
                            type: integer
                            minimum: 0
                        triggerHeartbeatNtf:
                            type: boolean
TraceJob-Single:
    allOf:

```

```

- $ref: '#/components/schemas/Top'
- type: object
  properties:
    attributes:
      $ref: '#/components/schemas/TraceJob-Attr'
    Files:
      $ref: '#/components/schemas/Files-Multiple'
ManagementDataCollection-Single:
  allOf:
    - $ref: '#/components/schemas/Top'
    - type: object
      properties:
        attributes:
          type: object
        properties:
          managementData:
            $ref: '#/components/schemas/ManagementData'
          targetNodeFilter:
            $ref: '#/components/schemas/NodeFilter'
          collectionTimeWindow:
            $ref: 'comDefs.yaml#/components/schemas/TimeWindow'
          reportingCtrl:
            type: string
          dataScope:
            type: string
            enum:
              - SNSSAI
              - 5QI
AlarmList-Single:
  allOf:
    - $ref: '#/components/schemas/Top'
    - type: object
      properties:
        attributes:
          type: object
        properties:
          administrativeState:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/AdministrativeState'
          operationalState:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/OperationalState'
          numOfAlarmRecords:
            type: integer
          lastModification:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/DateTime'
          alarmRecords:
            description: >-
              This resource represents a map of alarm records.
              The alarmIds are used as keys in the map.
            type: object
            additionalProperties:
              $ref: 'TS28532_FaultMnS.yaml#/components/schemas/AlarmRecord'
FileDownloadJob-Single:
  allOf:
    - $ref: '#/components/schemas/Top'
    - type: object
      properties:
        attributes:
          type: object
        properties:
          fileLocation:
            type: string
          notificationRecipientAddress:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
          cancelJob:
            type: string
            enum:
              - TRUE
              - FALSE
          jobMonitor:
            $ref: '#/components/schemas/FileDownloadJobProcessMonitor'
Files-Single:
  allOf:
    - $ref: '#/components/schemas/Top'
    - type: object
      properties:
        attributes:
          type: object
        properties:

```

```

        numberOfFiles:
          type: integer
        jobRef:
          $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
        jobId:
          type: string
        File:
          $ref: '#/components/schemas/File-Multiple'
File-Single:
  allOf:
    - $ref: '#/components/schemas/Top'
    - type: object
      properties:
        attributes:
          type: object
        properties:
          fileLocation:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
          fileCompression:
            type: string
          fileSize:
            type: integer
          fileDataType:
            type: string
            enum:
              - PERFORMANCE
              - TRACE
              - ANALYTICS
              - PROPRIETARY
          fileFormat:
            type: string
          fileReadyTime:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/DateTime'
          fileExpirationTime:
            $ref: 'TS28623_ComDefs.yaml#/components/schemas/DateTime'
          fileContent:
            type: string
        jobRef:
          $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
        jobId:
          type: string
MnsInfo-Single:
  type: object
  properties:
    mnsLabel:
      type: string
    mnsType:
      type: string
      enum:
        - ProvMnS
        - FaultSupervisionMnS
        - StreamingDataReportingMnS
        - FileDataReportingMnS
    mnsVersion:
      type: string
    mnsAddress:
      description: Resource URI as defined in the relevant Technical Specification
      $ref: 'TS28623_ComDefs.yaml#/components/schemas/Uri'
    mnsScope:
      description: >-
        List of the managed object instances that can be accessed using the MnS.
        If a complete SubNetwork can be accessed using the MnS, this attribute may contain the
        DN of the SubNetwork instead of the DNs of the individual managed entities within the
        SubNetwork.
      type: array
      items:
        $ref: 'TS28623_ComDefs.yaml#/components/schemas/Dn'
#----- Definition of YAML arrays for name-contained IOCs -----
VsDataContainer-Multiple:
  type: array
  items:
    $ref: '#/components/schemas/VsDataContainer-Single'
ManagedNFSERVICE-Multiple:
  type: array
  items:
    $ref: '#/components/schemas/ManagedNFSERVICE-Single'
ManagementNode-Multiple:

```

```

type: array
items:
$ref: '#/components/schemas/ManagementNode-Single'
MnsAgent-Multiple:
type: array
items:
$ref: '#/components/schemas/MnsAgent-Single'
MeContext-Multiple:
type: array
items:
$ref: '#/components/schemas/MeContext-Single'
PerfMetricJob-Multiple:
type: array
items:
$ref: '#/components/schemas/PerfMetricJob-Single'
ThresholdMonitor-Multiple:
type: array
items:
$ref: '#/components/schemas/ThresholdMonitor-Single'
TraceJob-Multiple:
type: array
items:
$ref: '#/components/schemas/TraceJob-Single'
ManagementDataCollection-Multiple:
type: array
items:
$ref: '#/components/schemas/ManagementDataCollection-Single'
NtfSubscriptionControl-Multiple:
type: array
items:
$ref: '#/components/schemas/NtfSubscriptionControl-Single'
FileDownloadJob-Multiple:
type: array
items:
$ref: '#/components/schemas/FileDownloadJob-Single'
Files-Multiple:
type: array
items:
$ref: '#/components/schemas/Files-Single'
File-Multiple:
type: array
items:
$ref: '#/components/schemas/File-Single'
MnsInfo-Multiple:
type: array
items:
$ref: '#/components/schemas/MnsInfo-Single'

```

#----- Definitions in TS 28.623 for TS 28.532 -----

```

resources-genericNrm:
oneOf:
- $ref: '#/components/schemas/VsDataContainer-Single'
- $ref: '#/components/schemas/ManagementNode-Single'
- $ref: '#/components/schemas/MnsAgent-Single'
- $ref: '#/components/schemas/MeContext-Single'
- $ref: '#/components/schemas/ManagedNFService-Single'
- $ref: '#/components/schemas/PerfMetricJob-Single'
- $ref: '#/components/schemas/ThresholdMonitor-Single'
- $ref: '#/components/schemas/TraceJob-Single'
- $ref: '#/components/schemas/ManagementDataCollection-Single'
- $ref: '#/components/schemas/NtfSubscriptionControl-Single'
- $ref: '#/components/schemas/HeartbeatControl-Single'
- $ref: '#/components/schemas/AlarmList-Single'
- $ref: '#/components/schemas/FileDownloadJob-Single'
- $ref: '#/components/schemas/Files-Single'
- $ref: '#/components/schemas/File-Single'
- $ref: '#/components/schemas/MnsRegistry-Single'
- $ref: '#/components/schemas/MnsInfo-Single'

```



---

## Annex D (normative): YANG definitions

### D.1 General

This annex contains the YANG definitions for the Generic NRM.

---

### D.2 Modules

#### D.2.1 module \_3gpp-common-ep-rp.yang

```
module _3gpp-common-ep-rp {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-ep-rp";
    prefix "eprp3gpp";

    import _3gpp-common-yang-types { prefix types3gpp; }
    import ietf-inet-types { prefix inet; }
    import _3gpp-common-measurements { prefix meas3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
    description "Common/basic class/grouping to be inherited/reused.
    This IOC represents an end point of a link used across a reference
    point between two network entities.";
    reference
        "3GPP TS 28.622
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Information Service (IS)

        3GPP TS 28.620
        Umbrella Information Model (UIM)";

    revision 2020-06-08 { reference "CR-0092"; }

    revision 2019-06-17 {
        description "Initial revision";
    }

    grouping EP_RPGrp {
        description "Abstract class, represents an end point of a link used
        across a reference point between two network entities.

        For naming the subclasses of EP_RP, the following rules shall apply:
        - The name of the subclassed IOC shall have the form 'EP_<rp>',
        where <rp> is a string that represents the name of the reference point.
        Thus, two valid examples of EP_RP subclassed IOC names would be:
        EP_S1 and EP_X2.";

        leaf userLabel {
            type string;
            description "A user-friendly (and user assignable) name of this object.";
        }

        leaf farEndEntity {
            config false;
            type types3gpp:DistinguishedName;
        }
    }

    grouping EP_Common {
        uses EP_RPGrp;
        uses meas3gpp:SupportedPerfMetricGroupGrp;
        list localAddress {
            description "Local IP address and VLAN ID.";
            key "ipAddress vlanId";
        }
    }
}
```

```

    min-elements 1;
    max-elements 1;
    uses types3gpp:AddressWithVlan;
}

leaf remoteAddress {
    description "Remote IP address.";
    mandatory true;
    type inet:ip-address;
}
}
}
}

```

## D.2.2 module \_3gpp-common-managed-element.yang

```

<CODE BEGINS>
module _3gpp-common-managed-element {
    yang-version 1.1;
    namespace urn:3gpp:sas:_3gpp-common-managed-element;
    prefix "me3gpp";

    import _3gpp-common-yang-types { prefix types3gpp ; }
    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-measurements { prefix meas3gpp; }
    import _3gpp-common-subscription-control { prefix subscr3gpp; }
    import _3gpp-common-fm { prefix fm3gpp; }
    import _3gpp-common-trace { prefix trace3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Defines ManagedElement which will be augmented
        by other IOCs";
    reference "3GPP TS 28.623
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Solution Set (SS) definitions

        3GPP TS 28.622
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Information Service (IS)

        3GPP TS 28.620
        Umbrella Information Model (UIM)";

    revision 2021-01-16 { reference "CR-0120"; }
    revision 2020-08-06 { reference "CR-0102"; }
    revision 2020-08-03 { reference "CR-0095"; }
    revision 2020-06-08 { reference "CR-0092"; }
    revision 2020-05-12 { reference "CR0084"; }
    revision 2020-02-24 { reference "S5-201365"; }
    revision 2019-06-17 { reference "S5-203316"; }
    revision 2019-05-08 { reference "Initial revision"; }

    feature MeasurementsUnderManagedElement {
        description "The MeasurementSubtree shall be contained under
            ManagedElement";
    }

    feature SubscriptionControlUnderManagedElement {
        description "The SubscriptionControlSubtree shall be contained under
            ManagedElement";
    }

    feature FmUnderManagedElement {
        description "The FmSubtree shall be contained under ManagedElement";
    }

    feature TraceUnderManagedElement {
        description "The TraceSubtree shall be contained under ManageElement";
    }

    feature DESManagementFunction {
        description "Class representing Distributed SON or Domain-Centralized SON
            Energy Saving feature. The DESManagementFunction shall be contained under
            ManagedElement";
    }
}

```

```

        ManagedElement.";

    }

feature DMROFunction {
    description "Class representing D-SON function of MRO feature. The
    DMROFunction shall be contained under ManagedElement.";
}

feature DRACHOptimizationFunction {
    description "Class representing D-SON function of RACH optimization
    feature. The DRACHOptimizationFunction shall be contained under
    ManagedElement.";
}

feature DPCIConfigurationFunction {
    description "Class representing Distributed SON or Domain-Centralized SON
    function of PCI configuration feature. The DPCIConfigurationFunction shall
    be contained under ManagedElement.";
}

feature CPCIConfigurationFunction {
    description "Class representing Cross Domain-Centralized SON function of PCI
    configuration feature. The CPCIConfigurationFunction shall be contained
    under ManagedElement.";
}

feature CESManagementFunction {
    description "Class representing Cross Domain-Centralized SON Energy Saving
    feature. The CESManagementFunction shall be contained under
    ManagedElement.";
}

grouping ManagedElement_Grp {
    description "Abstract class representing telecommunications resources.
    An ME communicates with a manager (directly or indirectly) for the
    purpose of being monitored and/or controlled. MEs may perform element
    management functionality.
    An ME (and its contained Function_(s)) may or may not be geographically
    distributed. An ME (and its contained Function_(s)) is often referred
    to as a Network Element";
}

leaf dnPrefix {
    description "Provides naming context that allows the Managed
    Elements to be partitioned into logical domains.
    A Distinguished Name(DN) is defined by 3GPP TS 32.300,
    which splits the DN into a DN Prefix and Local DN";
    type types3gpp:DistinguishedName;
}

leaf userLabel {
    description "A user-friendly (and user assignable) name of this object.";
    type string;
}

leaf locationName {
    description "The physical location (e.g. an address) of an entity
    represented by a (derivative of) ManagedElement_. It may contain no
    information to support the case where the derivative of
    ManagedElement_ needs to represent a distributed multi-location NE.";
    config false;
    type string;
}

leaf-list managedBy {
    description "Relates to the role played by ManagementSystem_ in the
    between ManagedSystem_ and ManagedElement_. This attribute contains
    a list of the DN(s) of the related subclasses of
    ManagementSystem_ instance(s).";

    config false;
    type types3gpp:DistinguishedName;
}

leaf-list managedElementTypeList {
    description "The type of functionality provided by the ManagedElement.
    It may represent one ME functionality or a combination of
    more than one functionality.
    1) The allowed values of this attribute are the names of the IOC(s)
}

```

that are (a) derived/subclassed from ManagedFunction and (b) directly name-contained by ManagedElement IOC (on the first level below ManagedElement), but with the string 'Function' excluded.

2) If a ManagedElement contains multiple instances of a ManagedFunction this attribute will not contain repeated values.

3) The capitalisation (usage of upper/lower case) of characters in this attribute is insignificant. Thus, the NodeB should be case insensitive when reading these values.

4) Two examples of allowed values are:

- NodeB;
- HLR, VLR.;"

```

config false;
min-elements 1;
type string;
}

grouping ManagedElementGrp {
    description "Represents telecommunications equipment or
TMN entities within the telecommunications network providing support
and/or service to the subscriber.";

uses ManagedElement_Grp;
uses meas3gpp:SupportedPerfMetricGroupGrp;

leaf vendorName {
    config false;
    type string;
}

leaf userDefinedState {
    type string;
    description "An operator defined state for operator specific usage";
}

leaf swVersion {
    config false;
    type string;
}

leaf priorityLabel {
    type uint32;
    mandatory true;
}
}

list ManagedElement {
    description "Represents telecommunications equipment or TMN entities within
the telecommunications network providing support and/or service to the
subscriber. An ManagedElement IOC is used to represent a Network Element
defined in TS 32.101 including virtualization or non-virtualization
scenario. An ManagedElement instance is used for communicating with a
manager (directly or indirectly) over one or more management interfaces
for the purpose of being monitored and/or controlled. ManagedElement may
or may not additionally perform element management functionality.
An ManagedElement contains equipment that may or may not be geographically
distributed.

```

A telecommunication equipment has software and hardware components. The ManagedElement IOC described above represents following two cases:

- In the case when the software component is designed to run on dedicated hardware component, the ManagedElement IOC description includes both software and hardware components.
- In the case when the software is designed to run on ETSI NFV defined NFVI [15], the ManagedElement IOC description would exclude the NFVI component supporting the above mentioned subject software.

A ManagedElement may be contained in either a SubNetwork or in a MeContext instance. A single ManagedElement may also exist stand-alone with no parent at all.

The relation of ManagedElement IOC and ManagedFunction IOC can be described as following:

- A ManagedElement instance may have 1..1 containment relationship to a ManagedFunction instance. In this case, the ManagedElement IOC may be used to represent a NE with single functionality. For example, a ManagedElement is used to represent the 3GPP defined RNC node;

- A ManagedElement instance may have 1..N containment relationship to multiple ManagedFunction IOC instances. In this case, the ManagedElement IOC may be used to represent a NE with combined ManagedFunction functionality (as indicated by the managedElementType attribute and the contained instances of different ManagedFunction IOCs). For example, a ManagedElement is used to represent the combined functionality of 3GPP defined gNBCUCPFunction, gNBUUPFunction and gNBDUFunction";

```

key id;
uses top3gpp:Top_Grp;
container attributes {
    uses ManagedElementGrp;
}

uses meas3gpp:MeasurementSubtree {
    if-feature MeasurementsUnderManagedElement;
}

uses subscr3gpp:SubscriptionControlSubtree {
    if-feature SubscriptionControlUnderManagedElement;
}

uses fm3gpp:FmSubtree {
    if-feature FmUnderManagedElement;
}

uses trace3gpp:TraceSubtree {
    if-feature TraceUnderManagedElement;
}

}

<CODE ENDS>
```

### D.2.3 module \_3gpp-common-managed-function.yang

```

<CODE BEGINS>
module _3gpp-common-managed-function {
    yang-version 1.1;
    namespace urn:3gpp:sa5:_3gpp-common-managed-function;
    prefix mf3gpp;

    import _3gpp-common-yang-types { prefix types3gpp; }
    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-measurements { prefix meas3gpp; }
    import _3gpp-common-trace { prefix trace3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
    description "The module defines a base class/grouping for major 3GPP
        functions.";
    reference
        "3GPP TS 28.622
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Information Service (IS)

        3GPP TS 28.620
        Umbrella Information Model (UIM)";
    revision 2022-01-07 { reference "CR-0146"; }
    revision 2021-01-25 { reference "CR-0122"; }
    revision 2020-09-30 { reference "CR-bbbb"; }
    revision 2020-08-06 { reference "CR-0102"; }
    revision 2020-08-03 { reference "CR-0095"; }
    revision 2020-06-23 { reference "CR-085"; }
    revision 2020-06-08 { reference "CR-0092"; }
    revision 2019-11-21 { reference "S5-197275, S5-197735"; }
    revision 2019-10-28 { reference S5-193518 ; }
    revision 2019-06-18 { reference "Initial revision"; }

    feature MeasurementsUnderManagedFunction {
        description "The MeasurementSubtree shall be contained under ManagedElement";
    }

    feature TraceUnderManagedFunction {
        description "The TraceSubtree shall be contained under ManagedFunction";
    }
```

```

grouping Operation {
    description "This data type represents an Operation.";
    reference "3gpp TS 28.622";

    leaf name {
        type string;
        mandatory true;
    }

    leaf-list allowedNFTypes {
        type string;
        min-elements 1;
        description "The type of the managed NF service instance
                     The specifc values allowed are described in TS 23.501";
    }

    leaf operationSemantics {
        type enumeration {
            enum REQUEST_RESPONSE;
            enum SUBSCRIBE_NOTIFY;

        }
        config false;
        mandatory true;
        description "Semantics type of the operation.";
        reference "3GPP TS 23.502";
    }
}

grouping ManagedNFServiceGrp {
    description "A ManagedNFService represents a Network Function (NF) service.";
    reference "Clause 7 of 3GPP TS 23.501.";

    leaf userLabel {
        type string;
        description "A user-friendly (and user assignable) name of this object.";
    }

    leaf nFServiceType {
        config false;
        mandatory true;
        type string;
        description "The type of the managed NF service instance
                     The specifc values allowed are described in clause 7.2 of TS 23.501";
    }

    list SAP {
        key "host port";
        min-elements 1;
        max-elements 1;
        description "The service access point of the managed NF service instance";
        uses types3gpp:SAP;
    }

    list operations {
        key name;
        min-elements 1;
        uses Operation ;
        description "Set of operations supported by the managed NF
                     service instance";
    }

    leaf administrativeState {
        type types3gpp:AdministrativeState;
        mandatory true;
        description "Permission to use or prohibition against using the instance";
    }

    leaf operationalState {
        type types3gpp:OperationalState;
        config false;
        mandatory true;
        description "Describes whether the resource is installed and working";
    }

    leaf usageState {
        type types3gpp:usageState ;
    }
}

```

```

    config false;
    mandatory true;
    description "Describes whether the resource is actively in use at a
      specific instant, and if so, whether or not it has spare
      capacity for additional users.";
}

leaf registrationState {
    type enumeration {
        enum REGISTERED;
        enum DREGISTERED;
    }
    config false;
}
}

grouping Function_Grp {
    description "A base grouping for 3GPP functions.";

    leaf userLabel {
        type string;
        description "A user-friendly (and user assignable) name of this object.";
    }
}

grouping ManagedFunctionGrp {
    description "Abstract root class to be inherited/reused by classes
      representing 3GPP functions.

      Anywhere this grouping is used by classes inheriting from ManagedFunction
      the list representing the inheriting class needs to include all
      contained classes of ManagedFunction too. Contained classes are
      either
      - augmented into the Function class or
      - shall be included in the list representing the inheriting class
      using the grouping ManagedFunctionContainedClasses:
          1) EP_RP solved using augment
          2) uses mf3gpp:ManagedFunctionContainedClasses;
    ";
}

uses Function_Grp;

list vnfParametersList {
    key vnfInstanceId;
    description "Contains the parameter set of the VNF
      instance(s) corresponding to an NE.
      The presence of this list indicates that the ManagedFunction
      represented is realized by one or more VNF instance(s). Otherwise it
      shall be absent.
      The presence of a vnfParametersList entry, whose vnfInstanceId with a
      string length of zero, in createMO operation can trigger the
      instantiation of the related VNF/VNFC instances.";

    leaf vnfInstanceId {
        type string ;
        description "VNF instance identifier";
        reference "ETSI GS NFV-IFA 008 v2.1.1:
          Network Functions Virtualisation (NFV); Management and Orchestration;
          Ve-Vnfm reference point - Interface and Information Model Specification
          section 9.4.2

          ETSI GS NFV-IFA 015 v2.1.2: Network Functions Virtualisation (NFV);
          Management and Orchestration; Report on NFV Information Model
          section B2.4.2.1.2.3";
    }

    leaf vnfdId {
        type string ;
        description "Identifier of the VNFD on which the VNF instance is based.
          The absence of the leaf or a string length of zero for vnfInstanceId
          means the VNF instance(s) does not exist (e.g. has not been
          instantiated yet, has already been terminated).";
        reference "ETSI GS NFV-IFA 008 v2.1.1:
          Network Functions Virtualisation (NFV); Management and Orchestration;
          Ve-Vnfm reference point - Interface and Information Model Specification
          section 9.4.2";
    }
}

```

```

leaf flavourId {
    type string ;
    description "Identifier of the VNF Deployment Flavour applied to this
    VNF instance.";
    reference "ETSI GS NFV-IFA 008 v2.1.1:
        Network Functions Virtualisation (NFV) Management and Orchestration";
}
leaf autoScalable {
    type boolean ;
    mandatory true;
    description "Indicator of whether the auto-scaling of this
    VNF instance is enabled or disabled.";
}
}

list peeParametersList {
key idx;
description "Contains the parameter set for the control
and monitoring of power, energy and environmental parameters of
ManagedFunction instance(s).";

leaf idx { type uint32; }

leaf siteIdentification {
    type string;
    mandatory true;
    description "The identification of the site where the
    ManagedFunction resides.";
}

leaf siteLatitude {
    type decimal64 {
        fraction-digits 4;
        range "-90.0000..+90.0000";
    }
    description "The latitude of the site where the ManagedFunction
    instance resides, based on World Geodetic System (1984 version)
    global reference frame (WGS 84). Positive values correspond to
    the northern hemisphere. This attribute is optional
    for BTSFunction, RNCFunction, GNBDUFunction and
    NRSectorCarrier instance(s).";
}

leaf siteLongitude {
    type decimal64 {
        fraction-digits 4;
        range "-180.0000..+180.0000";
    }
    description "The longitude of the site where the ManagedFunction
    instance resides, based on World Geodetic System (1984 version)
    global reference frame (WGS 84). Positive values correspond to
    degrees east of 0 degrees longitude. This attribute is optional
    for BTSFunction, RNCFunction, GNBDUFunction and
    NRSectorCarrier
    instance(s).";
}

leaf siteAltitude {
    type decimal64 {
        fraction-digits 4;
    }
    description "The altitude of the site where the ManagedFunction
    instance resides, in the unit of meter. This attribute is
    optional for BTSFunction, RNCFunction, GNBDUFunction and
    NRSectorCarrier instance(s).";
}

leaf siteDescription {
    type string;
    mandatory true;
    description "An operator defined description of the site where
    the ManagedFunction instance resides.";
}

leaf equipmentType {
    type string;
    mandatory true;
}

```

```

        description "The type of equipment where the managedFunction
                     instance resides.";
        reference "clause 4.4.1 of ETSI ES 202 336-12";
    }

    leaf environmentType {
        type string;
        mandatory true;
        description "The type of environment where the managedFunction
                     instance resides.";
        reference "clause 4.4.1 of ETSI ES 202 336-12";
    }

    leaf powerInterface {
        type string;
        mandatory true;
        description "The type of power.";
        reference "clause 4.4.1 of ETSI ES 202 336-12";
    }
}

leaf priorityLabel {
    mandatory true;
    type uint32;
}
uses meas3gpp:SupportedPerfMetricGroupGrp;
}

grouping ManagedFunctionContainedClasses {
    description "A grouping used to containe classes (lists) contained by
                 the abstract IOC ManagedFunction";
    list ManagedNFService {
        description "Represents a Network Function (NF)";
        reference "3GPP TS 23.501";
        key id;
        uses top3gpp:Top_Grp;
        container attributes {
            uses ManagedNFServiceGrp;
        }
    }
}

uses meas3gpp:MeasurementSubtree {
    if-feature MeasurementsUnderManagedFunction ;
}

uses trace3gpp:TraceSubtree {
    if-feature TraceUnderManagedFunction ;
}
}

<CODE ENDS>

```

## D.2.4 module \_3gpp-common-measurements.yang

```

<CODE BEGINS>
module _3gpp-common-measurements {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-measurements";
    prefix "meas3gpp";

    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-yang-types { prefix types3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Defines Measurement and KPI related groupings
                 Any list/class intending to use this should include 2 or 3 uses statements
                 controlled by a feature:

    A)
+++    feature MeasurementsUnderMyClass {
+++        description 'Indicates whether measurements and/or KPIs are supported
+++        for this class.';
+++    }

```

B) include the attribute measurementsList and/or kPIsList indicating the supported measurement and KPI types and GPs. Note that for classes inheriting from ManagedFunction, EP\_RP or SubNetwork these attributes are already inherited, so there is no need to include them once more. E.g.

```
+++ grouping MyClassGrp {
+++   uses meas3gpp:SupportedPerfMetricGroup;
+++ }
```

C) include the class PerfmetricJob to control the measurements/KPIs. E.g.

```
list MyClass {
  container attributes {
    uses MyClassGrp;
  }
+++ uses meas3gpp:MeasurementSubtree {
+++   if-feature MeasurementsUnderMyClass ;
+++ }
```

Measurements can be contained under ManagedElement, SubNetwork, or any list representing a class inheriting from Subnetwork or ManagedFunction. Note: KPIs will only be supported under SubNetwork";

reference "3GPP TS 28.623  
Generic Network Resource Model (NRM)  
Integration Reference Point (IRP);  
Solution Set (SS) definitions

3GPP TS 28.622  
Generic Network Resource Model (NRM)  
Integration Reference Point (IRP);  
Information Service (IS);  
  
revision 2021-07-22 { reference "CR-0137"; }  
revision 2020-11-06 { reference "CR-0118"; }  
revision 2020-09-04 { reference "CR-000107"; }  
revision 2020-06-08 { reference "CR-0092"; }  
revision 2020-05-31 { reference "CR-0084"; }  
revision 2020-03-11 { reference "S5-201581, SP-200229"; }  
revision 2019-11-21 { reference "S5-197275, S5-197735"; }  
revision 2019-10-28 { reference "S5-193516"; }  
revision 2019-06-17 { reference " "; }

```
grouping ThresholdInfoGrp {
  description "Defines a single threshold level.";

  leaf-list measurementTypes {
    type string;
    description "The Measurement type can be those specified in TS 28.552,  
TS 32.404 and can be those specified by other SDOs or can be  
vendor-specific.";
  }

  leaf thresholdLevel {
    type uint64;
    mandatory true;
    description "Number (key) for a single threshold in the threshold list  
applicable to the monitored performance metric.";
  }

  leaf thresholdDirection {
    type enumeration {
      enum UP;
      enum DOWN;
      enum UP_AND_DOWN;
    }
    must '. = "UP_AND_DOWN" or not(..../hysteresis)' {
      error-message "In case a threshold with hysteresis is configured, the  
+threshold direction attribute shall be set to 'UP_AND_DOWN'.";
    }
    mandatory true;
    description "Direction of a threshold indicating the direction for which  
a threshold crossing triggers a threshold.

    When the threshold direction is configured to 'UP', the associated  
threshold is triggered only when the performance metric value is going
```

up upon reaching or crossing the threshold value. The threshold is not triggered, when the performance metric is going down upon reaching or crossing the threshold value.

Vice versa, when the threshold direction is configured to 'DOWN', the associated threshold is triggered only when the performance metric is going down upon reaching or crossing the threshold value. The threshold is not triggered, when the performance metric is going up upon reaching or crossing the threshold value.

When the threshold direction is set to 'UP\_AND\_DOWN' the threshold is active in both directions.

In case a threshold with hysteresis is configured, the threshold direction attribute shall be set to 'UP\_AND\_DOWN'.";

}

```
leaf thresholdValue {
    type union {
        type int64;
        type decimal64 {
            fraction-digits 2;
        }
    }
    mandatory true;
    description "Value against which the monitored performance metric is compared at a threshold level in case the hysteresis is zero";
}
```

```
leaf hysteresis {
    type union {
        type uint64;
        type decimal64 {
            fraction-digits 2;
            range "0..max";
        }
    }
    description "Hysteresis of a threshold. If this attribute is present the monitored performance metric is not compared against the threshold value as specified by the thresholdValue attribute but against a high and low threshold value given by
```

threshold-high = thresholdValue + hysteresis  
threshold-low = thresholdValue - hysteresis

When going up, the threshold is triggered when the performance metric reaches or crosses the high threshold value. When going down, the threshold is triggered when the performance metric reaches or crosses the low threshold value.

A hysteresis may be present only when the monitored performance metric is not of type counter that can go up only. If present for a performance metric of type counter, it shall be ignored.";

}

```
grouping SupportedPerfMetricGroupGrp {
    list SupportedPerfMetricGroup {
        config false;
        description "Captures a group of supported performance metrics and associated parameters related to their production and reporting. A SupportedPerfMetricGroup attribute which is part of an MOI may define performanceMetrics for any MOI under the subtree contained under that MOI, e.g. SupportedPerfMetricGroup on a ManagedElement can specify supported metrics for contained ManagedFunctions like a GNBDUFunction.";
```

```
leaf-list performanceMetrics {
    type string;
    min-elements 1;
    description "Performance metrics include measurements defined in TS 28.552 and KPIs defined in TS 28.554. Performance metrics can also be specified by other SDOs or be vendor specific. Performance metrics are identified with their names.
```

For measurements defined in TS 28.552 the name is constructed as follows:

- 'family.measurementName.subcounter' for measurement types with

```

subcounters
- 'family.measurementName' for measurement types without subcounters
- 'family' for measurement families

For KPIs defined in TS 28.554 the name is defined in the KPI
definitions template as the component designated with e).

A name can also identify a vendor specific performance metric or a
group of vendor specific performance metrics.";

}

leaf-list granularityPeriods {
    type uint32 {
        range 1..max ;
    }
    units seconds;
}

leaf-list reportingMethods {
    type enumeration {
        enum FILE_BASED_LOC_SET_BY_PRODUCER;
        enum FILE_BASED_LOC_SET_BY_CONSUMER;
        enum STREAM_BASED;
    }
    min-elements 1;
}

leaf-list monitorGranularityPeriods {
    type uint32 {
        range 1..max ;
    }
    units seconds;
    description "Granularity periods supported for the monitoring of
        associated measurement types for thresholds";
}
}

grouping PerfMetricJobGrp {
    description "Represents the attributes of the IOC PerfMetricJob";

    leaf administrativeState {
        default UNLOCKED;
        type types3gpp:AdministrativeState ;
        description "Enable or disables production of the metrics";
    }

    leaf operationalState {
        config false;
        mandatory true;
        type types3gpp:OperationalState ;
        description "Indicates whether the PerfMetricJob is working.";
    }

    leaf jobId {
        type string;
        description "Id for a PerfMetricJob job.";
    }

    leaf-list performanceMetrics {
        type string;
        min-elements 1;
        description "Performance metrics include measurements defined in
            TS 28.552 and KPIs defined in TS 28.554. Performance metrics can
            also be those specified by other SDOs or vendor specific metrics.
            Performance metrics are identified with their names. A name can also
            identify a vendor specific group of performance metrics.

For measurements defined in TS 28.552 the name is constructed as
follows:
- 'family.measurementName.subcounter' for measurement types with
subcounters
- 'family.measurementName' for measurement types without subcounters
- 'family' for measurement families

For KPIs defined in TS 28.554 the name is defined in the KPI
definitions template as the component designated with e).";
    }
}

```

```

leaf granularityPeriod {
    type uint32 {
        range 1..max ;
    }
    units seconds;
    mandatory true;
    description "Granularity period used to produce measurements. The value
                 must be one of the supported granularity periods for the metric.";
}

leaf-list objectInstances {
    type types3gpp:DistinguishedName;
}

leaf-list rootObjectInstances {
    type types3gpp:DistinguishedName;
    description "Each object instance designates the root of a subtree that
                 contains the root object and all descendant objects.";
}

choice reportingCtrl {
    mandatory true;
    description "This choice defines the method for reporting collected
                 performance metrics to MnS consumers as well as the parameters for
                 configuring the reporting function. It is a choice between the control
                 parameter required for the reporting methods, whose presence selects
                 the reporting method as follows:
                 - When only the fileReportingPeriod attribute is present, the MnS
                   producer shall store files on the MnS producer at a location selected
                   by the MnS producer and inform the MnS consumer about the availability
                   of new files and the file location using the notifyFileReady
                   notification.
                 - When only the fileReportingPeriod and fileLocation attributes are
                   present, the MnS producer shall store the files on the MnS consumer at
                   the location specified by fileLocation. No notification is emitted by
                   the MnS producer.
                 - When only the streamTarget attribute is present, the MnS producer
                   shall stream the data to the location specified by streamTarget.

    For the file-based reporting methods the fileReportingPeriod attribute
    specifies the time window during which collected measurements are stored
    into the same file before the file is closed and a new file is opened.";

    case file-based-reporting {
        leaf fileReportingPeriod {
            type uint32 {
                range 1..max;
            }
            units minutes;
            must '(number(.)**"60") mod number(..../granularityPeriod) = "0"' {
                error-message
                    "The time-period must be a multiple of the granularityPeriod.";
            }
            mandatory true;
            description "For the file-based reporting method this is the time
                         window during which collected measurements are stored into the same
                         file before the file is closed and a new file is opened.
                         The time-period must be a multiple of the granularityPeriod.

                         Applicable when the file-based reporting method is supported";
        }

        leaf fileLocation {
            type string ;
            description "Applicable and must be present when the file-based
                         reporting method is supported, and the files are stored on the MnS
                         consumer.";
        }
    }
    case stream-based-reporting {
        leaf streamTarget {
            type string;
            mandatory true;
            description "Applicable when stream-based reporting method is
                         supported.";
        }
    }
}

```

```

        }

grouping ThresholdMonitorGrp {
    description "A threshold monitor that is created by the consumer for
    the monitored entities whose measurements are required by consumer
    to monitor./";

leaf administrativeState {
    default UNLOCKED;
    type types3gpp:AdministrativeState ;
    description "Enables or disables the ThresholdMonitor.";
}

leaf operationalState {
    config false;
    mandatory true;
    type types3gpp:OperationalState ;
    description "Indicates whether the ThresholdMonitor is working.";
}

list thresholdInfoList {
    key idx;
    min-elements 1;
    leaf idx { type uint32 ; }
    uses ThresholdInfoGrp;
}

leaf monitorGranularityPeriod {
    type uint32 {
        range "1..max";
    }
    units second;
    mandatory true;
    description " Granularity period used to monitor measurements for
    threshold crossings. ";
}

leaf-list objectInstances {
    type types3gpp:DistinguishedName;
}

leaf-list rootObjectInstances {
    type types3gpp:DistinguishedName;
    description "Each object instance designates the root of a subtree that
    contains the root object and all descendant objects.";
}

grouping MeasurementSubtree {
    description "Contains classes that define measurements.
    Should be used in all classes (or classes inheriting from)
    - SubNetwork
    - ManagedElement
    - ManagedFunction

If a YANG module wants to augment these classes/list/groupings they must
augment all user classes!

If a class uses this grouping in its list it shall also use the
grouping SupportedPerfMetricGroupGrp to add SupportedPerfMetricGroup as
an attribute to its grouping";

list PerfMetricJob {
    description "This IOC represents a performance metric production job. It
    can be name-contained by SubNetwork, ManagedElement, or ManagedFunction.

To activate the production of the specified performance metrics, a MnS
consumer needs to create a PerfMetricJob instance on the MnS producer.
For ultimate deactivation of metric production, the MnS consumer should
delete the job to free up resources on the MnS producer.

For temporary suspension of metric production, the MnS consumer can
manipulate the value of the administrative state attribute. The MnS
producer may disable metric production as well, for example in overload
situations. This situation is indicated by the MnS producer with setting
the operational state attribute to disabled. When production is resumed

```

the operational state is set back to enabled.

The jobId attribute can be used to associate metrics from multiple PerfMetricJob instances. The jobId can be included when reporting performance metrics to allow a MnS consumer to associate received metrics for the same purpose. For example, it is possible to configure the same jobId value for multiple PerfMetricJob instances required to produce the measurements for a specific KPI.

The attribute performanceMetrics defines the performance metrics to be produced and the attribute granularityPeriod defines the granularity period to be applied.

All object instances below and including the instance name-containing the PerfMetricJob (base object instance) are scoped for performance metric production. Performance metrics are produced only on those object instances whose object class matches the object class associated to the performance metrics to be produced.

The attributes objectInstances and rootObjectInstances allow to restrict the scope. When the attribute objectInstances is present, only the object instances identified by this attribute are scoped. When the attribute rootObjectInstances is present, then the subtrees whose root objects are identified by this attribute are scoped. Both attributes may be present at the same time meaning the total scope is equal to the sum of both scopes. Object instances may be scoped by both the objectInstances and rootObjectInstances attributes. This shall not be considered as an error by the MnS producer.

When the performance metric requires performance metric production on multiple managed objects, which is for example the case for KPIs, the MnS consumer needs to ensure all required objects are scoped. Otherwise a PerfMetricJob creation request shall fail.

The attribute reportingCtrl specifies the method and associated control parameters for reporting the produced measurements to MnS consumers. Three methods are available: file-based reporting with selection of the file location by the MnS producer, file-based reporting with selection of the file location by the MnS consumer and stream-based reporting.

For file-based reporting, all performance metrics that are produced related to a 'PerfMetricJob' instance for a reporting period shall be stored in a single reporting file.

When the administrative state is set to 'UNLOCKED' after the creation of a 'PerfMetricJob' the first granularity period shall start. When the administrative state is set to 'LOCKED' or the operational state to 'DISABLED', the ongoing reporting period shall be aborted, for streaming the ongoing granularity period. When the administrative state is set back to 'UNLOCKED' or the operational state to 'ENABLED' a new reporting period period shall start, in case of streaming a new granularity period.

Changes of all other configurable attributes shall take effect only at the beginning of the next reporting period, for streaming at the beginning of the next granularity period.

When the 'PerfMetricJob' is deleted, the ongoing reporting period shall be aborted, for streaming the ongoing granularity period.

A PerfMetricJob creation request shall fail, when the requested performance metrics, the requested granularity period, the requested reporting method, or the requested combination thereof is not supported by the MnS producer.

Creation and deletion of PerfMetricJob instances by MnS consumers is optional; when not supported, PerfMetricJob instances may be created and deleted by the system or be pre-installed.";

```
key id;
uses top3gpp:Top_Grp ;
container attributes {
    uses PerfMetricJobGrp ;
}
}

list ThresholdMonitor {
    key id;
```

description "Represents a threshold monitor for performance metrics. It can be contained by SubNetwork, ManagedElement, or ManagedFunction. A threshold monitor checks for threshold crossings of performance metric values and generates a notification when that happens.

To activate threshold monitoring, a MnS consumer needs to create a ThresholdMonitor instance on the MnS producer. For ultimate deactivation of threshold monitoring, the MnS consumer should delete the monitor to free up resources on the MnS producer.

For temporary suspension of threshold monitoring, the MnS consumer can manipulate the value of the administrative state attribute. The MnS producer may disable threshold monitoring as well, for example in overload situations. This situation is indicated by the MnS producer with setting the operational state attribute to disabled. When monitoring is resumed the operational state is set again to enabled.

All object instances below and including the instance containing the ThresholdMonitor (base object instance) are scoped for performance metric production. Performance metrics are monitored only on those object instances whose object class matches the object class associated to the performance metrics to be monitored.

The optional attributes objectInstances and rootObjectInstances allow to restrict the scope. When the attribute objectInstances is present, only the object instances identified by this attribute are scoped. When the attribute rootObjectInstances is present, then the subtrees whose root objects are identified by this attribute are scoped. Both attributes may be present at the same time meaning the total scope is equal to the sum of both scopes. Object instances may be scoped by both the objectInstances and rootObjectInstances attributes. This shall not be considered as an error by the MnS producer.

Multiple thresholds can be defined for multiple performance metric sets in a single monitor using thresholdInfoList. The attribute monitorGranularityPeriod defines the granularity period to be applied.

Each threshold is identified with a number (key) called thresholdLevel. A threshold is defined using the attributes thresholdValue, thresholdDirection and hysteresis.

When hysteresis is absent or carries no information, a threshold is triggered when the thresholdValue is reached or crossed. When hysteresis is present, two threshold values are specified for the threshold as follows: A high threshold value equal to the threshold value plus the hysteresis value, and a low threshold value equal to the threshold value minus the hysteresis value. When the monitored performance metric increases, the threshold is triggered when the high threshold value is reached or crossed. When the monitored performance metric decreases, the threshold is triggered when the low threshold value is reached or crossed. The hysteresis ensures that the performance metric value can oscillate around a comparison value without triggering each time the threshold when the threshold value is crossed.

Using the thresholdDirection attribute a threshold can be configured in such a manner that it is triggered only when the monitored performance metric is going up or down upon reaching or crossing the threshold.

A ThresholdMonitor creation request shall be rejected, if the performance metrics requested to be monitored, the requested granularity period, or the requested combination thereof is not supported by the MnS producer. A creation request may fail, when the performance metrics requested to be monitored are not produced by a PerfMetricJob.

Creation and deletion of ThresholdMonitor instances by MnS consumers is optional; when not supported, ThresholdMonitor instances may be created and deleted by the system or be pre-installed.";

```
uses top3gpp:Top_Grp ;
container attributes {
    uses ThresholdMonitorGrp ;
}
}
<CODE ENDS>
```

## D.2.5 module \_3gpp-common-subnetwork.yang

```
<CODE BEGINS>
module _3gpp-common-subnetwork {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-subnetwork";
    prefix "subnet3gpp";

    import _3gpp-common-yang-types { prefix types3gpp; }
    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-measurements { prefix meas3gpp; }
    import _3gpp-common-subscription-control { prefix subscr3gpp; }
    import _3gpp-common-fm { prefix fm3gpp; }
    import _3gpp-common-trace { prefix trace3gpp; }
    import ietf-yang-schema-mount { prefix yangmnt; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Defines basic SubNetwork which will be augmented by other IOCs";
    reference "3GPP TS 28.623
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Solution Set (SS) definitions

        3GPP TS 28.622
        Generic Network Resource Model (NRM)
        Integration Reference Point (IRP);
        Information Service (IS)

        3GPP TS 28.620
        Umbrella Information Model (UIM)";

    revision 2021-01-16 { reference "CR-0120"; }
    revision 2020-08-06 { reference "CR-0102"; }
    revision 2020-06-08 { reference "CR-0092"; }
    revision 2020-05-08 {
        reference "S5-203316";
    }

    revision 2020-03-11 {
        description "Added KPIs and corrections";
        reference "S5-201365, S5-201581, SP-200229";
    }

    revision 2020-02-24 {
        reference "S5-201365";
    }

    revision 2019-06-17 {
        reference "Initial revision";
    }

    feature ExternalsUnderSubNetwork {
        description "Classes representing external entities like EUtranFrequency,
            ExternalGNBCUCPFunction, ExternalENBFunction
            are contained under a Subnetwork list/class.";
    }

    feature MeasurementsUnderSubNetwork {
        description "The MeasurementSubtree shall be contained under SubNetwork";
    }

    feature SubscriptionControlUnderSubNetwork {
        description "The SubscriptionControlSubtree shall be contained under
            SubNetwork";
    }

    feature FmUnderSubNetwork {
        description "The FmSubtree shall be contained under SubNetwork";
    }

    feature TraceUnderSubNetwork {
        description "The TraceSubtree shall be contained under SubNetwork";
    }
}
```

```

feature DESManagementFunction {
    description "Class representing Distributed SON or Domain-Centralized SON
    Energy Saving feature. The DESManagementFunction shall be contained under
    SubNetwork.";
}

feature DMROFunction {
    description "Class representing D-SON function of MRO feature. The
    DMROFunction shall be contained under SubNetwork.";
}

feature DRACHOptimizationFunction {
    description "Class representing D-SON function of RACH optimization feature.
    The DRACHOptimizationFunction shall be contained under SubNetwork.";
}

feature DPCIConfigurationFunction {
    description "Class representing Distributed SON or Domain-Centralized SON
    function of PCI configuration feature. The DPCIConfigurationFunction shall
    be contained under SubNetwork.";
}

feature CPCIConfigurationFunction {
    description "Class representing Cross Domain-Centralized SON function of PCI
    configuration feature. The CPCIConfigurationFunction shall be contained
    under SubNetwork.";
}

feature CESManagementFunction {
    description "Class representing Cross Domain-Centralized SON Energy Saving
    feature. The CESManagementFunction shall be contained under SubNetwork.";
}

grouping Domain_Grp {
    description "A domain is a partition of instances of managed entities
    such that :
    - the group represents a topological structure which describes the
    potential for connectivity
    - Subject to common administration
    - With common characteristics";
}

leaf dnPrefix {
    type types3gpp:DistinguishedName;
    reference "Annex C of 32.300 ";
}

leaf userLabel {
    type string;
    description "A user-friendly (and user assignable) name of this object.";
}

leaf userDefinedNetworkType {
    type string;
    description "Textual information indicating network type, e.g. 'UTRAN'.";
}

grouping SubNetworkGrp {
    uses Domain_Grp;
    uses meas3gpp:SupportedPerfMetricGroupGrp;

    leaf-list setOfMcc {
        description "Set of Mobile Country Code (MCC).
        The MCC uniquely identifies the country of domicile
        of the mobile subscriber. MCC is part of the IMSI (3GPP TS 23.003)

        This list contains all the MCC values in subordinate object
        instances to this SubNetwork instance.

        See clause 2.3 of 3GPP TS 23.003 for MCC allocation principles.

        It shall be supported if there is more than one value in setOfMcc
        of the SubNetwork. Otherwise the support is optional.";
        type types3gpp:Mcc;
    }
}

leaf priorityLabel {
}

```

```

mandatory true;
type uint32;
}

}

list SubNetwork {
key id;
description "Represents a set of managed entities";

uses top3gpp:Top_Grp;
container attributes {
uses SubNetworkGrp;
leaf-list parents {
description "Reference to all containing SubNetwork instances
in strict order from the root subnetwork down to the immediate
parent subnetwork.
If subnetworks form a containment hierarchy this is
modeled using references between the child SubNetwork and the parent
SubNetworks.
This reference MUST NOT be present for the top level SubNetwork and
MUST be present for other SubNetworks.";
type leafref {
path "../../SubNetwork/id";
}
}

leaf-list containedChildren{
description "Reference to all directly contained SubNetwork instances.
If subnetworks form a containment hierarchy this is
modeled using references between the child SubNetwork and the parent
SubNetwork.";
type leafref {
path "../../SubNetwork/id";
}
}
}

uses meas3gpp:MeasurementSubtree {
if-feature MeasurementsUnderSubNetwork;
}

uses subscr3gpp:SubscriptionControlSubtree {
if-feature SubscriptionControlUnderSubNetwork;
}

uses fm3gpp:FmSubtree {
if-feature FmUnderSubNetwork;
}

uses trace3gpp:TraceSubtree {
if-feature TraceUnderSubNetwork;
}

yangmnt:mount-point children-of-SubNetwork {
description "Mountpoint for ManagedElement";
reference "RFC8528 YANG Schema Mount";
}

// augment external parts here
}
}
<CODE ENDS>

```

## D.2.6 module \_3gpp-common-top@2019-06-17.yang

```

module _3gpp-common-top {
yang-version 1.1;

namespace urn:3gpp:sa5:_3gpp-common-top;
prefix top3gpp;

organization "3gpp SA5";
description "The model defines a YANG mapping of the top level
information classes used for management of 5G networks and
network slicing.";
reference

```

```

"3GPP TS 28.622
Generic Network Resource Model (NRM)
Integration Reference Point (IRP);
Information Service (IS)

3GPP TS 28.620
Umbrella Information Model (UIM)";

revision 2019-06-17 {
    description "Initial revision";
}

grouping Top_Grp {
    description "Abstract class supplying a naming attribute";
    reference "3GPP TS 28.620";

    leaf id {
        type string;
        description "Key leaf (namingAttribute) for a class/list.
                      Should be used as a key leaf for lists representing
                      stage 2 classes.";
        reference "3GPP TS 32.300 Name convention for managed objects";
    }
}
}

```

## D.2.6a module \_3gpp-common-subscription-control.yang

```

<CODE BEGINS>
module _3gpp-common-subscription-control {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-subscription-control";
    prefix "subscr3gpp";

    import _3gpp-common-top { prefix top3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Defines IOCs for subscription and heartbeat control.";
    reference "3GPP TS 28.623
              Generic Network Resource Model (NRM)
              Integration Reference Point (IRP);
              Solution Set (SS) definitions
              3GPP TS 28.623";

    revision 2021-01-16 { reference "CR-0120"; }
    revision 2020-08-26 { reference "CR-0106"; }
    revision 2019-11-29 { reference "S5-197648 S5-197647 S5-197829 S5-197828"; }

    grouping NtfSubscriptionControlGrp {
        description "Attributes of a specific notification subscription";

        leaf notificationRecipientAddress {
            type string;
            mandatory true;
        }

        leaf-list notificationTypes {
            type string;
            description "Defines the types of notifications that are candidates
                         for being forwarded to the notification recipient.
                         If the notificationFilter attribute is not supported or not present
                         all candidate notifications types are forwarded to the notification;
                         discriminated by notificationFilter attribute.";
        }

        list scope {
            key "scopeType";
            min-elements 1;
            max-elements 1;
            description "Describes which object instances are selected with
                         respect to a base object instance.";
        }

        leaf scopeType {
            type enumeration {

```

```

        enum BASE_ONLY;
        enum BASE_ALL;
        enum BASE_NTH_LEVEL;
        enum BASE_SUBTREE;
    }
    description "If the optional scopeLevel parameter is not supported
    or absent, allowed values of scopeType are BASE_ONLY and BASE_ALL.

    The value BASE_ONLY indicates only the base object is selected.
    The value BASE_ALL indicates the base object and all of its
    subordinate objects (incl. the leaf objects) are selected.

    If the scopeLevel parameter is supported and present, allowed
    values of scopeType are BASE_ALL, BASE_ONLY, BASE_NTH_LEVEL
    and BASE_SUBTREE.

    The value BASE_NTH_LEVEL indicates all objects on the level,
    which is specified by the scopeLevel parameter, below the base
    object are selected. The base object is at scopeLevel zero.
    The value BASE_SUBTREE indicates the base object and all of its
    subordinate objects down to and including the objects on the level,
    which is specified by the scopeLevel parameter, are selected.
    The base object is at scopeLevel zero.";
}

leaf scopeLevel {
    when '../scopeType = "BASE_NTH_LEVEL" or ../scopeType = "BASE_SUBTREE"';
    type uint16;
    mandatory true;
    description "See description of scopeType.";
}
}

leaf notificationFilter {
    type string;
    description "Defines a filter to be applied to candidate notifications
    identified by the notificationTypes attribute.
    If notificationFilter is present, only notifications that pass the
    filter criteria are forwarded to the notification recipient; all other
    notifications are discarded.
    The filter can be applied to any field of a notification.";
}
}

grouping HeartbeatControlGrp {
    description "Attributes of HeartbeatControl. Note the triggerHeartbeatNtf
    attribute has no mapping in the present release.";

    leaf heartbeatNtfPeriod {
        type uint32;
        mandatory true;
        units seconds;
        description "Specifies the periodicity of heartbeat notification emission.
        The value of zero has the special meaning of stopping the heartbeat
        notification emission.";
    }
}

grouping SubscriptionControlSubtree {
    description "Contains notification subscription related classes.
    Should be used in all classes (or classes inheriting from)
    - SubNetwork
    - ManagedElement

    If some YAM wants to augment these classes/list/groupings they must
    augment all user classes!";

    list NtfSubscriptionControl {
        description "A NtfSubscriptionControl instance represents the
        notification subscription of a particular notification recipient.
        The scope attribute is used to select managed object instances.
        The base object instance of the scope is the object instance
        name-containing the NtfSubscriptionControl instance.
        The notifications related to the selected managed object instances
        are candidates to be sent to the address specified by the
        notificationRecipientAddress attribute.
        The notificationType attribute and notificationFilter attribute
        allow MnS consumers to exercise control over which candidate
    }
}

```

notifications are sent to the notificationRecipientAddress. If the notificationType attribute is supported and present, its value identifies the types of notifications that are candidate to be sent to the notificationRecipientAddress. If the notificationType attribute is not supported or not present, all types of notifications are candidate to be sent to notificationRecipientAddress. If supported, the notificationFilter attribute defines a filter that is applied to the set of candidate notifications. Only candidate notifications that pass the filter criteria are sent to the notificationRecipientAddress. If the notificationFilter attribute is not supported all candidate notifications are sent to the notificationRecipientAddress.

To receive notifications, a MnS consumer has to create NtfSubscriptionControl object instances on the MnS producer. A MnS consumer can create a subscription for another MnS consumer since it is not required the notificationRecipientAddress be his own address.

When a MnS consumer does not wish to receive notifications any more the MnS consumer shall delete the corresponding NtfSubscriptionControl instance.

Creation and deletion of NtfSubscriptionControl instances by MnS consumers is optional; when not supported, the NtfSubscriptionControl instances may be created and deleted by the system or be pre-installed.";

```
key id;
uses top3gpp:Top_Grp;
container attributes {
    uses NtfSubscriptionControlGrp;
}

list HeartbeatControl {
    description "MnS consumers (i.e. notification recipients) use heartbeat notifications to monitor the communication channels between them and data reporting MnS producers emitting notifications such as notifyNewAlarm and notifyFileReady.
```

A HeartbeatControl instance allows controlling the emission of heartbeat notifications by MnS producers. The recipients of heartbeat notifications are specified by the notificationRecipientAddress attribute of the NtfSubscriptionControl instance containing the HeartbeatControl instance.

Note that the MnS consumer managing the HeartbeatControl instance and the MnS consumer receiving the heartbeat notifications may not be the same.

As a pre-condition for the emission of heartbeat notifications, a HeartbeatControl instance needs to be created. Creation of an instance with an initial non-zero value of the heartbeatNtfPeriod attribute triggers an immediate heartbeat notification emission. Creation of an instance with an initial zero value of the heartbeatPeriod attribute does not trigger an emission of a heartbeat notification. Deletion of an instance does not trigger an emission of a heartbeat notification.

Once the instance is created, heartbeat notifications are emitted with a periodicity defined by the value of the heartbeatNtfPeriod attribute. No heartbeat notifications are emitted if the value is equal to zero. Setting a zero value to a non zero value, or a non zero value to a different non zero value, triggers an immediate heartbeat notification, that is the base for the new heartbeat period. Setting a non zero value to a zero value stops emitting heartbeats immediately; no final heartbeat notification is sent.

Creation and deletion of HeartbeatControl instances by MnS Consumers is optional; when not supported, the HeartbeatControl instances may be created and deleted by the system or be pre-installed.

Whether and when to emit heartbeat notifications is controlled by HeartbeatControl. Subscription for heartbeat is not supported via the NtfSubscriptionControl.";

```
max-elements 1;
key id;
uses top3gpp:Top_Grp;

container attributes {
```

```

        uses HeartbeatControlGrp;
    }
}
}

<CODE ENDS>
```

## D.2.7 module \_3gpp-common-yang-extensions@2019-06-23.yang

```
module _3gpp-common-yang-extensions {
```

```
    yang-version 1.1;
```

```
    namespace urn:3gpp:sa5:_3gpp-common-yang-extensions ;
    prefix yext3gpp ;
```

```
organization "3GPP SA5";
```

```
description "The module defines YANG extensions needed  
3GPP YANG modeling.
```

```
Copyright (c) 2019 3GPP. All rights reserved.
```

Extensions MUST be defined with the following structure in the description statement:

- What is this statement.
- Newline,
- This statement can be a substatement of the xxx statements with cardinality x..y.
- This statement can have the following substatements with cardinality x..y.
- Newline
- Is changing this statement an editorial, BC(backwards compatible) or NBC(non-BC) change?
- Newline.
- The argument its meaning and type. Preferably use YANG types and constraints to define the argument's type.

Any extension statement can be added with a deviation/deviate add statement. In this case the restriction about the parent statement of the extension SHALL be evaluated based on the target of the deviation statement.

Support for this module does not mean that a YANG server implements support for each of these extensions.

Implementers of each specific module using an extensions MUST check if the server implements support for the used extension.

Note: modules use many extensions which individual implementations MAY or MAY NOT support.

If support for an extension is missing the extension statement needs individual handling or it SHOULD be removed from the module using the extension e.g. with a deviation.

```
";
```

```
revision "2019-06-23" {
    description "Initial version";
}
```

```
extension inVariant {
```

```
    description
```

```
        "Indicates that the value for the data node can only be set when its  
parent data node is being created. To change the value after that, the  
parent data node must be deleted and recreated with the data node  
having the new value.
```

It is unnecessary to use and MUST NOT be used for key leafs.

The statement MUST only be a substatement of a leaf, leaf-list, list statements that is config=true.

Zero or one inVariant statement is allowed per parent statement.  
NO substatements are allowed.

```
Adding this statement is an NBC change, removing it is BC.";
```

```
}
```

```
extension initial-value {
    description "Specifies a value that the system will set for a leaf
```

leaf-list if a value is not specified for it when its parent list or container is created. The value has no effect in any other modification e.g. changing or removing the value.

The description statement of the parent statement SHOULD contain the label 'Initial-value: ' followed by the text from the argument.

The statement MUST only be a substatement of a leaf or leaf-list. The statement MUST NOT be present if the leaf or the leaf-list has a default statement or the type used for the data node has a default value.

The statement MUST NOT be used for config=false data or in an action, rpc or notification.

Zero or one initial-value statements are allowed for a leaf parent statement. Zero or more initial-value statements are allowed for a leaf-list parent statement. If the leaf-list is ordered-by user, the initial values are stored in the order they appear in the YANG definition. NO substatements are allowed.

Always consider using a YANG-default statement instead.

Modification of the initial-value is a non-backwards-compatible change.

The argument specifies a single initial value for a leaf or leaf-list. The value MUST be part of the valuespace of the leaf/leaf-list. It follows the same rules as the argument of the default statement.";

```
    argument "initial-value";
}
}
```

## D.2.8 module \_3gpp-common-yang-types.yang

```
<CODE BEGINS>
module _3gpp-common-yang-types {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-yang-types";
    prefix "types3gpp";

    import ietf-inet-types { prefix inet; }
    import ietf-yang-types { prefix yang; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
    description "The model defines a YANG mapping of the top level
        information classes used for management of 5G networks and
        network slicing.";
    reference "3GPP TS 28.623";

    revision 2022-01-03 { reference "CR-0144"; }
    revision 2021-11-01 { reference "CR-0141"; }

    revision 2021-09-30 {
        description "Added Longitude, Latitude, TenthOfDegrees, OnOff.";
        reference "CR-0138";
    }

    revision 2020-11-06 {
        description "Removed incorrect S-NSSAI definitions.";
        reference "CR-0118";
    }

    revision 2020-03-10 {
        description "Removed faulty when statements.";
        reference "SP-200229";
    }

    revision 2019-10-25 {
        description "Added ManagedNPFProfile.";
        reference "S5-194457";
    }

    revision 2019-10-16 {
        description "Added SAP and usageState.";
        reference "S5-193518";
    }
```

```

revision 2019-06-23 {
    reference "Initial version.";
}

typedef EnabledDisabled {
    type enumeration {
        enum DISABLED ;
        enum ENABLED ;
    }
}

grouping ProcessMonitor {
    description "Provides attributes to monitor the progress of processes
    with specific purpose and limited lifetime running on MnS producers.
    It may be used as data type for dedicated progress monitor attributes
    when specifying the management representation of these processes.
    The attributes in this clause are defined in a generic way.
    For some attributes specialisations may be provided when specifying a
    concrete process representation."
}

```

If a management operation on some IOCs triggers an associated asynchronous process (whose progress shall be monitored), this should also result in creating an attribute named 'processMonitor' (of type 'ProcessMonitor') in these IOC(s). The processMonitor attribute may be accompanied by use-case specific additional data items.

The progress of the process is described by the 'status' and 'progressPercentage' attributes. Additional textual qualifications for the 'status' attribute may be provided by the 'progressStateInfo' and 'resultStateInfo' attributes.

When the process is instantiated, the 'status' is set to 'NOT\_RUNNING' and the 'progressPercentage' to '0'. The MnS producer decides when to start executing the process and to transition into the 'RUNNING' state. This time is captured in the 'startTime' attribute. Alternatively, the process may start to execute directly upon its instantiation. One alternative must be selected when using this data type.

During the 'RUNNING' state the 'progressPercentage' attribute may be repeatedly updated. The exact semantic of this attribute is subject to further specialisation. The 'progressInfo' attribute may be used to provide additional textual information in the 'NOT\_RUNNING', 'CANCELLING' and 'RUNNING' states. Further specialisation of 'progressStateInfo' may be provided where this data type is used.

Upon successful completion of the process, the 'status' attribute is set to 'FINISHED', the 'progressPercentage' to 100%. The time is captured in the 'endTime' attribute. Additional textual information may be provided in the 'resultStateInfo' attribute. The type of 'resultStateInfo' in this data type definition is 'String'. Further specialisation of 'resultStateInfo' may be provided where this data type is used.

In case the process fails to complete successfully, the 'status' attribute is set to 'FAILED' or 'PARTIALLY\_FAILED', the current value of 'progressPercentage' is frozen, and the time captured in 'endTime'. The 'resultStateInfo' specifies the reason for the failure. Specific failure reasons may be specified where the data type defined in this clause is used. The exact semantic of failure may be subject for further specialisation as well.

In case the process is cancelled, the 'status' attribute is first set to 'CANCELLING' and when the process is really cancelled then to 'CANCELLED'. The transition to 'CANCELLED' is captured in the 'endTime' attribute. The value of 'progressPercentage' is frozen. Additional textual information may be provided in the 'resultStateInfo' attribute.

The 'resultStateInfo' attribute is provided only for additional textual qualification of the states 'FINISHED', 'FAILED', 'PARTIALLY\_FAILED' or 'CANCELLED'. It shall not be used for making the outcome, that the process may produce in case of success, available.

The process may have to be completed within a certain time after its creation, for example because required data may not be available any more after a certain time, or the process outcome is needed until a certain time and when not provided by this time is not needed any more.

The time until the MnS producer automatically cancels the process is indicated by the 'timer' attribute.";

```

leaf id {
    type string;
    mandatory true;
    description "Id of the process. It is unique within a single
                 multivalue attribute of type ProcessMonitor.";
}

leaf status {
    type enumeration {
        enum NOT_STARTED ;
        enum RUNNING ;
        enum CANCELLING ;
        enum FINISHED ;
        enum FAILED ;
        enum PARTIALLY_FAILED ;
        enum CANCELLED ;
    }
    config false;
    default RUNNING;
    description "Represents the status of the associated process,
                 whether it fails, succeeds etc.
                 It does not represent the returned values of a successfully finished
                 process. ";
}

leaf progressPercentage {
    type uint8 {
        range 0..100;
    }
    config false;
    description "Progress of the associated process as percentage";
}

leaf-list progressStateInfo {
    type string;
    config false;
    description "Additional textual qualification of the states
                 'NOT_STARTED', 'CANCELLING' and 'RUNNING'.
                 For specific processes, specific well-defined strings (e.g. string
                 patterns or enums) may be defined as a specialisation.";
}

leaf resultStateInfo {
    type string;
    config false;
    description "Additional textual qualification of the states
                 'FINISHED', 'FAILED', 'PARTIALLY_FAILED' and 'CANCELLED'.
                 For example, in the 'FAILED' or 'PARTIALLY_FAILED' state this
                 attribute may be used to provide error reasons.

                 This attribute shall not be used to make the outcome of the process
                 available for retrieval, if any. For this purpose, dedicated
                 attributes shall be specified when specifying the representation of
                 a specific process.

                 For specific processes, specific well-defined strings (e.g. string
                 patterns or enums) may be defined as a specialisation.";
}

leaf startTime {
    type yang:date-and-time;
    config false;
    description "Start time of the associated process, i.e. the time when the
                 status changed from 'NOT_STARTED' to 'RUNNING'.";
}

leaf endTime {
    type yang:date-and-time;
    config false;
    description "Date and time when status changed to 'SUCCESS', 'CANCELLED',
                 'FAILED' or 'PARTIALLY_FAILED'.

                 If the time is in the future, it is the estimated time
                 the process will end.";
}

```

```

}

leaf timer {
    type uint32;
    units minutes;
    description "Time until the associated process is automatically cancelled.
        If set, the system decreases the timer with time. When it reaches zero
        the cancellation of the associated process is initiated by the
        MnS_Producer.
        If not set, there is no time limit for the process.

    Once the timer is set, the consumer can not change it anymore.
    If the consumer has not set the timer the MnS Producer may set it.";
}

// grouping ManagedNFProfile will be removed as it is
// being moved to _3gpp-5gc-nrm-nfprofile
typedef TenthOfDegrees {
    type uint16 {
        range 0..3600;
    }
    units "0.1 degrees";
    description "A single integral value corresponding to an angle in degrees
        between 0 and 360 with a resolution of 0.1 degrees.";
}

typedef Latitude {
    type decimal64 {
        fraction-digits 4;
        range "-90.0000..+90.0000";
    }
    description "Latitude values";
}

typedef Longitude {
    type decimal64 {
        fraction-digits 4;
        range "-180.0000..+180.0000";
    }
    description "Longitude values";
}

typedef OnOff {
    type enumeration {
        enum ON;
        enum OFF;
    }
}

grouping ManagedNFProfile {
    description "Defines profile for managed NF";
    reference "3GPP TS 23.501";

    leaf idx { type uint32 ; }

    leaf nfInstanceID {
        config false;
        mandatory true;
        type yang:uuid ;
        description "This parameter defines profile for managed NF.
            The format of the NF Instance ID shall be a
            Universally Unique Identifier (UUID) version 4,
            as described in IETF RFC 4122 " ;
    }

    leaf-list nfType {
        config false;
        min-elements 1;
        type NfType;
        description "Type of the Network Function" ;
    }

    leaf hostAddr {
        mandatory true;
        type inet:host ;
        description "Host address of a NF";
    }
}

```

```

leaf authzInfo {
    type string ;
    description "This parameter defines NF Specific Service authorization
                 information. It shall include the NF type (s) and NF realms/origins
                 allowed to consume NF Service(s) of NF Service Producer." ;
    reference "See TS 23.501" ;
}

leaf location {
    type string ;
    description "Information about the location of the NF instance
                 (e.g. geographic location, data center) defined by operator";
    reference "TS 29.510" ;
}

leaf capacity {
    mandatory true;
    type uint16 ;
    description "This parameter defines static capacity information
                 in the range of 0-65535, expressed as a weight relative to other
                 NF instances of the same type; if capacity is also present in the
                 nfServiceList parameters, those will have precedence over this value." ;
    reference "TS 29.510" ;
}

leaf nFSrvGroupId {
    type string ;
    description "This parameter defines identity of the group that is
                 served by the NF instance.
                 May be config false or true depending on the ManagedFunction.
                 Config=true for Udrinfo. Config=false for UdmInfo and AusfInfo.
                 Shall be present if ../nfType = UDM or AUSF or UDR. ";
    reference "TS 29.510" ;
}

leaf-list supportedDataSetIds {
    type enumeration {
        enum SUBSCRIPTION;
        enum POLICY;
        enum EXPOSURE;
        enum APPLICATION;
    }
    description "List of supported data sets in the UDR instance.
                 May be present if ../nfType = UDR";
    reference "TS 29.510" ;
}

leaf-list smfServingAreas {
    type string ;
    description "Defines the SMF service area(s) the UPF can serve.
                 Shall be present if ../nfType = UPF";
    reference "TS 29.510" ;
}

leaf priority {
    type uint16;
    description "This parameter defines Priority (relative to other NFs
                 of the same type) in the range of 0-65535, to be used for NF selection;
                 lower values indicate a higher priority. If priority is also present
                 in the nfServiceList parameters, those will have precedence over
                 this value. Shall be present if ../nfType = AMF ";
    reference "TS 29.510" ;
}

typedef usageState {
    type enumeration {
        enum IDLE;
        enum ACTIVE;
        enum BUSY;
    }
    description "It describes whether or not the resource is actively in
                 use at a specific instant, and if so, whether or not it has spare
                 capacity for additional users at that instant. The value is READ-ONLY.";
    reference "ITU T Recommendation X.731";
}

grouping SAP {

```

```

leaf host {
    type inet:host;
    mandatory true;
}
leaf port {
    type inet:port-number;
    mandatory true;
}
description "Service access point.";
reference "TS 28.622";
}

typedef Mcc {
    description "The mobile country code consists of three decimal digits,
    The first digit of the mobile country code identifies the geographic
    region (the digits 1 and 8 are not used):";
    type string {
        pattern '[02-79][0-9][0-9]';
    }
    reference "3GPP TS 23.003 subclause 2.2 and 12.1";
}

typedef Mnc {
    description "The mobile network code consists of two or three
    decimal digits (for example: MNC of 001 is not the same as MNC of 01)";
    type string {
        pattern '[0-9][0-9][0-9]| [0-9][0-9]';
    }
    reference "3GPP TS 23.003 subclause 2.2 and 12.1";
}

grouping PLMNId {
    leaf mcc {
        mandatory true;
        type Mcc;
    }
    leaf mnc {
        mandatory true;
        type Mnc;
    }
    reference "TS 23.658";
}

typedef Nci {
    description "NR Cell Identity. The NCI shall be of fixed length of 36 bits
    and shall be coded using full hexadecimal representation.
    The exact coding of the NCI is the responsibility of each PLMN operator";
    reference "TS 23.003";
    type union {
        type string {
            length 36;
            pattern '[01]+';
        }
        type string {
            length 9;
            pattern '[a-fA-F0-9]*';
        }
    }
}

typedef OperationalState {
    reference "3GPP TS 28.625 and ITU-T X.731";
    type enumeration {
        enum DISABLED {
            value 0;
            description "The resource is totally inoperable.";
        }
        enum ENABLED {
            value 1;
            description "The resource is partially or fully operable.";
        }
    }
}

typedef AdministrativeState {
    reference "3GPP TS 28.625 and ITU-T X.731";
}

```

```

type enumeration {
    enum LOCKED {
        value 0;
        description "The resource is administratively prohibited from performing
                     services for its users.";
    }

    enum UNLOCKED {
        value 1;
        description "The resource is administratively permitted to perform
                     services for its users. This is independent of its inherent
                     operability.";
    }

    enum SHUTTINGDOWN {
        value 2;
        description "Use of the resource is administratively permitted to
                     existing instances of use only. While the system remains in
                     the shutting down state the manager or the managed element
                     may at any time cause the resource to transition to the
                     locked state.";
    }
}

typedef AvailabilityStatus {
    type enumeration {
        enum IN_TEST;
        enum FAILED;
        enum POWER_OFF;
        enum OFF_LINE;
        enum OFF_DUTY;
        enum DEPENDENCY;
        enum DEGRADED;
        enum NOT_INSTALLED;
        enum LOG_FULL;
    }
}

typedef CellState {
    type enumeration {
        enum IDLE;
        enum INACTIVE;
        enum ACTIVE;
    }
}

typedef Nrpcl {
    type uint32;
    description "Physical Cell Identity (PCI) of the NR cell.";
    reference "TS 36.211 subclause 6.11";
}

typedef Tac {
    type int32 {
        range 0..16777215 ;
    }
    description "Tracking Area Code";
    reference "TS 23.003 clause 19.4.2.3";
}

typedef AmfRegionId {
    type union {
        type uint8 ;
        type string {
            length 8;
            pattern '[01]*';
        }
    }
    reference "clause 2.10.1 of 3GPP TS 23.003";
}

typedef AmfSetId {
    type union {
        type uint16 {
            range '0..1023';
        }
        type string {
    }
}

```

```

        length 8;
        pattern '[01]*';
    }
}
reference "clause 2.10.1 of 3GPP TS 23.003";
}

typedef AmfPointer {
    type union {
        type uint8 {
            range '0..63';
        }
        type string {
            length 6;
            pattern '[01]*';
        }
    }
    reference "clause 2.10.1 of 3GPP TS 23.003";
}

grouping AmfIdentifier {
    leaf amfRegionId {
        type AmfRegionId;
    }
    leaf amfSetId {
        type AmfSetId;
    }
    leaf amfPointer {
        type AmfPointer;
    }
    description "The AMFI is constructed from an AMF Region ID,
    an AMF Set ID and an AMF Pointer.
    The AMF Region ID identifies the region,
    the AMF Set ID uniquely identifies the AMF Set within the AMF Region, and
    the AMF Pointer uniquely identifies the AMF within the AMF Set. ";
}

// type definitions especially for core NFs

typedef NfType {
    type enumeration {
        enum NRF;
        enum UDM;
        enum AMF;
        enum SMF;
        enum AUSF;
        enum NEF;
        enum PCF;
        enum SMSF;
        enum NSSF;
        enum UDR;
        enum LMF;
        enum GMLC;
        enum 5G_EIR;
        enum SEPP;
        enum UPF;
        enum N3IWF;
        enum AF;
        enum UDSF;
        enum BSF;
        enum CHF;
    }
}

typedef NotificationType {
    type enumeration {
        enum N1_MESSAGES;
        enum N2_INFORMATION;
        enum LOCATION_NOTIFICATION;
    }
}

typedef Load {
    description "Latest known load information of the NF, percentage ";
    type uint8 {
        range 0..100;
    }
}

```

```

typedef N1MessageClass {
    type enumeration {
        enum 5GMM;
        enum SM;
        enum LPP;
        enum SMS;
    }
}

typedef N2InformationClass {
    type enumeration {
        enum SM;
        enum NRPPA;
        enum PWS;
        enum PWS_BCAL;
        enum PWS_RF;
    }
}

grouping DefaultNotificationSubscription {
    leaf notificationType {
        type NotificationType;
    }

    leaf callbackUri {
        type inet:uri;
    }

    leaf n1MessageClass {
        type N1MessageClass;
    }

    leaf n2InformationClass {
        type N2InformationClass;
    }
}

grouping Ipv4AddressRange {
    leaf start {
        type inet:ipv4-address;
    }

    leaf end {
        type inet:ipv4-address;
    }
}

grouping Ipv6PrefixRange {
    leaf start {
        type inet:ipv6-prefix;
    }

    leaf end {
        type inet:ipv6-prefix;
    }
}

typedef NsiId {
    type string;
}

typedef UeMobilityLevel {
    type enumeration {
        enum STATIONARY;
        enum NOMADIC;
        enum RESTRICTED_MOBILITY;
        enum FULLY_MOBILITY;
    }
}

typedef ResourceSharingLevel {
    type enumeration {
        enum SHARED;
        enum NOT_SHARED;
    }
}

typedef TxDirection {
}

```

```

type enumeration {
    enum DL;
    enum UL;
    enum DL_AND_UL;
}

grouping AddressWithVlan {
    leaf ipAddress {
        type inet:ip-address;
    }
    leaf vlanId {
        type uint16;
    }
}

typedef DistinguishedName {      // TODO is this equivalent to TS 32.300 ?
    type string {
        pattern '([a-zA-Z][a-zA-Z0-9-]*=(\\(( |#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,# ])*
        + '(\\\\(|#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,,])*'
        + '(\\\\(|#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,,])?'
        + '[,\\+]*[a-zA-Z][a-zA-Z0-9-]*=(\\(( |#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,# ])*
        + '(\\\\(|#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,,])?'
        + '|[^\\><;+,,])*(\\\(|#|\\|>|<| |\"|\\+|,|[a-fA-F0-9]{2})|[^\\><;+,,]))?';
    }
}
description "Represents the international standard for the representation
of Distinguished Name (RFC 4512).
The format of the DistinguishedName REGEX is:
{AttributeType = AttributeValue}

AttributeType consists of alphanumeric and hyphen (OIDs not allowed).
All other characters are restricted.
The Attribute value cannot contain control characters or the
following characters : \\> < ; \" + , (Comma) and White space
The Attribute value can contain the following characters if they
are escaped : \\> < ; \" + , (Comma) and White space
The Attribute value can contain control characters if its an escaped
double digit hex number.
Examples could be
    UID=nobody@example.com,DC=example,DC=com
    CN=John Smith,OU=Sales,O=ACME Limited,L=Moab,ST=Utah,C=US";
reference "RFC 4512 Lightweight Directory Access Protocol (LDAP):
          Directory Information Models";
} // recheck regexp it doesn't handle posix [:cntrl:]"

typedef QOffsetRange {
    type int8 {
        range "-24 | -22 | -20 | -18 | -16 | -14 | -12 | -10 | -8 | -6 | " +
               "-5 | -4 | -3 | -2 | -1 | 0 | 1 | 2 | 3 | 4 | 5 | 6 | 8 | 10 | " +
               "12 | 14 | 16 | 18 | 20 | 22 | 24";
    }
    units dB;
}
<CODE ENDS>
```

## D.2.9 module \_3gpp-common-fm.yang

```

<CODE BEGINS>
module _3gpp-common-fm {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-fm";
    prefix "fm3gpp";

    import ietf-yang-types { prefix yang; }
    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-yang-types { prefix types3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Defines a Fault Management model";

    reference "3GPP TS 28.623
              Generic Network Resource Model (NRM)
              Integration Reference Point (IRP);
              Solution Set (SS) definitions"
```

```

3GPP TS 28.622
Generic Network Resource Model (NRM)
Integration Reference Point (IRP);
Information Service (IS)";

revision 2021-08-08 { reference "CR-0132"; }
revision 2021-06-02 { reference "CR-0130"; }
revision 2020-06-03 { reference "CR-0091"; }
revision 2020-02-24 {
    reference "S5-201365";
}

typedef eventType {
    type enumeration {
        enum COMMUNICATIONS_ALARM {
            value 2;
        }

        enum QUALITY_OF_SERVICE_ALARM {
            value 3;
        }

        enum PROCESSING_ERROR_ALARM {
            value 4;
        }

        enum EQUIPMENT_ALARM {
            value 5;
        }

        enum ENVIRONMENTAL_ALARM {
            value 6;
        }

        enum INTEGRITY_VIOLATION {
            value 7;
        }

        enum OPERATIONAL_VIOLATION {
            value 8;
        }

        enum PHYSICAL_VIOLATION {
            value 9;
        }

        enum SECURITY_SERVICE_OR_MECHANISM_VIOLATION {
            value 10;
        }

        enum TIME_DOMAIN_VIOLATION {
            value 11;
        }
    }
}

description "General category for the alarm.";
}

typedef severity-level {
    type enumeration {
        enum CRITICAL { value 3; }
        enum MAJOR { value 4; }
        enum MINOR { value 5; }
        enum WARNING { value 6; }
        enum INDETERMINATE { value 7; }
        enum CLEARED { value 8; }
    }
}

description "The possible alarm severities.
Aligned with ERICSSON-ALARM-MIB.";
}

grouping AlarmRecordGrp {
    description "Contains alarm information of an alarmed object instance.
A new record is created in the alarm list when an alarmed object
instance generates an alarm and no alarm record exists with the same
values for objectInstance, alarmType, probableCause and specificProblem.
"
}

```

When a new record is created the MnS producer creates an alarmId, that unambiguously identifies an alarm record in the AlarmList.

Alarm records are maintained only for active alarms. Inactive alarms are automatically deleted by the MnS producer from the AlarmList.

Active alarms are alarms whose

- a) perceivedSeverity is not CLEARED, or whose
- b) perceivedSeverity is CLEARED and its ackState is not ACKNOWLEDDED.";

```

leaf alarmId {
    type string;
    mandatory true;
    description "Identifies the alarmRecord";
}

leaf objectInstance {
    type string;
    config false ;
    mandatory true;
}

leaf notificationId {
    type int32;
    config false ;
    mandatory true;
}

leaf alarmRaisedTime {
    type yang:date-and-time ;
    config false ;
}

leaf alarmChangedTime {
    type yang:date-and-time ;
    config false ;
    description "not applicable if related alarm has not changed";
}

leaf alarmClearedTime {
    type yang:date-and-time ;
    config false ;
    description "not applicable if related alarm was not cleared";
}

leaf alarmType {
    type eventType;
    config false ;
    description "General category for the alarm.";
}

leaf probableCause {
    type string;
    config false ;
}

leaf specificProblem {
    type string;
    config false ;
    reference "ITU-T Recommendation X.733 clause 8.1.2.2.";
}

leaf perceivedSeverity {
    type severity-level;
    description "This is Writable only if producer supports consumer
        to set perceivedSeverity to CLEARED";
}

leaf backedUpStatus {
    type string;
    config false ;
    description "Indicates if an object (the MonitoredEntity) has a back
        up. See definition in ITU-T Recommendation X.733 clause 8.1.2.4.";
}

leaf backUpObject {
    type string;
    config false ;
}

```

```

leaf trendIndication {
    type string;
    config false ;
    description "Indicates if some observed condition is getting better,
    worse, or not changing. ";
    reference "ITU-T Recommendation X.733 clause 8.1.2.6.";
}

grouping ThresholdPackGrp {
    leaf thresholdLevel {
        type string;
    }
    leaf thresholdValue {
        type string;
    }
    leaf hysteresis {
        type string;
        description "The hysteresis has a threshold high and a threshold
        low value that are different from the threshold value.
        A hysteresis, therefore, defines the threshold-high and
        threshold-low levels within which the measurementType value is
        allowed to oscillate without triggering the threshold crossing
        notification.";
    }
}

grouping ThresholdInfoGrp {
    leaf measurementType {
        type string;
        mandatory true;
    }

    leaf direction {
        type enumeration {
            enum INCREASING;
            enum DECREASING;
        }
        mandatory true;
        description "
            If it is 'Increasing', the threshold crossing notification is
            triggered when the measurement value equals or exceeds a
            thresholdValue.

            If it is 'Decreasing', the threshold crossing notification is
            triggered when the measurement value equals or below a
            thresholdValue.";
    }

    uses ThresholdPackGrp;
}

list thresholdInfo {
    config false ;
    uses ThresholdInfoGrp;
}

leaf stateChangeDefinition {
    type string;
    config false ;
    description "Indicates MO attribute value changes. See definition
    in ITU-T Recommendation X.733 clause 8.1.2.11.";
}

leaf monitoredAttributes {
    type string;
    config false ;
    description "Indicates MO attributes whose value changes are being
    monitored. ";
    reference " ITU-T Recommendation X.733 clause 8.1.2.11.";
}

leaf proposedRepairActions {
    type string;
    config false ;
    description "Indicates proposed repair actions. See definition in
    ITU-T Recommendation X.733 clause 8.1.2.12.";
}

```

```

leaf additionalText {
    type string;
    config false ;
}

anydata additionalInformation {
    config false ;
}

leaf rootCauseIndicator {
    type enumeration {
        enum YES;
        enum NO;
    }
    config false ;
    description "It indicates that this AlarmInformation is the root cause
                 of the events captured by the notifications whose identifiers are in
                 the related CorrelatedNotification instances.";
}

leaf ackTime {
    type yang:date-and-time ;
    config false ;
    description "It identifies the time when the alarm has been
                 acknowledged or unacknowledged the last time, i.e. it registers the
                 time when ackState changes.";
}

leaf ackUserId {
    type string;
    description "It identifies the last user who has changed the
                 Acknowledgement State.";
}

leaf ackSystemId {
    type string;
    description "It identifies the system (Management System) that last
                 changed the ackState of an alarm, i.e. acknowledged or unacknowledged
                 the alarm.";
}

leaf ackState {
    type enumeration {
        enum ACKNOWLEDGED {
            description "The alarm has been acknowledged.";
        }
        enum UNACKNOWLEDGED {
            description "The alarm has unacknowledged or the alarm has never
                         been acknowledged.";
        }
    }
}

leaf clearUserId {
    type string;
    description "Carries the identity of the user who invokes the
                 clearAlarms operation.";
}

leaf clearSystemId {
    type string;
}

leaf serviceUser {
    type string;
    config false ;
    description "It identifies the service-user whose request for service
                 provided by the serviceProvider led to the generation of the
                 security alarm.";
}

leaf serviceProvider {
    type string;
    config false ;
    description "It identifies the service-provider whose service is
                 requested by the serviceUser and the service request provokes the
                 generation of the security alarm.";
}

```

```

        }

leaf securityAlarmDetector {
    type string;
    config false ;
}
}

grouping AlarmListGrp {
    description "Represents the AlarmList IOC.";

leaf administrativeState {
    type types3gpp:AdministrativeState ;
    default LOCKED;
    description "When set to UNLOCKED, the alarm list is updated.
    When the set to LOCKED, the existing alarm records are not
    updated, and new alarm records are not added to the alarm list.";
}

leaf operationalState {
    type types3gpp:OperationalState ;
    default DISABLED;
    config false;
    description "The producer sets this attribute to ENABLED, indicating
    that it has the resource and ability to record alarm in AlarmList
    else, it sets the attribute to DISABLED.";
}

leaf numOfAlarmRecords {
    type uint32 ;
    config false;
    mandatory true;
    description "The number of alarm records in the AlarmList";
}

leaf lastModification {
    type yang:date-and-time ;
    config false;
    description "The last time when an alarm record was modified";
}

list alarmRecords {
    key alarmId;
    description "List of alarmRecords";
    uses AlarmRecordGrp;
}
}

grouping FmSubtree {
    description "Contains FM related classes.
    Should be used in all classes (or classes inheriting from)
    - SubNetwork
    - ManagedElement

    If some YAM wants to augment these classes/list/groupings they must
    augment all user classes!";

list AlarmList {
    key id;
    max-elements 1;
    description "The AlarmList represents the capability to store and manage
    alarm records. The management scope of an AlarmList is defined by all
    descendant objects of the base managed object, which is the object
    name-containing the AlarmList, and the base object itself.

    AlarmList instances are created by the system or are pre-installed.
    They cannot be created nor deleted by MnS consumers.

    When the alarm list is locked or disabled, the existing alarm records
    are not updated, and new alarm records are not added to the alarm list";

    uses top3gpp:Top_Grp ;
    container attributes {
        uses AlarmListGrp ;
    }
}
}

```

```
}
```

<CODE ENDS>

## D.2.10 module \_3gpp-common-trace.yang

```
<CODE BEGINS>
module _3gpp-common-trace {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-trace";
    prefix "trace3gpp";

    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-yang-types {prefix types3gpp; }
    import ietf-inet-types { prefix inet; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";

    description "Trace handling";

    reference "3GPP TS 28.623
Generic Network Resource Model (NRM)
Integration Reference Point (IRP);
Solution Set (SS) definitions

3GPP TS 28.622
Generic Network Resource Model (NRM)
Integration Reference Point (IRP);
Information Service (IS)";

    revision 2022-04-27 { reference "CR-0159"; }
    revision 2021-10-18 { reference "CR-0139"; }
    revision 2021-07-22 { reference "CR-0137"; }
    revision 2021-01-25 { reference "CR-0122"; }
    revision 2020-11-16 { reference "CR-0117"; }
    revision 2020-08-06 { reference "CR-0102"; }

    grouping TraceJobGrp {
        leaf tjJobType {
            type enumeration {
                enum IMMEDIATE_MDT_ONLY;
                enum LOGGED_MDT_ONLY;
                enum TRACE_ONLY;
                enum IMMEDIATE_MDT_AND_TRACE;
                enum RLF_REPORT_ONLY;
                enum RCEF_REPORT_ONLY;
                enum LOGGED_MBSFN_MDT;
            }
            default TRACE_ONLY;
            description "Specifies the MDT mode and it specifies also whether the
TraceJob represents only MDT, Logged MBSFN MDT, Trace or a combined
Trace and MDT job. The attribute is applicable for Trace, MDT, RCEF and
RLF reporting.";
            reference "Clause 5.9a of 3GPP TS 32.422 for additional details on the
allowed values.";
        }
    }

    list tjListOfInterfaces {
        key idx;
        must 'count(MSCServerInterfaces)+count(MGWInterfaces)+count(RNCInterfaces)'+
        '+count(SGSNInterfaces)+count(GGSNInterfaces)+count(S-CSCFInterfaces)'+
        '+count(P-CSCFInterfaces)+count(I-CSCFInterfaces)+count(MRFCInterfaces)'+
        '+count(MGCFInterfaces)+count(IGCFInterfaces)+count(E-CSCFInterfaces)'+
        '+count(BGCFInterfaces)+count(ASInterfaces)+count(HSSInterfaces)'+
        '+count(EIRInterfaces)+count(BM-SCIInterfaces)+count(MMEInterfaces)'+
        '+count(SGWInterfaces)+count(PDN_GWInterfaces)+count(eNBInterfaces)'+
        '+count(en-gNBInterfaces)+count(AMFInterfaces)+count(AUSFInterfaces)'+
        '+count(NEFInterfaces)+count(NRFInterfaces)+count(NSSFInterfaces)'+
        '+count(PCFInterfaces)+count(SMFInterfaces)+count(SMSFInterfaces)'+
        '+count(UDMInterfaces)+count(UPFInterfaces)+count(ng-eNBInterfaces)'+
        '+count(gNB-CU-CPInterfaces)+count(gNB-CU-UPInterfaces)'+
        '+count(gNB-DUInterfaces)';

        description "Specifies the interfaces that need to be traced in the given
ManagedEntityFunction. The attribute is applicable only for Trace. In

```

```

    case this attribute is not used, it carries a null semantic.";
    reference "Clause 5.5 of 3GPP TS 32.422 for additional details on the
    allowed values.";

leaf idx { type uint32 ; }

leaf-list MSCServerInterfaces {
    type enumeration {
        enum A ;
        enum Iu-CS ;
        enum Mc ;
        enum MAP-G ;
        enum MAP-B ;
        enum MAP-E ;
        enum MAP-F ;
        enum MAP-D ;
        enum MAP-C ;
        enum CAP ;
    }
}
leaf-list MGWInterfaces {
    type enumeration {
        enum Mc ;
        enum Nb-UP ;
        enum Iu-UP ;
    }
}
leaf-list RNCInterfaces {
    type enumeration {
        enum Iu-CS ;
        enum Iu-PS ;
        enum Iur ;
        enum Iub ;
        enum Uu ;
    }
}
leaf-list SGSNInterfaces {
    type enumeration {
        enum Gb ;
        enum Iu-PS ;
        enum Gn ;
        enum MAP-Gr ;
        enum MAP-Gd ;
        enum MAP-Gf ;
        enum Ge ;
        enum Gs ;
        enum S6d ;
        enum S4 ;
        enum S3 ;
        enum S13 ;
    }
}
leaf-list GGSNInterfaces {
    type enumeration {
        enum Gn ;
        enum Gi ;
        enum Gmb ;
    }
}
leaf-list S-CSCFInterfaces {
    type enumeration {
        enum Mw ;
        enum Mg ;
        enum Mr ;
        enum Mi ;
    }
}
leaf-list P-CSCFInterfaces {
    type enumeration {
        enum Gm ;
        enum Mw ;
    }
}
leaf-list I-CSCFInterfaces {
    type enumeration {
        enum Cx ;
        enum Dx ;
        enum Mg ;
    }
}
```

```

        enum Mw ;
    }
}
leaf-list MRFCInterfaces {
    type enumeration {
        enum Mp ;
        enum Mr ;
    }
}
leaf-list MGCFInterfaces {
    type enumeration {
        enum Mg ;
        enum Mj ;
        enum Mn ;
    }
}
leaf-list IBCFInterfaces {
    type enumeration {
        enum Ix ;
        enum Mx ;
    }
}
leaf-list E-CSCFInterfaces {
    type enumeration {
        enum Mw ;
        enum M1 ;
        enum Mm ;
        enum Mi-Mg ;
    }
}
leaf-list BGCFInterfaces {
    type enumeration {
        enum Mi ;
        enum Mj ;
        enum Mk ;
    }
}
leaf-list ASInterfaces {
    type enumeration {
        enum Dh ;
        enum Sh ;
        enum ISC ;
        enum Ut ;
    }
}
leaf-list HSSInterfaces {
    type enumeration {
        enum MAP-C ;
        enum MAP-D ;
        enum Gc ;
        enum Gr ;
        enum Cx ;
        enum S6d ;
        enum S6a ;
        enum Sh ;
    }
}
leaf-list EIRInterfaces {
    type enumeration {
        enum MAP-F ;
        enum S13 ;
        enum MAP-Gf ;
    }
}
leaf-list BM-SCIInterfaces {
    type enumeration {
        enum Gmb ;
    }
}
leaf-list MMEInterfaces {
    type enumeration {
        enum S1-MME ;
        enum S3 ;
        enum S6a ;
        enum S10 ;
        enum S11 ;
        enum S13 ;
    }
}

```

```
        }
leaf-list SGWInterfaces {
    type enumeration {
        enum S4 ;
        enum S5 ;
        enum S8 ;
        enum S11 ;
        enum Gxc ;
    }
}
leaf-list PDN_GWInterfaces {
    type enumeration {
        enum S2a ;
        enum S2b ;
        enum S2c ;
        enum S5 ;
        enum S6b ;
        enum Gx ;
        enum S8 ;
        enum SGi ;
    }
}
leaf-list eNBInterfaces {
    type enumeration {
        enum S1-MME ;
        enum X2 ;
    }
}
leaf-list en-gNBInterfaces {
    type enumeration {
        enum S1-MME ;
        enum X2 ;
        enum Uu ;
        enum F1-C ;
        enum E1 ;
    }
}
leaf-list AMFInterfaces {
    type enumeration {
        enum N1 ;
        enum N2 ;
        enum N8 ;
        enum N11 ;
        enum N12 ;
        enum N14 ;
        enum N15 ;
        enum N20 ;
        enum N22 ;
        enum N26 ;
    }
}
leaf-list AUSFInterfaces {
    type enumeration {
        enum N12 ;
        enum N13 ;
    }
}
leaf-list NEFInterfaces {
    type enumeration {
        enum N29 ;
        enum N30 ;
        enum N33 ;
    }
}
leaf-list NRFInterfaces {
    type enumeration {
        enum N27 ;
    }
}
leaf-list NSSFInterfaces {
    type enumeration {
        enum N22 ;
        enum N31 ;
    }
}
leaf-list PCFInterfaces {
    type enumeration {
        enum N5 ;
    }
}
```

```

        enum N7 ;
        enum N15 ;
    }
}
leaf-list SMFInterfaces {
    type enumeration {
        enum N4 ;
        enum N7 ;
        enum N10 ;
        enum N11 ;
        enum S5-C ;
    }
}
leaf-list SMSFInterfaces {
    type enumeration {
        enum N20 ;
        enum N21 ;
    }
}
leaf-list UDMInterfaces {
    type enumeration {
        enum N8 ;
        enum N10 ;
        enum N13 ;
        enum N21 ;
    }
}
leaf-list UPFInterfaces {
    type enumeration {
        enum N4 ;
    }
}
leaf-list ng-eNBInterfaces {
    type enumeration {
        enum NG-C ;
        enum Xn-C ;
        enum Uu ;
    }
}
leaf-list gNB-CU-CPInterfaces {
    type enumeration {
        enum NG-C ;
        enum Xn-C ;
        enum Uu ;
        enum F1-C ;
        enum E1 ;
        enum X2-C ;
    }
}
leaf-list gNB-CU-UPInterfaces {
    type enumeration {
        enum E1 ;
    }
}
leaf-list gNB-DUInterfaces {
    type enumeration {
        enum F1-C ;
    }
}
}

leaf-list tjListOfNeTypes {
    type enumeration {
        enum MSC_SERVER;
        enum SGSN;
        enum MGW;
        enum GGSN;
        enum RNC;
        enum BM_SC;
        enum MME;
        enum SGW;
        enum PGW;
        enum ENB;
        enum EN_GNB;
        enum GNB_CU_CP;
        enum GNB_CU_UP;
        enum GNB_DU;
    }
}

```

```

description "Specifies in which type of ManagedFunction the trace should
be activated. The attribute is applicable only for Trace with
Signalling Based Trace activation. In case this attribute is not used,
it carries a null semantic";
reference "Clause 5.4 of 3GPP TS 32.422 for additional details on the
allowed values";
}

leaf tjPLMNTarget {
    type string;
    mandatory true;
    description "Specifies which PLMN that the subscriber of the session to
be recorded uses as selected PLMN. PLMN Target might differ from the
PLMN specified in the Trace Reference";
    reference "Clause 5.9b of 3GPP TS 32.422";
}

leaf tjStreamingTraceConsumerURI {
    when '../tjTraceReportingFormat = "STREAMING"';
    type inet:uri;
    mandatory true;
    description "URI of the Streaming Trace data reporting MnS consumer
(a.k.a. streaming target).
This attribute shall be present if file based trace data reporting is
supported and tjTraceReportingFormat set to 'file based' or when
tjJobType is set to Logged MDT or Logged MBSFN MDT.";
    reference "Clause 5.9 of 3GPP TS 32.422";
}

leaf tjTraceCollectionEntityAddress {
    when '../tjTraceReportingFormat = "FILE_BASED" or '
        + '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
    type union {
        type inet:uri;
        type inet:ip-address;
    }
    mandatory true;
    description "Specifies the address of the Trace Collection Entity when
the attribute tjTraceReportingFormat is configured for the file-based
reporting. The attribute is applicable for both Trace and MDT.";
    reference "Clause 5.9 of 3GPP TS 32.422";
}

leaf tjTraceDepth {
    when '../tjJobType = "TRACE_ONLY"'
        + ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
    type enumeration {
        enum MINIMUM;
        enum MEDIUM;
        enum MAXIMUM;
        enum VENDORMINIMUM;
        enum VENDORMEDIUM;
        enum VENDORMAXIMUM;
    }
    default MAXIMUM;
    description "Specifies how detailed information should be recorded in the
Network Element. The Trace Depth is a parameter for Trace Session level,
i.e., the Trace Depth is the same for all of the NEs to be traced in
the same Trace Session.
The attribute is applicable only for Trace, otherwise it carries a null
semantic.";
    reference "Clause 5.3 of 3GPP TS 32.422";
}

leaf tjTraceReference {
    type uint64;
    mandatory true;
    description "A globally unique identifier, which uniquely identifies the
Trace Session that is created by the TraceJob.
In case of shared network, it is the MCC and MNC of the Participating
Operator that request the trace session that shall be provided.
The attribute is applicable for both Trace and MDT.";
}

leaf tjTraceRecordSessionReference {
    type string;
    mandatory true;
    description "An identifier, which identifies the Trace Recording Session.

```

```

The attribute is applicable for both Trace and MDT.
See the clause 5.7 of 3GPP TS 32.422 for additional details on the
allowed values.";
```

```

}

leaf tjTraceReportingFormat {
    type enumeration {
        enum FILE_BASED;
        enum STREAMING;
    }
    default FILE_BASED;
    description "Specifies the trace reporting format - streaming trace
                 reporting or file-based trace reporting";
    reference "3GPP TS 32.422 clause 5.11";
}

list tjTraceTarget {
    key "targetIdType targetIdValue";
    max-elements 1;

    leaf targetIdType {
        type enumeration {
            enum IMSI;
            enum IMEI;
            enum IMEISV;
            enum PUBLIC_ID;
            enum UTRAN_CELL;
            enum E_UTRAN_CELL;
            enum NG_RAN_CELL;
            enum ENB;
            enum RNC;
            enum GNB;
            enum SUPI;
        }
    }

    leaf targetIdValue {
        type string;
    }
}

```

description "Specifies the target object of the Trace and MDT. The attribute is applicable for both Trace and MDT. This attribute includes the ID type of the target as an enumeration and the ID value.

The tjTraceTarget shall be public ID in case of a Management Based Activation is done to an ScscfFunction. The tjTraceTarget shall be cell only in case of the UTRAN cell traffic trace function.

The tjTraceTarget shall be E-UtranCell only in case of E-UTRAN cell traffic trace function. The tjTraceTarget shall be either IMSI or IMEI(SV) if the Trace Session is activated to any of the following ManagedEntity(ies):  

- HssFunction
- MscServerFunction
- SgsnFunction
- GgsnFunction
- BmscFunction
- RncFunction
- MmeFunction

The tjTraceTarget shall be IMSI if the Trace Session is activated to a ManagedEntity playing a role of ServinGWFunction.

In case of signaling based Trace/MDT, the tjTraceTarget attribute shall be able to carry (IMSI or IMEI(SV)or SUPI), the tjMDTAreaScope attribute shall be able to carry a list of (cell or E-UtranCell or NRCellDU or TA/LA/RA).

In case of management based Immediate MDT, the tjTraceTarget attribute shall be null value, the tjMDTAreaScope attribute shall carry a list of (Utrancell or E-UtranCell or NRCellDU).

In case of management based Logged MDT, the tjTraceTarget attribute shall carry an eBs or a RNC or gNBs. The Logged MDT should be initiated on the specified eNB or RNC or gNB in tjTraceTarget. The tjMDTAreaScope attribute shall carry a list of (Utrancell or E-UtranCell or NRCellDU or TA/LA/RA).

In case of RLF reporting, or RCEF reporting, the tjTraceTarget

```

attribute shall be null value, the tjMDTAreaScope attribute shall carry
one or list of eNBs/gNBs";
reference "3GPP TS 32.422";
}

leaf tjTriggeringEvent {
when '../tjJobType = "TRACE_ONLY" or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type string;
mandatory true;
description "Specifies the triggering event parameter of the trace session.
The attribute is applicable only for Trace. In case this attribute is
not used, it carries a null semantic.";
reference "Clause 5.1 of 3GPP TS 32.422";
}

leaf tjMDTAnonymizationOfData {
when ../tjMDTAreaScope ;
type enumeration {
enum NO_IDENTITY;
enum TAC_OF_IMEI;
}
default NO_IDENTITY;
description "Specifies level of MDT anonymization.";
reference "3GPP TS 32.422 clause 5.10.12.";
}

list tjMDTAreaConfigurationForNeighCell {
when '../tjJobType = "LOGGED_MDT_ONLY"';
key "idx";
min-elements 1;
leaf idx { type uint32 ; }

description "It specifies the area for which UE is requested to perform
measurement logging for neighbour cells which have list of frequencies.
If it is not configured, the UE shall perform measurement logging for
all the neighbour cells.

Applicable only to NR Logged MDT.";
reference "3GPP TS 32.422 clause 5.10.26.";

leaf frequency {
type string;
}

leaf cell {
type string;
}
}

leaf-list tjMDTAreaScope {
type string;
description "specifies MDT area scope when activates an MDT job.

For RLF and RCEF reporting it specifies the eNB or list of eNBs where the
RLF or RCEF reports should be collected.

List of cells/TA/LA/RA for signaling based MDT or management based Logged
MDT.

List of cells for management based Immediate MDT.

Cell, TA, LA, RA are mutually exclusive.

One or list of eNBs for RLF and RCEF reporting";
reference "Clause 5.10.2 of 3GPP TS 32.422";
}

leaf tjMDTCollectionPeriodRrmLte {
when '../tjJobType = "IMMEDIATE_MDT_ONLY" '
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
range "250|500|1000|2000|3000|4000|6000|8000|12000|16000|20000|
+"24000|28000|32000|64000";
}
units milliseconds;
description "Specifies the collection period for collecting RRM configured
measurement samples for M2, M3 in LTE. The attribute is applicable only

```

```

for Immediate MDT. In case this attribute is not used, it carries a
null semantic.";
reference "Clause 5.10.20 of 3GPP TS 32.422";
}
leaf tjMDTCollectionPeriodM6Lte {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
range "1024|2048|5120|10240";
}
units milliseconds;
description "Specifies the collection period for the Packet Delay
measurement (M6) for MDT taken by the eNB. The attribute is applicable
only for Immediate MDT. In case this attribute is not used,
it carries a null semantic.";
reference "Clause 5.10.32 of TS 32.422 ";
}

leaf tjMDTCollectionPeriodM7Lte {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint16 {
range 1..60 ;
}
description "It specifies the collection period for the Data Volume (M6)
and Throughput measurements (M7) for UMTS MDT taken by RNC. The
attribute is applicable only for Immediate MDT. In case this attribute
is not used, it carries a null semantic.";
reference "Clause 5.10.22 of TS 32.422 .";
}

leaf tjMDTCollectionPeriodRrmUmts {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
range "1024|1280|2048|2560|5120|
+"10240|60000";
}
units milliseconds;
description "Specifies the collection period for collecting RRM configured
measurement samples for M3, M4, M5 in UMTS. The attribute is applicable
only for Immediate MDT. In case this attribute is not used, it carries
a null semantic";
reference "Clause 5.10.21 of 3GPP TS 32.422";
}

leaf tjMDTCollectionPeriodRrmNR {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
range "1024|2048|5120|10240|60000";
}
units milliseconds;
description "Specifies the collection period for collecting RRM
configured measurement samples for M4, M5 in NR. The attribute is
applicable only for Immediate MDT. In case this attribute is not
used, it carries a null semantic.";
reference "Clause 5.10.30 of 3GPP TS 32.422";
}

leaf tjMDTCollectionPeriodM6NR {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type enumeration {
enum 120ms;
enum 240ms;
enum 480ms;
enum 640ms;
enum 1024ms;
enum 2048ms;
enum 5120ms;
enum 10240ms;
enum 20480ms;
enum 40960ms;
enum 1min;
enum 6min;
enum 12min;
enum 30min;
}
}
```

```

        }
        description "It specifies the collection period for the Packet Delay
        measurement (M6) for NR MDT taken by the gNB. The attribute is
        applicable only for Immediate MDT. In case this attribute is not used,
        it carries a null semantic.";
        reference "clause 5.10.34 of TS 32.422";
    }

leaf tjMDTCollectionPeriodM7NR {
    when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
        + ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
    type uint32 {
        range "1..60";
    }
    description "It specifies the collection period for the Packet Loss Rate
    measurement (M7) for NR MDT taken by the gNB. The attribute is
    applicable only for Immediate MDT. In case this attribute is not used,
    it carries a null semantic.";
    reference "clause 5.10.35 of TS 32.422";
}

leaf tjMDTEventListForTriggeredMeasurement {
    when '../tjJobType = "LOGGED_MDT_ONLY"';
    type enumeration {
        enum OUT_OF_COVERAGE ;
        enum A2_EVENT ;
    }
    mandatory true;
    description "Specifies event types for event triggered measurement in the
    case of logged NR MDT. Each trace session may configure at most one
    event. The UE shall perform logging of measurements only upon certain
    condition being fulfilled:
    - Out of coverage.
    - A2 event.";
    reference "Clause 5.10.28 of 3GPP TS 32.422";
}

leaf tjMDTEventThreshold {
    type int64;
    description "Specifies the threshold which should trigger the reporting
    in case A2 event reporting in LTE or 1F/11 event in UMTS. The attribute
    is applicable only for Immediate MDT and when reportingTrigger is
    configured for A2 event in LTE or 1F event or 11 event in UMTS. In
    case this attribute is not used, it carries a null semantic.";
    reference "Clauses 5.10.7 and 5.10.7a of 3GPP TS 32.422";
}

leaf tjMDTListOfMeasurements {
    when '../tjJobType = "IMMEDIATE_MDT_ONLY"';
    type int64;
    mandatory true;
    description "It specifies the UE measurements that shall be collected in
    an Immediate MDT job. The attribute is applicable only for Immediate MDT.
    In case this attribute is not used, it carries a null semantic.";
    reference "3GPP TS 32.422 clause 5.10.3";
}

leaf tjMDTLoggingDuration {
    when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
    type uint32 {
        range "600|1200|2400|3600|5400|7200";
    }
    units seconds;
    mandatory true;
    description "Specifies how long the MDT configuration is valid at the
    UE in case of Logged MDT. The attribute is applicable only for
    Logged MDT and Logged MBSFN MDT. In case this attribute is not used, it
    carries a null semantic.";
    reference "5.10.9 of 3GPP TS 32.422";
}

leaf tjMDTLoggingInterval {
    when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
    type uint32 {
        range "1280|2560|5120|10240|20480|"
            +"30720|40960|61440";
    }
    units milliseconds;
}

```

```

mandatory true;
description "Specifies the periodicity for Logged MDT. The attribute is
    applicable only for Logged MDT and Logged MBSFN MDT. In case this
    attribute is not used, it carries a null semantic";
reference "5.10.8 of 3GPP TS 32.422";
}

leaf tjMDTLoggingEventThreshold {
when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
type uint32 {
    range "0..127";
}
description "It specifies the threshold which should trigger
the reporting in case of event based reporting of logged NR MDT.
The attribute is applicable only for Logged MDT and when tjMDTReportType
is configured for event triggered reporting and when
tjMDTEventListForTriggeredMeasurement is configured for L1 event.
In case this attribute is not used, it carries a null semantic.";
reference "clause 5.10.36 of TS 32.422";
}

leaf tjMDTLoggedHysteresis {
when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
type uint32 {
    range "0..30";
}
description "It specifies the hysteresis used within the entry and leave
condition of the L1 event based reporting of logged NR MDT.
The attribute is applicable only for Logged MDT, when tjMDTReportType
is configured for event triggered reporting and when
tjMDTEventListForTriggeredMeasurement is configured for L1 event.
In case this attribute is not used, it carries a null semantic.";
reference "clause 5.10.37 of TS 32.422";
}

leaf tjMDTLoggedTimeToTrigger {
when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
type int32 ;
description "It specifies the threshold which should trigger
the reporting in case of event based reporting of logged NR MDT.
The attribute is applicable only for Logged MDT, when tjMDTReportType
is configured for event triggered reporting and when
tjMDTEventListForTriggeredMeasurement is configured for L1 event.
In case this attribute is not used, it carries a null semantic.";
reference "clauses 5.10.38 of TS 32.422";
}

leaf-list tjMDTMBSFNAreaList {
when '../tjJobType = "LOGGED_MBSFN_MDT"';
type string;
min-elements 1;
max-elements 8;
description "The MBSFN Area consists of a MBSFN Area ID and Carrier
Frequency (EARFCN). The target MBSFN area List can have up to 8 entries.
This parameter is applicable only if the job type is Logged MBSFN MDT.";
reference "5.10.25 of 3GPP TS 32.422";
}

leaf tjMDTMeasurementPeriodLTE {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
+ ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
    range "1024|1280|2048|2560|5120|"
    +"10240|60000";
}
units milliseconds;
mandatory true;
description "It specifies the measurement period for the Data Volume and
Scheduled IP throughput measurements for MDT taken by the eNB.
The attribute is applicable only for Immediate MDT. In case this
attribute is not used, it carries a null semantic.";
reference "Clause 5.10.23 of 3GPP TS 32.422";
}

leaf tjMDTMeasurementPeriodUMTS {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
+ 'or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint32 {
}

```

```

range "250|500|1000|2000|3000|4000|6000|8000|12000|16000|20000|"
      +"24000|28000|32000|64000";
}
units milliseconds;
mandatory true;
description "It specifies the measurement period for the Data Volume and
Throughput measurements for MDT taken by RNC.
The attribute is applicable only for Immediate MDT. In case this
attribute is not used, it carries a null semantic.";
reference "Clause 5.10.22 of 3GPP TS 32.422";
}

leaf tjMDTMeasurementQuantity {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
  + ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint64 ;
mandatory true;
description "It specifies the measurements that are collected in an MDT
job for a UMTS MDT configured for event triggered reporting.";
reference "Clause 5.10.15 of 3GPP TS 32.422";
}

leaf tjMDTM4ThresholdUmts {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
  + ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type uint16 {
  range 0..31 ;
}
description "It specifies the threshold which should trigger
the reporting in case of event-triggered periodic reporting for M4
(UE power headroom measurement) in UMTS. In case this attribute is
not used, it carries a null semantic.";
reference "3GPP TS 32.422 clause 5.10.A";
}

list tjMDTPLMLList {
when '../tjJobType = "LOGGED_MDT_ONLY"';
key "mcc mnc";
uses types3gpp:PLMNId;
min-elements 1;
max-elements 16;
description "It indicates the PLMNs where measurement collection, status
indication and log reporting is allowed.";
reference "Clause 5.10.24 of 3GPP TS 32.422";
}

leaf tjMDTPositioningMethod {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
  + ' or ../tjJobType = "IMMEDIATE_MDT_AND_TRACE"';
type enumeration {
  enum GNSS;
  enum E_CELL_ID;
}
mandatory true;
description "It specifies what positioning method should be used in the
MDT job.";
reference "Clause 5.10.19 of 3GPP TS 32.422";
}

leaf tjMDTReportAmount {
when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
  + ' and ./tjMDTReportingTrigger = "PERIODICAL"';
type union {
  type uint32 {
    range "1|4|8|16|32|64" ;
  }
  type enumeration {
    enum INFINITY;
  }
}
mandatory true;
description "It specifies the number of measurement reports that shall be
taken for periodic reporting while the UE is in connected.
The attribute is applicable only for Immediate MDT and when
tjMDTReportingTrigger is configured for periodical measurements. In
case this attribute is not used, it carries a null semantic.";
reference "Clause 5.10.6 of 3GPP TS 32.422";
}

```

```

leaf tjMDTReportingTrigger {
    when '../tjJobType = "IMMEDIATE_MDT_ONLY"';
    type enumeration {
        enum PERIODICAL;
        enum A2_FOR_LTE;
        enum 1F_FOR_UMTS;
        enum 1I_FOR_UMTS_MCPS_TDD;
        enum A2_TRIGGERED_PERIODIC_FOR_LTE;
        enum ALL_CONFIGURED_RRM_FOR_LTE;
        enum ALL_CONFIGURED_RRM_FOR_UMTS;
    }
    description "It specifies whether periodic or event based measurements should be collected.
The attribute is applicable only for Immediate MDT and when the tjMDTListOfMeasurements is configured for M1 (for both UMTS and LTE) or M2 (only for UMTS). In case this attribute is not used, it carries a null semantic.";
    reference "Clause 5.10.4 of 3GPP TS 32.422";
}

leaf tjMDTReportInterval {
    when '../tjJobType = "IMMEDIATE_MDT_ONLY"'
        + ' and ../tjMDTReportingTrigger = "PERIODICAL"';
    type uint32 {
        range "120|240|250|480|500|640|1000|1024|2000|2048|3000|4000|"
            +"5120|6000|8000|10240|12000|16000|20000|"
            +"24000|28000|32000|60000|64000|"
            +"360000|720000|1800000|3600000";
    }
    units milliseconds;
    mandatory true;
    description "It specifies the interval between the periodical measurements that shall be taken when the UE is in connected mode.
The attribute is applicable only for Immediate MDT and when tjMDTReportingTrigger is configured for periodical measurements. In case this attribute is not used, it carries a null semantic.";
    reference "5.10.5 of 3GPP TS 32.422";
}

leaf tjMDTReportType {
    when '../tjJobType = "LOGGED_MDT_ONLY"';
    type enumeration {
        enum PERIODICAL;
        enum EVENT_TRIGGERED;
    }
    mandatory true;
    description "It specifies report type for logged NR MDT";
    reference "Clause 5.10.27 of 3GPP TS 32.422";
}

leaf tjMDTSensorInformation {
    type bits {
        bit BAROMETRIC_PRESSURE;
        bit UE_SPEED;
        bit UE_ORIENTATION;
    }
    default "";
    description "It specifies which sensor information shall be included in logged NR MDT and immediate NR MDT measurement if they are available.
The following sensor measurement can be included or excluded for the UE.";
    reference "Clause 5.10.29 of 3GPP TS 32.422";
}

leaf tjMDTTraceCollectionEntityID {
    when '../tjJobType = "LOGGED_MDT_ONLY" or ../tjJobType = "LOGGED_MBSFN_MDT"';
    type uint8;
    mandatory true;
    description "It specifies the TCE Id which is sent to the UE in Logged MDT.";
    reference "Clause 5.10.11 of 3GPP TS 32.422";
}

grouping TraceSubtree {
    description "Contains classes that manage Tracing.
Should be used in all classes (or classes inheriting from)

```

- Subnetwork
- ManagedElement
- ManagedFunction

If a YANG module wants to augment these classes/list/groupings they must augment all user classes!";

```
list TraceJob {
  description "Represents the Trace Control and Configuration parameters of a
               particular Trace Job (see TS 32.421 and TS 32.422 for details).
               It can be name-contained by SubNetwork, ManagedElement, ManagedFunction
               or NetworkSliceSubnet."
```

To activate Trace Jobs, a MnS consumer has to create TraceJob object instances on the MnS producer. A MnS consumer can activate a Trace Job for another MnS consumer since it is not required the value of tjTraceCollectionEntityAddress or tjStreamingTraceConsumerUri to be his own.

When a MnS consumer wishes to deactivate a Trace Job, the MnS consumer shall delete the corresponding TraceJob instance.

For details of management Trace Job activation/deactivation see clause 4.1.1.1.2 of TS 32.422.

The attribute tjJobType specifies the kind of data to collect. Dependent on the selected type various parameters shall be available. The attributes tjJobType, tjTraceReference, tjTraceRecordSessionReference, tjTraceCollectionEntityAddress and tjTraceReportingFormat are mandatory for all job types. If streaming reporting is selected for tjTraceReportingFormat, tjStreamingTraceConsumerURI shall be present additionally. The attribute tjPLMNTarget shall be present if trace activation method is management based.

For the different job types the attributes are differentiated as follows:

- In case of TRACE\_ONLY additionally the following attributes shall be available: tjListOfNeTypes, tjTraceDepth, tjTraceTarget and tjTriggeringEvent.

For this case the optional attribute tjListOfInterfaces allows to specify the interfaces to be recorded.

- In case of IMMEDIATE\_MDT\_ONLY additionally the following attributes shall be available:
  - tjTraceTarget
  - tjMDTAnonymizationOfData,
  - tjMDTListOfMeasurements,
  - tjMDTCollectionPeriodRrmUmts (conditional for M3, M4 and M5 in UMTS),
  - tjMDTMeasurementPeriodUMTS (conditional for M6 and M7 in UMTS),
  - tjMDTCollectionPeriodRrmLte (conditional for M2 and M3 in LTE),
  - tjMDTMeasurementPeriodLTE (conditional for M4 and M5 in LTE),
  - tjMDTCollectionPeriodM6Lte (conditional for M6 in LTE),
  - tjMDTCollectionPeriodM7Lte (conditional for M7 in LTE),
  - tjMDTCollectionPeriodRrmNr (conditional for M4 and M5 in NR),
  - tjMDTCollectionPeriodM6Nr (conditional for M6 in NR),
  - tjMDTCollectionPeriodM7Nr (conditional for M7 in NR),
  - tjMDTReportInterval (conditional for M1 in LTE or NR and M1/M2 in UMTS),
  - tjMDTReportAmount (conditional for M1 in LTE or NR and M1/M2 in UMTS),
  - tjMDTReportingTrigger (conditional for M1 in LTE or NR and M1/M2 in UMTS),
  - tjMDTEventThreshold (conditional for A2 event reporting or A2 event triggered periodic reporting),
  - tjMDTMeasurementQuantity (conditional for 1F event reporting).

For this case the optional attribute tjMDTAreaScope allows to specify the area in terms of cells or Tracking Area/Routing Area/Location area where the MDT data collection shall take place and the optional attributes tjMDTPositioningMethod, tjMDTSensorInformation allow to specify the positioning methods to use or the sensor information to include.

- In case of IMMEDIATE\_MDT\_AND\_TRACE both additional attributes of TRACE\_ONLY and IMMEDIATE\_MDT\_ONLY shall apply.

- In case of LOGGED\_MDT\_ONLY additionally the following attributes shall be available: tjTraceTarget, tjMDTAnonymizationOfData,

```
tjMDTTraceCollectionEntityID, tjMDTLoggingInterval,
tjMDTLoggingDuration, tjMDTReportType,
tjMDTEventListForTriggeredMeasurements.
```

For this case the optional attribute tjMDTAreaScope allows to specify the area in terms of cells or Tracking Area/Routing Area/Location area where the MDT data collection shall take place, the optional attribute tjMDTPLMNLlist allows to specify the PLMNs where measurement collection, status indication and log reporting is allowed, the optional attribute tjMDTAreaConfigurationForNeighCell allows to specify the area for which UE is requested to perform measurements logging for neighbour cells which have list of frequencies and the optional attribute tjMDTSensorInformation allows to specify the sensor information to include.

- In case of RLF\_REPORT\_ONLY and RCEF\_REPORT\_ONLY additionally the attribute tjTraceTarget shall be available, the optional attribute tjMDTAreaScope allows to specify the eNB or list of eNBs or gNB or list of gNBs where the reports should be collected.

- In case of LOGGED\_MBSFN\_MDT additionally the following attributes shall be available: tjMDTAnonymizationOfData, tjMDTLoggingInterval, tjMDTLoggingDuration, tjMDTMBSFNAreaList.

Creation and deletion of TraceJob instances by MnS consumers is optional; when not supported, the TraceJob instances may be created and deleted by the system or be pre-installed.";

```
key id;
uses top3gpp:Top_Grp ;
container attributes {
    uses TraceJobGrp ;
}
}
}
}<CODE ENDS>
```

## D.2.11 module \_3gpp-common-mnsregistry.yang

```
<CODE BEGINS>
module _3gpp-common-mnsregistry {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-mnsregistry";
    prefix "mnsregist3gpp";

    import _3gpp-common-subnetwork { prefix subnet3gpp; }
    import _3gpp-common-top { prefix top3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
    description "Defines the YANG mapping of the MNSRegistry Information Object
    Class (IOC) that is part of the Generic Network Resource Model (NRM).";
    reference "3GPP TS 28.623 Generic Network Resource Model (NRM)";

    revision 2021-10-18 { reference "S5-215263"; }
    revision 2021-08-29 { reference "Initial revision, S5-214388"; }

    grouping MNSInfoGrp {
        description "Represents the MNSInfo IOC.";
        reference "3GPP TS 28.622";
        leaf mnsLabel {
            description "Human-readable name of management service.";
            mandatory true;
            type string;
        }
        leaf mnsType {
            description "Type of management service.";
            type enumeration {
                enum ProvMnS;
                enum FaultSupervisionMnS;
                enum StreamingDataReportingMnS;
                enum FileDataReportingMnS;
            }
        }
    }
}
```

```

leaf mnsVersion {
  description "Version of management service.";
  type string;
}

leaf mnsAddress {
  description "Addressing information for Management Service operations.";
  mandatory true;
  type string;
}

grouping MNSInfo {
  description "Represents the MNSInfo IOC.";
  reference "3GPP TS 28.622";
  uses top3gpp:Top_Grp;
  container attributes {
    uses MNSInfoGrp;
  }
}

grouping MNSRegistryGrp {
  description "Represents the MNSRegistry IOC.";
  reference "3GPP TS 28.622";
  uses top3gpp:Top_Grp;
}

grouping MNSRegistry {
  list mnsRegistry {
    description "Represents the MNSRegistry IOC.";
    reference "3GPP TS 28.622";
    uses top3gpp:Top_Grp;
    key "mnsType mnsVersion mnsAddress";
    container attributes {
      uses MNSInfoGrp;
    }
  }
}

augment "/subnet3gpp:SubNetwork" {
  uses MNSRegistryGrp;
}

}

<CODE ENDS>

```

## D.2.12 module \_3gpp-common-mnsregistry.yang

```

<CODE BEGINS>
module _3gpp-common-mnsregistry {
  yang-version 1.1;
  namespace "urn:3gpp:sa5:_3gpp-common-mnsregistry";
  prefix "mnsregist3gpp";

  import _3gpp-common-subnetwork { prefix subnet3gpp; }
  import _3gpp-common-top { prefix top3gpp; }
  import _3gpp-common-yang-types { prefix types3gpp; }

  organization "3GPP SA5";
  contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
  description "Defines the YANG mapping of the MNSRegistry Information Object
               Class (IOC) that is part of the Generic Network Resource Model (NRM).";
  reference "3GPP TS 28.623 Generic Network Resource Model (NRM)";

  revision 2021-11-23 { reference "S5-216090"; }
  revision 2021-10-18 { reference "S5-215263"; }
  revision 2021-08-29 { reference "Initial revision, S5-214388"; }

  grouping MNSInfoGrp {
    description "Represents the MNSInfo IOC.";
    reference "3GPP TS 28.622";
    leaf mnsLabel {
      description "Human-readable name of management service.";
      mandatory true;
      type string;
  }
}

```

```

leaf mnsType {
    description "Type of management service.";
    type enumeration {
        enum ProvMnS;
        enum FaultSupervisionMnS;
        enum StreamingDataReportingMnS;
        enum FileDataReportingMnS;
    }
}

leaf mnsVersion {
    description "Version of management service.";
    type string;
}

leaf mnsAddress {
    description "Addressing information for Management Service operations.";
    mandatory true;
    type string;
}

leaf-list mnsScope {
    description "List of the managed object instances that can be accessed using the MnS. If a complete SubNetwork can be accessed using the MnS, this attribute may contain the DN of the SubNetwork instead of the DNs of the individual managed entities within the SubNetwork.";
    min-elements 1;
    type types3gpp:DistinguishedName;
}

augment "/subnet3gpp:SubNetwork" {
    list MNSRegistry {
        description "Represents the MNSRegistry IOC.";
        reference "3GPP TS 28.622";
        uses top3gpp:Top_Grp;
        key id;
        max-elements 1;
        list MNSInfo {
            description "Represents the MNSInfo IOC.";
            reference "3GPP TS 28.622";
            uses top3gpp:Top_Grp;
            key "mnsType mnsVersion mnsAddress";
            uses MNSInfoGrp;
        }
    }
}
<CODE ENDS>

```

## D.2.13 module \_3gpp-common-filemanagement.yang

```

<CODE BEGINS>
module _3gpp-common-filemanagement {
    yang-version 1.1;
    namespace "urn:3gpp:sa5:_3gpp-common-filemanagement";
    prefix "filemgmt3gpp";

    import _3gpp-common-subnetwork { prefix subnet3gpp; }
    import _3gpp-common-top { prefix top3gpp; }
    import _3gpp-common-yang-types { prefix yang3gpp; }
    import _3gpp-common-managed-element { prefix me3gpp; }

    organization "3GPP SA5";
    contact "https://www.3gpp.org/DynaReport/TSG-WG--S5--officials.htm?Itemid=464";
    description "Defines the YANG mapping of the FileDownloadJob Information Object Class (IOC) that is part of the Generic Network Resource Model (NRM).";
    reference "3GPP TS 28.623 Generic Network Resource Model (NRM)";

    revision 2022-02-10 { reference "Initial revision, S5-221757"; }

    grouping FileDownloadProcessMonitor {
        description "Provides specialisations of the ProcessMonitor datatype.";
        uses yang3gpp:ProcessMonitor {
            refine resultStateInfo {

```

```

        description "If status is FAILED resultStateInfo will be one of
        the following or empty.";
        must '.. /status != \"FAILED\"'
        or . = "UNKNOWN"
        or . = "NO_STORAGE"
        or . = "LOW_MEMORY"
        or . = "NO_CONNECTION_TO_REMOTE_SERVER"
        or . = "FILE_NOT_AVAILABLE"
        or . = "DNS_CANNOT_BE_RESOLVED"
        or . = "TIMER_EXPIRED"
        or . = "OTHER"
        or . = "NULL" ';
    }
    refine status {
        description "Status must not be 'PARTIALLY_FAILED'.";
        must '. != \"PARTIALLY_FAILED\" ';
    }
}
}

grouping FileDownloadJobGrp {
    description "Represents the FileDownloadJob IOC.";
    reference "3GPP TS 28.622";
    uses top3gpp:Top_Grp;

    leaf fileLocation {
        description "Provides the location of a file.
        allowedValues: File URI (See RFC 8089)";
        mandatory true;
        type string;
    }

    leaf notificationRecipientAddress {
        description "Address of the notification recipient.";
        type string;
    }

    leaf cancelJob {
        description "Setting this attribute to TRUE cancels the file download job.
        As specified in the definition of ProcessMonitor, cancellation is possible in
        the NOT_STARTED and RUNNING state. Setting the attribute to FALSE has no
        observable result.";
        type boolean;
        mandatory true;
    }

    list jobMonitor {
        key "id";
        description "Provides monitoring for the file download job.";
        uses FileDownloadProcessMonitor;
    }
}

grouping FileDownloadJobSubtree {
    description "Helps augmenting FileDownloadJob into multiple places.";
    list FileDownloadJob {
        description "Specifies the FileDownloadJob IOC, see 3GPP TS 28.622.";
        key "id";
        uses top3gpp:Top_Grp;
        container attributes {
            uses FileDownloadJobGrp;
        }
    }
}

augment "/subnet3gpp:SubNetwork" {
    uses FileDownloadJobSubtree;
}

augment "/me3gpp:ManagedElement" {
    uses FileDownloadJobSubtree;
}
}

<CODE ENDS>
```

---

## D.3 Void

---

## Annex E (informative): Change history

Change history								
Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New	
2012-12					New version after approval	2.0.0	11.0.0	
2013-06	SA#60	SP-130304	002	2	Correction of XML schema	11.0.0	11.1.0	
2014-06	SA#64	SP-140332	003	1	upgrade XSD	11.1.0	11.2.0	
		SP-140358	004	-	remove the feature support statements			
2014-09	SA#65	SP-140560	005	-	Update the link from Solution Set to Information Service due to the end of Release 12	11.2.0	12.0.0	
2015-12	SA#70	SP-150691	006	1	Add missing id attribute	12.0.0	12.1.0	
2016-01					Upgrade to Rel-13 (MCC)	12.1.0	13.0.0	
2016-03	SA#71	SP-160031	010	1	Make the XML schema well formed	13.0.0	13.1.0	

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2016-06	SA#72	SP-160407	0011	-	F	Update the link from IRP Solution Set to IRP Information Service	13.2.0
2017-03	SA#75	-	-	-	-	Promotion to Release 14 without technical change	14.0.0
2017-06	SA#76	SP-170510	0015	2	B	Modifications to align with IS to support Configuration Management for mobile networks that include virtualized network functions	14.1.0
2018-03	SA#79	SP-180060	0016	1	B	Add attribute peeParametersList to Solution Set definitions	15.0.0
2018-12	SA#82	SP-181042	0018	1	F	Update NRM root IOCs Solution Set to support priority	15.1.0
2019-03	SA#83	SP-190121	0020	1	F	Update Generic NRM Solution Set to support JSON	15.2.0
2019-06	SA#84	SP-190371	0021	-	B	Add IOCs for threshold monitoring control	16.0.0
2019-09	SA#85	SP-190745	0026	1	F	generate JSON definition for generic NRM based on new style guideline	16.1.0
2019-09	SA#85	SP-190744	0027	-	A	Add IDL XML YANG solutions	16.1.0
2019-09	SA#85	SP-190751	0029	-	A	Correct references and remove not need abbreviations	16.1.0
2019-12	SA#86	SP-191166	0031	1	F	Correct XML solution set for generic NRM	16.2.0
2019-12	SA#86	SP-191166	0035	-	B	Updates to YANG SS	16.2.0
2019-12	SA#86	SP-191173	0037	1	A	Add the definition of attribute measurementsList	16.2.0
2019-12	SA#86	SP-191166	0039	-	B	Add heartbeat control NRM fragment - Stage 3	16.2.0
2019-12	SA#86	SP-191166	0040	-	B	Add notification subscription control NRM fragment - Stage 3	16.2.0
2020-03	SA#87E	SP-200163	0041	2	B	Add configurable KPI control NRM	16.3.0
2020-03	SA#87E	SP-200163	0042	-	B	Add configurable FM - YANG Solution	16.3.0
2020-03	SA#87E	SP-200230	0043	1	F	Add OpenAPI definitions required by the ProvMnS	16.3.0
2020-03	SA#87E	SP-200169	0045		F	Correct errors in yang solution set	16.3.0
2020-03	SA#87E					Correction in the implementation of CR0041	16.3.1
2020-03	SA#87E					Correction of implementation	16.3.2
2020-07	SA#88E	SP-200490	0046	2	B	Add OpenAPI definitions for the FM control fragment	16.4.0
2020-07	SA#88E	SP-200489	0047	-	F	Correct OpenAPI definition for notificationTypes	16.4.0
2020-07	SA#88E	SP-200483	0079	2	B	Add trace control NRM fragment stage 3	16.4.0
2020-07	SA#88E	SP-200484	0080	-	D	Fix inconsistent formatting	16.4.0
2020-07	SA#88E	SP-200493	0081	-	B	Stage3 add the NRM fragment for SON management	16.4.0
2020-07	SA#88E	SP-200485	0082	-	F	Update the definition of SNssai	16.4.0
2020-07	SA#88E	SP-200490	0084	-	F	Update ManagedElement YANG moduel	16.4.0
2020-07	SA#88E	SP-200596	0085	1	F	Update Nrm YANG	16.4.0
2020-07	SA#88E	SP-200490	0087	2	F	Update PM control fragment (OpenAPI definitions)	16.4.0
2020-07	SA#88E	SP-200490	0088	-	F	Clarify usage of the VsDataContainer (OpenAPI definitions)	16.4.0
2020-07	SA#88E	SP-200490	0089	-	F	Add common data definitions (OpenAPI definitions)	16.4.0
2020-07	SA#88E	SP-200490	0091	-	F	Update FM control fragment (YANG definitions)	16.4.0
2020-07	SA#88E	SP-200490	0092	-	F	Update PM Control fragment (YANG definitions)	16.4.0
2020-07	SA#88E	SP-200490	0093	1	F	Correct genericNRM definition in XML solution	16.4.0
2020-09	SA#89e	SP-200729	0095	-	F	Correction of YANG errors	16.5.0
2020-09	SA#89e	SP-200727	0101	1	A	Clean-up definitions and references	16.5.0
2020-09	SA#89e	SP-200729	0102	-	B	YANG SS for Trace Control	16.5.0
2020-09	SA#89e	SP-200724	0103	-	F	Add missing definitions to comDefs.yaml (OpenAPI definitions)	16.5.0
2020-09	SA#89e	SP-200724	0104	-	F	Correct various smaller errors (e.g. validation errors) in genericNRM.yaml (OpenAPI definitions)	16.5.0
2020-09	SA#89e	SP-200729	0105	1	F	Correct ThresholdMonitor definition (OpenAPI definitions)	16.5.0
2020-09	SA#89e	SP-200729	0106	-	F	Update HeartbeatControl YANG definition	16.5.0
2020-09	SA#89e	SP-200729	0107	-	F	Update ThresholdMonitor YANG definition	16.5.0
2020-12	SA#90e	SP-201057	0108	-	F	Correction of NRM YANG errors	16.6.0
2020-12	SA#90e	SP-201063	0109	1	F	Add new MDT specific parameter collection period for NR aligning with 28.622 for stage 3	16.6.0
2020-12	SA#90e	SP-201057	0110	-	F	Remove thresholdLevel attribute from ThresholdMonitor (OpenAPI definition)	16.6.0
2020-12	SA#90e	SP-201050	0111	1	F	Correct and add types in comDefs.yaml (OpenAPI definition)	16.6.0
2020-12	SA#90e	SP-201050	0112	1	F	Use comDefs.yaml instead of local definitions in genericNrm.yaml (OpenAPI definition)	16.6.0
2020-12	SA#90e	SP-201057	0113	1	F	Update attribute perfMetricJobGroupId.	16.6.0
2020-12	SA#90e	SP-201057	0114	-	F	Remove value handling from the granularityPeriod description	16.6.0
2020-12	SA#90e	SP-201088	0115	-	F	Correct and add types in comDefs.yaml (OpenAPI definition)	16.6.0
2020-12	SA#90e	SP-201063	0117		F	Correct trace target parameter for trace control in stage 3	16.6.0
2020-12	SA#90e	SP-201089	0118	1	F	Remove incorrect S-NSSAI definition from YANG SS	16.6.0
2021-03	SA#91e	SP-210146	0121	-	F	Fix compilation errors	16.7.0
2021-03	SA#91e	SP-210153	0125	-	F	YANG compilation error and missing stage 2 corrections	16.7.0
2021-06	SA#92e	SP-210406	0119	2	F	Replace legacy IRP Agent with MnsAgent (OpenAPI definition)	16.8.0
2021-06	SA#92e	SP-210397	0127	1	F	Correction of Trace/MDT related parameters (OpenAPI definition)	16.8.0

2021-06	SA#92e	SP-210397	0128	1	F	Align Trace/MDT related parameters to TS 32.422 (OpenAPI definition)	16.8.0
2021-06	SA#92e	SP-210406	0129	1	F	Clean up regarding common data types (OpenAPI definition)	16.8.0
2021-06	SA#92e	SP-210411	0130	-	F	Correct definition of additionalInformation (YANG)	16.8.0
2021-09	SA#93e	SP-210886	0131	1	F	Replace local data type definition for notificationFilter by common filter definition	16.9.0
2021-09	SA#93e	SP-210886	0132	1	F	Correct data type of notificationId (YANG definitions)	16.9.0
2021-09	SA#93e	SP-210886	0133	1	F	Clarify resource id is required and nullable (OpenAPI definitions)	16.9.0
2021-09	SA#93e	SP-210865	0134	-	F	Correction and clarification of reporting in TraceJob (stage3)	16.9.0
2021-09	SA#93e	SP-210865	0135	-	F	Adaptation and cleanup of Trace/MDT related parameters (stage3)	16.9.0
2021-09	SA#93e	SP-210871	0136	-	F	YANG updates to correct YANG merging problems	16.9.0
2021-09	SA#93e	SP-210867	0137	1	F	Correction of YANG Solution set	16.9.0
2021-12	SA#94e	SP-211475	0139	1	F	Correction of YANG Solution set	16.10.0
2021-12	SA#94e	SP-211458	0142	-	F	Introduce missing IEs for HSS and UDM Trace Record	16.10.0
2021-12	SA#94e	SP-211465	0138	1	B	Add new common types for YANG	17.0.0
2021-12	SA#94e	SP-211467	0140	-	B	Add support for MnS Discovery	17.0.0
2021-12	SA#94e	SP-211473	0141	-	B	Add new common types for YANG	17.0.0
2022-03	SA#95e	SP-220168	0144	1	C	Asynchronous operation NRM additions - YANG Stage-3	17.1.0
2022-03	SA#95e	SP-220177	0146	1	B	Enhance NRM with geographical information supporting MDA	17.1.0
2022-03	SA#95e	SP-220163	0147	1	B	Add support for discovery of managed entities	17.1.0
2022-03	SA#95e	SP-220183	0148	-	B	Add file retrieval NRM fragment (OpenAPI definitions)	17.1.0
2022-03	SA#95e	SP-220183	0149	1	B	Add file download NRM fragment (OpenAPI definitions)	17.1.0
2022-03	SA#95e	SP-220171	0153	-	B	Add parameter to configure beam level measurements in NR MDT	17.1.0
2022-03	SA#95e	SP-220183	0154	-	B	Add attribute to configure an identifier of a TraceJob	17.1.0
2022-03	SA#95e	SP-220187	0156	-	B	Add file download NRM fragment (YANG)	17.1.0
2022-06	SA#96	SP-220498	0159	-	A	Stage 3 Yang fix for 3GPP Common Trace	17.2.0
2022-06	SA#96	SP-220498	0162	1	A	OpenAPI file name and dependence change for comDefs.yaml	17.2.0
2022-06	SA#96	SP-220498	0163	1	A	OpenAPI file name and dependence change for genericNrm.yaml	17.2.0
2022-06	SA#96	SP-220498	0166	-	A	yaml indentation correction for comDefs.yaml	17.2.0
2022-06	SA#96	SP-220516	0168	-	A	Alignment of attribute names of TraceJob IOC to TS 32.422 (stage 3)	17.2.0
2022-06	SA#96	SP-220496	0169	-	F	Fix description of attribute mnsScope	17.2.0
2022-06	SA#96	SP-220516	0174	-	A	Alignment of attribute values of attribute tjMDTReportInterval to TS 32.422, TS 38.413 and TS 38.423	17.2.0
2022-06	SA#96	SP-220505	0175	-	B	Add stage 3 for management data collection and discovery (OpenAPI definitions)	17.2.0
2022-06	SA#96					Correction of implementation in D.2.10	17.2.1
2022-06	SA#96					Further corrections on the changes in the code from the annexes	17.2.2

---

## History

<b>Document history</b>		
V17.1.0	May 2022	Publication
V17.2.2	July 2022	Publication