

ETSI TS 138 522 V16.7.0 (2021-04)



**5G;
NR;**

**User Equipment (UE) conformance specification;
Applicability of radio transmission, radio reception and radio
resource management test cases
(3GPP TS 38.522 version 16.7.0 Release 16)**



Reference

RTS/TSGR-0538522vg70

Keywords

5G

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<http://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2021.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	4
1 Scope	5
2 References	5
3 Definitions, symbols and abbreviations	6
3.1 Definitions	6
3.2 Symbols.....	7
3.3 Abbreviations	7
4 Recommended test case applicability.....	7
4.0 Test case conditions and selection criteria.....	8
4.1 RF conformance test cases	15
4.1.1 FR1 standalone conformance test cases.....	16
4.1.2 FR2 standalone conformance test cases.....	28
4.1.3 NR interworking between NR FR1 and NR FR2 and between NR and LTE conformance test cases.....	36
4.1.4 Performance conformance test cases	60
4.2 RRM conformance test cases	65
Annex A (informative): Change history	88
History	91

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

The present document is one part of a multi-part Technical Specification (TS) covering the New Radio (NR) User Equipment (UE) conformance specification, which is divided in the following parts:

3GPP TS 38.521-1 [1]: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone;

3GPP TS 38.521-2 [2]: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Range 2 Standalone;

3GPP TS 38.521-3 [3]: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios;

3GPP TS 38.521-4 [4]: NR; User Equipment conformance specification; Radio transmission and reception; Part 4: Performance;

3GPP TS 38.522: NR; User Equipment (UE) conformance specification; Applicability of RF and RRM test cases;

3GPP TS 38.533 [5]: NR; User Equipment (UE) conformance specification; Radio resource management;

1 Scope

The present document specifies the recommended applicability statement and completion status for the test cases included in 3GPP TS 38.521-1 [1], TS 38.521-2 [2], TS 38.521-3 [3], TS 38.521-4 [4] and TS 38.533 [5]. These applicability statements are based on the features implemented in the UE.

Special conformance testing functions can be found in 3GPP TS 38.509 [6] and the common test environments are included in 3GPP TS 38.508-1 [7]. Common implementation conformance statement (ICS) proforma can be found in 3GPP TS 38.508-2 [8].

The present document is valid for UE implemented according to 3GPP releases starting from Release 15 up to the Release indicated on the cover page of the present document.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document in the same Release as the present document unless the context in which the reference is made suggests a different Release is relevant (information on the applicable release in a particular context can be found in e.g. test case title, description or applicability, message description or content).

- [1] 3GPP TS 38.521-1: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone
- [2] 3GPP TS 38.521-2: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Range 2 Standalone
- [3] 3GPP TS 38.521-3: NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios
- [4] 3GPP TS 38.521-4: NR; User Equipment conformance specification; Radio transmission and reception; Part 4: Performance
- [5] 3GPP TS 38.533: NR; User Equipment (UE) conformance specification; Radio resource management
- [6] 3GPP TS 38.509: 5GS; Special conformance testing functions for User Equipment (UE)
- [7] 3GPP TS 38.508-1: 5GS; User Equipment (UE) conformance specification; Part 1: Common test environment
- [8] 3GPP TS 38.508-2: 5GS; User Equipment (UE) conformance specification; Part 2: Common Implementation Conformance Statement (ICS) proforma
- [9] 3GPP TR 21.905: Vocabulary for 3GPP Specifications
- [10] 3GPP TS 36.521-2: Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Implementation Conformance Statement (ICS)
- [11] 3GPP TS 38.331: "NR; Radio Resource Control (RRC) protocol specification".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [9] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [9].

EIRP(Link=Link angle, Meas=Link angle): measurement of the UE such that the link angle is aligned with the measurement angle. EIRP (indicator to be measured) can be replaced by EIS, Frequency, EVM, carrier Leakage, In-band emission and OBW. Beam peak search grids, TX beam peak direction, and RX beam peak direction can be selected to describe Link.

EIRP(Link=Link angle, Meas=beam peak direction): measurement of the EIRP of the UE such that the measurement angle is aligned with the beam peak direction within an acceptable measurement error uncertainty.

Implementation Conformance Statement (ICS): statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented

ICS proforma: document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS

Implementation extra Information for Testing (IXIT): A statement made by a supplier or implementer of an UEUT which contains or references all of the information (in addition to that given in the ICS) related to the UEUT and its testing environment, which will enable the test laboratory to run an appropriate test suite against the UEUT

Inter-band carrier aggregation: Carrier aggregation of component carriers in different operating bands.

NOTE: Carriers aggregated in each band can be contiguous or non-contiguous.

Intra-band contiguous carrier aggregation: Contiguous carriers aggregated in the same operating band.

Intra-band non-contiguous carrier aggregation: Non-contiguous carriers aggregated in the same operating band.

IXIT proforma: A document, in the form of a questionnaire, which when completed for an UEUT becomes an IXIT

Protocol Implementation Conformance Statement (PICS): An ICS for an implementation or system claimed to conform to a given protocol specification

Protocol Implementation eXtra Information for Testing (PIXIT): An IXIT related to testing for conformance to a given protocol specification

Static conformance review: A review of the extent to which the static conformance requirements are claimed to be supported by the UEUT, by comparing the answers in the ICS(s) with the static conformance requirements expressed in the relevant specification(s)

TRP(Link=Link angle): measurement of the TRP of the UE such that the measurement angle is aligned with the beam peak direction within an acceptable measurement uncertainty. TX beam peak direction and RX beam peak direction can be selected to describe Link.

NOTE: For requirements based on EIRP/EIS, the radiated interface boundary is associated to the far-field region

3.2 Symbols

No specific symbols have been identified so far.

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [9] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [9].

For the purposes of the present document, the following abbreviations apply:

CA	Carrier Aggregation
EN-DC	E-UTRA NR-Dual Connection
FR1	Frequency Range 1 (410 MHz - 7125 MHz)
FR2	Frequency Range 2 (24250 MHz - 52600 MHz)
HST	High Speed Train
ICS	Implementation Conformance Statement
IXIT	Implementation eXtra Information for Testing
NR	New Radio
PIXIT	Protocol Implementation eXtra Information for Testing
SCS	System Conformance Statement
SUL	Supplementary UpLink
TC	Test Case
TRP	Total Radiated Power
UEUT	User Equipment Under Test

4 Recommended test case applicability

The applicability of each individual test is identified in the tables 4.1.1-1 / 4.1.2-1 / 4.1.3-1 / 4.1.4-1 / 4.2-1 / 4.2-2 / 4.2-3 / 4.2-4. This is just a recommendation based on the purpose for which the test case was written.

The applicability of every test is formally expressed by the use of Boolean expressions that are based on parameters (ICS). The parameters (ICS) included in TS 38.508-2 [8] are used in the test case applicability condition without reference. Parameters (ICS) specified in TS 36.521-2 [10] shall be referred with proper reference.

Selection criteria of tested bands and tested CA configurations for each applicable test is formally expressed using group theory based on parameters (ICS) included in annex A of TS 38.508-2 [8] without reference.

Additional information related to the Test Case (TC), e.g. affecting its dynamic behaviour or its execution may be provided as well.

The columns in tables 4.1.1-1 / 4.1.2-1 / 4.1.3-1 / 4.1.4-1 / 4.2-1 / 4.2-2 / 4.2-3 / 4.2-4 have the following meaning:

Clause

The clause column indicates the clause number in TS 38.521-1 [1], TS 38.521-2 [2], TS 38.521-3 [3], TS 38.521-4 [4] and TS 38.533 [5] that contains the test body.

TC Title

The TC Title column describes the name of the test and contains the clause title of the clause in TS 38.521-1 [1], TS 38.521-2 [2], TS 38.521-3 [3], TS 38.521-4 [4] and TS 38.533 [5] that contains the test body.

Release

The release column indicates the earliest release from which each test case is applicable. It may also indicate a range of releases or a single release to which a test case is applicable.

Applicability - Condition

The following notations are used for the applicability column:

R	recommended - the test case is recommended to all terminals supporting NR
O	optional - the test case is optional
N/A	not applicable - in the given context, the test case is not recommended.
C _i	conditional - the test is recommended ("R") or not ("N/A") depending on the support of other items. "i" is an integer identifying a unique conditional status expression which is defined in Table 4.0-1. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." is used to avoid ambiguities.

Applicability - Comment

This comment column contains a verbal description of the condition included in the applicability column.

Tested Bands / CA/DC Configurations Selection

This column defines a set of bands / CA/DC Configurations the test is to be run for, if the test is applicable. If the set is empty, the test is considered as not applicable.

The following notations are used in the tested bands selection column:

D _i	Derive the set based on Band Selection Criteria D _i defined in table 4.0-2.
E _i	Derive the set based on CA/DC Configurations Selection Criteria E _i defined in table 4.0-3.
TBD	Band selection not defined at this time, in the meantime test all Bands / CA/DC Configurations
Text	For more complex selection criteria, or if the criteria are already specified somewhere else in the spec, text reference to the clause is given.

Branch

This column contains indication if the test case may perform differently depending on the UE capabilities.

NOTE 1: Void.

NOTE 2: Void.

Additional Information

This column contains indication if the test case may perform differently depending on the UE capabilities and the measurement execution.

This column also contains indication of the completion status of the test case.

4.0 Test case conditions and selection criteria

For the purposes of the present document, the applicability of conformance test cases conditions given in Table 4.0-1 apply. The ICS proformas used in Table 4.0-1, Table 4.0-2 and Table 4.0-3 are defined in TS 38.508-2 [8] unless otherwise stated.

Table 4.0-1: Applicability of conformance test cases conditions

C001	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 THEN R ELSE N/A
C001a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.3.1-7/3 THEN R ELSE N/A
C001b	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.3.5-1/1 THEN R ELSE N/A
C002	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-2/3 OR A.4.1-2/5) THEN R ELSE N/A
C003	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.3.2-1/14 OR A.4.3.2-1/15) THEN R ELSE N/A
C004	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4A/5) AND A.4.3.2A.1-2/1 THEN R ELSE N/A
C005	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.1-4A/5 AND A.4.1-2/4 AND A.4.3.2A.1-1/1 AND A.4.1-3/1 THEN R ELSE N/A
C006	IF A.4.1-1/2 AND A.4.1-2/8 AND (A.4.1-3/1) THEN R ELSE N/A
C006a	IF A.4.1-1/2 AND A.4.1-2/8 AND (A.4.1-3/1 OR A.4.1-3/4) AND A.4.3.5-1/1 THEN R ELSE N/A
C006b	IF A.4.1-1/2 AND A.4.1-2/8 AND A.4.1-3/1 AND A.4.3.2-1/31a THEN R ELSE N/A
C007	IF A.4.1-1/2 AND A.4.1-2/8 AND (A.4.1-3/1 OR A.4.1-3/4) AND A.4.3.2-1/22 THEN R ELSE N/A
C008	IF A.4.1-1/2 AND A.4.1-2/8 AND (A.4.1-3/1 OR A.4.1-3/4) AND NOT(A.4.3.2-1/22) THEN R ELSE N/A
C009	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/1 AND A.4.3.2B.2.0-2/1 THEN R ELSE N/A
C009a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/1 AND A.4.3.2B.2.0-1/1 THEN R ELSE N/A
C009z	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/1 AND A.4.3.2B.2.0-2/1 AND A.4.3.2-1/25 THEN R ELSE N/A
C010	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/2 AND A.4.3.2B.2.0-2/1 THEN R ELSE N/A
C010a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/2 AND A.4.3.2B.2.0-1/1 THEN R ELSE N/A
C010z	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/2 AND A.4.3.2B.2.0-2/1 AND A.4.3.2-1/25 THEN R ELSE N/A
C011	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/3 AND A.4.3.2B.2.0-2/1 THEN R ELSE N/A
C011a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/3 AND A.4.3.2B.2.0-1/1 THEN R ELSE N/A
C011z	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/3 AND A.4.3.2B.2.0-2/1 AND A.4.3.2-1/25 THEN R ELSE N/A
C012	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-2/1 THEN R ELSE N/A
C012a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-1/1 THEN R ELSE N/A
C012b	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-2/2 AND A.4.3.2B.2.0-2A/2 THEN R ELSE N/A
C012c	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-2/3 AND A.4.3.2B.2.0-2A/3 THEN R ELSE N/A
C012d	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-2/4 AND A.4.3.2B.2.0-2A/4 THEN R ELSE N/A
C012e	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-1/2 AND A.4.3.2B.2.0-1A/2 THEN R ELSE N/A
C012z	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.1-4/4 AND A.4.3.2B.2.0-2/1 AND A.4.3.2-1/25 THEN R ELSE N/A
C013	IF (A.4.1-1/1 OR A.4.1-1/2) AND (A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/5) AND (A.4.1-4/3 OR A.4.1-4/4) THEN R ELSE N/A
C014	IF (A.4.1-1/1 OR A.4.1-1/2) AND (A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/5) AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/4) THEN R ELSE N/A
C015	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND NOT A.4.3.1-7a/2 THEN R ELSE N/A
C015b	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.2-1/6 AND NOT A.4.3.1-7a/2 THEN R ELSE N/A
C015x	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.9-1/1 AND NOT A.4.3.1-7a/2 THEN R ELSE N/A
C015y	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.2-1/33 AND NOT A.4.3.1-7a/2 THEN R ELSE N/A
C016	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND NOT A.4.3.1-7a/3 THEN R ELSE N/A
C016b	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.2-1/6 AND NOT A.4.3.1-7a/3 THEN R ELSE N/A
C016x	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.9-1/1 AND NOT A.4.3.1-7a/3 THEN R ELSE N/A
C016y	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND A.4.3.2-1/20 AND NOT A.4.3.1-7a/3 THEN R ELSE N/A
C017	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND A.4.3.9-4a/7 OR (A.4.3.9-4a/1 OR A.4.3.9-4a/2 OR A.4.3.9-4a/3 OR A.4.3.9-4a/66 OR A.4.3.9-4a/70)) THEN R ELSE N/A
C017b	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND A.4.3.9-4a/7 OR (A.4.3.9-4a/1 OR A.4.3.9-4a/2 OR A.4.3.9-4a/3 OR A.4.3.9-4a/66 OR A.4.3.9-4a/70)) AND A.4.3.2-1/6 THEN R ELSE N/A

C017x	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND A.4.3.9-4a/7 OR (A.4.3.9-4a/1 OR A.4.3.9-4a/2 OR A.4.3.9-4a/3 OR A.4.3.9-4a/66 OR A.4.3.9-4a/70)) AND A.4.3.9-1/1 THEN R ELSE N/A
C017y	IF A.4.1-1/1 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND A.4.3.9-4a/7 OR (A.4.3.9-4a/1 OR A.4.3.9-4a/2 OR A.4.3.9-4a/3 OR A.4.3.9-4a/66 OR A.4.3.9-4a/70)) AND A.4.3.2-1/33 THEN R ELSE N/A
C018	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND 4.3.2-1/9 THEN R ELSE N/A
C019	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND (A.4.3.9-4b/38 OR A.4.3.9-4b/41 OR A.4.3.9-4b/77 OR A.4.3.9-4b/78 OR A.4.3.9-4b/79) OR (A.4.3.9-4b/34 OR A.4.3.9-4b/39 OR A.4.3.9-4b/40 OR A.4.3.9-4b/48)) THEN R ELSE N/A
C019b	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND (A.4.3.9-4b/38 OR A.4.3.9-4b/41 OR A.4.3.9-4b/77 OR A.4.3.9-4b/78 OR A.4.3.9-4b/79) OR (A.4.3.9-4b/34 OR A.4.3.9-4b/39 OR A.4.3.9-4b/40 OR A.4.3.9-4b/48)) AND A.4.3.2-1/6 THEN R ELSE N/A
C019x	IF A.4.1-1/2 AND (A.4.1-3/1 OR A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/4 OR A.4.1-3/5) AND (NOT A.4.3.9-1/2 AND (A.4.3.9-4b/38 OR A.4.3.9-4b/41 OR A.4.3.9-4b/77 OR A.4.3.9-4b/78 OR A.4.3.9-4b/79) OR (A.4.3.9-4b/34 OR A.4.3.9-4b/39 OR A.4.3.9-4b/40 OR A.4.3.9-4b/48)) AND A.4.3.9-1/1 THEN R ELSE N/A
C020	IF (A.4.1-1/1 OR A.4.1-1/2) AND (A.4.1-3/2 OR A.4.1-3/3 OR A.4.1-3/5) THEN R ELSE N/A
C021	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 THEN R ELSE N/A
C021a	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND A.4.3.5-1/1 THEN R ELSE N/A
C022	IF (A.4.1-4/4 OR A.4.1-4/5) AND A.4.1-3/2 THEN R ELSE N/A
C022a	IF (A.4.1-4/4 OR A.4.1-4/5) AND A.4.1-3/2 AND A.4.3.5-1/1 THEN R ELSE N/A
C023	IF A.4.1-4/5 AND A.4.1-3/2 THEN R ELSE N/A
C023a	IF A.4.1-4/5 AND A.4.1-3/2 AND A.4.3.5-1/1 THEN R ELSE N/A
C024	IF A.4.1-1/1 AND A.4.1-2/7 AND A.4.1-3/1 THEN R ELSE N/A
C025	IF ((A.4.1-1/1 AND [10]A.4.1-1/1) OR (A.4.1-1/1 AND [10]A.4.1-1/2) OR (A.4.1-1/2 AND [10]A.4.1-1/1) OR (A.4.1-1/2 AND [10]A.4.1-1/2)) AND A.4.1-3/1 THEN R ELSE N/A
C025a	IF ((A.4.1-1/1 AND [10]A.4.1-1/1) OR (A.4.1-1/1 AND [10]A.4.1-1/2) OR (A.4.1-1/2 AND [10]A.4.1-1/1) OR (A.4.1-1/2 AND [10]A.4.1-1/2)) AND A.4.1-3/1 AND A.4.3.5-1/1 THEN R ELSE N/A
C026	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND 4.3.6-1/11 THEN R ELSE N/A
C027	Void
C028	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/1 AND 4.3.6-1/11 THEN R ELSE N/A
C029	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/1 AND 4.3.2-1/9 THEN R ELSE N/A
C030	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND 4.3.2-1/9 THEN R ELSE N/A
C031	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4A/5) AND A.4.3.2A.1-1/1 THEN R ELSE N/A
C032	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND (A.4.1-2/3 OR A.4.1-2/5) THEN R ELSE N/A
C033	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4A/5) AND A.4.3.2A.1-1/2 THEN R ELSE N/A
C034	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.3.6-1/6 THEN R ELSE N/A
C035	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND A.4.3.6-1/6 THEN R ELSE N/A
C036	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4A/5) AND A.4.3.2A.1-1/3 THEN R ELSE N/A
C037	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4/5 OR A.4.1-4/7) AND A.4.1-5/1 AND A.4.3.6-1/41 THEN R ELSE N/A
C037a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4/5 OR A.4.1-4/7) AND A.4.1-5/1 AND A.4.3.6-1/41 AND A.4.3.5-1/1 THEN R ELSE N/A
C038	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/2 AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.3.6-1/41 THEN R ELSE N/A
C038a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/2 AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.3.6-1/41 AND A.4.3.5-1/1 THEN R ELSE N/A
C039	IF A.4.1-1/1 AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4/5 OR A.4.1-4/7) AND A.4.1-5/1 AND A.4.3.6-1/41 THEN R ELSE N/A
C040	IF A.4.1-1/1 AND A.4.1-2/7 AND A.4.1-3/2 AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.3.6-1/41 THEN R ELSE N/A
C041	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4/5 OR A.4.1-4/7) AND A.4.1-5/1 AND A.4.3.2-1/34 AND A.4.3.6-1/41 THEN R ELSE N/A
C041a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND (A.4.1-4A/1 OR A.4.1-4A/2 OR A.4.1-4/5 OR A.4.1-4/7) AND A.4.1-5/1 AND A.4.3.2-1/34 AND A.4.3.6-1/41 AND A.4.3.5-1/1 THEN R ELSE N/A
C042	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/2 AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.3.2-1/34 AND A.4.3.6-1/41 THEN R ELSE N/A
C042a	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/2 AND (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.3.2-1/34 AND A.4.3.6-1/41 AND A.4.3.5-1/1 THEN R ELSE N/A
C043	IF (A.4.1-4/1 OR A.4.1-4/2 OR A.4.1-4/3 OR A.4.1-4/5) AND A.4.1-3/2 AND (4.3.6-1/43 OR 4.3.6-1/44) THEN R ELSE N/A
C044	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND 4.3.6-1/42 THEN R ELSE N/A

C045	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.3.2B.2.0-1/2 AND (A.4.1-4/1 OR (A.4.1-4/3 AND A.4.3.2B.2.0-1A/2)) THEN R ELSE N/A
C046	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.3.2B.2.0-1/3 AND (A.4.1-4/1 OR (A.4.1-4/3 AND A.4.3.2B.2.0-1A/3)) THEN R ELSE N/A
C047	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.3.2B.2.0-1/4 AND (A.4.1-4/3 AND A.4.3.2B.2.0-1A/4) THEN R ELSE N/A
C048	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.3.2B.2.0-1/2 AND A.4.1-4/1 THEN R ELSE N/A
C049	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-3/2 AND A.4.3.2B.2.0-1/3 AND A.4.1-4/1 THEN R ELSE N/A
C050	IF A.4.1-1/2 AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.3.2-1/36 THEN R ELSE N/A
C051	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.1-4A/5 AND A.4.3.2A.1-2/1 AND A.4.3.2-1/37 THEN R ELSE N/A
C052	IF (A.4.1-1/1 OR A.4.1-1/2) AND A.4.1-2/7 AND A.4.1-3/1 AND A.4.3.11-1/1 THEN R ELSE N/A
NOTE 1: Cxxxx applicability is defined for enhanced type 1 receiver for NR related tests (A.4.3.9-1/1).	
NOTE 2: Cxxyy applicability is defined for alternative additional DMRS position for co-existence with LTE CRS related tests (A.4.3.2-1/20).	
NOTE 3: Cxxzx applicability is defined for modified MPR behaviour related test (A.4.3.2-1/25).	

For the purposes of the present document, the tested bands selection criteria given in Table 4.0-2 apply. The ICS proformas used in Table 4.0-2 are defined in TS 38.508-2 [8] unless otherwise stated.

Table 4.0-2: Tested Bands Selection Criteria

Code	Tested Bands Selection Criteria	Comment
D001	(A.4.3.1-1 OR A.4.3.1-2) AND NOT (A.4.3.1-5 OR A.4.3.1-6)	All supported FR1 Bands without SUL/SDL bands
D002	A.4.3.1-4	All supported FR1 PC2 Bands
D003	A.4.3.1-5	All supported FR1 SUL Bands
D004	{1,2,3,5,7,8,12,14,20,25,28,30,34,38,39,40,41,50,51,65,66,70,71,74,75,76}	UE supported bands among n1,n2,n3,n5,n7,n8,n12,n14,n20,n25,n28,n30,n34,n38,n39,n40,n41,n50,n51,n65,n66,n70,n71,n74,n75,n76
D005	A.4.3.1-3	All supported FR2 Bands
D006	A.4.3.1-1 OR A.4.3.1-2	All supported FR1 Bands
D007	A.4.3.1-1 OR A.4.3.1-2 OR A.4.3.1-3	All supported NR Bands
D008	ANY((A.4.3.1-1 OR A.4.3.1-2) AND 10MHz)	Any band within the set supporting 10 MHz UE Channel BW
D009	ANY((A.4.3.1-2) AND 20MHz)	Any TDD FR1 band within the set supporting 20 MHz UE Channel BW
D010	ANY((A.4.3.1-2) AND 40MHz)	Any TDD FR1 band within the set supporting 40 MHz UE Channel BW
D011	A.4.3.9-4a OR A.4.3.9-4b	All supported 4 Rx antenna ports Bands
D012	A.4.3.1-1 AND NOT (A.4.3.1-5 OR A.4.3.1-6)	All supported FDD bands without SUL/SDL bands
<p>NOTE 1: Band Selection is based on set theory. For each feature, item number shall correspond to the Band number. The result is the set of bands for which the test shall be conducted. The following operators are used:</p> <p>AND: Set intersection (\cap). {1,2} AND {2,3} = {2}</p> <p>OR: Set union (\cup). {1,2} OR {2,3} = {1,2,3}</p> <p>NOT: Set complement (\setminus), full set being all bands. NOT{1} = {2 ...256}</p> <p>Also note that this is set without repetitions so {1} AND {1} = {1}</p> <p>The following basic sets are used:</p> <p>{1,2}: Explicitly given band set</p> <p>10MHz: All bands supporting 10 MHz</p> <p>The following sets derived from pro-forma tables are also used:</p> <p>TBD</p>		

For the purposes of the present document, the tested CA/DC configuration selection criteria given in Table 4.0-3 apply. The ICS proformas used in Table 4.0-3 are defined in TS 38.508-2 [8] unless otherwise stated.

Table 4.0-3: Tested CA/DC Configuration Selection Criteria

Code	Tested CA Configuration Selection Criteria	Comment
E001	A.4.3.2A.2.1-3 AND A.4.3.2B.2.0-1/1 AND NOT UL(A.4.3.2A.2.1-2)	All supported intra-band contiguous CA Configurations with 2 carriers in DL but no CA in UL
E002	A.4.3.2A.4.1-1 AND A.4.3.2B.2.0-1/1 AND NOT UL(A.4.3.2A.4.1-2)	All supported inter-band CA Configurations with 2 carriers in DL but no CA in UL
E003	UL(A.4.3.2B.2.1-2) AND A.4.3.2B.2.0-2/1	All supported Intra-band contiguous EN-DC configurations in FR1(2UL CCs)
E003a	A.4.3.2B.2.1-2 AND A.4.3.2B.2.0-1/1	All supported Intra-band contiguous EN-DC configurations in FR1(2DL CCs)
E004	UL(A.4.3.2B.2.2-2) AND A.4.3.2B.2.0-2/1	All supported Intra-band non-contiguous EN-DC configurations in FR1(2UL CCs)
E004a	A.4.3.2B.2.2-2 AND A.4.3.2B.2.0-1/1	All supported Intra-band non-contiguous EN-DC configurations in FR1(2DL CCs)
E005	UL(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2 OR A.4.3.2B.2.3.5-2) AND A.4.3.2B.2.0-2/1	All supported Inter-band EN-DC configurations within FR1 (2UL CCs)
E005a	A.4.3.2B.2.3.1-2 AND A.4.3.2B.2.0-1/1	All supported Inter-band EN-DC configurations within FR1 (2DL CCs)
E006	(A.4.3.2B.2.1-2 OR A.4.3.2B.2.2-2 OR A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2) AND A.4.3.2B.2.0-1/2	All supported EN-DC configurations within FR1 (3DL CCs)
E007	(A.4.3.2B.2.1-2 OR A.4.3.2B.2.2-2 OR A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2) AND A.4.3.2B.2.0-1/3	All supported EN-DC configurations within FR1 (4DL CCs)
E008	(A.4.3.2B.2.1-2 OR A.4.3.2B.2.2-2 OR A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2) AND A.4.3.2B.2.0-1/4	All supported EN-DC configurations within FR1 (5DL CCs)
E009	(A.4.3.2B.2.1-2 OR A.4.3.2B.2.2-2 OR A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2 OR A.4.3.2B.2.3.5-2) AND A.4.3.2B.2.0-1/5	All supported EN-DC configurations within FR1 (6DL CCs)
E010	UL(A.4.3.2B.2.3.6-2 OR A.4.3.2B.2.3.7-2 OR A.4.3.2B.2.3.8-2 OR A.4.3.2B.2.3.9-2 OR A.4.3.2B.2.3.10-2) AND A.4.3.2B.2.0-2/1	All supported Inter-band EN-DC configurations including FR2 (2UL CCs)
E010a	A.4.3.2B.2.3.6-2 AND A.4.3.2B.2.0-1/1	All supported Inter-band EN-DC configurations including FR2 (2DL CCs)
E011	UL(A.4.3.2B.2.3.6-2 OR A.4.3.2B.2.3.7-3) AND A.4.3.2B.2.0-2/2 AND A.4.3.2B.2.0-2A/2	All supported Inter-band EN-DC configurations including FR2 (3UL CCs(2NR UL CCs))
E011a	(A.4.3.2B.2.3.6-2 OR A.4.3.2B.2.3.7-3) AND A.4.3.2B.2.0-1/2 AND A.4.3.2B.2.0-1A/2	All supported Inter-band EN-DC configurations including FR2 (3DL CCs(2NR DL CCs))
E012	UL(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2) AND A.4.3.2B.2.0-2/3 AND NR_A.4.3.2B.2.0-2A/3	All supported Inter-band EN-DC configurations including FR2 (4UL CCs(3NR UL CCs))
E012a	(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2) AND A.4.3.2B.2.0-1/3 AND A.4.3.2B.2.0-1A/3	All supported Inter-band EN-DC configurations including FR2 (4DL CCs(3NR DL CCs))
E013	UL(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2) AND A.4.3.2B.2.0-2/4 AND A.4.3.2B.2.0-2A/4	All supported Inter-band EN-DC configurations including FR2 (5UL CCs(4NR UL CCs))
E013a	(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2) AND A.4.3.2B.2.0-1/4 AND A.4.3.2B.2.0-1A/4	All supported Inter-band EN-DC configurations including FR2 (5DL CCs(4NR DL CCs))
E014	(A.4.3.2B.2.3.1-2 OR A.4.3.2B.2.3.2-2 OR A.4.3.2B.2.3.3-2 OR A.4.3.2B.2.3.4-2 OR A.4.3.2B.2.3.5-2) AND A.4.3.2B.2.0-1/5 AND A.4.3.2B.2.0-1A/5	All supported Inter-band EN-DC configurations including FR2 (6DL CCs(5NR DL CCs))
E015	UL(A.4.3.2A.2.1-3 OR A.4.3.2A.3.1-3 OR A.4.3.2A.4.1-3 OR A.4.3.2A.4.2-3) AND A.4.3.2B.2.0-2/1	All supported FR1 2UL CA configurations
E016	(A.4.3.2A.2.1-3 OR A.4.3.2A.3.1-3 OR A.4.3.2A.4.1-3) AND A.4.3.2B.2.0-1/1	All supported FR1 2DL CA configurations
E017	(A.4.3.2A.2.1-3 OR A.4.3.2A.3.1-3 OR A.4.3.2A.4.1-3 OR A.4.3.2A.4.2-3) AND A.4.3.2B.2.0-1/2	All supported FR1 3DL CA configurations
E018	(A.4.3.2A.2.1-3 OR A.4.3.2A.3.1-3 OR A.4.3.2A.4.1-3 OR A.4.3.2A.4.2-3) AND A.4.3.2B.2.0-1/3	All supported FR1 4DL CA configurations
E019	ULSwitching(A.4.3.2A.4.1-3)	All supported FR1 2UL CA configurations with ULTxSwitching capability

4.1 RF conformance test cases

NOTE: To determine applicability of a test case, supported CBW and SCS in the *RF-Parameters* IE (see TS 38.331 [11]) which conveys RF related capabilities for NR operation is taken into account.

4.1.1 FR1 standalone conformance test cases

Table 4.1.1-1: Applicability of RF SA FR1 conformance test cases, ref. TS 38.521-1 [1]

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6	Transmitter Characteristics						
6.2.1	UE maximum output power	Rel-15	C001	UEs supporting 5GS FR1	D001	PC1 PC2 PC3	
6.2.2	Maximum Power Reduction (MPR)	Rel-15	C001	UEs supporting 5GS FR1	D001	PC2 PC3	Test execution is not necessary if TS 38.521-1 6.5.2.4.1 is executed. Skip TC 6.2.2 if UE supports NSA and TS 38.521-3 TC 6.2B.2.3 has been executed.
6.2.3	UE additional maximum output power reduction	Rel-15	C001	UEs supporting 5GS FR1 PC3	D001	PC2 PC3	Test execution is not necessary if TS 38.521-1 6.5.2.3 and 6.5.3.3 are executed. Skip TC 6.2.3 if UE supports NSA and TS 38.521-3 TC 6.2B.3.3 has been executed.
6.2.4	Configured transmitted power	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.2A.1.1	UE maximum output power for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.2A.2.1	Maximum Power Reduction (MPR) for CA (2 UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		Test execution is not necessary if TS 38.521-1 6.5A.2.4.1.1 is executed.
6.2A.3.1	UE additional maximum output power reduction for CA (2 UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		Test execution is not necessary if TS 38.521-1 6.5A.2.3 and 6.5A.3.3 are executed.
6.2A.4.1	Configured transmitted power for CA (2 UL CA)	Rel-15	C004	Ues supporting 5GS FR1 and CA (2UL CA)	E015		
6.2C.1	Configured transmitted power for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.2C.3	UE maximum output power for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.2C.4	UE maximum output power reduction for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.2C.5	UE additional maximum output power reduction for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.2D.1	UE maximum output power for UL-MIMO	Rel-15	N/A	Not recommended due to no test points are defined since there is no configuration satisfying MPR=0dB requirements in RAN4.	D001		Maximum Output Power for UL-MIMO is tested as part of the MPR test case with using MPR=1.5dB suggested by RAN4.
6.2D.2	UE maximum output power reduction for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		Test execution is not necessary if TS 38.521-1 6.5D.2.4.1 is executed.
6.2D.3	UE additional maximum output power reduction for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		Test execution is not necessary if TS 38.521-1 6.5D.2.3 and 6.5D.3.3 are executed.
6.2D.4	Configured transmitted power for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.3.1	Minimum output power	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.3.1 if UE supports NSA and TS 38.521-3 TC 6.3B.1.1 or 6.3B.1.2 or 6.3B.1.3 has been executed.
6.3.3.2	General ON/OFF time mask	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.3.3.2 if UE supports NSA and TS 38.521-3 TC 6.3B.3.1 or 6.3B.3.2 or 6.3B.3.3 has been executed.
6.3.3.4	PRACH time mask	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.3.3.4 if UE supports NSA and TS 38.521-3 TC 6.3B.4.1 or 6.3B.4.2 or 6.3B.4.3 has been executed.
6.3.3.6	SRS time mask	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.3.4.2	Absolute power tolerance	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.3.4.3	Relative power tolerance	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.3.4.4	Aggregate power tolerance	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.3A.1.1	Minimum output power for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.3A.3.1	Transmit ON/OFF time mask for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.3A.3.1_1	Time mask for switching between two uplink carriers	Rel-16	C051	UEs supporting 5GS FR1 and Inter-band CA (2UL CA) and dynamic UL Tx switching	E019		NOTE 1

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.3A.4.1	Absolute power tolerance for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.3A.4.2	Power Control Relative power tolerane for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.3A.4.3	Aggregate power tolerance for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	E015		
6.3C.1	Minimum output power for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.3C.3	Transmit ON/OFF time mask for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.3C.4.1	Absolute power tolerance for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.3C.4.2	Power Control Relative power tolerance for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.3C.4.3	Aggregate power tolerance for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.3D.1	Minimum output power for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.3D.3	Transmit ON/OFF time mask for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.3D.4.1	Absolute power tolerance for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.3D.4.2	Relative power tolerance for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.3D.4.3	Aggregate power tolerance for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4.1	Frequency error	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.4.1 if UE supports NSA and TS 38.521-3 TC 6.4B.1.1 or 6.4B.1.2 or 6.4B.1.3 has been executed.
6.4.2.1	Error Vector Magnitude	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.4.2.1 if UE supports NSA and TS 38.521-3 TC 6.4B.2.1.1 or 6.4B.2.2.1 or 6.4B.2.3.1 has been executed.
6.4.2.2	Carrier leakage	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.4.2.2 if UE supports NSA and TS 38.521-3 TC 6.4B.2.1.2 or 6.4B.2.2.2 or 6.4B.2.3.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4.2.3	In-band emissions	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.4.2.3 if UE supports NSA and TS 38.521-3 TC 6.4B.2.2.3 or 6.4B.2.3.3 has been executed.
6.4.2.4	EVM equalizer spectrum flatness	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.4.2.4 if UE supports NSA and TS 38.521-3 TC 6.4B.2.1.4 or 6.4B.2.2.4 or 6.4B.2.3.4 has been executed.
6.4.2.5	EVM equalizer spectrum flatness for Pi/2 BPSK	Rel-15	C050	UEs supporting 5GS FR1 and pi/2-BPSK modulation scheme for power boosting in FR1	D001		
6.4A.1.1	Frequency error for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.4A.2.1.1	Error Vector Magnitude for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.4A.2.2.1	Carrier leakage for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.4A.2.3.1	In-band emissions for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.4C.1	Frequency error for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.4C.2.1	Error Vector Magnitude for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.4C.2.2	Carrier leakage for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.4C.2.3	In-band emissions for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.4C.2.4	EVM equalizer spectrum flatness for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.4C.2.5	EVM equalizer spectrum flatness for Pi/2 BPSK for SUL	Rel-16	C002	UEs supporting 5GS FR1 and SUL	D003		NOTE 1
6.4D.1	Frequency error for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4D.2.1	Error Vector Magnitude for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4D.2.2	Carrier leakage for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4D.2.3	In-band emissions for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4D.2.4	EVM equalizer spectrum flatness for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4D.3	Time alignment error for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.4D.4	Requirements for coherent UL MIMO	FFS	FFS	FFS	FFS		NOTE 1
6.4E.2.2.1	Error Vector Magnitude for V2X / non-concurrent operation	FFS	FFS	FFS	FFS		NOTE 1
6.5.1	Occupied bandwidth	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.5.1 if UE supports NSA and TS 38.521-3 TC 6.5B.1.2 or 6.5B.1.3 has been executed.
6.5.2.2	Spectrum Emission Mask	Rel-15	C001	UEs supporting 5GS FR1	D001	PC2 PC3	Skip TC 6.5.2.2 if UE supports NSA and TS 38.521-3 TC 6.5B.2.2.1 or 6.5B.2.3.1 has been executed.
6.5.2.3	Additional spectrum emission mask	Rel-15	C001	UEs supporting 5GS FR1	D001	PC2 PC3	NOTE 1 Skip TC 6.5.2.3 if UE supports NSA and TS 38.521-3 TC 6.5B.2.3.2 has been executed.
6.5.2.4.1	NR ACLR	Rel-15	C001	UEs supporting 5GS FR1	D001	PC2 PC3	Skip TC 6.5.2.4.1 if UE supports NSA and TS 38.521-3 TC 6.5B.2.2.3 or 6.5B.2.3.3 has been executed.
6.5.2.4.2	UTRA ACLR	Rel-15	C001a	UEs supporting 5GS FR1 PC3	D001		
6.5.3.1	General spurious emissions	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.5.3.1 if UE supports NSA and TS 38.521-3 TC 6.5B.3.1.1 or 6.5B.3.2.1 has been executed.
6.5.3.2	Spurious emission for UE co-existence	Rel-15	C001	UEs supporting 5GS FR1	D001		
6.5.3.3	Additional spurious emissions	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.5.3.3 if UE supports NSA and TS 38.521-3 TC 6.5B.4.3 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5.4	Transmit intermodulation	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 6.5.4 if UE supports NSA and TS 38.521-3 TC 6.5B.5.3 has been executed.
6.5A.1.1	Occupied bandwidth for CA (2UL CA)	Rel-15	C004	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.2.2.1	Spectrum emission mask for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.2.4.1.1	NR ACLR for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.2.4.2.1	UTRA ACLR for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.3.1.1	General spurious emissions for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.3.2.1	Spurious emissions for UE co-existence for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5A.4.1	Transmit intermodulation for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR1 and CA (2UL CA)	FFS		NOTE 1
6.5C.1	Occupied bandwidth for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.2.2	Spectrum Emission Mask for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.2.3	Additional spectrum emission mask for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.2.4.1	NR ACLR for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.2.4.2	UTRA ACLR for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.3.1	General spurious emissions for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.3.2	Spurious emission for UE co-existence for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.3.3	Additional spurious emissions for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5C.4	Transmit intermodulation for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
6.5D.1	Occupied bandwidth for UL-MIMO	Rel-15 only	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.1_1	Occupied bandwidth for UL MIMO (Rel-16 onward)	Rel-16	FFS	UEs supporting 5GS FR1 and UL-MIMO and ULFPTx	FFS		NOTE 1
6.5D.2.2	Spectrum Emission Mask for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.2.3	Additional spectrum emission mask for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.2.4.1	NR ACLR for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.2.4.2	UTRA ACLR for UL-MIMO	Rel-15 only	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.2_1.4.2	UTRA ACLR for UL MIMO (Rel-16 onward)	Rel-16	FFS	FFS	FFS		NOTE 1

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5D.3.1	General spurious emissions for UL-MIMO	Rel-15 only	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.3.2	Spurious emission for UE co-existence for UL-MIMO	Rel-15 only	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.3.3	Additional spurious emissions for UL-MIMO	Rel-15 only	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
6.5D.3_1.1	General spurious emissions for UL-MIMO (Rel-16 onward)	Rel-16	FFS	UEs supporting 5GS FR1 and UL-MIMO and ULFPTx	FFS		NOTE 1
6.5D.3_1.2	Spurious emission for UE co-existence for UL-MIMO (Rel-16 onward)	Rel-16	FFS	UEs supporting 5GS FR1 and UL-MIMO and ULFPTx	FFS		NOTE 1
6.5D.3_1.3	Additional spurious emissions for UL-MIMO(Rel-16 onward)	Rel-16	FFS	UEs supporting 5GS FR1 and UL-MIMO and ULFPTx	FFS		NOTE 1
6.5D.4	Transmit intermodulation for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D001		
7	Receiver Characteristics						
7.3.2	Reference sensitivity power level	Rel-15	C001	UEs supporting 5GS FR1	D001	2Rx 4Rx	
7.3A.1	Reference sensitivity power level for 2DL CA without exception	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.3A.1_1	Reference sensitivity power level for 2DL CA exceptions	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.3A.2	Reference sensitivity level for CA (3DL CA)	FFS	FFS	FFS	FFS		NOTE 1
7.3A.3	Reference sensitivity level for CA (4DL CA)	FFS	FFS	FFS	FFS		NOTE 1
7.3C.2	Reference sensitivity power level for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
7.3D.2	Reference sensitivity power level for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.4	Maximum input level	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 7.4 if UE supports NSA and TS 38.521-3 TC 7.4B.3 or 7.4B.4 has been executed.
7.4A.1	Maximum input level for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.4A.2	Maximum input level for CA (3DL CA)	Rel-16	C033	UEs supporting 5GS FR1 and CA (3DL CA)	E017		
7.4A.3	Maximum input level for CA (4DL CA)	FFS	FFS	FFS	FFS		NOTE 1
7.4D	Maximum input level for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.5	Adjacent channel selectivity	Rel-15	C001	UEs supporting 5GS FR1	D001		NOTE 1 Skip TC 7.5 if UE supports NSA and TS 38.521-3 TC 7.5B.2 or 7.5B.3 has been executed.
7.5A.1	Adjacent channel selectivity for 2DL CA	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.5A.2	Adjacent channel selectivity for 3DL CA	FFS	FFS	FFS	FFS		NOTE 1
7.5A.3	Adjacent channel selectivity for 4DL CA	FFS	FFS	FFS	FFS		NOTE 1
7.5D	Adjacent channel selectivity for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.6.2	Inband Blocking	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 7.6.2 if UE supports NSA and TS 38.521-3 TC 7.6B.2.2 or 7.6B.2.3 has been executed.
7.6.3	Out-of-band blocking	Rel-15	C001	UEs supporting 5GS FR1	D001		
7.6.4	Narrow band blocking	Rel-15	C001	UEs supporting 5GS FR1	D004		Skip TC 7.6.4 if UE supports NSA and TS 38.521-3 TC 7.6B.4.2 or 7.6B.4.3 has been executed.
7.6A.2.1	In-band Blocking for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.6A.2.2	Inband blocking for CA (3DL CA)	Rel-16	C033	UEs supporting 5GS FR1 and CA (3DL CA)	E017		
7.6A.2.3	Inband blocking for CA (4DL CA)	Rel-16	C036	UEs supporting 5GS FR1 and CA (4DL CA)	E018		NOTE 1 Skip TC 7.6A.2.3 if UE supports NSA and TS 38.521-3 TC 7.6B.2.3_1.3 has been executed.
7.6A.3.1	Out-of-band blocking for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.6A.3.2	Out-of-band blocking for CA (3DL CA)	Rel-16	C033	UEs supporting 5GS FR1 and CA (3DL CA)	E017		
7.6A.3.3	Out-of-band blocking for CA (4DL CA)	Rel-16	C036	UEs supporting 5GS FR1 and CA (4DL CA)	E018		
7.6A.4.1	Narrow band blocking for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.6A.4.2	Narrow band blocking for CA (3DL CA)	Rel-16	C033	UEs supporting 5GS FR1 and CA (3DL CA)	E017		
7.6A.4.3	Narrow band blocking for CA (4DL CA)	Rel-16	C036	UEs supporting 5GS FR1 and CA (4DL CA)	E018		Skip TC 7.6A.4.3 if UE supports NSA and TS 38.521-3 TC 7.6B.4.3_1.3 has been executed.
7.6C.2	Inband blocking for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
7.6C.3	Out-of-band blocking for SUL	Rel-15	C002	UEs supporting 5GS FR1 and SUL	D003		
7.6D.2	Inband blocking for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.6D.3	Out-of-band blocking for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.6D.4	Narrow band blocking for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.7	Spurious response	Rel-15	C001	UEs supporting 5GS FR1	D001		
7.7A.1	Spurious response for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.7A.2	Spurious response for CA (3DL CA)	Rel-16	FFS	UEs supporting 5GS FR1 and CA (3DL CA)	FFS		NOTE 1
7.7A.3	Spurious response for CA (4DL CA)	Rel-16	FFS	UEs supporting 5GS FR1 and CA (4DL CA)	FFS		NOTE 1
7.7D	Spurious response for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		
7.8.2	Wide band Intermodulation	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 7.8.2 if UE supports NSA and TS 38.521-3 TC 7.8B.2.2 or 7.8B.2.3 has been executed.
7.8A.2.1	Wide band Intermodulation for CA (2DL CA)	Rel-15	C031	UEs supporting 5GS FR1 and CA (2DL CA)	E016		
7.8A.2.2	Wide band Intermodulation for CA (3DL CA)	Rel-16	C033	UEs supporting 5GS FR1 and CA (3DL CA)	E017		
7.8A.2.3	Wide band Intermodulation for CA (4DL CA)	Rel-16	C036	UEs supporting 5GS FR1 and CA (4DL CA)	E018		
7.8D.2	Wide band Intermodulation for UL-MIMO	Rel-15	C003	UEs supporting 5GS FR1 and UL-MIMO	D012		

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.9	Spurious emissions	Rel-15	C001	UEs supporting 5GS FR1	D001		Skip TC 7.9 if UE supports NSA and TS 38.521-3 TC 7.9B.1 or 7.9B.2 or 7.9B.3 has been executed.
7.9A.1	Spurious emission for 2DL CA	Rel-15	C005	UEs supporting 5GS FR1 and inter-band 2DL CA with a DL-only band	E002		
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.521-1.							

Table 4.1.1-1a: Void

Table 4.1.1-1b: Void

Table 4.1.1-1c: Void

4.1.2 FR2 standalone conformance test cases

Table 4.1.2-1: Applicability of RF SA FR2 conformance test cases, ref. TS 38.521-2 [2]

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6	Transmitter Characteristics						
6.2.1.1	UE maximum output power - EIRP and TRP	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 6.2.1.1 if UE supports NSA and TS 38.521-3 TC 6.2B.1.4.1 has been executed.
6.2.1.2	UE maximum output power - Spherical coverage	Rel-15	C007	UEs supporting 5GS FR2 and beam correspondence without UL beam sweeping	D005		NOTE 1
6.2.2	UE maximum output power reduction	FFS	FFS	FFS			NOTE 1 Skip TC 6.2.2 if UE supports NSA and TS 38.521-3 TC 6.2B.2.4 has been executed.
6.2.3	UE maximum output power with additional requirements	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.2.3 if UE supports NSA and TS 38.521-3 TC 6.2B.3.4 has been executed.
6.2A.1.1.1	UE maximum output power - EIRP and TRP for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.2A.1.1.1 if UE supports NSA and TS 38.521-3 TC 6.2B.1.4_1.1.1 has been executed.
6.2A.1.1.2	UE maximum output power - EIRP and TRP for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.2A.1.1.2 if UE supports NSA and TS 38.521-3 TC 6.2B.1.4_1.2.1 has been executed.
6.2A.1.1.3	UE maximum output power - EIRP and TRP for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.2A.1.1.3 if UE supports NSA and TS 38.521-3 TC 6.2B.1.4_1.3.1 has been executed.
6.2A.1.1.4	UE maximum output power - EIRP and TRP for CA (5UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.2A.1.1.5	UE maximum output power - EIRP and TRP for CA (6UL CA)	FFS	FFS	FFS	FFS		NOTE 1

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.2A.1.1.6	UE maximum output power - EIRP and TRP for CA (7UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.2A.1.1.7	UE maximum output power - EIRP and TRP for CA (8UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.3.1	Minimum output power	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.3.1 if UE supports NSA and TS 38.521-3 TC 6.3B.1.4 has been executed.
6.3.2	Transmit OFF power	FFS	FFS	FFS	FFS		NOTE 1
6.3.3.2	General ON/OFF time mask	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1
6.3.3.4	PRACH time mask	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1
6.3.4.2	Absolute power tolerance	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1
6.3.4.3	Relative power tolerance	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1
6.3.4.4	Aggregate power tolerance	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1
6.3A.1.1	Minimum output power for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.3A.2.1	Transmit OFF power for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.3A.2.1 if UE supports NSA and TS 38.521-3 TC 6.3B.2.4_1.1 has been executed.
6.3A.2.2	Transmit OFF power for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.3A.2.2 if UE supports NSA and TS 38.521-3 TC 6.3B.2.4_1.2 has been executed.
6.3A.2.3	Transmit OFF power for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.3A.2.3 if UE supports NSA and TS 38.521-3 TC 6.3B.2.4_1.3 has been executed.
6.3D.3.4	SRS time mask for UL-MIMO	FFS	FFS	FFS	FFS		NOTE 1
6.4.1	Frequency error	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 6.4.1 if UE supports NSA and TS 38.521-3 TC 6.4B.1.4 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4.2.1	Error vector magnitude	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.4.2.1 if UE supports NSA and TS 38.521-3 TC 6.4B.2.4.1 has been executed.
6.4.2.2	Carrier leakage	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.4.2.2 if UE supports NSA and TS 38.521-3 TC 6.4B.2.4.2 has been executed.
6.4.2.3	In-band emissions	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.4.2.3 if UE supports NSA and TS 38.521-3 TC 6.4B.2.4.3 has been executed.
6.4.2.4	EVM equalizer spectrum flatness	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.4.2.4 if UE supports NSA and TS 38.521-3 TC 6.4B.2.4.4 has been executed.
6.4.2.5	EVM spectral flatness for pi/2 BPSK modulation	Rel-15	C006b	UEs supporting 5GS FR2 and pi/2 BPSK modulation	D005		NOTE 1
6.4A.1.1	Frequency error for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.4A.1.2	Frequency error for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.4A.1.3	Frequency error for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1
6.4A.2.3.1	In-band emissions for CA (2UL CA)	Rel-15	FFS	UEs supporting 5GS FR2 CA (2UL CA)	FFS		NOTE 1
6.5.1	Occupied bandwidth	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 6.5.1 if UE supports NSA and TS 38.521-3 TC 6.5B.1.4 has been executed.
6.5.2.1	Spectrum Emission Mask	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 6.5.2.1 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.1 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5.2.3	Adjacent channel leakage ratio	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 6.5.2.3 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.3 has been executed.
6.5.3.1	Transmitter Spurious emissions	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 6.5.3.1 if UE supports NSA and TS 38.521-3 TC 6.5B.3.4.1 has been executed.
6.5.3.2	Spurious emission band UE co-existence	FFS	FFS	FFS	FFS		NOTE 1
6.5A.1.1	Occupied bandwidth for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.1.1 if UE supports NSA and TS 38.521-3 TC 6.5B.1.4_1.1 has been executed.
6.5A.1.2	Occupied bandwidth for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.1.2 if UE supports NSA and TS 38.521-3 TC 6.5B.1.4_1.2 has been executed.
6.5A.1.3	Occupied bandwidth for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.1.3 if UE supports NSA and TS 38.521-3 TC 6.5B.1.4_1.3 has been executed.
6.5A.2.1.1	Spectrum Emission Mask for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.1.1 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.1_1.1 has been executed.
6.5A.2.1.2	Spectrum Emission Mask for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.1.2 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.1_1.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5A.2.1.3	Spectrum Emission Mask for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.1.3 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.1_1.3 has been executed.
6.5A.2.2.1	Adjacent channel leakage ratio for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.2.1 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.3_1.1 has been executed.
6.5A.2.2.2	Adjacent channel leakage ratio for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.2.2 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.3_1.2 has been executed.
6.5A.2.2.3	Adjacent channel leakage ratio for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.2.2.3 if UE supports NSA and TS 38.521-3 TC 6.5B.2.4.3_1.3 has been executed.
6.5A.3.1.1	Transmitter Spurious emissions for CA (2UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.3.1.1 if UE supports NSA and TS 38.521-3 TC 6.5B.3.4.1_1.1 has been executed.
6.5A.3.1.2	Transmitter Spurious emissions for CA (3UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.3.1.2 if UE supports NSA and TS 38.521-3 TC 6.5B.3.4.1_1.2 has been executed.
6.5A.3.1.3	Transmitter Spurious emissions for CA (4UL CA)	FFS	FFS	FFS	FFS		NOTE 1 Skip TC 6.5A.3.1.3 if UE supports NSA and TS 38.521-3 TC 6.5B.3.4.1_1.3 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.6	Beam correspondence	Rel-15	C008	UEs supporting 5GS FR2 and not beam correspondence without UL beam sweeping	D005		NOTE 1
7	Receiver Characteristics						
7.3.2	Reference sensitivity power level	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 7.3.2 if UE supports NSA and TS 38.521-3 TC 7.3B.2.4 has been executed.
7.3.4	EIS spherical coverage	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 7.3.4 if UE supports NSA and TS 38.521-3 TC 7.3B.4 has been executed.
7.4	Maximum input level	Rel-15	N/A	not recommended due to testability issues	N/A		NOTE 1
7.5	Adjacent channel selectivity	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 7.5 if UE supports NSA and TS 38.521-3 TC 7.5B.4.1 has been executed.
7.6.2	In-band Blocking	Rel-15	C006	UEs supporting 5GS FR2	D005		NOTE 1 Skip TC 7.6.2 if UE supports NSA and TS 38.521-3 TC 7.6B.2.4 has been executed.
7.9	Spurious emissions	Rel-15	C006	UEs supporting 5GS FR2	D005		Skip TC 7.9 if UE supports NSA and TS 38.521-3 TC 7.9B.4 has been executed.
<p>NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.521-2.</p> <p>NOTE 2: Void.</p> <p>NOTE 3: Void.</p> <p>NOTE 4: Void.</p>							

Table 4.1.2-1a: Void

Table 4.1.2-1b: Void

Table 4.1.2-1c: Void

4.1.3 NR interworking between NR FR1 and NR FR2 and between NR and LTE conformance test cases

Table 4.1.3-1: Applicability of RF EN-DC FR1 and FR2 conformance test cases, ref. TS 38.521-3 [3]

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6	Transmitter Characteristics						
6.2	Transmitter power						
6.2B	Transmitter power for DC						
6.2B.1	UE Maximum Output Power for EN-DC						
6.2B.1.1	UE Maximum Output Power for Intra-Band Contiguous EN-DC	Rel-15	C009	UEs supporting Intra-Band Contiguous EN-DC (2UL CCs)	E003		NOTE 1
6.2B.1.2	UE Maximum Output Power for Intra-Band Non-Contiguous EN-DC	Rel-15	C010	UEs supporting Intra-Band non-contiguous EN-DC (2UL CCs)	E004		NOTE 1
6.2B.1.3	UE Maximum Output Power for Inter-Band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-Band EN-DC within FR1 (2UL CCs)	E005	PC3 PC2	
6.2B.1.4	UE Maximum Output Power for Inter-Band EN-DC including FR2						
6.2B.1.4.1	UE Maximum Output Power for Inter-Band EN-DC including FR2 - EIRP and TRP	Rel-15	C012	UEs supporting Inter-Band EN-DC including FR2 (2UL CCs)	E010		NOTE 5 Skip TC 6.2B.1.4.1 if UE supports SA and TSC 38.521-2 TC 6.2.1.1 has been executed.
6.2B.1.4.2	UE Maximum Output Power for Inter-Band EN-DC including FR2 - Spherical Coverage	Rel-15	C012	UEs supporting Inter-Band EN-DC including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5
6.2B.1.4_1	UE Maximum Output Power for Inter-Band EN-DC including FR2 (>2 CCs)						
6.2B.1.4_1.1	UE Maximum Output Power for Inter-Band EN-DC including FR2 (3 CCs)						
6.2B.1.4_1.1.1	UE Maximum Output Power for Inter-Band EN-DC including FR2 (3 CCs) - EIRP and TRP	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.2B.1.4_1.1.1 if UE supports SA and TS 38.521-2 TC 6.2A.1.1.1 has been executed.
6.2B.1.4_1.1.2	UE Maximum Output Power for Inter-Band EN-DC including FR2 (3 CCs) - Spherical Coverage	Rel-15	FFS	FFS	FFS		NOTE 1
6.2B.1.4_1.2	UE Maximum Output Power for Inter-Band EN-DC including FR2 (4 CCs)						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.2B.1.4_1.2.1	UE Maximum Output Power for Inter-Band EN-DC including FR2 (4 CCs) - EIRP and TRP	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.2B.1.4_1.2.1 if UE supports SA and TS 38.521-2 TC 6.2A.1.1.2 has been executed.
6.2B.1.4_1.2.2	UE Maximum Output Power for Inter-Band EN-DC including FR2 (4 CCs) - Spherical Coverage	Rel-15	FFS	FFS	FFS		NOTE 1
6.2B.1.4_1.3	UE Maximum Output Power for Inter-Band EN-DC including FR2 (5 CCs)						
6.2B.1.4_1.3.1	UE Maximum Output Power for Inter-Band EN-DC including FR2 (5 CCs) - EIRP and TRP	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.2B.1.4_1.3.1 if UE supports SA and TS 38.521-2 TC 6.2A.1.1.3 has been executed.
6.2B.1.4_1.3.2	UE Maximum Output Power for Inter-Band EN-DC including FR2 (5 CCs) - Spherical Coverage	Rel-15	FFS	FFS	FFS		NOTE 1
6.2B.2	UE Maximum Output Power reduction for EN-DC						
6.2B.2.1	UE Maximum Output Power reduction for Intra-Band Contiguous EN-DC	Rel-15	C009z	UEs supporting Intra-Band Contiguous EN-DC (2UL CCs) and modified MPR behaviour	E003		
6.2B.2.2	UE Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Rel-15	C010z	UEs supporting Intra-Band non-contiguous EN-DC (2UL CCs) and modified MPR behaviour	E004		
6.2B.2.3	UE Maximum Output Power reduction for Inter-Band EN-DC within FR1	Rel-15	C011z	UEs supporting Inter-Band EN-DC within FR1 (2UL CCs) and modified MPR behaviour	E005	PC3 PC2	NOTE 5 Skip TC 6.2B.2.3 if UE supports SA and TS 38.521-1 TC 6.2.2 has been executed.
6.2B.2.4	UE Maximum Output Power reduction for Inter-Band EN-DC including FR2	Rel-15	C012z	UEs supporting Inter-Band EN-DC including FR2 (2UL CCs) and modified MPR behaviour	E010		NOTE 1 NOTE 5 Skip TC 6.2B.2.4 if UE supports SA and TS 38.521-2 TC 6.2.2 has been executed.
6.2B.3	UE additional maximum output power reduction for EN-DC						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.2B.3.1	UE Additional Maximum Output Power reduction for Intra-band contiguous EN-DC	Rel-15	C009z	UEs supporting Intra-Band Contiguous EN-DC (2UL CCs) and modified MPR behaviour	E003		
6.2B.3.2	UE Additional Maximum Output Power reduction for Intra-Band Non-Contiguous EN-DC	Rel-15	FFS	FFS	FFS		NOTE 1
6.2B.3.3	UE additional Maximum Output power reduction for inter-band EN-DC within FR1	Rel-15	FFS	FFS	E005	PC3 PC2	NOTE 1 NOTE 5 Skip TC 6.2B.3.3 if UE supports SA and TS 38.521-1 TC 6.2.3 has been executed.
6.2B.3.4	UE Additional Maximum Output Power reduction for Inter-Band EN-DC including FR2	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.2B.3.4 if UE supports SA and TS 38.521-2 TC 6.2.3 has been executed.
6.2B.4	Configured output power for EN-DC						
6.2B.4.1	Configured output power level for EN-DC						
6.2B.4.1.1	Configured Output Power Level for Intra-Band Contiguous EN-DC	Rel-15	C009	UEs supporting Intra-Band Contiguous EN-DC (2UL CCs)	E003		NOTE 1
6.2B.4.1.2	Configured Output Power for Intra-Band Non-Contiguous EN-DC	Rel-15	C010	UEs supporting Intra-Band Non-Contiguous EN-DC (2UL CCs)	E004		NOTE 1
6.2B.4.1.3	Configured Output Power for Inter-Band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-Band EN-DC within FR1 (2UL CCs)	E005		NOTE 1
6.3	Output power dynamics						
6.3B	Output power dynamics for EN-DC						
6.3B.1	Minimum Output Power for EN-DC						
6.3B.1.1	Minimum Output power for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.3B.1.1 if UE supports SA and TS 38.521-1 TC 6.3.1 has been executed.
6.3B.1.2	Minimum output power for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.3B.1.2 if UE supports SA and TS 38.521-1 TC 6.3.1 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.3B.1.3	Minimum output power for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.3B.1.3 if UE supports SA and TS 38.521-1 TC 6.3.1 has been executed.
6.3B.1.4	Minimum Output Power for EN-DC Interband including FR2	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.3B.1.4 if UE supports SA and TS 38.521-2 TC 6.3.1 has been executed.
6.3B.2	Transmit OFF Power for EN-DC						
6.3B.2.4_1	Transmit OFF Power for inter-band EN-DC including FR2 (>2 CCs)						
6.3B.2.4_1.1	Transmit OFF Power for inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.3B.2.4_1.1 if UE supports SA and TS 38.521-2 TC 6.3A.2.1 has been executed.
6.3B.2.4_1.2	Transmit OFF Power for inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.3B.2.4_1.2 if UE supports SA and TS 38.521-2 TC 6.3A.2.2 has been executed.
6.3B.2.4_1.3	Transmit OFF Power for inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.3B.2.4_1.3 if UE supports SA and TS 38.521-2 TC 6.3A.2.3 has been executed.
6.3B.3	Tx ON/OFF time mask for EN-DC						
6.3B.3.1	Tx ON/OFF time mask for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.3B.3.1 if UE supports SA and TS 38.521-1 TC 6.3.3.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.3B.3.2	Tx ON/OFF time mask for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.3B.3.2 if UE supports SA and TS 38.521-1 TC 6.3.3.2 has been executed.
6.3B.3.3	Tx ON/OFF time mask for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.3B.3.3 if UE supports SA and TS 38.521-1 TC 6.3.3.2 has been executed.
6.3B.3.4	Tx ON/OFF time mask for inter-band EN-DC including FR2	Rel-15	FFS	FFS	FFS		NOTE 1
6.3B.4	PRACH Time Mask						
6.3B.4.1	PRACH time mask for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.3B.4.1 if UE supports SA and TS 38.521-1 TC 6.3.3.4 has been executed.
6.3B.4.2	PRACH Time Mask for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.3B.4.2 if UE supports SA and TS 38.521-1 TC 6.3.3.4 has been executed.
6.3B.4.3	PRACH Time Mask for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.3B.4.3 if UE supports SA and TS 38.521-1 TC 6.3.3.4 has been executed.
6.3B.8	Power control for EN-DC						
6.3B.8.1	Absolute power tolerance for EN-DC						
6.3B.8.1.1	Absolute Power Tolerance for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2 UL CCs)	E003		NOTE 5 Skip TC 6.3B.8.1.1 if UE supports SA and TS 38.521-1 TC 6.3.4.2 has been executed.
6.3B.8.1.2	Absolute Power Tolerance for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2 UL CCs)	E004		NOTE 5 Skip TC 6.3B.8.1.2 if UE supports SA and TS 38.521-1 TC 6.3.4.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.3B.8.1.3	Absolute Power Tolerance for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2 UL CCs)	E005		NOTE 5 Skip TC 6.3B.8.1.3 if UE supports SA and TS 38.521-1 TC 6.3.4.2 has been executed.
6.3B.8.1.4	Absolute Power Tolerance for inter-band EN-DC including FR2	Rel-15	FFS	FFS	FFS		NOTE 1
6.3B.8.2	Relative power tolerance for EN-DC						
6.3B.8.2.1	Relative Power Tolerance for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2 UL CCs)	E003		NOTE 5 Skip TC 6.3B.8.2.1 if UE supports SA and TS 38.521-1 TC 6.3.4.3 has been executed.
6.3B.8.2.2	Relative Power Tolerance for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2 UL CCs)	E004		NOTE 5 Skip TC 6.3B.8.2.2 if UE supports SA and TS 38.521-1 TC 6.3.4.3 has been executed.
6.3B.8.2.3	Relative Power Tolerance for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2 UL CCs)	E005		NOTE 5 Skip TC 6.3B.8.2.3 if UE supports SA and TS 38.521-1 TC 6.3.4.3 has been executed.
6.3B.8.2.4	Relative Power Tolerance for inter-band EN-DC including FR2	Rel-15	FFS	FFS	FFS		NOTE 1
6.3B.8.1	Aggregate power tolerance for EN-DC						
6.3B.8.3.1	Aggregate Power Tolerance for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2 UL CCs)	E003		NOTE 5 Skip TC 6.3B.8.3.1 if UE supports SA and TS 38.521-1 TC 6.3.4.4 has been executed.
6.3B.8.3.2	Aggregate Power Tolerance for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2 UL CCs)	E004		NOTE 5 Skip TC 6.3B.8.3.2 if UE supports SA and TS 38.521-1 TC 6.3.4.4 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.3B.8.3.3	Aggregate Power Tolerance for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2 UL CCs)	E005		NOTE 5 Skip TC 6.3B.8.3.3 if UE supports SA and TS 38.521-1 TC 6.3.4.4 has been executed.
6.3B.8.3.4	Aggregate Power Tolerance for inter-band EN-DC including FR2	Rel-15	FFS	FFS	FFS		NOTE 1
6.4	Transmit signal quality						
6.4B	Transmit Signal Quality for EN-DC						
6.4B.1	Frequency Error for EN-DC						
6.4B.1.1	Frequency Error for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting Intra-Band Contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.4B.1.1 if UE supports SA and TS 38.521-1 TC 6.4.1 has been executed.
6.4B.1.2	Frequency Error for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.4B.1.2 if UE supports SA and TS 38.521-1 TC 6.4.1 has been executed.
6.4B.1.3	Frequency error for Inter-band EN-DC within FR1	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.4B.1.3 if UE supports SA and TS 38.521-1 TC 6.4.1 has been executed.
6.4B.1.4	Frequency Error for inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-Band EN-DC including FR2 (2UL CCs)	E010		NOTE 5 Skip TC 6.4B.1.4 if UE supports SA and TS 38.521-2 TC 6.4.1 has been executed.
6.4B.1.4_1	Frequency Error for inter-band EN-DC including FR2 (>2 CCs)						
6.4B.1.4_1.1	Frequency Error for inter-band EN-DC including FR2 (3 CCs)	Rel-15	C012b	UEs supporting Inter-Band EN-DC including FR2 with 3 UL CCs (2NR UL CCs)	E011		NOTE 5
6.4B.1.4_1.2	Frequency Error for inter-band EN-DC including FR2 (4 CCs)	Rel-15	C012c	UEs supporting Inter-Band EN-DC including FR2 with 4 UL CCs (3NR UL CCs)	E012		NOTE 5

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4B.1.4_1.3	Frequency Error for inter-band EN-DC including FR2 (5 CCs)	Rel-15	C012d	UEs supporting Inter-Band EN-DC including FR2 with 5 UL CCs (4NR UL CCs)	E013		NOTE 5
6.4B.2	Transmit Modulation Quality EN-DC						
6.4B.2.1	Transmit Modulation Quality for intra-band contiguous EN-DC						
6.4B.2.1.1	Error Vector Magnitude for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.4B.2.1.1 if UE supports SA and TS 38.521-1 TC 6.4.2.1 has been executed.
6.4B.2.1.2	Carrier Leakage for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.4B.2.1.2 if UE supports SA and TS 38.521-1 TC 6.4.2.2 has been executed.
6.4B.2.1.3	In-band Emissions for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		
6.4B.2.1.4	EVM Equalizer Flatness for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.4B.2.1.4 if UE supports SA and TS 38.521-1 TC 6.4.2.4 has been executed.
6.4B.2.2	Transmit Modulation Quality for intra-band non-contiguous EN-DC						
6.4B.2.2.1	Error Vector Magnitude for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.4B.2.2.1 if UE supports SA and TS 38.521-1 TC 6.4.2.1 has been executed.
6.4B.2.2.2	Carrier Leakage for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.4B.2.2.2 if UE supports SA and TS 38.521-1 TC 6.4.2.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4B.2.2.3	In-band Emissions for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.4B.2.2.3 if UE supports SA and TS 38.521-1 TC 6.4.2.3 has been executed.
6.4B.2.2.4	EVM Equalizer Flatness for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.4B.2.2.4 if UE supports SA and TS 38.521-1 TC 6.4.2.4 has been executed.
6.4B.2.3	Transmit Modulation Quality for inter-band EN-DC within FR1						
6.4B.2.3.1	Error Vector Magnitude for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.4B.2.3.1 if UE supports SA and TS 38.521-1 TC 6.4.2.1 has been executed.
6.4B.2.3.2	Carrier Leakage for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.4B.2.3.2 if UE supports SA and TS 38.521-1 TC 6.4.2.2 has been executed.
6.4B.2.3.3	In-band Emissions for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.4B.2.3.3 if UE supports SA and TS 38.521-1 TC 6.4.2.3 has been executed.
6.4B.2.3.4	EVM Equalizer Flatness for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.4B.2.3.4 if UE supports SA and TS 38.521-1 TC 6.4.2.4 has been executed.
6.4B.2.4	Transmit Modulation Quality for inter-band EN-DC including FR2						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.4B.2.4.1	Error Vector Magnitude for inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.4B.2.4.1 if UE supports SA and TS 38.521-2 TC 6.4.2.1 has been executed.
6.4B.2.4.2	Carrier Leakage for inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.4B.2.4.2 if UE supports SA and TS 38.521-2 TC 6.4.2.2 has been executed.
6.4B.2.4.3	In-band Emissions for inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.4B.2.4.3 if UE supports SA and TS 38.521-2 TC 6.4.2.3 has been executed.
6.4B.2.4.4	EVM Equalizer Flatness for inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.4B.2.4.4 if UE supports SA and TS 38.521-2 TC 6.4.2.4 has been executed.
6.5B	Output RF spectrum emissions for EN-DC						
6.5B.1	Occupied bandwidth for EN-DC						
6.5B.1.1	Occupied bandwidth for Intra-Band Contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 1
6.5B.1.2	Occupied bandwidth for Intra-Band Non-Contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 1 NOTE 5 Skip TC6.5B.1.2 if UE supports SA and TS 38.521-1 TC 6.5.1 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.1.3	Occupied bandwidth for Inter-Band EN-DC within FR1	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC6.5B.1.3 if UE supports SA and TS 38.521-1 TC 6.5.1 has been executed.
6.5B.1.4	Occupied bandwidth for Inter-Band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.5B.1.4 if UE supports SA and TS 38.521-2 TC 6.5.1 has been executed.
6.5B.1.4_1	Occupied bandwidth for inter-band EN-DC including FR2 (>2 CCs)						
6.5B.1.4_1.1	Occupied bandwidth for inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.1.4_1.1 if UE supports SA and TS 38.521-2 TC 6.5A.1.1 has been executed.
6.5B.1.4_1.2	Occupied bandwidth for inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.1.4_1.2 if UE supports SA and TS 38.521-2 TC 6.5A.1.2 has been executed.
6.5B.1.4_1.3	Occupied bandwidth for inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.1.4_1.3 if UE supports SA and TS 38.521-2 TC 6.5A.1.3 has been executed.
6.5B.2	Out of Band emissions for EN-DC						
6.5B.2.1	Out of Band Emissions for intra-band contiguous EN-DC						
6.5B.2.1.1	Spectrum emissions mask for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		
6.5B.2.1.2	Additional spectrum emissions mask for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.2.1.3	Adjacent channel leakage ratio for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		
6.5B.2.2	Out-of-band emissions for Intra-band non-contiguous EN-DC						
6.5B.2.2.1	Spectrum emissions mask for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 1 NOTE 5 Skip TC 6.5B.2.2.1 if UE supports SA and TS 38.521-1 TC 6.5.2.2 has been executed.
6.5B.2.2.3	Adjacent channel leakage ratio for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 1 NOTE 5 Skip TC 6.5B.2.2.3 if UE supports SA and TS 38.521-1 TC 6.5.2.4.1 has been executed.
6.5B.2.3	Out-of-band emissions for Inter-band EN-DC within FR1						
6.5B.2.3.1	Spectrum emissions mask for Inter-band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.5B.2.3.1 if UE supports SA and TS 38.521-1 6.5.2.2 has been executed.
6.5B.2.3.2	Additional Spectrum emissions mask for Inter-band EN-DC within FR1	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.3.2 if UE supports SA and TS 38.521-1 6.5.2.2 has been executed.
6.5B.2.3.3	Adjacent channel leakage ratio for inter-band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.5B.2.3.3 if UE supports SA and TS 38.521-1 6.5.2.4.1 has been executed.
6.5B.2.4	Out-of-band emissions for Inter-band EN-DC including FR2						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.2.4.1	Spectrum emissions mask for Inter-band EN-DC including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 5 Skip TC 6.5B.2.4.1 if UE supports SA and TS 38.521-2 TC 6.5.2.1 has been executed.
6.5B.2.4.1_1	Spectrum emissions mask for Inter-band EN-DC including FR2 (>2 CCs)						
6.5B.2.4.1_1.1	Spectrum emissions mask for Inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.1_1.1 if UE supports SA and TS 38.521-2 TC 6.5A.2.1.1 has been executed.
6.5B.2.4.1_1.2	Spectrum emissions mask for Inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.1_1.2 if UE supports SA and TS 38.521-2 TC 6.5A.2.1.2 has been executed.
6.5B.2.4.1_1.3	Spectrum emissions mask for Inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.1_1.3 if UE supports SA and TS 38.521-2 TC 6.5A.2.1.3 has been executed.
6.5B.2.4.3	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (2 CCs)	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.3 if UE supports SA and TS 38.521-2 TC 6.5.2.3 has been executed.
6.5B.2.4.3_1	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (>2 CCs)						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.2.4.3_1.1	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.3_1.1 if UE supports SA and TS 38.521-2 TC 6.5A.2.2.1 has been executed.
6.5B.2.4.3_1.2	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.3_1.2 if UE supports SA and TS 38.521-2 TC 6.5A.2.2.2 has been executed.
6.5B.2.4.3_1.3	Adjacent channel leakage ratio for Inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.2.4.3_1.3 if UE supports SA and TS 38.521-2 TC 6.5A.2.2.3 has been executed.
6.5B.3	Spurious emissions for EN-DC						
6.5B.3.1	Spurious Emissions for intra-band contiguous EN-DC						
6.5B.3.1.1	General spurious emissions for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		NOTE 5 Skip TC 6.5B.3.1.1 if UE supports SA and TS 38.521-1 TC 6.5.3.1 has been executed.
6.5B.3.1.2	Spurious emission band UE co-existence for intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		
6.5B.3.2	Spurious Emissions for intra-band non-contiguous EN-DC						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.3.2.1	General spurious emissions for intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 5 Skip TC 6.5B.3.2.1 if UE supports SA and TS 38.521-1 TC 6.5.3.1 has been executed.
6.5B.3.2.2	Spurious emission band UE co-existence for intra-band non-contiguous EN-DC	Rel-15	FFS	FFS	FFS		NOTE 1
6.5B.3.3	Spurious emissions for Inter-band EN-DC within FR1						
6.5B.3.3.1	General spurious emissions for Inter-band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-band EN-DC within FR1 (2UL CCs)	E005		
6.5B.3.3.2	Spurious emission band UE co-existence for Inter-band within FR1	Rel-15	C011	UEs supporting Inter-band EN-DC within FR1 (2UL CCs)	E005		
6.5B.3.4	Spurious emissions for Inter-band including FR2						
6.5B.3.4.1	General Spurious Emissions for Inter-band including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1 NOTE 5 Skip TC 6.5B.3.4.1 if UE supports SA and TS 38.521-2 TC 6.5.3.1 has been executed.
6.5B.3.4.1_1	General Spurious Emissions for Inter-band including FR2 (>2 CCs)						
6.5B.3.4.1_1.1	General Spurious Emissions for Inter-band including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.3.4.1_1.1 if UE supports SA and TS 38.521-2 TC 6.5A.3.1.1 has been executed.
6.5B.3.4.1_1.2	General Spurious Emissions for Inter-band including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.3.4.1_1.2 if UE supports SA and TS 38.521-2 TC 6.5A.3.1.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
6.5B.3.4.1_1.3	General Spurious Emissions for Inter-band including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 6.5B.3.4.1_1.3 if UE supports SA and TS 38.521-2 TC 6.5A.3.1.3 has been executed.
6.5B.3.4.2	Spurious emission band UE co-existence for Inter-band including FR2	Rel-15	C012	UEs supporting Inter-band including FR2 (2UL CCs)	E010		NOTE 1
6.5B.4	Additional Spurious Emissions						
6.5B.4.1	Additional Spurious Emissions for Intra-band contiguous EN-DC	Rel-15	C009	UEs supporting intra-band contiguous EN-DC (2UL CCs)	E003		
6.5B.4.2	Additional Spurious Emissions for Intra-band non-contiguous EN-DC	Rel-15	C010	UEs supporting intra-band non-contiguous EN-DC (2UL CCs)	E004		NOTE 1
6.5B.4.3	Additional Spurious Emissions for Inter-band EN-DC	Rel-15	C011	UEs supporting inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.5B.4.3 if UE supports SA and TC 38.521-1 TC 6.5.3.3 has been executed.
6.5B.5	Transmit Intermodulation						
6.5B.5.3	Transmit Intermodulation for Inter-band EN-DC within FR1	Rel-15	C011	UEs supporting Inter-band EN-DC within FR1 (2UL CCs)	E005		NOTE 5 Skip TC 6.5B.5.3 if UE supports SA and TC 38.521-1 TC 6.5.4 has been executed.
7	Receiver Characteristics						
7.3	Reference sensitivity						
7.3A	Reference sensitivity for CA without EN-DC						
7.3B	Reference sensitivity level for DC						
7.3B.2	Reference Sensitivity for EN-DC						
7.3B.2.1	Reference sensitivity for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting intra-band contiguous EN-DC (2DL CCs)	E003a		
7.3B.2.2	Reference sensitivity for Intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting intra-band non-contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.3B.2.2 if UE supports SA and TS 38.521-1 TC 7.3.2 has been executed.
7.3B.2.3	Reference sensitivity for Inter-band EN-DC within FR1	Rel-15	C011a	UEs supporting inter-band EN-DC within FR1 (2DL CCs)	E005a		

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.3B.2.3_1	Reference sensitivity for EN-DC within FR1 (>2 CCs)						
7.3B.2.3_1.1	Reference sensitivity for EN-DC within FR1 (3 CCs)	Rel-15	FFS	FFS	FFS		
7.3B.2.4	Reference sensitivity for Inter-band EN-DC including FR2 (2 CCs)	Rel-15	C012a	UEs supporting inter-band EN-DC including FR2 (2DL CCs)	E010a		NOTE 5 Skip TC 7.3B.2.4 if UE supports SA and TS 38.521-2 TC 7.3.2 has been executed.
7.3B.2.4_1	Reference sensitivity for Inter-band EN-DC including FR2 (>2 CCs)						
7.3B.2.4_1.1	Reference sensitivity for Inter-band EN-DC including FR2 (3 CCs)	Rel-15	C012e	UEs supporting inter-band EN-DC including FR2 with 3 DL CCs (2NR DL CCs)	E011a		NOTE 5 Skip TC 7.3B.2.4_1.1 if UE supports SA and TS 38.521-2 TC 7.3A.2.1 has been executed.
7.3B.4	EIS Spherical Coverage for Inter-band EN-DC including FR2	Rel-15	C012a	UEs supporting inter-band EN-DC including FR2 (2DL CCs)	E010a		NOTE 5 Skip TC 7.3B.4 if UE supports SA and TS 38.521-2 TC 7.3.4 has been executed.
7.4	Maximum Input Level						
7.4B	Maximum Input Level for EN-DC						
7.4B.1	Maximum Input Level for Intra-Band Contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		
7.4B.2	Maximum Input Level for Intra-Band Non-Contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting Intra-Band Non-Contiguous EN-DC (2DL CCs)	E004a		
7.4B.3	Maximum Input Level for Inter-band EN-DC within FR1	Rel-15	C011a	UEs supporting Inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.4B.3 if UE supports SA and TS 38.521-1 TC 7.4 has been executed.
7.4B.4	Maximum Input Level for inter-band EN-DC including FR2 (2 CCs)	Rel-15	C012a	UEs supporting Inter-band including FR2 (2DL CCs)	E010a		NOTE 1 NOTE 5 Skip TC 7.4B.4 if UE supports SA and TS 38.521-1 7.4 has been executed.
7.5B.1	Adjacent Channel Selectivity for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting intra-band contiguous EN-DC (2DL CCs)	E003a		NOTE 1

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.5B.2	Adjacent Channel Selectivity for intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting intra-band non-contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.5B.2 if UE supports SA and TS 38.521-1 TC 7.5 has been executed.
7.5B.3	Adjacent Channel Selectivity for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.5B.3 if UE supports SA and TS 38.521-1 TC 7.5 has been executed.
7.5B.4	Adjacent Channel Selectivity for inter-band EN-DC including FR2						
7.5B.4.1	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (2 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.5B.4 if UE supports SA and TS 38.521-2 TC 7.5 has been executed.
7.5B.4_1	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (>2 CCs)						
7.5B.4_1.1	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.5B.4_1.1 if UE supports SA and TS 38.521-2 TC 7.5A.1 has been executed.
7.5B.4_1.2	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.5B.4_1.2 if UE supports SA and TS 38.521-2 TC 7.5A.2 has been executed.
7.5B.4_1.3	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.5B.4_1.3 if UE supports SA and TS 38.521-2 TC 7.5A.3 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.5B.4_1.4	Adjacent Channel Selectivity for inter-band EN-DC including FR2 (6 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.5B.4_1.4 if UE supports SA and TS 38.521-2 TC 7.5A.4 has been executed.
7.6A	Blocking Characteristics for CA	Rel-15	FFS	FFS	FFS		NOTE 1
7.6B	Blocking Characteristics for EN-DC in FR1						
7.6B.2	Inband blocking for EN-DC within FR1						
7.6B.2.1	Inband blocking for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		
7.6B.2.2	Inband blocking for intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting Intra-Band Non-Contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.6B.2.2 if UE supports SA and TS 38.521-1 TC 7.6.2 has been executed.
7.6B.2.3	Inband blocking for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting Inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.6B.2.3 if UE supports SA and TS 38.521-1 TC 7.6.2 has been executed.
7.6B.2.3_1.1	Inband blocking for EN-DC within FR1 (3 CCs)	Rel-15	C045	UEs supporting intra-band contiguous EN-DC within FR1 with 3 DL CCs or inter-band EN-DC within FR1 with 3 DL CCs (2NR DL CCs)	E006		
7.6B.2.3_1.2	Inband blocking for EN-DC within FR1 (4 CCs)	Rel-15	C046	UEs supporting intra-band contiguous EN-DC within FR1 with 4 DL CCs or inter-band EN-DC within FR1 with 4 DL CCs (3NR DL CCs)	E007		
7.6B.2.3_1.3	Inband blocking for EN-DC within FR1 (5 CCs)	Rel-16	C047	UEs supporting inter-band EN-DC within FR1 with 5 DL CCs (4 NR DL CCs)	E008		NOTE 1 Skip TC 7.6B.2.3_1.3 if UE supports NSA and TS 38.521-1 TC 7.6A.2.3 has been executed.
7.6B.2.4	Inband blocking for inter-band EN-DC including FR2 (2 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.6B.2.4 if UE supports SA and TS 38.521-2 TC 7.6.2 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.6B.3	Out-of-band blocking for EN-DC in FR1						
7.6B.3.1	Out-of-band blocking for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		
7.6B.3.2	Out-of-band blocking for intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting Intra-Band Non-Contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.6B.3.2 if UE supports SA and TS 38.521-1 TC 7.6.3 has been executed.
7.6B.3.3	Out-of-band blocking for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting Inter-band EN-DC within FR1 (2DL CCs)	E005a		
7.6B.3.3_1.1	Out-of-band blocking for EN-DC within FR1 (3 CCs)	Rel-15	C048	UEs supporting intra-band contiguous EN-DC in FR1 with 3 DL CCs	E006		
7.6B.3.3_1.2	Out-of-band blocking for EN-DC within FR1 (4 CCs)	Rel-15	C049	UEs supporting intra-band contiguous EN-DC in FR1 with 4 DL CCs	E007		
7.6B.4	Narrow band blocking for EN-DC in FR1						
7.6B.4.1	Narrow band blocking for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		
7.6B.4.2	Narrow band blocking for intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting Intra-Band Non-Contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.6B.4.2 if UE supports SA and TS 38.521-1 TC 7.6.4 has been executed.
7.6B.4.3	Narrow band blocking for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting Inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.6B.4.3 if UE supports SA and TS 38.521-1 TC 7.6.4 has been executed.
7.6B.4.3_1.1	Narrow band blocking for EN-DC within FR1 (3 CCs)	Rel-15	C045	UEs supporting intra-band contiguous EN-DC within FR1 with 3 DL CCs or inter-band EN-DC within FR1 with 3 DL CCs (2NR DL CCs)	E006		
7.6B.4.3_1.2	Narrow band blocking for EN-DC within FR1 (4 CCs)	Rel-15	C046	UEs supporting intra-band contiguous EN-DC within FR1 with 4 DL CCs or inter-band EN-DC within FR1 with 4 DL CCs (3NR DL CCs)	E007		
7.6B.4.3_1.3	Narrow band blocking for EN-DC within FR1 (5 CCs)	Rel-16	C047	UEs supporting inter-band EN-DC within FR1 with 5 DL CCs (4 NR DL CCs)	E008		Skip TC 7.6B.4.3_1.3 if UE supports NSA and TS 38.521-1 TC 7.6A.4.3 has been executed.

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.7	Spurious Response						
7.7B	Spurious Response for EN-DC in FR1						
7.7B.1	Spurious Response for intra-band contiguous EN-DC (2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		
7.7B.2	Spurious Response for intra-band non-contiguous EN-DC (2 CCs)	Rel-15	C010a	UEs supporting Intra-Band Non-Contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.7B.2 if UE supports SA and TS 38.521-1 TC 7.7 has been executed.
7.7B.3	Spurious Response for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting Inter-band EN-DC within FR1 (2DL CCs)	E005a		
7.7B.3_1.1	Spurious Response for EN-DC within FR1 (3 CCs)	Rel-15	C048	UEs supporting intra-band contiguous EN-DC in FR1 with 3 DL CCs	E006		
7.7B.3_1.2	Spurious Response for EN-DC within FR1 (4 CCs)	Rel-15	C049	UEs supporting intra-band contiguous EN-DC in FR1 with 4 DL CCs	E007		
7.8	Intermodulation Characteristics						
7.8B	Intermodulation Characteristics for EN-DC in FR1						
7.8B.2	Wideband Intermodulation						
7.8B.2.1	Wideband Intermodulation for intra-band contiguous EN-DC in FR1	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		NOTE 1
7.8B.2.2	Wideband Intermodulation for intra-band non-contiguous EN-DC in FR1	Rel-15	C010a	UEs supporting Intra-Band non-contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.8B.2.2 if UE supports SA and TS 38.521-1 TC 7.8.2 has been executed.
7.8B.2.3	Wideband Intermodulation for inter-band EN-DC in FR1 (2 CCs)	Rel-15	C011a	UEs supporting inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.8B.2.3 if UE supports SA and TS 38.521-1 TC 7.8.2 has been executed.
7.8B.2.3_1	Wideband Intermodulation for inter-band EN-DC within FR1 (>2 CCs)						
7.8B.2.3_1.1	Wideband Intermodulation for EN-DC within FR1 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1 NOTE 5 Skip TC 7.8B.2.3_1.1 if UE supports SA and TS 38.521-1 TC 7.8A.2.1 has been executed.
7.9	Spurious Emissions						

Clause	TC Title	Release	Applicability		Tested Bands/CA/DC-Configurations Selection	Branch	Additional Information
			Condition	Comment			
7.9B	Spurious Emissions for EN-DC in FR1						
7.9B.1	Spurious Emissions for intra-band contiguous EN-DC in FR1(2 CCs)	Rel-15	C009a	UEs supporting Intra-Band Contiguous EN-DC (2DL CCs)	E003a		NOTE 5 Skip TC 7.9B.1 if UE supports SA and TS 38.521-1 TC 7.9 has been executed.
7.9B.2	Spurious Emissions for intra-band non-contiguous EN-DC in FR1(2 CCs)	Rel-15	C010a	UEs supporting Intra-Band non-contiguous EN-DC (2DL CCs)	E004a		NOTE 5 Skip TC 7.9B.2 if UE supports SA and TS 38.521-1 TC 7.9 has been executed.
7.9B.3	Spurious Emissions for inter-band EN-DC within FR1 (2 CCs)	Rel-15	C011a	UEs supporting inter-band EN-DC within FR1 (2DL CCs)	E005a		NOTE 5 Skip TC 7.9B.3 if UE supports SA and TS 38.521-1 TC 7.9 has been executed.
7.9B.3_1	Spurious Emissions for inter-band EN-DC within FR1 (>2 CCs)						
7.9B.4	Spurious Emissions for inter-band EN-DC including FR2 (2 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1
7.9B.4_1	Spurious Emissions for inter-band EN-DC including FR2 (>2 CCs)						
7.9B.4_1.1	Spurious Emissions for inter-band EN-DC including FR2 (3 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1
7.9B.4_1.2	Spurious Emissions for inter-band EN-DC including FR2 (4 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1
7.9B.4_1.3	Spurious Emissions for inter-band EN-DC including FR2 (5 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1
7.9B.4_1.4	Spurious Emissions for inter-band EN-DC including FR2 (6 CCs)	Rel-15	FFS	FFS	FFS		NOTE 1
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.521-3.							
NOTE 2: Void.							
NOTE 3: Void.							
NOTE 4: Void.							
NOTE 5: Test only one EN-DC combination per 5G NR band as LTE anchor agnostic approach is applied.							

Table 4.1.3-1a: Void

Table 4.1.3-1b: Void

Table 4.1.3-1c: Void

4.1.4 Performance conformance test cases

Table 4.1.4-1: Applicability of performance test cases, ref. TS 38.521-4 [4]

Clause	TC Title	Release	Applicability		Tested Bands Selection	Additional Information
			Condition	Comment		
5	Demodulation performance requirements (Conducted requirements)					
5.2	PDSCH demodulation requirements					
5.2.2.1.1_1	2Rx FDD FR1 PDSCH mapping Type A performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008 D010	
5.2.2.1.1_2	2Rx FDD FR1 PDSCH mapping Type A performance - 2x2 MIMO with enhanced receiver type 1 for both SA and NSA	Rel-15	C015x	UEs supporting 5GS FDD FR1 and Enhanced Receiver Type 1 but not supporting FDD bands with 4Rx UE capability	D008	
5.2.2.1.2_1	2Rx FDD FR1 PDSCH mapping Type A and CSI-RS overlapped with PDSCH performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
5.2.2.1.3_1	2Rx FDD FR1 PDSCH mapping Type B performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C015b	UEs supporting 5GS FDD FR1 and PDSCH mapping Type B but not supporting FDD bands with 4Rx UE capability	D008	
5.2.2.1.4_1	2Rx FDD FR1 PDSCH Mapping Type A and LTE-NR coexistence performance - 4x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C015y	UEs supporting 5GS FDD FR1 and additional DMRS for coexistence with LTE CRS but not supporting FDD bands with 4Rx UE capability	D008	
5.2.2.2.1_1	2Rx TDD FR1 PDSCH mapping Type A performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D009 D010	
5.2.2.2.1_2	2Rx TDD FR1 PDSCH mapping Type A performance - 2x2 MIMO with enhanced receiver type 1 for both SA and NSA	Rel-15	C016x	UEs supporting 5GS TDD FR1 and Enhanced Receiver Type 1 but not supporting TDD bands with 4Rx UE capability	D010	
5.2.2.2.2_1	2Rx TDD FR1 PDSCH mapping Type A and CSI-RS overlapped with PDSCH performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
5.2.2.2.3_1	2Rx TDD FR1 PDSCH mapping Type B performance - 2x2 MIMO with baseline receiver for both SA and NSA	Rel-15	C016b	UEs supporting 5GS TDD FR1 and PDSCH mapping Type B but not supporting TDD bands with 4Rx UE capability	D010	
5.2.2.2.4_1	2Rx TDD FR1 PDSCH Mapping Type A and LTE-NR coexistence performance - 4x2 MIMO with baseline receiver for both SA and NSA	Rel-16	C016y	UEs supporting 5GS TDD FR1 and additional DMRS for coexistence with LTE CRS but not supporting TDD bands with 4Rx UE capability	D008	
5.2.3.1.1_1	4Rx FDD FR1 PDSCH mapping Type A performance - 2x4 MIMO baseline receiver for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D009	
5.2.3.1.1_2	4Rx FDD FR1 PDSCH mapping Type A performance - 4x4 MIMO baseline receiver for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D009	

Clause	TC Title	Release	Applicability		Tested Bands Selection	Additional Information
			Condition	Comment		
5.2.3.1.1_4	4Rx FDD FR1 PDSCH mapping Type A performance - 4x4 MIMO with enhanced receiver type 1 for both SA and NSA	Rel-15	C017x	UEs supporting 5GS FDD FR1 and 4Rx antenna ports and Enhanced Receiver Type 1	D008	
5.2.3.1.2_1	4Rx FDD FR1 PDSCH mapping Type A and CSI-RS overlapped with PDSCH performance - 4x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
5.2.3.1.3_1	4Rx FDD FR1 PDSCH mapping Type B performance - 2x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C017b	UEs supporting 5GS FDD FR1 and 4Rx antenna ports and PDSCH mapping Type B	D008 D011	
5.2.3.1.4_1	4Rx FDD FR1 PDSCH Mapping Type A and LTE-NR coexistence performance - 4x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C017y	UEs supporting 5GS FDD FR1 and 4Rx antenna ports and LTE-NR coexistence	D008	
5.2.3.2.1_1	4Rx TDD FR1 PDSCH mapping Type A performance - 2x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D009 D010	
5.2.3.2.1_2	4Rx TDD FR1 PDSCH mapping Type A performance - 4x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
5.2.3.2.1_4	4Rx TDD FR1 PDSCH mapping Type A performance - 4x4 MIMO with enhanced receiver type 1 for both SA and NSA	Rel-15	C019x	UEs supporting 5GS TDD FR1 and Enhanced Receiver Type 1 and 4Rx antenna ports	D010	
5.2.3.2.2_1	4Rx TDD FR1 PDSCH mapping Type A and CSI-RS overlapped with PDSCH performance - 2x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D009 D010	
5.2.3.2.3_1	4Rx TDD FR1 PDSCH mapping Type B performance - 2x4 MIMO with baseline receiver for both SA and NSA	Rel-15	C019b	UEs supporting 5GS TDD FR1 and 4Rx antenna ports and PDSCH mapping Type B	D009 D011	
5.3.2.1.1	2Rx FDD FR1 PDCCH 1 Tx antenna performance for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
5.3.2.1.2	2Rx FDD FR1 PDCCH 2 Tx antenna performance for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
5.3.2.2.1	2Rx TDD FR1 PDCCH 1 Tx antenna performance for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
5.3.2.2.2	2Rx TDD FR1 PDCCH 2 Tx antenna performance for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
5.3.3.1.1	4Rx FDD FR1 PDCCH 1 Tx antenna performance for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
5.3.3.1.2	4Rx FDD FR1 PDCCH 2 Tx antenna performance for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
5.3.3.2.1	4Rx TDD FR1 PDCCH 1 Tx antenna performance for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	

Clause	TC Title	Release	Applicability		Tested Bands Selection	Additional Information
			Condition	Comment		
5.3.3.2.2	4Rx TDD FR1 PDCCH 2 Tx antenna performance for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
5.5.1	FR1 Sustained downlink data rate performance for single carrier	Rel-15	C001	UEs supporting 5GS FDD FR1 or TDD FR1 (SA)	D008 D009 D010	
6	CSI reporting requirements (Conducted requirements)					
6.2.2.1.1.1	2Rx FDD FR1 periodic CQI reporting under AWGN conditions for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.2.2.1.2.1	2Rx FDD FR1 periodic wideband CQI reporting under fading conditions for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.2.2.1.2.2	2Rx FDD FR1 aperiodic subband CQI reporting under fading conditions for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.2.2.2.1.1	2Rx TDD FR1 periodic CQI reporting under AWGN conditions for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.2.2.2.2.1	2Rx TDD FR1 periodic wideband CQI reporting under fading conditions for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.2.2.2.2.2	2Rx TDD FR1 aperiodic subband CQI reporting under fading conditions for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.2.3.1.1.1	4Rx FDD FR1 periodic CQI reporting under AWGN conditions for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
6.2.3.1.2.1	4Rx FDD FR1 periodic wideband CQI reporting under fading conditions for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
6.2.3.1.2.2	4Rx FDD FR1 aperiodic subband CQI reporting under fading conditions for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008	
6.2.3.2.1.1	4Rx TDD FR1 periodic CQI reporting under AWGN conditions for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
6.2.3.2.2.1	4Rx TDD FR1 periodic wideband CQI reporting under fading conditions for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
6.2.3.2.2.2	4Rx TDD FR1 aperiodic subband CQI reporting under fading conditions for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
6.3.2.1.1	2Rx FDD FR1 Single PMI with 4Tx Type1 – SinglePanel codebook for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.3.2.1.2	2Rx FDD FR1 Single PMI with 8Tx Type1 – SinglePanel codebook for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	

Clause	TC Title	Release	Applicability		Tested Bands Selection	Additional Information
			Condition	Comment		
6.3.2.1.3	2Rx FDD FR1 Multiple PMI with 16Tx Type I – SinglePanel Codebook for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.3.2.2.1	2Rx TDD FR1 Single PMI with 4Tx Type1 - SinglePanel codebook for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.3.2.2.2	2Rx TDD FR1 Single PMI with 8Tx Type1 - SinglePanel codebook for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.3.2.2.3	2Rx TDD FR1 Single PMI with 16Tx Type1 - SinglePanel codebook for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.3.2.2.4	2Rx TDD FR1 Single PMI with 32Tx Type1 - SinglePanel codebook for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.3.3.1.1	4Rx FDD FR1 Single PMI with 4Tx Type1 -- SinglePanel codebook for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D011	
6.3.3.1.2	4Rx FDD FR1 Single PMI with 8Tx Type1 -- SinglePanel codebook for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D011	
6.3.3.1.3	4Rx FDD FR1 Multiple PMI with 16Tx Type I – SinglePanel Codebook for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D011	
6.3.3.2.1	4Rx TDD FR1 Single PMI with 4Tx Type1 -- SinglePanel codebook for both SA and NSA	Rel-15	C019	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D010 D011	
6.3.3.2.2	4Rx TDD FR1 Single PMI with 8Tx Type1 -- SinglePanel codebook for both SA and NSA	Rel-15	C019	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D010 D011	
6.3.3.2.3	4Rx TDD FR1 Single PMI with 16Tx Type1 - SinglePanel codebook for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010	
6.4.2.1_1	2Rx FDD FR1 RI reporting for both SA and NSA	Rel-15	C015	UEs supporting 5GS FDD FR1 but not supporting FDD bands with 4Rx UE capability	D008	
6.4.2.2_1	2Rx TDD FR1 RI reporting for both SA and NSA	Rel-15	C016	UEs supporting 5GS TDD FR1 but not supporting TDD bands with 4Rx UE capability	D010	
6.4.3.1_1	4Rx FDD FR1 RI reporting for both SA and NSA	Rel-15	C017	UEs supporting 5GS FDD FR1 and 4Rx antenna ports	D008 D011	
6.4.3.2_1	4Rx TDD FR1 RI reporting for both SA and NSA	Rel-15	C019	UEs supporting 5GS TDD FR1 and 4Rx antenna ports	D010 D011	
7	Demodulation performance requirements (Radiated requirements)					
7.2.2.2.1_1	2Rx TDD FR2 PDSCH mapping Type A performance - 2x2 MIMO with baseline receiver for SA and NSA	FFS	FFS	FFS	FFS	NOTE 1

Clause	TC Title	Release	Applicability		Tested Bands Selection	Additional Information
			Condition	Comment		
7.2.2.2.1_2	2Rx TDD FR2 PDSCH mapping Type A performance - 2x2 MIMO with enhanced type 1 receiver for SA and NSA	FFS	FFS	FFS	FFS	NOTE 1
7.3.2.2.1	2Rx TDD FR2 PDCCH 1 Tx antenna performance for both SA and NSA	FFS	FFS	FFS	FFS	NOTE 1
7.3.2.2.2	2Rx TDD FR2 PDCCH 2 Tx antenna performance for both SA and NSA	FFS	FFS	FFS	FFS	NOTE 1
8	CSI reporting requirements (Radiated requirements)					
8.3.2.2.1	2Rx TDD FR2 Single PMI with 2Tx Type1 -- SinglePanel codebook for both SA and NSA	FFS	FFS	FFS	FFS	NOTE 1
9	Demodulation performance requirements for interworking					
9.4B.1.1	SDR test for sustained downlink data rate performance for EN-DC within FR1	Rel-15	C020	UEs supporting 5GS FDD FR1 or TDD FR1 (NSA)	D008 D009 D010	
10	CSI reporting requirements for interworking					
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.521-4.						
NOTE 2: Void.						
NOTE 3: Void.						

Table 4.1.4-1a: Void

Table 4.1.4-1b: Void

Table 4.1.4-1c: Void

4.2 RRM conformance test cases

Table 4.2-1: Applicability of RRM EN-DC FR1 conformance test cases, ref. TS 38.533 [5]

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
4.3	RRC_CONNECTED state mobility					
4.3.2	RRC connection mobility control					
4.3.2.2	Random access					
4.3.2.2.1	EN-DC FR1 contention based random access Contention based random access test in FR1 for PSCell in EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.3.2.2.2	EN-DC FR1 non-contention based random access	Rel-15	C030	UEs supporting EN-DC FR1 and CSI-RS based PRACH		
4.4	Timing					
4.4.1	UE Transmit Timing					
4.4.1.1	EN-DC FR1 UE transmit timing accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.4.2	UE timer accuracy					
4.4.3	Timing Advance					
4.4.3.1	EN-DC FR1 timing advance adjustment accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.5	Signalling characteristics					
4.5.1	Radio link monitoring					
4.5.1.1	EN-DC FR1 radio link monitoring out-of-sync test for PSCell configured with SSB-based RLM RS in non-DRX mode	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.1.2	EN-DC FR1 radio link monitoring in-sync test for PSCell configured with SSB-based RLM RS in non-DRX mode	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.1.3	EN-DC FR1 radio link monitoring out-of-sync test for PSCell configured with SSB-based RLM RS in DRX mode	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.5.1.4	EN-DC FR1 radio link monitoring in-sync test for PSCell configured with SSB-based RLM RS in DRX mode	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.5.1.5	EN-DC FR1 radio link monitoring out-of-sync test for PSCell configured with CSI-RS-based RLM RS in non-DRX mode	Rel-15	C038	UEs supporting EN-DC FR1 and CSI-RS-based RLM		
4.5.1.6	EN-DC FR1 radio link monitoring in-sync test for PSCell configured with CSI-RS-based RLM RS in non-DRX mode	Rel-15	C038	UEs supporting EN-DC FR1 and CSI-RS-based RLM		
4.5.1.7	EN-DC FR1 radio link monitoring out-of-sync test for PSCell configured with CSI-RS-based RLM RS in DRX mode	Rel-15	C038a	UEs supporting EN-DC FR1, CSI-RS-based RLM and long DRX cycle		
4.5.1.8	EN-DC FR1 radio link monitoring in-sync test for PSCell configured with CSI-RS-based RLM RS in DRX mode	Rel-15	C038a	UEs supporting EN-DC FR1, CSI-RS-based RLM and long DRX cycle		
4.5.2	Interruption					
4.5.2.1	EN-DC FR1 interruptions at transitions between active and non-active during DRX in synchronous EN-DC	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
4.5.2.2	EN-DC FR1 interruptions at transitions between active and non-active during DRX in asynchronous EN-DC	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.5.2.3	EN-DC FR1 interruptions during measurements on deactivated NR SCC in synchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.2.4	EN-DC FR1 interruptions during measurements on deactivated NR SCC in asynchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.2.5	EN-DC FR1 interruptions during measurements on deactivated E-UTRAN SCC in synchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.2.6	EN-DC FR1 interruptions during measurements on deactivated E-UTRAN SCC in asynchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.3	SCell activation and deactivation delay					
4.5.3.1	EN-DC FR1 SCell activation and deactivation of known SCell in non-DRX for 160ms SCell measurement cycle	Rel-15	C021	UEs supporting EN-DC FR1	NOTE 1	
4.5.3.2	EN-DC FR1 SCell activation and deactivation of known SCell in non-DRX for 320ms SCell measurement cycle	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.3.3	EN-DC FR1 SCell activation and deactivation of unknown SCell in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.4	UE UL carrier RRC reconfiguration delay					
4.5.4.1	EN-DC FR1 UE UL carrier RRC reconfiguration delay	Rel-15	C032	UEs supporting EN-DC FR1 and SUL		
4.5.5	Beam failure detection and link recovery procedures					
4.5.5.1	EN-DC FR1 SSB-based beam failure detection and link recovery in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.5.2	EN-DC FR1 SSB-based beam failure detection and link recovery in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.5.5.3	EN-DC FR1 CSI-RS-based beam failure detection and link recovery in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.5.4	EN-DC FR1 CSI-RS-based beam failure detection and link recovery in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.5.6	Active BWP switch delay					
4.5.6.1	DCI-based and timer-based active BWP switch					
4.5.6.1.1	EN-DC FR1 DCI-based DL active BWP switch in non-DRX in synchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.6.1.2	EN-DC FR1 DCI-based DL active BWP switch with SCell in non-DRX in synchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.6.2	RRC-based active BWP switch					
4.5.6.2.1	EN-DC FR1 RRC-based DL active BWP switch in non-DRX in synchronous EN-DC	Rel-15	C021	UEs supporting EN-DC FR1		
4.5.7	PSCell addition and release delay					
4.5.7.1	EN-DC FR1 addition and release delay of known PSCell	Rel-15	C021	UEs supporting EN-DC FR1		
4.6	Measurement procedures					
4.6.1	Intra-frequency measurements					

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
4.6.1.1	EN-DC FR1 event-triggered reporting without gap in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.1.2	EN-DC FR1 event-triggered reporting without gap in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.6.1.3	EN-DC FR1 event-triggered reporting with gap in non-DRX	Rel-15	C042	UEs supporting EN-DC FR1 and CSI-RS-based RLM and BWP operation without bandwidth restriction		
4.6.1.4	EN-DC FR1 event-triggered reporting with gap in DRX	Rel-15	C042a	UEs supporting EN-DC FR1, CSI-RS-based RLM, BWP operation without bandwidth restriction and long DRX cycle		
4.6.1.5	EN-DC FR1 event-triggered reporting without gap in non-DRX with SSB time index detection	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.1.6	EN-DC FR1 event-triggered reporting with gap in non-DRX with SSB time index detection	Rel-15	C042	UEs supporting EN-DC FDD FR1 and CSI-RS based RLM and BWP operation without bandwidth restriction		
4.6.2	Inter-frequency measurements					
4.6.2.1	EN-DC FR1-FR1 event-triggered reporting in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.2.2	EN-DC FR1-FR1 event-triggered reporting in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.6.2.5	EN-DC FR1-FR1 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.2.6	EN-DC FR1-FR1 event-triggered reporting in DRX with SSB time index detection	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.6.4	L1-RSRP for beam reporting					
4.6.4.1	EN-DC FR1 SSB-based L1-RSRP measurement in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.4.2	EN-DC FR1 SSB-based L1-RSRP measurement in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.6.4.3	EN-DC FR1 CSI-RS-based L1-RSRP measurement in non-DRX	Rel-15	C021	UEs supporting EN-DC FR1		
4.6.4.4	EN-DC FR1 CSI-RS-based L1-RSRP measurement in DRX	Rel-15	C021a	UEs supporting EN-DC FR1 and long DRX cycle		
4.7	Measurement performance requirements					
4.7.1	SS-RSRP					
4.7.1.1	Intra-frequency measurements					
4.7.1.1.1	EN-DC FR1 SS-RSRP absolute measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.1.1.2	EN-DC FR1 SS-RSRP relative measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.1.2	Inter-frequency measurements					
4.7.1.2.1	EN-DC FR1-FR1 SS-RSRP absolute measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
4.7.1.2.2	EN-DC FR1-FR1 SS-RSRP relative measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.2	SS-RSRQ					
4.7.2.1	EN-DC FR1 SS-RSRQ measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.2.2.1	EN-DC FR1-FR1 SS-RSRQ absolute measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.2.2.2	EN-DC FR1-FR1 SS-RSRQ relative measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.3	SS-SINR					
4.7.3.1	EN-DC FR1 SS-SINR measurement accuracy	Rel-15	C035	UEs supporting EN-DC FR1 and SS-SINR-meas		
4.7.3.2.1	EN-DC FR1-FR1 SS-SINR absolute measurement accuracy	Rel-15	C035	UEs supporting EN-DC FR1 and SS-SINR-meas		
4.7.3.2.2	EN-DC FR1-FR1 SS-SINR relative measurement accuracy	Rel-15	C035	UEs supporting EN-DC FR1 and SS-SINR-meas		
4.7.4	L1-RSRP					
4.7.4.1.1	EN-DC FR1 SSB-based L1-RSRP absolute measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.4.1.2	EN-DC FR1 SSB-based L1-RSRP relative measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.4.2.1	EN-DC FR1 CSI-RS-based L1-RSRP absolute measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.4.2.2	EN-DC FR1 CSI-RS-based L1-RSRP relative measurement accuracy	Rel-15	C021	UEs supporting EN-DC FR1		
4.7.5	SFTD					
4.7.5.1	EN-DC FR1 SFTD measurement accuracy	Rel-15	C043	UEs supporting EN-DC FR1 and SFTD measurements between E-UTRA PCell and NR PSCell		
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.533.						
NOTE 2: Test X refers to the corresponding Sub-Test as defined in TS 38.533 [5].						

Table 4.2-1a: Void

Table 4.2-2: Applicability of RRM EN-DC FR2 conformance test cases, ref. TS 38.533 [5]

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
5.3	RRC_CONNECTED state mobility					
5.3.2	RRC connection mobility control					
5.3.2.2	Random access					
5.4	Timing					
5.4.1	UE transmit timing					
5.4.1.1	EN-DC FR2 UE transmit timing accuracy	Rel-15	C022	UEs supporting EN-DC FR2		
5.4.2	UE timer accuracy					
5.4.3	Timing advance					
5.4.3.1	EN-DC FR2 timing advance adjustment accuracy	Rel-15	C022	UEs supporting EN-DC FR2		
5.5	Signalling characteristics					
5.5.1	Radio link monitoring					
5.5.1.1	EN-DC FR2 radio link monitoring out-of-sync test for PSCell configured with SSB-based RLM RS in non-DRX mode	FFS	FFS	FFS	NOTE 1	
5.5.1.2	EN-DC FR2 radio link monitoring in-sync test for PSCell configured with SSB-based RLM RS in non-DRX mode	FFS	FFS	FFS	NOTE 1	
5.5.1.3	EN-DC FR2 radio link monitoring out-of-sync test for PSCell configured with SSB-based RLM RS in DRX mode	FFS	FFS	FFS	NOTE 1	
5.5.1.4	EN-DC FR2 radio link monitoring in-sync test for PSCell configured with SSB-based RLM RS in DRX mode	FFS	FFS	FFS	NOTE 1	
5.5.2	Interruption					
5.5.2.1	EN-DC FR2 interruptions at transitions between active and non-active during DRX in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.2.2	EN-DC FR2 interruptions at transitions between active and non-active during DRX in asynchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.2.3	EN-DC FR2 interruptions during measurements on deactivated NR SCC in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.2.4	EN-DC FR2 interruptions during measurements on deactivated NR SCC in asynchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.2.5	EN-DC FR2 interruptions during measurements on deactivated E-UTRAN SCC in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.2.6	EN-DC FR2 interruptions during measurements on deactivated E-UTRAN SCC in asynchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.3	SCell activation and deactivation delay					
5.5.3.1	EN-DC FR2 SCell activation and deactivation intra-band in non-DRX	FFS	FFS	FFS	NOTE 1	
5.5.4	UE UL carrier RRC reconfiguration delay					
5.5.5	Beam failure detection and link recovery procedures					

5.5.5.5	EN-DC FR2 scheduling available restriction during SSB-based beam failure detection and link recovery in non-DRX	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.5.6	Active BWP switch delay					
5.5.6.1	DCI-based and timer-based active BWP switch					
5.5.6.1.1	EN-DC FR2 DCI-based DL active BWP switch in non-DRX in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.6.1.2	EN-DC FR2 DCI-based DL active BWP switch with SCell in non-DRX in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.6.2	RRC-based active BWP switch					
5.5.6.2.1	EN-DC FR2 RRC-based DL active BWP switch in non-DRX in synchronous EN-DC	FFS	FFS	FFS	NOTE 1	
5.5.7	PSCell addition and release delay					
5.5.7.1	EN-DC FR2 addition and release delay of known PSCell	FFS	FFS	FFS	NOTE 1	
5.5.8	Active TCI state switch delay					
5.5.8.1	EN-DC FR2 MAC-CE based active TCI state switch	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.5.8.2	EN-DC FR2 RRC based active TCI state switch	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.6	Measurement procedures					
5.6.1	Intra-frequency measurements					
5.6.2	Inter-frequency measurements					
5.6.2.1	EN-DC FR2-FR2 event-triggered reporting in non-DRX	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.6.2.2	EN-DC FR2-FR2 event-triggered reporting in DRX	Rel-15	C022a	UEs supporting EN-DC FR2 and long DRX cycle	NOTE 1	
5.6.2.3	EN-DC FR2-FR2 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.6.2.4	EN-DC FR2-FR2 event-triggered reporting in DRX with SSB time index detection	Rel-15	C022a	UEs supporting EN-DC FR2 and long DRX cycle	NOTE 1	
5.6.2.5	EN-DC FR1-FR2 event-triggered reporting in non-DRX	Rel-15	C023	UEs supporting EN-DC FR1 and FR2	NOTE 1	
5.6.2.6	EN-DC FR1-FR2 event-triggered reporting in DRX	Rel-15	C023a	UEs supporting EN-DC FR1 and FR2 and long DRX cycle	NOTE 1	
5.6.2.7	EN-DC FR1-FR2 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C023	UEs supporting EN-DC FR1 and FR2	NOTE 1	
5.6.2.8	EN-DC FR1-FR2 event-triggered reporting in DRX with SSB time index detection	Rel-15	C023a	UEs supporting EN-DC FR1 and FR2 and long DRX cycle	NOTE 1	
5.6.3	L1-RSRP for beam reporting					
5.6.3.1	EN-DC FR2 SSB-based L1-RSRP measurement in non-DRX	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.6.3.2	EN-DC FR2 SSB-based L1-RSRP measurement in DRX	Rel-15	C022a	UEs supporting EN-DC FR2 and long DRX cycle	NOTE 1	
5.6.3.3	EN-DC FR2 CSI-RS-based L1-RSRP measurement in non-DRX	Rel-15	C022	UEs supporting EN-DC FR2	NOTE 1	
5.6.3.4	EN-DC FR2 CSI-RS-based L1-RSRP measurement in DRX	Rel-15	C022a	UEs supporting EN-DC FR2 and long DRX cycle	NOTE 1	
5.7	Measurement performance requirements					
5.7.1	SS-RSRP					

5.5.7.1	EN-DC FR2 addition and release delay of known PSCell	FFS	FFS	FFS	NOTE 1	
5.7.1.1	EN-DC FR2 SS-RSRP measurement accuracy	FFS	FFS	FFS	NOTE 1	
5.7.1.2	EN-DC FR2-FR2 SS-RSRP measurement accuracy	FFS	FFS	FFS	NOTE 1	
5.7.1.3	Inter-frequency measurements between FR1 and FR2					
5.7.1.3.1	EN-DC FR1-FR2 SS-RSRP absolute measurement accuracy	FFS	FFS	FFS	NOTE 1	
5.7.1.3.2	EN-DC FR1-FR2 SS-RSRP relative measurement accuracy	FFS	FFS	FFS	NOTE 1	
5.7.2	SS-RSRQ					
5.7.3	SS-SINR					
5.7.4	L1-RSRP for beam reporting					
<p>NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.533.</p> <p>NOTE 2: Void.</p> <p>NOTE 3: Void.</p>						

Table 4.2-2a: Void

Table 4.2-3: Applicability of RRM NR SA FR1 conformance test cases, ref. TS 38.533 [5]

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
6.1	RRC_IDLE state mobility					
6.1.1	NR cell re-selection					
6.1.1.1	NR SA FR1 cell re-selection	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.1.1.2	NR SA FR1-FR1 cell re-selection	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.1.1.7	NR SA FR1 cell re-selection for UE configured with highSpeedMeasFlag-r16	Rel-16	C052	UEs supporting 5GS NR SA FR1 and measurement enhancements in HST	NOTE 1	
6.1.2	NR – E-UTRA cell re-selection					
6.1.2.1	NR SA FR1 – E-UTRA cell re-selection to higher priority E-UTRA	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
6.1.2.2	NR SA FR1 – E-UTRA cell re-selection to lower priority E-UTRA	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
6.2	RRC_INACTIVE state mobility					
6.3	RRC_CONNECTED state mobility					
6.3.1	Handover					
6.3.1.1	NR SA FR1 handover with known target cell	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.1.2	NR SA FR1 handover with unknown target cell	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.1.3	NR SA FR1-FR1 handover with unknown target cell	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.1.4	NR SA FR1 – E-UTRA handover with known target cell	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
6.3.1.5	NR SA FR1 – E-UTRA handover with unknown target cell	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
6.3.2	RRC connection mobility control					
6.3.2.1	RRC re-establishment					
6.3.2.1.1	NR SA FR1 RRC re-establishment	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.2.1.2	NR SA FR1 – FR1 RRC re-establishment	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.2.1.3	NR SA FR1 – FR1 RRC re-establishment without serving cell timing	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.3.2.2	Random access					
6.3.2.2.1	NR SA FR1 contention based random accessContention based random access test in FR1 for NR standalone	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.2.2.2	NR SA FR1 non-contention based random accessNon-Contention based random access test in FR1 for NR standalone	Rel-15	C029	UEs supporting 5GS NR SA FR1 and CSI-RS based PRACH		
6.3.2.3	RRC connection release with redirection					
6.3.2.3.1	NR SA FR1 RRC connection release with redirection	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.3.2.3.2	NR SA FR1 – E-UTRA RRC connection release with redirection	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
6.4	Timing					
6.4.1	UE transmit timing					
6.4.1.1	NR SA FR1 transmit timing accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.4.2	UE timer accuracy					
6.4.3	Timing advance					
6.4.3.1	NR SA FR1 timing advance adjustment accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
6.5	Signalling characteristics					
6.5.1	Radio Link Monitoring					
6.5.1.1	NR SA FR1 radio link monitoring out-of-sync test for PCell configured with SSB-based RLM RS in non-DRX mode	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.5.1.2	NR SA FR1 radio link monitoring in-sync test for PCell configured with SSB-based RLM RS in non-DRX mode	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.5.1.3	NR SA FR1 radio link monitoring out-of-sync test for PCell configured with SSB-based RLM RS in DRX mode	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.5.1.4	NR SA FR1 radio link monitoring in-sync test for PCell configured with SSB-based RLM RS in DRX mode	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.5.1.5	NR SA FR1 radio link monitoring out-of-sync test for PCell configured with CSI-RS-based RLM RS in non-DRX mode	Rel-15	C037	UEs supporting 5GS NR SA FR1 and CSI-RS-based RLM		
6.5.1.6	NR SA FR1 radio link monitoring in-sync test for PCell configured with CSI-RS-based RLM RS in non-DRX mode	Rel-15	C037	UEs supporting 5GS NR SA FR1 and CSI-RS-based RLM		
6.5.1.7	NR SA FR1 radio link monitoring out-of-sync test for PCell configured with CSI-RS-based RLM RS in DRX mode	Rel-15	C037a	UEs supporting 5GS NR SA FR1, CSI-RS-based RLM and long DRX cycle		
6.5.1.8	NR SA FR1 radio link monitoring in-sync test for PCell configured with CSI-RS-based RLM RS in DRX mode	Rel-15	C037a	UEs supporting 5GS NR SA FR1, CSI-RS-based RLM and long DRX cycle		
6.5.2	Interruption					
6.5.2.1	NR SA FR1 interruptions during measurements on deactivated NR SCC	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.3	Scell activation and deactivation delay					
6.5.3.1	NR SA FR1 SCell activation and deactivation of known SCell in non-DRX for 160ms SCell measurement cycle	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.3.2	NR SA FR1 SCell activation and deactivation of known SCell in non-DRX for 320ms SCell measurement cycle	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.3.3	NR SA FR1 SCell activation and deactivation of unknown SCell in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.4	UE UL carrier RRC reconfiguration delay					
6.5.4.1	NR SA FR1 UE UL carrier RRC reconfiguration delay	FFS	FFS	FFS	NOTE 1	
6.5.5	Link recovery procedures					
6.5.5.1	NR SA FR1 SSB-based beam failure detection and link recovery in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.5.2	NR SA FR1 SSB-based beam failure detection and link recovery in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle	NOTE 1	
6.5.5.3	NR SA FR1 CSI-RS-based beam failure detection and link recovery in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
6.5.5.4	NR SA FR1 CSI-RS-based beam failure detection and link recovery in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle	NOTE 1	
6.5.6	Active BWP switch delay					
6.5.6.1	DCI-based and timer-based active BWP switch					
6.5.6.1.1	NR SA FR1 DCI-based DL active BWP switch in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.6.1.2	NR SA FR1 DCI-based DL active BWP switch in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.5.6.2	RRC-based active BWP switch					
6.5.6.2.1	NR SA FR1 RRC-based DL active BWP switch in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1	NOTE 1	
6.6	Measurement procedures					
6.6.1	Intra-frequency measurements					
6.6.1.1	NR SA FR1 event-triggered reporting without gap in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.6.1.2	NR SA FR1 event-triggered reporting without gap in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.6.1.3	NR SA FR1 event-triggered reporting with gap in non-DRX	Rel-15	C041	UEs supporting 5GS NR SA FR1 and CSI-RS-based RLM and BWP operation without bandwidth restriction		
6.6.1.4	NR SA FR1 event-triggered reporting with gap in DRX	Rel-15	C041a	UEs supporting 5GS NR SA FR1, CSI-RS-based RLM, BWP operation without bandwidth restriction and long DRX cycle		
6.6.1.5	NR SA FR1 event-triggered reporting without gap in non-DRX with SSB index reading	Rel-15	C024	UEs supporting 5GS NR FDD SA FR1		
6.6.1.6	NR SA FR1 event-triggered reporting with gap in non-DRX with SSB index reading	Rel-15	C041	UEs supporting 5GS NR FDD SA FR1 and CSI-RS-based RLM and BWP operation without bandwidth restriction		
6.6.1.7	NR SA FR1 event-triggered reporting without gap in DRX for UE configured with highSpeedMeasFlag-r16	Rel-16	C052	UEs supporting 5GS NR SA FR1 and measurement enhancements in HST	NOTE 1	
6.6.2	Inter-frequency measurements					
6.6.2.1	NR SA FR1-FR1 event-triggered reporting in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.6.2.2	NR SA FR1-FR1 event-triggered reporting in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.6.2.5	NR SA FR1-FR1 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.6.2.6	NR SA FR1-FR1 event-triggered reporting in DRX with SSB time index detection	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.6.3	Inter-RAT measurements					
6.6.3.1	NR SA FR1 – E-UTRAN event-triggered reporting in non-DR	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRAN		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
6.6.3.2	NR SA FR1 – E-UTRAN event-triggered reporting in DRX	Rel-15	C025a	UEs supporting 5GS NR SA FR1, E-UTRAN and long DRX cycle		
6.6.3.3	NR SA FR1 – E-UTRAN event-triggered reporting in DRX for UE configured with highSpeedMeasFlag-r16	Rel.16	C052	UEs supporting 5GS NR SA FR1 and E-UTRAN configured with highSpeedMeasFlag-r16	NOTE 1	
6.6.4	L1-RSRP for beam reporting					
6.6.4.1	NR SA FR1 SSB-based L1-RSRP measurement in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.6.4.2	NR SA FR1 SSB-based L1-RSRP measurement in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.6.4.3	NR SA FR1 CSI-RS-based L1-RSRP measurement in non-DRX	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.6.4.4	NR SA FR1 CSI-RS-based L1-RSRP measurement in DRX	Rel-15	C001b	UEs supporting 5GS NR SA FR1 and long DRX cycle		
6.7	Measurement performance requirements					
6.7.1	SS-RSRP					
6.7.1.1	Intra-frequency measurements					
6.7.1.1.1	NR SA FR1 SS-RSRP absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.1.1.2	NR SA FR1 SS-RSRP relative measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.1.2	Inter-frequency measurements					
6.7.1.2.1	NR SA FR1-FR1 SS-RSRP absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.1.2.2	NR SA FR1-FR1 SS-RSRP relative measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.2	SS-RSRQ					
6.7.2.1	NR SA FR1 SS-RSRQ measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.2.2.1	NR SA FR1-FR1 SS-RSRQ absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.2.2.2	NR SA FR1-FR1 SS-RSRQ relative measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.3	SS-SINR					
6.7.3.1	NR SA FR1 SS-SINR measurement accuracy	Rel-15	C034	UEs supporting 5GS NR SA FR1 and SS-SINR-meas		
6.7.3.2.1	NR SA FR1-FR1 SS-SINR absolute measurement accuracy	Rel-15	C034	UEs supporting 5GS NR SA FR1 and SS-SINR-meas		
6.7.3.2.2	NR SA FR1-FR1 SS-SINR relative measurement accuracy	Rel-15	C034	UEs supporting 5GS NR SA FR1 and SS-SINR-meas		
6.7.4	L1-RSRP for beam reporting					
6.7.4.1.1	NR SA FR1 SSB-based L1-RSRP absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.4.1.2	NR SA FR1 SSB-based L1-RSRP relative measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
6.7.4.2.1	NR SA FR1 CSI-RS-based L1-RSRP absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.4.2.2	NR SA FR1 CSI-RS-based L1-RSRP relative measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.5	E-UTRAN RSRP					
6.7.5.1	NR SA FR1 – E-UTRAN RSRP absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.6	E-UTRAN RSRQ					
6.7.6.1	NR SA FR1 – E-UTRAN RSRQ absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
6.7.7	E-UTRAN RS-SINR					
6.7.7.1	NR SA FR1 – E-UTRAN RS-SINR absolute measurement accuracy	Rel-15	C001	UEs supporting 5GS NR SA FR1		
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.533.						
NOTE 2: Test X refers to the corresponding Sub-Test as defined in TS 38.533 [5].						

Table 4.2-3a: Void

Table 4.2-4: Applicability of RRM NR SA FR2 conformance test cases, ref. TS 38.533 [5]

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
7.1	RRC_IDLE state mobility					
7.1.1	NR cell re-selection					
7.1.1.1	NR SA FR2 cell re-selection	FFS	FFS	FFS	NOTE 1	
7.1.1.2	NR SA FR2-FR2 cell re-selection	FFS	FFS	FFS	NOTE 1	
7.2	RRC_INACTIVE state mobility					
7.3	RRC_CONNECTED state mobility					
7.3.1	Handover					
7.3.2	RRC connection mobility control					
7.3.2.1	RRC re-establishment					
7.3.2.1.1	NR SA FR2 RRC re-establishment	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.3.2.1.2	NR SA FR2 - FR2 RRC re-establishment	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.3.2.1.3	NR SA FR2 - FR2 RRC re-establishment without serving cell timing	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.3.2.2	Random access					
7.3.2.3	RRC connection release with redirection					
7.3.2.3.1	NR SA FR2 RRC connection release with redirection	FFS	FFS	FFS	NOTE 1	
7.4	Timing					
7.4.1	UE transmit timing					
7.4.2	UE timer accuracy					
7.4.3	Timing advance					
7.5	Signalling characteristics					
7.5.1	Radio Link Monitoring					
7.5.1.9	NR SA FR2 radio link monitoring UE scheduling restrictions	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.5.2	Interruption					
7.5.3	Scell activation and deactivation delay					
7.5.4	UE UL carrier RRC reconfiguration delay					
7.5.5	Beam failure detection and link recovery procedures					
7.5.5.1	NR SA FR2 SSB-based beam failure detection and link recovery in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.5.5.2	NR SA FR2 SSB-based beam failure detection and link recovery in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.5.5.3	NR SA FR2 CSI-RS-based beam failure detection and link recovery in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.5.5.4	NR SA FR2 CSI-RS-based beam failure detection and link recovery in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.5.5.5	NR SA FR2 scheduling availability restriction during SSB-based beam failure detection and link recovery in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.5.6	Active BWP switch delay					
7.5.6.1	Intra-frequency measurements					

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
7.5.6.1.1	NR SA FR2 2DL CA DCI-based DL active BWP switch in non-DRX	FFS	FFS	FFS	NOTE 1	
7.5.6.1.2	NR SA FR1-FR2 DCI-based DL active BWP switch in non-DRX	FFS	FFS	FFS	NOTE 1	
7.5.6.1.3	NR SA FR2 DCI-based DL active BWP switch in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.5.6.2	RRC-based active BWP switch					
7.5.6.2.1	NR SA FR2 RRC-based DL active BWP switch in non-DRX	FFS	FFS	FFS	NOTE 1	
7.6	Measurement procedures					
7.6.1	Intra-frequency measurements					
7.6.1.1	NR SA FR2 event-triggered reporting without gap in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.1.2	NR SA FR2 event-triggered reporting without gap in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.1.3	NR SA FR2 event-triggered reporting with gap in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.1.4	NR SA FR2 event-triggered reporting with gap in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.2	Inter-frequency measurements					
7.6.2.1	NR SA FR2-FR2 event-triggered reporting in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.2.2	NR SA FR2-FR2 event-triggered reporting in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.2.3	NR SA FR2-FR2 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.2.4	NR SA FR2-FR2 event-triggered reporting in DRX with SSB time index detection	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.2.5	NR SA FR1-FR2 event-triggered reporting in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.2.6	NR SA FR1-FR2 event-triggered reporting in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.2.7	NR SA FR1-FR2 event-triggered reporting in non-DRX with SSB time index detection	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.2.8	NR SA FR1-FR2 event-triggered reporting in DRX with SSB time index detection	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.3	L1-RSRP for beam reporting					
7.6.3.1	NR SA FR2 SSB-based L1-RSRP measurement in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	
7.6.3.2	NR SA FR2 SSB-based L1-RSRP measurement in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.6.3.3	NR SA FR2 CSI-RS-based L1-RSRP measurement in non-DRX	Rel-15	C006	UEs supporting 5GS NR SA FR2	NOTE 1	

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
7.6.3.4	NR SA FR2 CSI-RS-based L1-RSRP measurement in DRX	Rel-15	C006a	UEs supporting 5GS NR SA FR2 and long DRX cycle	NOTE 1	
7.7	Measurement performance requirements					
7.7.1	SS-RSRP					
7.7.1.1	NR SA FR2 SS-RSRP measurement accuracy	FFS	FFS	FFS	NOTE 1	
7.7.1.2	NR SA FR2-FR2 SS-RSRP measurement accuracy	FFS	FFS	FFS	NOTE 1	
7.7.1.3	Inter-frequency measurements between FR1 and FR2					
7.7.1.3.1	NR SA FR1-FR2 SS-RSRP measurement accuracy	FFS	FFS	FFS	NOTE 1	
7.7.2	SS-RSRQ					
7.7.3	SS-SINR					
7.7.4	L1-RSRP for beam reporting					
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.533.						
NOTE 2: Void.						
NOTE 3: Void.						

Table 4.2-4a: Void

Table 4.2-5: Applicability of E-UTRA – NR Inter-RAT conformance test cases, ref. TS 38.533 [5]

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
8.2	RRC_IDLE state mobility					
8.2.1	Inter-RAT cell re-selection					
8.2.1.1	E-UTRA – NR FR1 cell re-selection to higher priority NR target cell	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.2.1.2	E-UTRA – NR FR1 Cell reselection to lower priority NR target Cell in FR1 for UE configured with highSpeedInterRAT-NR-r16	Rel.16	C052	UEs supporting 5GS NR SA FR1 and E-UTRAN configured with highSpeedMeasFlag-r16	NOTE 1	
8.3	RRC_CONNECTED state mobility					
8.3.1	Inter-RAT cell handover					
8.3.1.1	E-UTRA – NR FR1 handover with known target cell	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.4	Measurement procedures					
8.4.1	SFTD measurement delay					
8.4.1.1	E-UTRA – NR FR1 SFTD measurement delay in non-DRX	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.4.1.2	E-UTRA – NR FR1 SFTD measurement delay in DRX	Rel-15	C025a	UEs supporting 5GS NR SA FR1, E-UTRA and long DRX cycle		
8.4.2	Inter-RAT measurements					
8.4.2.1	E-UTRA – NR FR1 event-triggered reporting without SSB time index detection in non-DRX	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.4.2.2	E-UTRA – NR FR1 event-triggered reporting without SSB time index detection in DRX	Rel-15	C025a	UEs supporting 5GS NR SA FR1, E-UTRA and long DRX cycle		
8.4.2.3	E-UTRA – NR FR1 event-triggered reporting with SSB time index detection in non-DRX	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.4.2.4	E-UTRA – NR FR1 event-triggered reporting with SSB time index detection in DRX	Rel-15	C025a	UEs supporting 5GS NR SA FR1, E-UTRA and long DRX cycle		
8.4.2.9	E-UTRA – NR Inter-RAT event triggered reporting tests for FR1 with SSB time index detection in DRX for UE configured with highSpeedInterRAT-NR-r16	Rel.16	C052	UEs supporting 5GS NR SA FR1 and E-UTRAN configured with highSpeedMeasFlag-r16	NOTE 1	
8.5	Measurement performance requirements					
8.5.1	SFTD measurement accuracy					
8.5.1.1	E-UTRA – NR FR1 SFTD measurement accuracy	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA	NOTE 1	
8.5.2	Inter-RAT					
8.5.2.1	SS-RSRP					
8.5.2.1.1.1	E-UTRA – NR FR1 SS-RSRP absolute measurement accuracy	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.5.2.1.2	E-UTRA – NR FR2 SS-RSRP measurement accuracy	Rel-15	C051	UEs supporting 5GS NR SA FR2 and E-UTRA		
8.5.2.2	SS-RSRQ					
8.5.2.2.1	E-UTRA – NR FR1 SS-RSRQ measurement accuracy	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		

Clause	TC Title	Release	Applicability		Additional Information	Branch
			Condition	Comment		
8.5.2.2.2	E-UTRA – NR FR2 SS-RSRQ measurement accuracy	Rel-15	C051	UEs supporting 5GS NR SA FR2 and E-UTRA		
8.5.2.3	SS-SINR					
8.5.2.3.1	E-UTRA – NR FR1 SS-SINR measurement accuracy	Rel-15	C025	UEs supporting 5GS NR SA FR1 and E-UTRA		
8.5.2.3.2	E-UTRA – NR FR2 SS-SINR measurement accuracy	Rel-15	C051	UEs supporting 5GS NR SA FR2 and E-UTRA		
NOTE 1: The test case/branch is incomplete for any Band/CA/DC Configuration but has basic test configurations already. NOTE 1 can be removed only when the test case/branch is complete for at least one Band / CA/DC Configuration for at least one feature included in the test case/branch. Detailed completion status can be found in the corresponding test case section in 38.533.						

Annex A (informative): Change history

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-08	RAN5#76	R5-173911	-	-	-	Draft skeleton	0.0.1
2018-01	RAN5#1-5G-NR Adhoc	R5-180107	-	-	-	Updated after RAN5#1-5G-NR Adhoc : - Foreword, scope, references, definitions, symbols and abbreviations, recommended test case applicability updated - clause 4.1.1, 4.1.2, 4.1.3 and 4.1.4 added - change history added	0.1.0
2018-03	RAN5 #78	R5-181687	-	-	-	TP for Clause 4.1.1 Range 1 standalone conformance test cases	0.2.0
2018-03	RAN5 #78	R5-181688	-	-	-	TP for Clause 4.1.2 Range 2 standalone conformance test cases	0.2.0
2018-03	RAN5 #78	R5-181689	-	-	-	TP for Clause 4.1.3 NR interworking between NR range1 and NR range2 and between NR and LTE conformance test cases	0.2.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182013	-	-	-	TP for Clause 3 Definitions, symbols and abbreviations	0.3.0
2018-04	RAN5#2-5G-NR Adhoc	R5-182047	-	-	-	TP for Clause 4 Recommended test case applicability	0.3.0
2018-08	RAN5#80	R5-185209	-	-	-	TP for Clause 4.1.1 of TS 38.522	1.0.1
2018-08	RAN5#80	R5-185210	-	-	-	TP for Clause 4.1.2 of TS 38.522	1.0.1
2018-08	RAN5#80	R5-185211	-	-	-	TP for Clause 4.1.3 of TS 38.522	1.0.1
2018-09	RAN#81	-	-	-	-	raised to v15.0.0 with editorial changes only	15.0.0
2018-12	RAN#82	R5-186501	0013	-	F	Applicability rules implementation in 38.522	15.1.0
2018-12	RAN#82	R5-188223	0015	-	F	Applicability for RRM NR tests	15.1.0
2018-12	RAN#82	R5-187566	0016	-	F	Update note in section 4.1 to include CBW and SCS in RF test applicability	15.1.0
2018-12	RAN#82	R5-187849	0014	1	F	Adding applicability for new 38.521-1 CA TCs	15.1.0
2018-12	RAN#82	R5-187881	0008	1	F	Update Clause 1 Scope of TS 38.522	15.1.0
2018-12	RAN#82	R5-187884	0011	1	F	TP for Clause 4.1.3 of TS 38.522	15.1.0
2018-12	RAN#82	R5-187922	0017	-	F	Removing FR2 test case 7.4 from TS 38.522 due to testability issue	15.1.0
2019-01	RAN#82	R5-187882	0009	1	F	Update Clause 3 of TS 38.522	15.1.1
2019-01	RAN#82	R5-187883	0010	1	F	TP for Clause 4.1.1 of TS 38.522	15.1.1
2019-01	RAN#82	R5-187885	0012	1	F	TP for Clause 4.1.3 of TS 38.522	15.1.1
2019-03	RAN#83	R5-191722	0021	-	F	addition of applicability for BFD and measurement	15.2.0
2019-03	RAN#83	R5-192507	0020	1	F	TP for TS 38.522	15.2.0
2019-03	RAN#83	R5-192508	0022	1	F	Addition of RRM Test Cases Applicability	15.2.0
2019-06	RAN#84	R5-195444	0027	1	F	TP for TS 38.522	15.3.0
2019-06	RAN#84	-	-	-	-	Administrative release upgrade to match the release of 3GPP TS 38.508-1 and TS 38.521-1 which were upgraded at RAN#84 to Rel-16 due to Rel-16 relevant CR(s)	16.0.0
2019-06	RAN#84	-	-	-	-	Addition of missing Table part of R5-195444 and part of a note.	16.0.1
2019-06	RAN#84	-	-	-	-	Formatted big tables to landscape	16.0.2
2019-09	RAN#85	R5-197650	0030	1	-	TP for TS 38.522	16.1.0
2019-09	RAN#85	R5-197650	0030	1	-	Added missing changes of R5-197650	16.1.1
2019-12	RAN#86	R5-199089	0032	2	-	TP for TS 38.522	16.2.0
2020-03	RAN#87	R5-201036	0033	1	F	TP and format updated for TS 38.522	16.3.0
2020-06	RAN#88	R5-202958	0040	1	F	R16 TDD ENDC PC2 TP for TS 38.522	16.4.0
2020-06	RAN#88	R5-203114	0037	2	F	TP updated to applicability table	16.4.0
2020-09	RAN#89	R5-204098	0046	-	F	Correct applicability EN-DC event-triggered inter-frequency tests	16.5.0
2020-09	RAN#89	R5-204099	0047	-	F	Correct applicability NR SA event-triggered inter-frequency tests	16.5.0
2020-09	RAN#89	R5-204939	0043	1	F	TP for TS 38.522	16.5.0
2020-09	RAN#89	R5-204940	0044	1	F	Correction of 38.522	16.5.0
2020-12	RAN#90	R5-206905	0051	1	F	Update to applicability spec for 5G test cases	16.6.0
2021-03	RAN#91	R5-210506	0055	-	F	Correction of applicability definitions for long DRX cycle related test cases	16.7.0
2021-03	RAN#91	R5-210792	0058	-	F	Adding the test applicability of RF test cases for eMIMO	16.7.0
2021-03	RAN#91	R5-211158	0060	-	F	Addition of applicability new test case 6.3.2.1.3 in TS 38.521-4	16.7.0

2021-03	RAN#91	R5-211159	0061	-	F	Addition of applicability new test case 6.3.3.1.3 in TS 38.521-4	16.7.0
2021-03	RAN#91	R5-211610	0067	-	F	Applicability of Error Vector Magnitude for V2X for non-concurrent operation	16.7.0
2021-03	RAN#91	R5-211720	0054	1	F	Correction of applicability definitions for PUSCH HalfPi BPSK related test cases	16.7.0
2021-03	RAN#91	R5-211853	0059	1	F	Update to applicability spec for 5G test cases	16.7.0
2021-03	RAN#91	R5-211913	0057	1	F	Adding test applicability for switching test case	16.7.0
2021-03	RAN#91	R5-211917	0066	1	F	Addition of new RRM test cases to the applicability table in 4.2	16.7.0
2021-03	RAN#91	R5-211918	0068	1	F	Applicability for RRM NR HST test case 6.1.1.7 and 6.6.1.7	16.7.0

History

Document history		
V16.4.0	July 2020	Publication
V16.5.0	November 2020	Publication
V16.6.0	January 2021	Publication
V16.7.0	April 2021	Publication